

IBM Security Directory Integrator
Version 7.2

Message Guide



IBM Security Directory Integrator
Version 7.2

Message Guide



Note

Before using this information and the product it supports, read the general information under “Notices” on page 1227.

Edition notice

Note: This edition applies to version 7.2 of *IBM Security Directory Integrator* licensed program (5724-K74) and to all subsequent releases and modifications until otherwise indicated in new editions.

© Copyright IBM Corporation 2006, 2013.

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

About this publication cxvii

Access to publications and terminology	cxvii
Accessibility	cxix
Technical training.	cxix
Support information.	cxix
Statement of Good Security Practices	cxix

Error Message Reference 1

Overview	1
Message format	1
Message ID format	1
Component identifiers	1
Severity	3
Presentation of messages	4
Messages	4
CTGDJB501I Rule <i>rule name</i> triggered.	4
CTGDJB502E Unable to create Action Manager Thread for [AM_ID]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	5
CTGDJB503E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	5
CTGDJB504E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	5
CTGDJB505E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register an AssemblyLine terminate listener.	6
CTGDJB506I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine</i>	6
CTGDJB507I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	6
CTGDJB508I AssemblyLine <i>AssemblyLine name</i> has not run since <i>time</i> seconds. Starting execution of associated actions.	6
CTGDJB509I Rule <i>rule name</i> has already been triggered earlier. Awaiting the next run of AssemblyLine <i>AssemblyLine name</i>	7
CTGDJB510I Rule <i>rule name</i> terminated.	7
CTGDJB511I Action Manager initialization completed.	7
CTGDJB512I Started Health AssemblyLine Manager.	7

CTGDJB513I Action Manager initialization started.	7
CTGDJB514E Property <i>property name</i> is not set.	8
CTGDJB515E Unable to load the <i>am_config.properties</i> file. Check the value of <i>action.manager.prop.file</i> property. Current value is: <i>file path</i>	8
CTGDJB516E Unable to load the <i>amc.properties</i> file. Current value of <i>com.ibm.di.amc.properties.file.location</i> property is: <i>file path</i>	8
CTGDJB517I SSL Trust Store: <i>trust store path</i>	8
CTGDJB518I SSL Key Store: <i>key store path</i>	9
CTGDJB519I Initializing connection to database.	9
CTGDJB520E Unable to initialize database.	9
CTGDJB521W Action Manager was unable to read property <i>com.ibm.di.amc.am.healthAL.interval.time</i> . Health AssemblyLine triggering interval set to a default value of 30 minutes.	10
CTGDJB522I Creating Action Manager threads.	10
CTGDJB523E Unable to obtain connection to database.	10
CTGDJB524I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On termination of AssemblyLine.	11
CTGDJB525I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On receiving Event.	11
CTGDJB526I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On specific property value.	11
CTGDJB527I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On query of AssemblyLine result.	12
CTGDJB528I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On server API failure.	12
CTGDJB529I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On elapsed time interval since last execution of AssemblyLine.	12
CTGDJB530E Exception while constructing Action Manager threads.	12
CTGDJB531I Action Manager threads created.	13
CTGDJB532I Database modification listener started.	13

CTGDJB533I Checking for any Action Manager rule updates.	13
CTGDJB534E Error occurred while running Database modification listener.	13
CTGDJB535E Error occurred while trying to delete data from the AM_UPDATE_DETAILS table.	13
CTGDJB536I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On termination of AssemblyLine.	14
CTGDJB537I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On receiving Event.	14
CTGDJB538I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On specific property value.	14
CTGDJB539I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On query of AssemblyLine result.	14
CTGDJB540I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On server API failure.	15
CTGDJB541I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On elapsed time interval since last execution of AssemblyLine.	15
CTGDJB542E Error occurred while constructing Action Manager thread for rule: <i>rule name</i>	15
CTGDJB543E Error occurred while trying to insert data into the AM_UPDATE_DETAILS table.	15
CTGDJB544E Error occurred while trying to delete all data from the AM_UPDATE_DETAILS table.	16
CTGDJB545I Rule <i>rule name</i> triggered.	16
CTGDJB546I Created Action Manager thread for [Config]: <i>Config instance</i>	16
CTGDJB547I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	16
CTGDJB548I Rule <i>rule name</i> terminated.	17
CTGDJB549I Rule <i>rule name</i> triggered.	17
CTGDJB550E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	17
CTGDJB551E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	17

CTGDJB552E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	18
CTGDJB553E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register AssemblyLine terminate listener.	18
CTGDJB554I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine</i>	18
CTGDJB555I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	18
CTGDJB556I Rule <i>rule name</i> terminated.	19
CTGDJB557I DBConnectionFactory instance created.	19
CTGDJB558I Derby network server already running.	19
CTGDJB559I Unable to ping Derby network server. Attempting to start.	19
CTGDJB560I Started Derby network server.	19
CTGDJB561E Unable to start Derby network server. Database unavailable.	20
CTGDJB561W Error while closing database Statement.	20
CTGDJB562W Error while closing database ResultSet.	20
CTGDJB563W Error while closing database Connection.	21
CTGDJB564I Rule <i>rule name</i> not triggered since event data did not match.	21
CTGDJB565I Rule <i>rule name</i> not triggered since event source did not match.	21
CTGDJB566I Rule <i>rule name</i> triggered.	21
CTGDJB567E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	21
CTGDJB568E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	22
CTGDJB569E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	22
CTGDJB570E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register specified Event listener.	22
CTGDJB571I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine</i>	23

CTGDJB572I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	23
CTGDJB573I Rule <i>rule name</i> terminated.	23
CTGDJB574W Unable to get list of running AssemblyLines for Solution View: <i>Solution View</i> . Ignoring Health AssemblyLine for this Solution view.	23
CTGDJB575W Unable to obtain Config Instance associated with the Solution View: <i>Solution View</i> . Ignoring Health AssemblyLine for this Solution view.	24
CTGDJB576E Unable to obtain list of Health AssemblyLines for Solution Views.	24
CTGDJB577I Updating Health AssemblyLine status in database for Solution view <i>Solution View ID</i> . [HealthAL Result]: <i>result</i> . [HealthAL Status]: <i>status_description</i>	24
CTGDJB578E Error updating Health AssemblyLine status in database for Solution view <i>Solution View ID</i> . [HealthAL Result]: <i>result</i> . [HealthAL Status]: <i>status_description</i>	24
CTGDJB579I Creating Health AssemblyLine Listener thread for [Solution View]: <i>Solution View ID</i> . [Config]: <i>Config instance</i> . [AssemblyLine]: <i>AssemblyLine name</i>	25
CTGDJB580W Unable to obtain session with remote Security Directory Integrator server for Health AssemblyLine: <i>AssemblyLine name</i>	25
CTGDJB581E Unable to create base listener for Health AssemblyLine: <i>AssemblyLine name</i>	25
CTGDJB582E Unable to register stop AssemblyLine listener for Health AssemblyLine: <i>AssemblyLine name</i>	25
CTGDJB583E Unable to start Health AssemblyLine: <i>AssemblyLine name</i>	26
CTGDJB584E Result work entry is null in Health AssemblyLine: <i>AssemblyLine name</i> . No Health status update will be done in database.	26
CTGDJB585I In Health AssemblyLine <i>AssemblyLine name</i> healthAL.result attribute value is: <i>attribute_value</i>	26
CTGDJB586I In Health AssemblyLine <i>AssemblyLine name</i> healthAL.status attribute value is: <i>attribute_value</i>	26
CTGDJB587I Terminating Health AssemblyLine thread for [Solution View]: <i>Solution View ID</i> [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine name</i>	27
CTGDJB588W Unable to remove event listener registered for AssemblyLine terminate events for [Solution View]: <i>Solution View ID</i> [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine name</i>	27
CTGDJB588E Unable to obtain handle to AssemblyLine object for Health AssemblyLine: <i>AssemblyLine name</i>	27
CTGDJB589I Rule <i>rule name</i> triggered.	27

CTGDJB590E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	28
CTGDJB591E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	28
CTGDJB592E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to obtain Config Instance: <i>Config Instance</i>	28
CTGDJB593E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . [Config Instance]: <i>Config Instance</i> . Unable to obtain handle to Security Directory Integrator Properties object.	28
CTGDJB594I Created Action Manager thread for [Config]: <i>Config instance</i>	29
CTGDJB595I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	29
CTGDJB596E Error in [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> The property values cannot be compared since one of the property is not a valid integer. [Key]: <i>property name</i> [Current Value]: <i>property value</i> [Compared to value]: <i>value</i>	29
CTGDJB597E Error in [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> Unable to determine triggering condition.	29
CTGDJB598I Rule <i>rule name</i> terminated.	30
CTGDJB599I Rule <i>rule name</i> triggered.	30
CTGDJB600E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	30
CTGDJB601E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	30
CTGDJB602I The Config instance <i>Config instance</i> is not running. Will obtain handle to AssemblyLine later.	31
CTGDJB603E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	31

CTGDJB604E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register AssemblyLine listener.	31	CTGDJB624E Unable to read action information from AM_ACTION_DETAILS_COPY_PROPERTY table.	36
CTGDJB605I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine</i>	31	CTGDJB625E Unable to obtain Config instance for Config: <i>Config instance</i>	36
CTGDJB606I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	32	CTGDJB626E Unable to copy properties.	36
CTGDJB607I Rule <i>rule name</i> terminated.	32	CTGDJB627E Unable to obtain property information.	36
CTGDJB608W Unable to obtain handle to AssemblyLine object for AssemblyLine: <i>AssemblyLine name</i>	32	CTGDJB628E Unable to obtain Config instance for Config: <i>Config instance</i>	36
CTGDJB609E Result work entry is null in AssemblyLine: <i>AssemblyLine name</i> . Rule will not be triggered.	32	CTGDJB629E Unable to modify property to new value: <i>value</i>	37
CTGDJB610E No value found for attribute <i>attribute name</i> . in result work entry. Rule will not be triggered.	32	CTGDJB630E Unable to obtain Event information.	37
CTGDJB611I Attribute <i>attribute name</i> value is <i>attribute value</i>	33	CTGDJB631E Unable to send Event notification.	37
CTGDJB612E Error in [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> The attribute values cannot be compared since one of the values is not a valid integer. [Attribute]: <i>Attribute name</i> [Current Value]: <i>Attribute value</i> [Compared to value]: <i>value</i>	33	CTGDJB632E Unable to enable rule.	37
CTGDJB613W Unable to obtain handle to AssemblyLine object for AssemblyLine: <i>AssemblyLine name</i> Cannot obtain result work entry.	33	CTGDJB633E Unable to disable rule.	37
CTGDJB614E An error occurred while executing an action. [Solution View]: <i>Solution View name</i> [Rule]: <i>Rule name</i> [Action Order]: <i>sequence order</i> [Action Type]: <i>action type</i>	33	CTGDJB634E Unable to enable rule <i>rule name</i>	38
CTGDJB615I Action successfully executed. [Solution View]: <i>Solution View name</i> [Rule]: <i>Rule Name</i> [Action Order]: <i>sequence_order</i> [Action Type]: <i>action_type</i>	34	CTGDJB635E Unable to disable rule <i>rule name</i>	38
CTGDJB616E An error occurred while executing an action. [Solution View]: <i>Solution View name</i> [Rule]: <i>Rule Name</i>	34	CTGDJB636E Unable to enable rule.	38
CTGDJB617E Unable to insert/commit into AM_RUN_HISTORY table.	34	CTGDJB637E Unable to disable rule.	38
CTGDJB618E Unable to obtain rule information from AM_ACTION_DETAILS_RULE table.	34	CTGDJB638E Unable to obtain AssemblyLine information.	38
CTGDJB619E Unable to obtain rule information from AM_RULES_MASTER table.	34	CTGDJB639E Unable to obtain session for stopping AssemblyLine <i>AssemblyLine name</i> with remote Security Directory Integrator server.	39
CTGDJB620I Triggering rule <i>rule name</i> of Solution view <i>Solution View</i>	35	CTGDJB640E Config <i>Config instance</i> is not loaded on the remote server.	39
CTGDJB621E Unable to obtain log information from AM_ACTION_DETAILS_WRITE_LOG table.	35	CTGDJB641E Unable to stop AssemblyLine: <i>AssemblyLine name</i>	39
CTGDJB622I [Message]: <i>log message</i> [Description]: <i>log description</i>	35	CTGDJB642E AssemblyLine: <i>AssemblyLine name</i> is not running on the Config instance: <i>Config instance</i>	39
CTGDJB623E Unable to write log information to AM_LOGS table.	35	CTGDJB643E Unable to obtain AssemblyLine information.	39
		CTGDJB644E Unable to obtain session for starting AssemblyLine <i>AssemblyLine name</i> with remote Security Directory Integrator server.	40
		CTGDJB645I Config <i>Config instance</i> is not loaded on the remote server. Attempting to load it now.	40
		CTGDJB646E Unable to start Config instance <i>Config instance</i>	40
		CTGDJB647E Unable to start AssemblyLine <i>AssemblyLine name</i>	40
		CTGDJB648I Security Directory Integrator Session Generator Created.	41
		CTGDJB649I Trying to establish connection to: <i>server</i> : <i>port</i>	41
		CTGDJB650I Custom Authentication with username: <i>username</i>	41
		CTGDJB651E Unable to obtain session with remote Security Directory Integrator Server: <i>server</i> : <i>port</i>	41
		CTGDJB652I Started Action Manager Status Update thread.	41
		CTGDJB653E Unable to update status of Action Manager.	42
		CTGDJB654I ServerConfigHandler created.	42

CTGDJB655E ServerStatusListener thread unable to update server status.	42	CTGDJB674E Unable to start AssemblyLine <i>AssemblyLine name</i>	47
CTGDJB656E Unable to create ConfigLoadReloadListener thread for [SERVER_ID]: <i>Server ID</i> . Unable to create base listener.	42	CTGDJB675I Rule <i>rule name</i> triggered.	48
CTGDJB657E Unable to create ConfigLoadReload Thread for [SERVER_ID]: <i>Server ID</i> . Unable to register ConfigLoadReloadListener.	43	CTGDJB676E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	48
CTGDJB658E Unable to remove EventListener for [SERVER_ID]: <i>Server ID</i> . Unable to remove event listener.	43	CTGDJB677E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	48
CTGDJB659I Started AMCServerModificationListener thread.	43	CTGDJB678I The Config instance <i>Config instance</i> is not running. Will obtain handle to AssemblyLine later.	48
CTGDJB660E Unable to create ServerStatusListener threads.	43	CTGDJB679E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	49
CTGDJB661I Checking for any Administration and Monitoring Console Server updates.	43	CTGDJB680E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register AssemblyLine listener.	49
CTGDJB662E Unable to obtain connection to the Administration and Monitoring Console database.	44	CTGDJB681I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine name</i>	49
CTGDJB663E Unable to obtain connection to the Administration and Monitoring Console database.	44	CTGDJB682I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	49
CTGDJB664E Exception while constructing Action Manager threads.	45	CTGDJB683I Rule <i>rule name</i> terminated.	50
CTGDJB665I ServerStatusListener thread started for server [SERVER_NAME]: <i>Server Name</i>	45	CTGDJB684W Unable to obtain handle to AssemblyLine object for AssemblyLine: <i>AssemblyLine name</i>	50
CTGDJB666I ConfigLoadReloadListener thread started for server [SERVER_NAME]: <i>Server Name</i>	45	CTGDJB685E Result work entry is null in AssemblyLine: <i>AssemblyLine name</i> . Rule will not be triggered.	50
CTGDJB667E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	46	CTGDJB686E No value found for attribute <i>attribute name</i> . in result work entry. Rule will not be triggered.	50
CTGDJB668E ServerStatusListener unable to check server restart status.	46	CTGDJB687I Attribute <i>attribute name</i> value is <i>attribute value</i>	50
CTGDJB669I [SERVER_NAME]: <i>Server Name</i> has been restarted in polling interval. Rule threads will be terminated and re-created.	46	CTGDJB688E Error in [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> The attribute values cannot be compared since one of the values is not a valid integer. [Attribute]: <i>Attribute name</i> [Current Value]: <i>Attribute value</i> [Compared to value]: <i>value</i>	51
CTGDJB670E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	46	CTGDJB689W Unable to obtain handle to AssemblyLine object for AssemblyLine: <i>AssemblyLine name</i> Cannot obtain result work entry.	51
CTGDJB671E Action Manager was unable to create Action Manager Thread for the following rule: [Rule]: <i>rule name</i> [Reason]: Unable to connect to server <i>Server Name</i>	47	CTGDJB690I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: Inspect AssemblyLine Exit code.	51
CTGDJB672E Error occurred while trying to delete data from the AM_SERVER_UPDATE_DETAILS table.	47		
CTGDJB673E Config <i>Config instance</i> is not loaded on the remote server so ActionManager cannot query the AssemblyLine result.	47		

CTGDJB691I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On AssemblyLine start	51
CTGDJB692I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On config load	52
CTGDJB693I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On config unload	52
CTGDJB694I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: Timer	52
CTGDJB695E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	52
CTGDJB696E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	53
CTGDJB697E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	53
CTGDJB698E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register AssemblyLine start listener.	53
CTGDJB699I Rule <i>rule name</i> terminated.	53
CTGDJB700I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	54
CTGDJB701E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	54
CTGDJB702E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	54
CTGDJB703E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	55
CTGDJB704E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register config load listener.	55

CTGDJB705I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine</i>	55
CTGDJB706I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine</i>	55
CTGDJB707I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	56
CTGDJB708E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	56
CTGDJB709E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to connect to remote Security Directory Integrator server.	56
CTGDJB710E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to create base listener.	56
CTGDJB711E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i> . Unable to register config unload listener.	57
CTGDJB712I Created Action Manager thread for [Config]: <i>Config instance</i> [AssemblyLine]: <i>AssemblyLine name</i>	57
CTGDJB713I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	57
CTGDJB714E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	57
CTGDJB715I Killing Action Manager thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	58
CTGDJB716I Rule <i>rule name</i> triggered.	58
CTGDJB717I Rule <i>rule name</i> triggered.	58
CTGDJB718I Rule <i>rule name</i> triggered.	58
CTGDJB719W The Action manager RMI Registry is starting on default port <i>port</i>	59
CTGDJB720I The Action Manager RMI registry is started on port <i>port</i>	59
CTGDJB721E An exception occurred while starting the Action Manager RMI Registry: <i>exception</i>	59
CTGDJB722W The client information provided <i>data value</i> is not sufficient for extracting the client name and client version.	59
CTGDJB723I The System Security Manager is null. Using the Action Manager custom security manager instead.	59

CTGDJB724I The Action manager is resetting the System Security Manager to null.	60	CTGDJB745I Failed to connect to the target computer using any of the supported protocols. Action Manager is assuming that command <i>command</i> is to be executed on localhost.	64
CTGDJB725I Creating Action Manager thread for [Solution View]: <i>Solution View name</i> [Rule]: <i>rule name</i> [Trigger Type]: On local variable.	60	CTGDJB746E An error <i>error</i> occurred while executing the command <i>command</i> on action manager host <i>hostname</i>	65
CTGDJB726E Unable to create Action Manager Thread for [Action Manager Rule Id]: <i>Action Manager Rule ID</i> [Rule]: <i>rule name</i> [Solution View]: <i>Solution View name</i>	60	CTGDJB747I The command <i>command</i> is executed successfully on host <i>hostname</i>	65
CTGDJB727I Rule <i>rule name</i> triggered.	60	CTGDJB748E The command <i>command</i> execution failed on host <i>hostname</i> with exit code <i>Integer</i>	65
CTGDJB728E Unable to modify local variable to new value: <i>value</i>	61	CTGDJB749E An error occurred while executing the command <i>command</i> on host <i>hostname: error</i>	65
CTGDJB729E An exception occurred while getting <i>rule name</i> details: <i>exception</i>	61	CTGDJB750E The command <i>command</i> is not executed.	65
CTGDJB730E An exception occurred while executing rule <i>rule name</i> : <i>exception</i>	61	CTGDJB751E An error was encountered while retrieving data from the database: <i>error</i>	66
CTGDJB731I The rule <i>rule name</i> has no actions to be backed up.	61	CTGDJB752E Failed to establish a connection with the target computer.	66
CTGDJB732E An exception occurred while backing up the original values for rule <i>rule name</i> : <i>exception</i>	61	CTGDJB753E An error occurred while executing the command <i>command</i>	66
CTGDJB733I The client info <i>client info</i> used for connecting with Action Manager is invalid.	62	CTGDJB754W Cannot rollback the properties changes because the config instance id is null.	66
CTGDJB734I The table AM_ACTION_DETAILS_WRITE_LOG is empty.	62	CTGDJB755E An error occurred while rolling back the properties: <i>error message</i>	66
CTGDJB735E The API Listener is not able to create the Action Manager thread because of the exception: <i>exception</i>	62	CTGDJB756E An error occurred while rolling back the database changes: <i>error message</i>	67
CTGDJB736E Action Manager was unable to obtain the Action Manager logs to be attached with the email.	62	CTGDJB757E An error occurred while backing up the property: <i>error message</i>	67
CTGDJB737E Action Manager was unable to obtain the host and port information of the SMTP server.	62	CTGDJB758E No command specified in the execute command action.	67
CTGDJB738E Action Manager was unable to create and send an email message.	63	CTGDJB759E Action Manager was unable to obtain local variable <i>variable name</i>	67
CTGDJB739E Action Manager was unable to obtain the host and port information of the SMTP server from the Action Manager config file.	63	CTGDJB760E Unable to obtain local variable information.	67
CTGDJB740E Property java.util.logging.config.file is not set in startAM.bat(sh).	63	CTGDJB761E An error occurred while terminating thread for rule <i>rule name</i> : <i>error</i>	68
CTGDJB741E Unable to load the am_logging.properties file. Check the value of java.util.logging.config.file property in the startAM.bat(sh). The current value is set to <i>file path</i>	63	CTGDJB762E An error occurred while starting thread for rule <i>rule name</i> : <i>error</i>	68
CTGDJB742I The target computer is the same as the Action Manager host.	64	CTGDJB763W An error occurred while closing the database connection: <i>error</i>	68
CTGDJB743W The user name or keystore is set to <i>property value</i> and the password or keystore password is set to <i>property value</i>	64	CTGDJB764W An error occurred while checking for server updates: <i>error</i>	68
CTGDJB744E Failed to connect to the target computer using protocol <i>protocol</i>	64	CTGDJB765I An error occurred while closing the input stream of file <i>file name</i> : <i>error</i>	68
		CTGDJB766E An error occurred while starting thread: <i>error</i>	69
		CTGDJB767W An error occurred while rolling back the database changes: <i>error</i>	69
		CTGDJB768I Action Manager trying to connect to <i>hostname</i> host using protocol <i>protocol</i>	69
		CTGDJB769I Action Manager failed to connect to <i>hostname</i> host using protocol <i>protocol</i>	69
		CTGDJB770I Password is null, hence failed to connect to <i>hostname</i> host using protocol <i>protocol</i>	69

CTGDJB771I Failed to connect to <i>hostname</i> host using protocol <i>protocol</i> because either password or keystore or keystore password is not provided.	70
CTGDJB772E Failed to start Action Manager because an exception occurred: <i>exception</i>	70
CTGDJB772I Exiting Action Manager with error code <i>error code</i>	70
CTGDJB774E An error occurred while initializing truststores: <i>exception</i>	70
CTGDJB775E An error occurred while initializing keystores: <i>exception</i>	71
CTGDJB776E An error occurred while initializing Action Manage RMI: <i>exception</i>	71
CTGDJB777E Unable to establishing a connection to the database. An exception occurred: <i>exception</i>	71
CTGDJB778E Unable to execute the rule <i>rule name</i> . An exception occurred: <i>exception</i>	71
CTGDJB779E An error occurred while rolling back the database changes for rule <i>rule name</i> : <i>exception</i>	71
CTGDJB780E An error occurred while rolling back the actions for rule <i>rule name</i> : <i>exception</i>	72
CTGDJB781E An error occurred while retrieving actions: <i>error message</i>	72
CTGDJB782E An error occurred while retrieving trigger types for Rule Id <i>rule id</i> : <i>error message</i>	72
CTGDJB783E An error occurred <i>error message</i> while retrieving rules for Server Id <i>server id</i>	72
CTGDJB784E An error occurred while retrieving rules for Config URL <i>URL</i> : <i>error message</i>	72
CTGDJB785E An error occurred while retrieving the Server version: <i>error message</i>	73
CTGDJB786E An error occurred while checking the Server version: <i>error message</i>	73
CTGDJB787E An error occurred while getting the Server name for Server Id <i>server id</i> : <i>error message</i>	73
CTGDJB788E An error occurred while getting the triggered triggers: <i>error message</i>	73
CTGDJB789E An error occurred while getting the Rule Id for rule <i>rule name</i> : <i>error message</i>	73
CTGDJB790E An error occurred while getting the Config Instance for Solution View <i>solution view name</i> : <i>error message</i>	74
CTGDJB791E An error occurred while getting the Solution Id for Solution View <i>solution view name</i> : <i>error message</i>	74
CTGDJB792E An error occurred while getting the Solution View name for Solution Id <i>solution id</i> : <i>error message</i>	74
CTGDJB793E An error occurred while getting the action details for Rule Id <i>rule id</i> : <i>error message</i>	74

CTGDJB794E An error occurred while enabling/disabling a rule with Rule id <i>rule id</i> : <i>error message</i>	74
CTGDJB795E An error occurred while retrieving actions for rule with Rule ID <i>rule id</i> : <i>error message</i>	75
CTGDJB796E An error occurred while initializing of String encryption decryption utility: <i>error message</i>	75
CTGDJB797I Encryption scheme <i>encryption scheme</i> is not supported.	75
CTGDJB798I The string being encrypted is empty or null.	75
CTGDJB799E An error occurred while encrypting a string: <i>error</i>	75
CTGDJB800I The string being decrypted is empty or null.	76
CTGDJB801E An error occurred while decrypting: <i>error message</i>	76
CTGDJB802E An error occurred while decrypting property: <i>error message</i>	76
CTGDJB803E An error occurred while encrypting property: <i>error message</i>	76
CTGDJB804E An error occurred while killing Action Manager thread: <i>error message</i>	76
CTGDJB805W An error occurred while executing command <i>command</i> : <i>error message</i>	77
CTGDJB806E The hostname <i>hostname</i> is unknown. Exception occurred: <i>exception</i>	77
CTGDJB807E An error occurred while unregistering the listener: <i>error</i>	77
CTGDJB808I Executing the SQL command for rolling back the action.	77
CTGDJB809I Rolling back the properties changes made by force trigger.	77
CTGDJB810E An error occurred while rolling back the database transaction: <i>error</i>	78
CTGDJB811E A threading exception has occurred.	78
CTGDJB812E An error occurred while trying to kill the QueryAL listener thread.	78
CTGDJB813E A threading exception has occurred.	78
CTGDJB814E A threading exception has occurred.	78
CTGDJB815W An exit code for the command execution cannot be displayed.	79
CTGDJB816E An error occurred while getting values for local Action Manager variable : <i>error message</i>	79
CTGDJF001E The 'iteratorStateKey' parameter must be set to use the Active Directory Change Detection Connector.	79
CTGDJF002W An old configuration parameter 'usnFileName' is used that stores the USN in a text file. This function is no longer supported.	79
CTGDJF003W The 'sleepInterval' parameter set to an invalid value ' <i>parameter value</i> '. The default value ' <i>parameter value</i> ' will be used instead.	80

CTGDKF018E The 'Start at' parameter not specified.	89	CTGDIY007I Performing operation: <i>operation name</i> , work Entry: <i>entry name</i>	95
CTGDKF019I Synchronization from End Of Data will be performed: the Connector will only report changes that occur after it is started.	90	CTGDIY008I Operation <i>operation name</i> returned <i>Java object</i>	95
CTGDKF020E Error: Synchronization from End Of Data requested, but can't find highest committed USN number: <i>exception</i>	90	CTGDIY101E Unable to select AssemblyLine operation. The remote Config ' <i>Config name</i> ' cannot be found on server ' <i>server name</i> '.	95
CTGDKF021E Invalid 'Start at' value specified: <i>mStartAt</i>	90	CTGDIY102E Unable to select AssemblyLine operation. Connection to server ' <i>server name</i> ' cannot be obtained.	95
CTGDKF022I Start USN values:	90	CTGDIY103E No server configured.	96
CTGDKF023I Initial 'CURRENT_USN_CREATED' parameter is greater than the 'END_USN' parameter. Setting 'CURRENT_USN_CREATED' parameter to the value of the 'START_USN' parameter.	90	CTGDIY104E Unable to retrieve initialized schema. The remote Config ' <i>Config name</i> ' cannot be found on server ' <i>server name</i> '.	96
CTGDKF024I Both the 'CURRENT_USN_CREATED' and 'CURRENT_USN_CHANGED' parameters are smaller than the 'START_USN' parameter. Setting the 'CURRENT_USN_CREATED' parameter to the value of 'START_USN' parameter.	91	CTGDIY105E Unable to select AssemblyLine. The remote Config ' <i>Config name</i> ' cannot be found on server ' <i>server name</i> '.	96
CTGDKF025I Start USN values internally adjusted to:	91	CTGDIY106E Unable to retrieve initialized schema. Connection to server ' <i>server name</i> ' cannot be obtained.	96
CTGDKF026E Could not retrieve highest committed USN number.	91	CTGDIY107E Unable to select AssemblyLine. Connection to server ' <i>server name</i> ' cannot be obtained.	97
CTGDKF027E Could not retrieve highest committed USN number.	91	CTGDIY108I Waiting 2 seconds for remote AssemblyLine to complete: ' <i>AssemblyLine Name</i> '.	97
CTGDKF028I LDAP search query: <i>filter</i>	92	CTGDIY109E The Config instance not specified for server ' <i>server name</i> '.	97
CTGDKF029E An PartialResultException caught when retrieving an Entry from the Active Directory Server based on the given filter: <i>exception</i>	92	CTGDIY110E The 'assemblyLine' parameter must be set to use the AssemblyLine Function Component.	97
CTGDKF030I Timeout waiting for next changed entry.	92	CTGDIY111E Unable to parse attributes in the entry. Encountered an unknown TCB parameter ' <i>parameter name</i> '.	97
CTGDKF031E Could not store USN values in file ' <i>file name</i> '. Exception occurred: <i>exception</i>	92	CTGDIY112E Exception occurred while retrieving configuration: <i>exception</i>	98
CTGDKF032I Current USN values are:	92	CTGDIY113W Warning: Cannot run local AssemblyLines.	98
CTGDKF033E Could not store USN values in Persistent Parameter Store. Exception occurred: <i>exception</i>	93	CTGDIA201E The required WSDL file location was not provided.	98
CTGDKF034I Current USN values are:	93	CTGDIA202E No service specified in the Function Component's configuration.	98
CTGDKF035E Restart info is NULL. Cannot restart.	93	CTGDIA203E No endpoint specified in the Function Component's configuration.	99
CTGDKF036I USN values needed for the next synchronization with Active Directory.	93	CTGDIA204E No operation specified in the Function Component's configuration.	99
CTGDKF037I USN attribute <i>name</i> : <i>value</i>	93	CTGDIA205I Setting HTTP Basic Authentication headers. The username is: <i>username</i>	99
CTGDIY001E Unable to get next entry. No AssemblyLine to execute.	94	CTGDIA206E The Axis2 Web Service Client Function Component accepts only a IBM Security Directory Integrator Entry for input.	99
CTGDIY002E Expecting com.ibm.di.entry.Entry, object found <i>Java class name</i>	94	CTGDIA207E An Exception occurred while trying to invoke the Web Service. Exception message: <i>exception</i>	100
CTGDIY003I Computed modes for <i>Connector name</i> :	94	CTGDIA208E The input operation message parameter was not found in the provided input entry. The required input parameter is: <i>exception</i>	100
CTGDIY004I Operations for <i>Assembly Line name</i> :	94		
CTGDIY005I Standard modes recorded :	94		
CTGDIY006E Unable to connect to server/config: <i>server host / Config instance id</i>	95		

CTGDIA101E There are multiple services described in the WSDL document at ' <i>URL</i> '. Select one of them.	100	CTGDIZ602I Parameter ' <i>wsdlUrl</i> ': <i>parameter value</i>	105
CTGDIA102E The WSDL document at ' <i>URL</i> ' does not contain a description of service ' <i>service name</i> '.	100	CTGDIZ603E Parameter ' <i>wsdlUrl</i> ' is empty.	105
CTGDIA103I An HTTP client connection failed with error: <i>exception</i>	100	CTGDIZ604I Parameter ' <i>soapOperation</i> ': <i>parameter value</i>	105
CTGDIA104E A problem was encountered while parsing the SOAP request ' <i>SOAP request</i> '. The error is: <i>exception</i>	101	CTGDIZ605E Parameter ' <i>soapOperation</i> ' is empty.	105
CTGDIA105I The response payload is expected in an Attribute with name ' <i>attribute name</i> '.	101	CTGDIZ606I Parameter ' <i>complexType</i> ': <i>parameter value</i>	105
CTGDIA106E The Connector has been passed both a normal message and a fault message. Only one outgoing message is allowed.	101	CTGDIZ607I Parameter ' <i>operationParamList</i> ': <i>parameter value</i>	106
CTGDIA107E A problem was encountered while constructing the SOAP response message. The error is: <i>exception</i>	101	CTGDIZ608I WSDL service QName: <i>service queue name</i>	106
CTGDIA108I Neither a normal response payload, nor a fault has been passed to the Connector. Will not generate a SOAP response.	102	CTGDIZ609I WSDL port QName: <i>port queue name</i>	106
CTGDIA109E Provide a <i>\$faultReason</i> Attribute.	102	CTGDIZ610I WSDL operation style: <i>operation style</i>	106
CTGDIA110E A problem was encountered while constructing the SOAP fault message. The error is: <i>exception</i>	102	CTGDIZ611I Registered class ' <i>class name</i> ' for ' <i>queue name</i> '.	106
CTGDIA111E A problem was encountered while configuring the underlying Axis2 library. The error is: <i>exception</i>	102	CTGDIZ612E Entry Attribute ' <i>attribute</i> ' is missing.	107
CTGDIA112E A problem was encountered while reading the WSDL document at ' <i>URL</i> '. The error is: <i>exception</i>	102	CTGDIZ613I About to call web service...	107
CTGDIA113E Unknown SOAP version: ' <i>SOAP namespace URI</i> '.	103	CTGDIZ614I SOAP response Java Object: <i>response Java Object</i>	107
CTGDIA114E Missing ' <i>wsdlUrl</i> ' parameter.	103	CTGDIZ615W This web service returned a SOAP Fault message. Fault string is: <i>axisFault string</i>	107
CTGDIA115E Could not obtain AssemblyLine configuration.	103	CTGDIZ617E The invocation of this web service failed for the following reason: <i>class name: message</i>	107
CTGDIA116E Cannot derive a web service description from the AssemblyLine configuration. The error is: <i>exception</i>	103	CTGDIZ619I Additional output parameter: parameter name: <i>parameter name</i> , parameter value: <i>parameter value</i>	108
CTGDIA117E A problem was encountered while writing the WSDL document to file ' <i>file name</i> '. The error is: <i>exception</i>	103	CTGDIZ620I Additional output parameter: parameter name: <i>parameter name</i> , parameter value: <i>parameter value</i>	108
CTGDIA118E The message exchange pattern ' <i>URL</i> ' of operation ' <i>operation name</i> ' does not allow a SOAP fault response.	104	CTGDIZ621E Axis EasyInvoke Soap WS Function Component expected either an Entry or an Object[], but received ' <i>class</i> ' instead.	108
CTGDIA119E The message exchange pattern ' <i>URL</i> ' of operatio ' <i>operation name</i> ' requires a response. Either provide a normal response in an Attribute named ' <i>Attribute name</i> ' or provide a SOAP fault.	104	CTGDIZ622w The value ' <i>value</i> ' is invalid for the ' <i>timeOut</i> ' parameter.	108
CTGDIA120I Will not generate a SOAP response, because an HTTP body is provided in the ' <i>conn</i> ' Entry.	104	CTGDIZ623I The invocation of a service will wait forever for a response.	108
CTGDIA121I WSDL file generated successfully.	104	CTGDIZ001E The ' <i>wsdlFile</i> ' parameter must be set to use the Axis Easy Web Service Server Connector.	109
CTGDIZ601I Web service called successfully.	104	CTGDIZ002I The ' <i>wsdlFile</i> ' parameter is set to <i>parameter value</i>	109
		CTGDIZ003E The ' <i>soapOperation</i> ' parameter must be set to use the Axis Easy Web Service Server Connector.	109
		CTGDIZ004I The ' <i>soapOperation</i> ' parameter is set to <i>parameter value</i>	109
		CTGDIZ005I The ' <i>complexType</i> ' parameter is set to <i>parameter value</i>	110
		CTGDIZ006E Cannot find the <i>attribute name</i> attribute of the op-entry.	110
		CTGDIZ007E The operation name ' <i>operation name</i> ' extracted from the SOAP request is not valid operation name.	110

CTGDIZ008I Response Object values: <i>array of values</i>	110
CTGDIZ009I Request Object array: <i>array of values</i>	110
CTGDIZ201I Successfully generated a SOAP message.	111
CTGDIZ202E Parameter 'wsdlUrl' is empty.	111
CTGDIZ203I Parameter 'wsdlUrl': <i>parameter value</i>	111
CTGDIZ204E Parameter 'soapOperation' is empty.	111
CTGDIZ205I Parameter 'soapOperation': <i>parameter value</i>	111
CTGDIZ206I Parameter 'complexTypes': <i>parameter value</i>	111
CTGDIZ207E Parameter 'mode' is empty.	112
CTGDIZ208I Parameter 'mode': <i>parameter value</i>	112
CTGDIZ209E Parameter 'mode' has invalid value: ' <i>parameter value</i> '.	112
CTGDIZ210I Parameter 'operationParamList': <i>parameter value</i>	112
CTGDIZ211I Parameter 'returnXMLType': <i>mReturnXMLType</i>	112
CTGDIZ212E Invalid value for 'returnXMLType': <i>parameter value</i>	113
CTGDIZ213I Generated SOAP message Attribute: <i>attribute</i>	113
CTGDIZ214I WSDL service QName: <i>service queue name</i>	113
CTGDIZ215I WSDL port QName: <i>port queue name</i>	113
CTGDIZ216I WSDL operation style: <i>operationStyle</i>	113
CTGDIZ217I AXIS href/multiRef is to <i>boolean</i>	114
CTGDIZ218E The value of the 'soapFault' attribute has an invalid type: <i>attribute value</i>	114
CTGDIZ219E Entry Attribute ' <i>attribute name</i> ' is missing.	114
CTGDIZ220I About to generate a SOAP message using the following parameters:	114
CTGDIZ221I Target namespace: <i>namespace</i>	114
CTGDIZ222I SOAP operation: <i>operation</i>	115
CTGDIZ223I Complex types: <i>types</i>	115
CTGDIZ224I SOAP operation parameters: <i>parameters</i>	115
CTGDIZ225I This is a <i>message type</i> message.	115
CTGDIZ226I Generated SOAP message: <i>SOAP message</i>	115
CTGDIZ227E The Function Component expected either an Entry or an Object[], but received the class ' <i>class</i> ' instead.	116
CTGDIZ228I Registered type mapping: Java type: <i>Java class name</i> XML type: <i>XML qualified name</i> Serializer Factory: <i>Java class name</i> Deserializer Factory: <i>Java class name</i>	116
CTGDIZ501I Parsed a SOAP message successfully.	116

CTGDIZ502I Parameter 'wsdlUrl': <i>parameter value</i>	116
CTGDIZ503E Parameter 'wsdlUrl' is empty.	116
CTGDIZ504I Parameter 'soapOperation': <i>parameter value</i>	117
CTGDIZ505E Parameter 'soapOperation' is empty.	117
CTGDIZ506I Parameter 'complexTypes': <i>parameter value</i>	117
CTGDIZ507I Parameter 'mode': <i>parameter value</i>	117
CTGDIZ508E Parameter 'mode' is empty.	117
CTGDIZ509E Parameter 'mode' has invalid value: ' <i>parameter value</i> '.	117
CTGDIZ510I Parameter 'inputType': <i>parameter value</i>	118
CTGDIZ511E Invalid value for 'inputType': <i>parameter value</i>	118
CTGDIZ512I Parsed Java Object Attribute: <i>attribute</i>	118
CTGDIZ513I WSDL service QName: <i>service queue name</i>	118
CTGDIZ514I WSDL port QName: <i>port queue name</i>	118
CTGDIZ515E Entry Attribute ' <i>attribute</i> ' is missing.	119
CTGDIZ516I About to parse a SOAP message using the following parameters:	119
CTGDIZ517I Complex types: <i>complex type</i>	119
CTGDIZ518I SOAP message: <i>SOAP message</i>	119
CTGDIZ519I Parsed Java Object: <i>Java object</i>	119
CTGDIZ520E The message parsed is a SOAP Fault message. The fault string is: <i>fault string</i>	120
CTGDIZ521I Additional output parameter: parameter name: <i>parameter name</i> , parameter value: <i>parameter value</i>	120
CTGDIZ522I Additional output parameter: parameter name: <i>parameter name</i> , parameter value: <i>parameter value</i>	120
CTGDIZ523I Registered type mapping: Java type: <i>Java class name</i> XML type: <i>XML qualified name</i> Serializer Factory: <i>Java class name</i> Deserializer Factory: <i>Java class name</i>	120
CTGDIZ524E Invalid object recieved: <i>object</i>	120
CTGDKM401E Missing source file. Use " <i>command line switch</i> " to specify it.	121
CTGDKM402E Cannot read file: " <i>file which was unable to read</i> ".	121
CTGDKM403E Duplicate files specified!	121
CTGDKM404E Cannot write file: " <i>file which was unable to write</i> ".	121
CTGDKM405E Cannot delete file: " <i>file which was unable to delete</i> ".	121
CTGDKM406E Cannot rename file " <i>filename of source file</i> " to " <i>filename of destination file</i> ".	122

CTGDKM407I Usage: <migration command> -f source_file [-b backup_file] [-n dest_file] [-?][-v]... -? Shows this help. -v Print more verbose information to the standard output. -f source_file Specifies the file to migrate. -b bakup_file Specifies the file to use as backup. -n dest_file Specifies the file to output the migration result to. 122	CTGDKJ112E Could not select XML elements: <i>Exception message</i> 128
CTGDKM408E Error migrating file. 122	CTGDKJ113E Invalid input data passed. The Function Component was passed the following expected type: <i>input type</i> . Exception occurred: <i>Exception message</i> 128
CTGDKM409I File successfully migrated. 122	CTGDJA001E The situation.reasoningScope attribute has not been defined. 128
CTGDKJ001E Castor mapping file not specified. 123	CTGDJA002E The value of attribute situation.categoryName is not defined. . . 128
CTGDKJ002E Invalid value for ' <i>parameter name</i> ': <i>parameter value</i> 123	CTGDJA003E The value of attribute RepeatCount is invalid. 128
CTGDKJ003E Could not load mapping file: <i>Exception message</i> 123	CTGDJA004E The value of attribute ElapsedTime is undefined. 129
CTGDKJ004E Could not create Document Builder: <i>exception message</i> 123	CTGDJA005E The value of attribute ElapsedTime is invalid. 129
CTGDKJ005E Invalid root element name: <i>Exception message</i> 123	CTGDJA006E The value of attribute Severity is invalid. 129
CTGDKJ006E Error on marshalling Entry attributes: <i>Exception message</i> 124	CTGDJA007E The value of attribute Priority is invalid. 129
CTGDKJ007E Error while transforming DOM to string: <i>Exception message</i> 124	CTGDJA008E The value of attribute SequenceNumber is invalid. 129
CTGDKJ008E Could not load mapping file: <i>Exception message</i> 124	CTGDJA009E The value of attribute situation.categoryName is invalid: <i>Value of attribute</i> 130
CTGDKJ009E Could not create Document Builder: <i>Exception message</i> 124	CTGDJA010E The argument being passed to perform method is invalid. 130
CTGDKJ010E Error on object marshalling: <i>exception message</i> 125	CTGDJA011E A null value cannot be passed as an argument to the perform method. . . . 130
CTGDKJ011E Exception while transforming DOM to String: <i>exception message</i> 125	CTGDJA012E Both of the attributes 'event' and 'eventXml' have invalid or undefined values. 130
CTGDKJ012E Invalid return type specified: <i>return type</i> 125	CTGDJA013E The 'eventXml' attribute does not contain a valid XML as a CBE object representation. Reason: <i>Exception Message</i> . 130
CTGDKJ101E Castor mapping file not specified. 125	CTGDJA014E Only one of the attributes 'event', 'eventXml' must be set. 131
CTGDKJ102E Invalid value for ' <i>parameter name</i> ': <i>parameter value</i> 125	CTGDJA015E Could not retrieve a CBE object from the XML specified in 'eventXml' attribute. 131
CTGDKJ103E Empty attribute specification: <i>attributes</i> 126	CTGDKL101E Error parsing XML. An invalid XML representation of a CBE object. Exception occurred: <i>ExceptionMSG</i> 131
CTGDKJ104E XPath not specified for attribute: <i>attribute name</i> 126	CTGDKL103E Error generating a CBE object from the specified attributes. 131
CTGDKJ105E Could not load mapping file: <i>exception message</i> 126	CTGDKL106E Unable to validate the CBE object in the 'event' attribute. Exception occurred: <i>ExceptionMSG</i> 131
CTGDKJ106E Could not create Unmarshaller: <i>exception message</i> 126	CTGDKL107E The CBEParseWriter is not initialized. 132
CTGDKJ107E Unable to create DOM Document from XML String: <i>exception message</i> 126	CTGDIH201E Parameter ' <i>param name</i> ' was initialized with value: ' <i>value</i> '. 132
CTGDKJ108E No input data was passed to the Function Component. The Function Component was passed the following expected type: <i>input type</i> 127	CTGDIH202E Parameter ' <i>param name</i> ' is not provided. 132
CTGDKJ109E Special type ' <i>special type attribute</i> ' with attribute: <i>attribute name</i> is not supported. 127	CTGDIH203E Unsupported mode: ' <i>mode</i> ' for selected artifact type: ' <i>type name</i> ' . . . 132
CTGDKJ110E Unable to select attribute from XML at path: <i>attribute xPath</i> Exception occurred: <i>Exception message</i> 127	CTGDIH204E An exception occurred while trying to close the database connection: <i>message</i> 132
CTGDKJ111E Error on unmarshalling: <i>exception message</i> 127	CTGDIH205E No Entry provided. 133

CTGDIH206E Incompatible classification: expected - ' <i>expected class name</i> ', found - ' <i>actual class name</i> '	133	CTGDIZ715I JAR argument at index <i>index</i> : ' <i>argument</i> '.	139
CTGDIH207E Unable to create ' <i>instance</i> ' instance from an input Entry.	133	CTGDJW001I The column separator is set to ' <i>separator</i> '.	139
CTGDIH208I Search Query for ' <i>instance</i> ' : ' <i>searchQuery</i> '.	133	CTGDJW002I Parser will use provide column names: ' <i>column names</i> '.	139
CTGDIH209E Actual CI already exists for GUID - ' <i>guid</i> '.	133	CTGDJW003I Parser will use first input line for column names.	140
CTGDIH210E Config Item already exists for GUID - ' <i>guid</i> '.	134	CTGDJW004I No column names provide. Will use first output entry for column names: ' <i>column names</i> '.	140
CTGDIH211E Relation already exists: ' <i>relation</i> '.	134	CTGDJW005I A long Line was encountered at line number ' <i>line number</i> '. The line is ' <i>number of bytes</i> ' bytes and the line contents are ' <i>line</i> '.	140
CTGDIH212E CI Relation already exists: ' <i>ciRelation</i> '.	134	CTGDJZ701I The Class Type <i>param name</i> has value: ' <i>value</i> '.	140
CTGDIH213E Could not get the classification for the selected class type ' <i>classType</i> '.	134	CTGDJZ702I Use a DIS system for the needed meta-data: ' <i>use dis</i> '.	140
CTGDJZ551E Close IdML Function Component accepts only a IBM Security Directory Integrator Entry as input.	134	CTGDJZ703I The parameter <i>param name</i> was initialized with the value: ' <i>value</i> '.	141
CTGDJZ552E The book ' <i>book name</i> ' is already closed or has never been created.	135	CTGDJZ704E Parameter ' <i>param name</i> ' is not provided.	141
CTGDJZ553I Close IdML Function Component will work with book: ' <i>book name</i> '.	135	CTGDJZ705E The Data Cleaser Function Component accepts only a IBM Security Directory Integrator Entry as input.	141
CTGDJZ554I The name of the currently used book ' <i>book name</i> ' has been overridden to ' <i>new name</i> '.	135	CTGDIZ901E Delta key attribute not defined.	141
CTGDJZ555I Close IdML Function Component closed book ' <i>book name</i> '.	135	CTGDIZ902E The perform method of the Function Component was not passed an object of type com.ibm.di.entry.Entry. This object is not a valid parameter to pass to the perform method.	142
CTGDJZ556E Parameter ' <i>param name</i> ' is not provided.	136	CTGDIZ903E DELTA: Duplicate delta key: <i>key value</i>	142
CTGDIX001E The ' <i>commandLine</i> ' parameter must be set to use the Command Line Connector.	136	CTGDIZ904I DELTA: new entry, key = <i>key value</i>	142
CTGDIX002E Unable to run a command. The ' <i>commandLine</i> ' parameter must be set to use the Command Line Connector.	136	CTGDIZ905I DELTA: modified entry, key = <i>key value</i>	142
CTGDIZ701I Running WSDL2Java...	136	CTGDIZ906I DELTA: No changes, key = <i>key value</i>	142
CTGDIZ702I WSDL2Java finished running.	136	CTGDIZ907I DELTA: skip next unchanged entry..	143
CTGDIZ703I Compiling java files...	137	CTGDIZ908I DELTA: Iterating through deleted entries.	143
CTGDIZ704I Creating JAR file...	137	CTGDIZ909I DELTA: get next deleted entry.	143
CTGDIZ705I Purging java files...	137	CTGDIZ910I DELTA: Remove deleted entry, key = <i>key value</i>	143
CTGDIZ706I Purging class files...	137	CTGDIZ911W DELTA: The Key Attribute ' <i>attribute name</i> ' contains more than one value. <i>Number of values</i> values were found.	143
CTGDIZ707I Deleting JAR file...	137	CTGDIZ912I DELTA: Entry without value for key attribute = <i>attribute name</i>	144
CTGDIZ708I Deleting ' <i>file name</i> '.	138	CTGDIZ913W Delete table <i>table name</i> ?	144
CTGDIZ709I Creating directory ' <i>directory path</i> '.	138	CTGDIZ914I Table <i>table name</i> deleted.	144
CTGDIZ710E Could not generate Java source files from the specified WSDL. Exception occurred: <i>exception</i>	138	CTGDIZ915I Using Derby Delta: tableName= <i>table name</i> , database= <i>database URL</i>	144
CTGDIZ711E Could not compile generated Java source files. Exception occurred: <i>exception</i>	138	CTGDIZ916I Delta component using unique key <i>key name</i>	144
CTGDIZ712E Could not generate JAR file from the compiled Java class files. Exception occurred: <i>exception</i>	138	CTGDKN401I Initialization in progress...	145
CTGDIZ713I Command part at index <i>index</i> : ' <i>command part</i> '.	139		
CTGDIZ714I Compile argument at index <i>index</i> : ' <i>argument</i> '.	139		

CTGDKN402E An exception occurred while creating the Message Queue: <i>exception</i>	145	CTGDKN431I Will use the Distinguished Name for password synchronization.	151
CTGDKN403E An exception occurred while opening the Message Queue: <i>exception</i>	145	CTGDKN432I Will prefix Distinguished Name with: ' <i>prefix name</i> '.	151
CTGDKN404E An exception occurred: <i>exception</i>	145	CTGDKN433I Found UNID: ' <i>UNID</i> '.	151
CTGDKN405I Terminating...	145	CTGDKN434I Synchronizing User ID: ' <i>user name</i> '.	151
CTGDKN406I Terminated.	146	CTGDKN435I Domino Plug-in/Proxy authentication successful.	151
CTGDKN407E The Password Store is not ready. No password synchronization will be performed on this agent run.	146	CTGDKN436I Domino Plug-in/Proxy authentication failed.	152
CTGDKN408I Agent search returned no documents.	146	CTGDKN437E Could not connect to localhost on port <i>port number</i>	152
CTGDKN409I Agent search returned <i>number of documents</i> documents.	146	CTGDKN438E The file ' <i>file name</i> ' could not be found.	152
CTGDKN410E An unexpected Lotus Notes exception occurred.	146	CTGDKN439E The file ' <i>file name</i> ' could not be read.	152
CTGDKN411E An unexpected exception occurred.	147	CTGDJE002E The Notes Thread not alive. Domino Change Detection Connector cannot execute the needed command against the Domino Server without an active Notes Thread.	152
CTGDKN412I Processing admin request with UNID: ' <i>UNID</i> '.	147	CTGDJE003E Fatal Error while executing command against Domino Server: <i>exception</i>	153
CTGDKN413I Unable to obtain parent document for admin log with UNID: ' <i>UNID</i> '. The password change will not be stored.	147	CTGDJE004I Domino Change Detection Connector is restarting.	153
CTGDKN414I Missing or hashed password in admin request with UNID ' <i>UNID</i> '. Skipping this admin request.	147	CTGDJE005I Checkpoint/restart is only supported in 'After read' and 'End of cycle' mode.	153
CTGDKN415I Missing FullName in admin request. Skipping this request.	147	CTGDJE006E No documents in the list of UnIDs, or the list is null.	153
CTGDKN416I The password of user ' <i>user name</i> ' is successfully stored.	148	CTGDJE007E No documents in the list of UnIDs, or the list is null.	153
CTGDKN417I The password of user ' <i>user name</i> ' could not be stored.	148	CTGDJE008E No documents in the list of UnIDs, or the list is null.	154
CTGDKN418E Unable to mark admin request ' <i>UNID</i> ' as processed.	148	CTGDJE009E Connector already initialized. You must terminate it before initializing again.	154
CTGDKN419I Will assume the objects [<i>object name</i> ;] and [<i>object name</i>] are equal.	148	CTGDJE010E Connector was unable to initialize local Notes session to Domino Server. Exception encountered: <i>exception</i>	154
CTGDKN420E Unable to retrieve password document from helper database.	148	CTGDJE011I Enabling SSL flag since 'iioSSL' was not set to true or false.	154
CTGDKN421E The field ' <i>field ID</i> ' is missing from a document in the ' <i>database name</i> ' database.	149	CTGDJE012E NotesException encountered trying to create a session with the Domino Server: Class Name=' <i>class name</i> ', Exception= <i>exception</i>	155
CTGDKN422I Could not save success indicator for Notes client.	149	CTGDJE013I Successfully connected to Domino Server: Name=' <i>server name</i> ', Version=' <i>version number</i> ', Platform=' <i>operating system</i> '.	155
CTGDKN423I Will reject all changes to the Person document for user ' <i>user name</i> '.	149	CTGDJE014E Domino Change Detection Connector unable to open database ' <i>database name</i> ' on server ' <i>server name</i> '.	155
CTGDKN424E An error has occurred while retrieving the Person document.	149	CTGDJE015E Domino Change Detection Connector unable to open database ' <i>database name</i> ' on server ' <i>server name</i> '.	155
CTGDKN425E Could not read data from the Person document.	149	CTGDJE016E Could not initialize the Domino Change Detection Connector. Exception occurred: <i>exception</i>	156
CTGDKN426E Could not remove custom fields in the Person document.	150		
CTGDKN427E Cannot synchronize password. User identifier field ' <i>field ID</i> ' is empty.	150		
CTGDKN428I User identifier is NULL. Will not synchronize password.	150		
CTGDKN429I Searching for UNID with filter: ' <i>filter</i> '.	150		
CTGDKN430I Missing UNID. Password will not be synchronized.	150		

CTGDJE017W Domino Change Detection Connector could not terminate the local Notes session. Exception occurred: <i>exception</i>	156	CTGDJE042E Could not retrieve document with UnID ' <i>unID</i> '.	161
CTGDJE018W Domino Change Detection Connector could not close the IIOP objects. Exception occurred: <i>id=id</i>	156	CTGDJE043I Check database permissions.	161
CTGDJE020E The 'dominoServerIP' parameter must be set to use the Domino Change Detection Connector.	156	CTGDJE044I If the document is already deleted, it will be reported on the next poll.	161
CTGDJE021E The 'userName' parameter must be set to use the Domino Change Detection Connector.	156	CTGDJE045E Could not read document's last modification date. Exception occurred: <i>id=id; exception=exception</i>	161
CTGDJE022E The 'database' parameter must be set to use the Domino Change Detection Connector.	157	CTGDJE046E Invalid end date value: <i>time stamp</i>	161
CTGDJE024E The 'deliveryMode' parameter was set to an invalid value: ' <i>parameter value</i> '.	157	CTGDJE047E Error on closing the store: <i>exception</i>	162
CTGDJE025E The 'systemStoreKey' parameter must be set to use the Domino Change Detection Connector.	157	CTGDJE048E Could not clear Property Store table:. Exception occurred: <i>exception</i>	162
CTGDJE026W The 'sleepInterval' parameter set to an invalid value ' <i>parameter value</i> '. The default value ' <i>parameter value</i> ' will be used instead.	157	CTGDJE049I Stores the synchronization state in the System Store. Start date is ' <i>date</i> '.	162
CTGDJE027W The 'timeout' parameter set to an invalid value ' <i>parameter value</i> '. The default value ' <i>parameter value</i> ' will be used instead.	158	CTGDJE050I Check docs is set to ' <i>UnIDs</i> ' UnID.	162
CTGDJE028E Could not read synchronization state from System Store. Exception occurred: <i>exception</i>	158	CTGDJE051E Could not store the synchronization state in the System Store. Exception occurred: <i>exception</i>	162
CTGDJE029E Could not retrieve state from persistent store. Exception occurred: <i>exception</i>	158	CTGDJE052E Could not terminate the IIOP session. Exception occurred: <i>id=ID, exception=exception</i>	163
CTGDJE030E The System Store key not found and 'Start At' parameter not specified.	158	CTGDJE053E Could not terminate the local Notes session. Exception occurred: <i>exception</i>	163
CTGDJE031I Start at start of data. Will perform full synchronization.	158	CTGDJE054E Error on stopping internal thread. Exception occurred: <i>exception</i>	163
CTGDJE032I Start at end of data. Will listen for new changes only.	159	CTGDJE055E Exception while closing the System Store table: <i>exception</i>	163
CTGDJE033I Start at specific date. Will use start date: <i>date</i>	159	CTGDJE056E Could not retrieve created date for the document ' <i>document ID</i> '. Exception occurred: <i>id=ID, exception=exception</i>	163
CTGDJE034E Invalid Start At value: <i>date</i>	159	CTGDJE057I Will assign a value of NULL to attribute '\$\$DateCreated'.	164
CTGDJE035E The System Store Entry does not contain the 'SYNC_TIME' attribute.	159	CTGDJE058E Could not retrieve last modified date for document ' <i>document ID</i> '. Exception occurred: <i>id=ID, exception=exception</i>	164
CTGDJE036E Invalid value of the ' <i>PROP_SYNC_TIME</i> ' System Store Entry attribute: <i>attrValue</i>	159	CTGDJE059I Will assign a value of NULL to attribute '\$\$DateModified'.	164
CTGDJE037E The System Store Entry attribute 'SYNC_TIME' is of unknown type: <i>class name</i>	160	CTGDJE060I The item ' <i>item name</i> ' is of type ATTACHMENT and will not be added to the Entry.	164
CTGDJE038I Start date for synchronization: <i>date</i>	160	CTGDJE061I Added a new attribute to the entry: <i>attribute name</i>	165
CTGDJE039I Verify reported UnIDs are processed on previous runs.	160	CTGDJE062I The item type is <i>item type</i>	165
CTGDJE040I Timeout waiting for next changed entry.	160	CTGDJE063E Could not retrieve item values. Exception occurred: <i>id=ID, exception=exception</i>	165
CTGDJE041E UnID list is null.	160	CTGDJE064I Value(s) for attribute ' <i>attribute name</i> ' will be skipped.	165
		CTGDJE065I The data is: <i>value</i>	165
		CTGDJE066E Could not convert Notes date to Java date. Exception occurred: <i>id=ID, exception=exception</i>	166
		CTGDJE067I Date value for attribute ' <i>attribute name</i> ' will be skipped.	166

CTGDJE068E Could not determine change type for document with UNID ' <i>document ID</i> '. Exception occurred: <i>id=ID</i> , <i>exception=exception</i>	166	CTGDJE089E Failed to convert the port parameter value to a numeric type: <i>parameter value</i>	171
CTGDJE069I Will assign change type 'unknown' to document ' <i>document ID</i> '.	166	CTGDJE090I The Delivery Mode parameter is removed since IBM Security Directory Integrator 6.1.1. Refer to the IBM Security Directory Integrator documentation for more information.	171
CTGDJE070E Native call to getModifiedNotes method returned NULL.	166	CTGDJE091I Sorting changed documents.	171
CTGDJE071E Could not parse end date value: <i>date</i>	167	CTGDIE092W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used.	171
CTGDJE072E Invalid string date format passed: <i>date string</i>	167	CTGDKC001E Connector Notes Thread not alive. Cannot perform.	172
CTGDJE073E Exception occurred while retrieving document with UnID ' <i>unID</i> ': <i>id=ID</i> , <i>exception=exception</i>	167	CTGDKC002E Failed to execute the command. NotesException occurred: <i>exception</i>	172
CTGDJE074I Local Client Session successfully created.	167	CTGDKC003E Fatal error while executing the command. Exception occurred: <i>exception</i>	172
CTGDJE075E Connector unable to create Local Client Session. Exception encountered: <i>exception detail message string</i>	167	CTGDKC004E Connector already initialized. You must terminate it before initializing again.	172
CTGDJE076I IIOP Session successfully created. The specified IOR string is used. SSL is turned on.	168	CTGDKC005W Exception occurred while terminating: <i>exception</i>	173
CTGDJE077E Connector unable to create IIOP Session with the configured IOR string. SSL is turned on. Exception encountered: <i>exception detail message string</i>	168	CTGDKC009I Will use full-text search in Iterator and Lookup modes.	173
CTGDJE078I IIOP Session successfully created. SSL is turned on.	168	CTGDKC010I Will use regular database search in Iterator and Lookup modes.	173
CTGDJE079E Connector unable to create IIOP Session with SSL turned on. Exception encountered: <i>exception detail message string</i>	168	CTGDKC012I Successfully connected to Domino Server: Name=' <i>server name</i> ', Version=' <i>version number</i> ', Platform=' <i>operating system</i> '.	173
CTGDJE080I IIOP Session successfully created. SSL is turned off.	169	CTGDKC013E Unable to open 'Name and Address Book' database: <i>database name</i>	174
CTGDJE081E Connector unable to create IIOP Session with the configured IOR string. SSL is turned off. Exception encountered: <i>exception detail message string</i>	169	CTGDKC014I Successfully opened 'Name and Address Book' database <i>database name</i>	174
CTGDJE082I IIOP Session successfully created. SSL is turned off.	169	CTGDKC015I The Database <i>database name</i> is full-text indexed.	174
CTGDJE083E Connector unable to create IIOP Session. SSL is turned off. Exception encountered: <i>exception detail message string</i>	169	CTGDKC016I The database <i>database name</i> is not full-text indexed.	174
CTGDJE084W The 'systemStoreKey' parameter was not specified in the Domino Change Detection Connector. The Connector will not persist state.	170	CTGDKC017E Unable to open Admin database: <i>database name</i>	174
CTGDJE085W The Document item <i>name of document item</i> of type <i>type of document item</i> was not handled.	170	CTGDKC018I Successfully opened the Administration Requests Database: <i>database name</i>	175
CTGDJE086I Notes API exception ID: <i>ID of Notes API exception</i> Notes API exception text: <i>text of Notes API exception</i>	170	CTGDKC019E Unable to select entries. The View 'People' was not found.	175
CTGDJE087E The following exception occurred during Connector's initialization: <i>exception</i>	170	CTGDKC020E Could not filter documents. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	175
CTGDJE088E The following exception occurred during Connector's termination: <i>exception</i>	171	CTGDKC021I View search returned NULL.	175
		CTGDKC022I View search returned <i>number of documents</i> documents.	176
		CTGDKC023E Could not perform database search. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	176
		CTGDKC024I Database search returned NULL.	176
		CTGDKC025I Database search returned <i>number of documents</i> documents.	176
		CTGDKC026E Error retrieving next user Document. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	176

CTGDKC027E Unable to find the entry. The View 'People' was not found.	177
CTGDKC028I Full Text Search view for: <i>filter</i>	177
CTGDKC029I Full Text Search returns <i>number of documents</i> documents.	177
CTGDKC030I Database search with formula: <i>formula</i>	177
CTGDKC031I Database search returned NULL in the findEntry method.	177
CTGDKC032I Database search returned <i>number of documents</i> documents.	178
CTGDKC033E Given Document is NULL. Cannot build Entry.	178
CTGDKC034I Document vector of items is NULL.	178
CTGDKC035I Building entry with all items: <i>items</i>	178
CTGDKC036I Item ' <i>item name</i> ' is of type ATTACHMENT will not be added to Entry. . .	178
CTGDKC037I New Attribute: <i>attribute name</i> . . .	179
CTGDKC038I item type: <i>item type</i>	179
CTGDKC039I Item values: <i>item values</i>	179
CTGDKC040E Unable to modify the entry. The document not found or multiple documents found.	179
CTGDKC041E Unable to modify the entry. The user FullName not found. Cannot set user's access type.	179
CTGDKC042E Entry Attribute ' <i>attribute name</i> ' is required when creating a mail database using a custom mail template. . .	180
CTGDKC043E Unable to add entry. Cannot build search criteria to find user document after registration. User document not updated.	180
CTGDKC044E Unable to add the entry. Cannot update user document after registration. User document not found or multiple documents found.	180
CTGDKC045E Unable to add the entry. Cannot create person document. The required Attribute ' <i>attribute name</i> ' is missing or empty.	180
CTGDKC046E Unable to add the entry. Cannot create new user document.	181
CTGDKC047E Unable to delete the entry. The document not found or multiple documents were found.	181
CTGDKC048E Unable to delete the entry. The user FullName not found. Cannot delete user.	181
CTGDKC049I Will find person document using formula: <i>formula</i>	181
CTGDKC050I Updating attribute in document: <i>attribute name</i>	181
CTGDKC051E Could not hash the http password. Exception occurred: <i>exception</i> . . .	182
CTGDKC052I Updating password value in document: <i>password</i>	182

CTGDKC053I Updating value in document: <i>attribute value</i>	182
CTGDKC054I Updating values in document: <i>attribute values</i>	182
CTGDKC055E Cannot update the document. The document cannot be saved.	182
CTGDKC056I FullName criteria element value changed from ' <i>FullName</i> ' to ' <i>FullName</i> '. . .	183
CTGDKC057I FullName Attribute changed from ' <i>FullName</i> ' to ' <i>FullName</i> '.	183
CTGDKC058W Could not recycle Domino object. Exception occurred: <i>exception</i> . . .	183
CTGDKC059E NotesException occurred while performing Domino Action: ID= <i>ID</i> , Error Text= <i>error text</i>	183
CTGDKC060E NotesException occurred while trying to reset and extract the data: ID= <i>ID</i> , Error Text= <i>error text</i>	183
CTGDKC061E Cannot perform Domino Action: <i>error message</i>	184
CTGDKC062E Cannot perform Domino Action. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	184
CTGDKC063E Unable to clear attributes. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	184
CTGDKC064E Cannot perform Domino Action: <i>error message</i>	184
CTGDKC065E Unable to execute Domino Action. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	184
CTGDKC066E The isDenyGroupMember method was passed NULL for the Deny Group Document parameter.	185
CTGDKC067E The isDenyGroupMember method was passed NULL for the User Name parameter. . .	185
CTGDKC068E Deny Access Group ' <i>group name</i> ' does not exists.	185
CTGDKC069E Cannot instantiate UserAccess. The Connector's Notes session is NULL. . . .	185
CTGDKC070E Cannot instantiate UserAccess. The Connector's database is NULL.	185
CTGDKC071E Unable to enable the user. Could not find view ' <i>view name</i> '.	186
CTGDKC072E Unable to enable the user. Could not find view ' <i>view name</i> '.	186
CTGDKC073E Unable to enable the user. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	186
CTGDKC074E Unable to disable user. Could not find view ' <i>view name</i> '.	186
CTGDKC075E Unable to disable user. Could not find view ' <i>view name</i> '.	186
CTGDKC076E Unable to disable user. Deny Access Group ' <i>group name</i> ' does not exists. . .	187
CTGDKC077E Unable to disable user. Deny Access Group ' <i>group name</i> ' does not exists. . .	187
CTGDKC078E Unable to disable user. NotesException occurred: ID= <i>ID</i> , Error Text= <i>error text</i>	187

CTGDKC079E Cannot instantiate UserDeletion. The Connector's Notes session is NULL.	187	CTGDKC100I Domino Users Connector's local Notes thread terminated.	192
CTGDKC080E Cannot instantiate UserDeletion. Admin database is NULL.	187	CTGDKC101I Missing 'attr name set type' value	192
CTGDKC081E Cannot instantiate UserDeletion. The Connector's database is NULL.	188	CTGDKC102I Invalid 'attr name set type' value	192
CTGDKC082E The UserDeletion::sendAdminRequestDeleteUser method could not create admin request document.	188	CTGDKC103I Missing 'attr name deny group' value	192
CTGDKC083E Could not create admin request document.	188	CTGDKC104I Group does not exist: <i>group name</i>	193
CTGDKC084E Cannot instantiate UserRegistration. The Connector's Notes session is NULL.	188	CTGDKC105I Missing user's FullName value	193
CTGDKC085W The UserRegistration::extractAndStoreData method could not parse 'REG_Expiration' value (<i>attribute value</i>). Will use default value of NULL.	189	CTGDKC106I Invalid Delete Mail File value	193
CTGDKC086E The UserRegistration::perform method could not create Registration object.	189	CTGDKC107E Group does not exist: <i>group name</i>	193
CTGDKC087E Could not create Registration object.	189	CTGDKC108E Invalid Delete Mail File value	193
CTGDKC088E Failed to convert the port parameter value to a numeric type: <i>parameter value</i>	189	CTGDKC109I Required Attribute ' <i>attr name</i> ' is missing.	194
CTGDKC089E NotesException encountered while trying to create a session with the Domino Server: Class Name=' <i>class name</i> ', Exception= <i>exception</i>	189	CTGDKC110I Invalid value (' <i>id</i> ') set to Attribute ' <i>type</i> '. Check Connector's documentation.	194
CTGDKC090I IIOP Session successfully created. The specified IOR string is used. SSL is turned on.	190	CTGDKC111I User Registration should not perform according to the ' <i>attribute name</i> ' Attribute.	194
CTGDKC091I IIOP Session successfully created. SSL is turned on.	190	CTGDKC112E Could not register user ' <i>last name</i> '.	194
CTGDKC092I IIOP Session successfully created. The specified IOR string is used. SSL is turned off.	190	CTGDIH251E An exception occurred while trying to close the database connection: <i>message</i>	194
CTGDKC093I IIOP Session successfully created. SSL is turned off.	190	CTGDIH252E Parameter ' <i>param name</i> ' is not provided.	195
CTGDKC094I Using specified 'IOR' in the connection information for opening the session.	191	CTGDIH253E Parameter ' <i>param name</i> ' was initialized with value: ' <i>value</i> '.	195
CTGDKC095I Session to Domino Server is created.	191	CTGDIH254E No Entry provided.	195
CTGDKC096I Opening Session to Domino Server: Session Type=' <i>Session Type</i> ',, Hostname=' <i>Hostname</i> ', User ID=' <i>User ID</i> ', Requested IIOP/SSL=' <i>Boolean</i> '.	191	CTGDIH255E Primary key not found while deleting an deployed asset!	195
CTGDKC097E Unable to create local Notes thread because the lotus.domino.NotesThread class was not found in the classpath of the program. Exception occurred: <i>exception</i>	191	CTGDIH256I deleteRow(...); Query: ' <i>query</i> '	195
CTGDKC098I Domino Users Connector's local Notes thread started.	191	CTGDIH257E Deployed Asset with the given description already exists!: ' <i>dpaObject</i> '	196
CTGDKC099W Domino Users Connector could not terminate the local Notes thread. Exception occurred: <i>exception</i>	192	CTGDIH258I saveClassInstance(..); saved instance: ' <i>instance</i> '	196
		CTGDIH259E Foreign Key to parent class is null or missing. ' <i>instanceDesc</i> '	196
		CTGDIH260E Multiple parent instance found: keys - [' <i>pkList</i> '] for ' <i>instanceDesc</i> '	196
		CTGDIH261E Parent instance not found for: ' <i>instanceDesc</i> '	196
		CTGDIH262E Missing or unsupported data type: ' <i>dataType</i> '	197
		CTGDIH263E Missing child named ' <i>childName</i> ' under ' <i>nodeName</i> '	197
		CTGDIH264E Missing Class definition for: ' <i>className</i> '	197
		CTGDIH265E Primary key not specified for ' <i>classDef</i> '	197
		CTGDIH266E Parent class reference not found for: ' <i>classDesc</i> '	197
		CTGDIH267E Parent class instance not found for: ' <i>classDesc</i> '	198
		CTGDIH268E Parent is null for: ' <i>classDesc</i> '.	198

CTGDIH269E Required property is missing: 'propName'	198
CTGDIH270E Required reference is missing: 'refName'	198
CTGDIH271E Multiple reference found: 'refName'	198
CTGDIH272I getNextEntry(...) return: 'entry'	199
CTGDIH273E Unable to create a class instance for the input Entry 'entry'	199
CTGDIH274I addEntry(...); class instance: 'classInst'	199
CTGDIH275E Incompatible asset class found while adding a new asset 'asset'	199
CTGDIH276I addEntry(...); saved class instance: 'classInst'	199
CTGDIH277I removeEntry(...); class instance: 'classInst'	200
CTGDIH278E Missing asset class name in the input entry 'entry'	200
CTGDIH279I createSelectQuery(...); Query: 'query'	200
CTGDIM101E Failed to read DSML because input stream was not found. The input or output modes of the DSML Parser may not be valid.	200
CTGDIM102W Writing out entry but the entry is missing the DN attribute 'attribute value'.	200
CTGDIM103I Reading entry where parent node is 'node name' and the current node is 'node name'.	201
CTGDIM104I indent DOCUMENT node type.	201
CTGDIM105I indent Node Name: node name	201
CTGDIM106I indent Node Value: node value	201
CTGDIM107I indent Node type is not recognized.	201
CTGDIN001E The 'url' parameter must be set to use the DSML v2 SOAP Connector.	202
CTGDIN002I Connector will use SOAP binding.	202
CTGDIN003E Unable to initialize DSML v2 SOAP Connector because an unsupported protocol ' <i>protocol name</i> ' was specified.	202
CTGDIN004E The putEntry method was called without the required '\$dn' Attribute in Entry.	202
CTGDIN005I The putEntry method called with '\$dn' attribute set to ' <i>attribute value</i> '.	202
CTGDIN006I Selecting entries with search base of ' <i>DN</i> ' and filter of ' <i>filter</i> '.	203
CTGDIN007I Searching for entry where ' <i>naming DN</i> ' equals ' <i>DN</i> '.	203
CTGDIN008I Searching for entry using filter ' <i>filter</i> '.	203
CTGDIN009I No entries found while searching for entry in DSML v2 SOAP Connector.	203
CTGDIN0010I Single entry found while searching for entry in DSML v2 SOAP Connector.	204

CTGDIN0011I Multiple entries found while searching for entry in DSML v2 SOAP Connector.	204
CTGDIN0012E The modify entry operation failed because the operation was invoked without an update entry being specified.	204
CTGDIN0013E The modify entry operation failed because it was a delta modify and no '\$dn' attribute was provided in either the conn entry or the link criteria.	204
CTGDIN0014E The modify entry operation failed because no distinguished name was found in existing entry.	204
CTGDIN0015I The modify entry for the modify operation is ' <i>DN</i> '.	205
CTGDIN0016I The modify operation will rename entry ' <i>old DN</i> ' to ' <i>DN</i> '.	205
CTGDIN0017E The deleteEntry method was called with no '\$dn' attribute or link-criteria.	205
CTGDIN0018I The deleteEntry method was called with '\$dn' attribute equal to ' <i>DN</i> '.	205
CTGDIN0019I No DSML response returned from server.	205
CTGDIN0020I No message body returned from server.	206
CTGDIN0021I No response returned from DSML server.	206
CTGDIN0022E Received a error DSML response Entry. Entry attribute information: dsml.operation attribute: <i>attribute value</i> , dsml.errorType attribute: <i>attribute value</i> , dsml.message attribute: <i>attribute value</i>	206
CTGDIN0023I Received a search DSML response Entry. Entry attribute information: dsml.operation attribute: <i>attribute value</i> , dsml.resultcode attribute: <i>attribute value</i> , resultDescr: <i>attribute value</i> , dsml.error attribute: <i>attribute value</i>	206
CTGDIN0024E Received a search DSML response Entry. Entry attribute information: dsml.operation attribute: <i>attribute value</i> , dsml.resultcode attribute: <i>attribute value</i> , dsml.resultdescr attribute: <i>attribute value</i> , dsml.error attribute: <i>attribute value</i>	207
CTGDIN025I Connector will not use SOAP binding.	207
CTGDIM001E Required parameter is missing: ' <i>parameter</i> '.	207
CTGDIM002I The Parser is running in server mode.	207
CTGDIM003I The Parser output indentation is disabled.	207
CTGDIM004I Soap envelope enabled in the Parser.	208
CTGDIM005E Failed to read DSML because input stream was not found. The input or output modes of the DSMLv2 Parser may not be valid.	208
CTGDIM006I Initializing DSML Input Document.	208

CTGDIM007E The DSML document being parsed has no root node.	208	CTGDIM034E The required attribute 'requestValue' was not set for the extended request.	214
CTGDIM008I Reading batchRequest.	208	CTGDIM035E The searchResultEntry was not set while creating the search request.	214
CTGDIM009I Reading batchResponse.	209	CTGDIM036E The searchResultEntry was not set while creating the search response.	214
CTGDIM010E Failed to write DSML because output stream was not found. The input or output modes of the DSMLv2 Parser may not be valid.	209	CTGDIM037E The require attribute 'errorType' not set for the error response.	214
CTGDIM011I Initializing Output Document.	209	CTGDIM038E Unable to write the Entry. The required attribute 'dsml.operation' was missing from the Entry.	214
CTGDIM012I Parser configured to resume on error.	209	CTGDIO001I Exiting initialization early because Connector already initialized with a java.net.Socket object.	215
CTGDIM013I Parser will perform parallel processing.	209	CTGDIO002I Connector will use SOAP binding.	215
CTGDIM014I Parser configured so that responses will be unordered.	210	CTGDIO003I Using provided java.net.Socket object for DSML client session.	215
CTGDIM015E Message type not supported while reading an Entry: <i>DSML operation</i>	210	CTGDIO004I No DSML request available from client.	215
CTGDIM016E Error while transforming DOM to string: <i>exception</i>	210	CTGDIO005W Exception while authenticating to HTTP Parser: <i>exception</i>	215
CTGDIM017W An error ocured while flushing the SOAP message: <i>exception</i>	210	CTGDIO006W No message body available from client.	216
CTGDIM018I Base64 decoding attribute: <i>attribute name</i>	210	CTGDIO007W Failed to initialize the DSML v2 SOAP Server Connector because the DSML Parser could not be initialized. Exception encountered: <i>exception</i>	216
CTGDIM019I Attribute <i>attribute anem</i> is specified as binary attribute but the value received is not Base64 encoded. A value of NULL will be assigned.	211	CTGDIO008E The 'dsmlPort' parameter must be set to use the DSML v2 SOAP Server Connector.	216
CTGDIM020E The required attribute 'principal' was not set for the authorization request.	211	CTGDIO009I Listening for DSML SSL connections on port ' <i>port number</i> '.	216
CTGDIM021E The required attribute 'DN' was not set for the search request.	211	CTGDIO0010I Listening for DSML connections on port ' <i>port number</i> '.	216
CTGDIM022W Error on base64 decoding: <i>entry</i>	211	CTGDIO0011I DSML v2 SOAP Server Connector closed client connection.	217
CTGDIM023E The required attribute 'DN' was not set for the modify request.	211	CTGDIO0012I Terminate server request received.	217
CTGDIM024E The required attribute 'modification' was not set for modify request.	212	CTGDIO0013I Creating dummy connection using IP Address ' <i>IP Address</i> ' and port ' <i>port number</i> '.	217
CTGDIM025E The required attribute 'DN' was not set for the add request.	212	CTGDIO0014W Encountered an IOException on unblocking the DSML v2 SOAP Server Connector's server socket: <i>exception</i>	217
CTGDIM026E Attribute not set for the add request: <i>attribute name</i>	212	CTGDIO0015I DSML v2 SOAP Server Connector is already terminating. Not sending termination request.	217
CTGDIM027E The required attribute 'DN' was not set for the delete request.	212	CTGDIO0016I Sending termination request to the DSML v2 SOAP Server Connector.	218
CTGDIM028E The required attribute 'DN' was not set for the modifyDN request.	212	CTGDIO0017E Server Socket is not open, cannot accept client requests.	218
CTGDIM029E The required attribute 'newRDN' was not set for the modifyDN request.	213	CTGDIO0018I Connector terminated by external request.	218
CTGDIM030E The required attribute 'DN' was not set for the compare request.	213	CTGDIO0019W Authentication failed. Client could not authenticate more than 3 times. Exiting...	218
CTGDIM031E Assertion is not set for the compare request.	213	CTGDIO0020I The user name is set to ' <i>user name</i> '.	218
CTGDIM032E The required attribute 'abandonID' not set for the abandon request.	213		
CTGDIM033E The required attribute 'requestName' was not set for the extended request.	213		

CTGDIO021I Connector will not use SOAP binding.	219
CTGDJK201W The Connector has overridden the Server Location parameter: ' <i>new value</i> '.	219
CTGDJK20wW The connector has overridden the Server Port parameter: ' <i>new value</i> '.	219
CTGDJK103I Initialization successful.	219
CTGDJK104I Waiting <i>number of seconds</i> second(s) for an event to occur.	219
CTGDJK105I Getting an event from the cache.	220
CTGDJK106I Waiting for an event to occur.	220
CTGDJK107I Sending event: <i>raw message text</i>	220
CTGDJK208E Error sending event. Error code: ' <i>error code</i> '	220
CTGDJK109I Termination successful.	220
CTGDJK110I Received event: ' <i>event raw text</i> '.	220
CTGDJK111I The Event contains <i>number of entries</i> entry(s).	221
CTGDJK212E Error parsing event message: ' <i>event raw text</i> '.	221
CTGDJK213E Error processing mapping file: <i>exception</i>	221
CTGDIA001E The perform method of the Function Component was not passed an object of type com.ibm.di.entry.Entry. This object is not a valid parameter to pass to perform method.	221
CTGDIA002E Error occurred while converting the Data Objects to XML: <i>exception</i>	222
CTGDIA003E Required Function Component parameter ' <i>parameter name</i> ' is not set.	222
CTGDIA004E Invalid prefix to namespace URI mapping on line ' <i>line number</i> '.	222
CTGDIA005E An error occurred while processing the XML Schema file ' <i>file name</i> ': <i>exception</i>	222
CTGDIA006E There is no feature representing the XML element or attribute with name ' <i>attribute name</i> '.	222
CTGDIA007E There are siblings from the same namespace with case-insensitive equality in names: ' <i>feature name</i> '.	223
CTGDIA008E There are siblings from different namespaces with case-insensitive equality in names, and the names are not namespace prefixed: ' <i>feature name</i> '.	223
CTGDIA009E The ' <i>feature name</i> ' XML element or attribute is invalid according to the XML Schema.	223
CTGDIA010E The Entry Attribute ' <i>attribute name</i> ' specifies an XML element or attribute with ancestor ' <i>feature name</i> ' that has a sibling with the same name.	223
CTGDIA011E The XML Schema does not define a root element.	224
CTGDIA012I The XML Schema has been successfully parsed and an Ecore model has been created.	224

CTGDIA013I The Entry Attributes have been successfully applied to the data structure.	224
CTGDIA014I The parameter ' <i>parameter name</i> ' initialized with a value of ' <i>parameter value</i> '.	224
CTGDIA015E An error occurred while processing the XML Schema file ' <i>file name</i> ': ' <i>diagnostic message</i> '.	224
CTGDIA016E An error occurred while processing the XML Schema file ' <i>file name</i> '.	225
CTGDIA017E An error occurred while processing the XML Schema file ' <i>file name</i> ': <i>exception</i>	225
CTGDIA018I The XML that results from conversion from the DOM Element to XML is: <i>xml data</i>	225
CTGDIA019E Invalid value encountered in attribute ' <i>attribute name</i> ' ' <i>attribute value</i> '.	225
CTGDIB001E The perform method of the Function Component was not passed an object of type com.ibm.di.entry.Entry. This object is not a valid parameter to pass to perform method.	226
CTGDIB002E The Entry Attribute ' <i>attribute name</i> ' is not present in the Entry.	226
CTGDIB003E Error occurred while processing the XML document: <i>exception</i>	226
CTGDIB004E The required Function Component parameter ' <i>parameter name</i> ' is not set.	226
CTGDIB005E Invalid prefix to namespace URI mapping on line ' <i>line number</i> '.	227
CTGDIB006E An error occurred while processing the XML Schema file ' <i>file name</i> ': <i>exception</i>	227
CTGDIB007E There are siblings from the same namespace with case-insensitive equality in names: ' <i>feature name</i> '.	227
CTGDIB008E There are siblings from different namespaces with case-insensitive equality in names, and the names are not namespace prefixed: ' <i>feature name</i> '.	227
CTGDIB009I The parameter ' <i>parameter name</i> ' initialized with a value of ' <i>parameter value</i> '.	227
CTGDIB010I The XML parsing has been completed. Data Objects have been successfully created.	228
CTGDIB011I The Entry Attributes have been successfully created.	228
CTGDIB012I The XML Schema has been successfully parsed and an Ecore model has been created.	228
CTGDIB013I The Ecore model has been successfully checked for conformity.	228
CTGDIB014E An error occurred while processing the XML Schema file ' <i>file name</i> ': ' <i>diagnostic message</i> '.	229

CTGDIB015E An error occurred while processing the XML Schema file ' <i>file name</i> '.	229	CTGDIT069E Copying ' <i>from file</i> ' to ' <i>to file</i> ' failed.	234
CTGDIB016E An error occurred while processing the XML Schema file ' <i>file name</i> ': ' <i>diagnostic message</i> '.	229	CTGDIT070E Moving ' <i>from file</i> ' to ' <i>to file</i> ' failed.	235
CTGDIB017E The Entry Attribute ' <i>attribute name</i> ' is not present in the Entry.	229	CTGDIT071E Boolean attributes expect values true or false.	235
CTGDIB018I The XML resulting from the conversion from DOM Element is: <i>xml data</i>	229	CTGDJZ801I The parameter <i>param name</i> was initialized with the value: ' <i>value</i> '.	235
CTGDIT001E The ' <i>filePath</i> ' parameter must be set to use the File Connector.	230	CTGDJZ802E Parameter ' <i>param name</i> ' is not provided.	235
CTGDIT002I File Connector waiting for data. On attempt ' <i>attempt count</i> ' and will timeout after attempt ' <i>maximum number of attempts</i> '.	230	CTGDJZ803I File Transfer Function Component will work FTP file transfer mode set to: ' <i>value</i> '.	235
CTGDIT003E The ' <i>filePath</i> ' parameter must be set to use the File Connector to a open file for reading.	230	CTGDJZ804I File Transfer Function Component will work 'Convert source file to character set of target system' option set to: ' <i>value</i> '.	236
CTGDIT004E The ' <i>filePath</i> ' parameter must be set to use the File Connector to a open file for writing.	230	CTGDJZ805I File Transfer Function Component will work 'Enable SSL for AS400 connection' option set to: ' <i>value</i> '.	236
CTGDIT008E File Connector timed out while waiting for lock on file.	231	CTGDJZ806I File Transfer Function Component will use ' <i>value</i> ' for AS400 connections.	236
CTGDIT010I Open input: <i>path</i>	231	CTGDJZ807I The parameter <i>param name</i> is not specified. Default connection protocol ' <i>value</i> ' will be used.	236
CTGDIT011I Open output: <i>path</i>	231	CTGDJZ808I The value of Source parameter <i>param name</i> is set with the value: ' <i>value</i> '.	236
CTGDIT051E The starting directory path is not specified.	231	CTGDJZ809I The value of Target parameter <i>param name</i> is set with the value: ' <i>value</i> '.	237
CTGDIT052E The depth parameter can not be negative.	231	CTGDJZ810I The direction of the file transfer is: ' <i>value</i> '.	237
CTGDIT053E The glob pattern ' <i>glob pattern</i> ' is invalid.	231	CTGDJZ811E Unable to determine the direction of the file transfer.	237
CTGDIT054I No permission to read ' <i>directory</i> ' directory.	232	CTGDJZ812I File Transfer Function Component is establishing connection to the host: ' <i>value</i> '.	237
CTGDIT055I ' <i>file</i> ' does not exist.	232	CTGDJZ813I File Transfer Function Component has successfully established a connection to the host: ' <i>value</i> '.	238
CTGDIT056I Full Path ' <i>full path</i> ' criteria is used. Connector will skip Lookup and use the specified file or directory directly.	232	CTGDJZ814E File Transfer Function Component could not establish a connection to the host: ' <i>value</i> '.	238
CTGDIT057I Read only file ' <i>file</i> ' is deleted.	232	CTGDJZ815E File Transfer Function Component could not establish a connection to the target machine.	238
CTGDIT058E File ' <i>file</i> ' is read-only.	232	CTGDJZ816E Parameter ' <i>param name</i> ' is not provided.	238
CTGDIT059I Non-empty directory ' <i>directory</i> ' is deleted.	233	CTGDJZ817E File Transfer Function Component accepts only a IBM Security Directory Integrator Entry as input.	238
CTGDIT060E Directory ' <i>directory</i> ' is not empty.	233	CTGDJZ818I The value of configuration parameter ' <i>param</i> ' set in configuration GUI has been overridden to ' <i>value</i> '.	239
CTGDIT061E Deleting ' <i>file</i> ' failed.	233	CTGDJZ819E An invalid connection type has been specified. The valid values for the ' <i>connectionType</i> ' parameter are: 'RSH', 'SSH', 'REXEC', 'AS400', 'WIN' and 'FTP'.	239
CTGDIT062E ' <i>file</i> ' is not a directory.	233		
CTGDIT063E The name of the file or directory is not specified. At least the ' <i>fullPath</i> ' or ' <i>name</i> ' attribute must be provided in the Output Map.	233		
CTGDIT064E ' <i>file</i> ' already exists.	234		
CTGDIT065E Directory ' <i>directory</i> ' could not be created.	234		
CTGDIT066E File ' <i>file</i> ' could not be created.	234		
CTGDIT067E ' <i>file</i> ' could not be made Read-Only.	234		
CTGDIT068E Dates must use format: <i>date format</i>	234		

CTGDJZ820E Not all parameters have been provided. Ensure you have provided a hostname and username. For an REXEC, FTP and Windows connection you will also need to provide a password. For an SSH connection you have the option of providing a password OR a keystore (with associated passphrase if applicable). 239

CTGDJZ821E Parameter '*param name*' is not provided. 240

CTGDJZ822E Unable to delete temporary file '*param name*'. 240

CTGDJZ823E Target file path '*param name*' is same as Source file path, unable to transfer file. 240

CTGDJZ824E Source file path '*param name*' not found. 240

CTGDJZ825E Target file '*param name*' might be in use or read-only or target path does not exist. 240

CTGDJZ826E File Transfer Function Component could not establish a connection to the target machine using given parameters in Configuration Editor. File Transfer Function Component will continue, if any attribute mapping provided in runtime. . . 241

CTGDJZ827E Specified target directory '*param name*' does not exist. 241

CTGDJZ828E Unable to create specified target directory '*param name*'. 241

CTGDJY101I Parser set padding character to '*character*'. 241

CTGDIP001I Connector terminating: '*Connector name*'. 241

CTGDIP002W Exception encountered while closing socket connection to ftp server: '*error*'. 242

CTGDIP003I Opening connection to FTP Server: '*hostname*'. 242

CTGDIP004I Logging onto FTP server with user ID '*user ID*'. 242

CTGDIP005I Using FTP operation '*operation*' at server location '*location*'. 242

CTGDIP006E The '*ftpHost*' parameter must be set to use the FTP Client Connector. . . . 242

CTGDKK101E The '*configFile*' parameter must be set to use the GLA Connector. . . . 243

CTGDKK102E The adapter configuration file is not valid: *exception message*. 243

CTGDKK103I The adapter configuration file is validated. 243

CTGDKK104I The adapter configuration file is started. 243

CTGDKK105E The execution of the adapter configuration file failed: *Exception message* 243

CTGDKK106E There is no registered GLAConnector matching the specified in the TDIOutputter '*tdi_correlation_id*' parameter: *Correlation ID*. 244

CTGDKK107E There are more than one configured TDIOutputters in the adapter configuration file. 244

CTGDKK108E An exception occurred while converting the XML file to Document object: *exception message* 244

CTGDKK109E The given adapter configuration file does not have a configured TDIOutputter. 244

CTGDJP201I Finding entries with URL set to *URL*. 244

CTGDJP202E Unable to send request to HTTP Server because an invalid protocol *protocol* was specified in the URL. 245

CTGDJP203I Connected to *URL*. 245

CTGDJP204I Constructing filtered entry for Parser *Parser name* to generate http.body contents. 245

CTGDJP205I Setting attribute *attribute name*. 245

CTGDJP206E Exception occurred while writing HTTP body to file: *error* 245

CTGDJP207I Using persistent connection for *url*. 246

CTGDJP208I Connecting through *proxy* to *host*. 246

CTGDJP209I Failed to connect through *proxy* to *host* with the response, *response*. . . . 246

CTGDJP210I Unable to parse the proxy host *proxy*. 246

CTGDJP401I HTTP Parser will use the input reader. 246

CTGDJP402I HTTP Parser will read a line from the input stream using character set '*character set*'. 247

CTGDJP403I HTTP Parser starting to reading line. 247

CTGDJP404I HTTP Parser read in character '*integer value*' which has an ascii character value of '*character*'. 247

CTGDJP405I HTTP Parser will read an entry using the character set '*character set*'. . 247

CTGDJP406I HTTP Parser read in the following line: '*line*'. 248

CTGDJP407I HTTP Parser will write entry with client mode of '*boolean*'. 248

CTGDJP408E Unable to write entry because no URL was provided for the client mode in the HTTP Parser. 248

CTGDJP409I HTTP Parser entry begin writtent redirect to '*redirect info*'. 248

CTGDJP410I HTTP Parser entry being written has status set to '*status*'. 248

CTGDJP411I HTTP Parser entry being written has header set to '*header*'. 249

CTGDJP412I Unsafe output conversion. . . . 249

CTGDJP413I HTTP Parser reading HTTP body: Body length=*length*, Input stream=*stream information*, Reader=*reader information*. . . 249

CTGDJP414I Only a Reader available. This might cause problems when reading a multi-byte character set.	249	CTGDJP313I Sending termination request to server Connector.	255
CTGDJP415E No input stream/reader available.	250	CTGDJP314I Client connection closed.	255
CTGDJP416I HTTP Parser successfully read the HTTP body.	250	CTGDJP315E Unable to get the next Entry. A SocketException occurred: <i>exception</i>	256
CTGDJP417I 'http.Transfer-Encoding' parameter: <i>parameter value</i>	250	CTGDJP316E Connection closed by client.	256
CTGDJP418I Disable charset conversion since Reader object used to read data.	250	CTGDJP317I Reject Client Authentication.	256
CTGDJP419I Content type charset: <i>character set</i>	250	CTGDJP318I Constructing filtered entry for Parser <i>Parser name</i> to generate http.body contents.	256
CTGDJP420I Chunk size line: <i>size</i>	251	CTGDJP319I Setting attribute <i>attribute name</i>	256
CTGDJP421I Chunk size is: <i>size</i>	251	CTGDJP320I Authenticate user: <i>user name</i>	257
CTGDJP422I Authentication information from the Entry: http.remote_user= <i>username</i> , http.remote_pass= <i>password</i>	251	CTGDJP321E Unable to authenticate Connector. Exception occurred: <i>exception</i>	257
CTGDJP423I Trying to decode the URL: <i>URL</i>	251	CTGDJP322E Authentication failed. Client could not authenticate 3 times. Exiting	257
CTGDJP424I Skipping token: <i>token name</i>	251	CTGDJP323I Authentication successful.	257
CTGDJP425I Parsing HTTP URL to retrieve the credentials. Pure HTTP URL has been stripped off of its prefix and suffix, but still contains credential information: <i>pure HTTP URL</i>	252	CTGDJP324E Username or Password not provided. Client could not authenticate 3 times. Exiting	258
CTGDJP426I Authentication information: username: <i>username</i> , password: <i>password</i>	252	CTGDJP325I Username: <i>username</i>	258
CTGDJP427I Authorization result: <i>authorization string</i>	252	CTGDJP326E No HTTP request available from client.	258
CTGDJP428I Chunk part is: buffer length= <i>length</i> , size= <i>size</i>	252	CTGDJP327E Authentication exception: <i>exception</i>	258
CTGDJP429I HTTP Parser found no content type and will default it to <i>content type</i>	252	CTGDJP328I SSL exception occurred. The only action to be taken is to ignore this exception.	258
CTGDJP430I HTTP body for the HTTP Parser: <i>HTTP body</i>	253	CTGDJP329I NoSuchElementException occurred. The only action to be taken is to ignore this exception.	259
CTGDJP431I Parsed HTTP header: <i>HTTP header</i>	253	CTGDKG001I Usage: IDILoader java-class [params]	259
CTGDJP301I Exiting initialization early because Connector already initialized with a java.net.Socket object.	253	CTGDKG002E The IDILoader cannot locate installation directory.	259
CTGDJP302I Using provided java.net.Socket object for HTTP client session.	253	CTGDKG003I Jars Directory: <i>directory</i>	259
CTGDJP303E Unable to load authenticator Connector <i>Connector name</i> . Exception occurred: <i>exception</i>	253	CTGDKG004I addFiles: <i>path</i>	259
CTGDJP304I Listening for HTTP SSL connections on port: <i>port number</i>	254	CTGDKG005I The directory path specified does not exist: <i>path</i>	260
CTGDJP305I Listening for HTTP connections on port: <i>port number</i>	254	CTGDKG006I The file is not a jar or zip file: <i>path</i>	260
CTGDJP306E Server Socket is not open, cannot accept client requests.	254	CTGDKG007I No files found in the path: <i>path</i>	260
CTGDJP307I Connector terminated by external request.	254	CTGDKG008I Adding files to the jar files list: <i>path</i>	260
CTGDJP309I Terminate server request received.	254	CTGDKG009I addPackages: <i>path</i>	260
CTGDJP310I Creating dummy connection using IP Address ' <i>IP Address</i> ' and port ' <i>port number</i> '.	255	CTGDKG010I The directory path specified does not exist: <i>path</i>	261
CTGDJP311W IOException on unblocking Connector server socket: <i>exception</i>	255	CTGDKG011I No files found in the path: <i>path</i>	261
CTGDJP312I Server is already terminating.	255	CTGDKG012I Adding files to the packages list: <i>path</i>	261
		CTGDKG019I cacheJarContents: <i>path</i> . Exception occurred: <i>exception</i>	261
		CTGDKG020I Load initial class: <i>class name</i>	261
		CTGDKG021I Get main method: <i>class name</i>	262
		CTGDKG022I Invoke main method: <i>class name</i>	262

CTGDKG023E Error while starting main class.	262	CTGDJR007W Thread interrupted: <i>exception</i>	268
CTGDKG024I findResource: <i>resource name</i>	262	CTGDJR008I Timeout waiting for next changed entry.	268
CTGDKG029I URL: <i>URL</i>	262	CTGDJR009I LDAP search query set to ' <i>filter</i> '.	268
CTGDKG030I The resource <i>resource name</i> was not found by the IDILoader. Try the parent Loader.	263	CTGDJR010I Getting the next changelog entry: <i>CN</i>	269
CTGDKG031I Searching for the library <i>library name</i> in directory <i>directory</i>	263	CTGDJR011I Got next changelog entry: <i>CN</i>	269
CTGDKG032I The library <i>library name</i> was found in the file <i>file</i>	263	CTGDJR012I Entry not found in Changelog: <i>CN</i>	269
CTGDKG037I Looking for tdi.xml or idi.inf in <i>path</i>	263	CTGDJR013I Skipping and trying next changelog entry: <i>change number</i>	269
CTGDKG038I Found <i>file name</i> in <i>path</i>	263	CTGDJR014E Unable to get next search result. PartialResultException occurred: <i>exception</i>	269
CTGDKG039I An exception occurred while reading <i>path</i> : <i>exception</i>	264	CTGDJR015I Get next page: <i>filter</i>	270
CTGDJZ651E Attribute <i>attribute</i> does not accept value ' <i>value</i> '.	264	CTGDJR016E The entry does not contain a valid changelog entry (changes attribute missing) for operation: <i>operation type</i>	270
CTGDJZ652E The IdML book is opened in REFRESH mode and supports only CREATE operations.	264	CTGDJR017E LDIF Parser could not parse ' <i>changes</i> ' attribute from the entry.	270
CTGDJZ653E No class type specified in the configuration of the IdML Ci and Relationship Connector.	264	CTGDJR018I The attributes does not contain ' <i>lastchangenumber</i> ' attribute.	270
CTGDJZ654I IdML Ci and Relationship Connector will work with book: <i>book name</i>	265	CTGDJR019E Could not retrieve the last change number.	270
CTGDJZ655I The parameter <i>param name</i> was initialized with the value: ' <i>value</i> '.	265	CTGDJR020E Could not store the change number value in the System Store. Exception occurred: <i>exception</i>	271
CTGDJZ656I The name of the currently used book ' <i>book name</i> ' has been overridden to ' <i>new name</i> '.	265	CTGDJR021I The current change number value is: <i>change number</i>	271
CTGDJZ657I Use an IT registry for the needed meta-data: ' <i>use it registry</i> '.	265	CTGDJR022I A NamingExceptionEvent occurred: <i>event</i>	271
CTGDJZ658I The book ' <i>book name</i> ' does not exist or is already closed.	265	CTGDJR023I A notification event was received: <i>event</i>	271
CTGDJZ659E Parameter ' <i>param name</i> ' is not provided.	266	CTGDJR024E Restart info does not contain ' <i>changeNumber</i> ' attribute.	271
CTGDJZ751E Error parsing XML. An invalid input IdML XML is passed to the parser.	266	CTGDJR025W Exception occurred while terminating the Connector: <i>exception</i>	272
CTGDJZ752I Reading entry where parent node is ' <i>node name</i> ' and the current node is ' <i>node name</i> '.	266	CTGDJR026W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used.	272
CTGDJZ754I <i>indent</i> Node Name: <i>node name</i>	266	CTGDJZ401E An Exception occurred when using the Naming and Reconciliation Service API.	272
CTGDJZ755I <i>indent</i> Node Value: <i>node value</i>	266	CTGDJZ402E An Exception occurred during a database operation when using Naming and Reconciliation Service API.	272
CTGDJR001W The ' <i>pageSize</i> ' parameter set to an invalid value ' <i>parameter value</i> '. Will not use paging.	267	CTGDJZ403I The parameter <i>param name</i> was initialized with the value: ' <i>value</i> '.	272
CTGDJR002W The ' <i>pageSize</i> ' parameter set to a negative value ' <i>parameter value</i> '. Will not use paging.	267	CTGDJZ404I Init IT registry Function Component will work with book: ' <i>book name</i> '.	273
CTGDJR003E Unable to initialize Connector because a connection to the directory server could not be established or the search at base DN <i>DN</i> was not valid.	267	CTGDJZ405I Init IT registry Function Component will work with Refresh set to: ' <i>value</i> '.	273
CTGDJR004W Cannot set starting change number to ' <i>change number</i> '.	267	CTGDJZ406I The Common Data Model version of the registered MSS will be ' <i>cdm version</i> '.	273
CTGDJR005I Starting with change number set to ' <i>change number</i> ' and the ' <i>iteratorStateKey</i> ' was set to ' <i>state value</i> '.	268	CTGDJZ407E Parameter ' <i>param name</i> ' is not provided.	273
CTGDJR006I Block for notifications	268	CTGDJZ408I Use an IT registry system for the needed meta-data: ' <i>use it registry</i> '.	274

CTGDJZ409E Init IT registry Function Component accepts only a IBM Security Directory Integrator Entry as input.	274	CTGDIZ421I Web service is one way: <i>boolean</i>	280
CTGDJZ410E The Common Data Model version specified ' <i>param name</i> ' is not a valid Common Data Model version.	274	CTGDIZ422E The SOAP request message is not initialized.	280
CTGDJZ411I The MSS's <i>param name</i> has value: ' <i>value</i> '.	274	CTGDIZ423E Invalid object recieved: <i>object</i>	280
CTGDJZ412E Either MSS Name or Manufacturer Name, Hostname and Product Name are not set in output map of FC.	274	CTGDIR301I Password not specified. Will use empty string value for password.	280
CTGDJZ413E The Common Data Model version is not set in configuration panel of FC.	275	CTGDIR302E Required parameter is missing: <i>parameter name</i>	280
CTGDJZ414I The name of the currently used book ' <i>book name</i> ' has been overridden to ' <i>new name</i> '.	275	CTGDIR303I The selectEntries method will perform Agent search with filter: <i>filter</i>	281
CTGDJZ415E JDBC parameter ' <i>param name</i> ' is not set in Configuration panel of FC and can not be read from the IT registry's properties file.	275	CTGDIR304I The selectEntries method's search returned at least one Entry.	281
CTGDJZ416I Init IT registry Function Component has already opened book ' <i>book name</i> '.	275	CTGDIR305I No Entries returned by search in the selectEntries method.	281
CTGDJZ417E The book ' <i>book name</i> ' is opened and currently used.	276	CTGDIR306I The getNextEntry method has no more Entries to return.	281
CTGDIZ401I There was no SOAP response header.	276	CTGDIR307E The putEntry method could not add new Entry. Exception occurred: <i>exception</i>	282
CTGDIZ402E Parameter ' <i>wsdlUrl</i> ' is empty.	276	CTGDIR308E Unable to add Entry. The naming attribute \$dn was not specified in Entry.	282
CTGDIZ403I Parameter ' <i>wsdlUrl</i> ': <i>parameter value</i>	276	CTGDIR309E Unable to modify the Entry because the Entry to modify was not found.	282
CTGDIZ404E Parameter ' <i>soapOperation</i> ' is empty.	276	CTGDIR310E The modEntry was unable to modify the Entry because the <i>aOldEntry</i> parameter passed in was null.	282
CTGDIZ405I Parameter ' <i>soapOperation</i> ': <i>parameter value</i>	277	CTGDIR311I No distinguished name was given to the modEntry method. Will use the existing one.	282
CTGDIZ406I Parameter ' <i>providerUrl</i> ': <i>parameter value</i>	277	CTGDIR312E Unable to modify entry. The entry is missing the naming attribute.	283
CTGDIZ407I Parameter ' <i>returnXMLType</i> ': <i>parameter value</i>	277	CTGDIR313I Rename entry from <i>old DN</i> to <i>DN</i>	283
CTGDIZ408E Invalid value for ' <i>returnXMLType</i> ': <i>parameter value</i>	277	CTGDIR314I Ignoring attribute <i>attribute ID</i> . It is empty and does not exist in the current Entry.	283
CTGDIZ409I Parameter ' <i>inputType</i> ': <i>parameter value</i>	277	CTGDIR315I No modification items for entry: <i>DN</i>	283
CTGDIZ410E Invalid value for ' <i>inputType</i> ': <i>parameter value</i>	278	CTGDIR316E The entry will not be modified. There are no modification items.	283
CTGDIZ411I SOAP request Attribute: <i>mInputAttr</i>	278	CTGDIR317E Unable to modify entry. Exception occurred while building ModificationItems object: <i>exception</i>	284
CTGDIZ412I SOAP response Attribute: <i>attribute</i>	278	CTGDIR318E Deletion of multiple entries not yet supported by the deleteEntry method.	284
CTGDIZ413E Entry Attribute ' <i>attribute</i> ' is missing.	278	CTGDIR319E The deleteEntry method was called with no \$dn attribute in the Entry.	284
CTGDIZ414I About to call web service at <i>provider URL</i> using:	278	CTGDIR320I Searching for Entry with \$dn equal to <i>DN</i>	284
CTGDIZ415I SOAP Action: <i>SOAP action</i>	278	CTGDIR321I Search for <i>DN</i> did not return any entries.	284
CTGDIZ416I SOAP request: <i>SOAP request</i>	279	CTGDIR322I The findEntry method found the Entry: <i>entry</i>	285
CTGDIZ417I Called successfully web service at <i>provider URL</i>	279	CTGDIR323I The findEntry method could not add found entry: <i>entry</i>	285
CTGDIZ418I SOAP response: <i>SOAP response</i>	279	CTGDIR324I NULL entry returned by findEntry method.	285
CTGDIZ419I SOAP response header: <i>SOAP response header</i>	279	CTGDIR325E Could not find a JNDI Entry with the given search criteria: <i>exception</i>	285
CTGDIZ420I SOAP response body: <i>SOAP response body</i>	279	CTGDIR326E Could not find a JNDI Entry with the given search criteria: <i>exception</i>	285

CTGDIR327I The findEntry method search using the filter *filter* on the base DN *DN*. 286

CTGDIR328I Search for Entries using the filter *filter* did not return any entries. 286

CTGDIR329I The findEntry method found the Entry: *entry*. 286

CTGDIR330I The findEntry method could not add found entry: *entry*. 286

CTGDIR331I NULL entry returned by findEntry method. 286

CTGDIR332E Could not find a JNDI Entry with the given search criteria: *exception* 287

CTGDIR333E Could not find a JNDI Entry with the given search criteria: *exception* 287

CTGDIR334I addDNFromCriteria: Vector instance. 287

CTGDIR335I addDNFromCriteria: SearchCriteria instance. 287

CTGDIR336I The addDNFromCriteria method was passed an SearchCriteria.rscSearch instance object. 287

CTGDIR337E Cannot mix \$dn matching with other attributes in a search. 288

CTGDIR338I The addDNFromCriteria method will add DN value to list: *search filter*. 288

CTGDIR339E Unknown object type in search filter: *class name: search filter*. 288

CTGDIR340W Exception occurred while trying to terminate: *exception* 288

CTGDJZ451E Attribute *attribute* does not accept value '*value*'. 288

CTGDJZ452E An IT registry book opened in REFRESH mode supports only CREATE operations. 289

CTGDJZ453E No class type specified in the configuration of the IT registry Ci and Relationship Connector. 289

CTGDJZ454I IT registry Ci and Relationship Connector will work with book: *book name*. 289

CTGDJZ455I The parameter *param name* was initialized with the value: '*value*'. 289

CTGDJZ456I The name of the currently used book '*book name*' has been overridden to '*new name*'. 290

CTGDJZ457I Use an IT registry system for the needed meta-data: '*use it registry*'. 290

CTGDJZ458I The book '*book name*' does not exist or is already closed. 290

CTGDJZ459E Parameter '*param name*' is not provided. 290

CTGDJZ460E Relationship '*relationship name*' cannot be updated. 290

CTGDJZ461E Lookup Criteria '*criterion*' is not supported. 291

CTGDJZ462E Filter Criteria '*criterion*' is not valid 291

CTGDJZ463E An exception occurred while trying to close the database connection: *exception message* 291

CTGDJZ464E Configuration Item '*ci name*' cannot be updated. 291

CTGDJZ465E Incorrect GUID value passed to attribute '*guid attr*'. 291

CTGDJZ466I All IT registry items will be queried. 292

CTGDJZ468E Relationship '*relationship name*' cannot be fetched as '*isDeleted*' is set. 292

CTGDJJ001E The '*method*' parameter must be set to use the Java Class FC. 292

CTGDJJ002E The '*javaClass*' parameter must be set to use the Java Class FC. 292

CTGDJJ003E Unable to locate the method '*method name*' in class '*class name*'. 292

CTGDJJ004E Unable to locate the method '*method name*' in class '*class name*'. 293

CTGDJJ005E Function Component could not perform the configured method because it expected an Entry object but encountered an object of another type. 293

CTGDJJ006E Function Component failed to convert the object '*object type*' to a Date object. Exception occurred: *exception* 293

CTGDJJ007E Function Component could not convert the object '*object type*' with the name '*object name*' to class '*class name*' because the class type was not recognized. 293

CTGDIJ001E No default JDBC driver. The '*jdbcDriver*' parameter must be set. 294

CTGDIJ002W An exception occurred while trying to disable autocommit mode in the database. The database does not allow autocommits to be disabled. Autocommit will always occur on the database itself. 294

CTGDIJ003I Successfully built an entry. 294

CTGDIJ004W Unable to set the commit mode specified in the '*jdbcCommit*' parameter with a value of '*commit mode*'. 294

CTGDIJ005W Unable to obtain schema information from the database. The following exception was encountered: *error*. 295

CTGDIJ006I Executing query to catch the metadata: *meta query* 295

CTGDIJ007I JDBC provider parameter being parsed with the following value: '*parameter*'. 295

CTGDIJ008W JDBC provider parameter was encountered with no colon separator in line and will be skipped: '*parameter*'. 295

CTGDIJ009I JDBC provider parameter successfully parsed. The parameter name is '*parameter*' and the value is '*value*'. 295

CTGDIJ010I Executing a ALTER SESSION SQL statement: *SQL statement*. 296

CTGDIJ011I Executing a SELECT SQL statement to retrieve entries: *SQL statement*. 296

CTGDIJ012E Cannot execute SQL Statement: *SQL statement*. 296

CTGDIJ013I JDBC/ODBC Source Columns. 296

CTGDIJ014I Committing the SELECT statement issued. 296

CTGDIJ015I Entries has been selected. 297

CTGDIJ016I No more entries to retrieve from SQL search results.	297	CTGDIJ042E Cannot build where clause (initial string match).	302
CTGDIJ017I Preparing and executing the query SQL statement to find an entry: <i>SQL statement</i>	297	CTGDIJ043E Cannot build where clause (final string match).	302
CTGDIJ018W Prepared SQL statement to find entry failed: <i>exception</i>	297	CTGDIJ044I Prepared SQL statement: <i>SQL statement</i>	303
CTGDIJ019I Executing query SQL statement to find entry: <i>SQL statement</i>	298	CTGDIJ045I Preparing to set prepared SQL statement value using attribute name ' <i>attribute name</i> ' and attribute value ' <i>attribute value</i> '. The index is set at ' <i>index</i> '.	303
CTGDIJ020W No attributes found in the entry to modify.	298	CTGDIJ046E No MetaData description for attribute being set in the prepared SQL statement: ' <i>attribute name</i> '.	303
CTGDIJ021E No attributes specified to modify.	298	CTGDIJ047I Set prepared SQL statement value for attribute to null at index apos;' <i>index</i> '.	303
CTGDIJ022I Set update attribute in prepared SQL statement: <i>attribute name</i>	298	CTGDIJ048I Java Class name of attribute value: ' <i>class name</i> '.	303
CTGDIJ023W The prepared SQL statement to modify the entry will not be used. Exception occurred: <i>exception</i>	298	CTGDIJ049I Type of attribute value: ' <i>attribute type</i> '.	304
CTGDIJ024I Executing update SQL statement modify an entry: <i>SQL statement</i>	299	CTGDIJ050I Set 'LONGVARCHAR' value: ' <i>value</i> '.	304
CTGDIJ025I Update SQL statement to modify an entry returned ' <i>return value</i> '.	299	CTGDIJ051I Set 'VARCHAR' value: ' <i>value</i> '.	304
CTGDIJ026W The prepared SQL statement to add an entry will not be used. Exception occurred: <i>exception</i>	299	CTGDIJ052I Set 'CHAR' value: ' <i>value</i> '.	304
CTGDIJ027I Executing update SQL statement to add an entry: <i>SQL statement</i>	299	CTGDIJ053I 'CHAR' value found but has a different size from the column. The column size is ' <i>column size</i> ' and the value length is ' <i>value length</i> '. The Connector will attempt to pad or trim the value.	304
CTGDIJ028I Update SQL statement to add an entry returned ' <i>return value</i> '.	299	CTGDIJ054I Unable to pad or trim 'CHAR' value. The column size is ' <i>column size</i> ' and the value length is ' <i>value length</i> '.	305
CTGDIJ029I Executing update SQL statement to delete an entry: <i>SQL statement</i>	300	CTGDIJ055I Successfully padded or trimmed the 'CHAR' value: ' <i>value</i> '.	305
CTGDIJ030I Update SQL statement to delete an entry returned ' <i>return value</i> '.	300	CTGDIJ056I Set 'OTHER' value: ' <i>value</i> '.	305
CTGDIJ031W Exception caught in getNextSQLSelectEntry method while building an Entry: <i>exception</i>	300	CTGDIJ057I Set 'INTEGER/TINYINT/SMALLINT' value: ' <i>value</i> '.	305
CTGDIJ032E No metadata available for the specified table: ' <i>table name</i> '.	300	CTGDIJ058W Exception caught while parsing Integer from 'INTEGER/TINYINT/SMALLINT' value: <i>exception</i>	306
CTGDIJ033E The jdbc table name was not specified.	300	CTGDIJ059I Set 'DECIMAL/BIGINT/NUMERIC' value: ' <i>value</i> '.	306
CTGDIJ034E Null ResultSet is received when retrieving metadata of the table.	301	CTGDIJ060W Exception caught while parsing Double from 'DECIMAL/BIGINT/NUMERIC' value: ' <i>exception</i> '.	306
CTGDIJ035I ResultSet object was received successful when retrieving metadata of the table. Message: <i>message</i>	301	CTGDIJ061I Set 'FLOAT' value: ' <i>value</i> '.	306
CTGDIJ036I Metadata was received successful. The metadata contained <i>number of elements</i> elements.	301	CTGDIJ062I Set 'REAL/DOUBLE' value: ' <i>value</i> '.	306
CTGDIJ037E The table or view specified (<i>tablename</i>) was not found, or not accessible.	301	CTGDIJ063I Set 'BIT' value: ' <i>value</i> '.	307
CTGDIJ038W Cannot build where clause (Advanced Link Mode).	301	CTGDIJ064I Set 'DATE/TIME/TIMESTAMP' value: ' <i>class name</i> ', ' <i>value</i> '.	307
CTGDIJ039E Cannot build where clause because the link criteria list is empty.	302	CTGDIJ065I Set 'java.sql.Timestamp' value: ' <i>value</i> '.	307
CTGDIJ040E Cannot build where clause because an unknown criteria type was specified.	302	CTGDIJ066I Set 'java.sql.Date' value: ' <i>value</i> '.	307
CTGDIJ041E Cannot build where clause (substring match).	302	CTGDIJ067I Set 'java.sql.Time' value: ' <i>value</i> '.	307
		CTGDIJ068I Set 'java.util.Date' value: ' <i>value</i> '.	308

CTGDIJ069I Converting 'java.util.Date' to 'java.sql.Timestamp': ' <i>value</i> '	308
CTGDIJ070I Creating a timestamp value using the current time in the format specified in the 'jdbcDateFormat' parameter with the 'SimpleDateFormat' class: ' <i>date format</i> '	308
CTGDIJ071W Exception encountered using the 'SimpleDateFormat' class to create timestamp value: <i>exception</i>	308
CTGDIJ072I Creating a timestamp value using the current time with the 'DateFormat' class: ' <i>value</i> '	309
CTGDIJ073I Creating a timestamp value using the current time in the format 'yyyy.MM.dd hh:mm' with the 'SimpleDateFormat' class.	309
CTGDIJ074I Set timestamp value from 'SimpleDateFormat' class: ' <i>date</i> '	309
CTGDIJ075I Convert and set the timestamp value to a long value: ' <i>value</i> '	309
CTGDIJ076I Set 'LOB': <i>value</i>	309
CTGDIJ077I Set 'CLOB': <i>value</i>	310
CTGDIJ078I Set value for an unhandled type ' <i>type</i> ' as a string on column ' <i>column name</i> '	310
CTGDIJ079W SQL warning encountered from prepared SQL statement: <i>SQL statement</i>	310
CTGDIJ080I Attempting to build an entry.	310
CTGDIJ081I Retrieving attribute value based on the column name ' <i>column name</i> '	310
CTGDIJ082I Retrieved attribute of type 'CHAR/VARCHAR': ' <i>value</i> '	311
CTGDIJ083I Retrieved attribute of type 'OTHER': ' <i>value</i> '	311
CTGDIJ084I Retrieved attribute of type 'LONGVARIABLE'	311
CTGDIJ085I Retrieved attribute of type 'LONGVARCHAR'	311
CTGDIJ086I Retrieved attribute of type 'DECIMAL/INTEGER': ' <i>value</i> '	311
CTGDIJ087W When building Entry 'null' value has been received for INT: <i>value</i>	312
CTGDIJ088I Retrieved attribute of type 'NUMERIC': ' <i>value</i> '	312
CTGDIJ089W 'null' value has been received for NUMERIC while building Entry: <i>value</i>	312
CTGDIJ090I Retrieved attribute of type 'REAL/FLOAT/DOUBLE': ' <i>value</i> '	312
CTGDIJ091W 'null' value has been received for REAL/FLOAT/DOUBLE while building Entry: <i>value</i>	312
CTGDIJ092I Retrieved attribute of type 'DATE': ' <i>class name</i> '	313
CTGDIJ093W Retrieved attribute of type 'DATE': 'null'.	313
CTGDIJ094I Retrieved attribute of type 'TIME': ' <i>class name</i> '	313
CTGDIJ095W Retrieved attribute of type 'TIME': 'null'.	313
CTGDIJ096I Retrieved attribute of type 'TIMESTAMP': ' <i>class name</i> '	313

CTGDIJ097W Retrieved attribute of type 'TIMESTAMP': 'null'.	314
CTGDIJ098I Retrieved attribute of type 'VARIABLE': <i>class name</i>	314
CTGDIJ099I Retrieved attribute value of type 'VARIABLE': 'null'.	314
CTGDIJ100I Retrieved attribute value of type 'OBJECT': ' <i>class name</i> '.	314
CTGDIJ101I Set value of attribute ' <i>attribute name</i> ': ' <i>attribute value</i> '. The class type of the attribute is ' <i>class name</i> '.	315
CTGDIJ102I Set value of attribute ' <i>attribute name</i> ': ' <i>attribute value</i> '. The class type of the attribute is 'basic'.	315
CTGDIJ103I Set value of attribute ' <i>attribute name</i> ': 'null'.	315
CTGDIJ104W Exception encountered using the 'DateFormat' class to create a timestamp value: <i>exception</i>	315
CTGDIJ105W Exception encountered using the 'SimpleDateFormat' class to create a timestamp value: <i>exception</i>	316
CTGDIJ106W Unable to set 'DATE/TIME/TIMESTAMP' value: ' <i>class name</i> ', ' <i>value</i> '. Exception encountered trying to convert the timestamp value to a long: <i>exception</i>	316
CTGDIJ107I 'CHAR' value found but has a different size from the column. The column size is ' <i>column size</i> ' and the value length is ' <i>value length</i> '. The Connector will not pad or trim the value since the padding is disabled.	316
CTGDIJ108E The database 'Schema' name is not provided.	316
CTGDIJ109E Unable to connect to the database (<i>exception message</i>). Verify that all the database connection parameters are correctly specified.	317
CTGDIJ110E The database user 'Password' is not provided.	317
CTGDIJ111E An error occurred while trying to create sql statement.	317
CTGDIJ112E An exception occurred while trying to close the database connection: <i>exception message</i>	317
CTGDIJ113E An exception occurred while trying to clear warnings from connection object: <i>exception message</i>	317
CTGDIJ114E Unable to set 'BIT' value using attribute name: ' <i>attribute name</i> ' and attribute value ' <i>attribute value</i> '.	318
CTGDIJ115E Incorrect number of parameters in prepared SQL statement: <i>sql statement</i>	318
CTGDIJ116W Unable to get MetaData for PreparedStatement: <i>exception</i>	318
CTGDII001I The getNextEntry method received message of type <i>class name</i>	318
CTGDII002I Topic factory obtained from script.	318

CTGDII003I Topic obtained from script.	319	CTGDII038I Setting JMS reply to <i>value</i>	326
CTGDII004I JMS Topic Session Established.	319	CTGDII039I No message to acknowledge.	326
CTGDII005I Queue factory obtained from script.	319	CTGDII040I Using the configured Parser for this JMS Connector to generate a JMS text message.	326
CTGDII006I queueSession and sendSession are created.	319	CTGDII041I While generating JMS text message - using the value of the following Entry attribute for the contents of the JMS text message:	326
CTGDII007I readQueue initialized from script.	319	CTGDII042I While generating JMS bytes message - using the serialized Entry object as the contents of this JMS bytes message.	327
CTGDII008I sendQueue initialized from script.	320	CTGDII043I While generating JMS object message - using the Entry object as the contents of this JMS object message.	327
CTGDII009I readQueue created: <i>queue name</i>	320	CTGDII044I Parsing a JMS text message with the following contents:	327
CTGDII010I sendQueue created: <i>queue name</i>	320	CTGDII045I Using the configured Parser for this JMS Connector to parse this JMS text message into an Entry.	327
CTGDII011I JMS Queue Session Established.	320	CTGDII046I While parsing JMS text message - there is no configured Parser for this JMS Connector; storing the raw text data in the 'message' Entry attribute.	327
CTGDII012I queueConnection created.	320	CTGDII047I Deserializing JMS bytes message into Entry.	328
CTGDII013I Get topic connection factory from System Queue.	321	CTGDII048I Storing the raw bytes data of the JMS bytes message in the 'message' Entry attribute as a byte array.	328
CTGDII014I Get queue connection factory from System Queue.	321	CTGDII049I Successfully extracted Entry object from JMS bytes message.	328
CTGDII015I JMS load driver: <i>driver class name</i>	321	CTGDII050I Map certain properties.	328
CTGDII016I Map all JMS headers to/from attributes.	321	CTGDII051E No default JMS driver. The 'jms.driver' parameter must be set to use the JMS Connector.	328
CTGDII017I Map specific JMS headers to/from attributes.	321	CTGDII052E Unknown JMS Header: <i>JMS header</i>	329
CTGDII018I No specific mapping of JMS headers to/from attributes.	322	CTGDII053W Error while closing topic connection: <i>exception</i>	329
CTGDII019I Map all JMS properties to/from attributes.	322	CTGDII054W Error while closing queue connection: <i>exception</i>	329
CTGDII020I Map specific JMS properties to/from attributes.	322	CTGDII055W Unable to deserialize bytes message: <i>exception</i>	329
CTGDII021I Using backwards compatible mapping of all JMS properties to Entry properties.	322	CTGDII056I Interrupted while waiting for messages. Closing connection to server.	329
CTGDII022I Topic listener started.	322	CTGDKN601E <i>parameter name</i> JMS IBMMQ Driver parameter must be provided.	330
CTGDII023I Queue listener started.	323	CTGDKN602E Bad broker parameter for IBMMQ. Expecting host:port. Exception occurred: <i>exception</i>	330
CTGDII024I Lookup filter: <i>filter</i>	323	CTGDKN603E <i>parameter name</i> JMS IBMMQe Driver parameter must be provided	330
CTGDII025I Lookup will remove JMS messages found.	323	CTGDKN604E MQe does not support JMS Topics.	330
CTGDII026I No entries in QueueReceiver. Attempts to retrieve entries: <i>number of attempts</i>	323	CTGDKN605E Either the 'js.jsfile' or 'js.jsscript' parameter must be set to use the JMS Script Driver.	330
CTGDII027I Lookup will not remove JMS messages found.	323	CTGDKN606E Unable to read custom script from file: <i>file name</i>	331
CTGDII028I No entries in QueueBrowser: Attempts to retrieve entries: <i>number of attempts</i>	324	CTGDKN607E Unable to initialize ScriptEngine:	331
CTGDII029I Lookup mode not supported for Topic Connections.	324	CTGDKN608E Script error:	331
CTGDII030I Received a message of type <i>message type</i>	324		
CTGDII031I MQ format: ' <i>MQ format</i> '.	324		
CTGDII032I Perform backward compatible property mapping of all properties.	324		
CTGDII033I Map all properties.	325		
CTGDII034I Not set JMS property <i>property name</i> . The JMS property is either a JMS Header or does not start with 'jms.'.	325		
CTGDII035I Getting JMS header: <i>JMS header</i>	325		
CTGDII036I No attribute for JMS header: <i>JMS header</i>	325		
CTGDII037I Setting JMS header: <i>JMS header</i>	325		

CTGDKN609E Exception occurred in Script Driver initialization: <i>exception</i>	331	CTGDKN215E The required property ' <i>property name</i> ' is missing from the configuration file.	337
CTGDKN610E The JMS Driver is missing the required property ' <i>property name</i> '.	331	CTGDKN216I Exit requested.	337
CTGDKN611E Invalid numeric value for property ' <i>property name</i> ': <i>property value</i> '.	332	CTGDKN217I JMS connection closed.	337
CTGDKN612E The MQe JMS Driver could not open a port to receive notifications.	332	CTGDKN218I The password for user ' <i>user name</i> ' was successfully stored as changed.	337
CTGDKN613E Exception caught: <i>exception</i>	332	CTGDKN219I Successfully set port range 1414-1700.	338
CTGDKN614I Notification server terminated.	332	CTGDKN220I Unable to set port range, error: <i>error</i>	338
CTGDKN615I Received notification operation opcode: ' <i>operation code</i> '.	332	CTGDJK001E The ' <i>mode</i> ' parameter must be set to use the JMX Connector.	338
CTGDKN616I Connection accepted from <i>hostname</i> : <i>port number</i>	333	CTGDJK002E Invalid ' <i>mode</i> ' parameter set in the the JMX Connector: ' <i>parameter value</i> '.	338
CTGDKN617I Message transfer was triggered.	333	CTGDJK003E The ' <i>mBeanTypes</i> ' parameter must be set to use the JMX Connector.	338
CTGDKN618E Invalid notification operation code: ' <i>operation code</i> '.	333	CTGDJK004E The ' <i>url</i> ' parameter must be set to use the JMX Connector.	339
CTGDKN619I Message transfer was not triggered.	333	CTGDJK005E The MBean name ' <i>MBean name</i> ' provided does not match any of the registered MBeans.	339
CTGDKN620E <i>parameter name</i> JMS WebsphereESB Driver parameter must be provided.	333	CTGDJK006E A communication problem occurred when talking to the MBean server. Exception occurred: <i>exception</i>	339
CTGDKN621E Bad broker parameter for WebsphereESB. Expecting <i>host</i> : <i>port</i> : <i>sib_endpoint</i> . Exception occurred: <i>exception</i>	334	CTGDJK007E The MBean name ' <i>object name</i> ' provided does not match any of the registered MBeans.	339
CTGDKN201E Invalid values for the properties: ' <i>property name</i> ' and ' <i>property name</i> '. Only one of the properties can have a value of true.	334	CTGDJK008E A communication problem occurred when talking to the MBean server. Exception occurred: <i>exception</i>	339
CTGDKN202E An unexpected exception has been thrown.	334	CTGDJK009E The MBean name ' <i>object name</i> ' provided does not match any of the registered MBeans.	340
CTGDKN203I The remote JMS Provider could not be contacted at the moment: ' <i>exception</i> '. The password change will be rejected.	334	CTGDJK010E A communication problem occurred when talking to the MBean server. Exception occurred: <i>exception</i>	340
CTGDKN204I The password for user ' <i>user name</i> ' could not be stored as changed.	334	CTGDJK011E The listener object name ' <i>object name</i> ' is not registered in the MBean.	340
CTGDKN205I The password for user ' <i>user name</i> ' was successfully stored as added.	335	CTGDJK012I The listener object name ' <i>object name</i> ' has been successfully removed from a registered MBean.	340
CTGDKN206I The password for user ' <i>user name</i> ' could not be stored as added.	335	CTGDJK013I Notification received: Type: <i>type object</i> , Sequence number: <i>SequenceNumber</i>	341
CTGDKN207I The password for user ' <i>user name</i> ' was successfully stored as deleted.	335	CTGDIL001I Using LDAP SSL connection. Ensure that TCP port number is changed accordingly.	341
CTGDKN208I The password for user ' <i>user name</i> ' could not be stored as deleted.	335	CTGDIL002I Parsing next JNDI Provider Parameter: ' <i>JNDI Provider Parameter</i> '.	341
CTGDKN209I Loading JMS Driver: ' <i>driver name</i> '.	336	CTGDIL003E Bad JNDI Provider Parameter encountered: ' <i>JNDI Provider Parameter</i> '.	341
CTGDKN210I Could not configure JMS but the exception will be ignored: <i>exception</i>	336	CTGDIL004I Searching for entries from base DN ' <i>DN</i> ' using search filter ' <i>filter</i> '.	341
CTGDKN211I The linked exception is: <i>exception</i>	336	CTGDIL005I There are more entries that can be processed in the search results.	342
CTGDKN212I Connecting to the JMS Provider...	336	CTGDIL006I No entries returned in the search results.	342
CTGDKN213I JMS connection started.	336		
CTGDKN214I An exception occurred while sending password update message. The exception will be ignored.	337		

CTGDIL007W The throw limit was exceeded, when method `selectEntries` performed the search in the named context. 342

CTGDIL008W The naming exception is encountered when the method `selectEntries` performed the search in the named context: *exception* 342

CTGDIL009I No entries returned in the search results. 343

CTGDIL010I No more entries to retrieve, so no entries returned in search results. . . 343

CTGDIL011I Performing a directory search. 343

CTGDIL012I Search filter for directory search is set to '*filter*'. 343

CTGDIL013E Cannot add entry because the naming parameter *parameter name* was not found in the entry. 343

CTGDIL014W The modify entry operation failed because no distinguished name was found in existing entry. 344

CTGDIL015I Renaming entry from '*old DN*' to '*new DN*'. 344

CTGDIL016I No distinguished name given, using existing one. 344

CTGDIL017E The `deleteEntry` method was called with no *naming parameter* attribute. . 344

CTGDIL018I Searching for an entry where '*naming parameter*' equals '*DN*'. . . 344

CTGDIL019I Searching for entry using filter '*filter*'. 345

CTGDIL020I No entries found while searching for entry in JNDI Connector. 345

CTGDIL021I Single entry found while searching for entry in JNDI Connector. . . 345

CTGDIL022I No entries found while searching for entry in JNDI Connector. 345

CTGDIL023I Multiple entries found while searching for entry in JNDI Connector. . . 345

CTGDIL024I JNDI Connector successfully added attribute value to attribute in entry. 346

CTGDIL025W Modification of entry failed. Attribute already exists with given value. Exception occurred: *exception* 346

CTGDIL026W Modification of entry failed. An exception was encountered when the method `addAttributeValue` tried to add a given value to an attribute: *exception* 346

CTGDIL027I Retrieving next schema entry. 346

CTGDIL028I The class definition for object class '*object class name*' is *class definition*. 346

CTGDIL029W An exception was encountered when retrieving a context containing the schema objects of the named object's class definitions. The name of the object whose object class definition is to be retrieved: *search DN*. The exception is: *exception* . . 347

CTGDIL030W A naming exception was encountered when retrieving the named object in the method `getAttributeSyntax`. The name of the object to look up is: *attribute name*. The exception is: *error* 347

CTGDIL031I Successfully replaced a given attribute value from an entry. 347

CTGDIL032I Successfully removed a given attribute value from an entry. 347

CTGDIL033I Successfully remove an attribute from an entry. 348

CTGDIL034W Modification of entry failed. An exception was encountered while replacing a given attribute with a certain value: *exception* 348

CTGDIL035W Modification of entry failed. An exception was encountered while removing a given attribute value from an entry: *exception* 348

CTGDIL036W Modification of entry failed. An exception was encountered while removing a given attribute from an entry: *exception* . 348

CTGDIL037W Modification of entry failed. An attribute already exists with given value. Exception occurred: *exception* . . . 348

CTGDJQ001I Using LDAP SSL connection. Ensure TCP port number is changed accordingly. 349

CTGDJQ002I Username specified, using Simple authentication. 349

CTGDJQ003I Using Anonymous bind. 349

CTGDJQ004I No username specified, using Anonymous bind. 349

CTGDJQ005I Next extra parameter: *parameter*. 349

CTGDJQ006I Parsed a JNDI extra parameter with no colon separator in the line: *parameter*. 350

CTGDJQ007I JNDI Provider Parameter: *parameter name=parameter name, parameter value=value*. 350

CTGDJQ008I Setting binary attributes to: *attribute value*. 350

CTGDJQ009I No binary attributes specified using default: *attribute names*. 350

CTGDJQ010E Cannot perform VirtualListView search without sort attribute specified. . 351

CTGDJQ011I Using Virtual List View. The sort attribute is *attribute name* and page size is *page size*. 351

CTGDJQ012I Requesting Sort Control for attribute *attribute name*. 351

CTGDJQ013I Dumping LDAP return attributes... 351

CTGDJQ014I Attribute: *attribute name*. . . 351

CTGDJQ015I Using 'Paged Search' control: The page size is set to *page size*. 352

CTGDJQ016W The LDAP server did not confirm that it supports 'Paged Search' control. 352

CTGDJQ017I The selectEntries method will search the LDAP server for entries using the search base <i>DN</i> and the search filter ' <i>search filter</i> '.	352
CTGDJQ019I Entries were returned from the search.	352
CTGDJQ020I No entries returned from the search	353
CTGDJQ021I The selectEntries method will return a NULL value for the entries.	353
CTGDJQ022I The selectEntries method will return no entries.	353
CTGDJQ023I A PartialResultException occurred and will be ignored.	353
CTGDJQ024I Request the next page using Virtual List View Control at offset <i>index</i>	353
CTGDJQ025W PartialResultException occurred while retrieving the next entry from the LDAP server. LDAP server does not support paged results.	354
CTGDJQ026E The putEntry method failed because no distinguished name (<i>\$dn</i> attribute) was specified in entry.	354
CTGDJQ027E Unable to modify the entry. A delta modify occurred and no distinguished name (<i>\$dn</i> attribute) was provided in the conn entry or the link criteria.	354
CTGDJQ028I No distinguished name (<i>\$dn</i> attribute) was given. The existing distinguished name will be used to modify the entry.	354
CTGDJQ029E Unable to modify the entry. No distinguished name (<i>\$dn</i> attribute) was given and no existing entry was found.	355
CTGDJQ030I Renaming entry from ' <i>old DN</i> ' to ' <i>new DN</i> '.	355
CTGDJQ031I Initial rename of entry was unsuccessful. A manual move of entry will be attempted.	355
CTGDJQ032I Initial rename of entry was unsuccessful. A manual move of entry will not be attempted.	355
CTGDJQ033I The modify operation on attribute <i>attribute name</i> will be ignored. The attribute value would have been removed if the attribute was present in the current entry.	355
CTGDJQ034E Unable to modify the entry. The attribute <i>attribute name</i> at index <i>index</i> was specified to be modified but had an attribute value with an undefined operation code.	356
CTGDJQ035I The attribute <i>attribute name</i> will not be modified. The operation code for attribute value ' <i>attribute value</i> ' was unchanged.	356
CTGDJQ036I The entry <i>DN</i> will not be modified because there were no modification operations specified on the entry.	356

CTGDJQ038E LDAP Connector was unable to modify the entry. An exception occurred while creating a ModificationItem object that is used to modify the entry: <i>exception</i>	356
CTGDJQ039I Dumping LDAP Connector Modification List...	357
CTGDJQ040I Modification item: <i>modification item</i>	357
CTGDJQ041I Finished dumping LDAP Connector Modification List.	357
CTGDJQ042I Attribute already exists with given value: <i>exception</i>	357
CTGDJQ043E The deleteEntry method was called with no ' <i>\$dn</i> ' attribute or link-criteria.	357
CTGDJQ044I Searching for <i>\$dn = DN</i>	358
CTGDJQ045I Object found for <i>DN</i>	358
CTGDJQ046E Unable to find the Entry. The findEntry method encountered a PartialResultException: <i>exception</i>	358
CTGDJQ047I LDAP Connector will look for Entry using the filter <i>filter</i> on the base DN <i>DN</i>	358
CTGDJQ048E Unable to find the Entry. The findEntry method encountered a PartialResultException: <i>exception</i>	358
CTGDJQ049E Unable to find the Entry. The findEntry method encountered a NameNotFoundException: <i>exception</i>	359
CTGDJQ050E Unable to convert the entry to a set of attributes. The AD unicode password is not a multi-value field (ref AutoMapADPassword).	359
CTGDJQ051I The Attribute 'userPassword' was encoded and auto-mapped to 'unicodePwd'.	359
CTGDJQ052I Ignoring unchanged attribute: <i>attribute name</i>	359
CTGDJQ053I Removing empty string value for attribute <i>attribute name</i>	359
CTGDJQ055I Removing empty attribute: <i>attribute ID</i>	360
CTGDJQ056E Unable to move the Entry. Exception occurred: <i>exception</i>	360
CTGDJQ057E The moveEntry method removed the Entry ' <i>DN</i> ' but failed to add it again during rename.	360
CTGDJQ058I Successfully moved entry ' <i>DN</i> ' to ' <i>DN</i> '.	360
CTGDJQ059I Doing a compare of DN <i>DN</i> using filter <i>filter</i>	360
CTGDJQ060I Comparison is true using filter <i>filter</i>	361
CTGDJQ061I Comparison is false using filter <i>filter</i>	361
CTGDJQ062I The modification was successful. The attribute value was added.	361
CTGDJQ063E Attribute already exists with given value: <i>exception</i>	361
CTGDJQ064E The modification failed. An exception occurred while trying to add an attribute value: <i>exception</i>	361

CTGDJQ065I The modification was successful. The attribute value was replaced.	362
CTGDJQ066E Attribute already exists with given value: <i>exception</i>	362
CTGDJQ067E The modification failed. An exception occurred while trying to replace an attribute value: <i>exception</i>	362
CTGDJQ068I The modification was successful. The attribute value was removed.	362
CTGDJQ069E The modification failed. An exception occurred while trying to remove an attribute value: <i>exception</i>	362
CTGDJQ070I The modification was successful. All attribute values were removed.	363
CTGDJQ071E The modification failed. An exception occurred while trying to remove all the attribute values: <i>exception</i>	363
CTGDJQ072I The page result size: <i>result size</i>	363
CTGDJQ073I The page result size is unknown.	363
CTGDJQ074E Virtual List View Sort did not complete successfully. The return code returned was <i>return code</i>	363
CTGDJQ075I Virtual List View List Size: <i>size</i>	364
CTGDJQ076I Virtual List View Target Offset: <i>offset</i>	364
CTGDJQ077I Target Offset: <i>offset</i>	364
CTGDJQ078I Virtual List View changed result set size from <i>size</i> to <i>size</i>	364
CTGDJQ079I Virtual List View Context ID is NULL.	364
CTGDJQ080I Getting the next Schema class.	365
CTGDJQ081I The object class <i>object class</i> attributes: <i>attributes</i>	365
CTGDJQ082W Unable to query server information: <i>error message</i>	365
CTGDJQ083I The LDAP server does not tell us about its supported controls.	365
CTGDJQ085I The LDAP server does not tell us about its supported extensions.	365
CTGDJQ086I Dumping LDAP Server Information...	366
CTGDJQ087W Unable to get server information.	366
CTGDJQ088I Supported Controls of LDAP Server:	366
CTGDJQ089I Control <i>control name</i> : <i>boolean</i>	366
CTGDJQ090I Naming Contexts (use in your search base parameter).	366
CTGDJQ091I No info on the naming contexts.	367
CTGDJQ092I Naming context at <i>indexindex</i> : <i>naming context</i>	367
CTGDJQ093I Finished dumping LDAP Server Information.	367
CTGDJQ094I The feature object passed to the addDNFromCriteria method is an instance of class Vector.	367

CTGDJQ095I The feature object passed to the addDNFromCriteria method is an instance of class SearchCriteria.	367
CTGDJQ096I The feature object passed to the addDNFromCriteria method is an instance of class SearchCriteria.rscSearch.	368
CTGDJQ097E Cannot mix \$dn matching with other attributes in a search.	368
CTGDJQ098I Add DN value: ' <i>value</i> '.	368
CTGDJQ099E Unknown object type in search filter: <i>class name</i> : <i>object</i>	368
CTGDJQ100E LDAP Connector is unable to rebind to the LDAP server.	369
CTGDJQ101E Failed to query the schema on the search DN <i>DN</i> . Exception occurred: <i>exception</i>	369
CTGDJQ102E Failed to get the attribute syntax on the search DN <i>DN</i> . Exception occurred: <i>exception</i>	369
CTGDJQ103E The VirtualListViewControl class cannot be loaded.	369
CTGDJQ104E The VirtualListViewControl class does not provide the required interface.	369
CTGDJQ105E The VirtualListViewResponseControl class cannot be loaded.	370
CTGDJQ106E The VirtualListViewResponseControl class does not provide the required interface.	370
CTGDJQ107W The selectEntries method was unable to perform the search. Exception occurred: <i>exception</i>	370
CTGDJQ108W The compare method was unable to perform the search. Exception occurred: <i>exception</i>	370
CTGDJQ109W Error while querying schema. Exception occurred: <i>exception</i>	370
CTGDJQ110W Cannot close the connection to the LDAP Server. Exception occurred: <i>exception</i>	371
CTGDJQ111W Unable to find the Entry. The findEntry method encountered a NameNotFoundException: <i>exception</i>	371
CTGDJQ112W The LDAP " <i>ldapUrl</i> " name is not provided.	371
CTGDJQ113W The Distinguished Name <i>url</i> cannot be parsed as a URL.	371
CTGDKN101I Adding LDAP entry for person with distinguished name ' <i>distinguished name</i> '.	371
CTGDKN102I Successfully added LDAP entry for person with name ' <i>person name</i> '.	372
CTGDKN103E Failed to add LDAP entry for person with distinguished name ' <i>distinguished name</i> '. An exception occurred: <i>exception</i>	372
CTGDKN104E An exception occurred during password encryption: <i>exception</i>	372
CTGDKN105E An exception occurred during password decryption: <i>exception</i>	372

CTGDKN106E Failed to initialize encryption: <i>exception</i>	372
CTGDKN107E Missing required property: <i>property name</i>	373
CTGDKN108E Failed to connect to the LDAP server. An exception occurred: <i>exception</i>	373
CTGDKN109I Adding password values for user with distinguished name ' <i>distinguished name</i> '.	373
CTGDKN110E Could not add password values, because the user name is empty.	373
CTGDKN111E Unable to add password values for user ' <i>user name</i> ' because the password store could not connect to the LDAP Server. An exception occurred: <i>exception</i>	373
CTGDKN112I There is no LDAP entry for user ' <i>user name</i> '. Will create one.	374
CTGDKN113E Could not add password values for user ' <i>user name</i> ': <i>exception</i>	374
CTGDKN114I Deleting password values for user with distinguished name ' <i>distinguished name</i> '.	374
CTGDKN115E Could not delete password values, because the user name is empty.	374
CTGDKN116E Could not delete password values for user ' <i>user name</i> '. Failed to obtain the original list of passwords for the user from the LDAP server: <i>exception</i>	375
CTGDKN117E Could not delete password values for user ' <i>user name</i> ': <i>exception</i>	375
CTGDKN118E Could not delete password values for user ' <i>user name</i> ': <i>exception</i>	375
CTGDKN119I Checking if the LDAP server is accessible.	375
CTGDKN120I Modifying password values for user with distinguished name ' <i>distinguished name</i> '.	375
CTGDKN121E Could not modify password values because the user name is empty.	376
CTGDKN122I Empty list of passwords found while modifying password values. Will remove the password attribute.	376
CTGDKN123I There is no LDAP entry for user ' <i>user name</i> '. Will create one.	376
CTGDKN124E Could not modify password values for user ' <i>user name</i> ': <i>exception</i>	376
CTGDKN125I The password values to modify are <i>count</i>	376
CTGDKN126I There is no LDAP entry for user ' <i>user name</i> '. Will create one.	377
CTGDKN127E Could not modify password values for user ' <i>user name</i> ': <i>exception</i>	377
CTGDKN128I No password attribute was found while trying to remove the password attribute for user ' <i>user name</i> '.	377
CTGDKN129E Failed to remove password attribute for user ' <i>user name</i> ': <i>exception</i>	377
CTGDKN130I Verifying LDAP suffix.	378
CTGDKN131E Suffix ' <i>LDAP suffix</i> ' does not exist in the LDAP server: <i>exception</i>	378

CTGDKN132E An exception occurred while verifying the LDAP suffix: <i>exception</i>	378
CTGDKN133W Password values will not be stored in the Password Store, because the user identifier is empty.	378
CTGDKN136W Additional information about a user will not be written to the Password Store because the user identifier is empty.	378
CTGDKN137I There is no LDAP entry for user ' <i>user name</i> '. Will create one.	379
CTGDKN138E Could not set additional information for user ' <i>user name</i> ': <i>exception</i>	379
CTGDKN139I Setting additional information ' <i>extra info</i> ' for user with distinguished name ' <i>distinguished name</i> '.	379
CTGDJQ300I Terminate server request received while accepting connections.	379
CTGDJQ302I Creating dummy connection using IP Address ' <i>IP Address</i> ' and port ' <i>port number</i> '.	379
CTGDJQ303I LDAP Server Connector is already terminating. Not sending termination request.	380
CTGDJQ304I Sending termination request to LDAP Server Connector.	380
CTGDJQ305E No server Connector available or this Connector is no longer accepting connections.	380
CTGDJQ306I Connector already initialized with a java.net.Socket object.	380
CTGDJQ307I Using provide java.net.Socket object for LDAP client session.	381
CTGDJQ308I Listening for LDAP SSL connections on port: <i>port</i>	381
CTGDJQ309I Listening for LDAP connections on port: <i>port</i>	381
CTGDJQ310E Server Socket is not open, cannot accept client requests.	381
CTGDJQ311I Connector terminated by external request.	381
CTGDJQ312E LDAP Server Connector was unable to get the next message because there is no client session.	382
CTGDJQ313E Failed to get the next message. An IOException occurred while reading the next request: <i>exception</i>	382
CTGDJQ314E LDAP Server Connector unable to get the next entry. The LDAPMessage object returned a NULL Request object.	382
CTGDJQ315I Starting packet dump...	382
CTGDJQ316I Finished packet dump.	382
CTGDJQ317I Start of packet dump of search result...	383
CTGDJQ318I Finished packet dump of search result.	383
CTGDJQ319I Start of packet dump of response...	383
CTGDJQ320I Finished packet dump of response.	383
CTGDJQ321I LDAP Server Connector closed the connection.	383

CTGDJQ322E Unable to get the boolean value from the byte buffer. The byte buffer contained more than one byte.	384	CTGDII512I No RDN attribute found in entry read	389
CTGDJQ323E The byte comparison failed. Expected the byte value <i>hex value</i> but found byte value <i>hex value</i>	384	CTGDII513I migrating group entries using search filter	390
CTGDJQ324I Starting packet dump....	384	CTGDII514I migrating person entries using search filter	390
CTGDJQ325I Finished packet dump.	384	CTGDII515I Resetting change detection state for Flow	390
CTGDJQ326E Unknown bind type was specified. Only simple and SASL binds are currently supported.	384	CTGDII516I Mirroring hierarchy	390
CTGDJQ327E Unable to convert the entry into a control. An unknown control type was found in the entry: <i>control type</i>	385	CTGDII517I Flattening hierarchy	391
CTGDJQ328E Unable to parse input message. The input message did not begin with a BER sequence: <i>character</i>	385	CTGDII518I Starting migration.	391
CTGDJQ329E Unable to parse input message. The input message contained an unknown operation: <i>operation ID</i>	385	CTGDII519I containers to migrate.	391
CTGDJQ330E An unknown control type was encountered while parsing the input message: <i>control type</i> . Control will not be added to the entry.	385	CTGDII520I containers to skip.	392
CTGDJQ331I Adding control <i>object</i>	385	CTGDII521I Property not set.	392
CTGDJQ332E Unable to add control. Object was not of type LDAPControl: <i>object</i>	386	CTGDII522I You must specify where person entries are to be flattened under.	392
CTGDJQ333I Message ID of LDAPMessage object: <i>message ID</i>	386	CTGDII523I You must specify where group entries are to be flattened under.	392
CTGDJQ334I Dumping request entry...	386	CTGDII524E Error re-parsing container DN	393
CTGDJQ335E Unable to parse search filter. The search filter contained an unknown filter code: <i>filter code</i>	386	CTGDII525I Creating suffix in target	393
CTGDJQ336I Hexadecimal value: <i>hexadecimal value</i>	386	CTGDII526W LDAPSync can not be simulated. Please change the simulate property.	393
CTGDJQ337I Decimal value: <i>decimal value</i>	387	CTGDII527W Please set the following property: simulate=false.	393
CTGDJQ338I Hexadecimal value: <i>hexadecimal value</i>	387	CTGDII528W or use the commandline option: -0 actual	393
CTGDJQ339I Decimal value: <i>decimal value</i>	387	CTGDII529E Error dropping delta snapshot table	394
CTGDII501E Skipping undefined flow specified	387	CTGDII530W Unable to delete delta store table	394
CTGDII502E Error starting migration for Flow	387	CTGDII531E Properties in error - cannot configure Connector.	394
CTGDII503E Error starting synchronization for Flow	388	CTGDII532E Connector not found	394
CTGDII504I Check that the source.changeDetectionType property is set to Sun, AD, SDS or Delta.	388	CTGDII533I Initializing Connector	394
CTGDII505E Cannot handle delete of entry - lastKnownParent not found.	388	CTGDII534I Include entries from the following container.	395
CTGDII506E Error parsing the DN attribute returned by the Active Directory Change Detection Connector.	388	CTGDII535E Error initializing Connector	395
CTGDII507I migrating container entries using search filter.	388	CTGDII536E Error during operation	395
CTGDII508E No \$dn attribute found in entry - skipping	389	CTGDII537I Searching with Connector.	395
CTGDII509E Error parsing container DN.	389	CTGDII538I success	395
CTGDII510W Type of entry not set - defaulting to 'person'.	389	CTGDII539E Error selecting entries with Connector	396
CTGDII511E Parser not found	389	CTGDII540E Error reading change entry with Connector	396
		CTGDII541E Check properties - unable to set up	396
		CTGDII542I Confirming container exists	396
		CTGDII543E Container not found	397
		CTGDII544I Checking for property.	397
		CTGDII545I Property not defined	397
		CTGDII546E Map file is missing	397
		CTGDII547I Testing configuration and connections.	397
		CTGDII548I Testing configuration and connection for Flow.	398
		CTGDII549I !SUCCESS! All connections worked correctly!	398
		CTGDII550E !FAILURE! You must correct the problems listed above	398
		CTGDII551E error reading group.map file	398
		CTGDII552E error reading person.map file	399

CTGDII553E Error creating missing members file	399	CTGDII688I Behavior.	408
CTGDII554E Error during initial parsing of source dn	399	CTGDII689I not set	409
CTGDII555I changelog number.	399	CTGDII690I Simulation Only - no data will be changed in the target.	409
CTGDII556I failed	399	CTGDII691I Simulation Only - no data has been changed in the target	409
CTGDII557E Error parsing source dn after target lookup	400	CTGDII692I Summary for Flow.	410
CTGDII558I detected rename!.	400	CTGDII693I Total.	410
CTGDII559I SIMULATED RUN - NO DATA WILL BE MODIFIED.	400	CTGDII694I Add	410
CTGDII560I Property is not set	400	CTGDII695I Mod	410
CTGDII561I Count for progress display.	401	CTGDII696I Unchanged	411
CTGDII562E Error parsing source dn to handle moddn	401	CTGDII697I Skip	411
CTGDII563E Error parsing source dn for moddn/modrdn	401	CTGDII698E Error	411
CTGDII564I Multiple entries were found in the target..	401	CTGDII699E Errors	411
CTGDII565W Duplicate entry	402	CTGDII700I Warnings.	412
CTGDII566W More entries exist	402	CTGDII701I One or more group members were not migrated.	412
CTGDII567W Unable to identify type of entry	402	CTGDII702E These are listed in the GroupMembersMissing.log file located in the log folder	412
CTGDII568W Cannot find RDN attribute.	402	CTGDII703E To troubleshoot errors and warnings, check the log file	412
CTGDII569I Processing	402	CTGDII704I Successful.	412
CTGDII570I current count.	403	CTGDII705I Skipping.	413
CTGDII571I Skipping member because multiple entries were found in the target:	403	CTGDII706I sourceUserObjectClass and/or sourceGroupObjectClass is undefined.	413
CTGDII572I Skipping member because no entry was found in the target:	403	CTGDII707E Error deleting old log	413
CTGDII573W The following members were not added from source group	403	CTGDII708E Error renaming old log	413
CTGDII574I cannot find these members of the Group	404	CTGDII709E Error renaming previous log	414
CTGDII575W Skipping entry because member attribute is empty..	404	CTGDII710E Error renaming latest log	414
CTGDII626I No RDN value attribute found in entry read	404	CTGDII711E Error writing to log	414
CTGDII669I accumulating membership	404	CTGDII712E Property is missing or blank	414
CTGDII670W Unable to find member entry in source ldap.	405	CTGDII713I Property is invalid	414
CTGDII671E Error reading next entry from source.	405	CTGDII714I Make sure that the search base is visible in the source system, for example from an LDAP browser.	415
CTGDII672E The property 'global.flows' is incorrect	405	CTGDII715I Also ensure that the credentials defined for the Source connection are authorized to see entries in this container.	415
CTGDII673E Error parsing source dn.	405	CTGDII716I Invalid search filter specified	415
CTGDII674I reading data	405	CTGDII717I Make sure that the properties source.userObjectClass and source.groupObjectClass are correct.	415
CTGDII675I performing search	406	CTGDII718I Also, make sure the client certificate for this server has been imported to the SDI keystore.	416
CTGDII676E Error during initialization	406	CTGDII719I Username and/or password properties are incorrect.	416
CTGDII677W Unable to find entry in target system - unable to delete. Type:	406	CTGDII720I Username and/or SearchBase properties are incorrect.	416
CTGDII678E Source Endpoint form is missing	406	CTGDII721I Note: make sure the Changelog feature is enabled for the source directory server.	417
CTGDII679E Target Flow form is missing	406	CTGDII722I Make sure that the user name specified references a Person entry that exists in the directory.	417
CTGDII680E ** Form is missing.	407	CTGDII723I Also that containers have been migrated before Person or Group entries.	417
CTGDII681I Source Endpoint	407	CTGDII724I Make sure that the target suffix references a node that exists in the target.	417
CTGDII682I Flow Settings.	407	CTGDII725I Start dumping.	418
CTGDII683I Endpoint.	407		
CTGDII684E property not specified	408		
CTGDII685I Ok	408		
CTGDII686E Not found or inaccessible!.	408		
CTGDII687I Mapping Files.	408		

CTGDII726I End dumping	418
CTGDII727E Error retrieving property	418
CTGDII728I flowKey is undefined	418
CTGDII729E Error parsing dn to translate it	419
CTGDII730E Error parsing newSuperior	419
CTGDII731E Error parsing targetDn	419
CTGDII732I Connector parameters	419
CTGDII733E Error parsing source searchBase	419
CTGDII734E Error opening file.	420
CTGDII735W Any entries that were not written to the target can be found here	420
CTGDII736I Source entry not written to target.	420
CTGDII737E Error initializing join connector	420
CTGDII738E Error joining data.	420
CTGDII739E Error parsing	421
CTGDII740E Internal error	421
CTGDII751I Warning	421
CTGDII752E Error creating log file.	421
CTGDII753I Unable to create file.	421
CTGDII754E Error parsing rules	422
CTGDII755I property name invalid.	422
CTGDII756E Multiple matches found by join	422
CTGDII757E No match found by join	422
CTGDII761E Error calling post-write AL	422
CTGDII762E Error loading CI	423
CTGDII763E AssemblyLine name not specified	423
CTGDII769I Response AL in failed state	423
CTGDII770I Response AL failed.	423
CTGDII771E Response AL not specified or not found	424
CTGDII772I Response AL initialization failed.	424
CTGDII773I Unknown condition type	424
CTGDII774E Rule-response error	424
CTGDII775E Writeback could not find entry with dn	424
CTGDII777E Endpoint is not an Active Directory Domain Controller.	425
CTGDII779E Error opening response log file	425
CTGDII780I Ensure that nothing is blocking your access to the system, for example a firewall.	425
CTGDII781I Ensure that the system is running and ensure the communication port is open.	425
CTGDII782E Changelog is not enabled for the directory server	426
CTGDII785E SSL has been specified for this directory (ldaps://), but may not be enabled for the LDAP server itself	426
CTGDII786E SSL has not been specified for this server (ldap://), but may be required by the LDAP server.	426
CTGDJX001E Unable to process entry read because a line read in was not in the key:value pair format: ' <i>line</i> '.	426

CTGDJX002I LDIF Parser encountered attribute ' <i>attribute name</i> ' which has a language tag. The Parser ignores language tag attributes.	427
CTGDJX003E Unknown LDIF changetype in: <i>value</i>	427
CTGDJX004E Exception while encoding the string ' <i>string</i> ': <i>exception</i>	427
CTGDJX005I LDIF file to be tested: <i>file name</i>	427
CTGDJX006E File not found: <i>file name</i>	427
CTGDJX007I Entry: <i>entry</i>	428
CTGDJX008E Error reading line from file: <i>file name</i>	428
CTGDJY001I The parameter 'attributeName' set to ' <i>parameter value</i> '.	428
CTGDKK301E The 'com.ibm.di.log.interface' parameter must be set to use the Log Connector.	428
CTGDKN301I Initializing the Password Store class...	428
CTGDKN302I Initializing method received the object: ' <i>object name</i> '.	429
CTGDKN303I Checking Password Store for user ' <i>user name</i> '.	429
CTGDKN304I ...with passwords: ' <i>password values</i> '.	429
CTGDKN305I Storing password modifications for user: ' <i>userName</i> ' with passwords: ' <i>password values</i> ', timestamp: ' <i>timestamp</i> ' and ' <i>customData</i> '.	429
CTGDKN306I Storing password additions for user: ' <i>user name</i> ' with passwords: ' <i>password values</i> ', timestamp: ' <i>timestamp</i> ' and ' <i>customData</i> '.	429
CTGDKN307I Storing password deletions for user: ' <i>user name</i> ' with passwords: ' <i>password values</i> ', timestamp: ' <i>timestamp</i> ' and ' <i>customData</i> '.	430
CTGDKN308I Terminating the Password Store class.	430
CTGDKN309I Storing additional information for user: ' <i>user name</i> ' with extra data: ' <i>additional information about the user</i> '.	430
CTGDIV001E NotesException encountered while trying to retrieve the next entry from the Domino Server: ' <i>exception ID</i> ', ' <i>exception message</i> '.	430
CTGDIV002I Opening Session to Domino Server: Session Type=' <i>Session Type</i> ',, Hostname=' <i>Hostname</i> ', User ID=' <i>User ID</i> ', Requested IIOP/SSL=' <i>Boolean</i> '.	431
CTGDIV003I Using specified 'IOR' in the connection information for opening the session.	431
CTGDIV004E NotesException encountered trying to create a session with the Domino Server: Class Name=' <i>class name</i> ', Exception= <i>exception</i>	431

CTGDIV005I Success establishing a Notes Session: Name='server name', Version='version number', Platform='operating system'.	431
CTGDIV006E Lotus Notes Connector unable to open database 'database name' on server 'server name'.	432
CTGDIV007I The Database connected to is full-text indexed.	432
CTGDIV008I The Database connected to not is full-text indexed.	432
CTGDIV009I The Connector will use full-text search on the database.	432
CTGDIV010I The Connector will not use full-text search on the database.	432
CTGDIV011E The specified search view 'search view' was not found in the database. The Lotus Notes Connector is unable to select entries without a valid database search view.	433
CTGDIV012I Database select statement: 'select statement'.	433
CTGDIV013E Unable to retrieve entries from Domino Server. NotesException encountered: exception	433
CTGDIV014I No results returned from database search.	433
CTGDIV015I Database search returned number of documents documents.	434
CTGDIV016E The Lotus Notes Connector failed to create a new document on the Domino Server.	434
CTGDIV017I Lotus Notes Connector building entry from retrieved document: document attributes.	434
CTGDIV018I Lotus Notes Connector's local Notes thread started.	434
CTGDIV019I Lotus Notes Connector's local Notes thread terminated.	434
CTGDIV020E Unable to create local Notes thread because the lotus.domino.NotesThread class was not found in the classpath of the program. Exception occurred: exception	435
CTGDIV021E Lotus Notes Connector was unable to modify the entry because the entry was not found on the Domino Server.	435
CTGDIV022E Lotus Notes Connector was unable to delete the entry because the entry was not found on the Domino Server.	435
CTGDIV023I Adding attribute to entry: attribute name.	435
CTGDIV024I Attribute value added was null.	436
CTGDIV025I Attribute value added was 'attribute value'.	436
CTGDIV026I Attempting to build an entry in the Lotus Notes Connector.	436
CTGDIV027I Successfully built an entry in the Lotus Notes Connector.	436
CTGDIV028I Database search view is set to search view.	436

CTGDIV029I FTSearch filter on search view: filter.	437
CTGDIV030I FTSearch return code was return code.	437
CTGDIV031W Reverting to basic search because FTSearch on database view failed: filter. NotesException occurred: Error=error, Error Text=error text	437
CTGDIV032I FTSearch filter on database: filter.	437
CTGDIV033I Formula Search filter on database: filter.	437
CTGDIV034I No documents found.	438
CTGDIV035I Found number of documents documents.	438
CTGDIV036I Get document with Notes ID 'Notes ID'.	438
CTGDIV037I Document with Notes ID 'Notes ID' not found.	438
CTGDIV038W Unable to get document with Notes ID: Notes ID. NotesException occurred: Error=error, Error Text=error text	438
CTGDIV039I Will update number of attributes attributes in document.	439
CTGDIV040E Lotus Notes Connector was unable to save the document it was trying to modify.	439
CTGDIV041E Lotus Notes Connector was unable to save the document it was trying to modify. Exception occurred: exception	439
CTGDIV042I Attribute 'attribute name' will be updated with value 'attribute value'.	439
CTGDIV043I Attribute 'attribute name' will be updated with value 'attribute value' which is of class type 'class name'.	439
CTGDIV044W Lotus Notes Connector could not terminate the local Notes thread. Exception occurred: exception	440
CTGDIV045I IIOP Session with specified IOR string is created. SSL is on.	440
CTGDIV046I IIOP Session with specified IOR string is created. SSL is off.	440
CTGDIV047I IIOP Session is created. SSL is on.	440
CTGDIV048I IIOP Session is created. SSL is off.	440
CTGDIV049I Session to Domino Server is created.	441
CTGDIV050I The specified port: 'port' is bigger than 65535. The default port 80 will be used.	441
CTGDIV051I No port is specified. The default port 80 will be used.	441
CTGDIV052E The specified match operation for the UNID or NoteID in the Link Criteria is not correct.	441
CTGDIV053E Document with the specified UNID/NoteID was not found.	442

CTGDIV054E Connector already initialized. You must terminate it before initializing again.	442	CTGDJN015E Unable to delete entry because the specified entry does not have the required property 'mail.message'.	446
CTGDIV055W Error occurred while executing the command 'SET_CURRENT'. Exception thrown: <i>exception</i>	442	CTGDJN016I Folder does not support the expunge method.	446
CTGDIV056W Exception occurred while terminating: <i>exception</i>	442	CTGDJN017W Mail message at index ' <i>index number</i> ' could have been deleted from the mail server and could not be deleted. Error encountered while creating an Entry from a javax.mail.Message object: <i>exception</i>	447
CTGDIV057E The Notes thread is not alive. Lotus Notes Connector cannot execute the required command against the Domino Server without an active Notes Thread.	442	CTGDJN018E POP3 protocol does not support appending of messages.	447
CTGDIV058E Fatal Error while executing command against Domino Server: <i>exception</i>	443	CTGDJN019I Mail Folder is automatically set to 'INBOX' for POP3 protocol.	447
CTGDIV059I Did not find view <i>view name</i> in database <i>database name</i> : Database.getView returned NULL.	443	CTGDJN020E Mail Folder ' <i>folder name</i> ' does not exist on the mail server and parameter 'createFolder' is set to false.	447
CTGDJN001E Required Connector parameter 'mailServer' is not set.	443	CTGDJN021I The mail folder ' <i>folder name</i> ' did not exist on mail server and was automatically created.	447
CTGDJN002E Required Connector parameter 'mailUser' is not set.	443	CTGDJN022I The mail folder ' <i>folder name</i> ' was searched for messages, but none were found.	448
CTGDJN003E Required Connector parameter 'mailFolder' is not set.	443	CTGDJN022E The Mailbox Connector cannot find mail matching the specified Link Criteria.	448
CTGDJN004E The 'pollInterval' parameter set to an invalid value ' <i>parameter value</i> '. The default value ' <i>parameter value</i> ' will be used instead.	444	CTGDJN023E No Entry is supplied in the output map for 'update' or 'add' operation.	448
CTGDJN005E The 'pollInterval' parameter set to an invalid value ' <i>parameter value</i> '. The default value ' <i>parameter value</i> ' will be used instead.	444	CTGDJN024E Message in Attribute 'message' is not in appropriate format.	448
CTGDJN006E The port specified as part of the 'mailServer' parameter must be a numeric value. Exception encountered while try to parse out port: <i>parameter value</i>	444	CTGDJN025E An Error occurred when appending the message to the specified folder: ' <i>Exception</i> '.	449
CTGDJN007I Opened mail folder ' <i>folder name</i> ' in read and write mode.	444	CTGDJN026I The supplied messages were successfully added to the folder: ' <i>folder name</i> '.	449
CTGDJN008E Unable to initialize Mailbox Connector. The mail folder ' <i>folder name</i> ' does not exist on the mail server.	445	CTGDJN027E Unable to update entry, because the specified entry to update could not be found.	449
CTGDJN009I Initializing SSL settings.	445	CTGDJN028E Unable to update entry, because the specified entry to update does not contain the message.	449
CTGDJN010I Disconnecting from mail server but exception was encountered while closing the mailbox: <i>exception</i>	445	CTGDJN029I Searching folder: ' <i>folder name</i> ' for subfolders.	449
CTGDJN011W Mail message at index ' <i>index number</i> ' could have been deleted from the mail server and could not be retrieved. Error encountered while creating an Entry from a javax.mail.Message object: <i>exception</i>	445	CTGDJN030I No subfolders were found in folder: ' <i>folder name</i> '.	450
CTGDJN012E The findEntry method could not process request because it was passed a search criteria one or more attributes it does not support.	445	CTGDJN031I The folder: ' <i>folder name</i> ' does not exist on the store.	450
CTGDJN013E Unable to delete entry because more than one entry found to potentially remove.	446	CTGDJN032I The folder: ' <i>folder name</i> ' cannot be opened.	450
CTGDJN014E Unable to delete entry because the specified entry to delete could not be found.	446	CTGDJN033I Searching folders in namespaces: ' <i>folder name</i> '.	450
		CTGDJN034E The folder: ' <i>folder name</i> ' cannot be created successfully.	450
		CTGDJN035E The value for flag: ' <i>flag name</i> ' was not updated due to the following error: ' <i>Exception</i> '.	451
		CTGDJN036I POP3 Messages do not support 'Flags.Flag.RECENT', therefore the Flag is not updated.	451

CTGDJN037E Unable to initialize Mailbox Connector. The Mailbox Connector supports only the 'INBOX' folder when the POP3 protocol is chosen.	451
CTGDIQ201I The 'watermark' parameter is set to <i>parameter value</i>	451
CTGDIQ202E Queue with name <i>name</i> does not exist.	452
CTGDIQ001E The Memory Stream Connector cannot add the entry because it has no Parser to write to.	452
CTGDIQ101E Required Connector parameter 'queueName' is not set.	452
CTGDIQ102E Required Connector parameter 'jdbcTable' is not set.	452
CTGDIQ103E Unable to get next entry because a non-entry object was received from queue: ' <i>object info</i> '.	452
CTGDIQ104E Queue with name <i>name</i> does not exist.	453
CTGDIC001I Delete selected items?	453
CTGDIC002E Cannot load a Connector with configuration type: <i>class</i>	453
CTGDIC003W Delete table <i>table name</i> ?	453
CTGDIC004I Table <i>table name</i> deleted.	453
CTGDIC005I Server says it supports the Paged Search control.	454
CTGDIC006W Unable to determine whether the LDAP Server supports paged searches. Verify the LDAP Server supports paged searches.	454
CTGDIC007W Unable to perform paged search. This LDAP server does not support paged search.	454
CTGDIC008W Unable to lookup changelog information. The LDAP server does not provide server information.	454
CTGDIC009W Unable to lookup changelog information. The Context attribute 'firstchangenumber' does not exist on the LDAP Server.	454
CTGDIC010I The First Change number is set to <i>first number</i> . The Last Change number is set to <i>last number</i>	455
CTGDIC011W Unable to retrieve Changelog base name. The 'changelog' attribute does not exist in the LDAP server info entry.	455
CTGDIC012I LDAP Server changelog base name: ' <i>changelog</i> '.	455
CTGDIC013W Delete table <i>table name</i> ?	455
CTGDIC014W Unable to query schema until the Connector is configured.	455
CTGDIC015W Unable to lookup change number information. The LDAP server does not provide server information.	456
CTGDIC016E Enter the WSDL URL first.	456
CTGDIC017E No services were found in the specified WSDL file.	456
CTGDIC018E Enter a service name first.	456
CTGDIC019E No endpoints were found in the specified WSDL file.	456

CTGDIC020E No operations were found in the specified WSDL file.	457
CTGDIC022E The attribute ' <i>attribute name</i> ' is already mapped.	457
CTGDIC023E Exception encountered while creating component of type ' <i>component type</i> ': ' <i>error message</i> '.	457
CTGDIC024W Unable to update component. The referenced component no longer exists: <i>file name</i>	457
CTGDIC025E Exception encountered while updating an external component.	457
CTGDIC026E The remote Config <i>Config file</i> cannot be found on server <i>server name</i>	458
CTGDIC027E Connection to server <i>server name</i> cannot be obtained.	458
CTGDIC028E No server configured.	458
CTGDIC029I The application will not function properly without the IBM Security Directory Integrator install directory. Specify the IBM Security Directory Integrator install directory.	458
CTGDIC030E Installation directory specified is not valid. A local IBM Security Directory Integrator installation is required for the application to run.	459
CTGDIC031E Exception encountered while loading the Config file: ' <i>file name</i> '.	459
CTGDIC032W Exception encountered while loading the Config file: ' <i>file name</i> '.	459
CTGDIC033E Unable to load Config file. Cannot determine folder for referenced Config file: ' <i>file name</i> '.	459
CTGDIC034E Unable to save file because an exception was encountered.	460
CTGDIC035E Unable to load BaseEditor because there is no quick-edit object.	460
CTGDIC036E Exception occurred while downloading properties.	460
CTGDIC037I Update completed successfully.	460
CTGDIC038E Exception occurred while upload properties.	460
CTGDIC039I The connector did not return any schema information. Do you want to open the connection and read one entry?	461
CTGDIC040I Do you want to clear the current schema before updating?	461
CTGDIC041I Do you want to clear the current schema before updating?	461
CTGDIC043I The Component returned an empty entry.	461
CTGDIC044I No schema information returned. Would you like to read an entry?	461
CTGDIC045I Solution directory updated.	462
CTGDIC046E The folder already exists: ' <i>folder name</i> '.	462
CTGDIC047E Attribute already assigned to attribute ' <i>attribute name</i> '.	462
CTGDIC048E Error: ' <i>error message</i> '	462

CTGDIC049E Exception encountered while opening the configuration file: ' <i>error message</i> '	462	CTGDIC075I The attribute map ' <i>attribute map name</i> ' references undefined/unavailable work attribute ' <i>attribute name</i> '.	468
CTGDIC050E Unable to open the configuration file. An exception occurred: ' <i>error message</i> '	463	CTGDIC076I Local development server launched	468
CTGDIC051I Solution directory created.	463	CTGDIC077I Process exit code: ' <i>exit code</i> '.	468
CTGDIC052I Unable to build configuration file. An exception occurred: ' <i>error message</i> '	463	CTGDIC078I The Connector ' <i>Connector name</i> ' references the object ' <i>object name</i> '.	469
CTGDIC053I Unable to create folder ' <i>name</i> '. An exception occurred: ' <i>error message</i> '	463	CTGDIC079I You have not updated the solution directory and not doing so may affect your connection to this server. Do you want to update the solution properties before saving?	469
CTGDIC054E Target folder ' <i>folder name</i> ' is not a folder.	463	CTGDIC080I Resource already exists. Do you wish to overwrite? Overwrite: ' <i>File name</i> ' Last modified: ' <i>Last modified</i> '	469
CTGDIC055E Unable to remove object from configuration file. An exception occurred: ' <i>error message</i> '	464	CTGDIC081I Cannot find a form to display for object class <i>Object Class</i>	469
CTGDIC056E Cannot determine folder for object ' <i>object name</i> '.	464	CTGDIC082I The file <i>.rs.xml</i> cannot be imported, please export the project and then import that file.	470
CTGDIC057W Cannot find cached configuration for file ' <i>file name</i> '.	464	CTGDIC083I A restart of the IBM Security Directory Integrator server is required to activate changes made to the system store of a running IBM Security Directory Integrator server.	470
CTGDIC058W Using cached version of file ' <i>file name</i> '.	464	CTGDIC084I IBM Security Directory Integrator Version: 7.2 This plug-in is provided by IBM Corp. Your use of this plug-in is governed by the license that was agreed to when the plug-in was installed as part of a feature installation. Licensed Materials - Property of IBM Corp. Copyright IBM Corp. and other(s), 2002, 2013. All Rights Reserved.	470
CTGDIC059E An unsupported action was encountered. You can only open configuration files that exist in your workspace.	464	CTGDIC085I Do you want to restore the file from the runtime configuration of the project?	470
CTGDIC060E Cannot create the specified directory: ' <i>directory name</i> '.	465	CTGDIC086W A Property can only be exposed once.	471
CTGDIC061E The specified solution directory ' <i>name</i> ' is a file.	465	CTGDIC087W An item with that name already exists.	471
CTGDIC062E Created the file ' <i>file name</i> '.	465	CTGDIC088W Error while renaming to ' <i>new name</i> '.	471
CTGDIC063I Do you want to stop the local server running on ' <i>server address</i> '?	465	CTGDIC089W You must configure sandbox settings before running the AssemblyLine in Record or Playback mode.	471
CTGDIC064I The server is being started...	465	CTGDIC090W This Attribute Map item contains an expression. If it is changed, it must be changed to javascript code.	471
CTGDIC065I This will clear the current object(s) and restore the value to the inherited one.	466	CTGDIC091W The proxy AssemblyLine was successfully updated.	472
CTGDIC066I When the Skip Lookup option is selected, no 'Before/After Lookup' and 'On Multiple Entries' hooks are invoked. Also, no add is done in Update mode if an entry is not found to match the criteria.	466	CTGDIC092E The ikeyman.exe file not found. Searched in folders <i>path1</i> and <i>path2</i>	472
CTGDIC067I The Schema item ' <i>schema name</i> ' already exists.	466	CTGDIC093E No // found in ' <i>url</i> '.	472
CTGDIC068I The file has been changed on the file system. Do you want to reload the editor?	466	CTGDIC094I Delete selected items? There will be no undo.	472
CTGDIC069I Referenced component no longer exists: ' <i>file name</i> '.	467	CTGDIC095W Component ' <i>name</i> ' automatically moved to the DataFlow section.	472
CTGDIC070I Unknown class encountered. Unable to reattach to the class ' <i>class name</i> '.	467		
CTGDIC071I The parent is not a container.	467		
CTGDIC072I Th Server Mode Connector ' <i>Connector name</i> ' appears after another Server Mode Connector.	467		
CTGDIC073I The Connector ' <i>Connector name</i> ' references unknown property ' <i>property name</i> '.	467		
CTGDIC074I The Connector ' <i>Connector name</i> ' references unknown string ' <i>string value</i> ' which is not defined in the schema.	468		

CTGDIC096W The AssemblyLine is still running on the server. Do you want to stop it?	473	CTGDI3245I Failed to connect to the database (parameters: <i>credentials</i>). The thrown exception is: <i>exception</i>	478
CTGDIC097W Could not locate <i>name</i> while resolving dependencies.	473	CTGDIC121I No types were found.	478
CTGDIC098I Connection to <i>DataBase</i> Successful.	473	CTGDIC122I Common Data Model version is ' <i>cdm</i> '.	479
CTGDIC099W Connection to <i>DataBase</i> Failed.	473	CTGDIC123E AssemblyLine failed: <i>string</i>	479
CTGDIC100I The branch ' <i>Branch name</i> ' has no preceding IF/ELSEIF component.	473	CTGDIC124I AssemblyLine Completed- <i>number</i> record(s) read- <i>number</i> record(s) written- <i>number</i> error(s) <i>string</i>	479
CTGDIC101I The case ' <i>Case name</i> ' is not inside a Switch component.	474	CTGDIC126I <i>number</i> record(s) record(s) found.	479
CTGDIC102I The attribute map for ' <i>Connector name</i> ' is empty (auto-mapping is either off in the AssemblyLine or the connector is not part of an AssemblyLine).	474	CTGDIC127I No MSS were found.	479
CTGDIC103I Do you want to replace the reference to ' <i>Property name</i> ' with the value ' <i>Value name</i> '?	474	CTGDIC128I The Component has reached the end of the data source.	480
CTGDIC104I The system store configuration has no value for parameter: {0}	474	CTGDIC129I Input value:- <i>string</i> Output value: <i>string</i>	480
CTGDIC105E The specified namespace is already defined	474	CTGDIC130I AssemblyLine Completed- <i>number</i> record(s) read- <i>number</i> record(s) added- <i>number</i> record(s) modified- <i>number</i> record(s) unchanged- <i>number</i> error(s) <i>string</i>	480
CTGDIC106I <i>Run option</i> on <i>Server name</i>	475	CTGDIC131I An error occurred while initializing component [<i>name</i>].	480
CTGDIC107W An Operation with that name already exists.	475	CTGDIC132I An error occurred in component [<i>name</i>].	480
CTGDIC108E The system encountered an internal error while trying to validate a product license. Message: <i>message</i>	475	CTGDIC133I An error occurred while executing AssemblyLine Hook <i>name</i>	481
CTGDIC109E The system cannot find an enrolled product license.	475	CTGDIC134I Illegal character ' <i>character</i> ' in name.	481
CTGDIC110E The evaluation period has expired.	475	CTGDIC135E Parameter ' <i>parameter name</i> ' must be a number.	481
CTGDIC111W There are <i>number of days</i> days left in the evaluation period.	476	CTGDIC136E Parameter ' <i>parameter name</i> ' cannot be less than <i>value</i>	481
CTGDIC112E The evaluation period is invalid.	476	CTGDIC137E Parameter ' <i>parameter name</i> ' cannot be greater than <i>value</i>	481
CTGDIC113E No help page found for topic ' <i>topic</i> '.	476	CTGDIC138E Value for ' <i>label</i> ' must be a list of increasing numbers.	482
CTGDIC114E Parameter ' <i>parameter name</i> ' is required.	476	CTGDIC139E There are not that many days in the month.	482
CTGDIC115E There are <i>number</i> missing values.	477	CTGDIC140W For some combinations of Day and Month this Scheduler will not run.	482
CTGDIC116W AssemblyLine terminated - showing last 10 log messages (use view log file to view entire log)	477	CTGDIC141W Some months this Scheduler will not run.	482
CTGDIC117W Software Update is disabled in this product.	477	CTGDIC142E Can not find a suitable protocol.	482
CTGDIC118E An error occurred while retrieving the CDM version.	477	CTGDIC143W Some files could not be refactored. Check Error log for details.	483
CTGDIC119E Failed to connect to the IT registry database (parameters: <i>it_registry_credentials</i>). The thrown exception is: <i>exception</i>	478	CTGDIC144W Unable to locate the connection form for this component. This is mostly likely because a jar or zip file is missing. Make these library files available to SDI by copying them anywhere under the 'jars' subfolder of the SDI installation directory. Or if you want to leave these files in place and point to them instead, then add their file/folder paths to the 'com.ibm.di.loader.userjars' property. You must restart SDI for changes made to take affect.	483
CTGDIC120I Successfully connected to the IT registry database (parameters: <i>it_registry_credentials</i>).	478		
CTGDI3244I Successfully connected to the database (parameters: <i>credentials</i>).	478		

CTGDIC145W The port for your <i>name</i> SDI Server is already in use at <i>address</i> in the Solution Directory <i>directory name</i>	483	CTGDKE030I The Property Store cache is enabled. The cache timeout is set to <i>number of seconds</i> seconds.	489
CTGDKE001I Use a named ExternalProperties object for this call.	484	CTGDKE031I Caching all properties from data source.	489
CTGDKE002I Listing property store <i>property store name</i>	484	CTGDKE032I Cached <i>number of properties</i> properties.	490
CTGDKE003E No Config driver for: <i>URL</i>	484	CTGDKE033I Returning cached entry for key <i>key</i>	490
CTGDKE004E Missing password for Encrypted file.	484	CTGDKE034I Removing expired cache entry for key= <i>key</i>	490
CTGDKE005I Inside the getNamespace method: name= <i>object</i> , namespace contains the key= <i>boolean</i>	484	CTGDKE035I Adding cache entry for key <i>key</i>	490
CTGDKE006I Registering namespace: ' <i>object</i> '.	485	CTGDKE036E Property key ' <i>key</i> ' is not unique.	490
CTGDKE007I Unregister namespace: ' <i>object</i> '.	485	CTGDKE037E Property store ' <i>property store name</i> ' is configured as read-only.	491
CTGDKE008I Add namespace pending unload list: ' <i>object</i> '.	485	CTGDKE038E No ' <i>key</i> ' attribute specified.	491
CTGDKE009I The namespace is not in global namespace: <i>object</i>	485	CTGDKE039E Error occurred when creating IBM Security Directory Integrator Property store. Property store: <i>property store name</i> Exception: <i>exception</i>	491
CTGDKE010I Inside the garbageCollect method...	485	CTGDKE040E Property store ' <i>store name</i> ' is not available to read key ' <i>key</i> '.	491
CTGDKE011I Reviewing namespace <i>named URL</i> for garbage collection.	486	CTGDKE041W Property store ' <i>store name</i> ' does not contain key ' <i>key</i> '.	491
CTGDKE012I Removing namespace: <i>named URL</i>	486	CTGDKE042E Problem parsing component definition file ' <i>path name</i> '.	492
CTGDKE013I Inside canRemoveNamespace method: <i>object</i>	486	CTGDKE043E An error occurred while encrypting data.	492
CTGDKE014I The canRemoveNamespace method check includes: <i>object</i>	486	CTGDKM201I Parsing to get options provided by user.	492
CTGDKE015I The canRemoveNamespace method determined the ' <i>named URL</i> ' is referenced by ' <i>object</i> '.	486	CTGDKM202I Starting the Administration and Monitoring Console back up operations to location: <i>location</i>	492
CTGDKE016E Not a namespace reference: <i>name</i>	487	CTGDKM203I Starting the Administration and Monitoring Console restore operations from location: <i>location</i>	492
CTGDKE017E Undefined namespace reference: <i>string</i>	487	CTGDKM204I Parsing to get options provided by user.	493
CTGDKE018E Undefined namespace reference: <i>namespace</i> in <i>object</i>	487	CTGDKM205I The database table being backedup is: <i>table name</i>	493
CTGDKE019E Package has no Info/packageid node.	487	CTGDKM206E SQL Exception while trying to read Database tables	493
CTGDKE020I Registered package ' <i>package name</i> '.	487	CTGDKM207E An Exception was encountered while trying to connect to customer database. Unable to back the database.	493
CTGDKE021I Inside the removeNamespace method: name= <i>object</i> , namespace contains the key= <i>boolean</i>	487	CTGDKM208E An exception occurred while trying to write to an xml file for the database table <i>table name</i>	493
CTGDKE022E No available property stores to read key ' <i>key</i> '.	488	CTGDKM209E An exception occurred while trying to read column data from tables to create xml files.	494
CTGDKE023I The getProperty method will search using key <i>key</i>	488	CTGDKM210I Column Name: <i>column name</i> . Column Value: <i>column value</i>	494
CTGDKE024I Checking to see if property is in the property store: <i>property store name</i>	488	CTGDKM211I Generated SQL statements for rest of the tables.	494
CTGDKE025I Found the property in the property store: <i>property store name</i>	488	CTGDKM212I Back up location is: <i>location</i>	494
CTGDKE026I The property was not found.	488	CTGDKM213I SQL exception thrown while executing the following SQL statement: <i>SQL statement</i>	494
CTGDKE027E No available property stores to write key ' <i>key</i> '.	489		
CTGDKE028E No default store to accept: <i>key</i>	489		
CTGDKE029I The Property Store cache is disabled. The cache timeout is set to <i>number of seconds</i> seconds.	489		

CTGDKM214I Adding the autogenerated ids from master tables to rest of xml files.	495	CTGDKM243E An error has occurred while autogenerating key.	500
CTGDKM215I Updating xml of table: <i>statement</i> with new ID.	495	CTGDKM244E An error has occurred while removing columns to update saved data.	501
CTGDKM216I Writing to xml files:	495	CTGDKM245E An error has occurred while adding columns to update saved data.	501
CTGDKM217I Inspecting xml files for new constraints added.	495	CTGDKM246E An error has occurred while renaming table to update saved data.	501
CTGDKM218E The global id, host, or port is null.	495	CTGDKM247E An error has occurred while creating sql insert statements.	501
CTGDKM219E The data violates unique constraint requirement of table TDI_SERVER_MASTER. The data cannot be migrated.	496	CTGDKM248E An error has occurred while updating xml files with newly generated ids.	501
CTGDKM220I Generating Autogenerated IDs for the following table: <i>table name</i>	496	CTGDKM249I Updating the XML for table: <i>table name</i> with new ID.	502
CTGDKM221I Old ID value is: <i>ID value</i>	496	CTGDKM301I Starting file migration...	502
CTGDKM222I Column added to insert: <i>column name</i>	496	CTGDKM302I Parsing options...	502
CTGDKM223I SQL statement in master tables:	496	CTGDKM303E The <i>operator switch</i> option occurred more than once.	502
CTGDKM224I Generated ID: <i>ID</i>	497	CTGDKM304E No value specified for <i>option name</i> option.	502
CTGDKM225E Error cannot generate key for table: <i>table name</i>	497	CTGDKM305E Incorrect command usage.	503
CTGDKM226E An error was encountered while connecting to the database for generating IDs for master tables.	497	CTGDKM306E Unknown option <i>operator switch</i> encountered.	503
CTGDKM227I SQL insert statements for the rest of the tables:	497	CTGDKM307E The <i>operator switch</i> option was not specified. This is a mandatory option.	503
CTGDKM228I Reading list of files from directory...	497	CTGDKM308I Options Parsed: <i>options</i>	503
CTGDKM229I Renaming table <i>table name</i> to <i>table name</i>	498	CTGDKM309E An error <i>error</i> occurred while reading the XML properties file.	503
CTGDKM230I Adding columns for Security Directory Integrator 7.2 changes.	498	CTGDKM310E Unable to migrate the file <i>file name</i> . The file does not exist or cannot be read.	504
CTGDKM231I Number of columns to be added: <i>number of columns</i>	498	CTGDKM311E Unable to migrate the file <i>file name</i> . The file specified is not a file.	504
CTGDKM232I Column data added to xml. Column name: <i>column name</i> . Column value: <i>column value</i>	498	CTGDKM312E Unable to migrate the file <i>file name</i> . The file specified cannot be written to.	504
CTGDKM233I Initializing DB Connection properties...	498	CTGDKM313E Unable to migrate the file <i>file name</i> . The file name of the backup file must not be the same name as the file name.	504
CTGDKM234E An error was encountered while trying to read amc.properties file.	499	CTGDKM314E Unable to migrate the file <i>file name</i> . The file name of the backup file must not be the same name as the new file.	505
CTGDKM235E An error was encountered while trying to write to file.	499	CTGDKM315E Unable to perform the migration. Unable to backup the file <i>file name</i> to <i>file name</i>	505
CTGDKM236E An error was encountered while trying to add data to database.	499	CTGDKM316I Adding the new properties...	505
CTGDKM237I Updating XML files with constraints added in new release.	499	CTGDKM317I Completed adding the new properties.	505
CTGDKM238E The global id, host or port is null.	499	CTGDKM318I Started modifying the old properties with new values and commenting the old properties...	505
CTGDKM239E The data violates unique constraint requirement. The data cannot be migrated.	500	CTGDKM319I Completed modifying the old properties with new values and commenting the old properties.	506
CTGDKM240E An error has occurred while parsing the xml holding AMC DB data.	500	CTGDKM320I Starting commenting the old properties...	506
CTGDKM241E An error has occurred while reading Administration and Monitoring Console data transferred to xml files.	500	CTGDKM321I The number of old properties to be commented are <i>number of properties</i>	506
CTGDKM242I Autogenerating ids for : <i>table name</i>	500	CTGDKM322I There are no old properties to be removed for release <i>release version</i>	506

CTGDKM323I There are no new properties added for release <i>release version</i>	507
CTGDKM324I Updating the properties....	507
CTGDKM325I Migration completed with exit code <i>exit code</i>	507
CTGDKM326I The file <i>file name</i> is successfully deleted.	507
CTGDKM327I Failed to delete file <i>file name</i>	507
CTGDKM328I Initializing migration, loading the <i>xml prop file</i> properties file .	508
CTGDKM329I There are no properties in the new release which need to be updated in the older release.	508
CTGDKM101W The command did not complete successfully. See previous messages or error logs for details.	508
CTGDKM102E Unknown value passed for '-op' option.	508
CTGDKM103E Incorrect command usage.	508
CTGDKM104E No value specified for <i>option name</i> option.	509
CTGDKM105I The usage for the command is: <i>tdimigam -f propfile [-b backfile] [-n newfile] [-v] [-?]</i> where: -f propfile The name of the file to migrate -b backfile Back up the original file with the specified name -n newfile Name to give the file that is migrated -v Enable verbose mode -? Prints this usage statement	509
CTGDKM106I Return Code: <i>return code</i>	509
CTGDKM107I Parsing options...	509
CTGDKM108I Options Parsed: <i>options</i>	510
CTGDKM109E The <i>operator switch</i> option occurred more than once.	510
CTGDKM110E Unknown option <i>operator switch</i> encountered.	510
CTGDKM111W Already reached the end of argument list.	510
CTGDKM112E The <i>operator switch</i> option was not specified. This is a mandatory option.	510
CTGDKM113I Starting file migration...	511
CTGDKM114E Unable to perform the migration. Unable to backup the file <i>file name</i> to <i>file name</i>	511
CTGDKM115E Unable to migrate the file <i>file name</i> . The file does not exist or cannot be read.	511
CTGDKM116E Unable to migrate the file <i>file name</i> . The file specified is not a file.	511
CTGDKM117E Unable to migrate the file <i>file name</i> . The file specified cannot be written to.	511
CTGDKM118E Unable to migrate the file <i>file name</i> . The file name of the backup file must not be the same name as the file name.	512
CTGDKM119E Unable to migrate the file <i>file name</i> . The file name of the backup file must not be the same name as the new file.	512
CTGDKM120E Error deleting file: <i>file name</i>	512

CTGDKM001W The command did not complete successfully. See previous messages or error logs for details.	512
CTGDKM002E Unknown value passed for '-op' option.	513
CTGDKM003E Incorrect command usage.	513
CTGDKM004E No value specified for <i>option name</i> option.	513
CTGDKM005I The usage for the command is: <i>tdimigbl -f propfile [-b backfile] [-n newfile] [-v] [-?]</i> where: -f propfile The name of the file to migrate -b backfile Backup the original file with the specified name -n newfile Name to give the file that is migrated -s dir Specifies the working directory where the solution directory is located. -v Enable verbose mode -? Prints this usage statement	513
CTGDKM006I Return Code: <i>return code</i>	514
CTGDKM007I Parsing options...	514
CTGDKM008I Options Parsed: <i>options</i>	514
CTGDKM009E The <i>operator switch</i> option occurred more than once.	514
CTGDKM010E Unknown option <i>operator switch</i> encountered.	514
CTGDKM011W Already reached the end of argument list.	515
CTGDKM012E The <i>operator switch</i> option was not specified. This is a mandatory option.	515
CTGDKM013I Starting file migration...	515
CTGDKM014E Unable to perform the migration. Unable to backup the file <i>file name</i> to <i>file name</i>	515
CTGDKM015E Unable to migrate the file <i>file name</i> . The file does not exist or cannot be read.	515
CTGDKM016E Unable to migrate the file <i>file name</i> . The file specified is not a file.	516
CTGDKM017E Unable to migrate the file <i>file name</i> . The file specified cannot be written to.	516
CTGDKM018E Unable to migrate the file <i>file name</i> . The file name of the backup file must not be the same name as the file name.	516
CTGDKM019I Performing migration deletion operations...	516
CTGDKM020I Performing migration addition operations...	516
CTGDKM021I Performing migration Derby operations...	517
CTGDKM022I Performing migration modification operations...	517
CTGDKM023E Unable to migrate the file <i>file name</i> . The file name of the backup file must not be the same name as the new file.	517
CTGDKM024E An error has occurred while reading the stash file: <i>exception</i>	517
CTGDKM025E No password has been found in the Server stash file.	518
CTGDIS001E The version number of the Connector is undefined.	518

CTGDIS002E Error on printing component version numbers.	518
CTGDIS003I *** Start dumping Entry . . .	518
CTGDIS004I *** Finished dumping Entry . .	518
CTGDIS005I *** Start dumping Object *** .	519
CTGDIS006I *** Finished dumping Object ***	519
CTGDIS007I Dump of SYSTEM.PROPERTIES. . .	519
CTGDIS008I Loading system templates. . . .	519
CTGDIS009E Error while setting log file: ' <i>file name</i> '.	519
CTGDIS010E No configuration file specified.	520
CTGDIS011E Error loading configuration file <i>file name</i>	520
CTGDIS012E Error while setting properties.	520
CTGDIS014E Error while initializing manager.	520
CTGDIS015E Error while auto starting AssemblyLines.	520
CTGDIS016E Error while auto starting EventHandlers.	521
CTGDIS017E Error while starting EventHandler <i>EventHandler name</i>	521
CTGDIS018E Cannot declare the error object.	521
CTGDIS019E The EventHandler <i>EventHandler name</i> has no associated Java class.	521
CTGDIS020E Cannot debug old style EventHandlers.	521
CTGDIS021E No Config path configured. . .	522
CTGDIS022E Error while loading configuration.	522
CTGDIS023E Error while getting AttributeMap for <i>attribute map</i>	522
CTGDIS024E Error while getting Config for AssemblyLine <i>AssemblyLine name</i>	522
CTGDIS025E Exception while loading configuration: <i>file name</i>	522
CTGDIS026E SkipTo: Unknown Connector <i>Connector name</i>	523
CTGDIS027E Could not auto-start the EventHandler(s).	523
CTGDIS028I Starting AssemblyLine <i>AssemblyLine name</i>	523
CTGDIS029I Starting AssemblyLine <i>AssemblyLine name</i> for debug.	523
CTGDIS030I AssemblyLine <i>AssemblyLine name</i> started.	524
CTGDIS031I AssemblyLine <i>AssemblyLine name</i> started for debugging.	524
CTGDIS032I Starting EventHandler: <i>EventHandler name</i>	524
CTGDIS033I EventHandler <i>EventHandler name</i> has started.	524
CTGDIS034I Wait for completion of AssemblyLine: <i>AssemblyLine name</i>	524
CTGDIS035I Wait for completion of EventHandler: <i>EventHandler name</i>	525
CTGDIS036I Exit after auto-run requested.	525
CTGDIS037I Server terminates because only main thread is left.	525

CTGDIS038I System termination requested by external process.	525
CTGDIS039I Waiting for the completion of the currently executing task.	525
CTGDIS040I Loading configuration from stdin.	526
CTGDIS041I Loading configuration from <i>file name</i>	526
CTGDIS042W Possible deadlock detected, allowing one more thread to start.	526
CTGDIS043I Enabled hook script for <i>hook name</i> is empty.	526
CTGDIS044I Initializing Connector.	526
CTGDIS045I Connector is iterator, call selectEntries.	527
CTGDIS046I Initialization finished. . . .	527
CTGDIS047W Entry not found.	527
CTGDIS048E Multiple entries found and no 'On Multiple Entries' Hook defined. . . .	527
CTGDIS049I Entry not found, calling ADD.	527
CTGDIS050I Entry found, calling MODIFY. . .	528
CTGDIS051W Task is not allowed to modify entries.	528
CTGDIS052I (Modify) Attribute <i>attribute name</i> removed. It is part of the attribute map (mod) but not present in the conn entry (ref. Null Value Behavior).	528
CTGDIS053I (Modify) Attribute <i>attribute name</i> included in modify operation.	528
CTGDIS054E Connector is not configured to add Entries.	529
CTGDIS055I Loading user jars from <i>path</i> . . .	529
CTGDIS056I Trigger <i>trigger name</i> was not handled, call default handler.	529
CTGDIS057I Hook <i>hook name</i> not enabled. . .	529
CTGDIS058I Connector <i>Connector name</i> inherits from <i>Connector name</i>	529
CTGDIS059I Virtual Connector provided. . .	530
CTGDIS060W No Connector provided for runtime Connector.	530
CTGDIS061I Reuse Connector <i>Connector name</i> .	530
CTGDIS062I Cannot load Connector <i>Connector name</i>	530
CTGDIS063I Using advanced link criteria (script).	530
CTGDIS064I Loading Attribute Map.	530
CTGDIS065I Load Hooks.	531
CTGDIS066W No link criteria configured.	531
CTGDIS067E Unable to find configuration for AssemblyLine <i>AssemblyLine name</i>	531
CTGDIS068E Unknown object class passed as parameter to AssemblyLine: <i>AssemblyLine name</i>	531
CTGDIS069I Loading Connectors.	532
CTGDIS070I Finished loading Connectors. . .	532
CTGDIS071I Entering TaskCallBlock. . . .	532
CTGDIS072I Succeeded entering TaskCallBlock.	532
CTGDIS073I Initializing Connectors. . . .	532
CTGDIS074I Finished initializing Connectors.	533

CTGDIS075I Trying to exit TaskCallBlock.	533	CTGDIS113I The Epilog	540
CTGDIS076I Succeeded exiting TaskCallBlock.	533	CTGDIS114I The Shutdown hook	540
CTGDIS077I Failed with error: <i>error</i>	533	CTGDIS115I Starting scripting hook of type	
CTGDIS078I AssemblyLine <i>AssemblyLine name</i>		<i>operation</i>	540
failed with error: <i>error</i>	533	CTGDIS116I Scripting hook of type <i>operation</i>	
CTGDIS079I AssemblyLine <i>AssemblyLine name</i>		finished.	541
terminated successfully.	534	CTGDIS117I Execute script for <i>component</i>	
CTGDIS080I Terminated successfully (<i>number</i>		<i>hook</i>	541
<i>of errors errors</i>).	534	CTGDIS118I Script execution failed.	541
CTGDIS081I AssemblyLine component <i>component</i>		CTGDIS119I The script <i>wasscript name</i>	541
<i>name</i> disabled by configuration.	534	CTGDIS120I Include from Script Library	
CTGDIS082I Load: <i>component name</i>	534	disabled by configuration.	541
CTGDIS083I While loading Connector		CTGDIS121I Expecting String for	
<i>Connector name</i>	534	AttributeMap, got <i>value</i>	542
CTGDIS084I Initialization of <i>component name</i>		CTGDIS122I Printing attribute map:	
failed: <i>error</i>	535	<i>attribute name attribute name</i>	542
CTGDIS085I Initializing Component <i>component</i>		CTGDIS123I Returned object class <i>class</i>	
<i>name</i>	535	<i>name</i>	542
CTGDIS086I No iterator in AssemblyLine,		CTGDIS124I Copying file " <i>source file</i> " to	
will run single pass only.	535	file " <i>destination file</i> ".	542
CTGDIS087I Iterating.	535	CTGDIS126I Return <i>return value</i>	542
CTGDIS088I Finished iterating.	535	CTGDIS127I Null Behavior for <i>value: value</i>	543
CTGDIS089I Current statistics:		CTGDIS128E Cannot find AssemblyLine	
Interval= <i>interval</i> , Maximum Errors= <i>max</i>		<i>AssemblyLine name</i>	543
errors, Maximum Read= <i>max read</i>	536	CTGDIS129I No config entry for Component	
CTGDIS090I Task specified maximum number of		<i>component name</i>	543
errors encountered: <i>max errors</i>	536	CTGDIS131I Delta Sequence now at <i>sequence</i>	
CTGDIS091I Ending AssemblyLine after		<i>ID</i>	543
reaching maximum number of entries to read:		CTGDIS140E Unable to decrypt the file.	
<i>max errors</i>	536	Either no password was specified or the	
CTGDIS092I Using runtime provided entry as		password specified is not correct.	543
working entry (first pass only).	536	CTGDIS141I Load properties from <i>file name</i>	544
CTGDIS093I Switching to iterator <i>iterator</i>		CTGDIS142I Error while loading <i>file name</i> ,	
<i>name</i>	536	exception is <i>message</i>	544
CTGDIS094I Skip input entry.	537	CTGDIS143E No criteria can be built from	
CTGDIS095I Ignore entry.	537	input (no link criteria specified).	544
CTGDIS096I Restarting entry from iterator		CTGDIS144E No such AssemblyLine:	
(potential loop).	537	<i>AssemblyLine name</i>	544
CTGDIS097I Skip to <i>message</i>	537	CTGDIS145E TCB: Missing required parameter	
CTGDIS098I Abort AssemblyLine requested:		<i>parameter name</i>	544
<i>message</i>	537	CTGDIS147E TCB:Wrong accumulator object	
CTGDIS099I <i>number of entries</i> entries		type <i>object type</i>	545
processed	538	CTGDIS148I Setting Connector parameters.	545
CTGDIS100I Printing the Connector		CTGDIS149I Finished setting Connector	
statistics.	538	parameters.	545
CTGDIS101I Finished printing the Connector		CTGDIS150I Changing parameters for	
statistics.	538	<i>component name</i>	545
CTGDIS103I No statistics.	538	CTGDIS151I Setting parameter <i>key</i>	545
CTGDIS104I Total: <i>total</i>	538	CTGDIS152I Building TCB entry.	546
CTGDIS105I Set parameter <i>parameter name</i> to		CTGDIS153I Finished building TCB entry.	546
<i>parameter value</i>	539	CTGDIS156E Input Attribute <i>attribute name</i>	
CTGDIS106I Wrote parameter <i>parameter name</i>		is required, but not present.	546
to <i>parameter value</i>	539	CTGDIS157E Output Attribute <i>attribute name</i>	
CTGDIS108E Bad number for <i>component name</i>		is required, but not present.	546
parameter: <i>parameter name</i>	539	CTGDIS158I Registering Script Beans.	546
CTGDIS109I Declare Connector bean as <i>name</i>	539	CTGDIS159E This Connector has no	
CTGDIS110I No script for <i>hook name</i>	539	configured Parser.	547
CTGDIS111I The Prolog before initialization		CTGDIS160E Connector does not support	
of Connectors.	540	<i>getNextEntry</i>	547
CTGDIS112I The Prolog after initialization		CTGDIS161E Connector does not support	
of Connectors.	540	<i>modEntry</i>	547

CTGDIS162E Connector does not support deleteEntry.	547
CTGDIS163E Connector does not support findEntry.	548
CTGDIS164E Connector does not support putEntry.	548
CTGDIS165E Connector does not support queryReply.	548
CTGDIS167E Connector does not support queryTables.	548
CTGDIS168E Pipe with name <i>pipe name</i> already exists.	548
CTGDIS169E No value specified.	549
CTGDIS170E The memory queue pipe is full.	549
CTGDIS171E Error calculating threshold.	549
CTGDIS172E Error while initializing system store for paging support.	549
CTGDIS173E The MemBufferQ Callback could not be found.	549
CTGDIS174I Config Instance <i>Config name</i> exited with status <i>return code</i>	550
CTGDIS175I Non delta-entry provided in update mode with use-delta on.	550
CTGDIS176I Delta-entry provided in normal update mode.	550
CTGDIS179E Error while saving the task parameters.	550
CTGDIS180E Error while restoring the task parameters.	550
CTGDIS181E Error while evaluating Hook ' <i>Hook name</i> ' in the Component ' <i>Component name</i> ' (<i>Internal Hook name</i>).	551
CTGDIS182E Error while registering the JSE Provider <i>provider name</i>	551
CTGDIS183E Error while mapping attribute ' <i>attribute name</i> ' in the <i>MapName</i> Attribute Map of Component ' <i>component name</i> ' (<i>internal name</i>).	551
CTGDIS184E This AssemblyLine was invoked with operation ' <i>operation</i> ', which does not match any of the defined operations for this AssemblyLine.	551
CTGDIS185I Cannot load pooled Connector: <i>Connector name</i> . Pool not found.	552
CTGDIS186I Could not get Connector from pool: <i>Connector name</i>	552
CTGDIS187I Loaded <i>Connector name</i> , <i>Connector version</i>	552
CTGDIS188E An error has occurred while starting the Derby network server: <i>exception</i>	552
CTGDIS189E Cannot find AssemblyLine with name ' <i>AssemblyLine name</i> '.	552
CTGDIS191E TaskCallBlock (TCB) does not name an AssemblyLine.	553
CTGDIS192E An error has occurred while terminating Connector Pool: <i>exception</i>	553
CTGDIS193E An error has occurred on Connector Pool initialization: <i>exception</i>	553
CTGDIS194E Could not create Connector Pool for Connector ' <i>Connector name</i> '. Exception occurred: <i>exception</i>	553

CTGDIS195E An error has occurred while executing server hook file ' <i>file name</i> ': <i>exception</i>	553
CTGDIS196E Config or group name is not specified.	554
CTGDIS197E Config instance with name ' <i>Config name</i> ' is already running.	554
CTGDIS198E getServer(): an error has occurred while trying to obtain the RS context: <i>exception</i>	554
CTGDIS199E Error has occurred while initializing the server Hooks: <i>exception</i>	554
CTGDIS200E An error has occurred while reading the stash file: <i>exception</i>	554
CTGDIS201E No password has been found in the Server stash file.	555
CTGDIS202E Could not set up the Server keystore password info. Exception occurred: <i>exception</i>	555
CTGDIS203E Unable to find EventHandler configuration for the name: <i>EventHandler name</i>	555
CTGDIS204E AutoStart Folder: an exception occurred while finding/loading autostart element with name ' <i>name</i> ': <i>exception</i>	555
CTGDIS205E AutoStart Folder: Do not know how to start component: <i>name</i>	555
CTGDIS206W An error has occurred on Remote Server API initialization: <i>exception</i>	556
CTGDIS207W The Remote Server API engine is not started.	556
CTGDIS208W An error has occurred on Remote JMX initialization: <i>exception</i>	556
CTGDIS209W The Remote JMX Server Connector is not started.	556
CTGDIS210W An error has occurred on Server API initialization: <i>exception</i>	556
CTGDIS211W Server API engine is not started.	557
CTGDIS212W The ' <i>property name</i> ' external property is already specified and will be overwritten.	557
CTGDIS213W No external file is specified in [-f] parameter.	557
CTGDIS214W There is no such property store ' <i>property store name</i> ' in ' <i>Config ID</i> ' configuration.	557
CTGDIS215W An error has occurred while processing command line parameter [-f].	557
CTGDIS216W An error has occurred while decrypting protected property: <i>exception</i>	558
CTGDIS217W An error has occurred while encrypting protected property ' <i>property name</i> ' in file ' <i>file name</i> ': <i>exception</i>	558
CTGDIS218W An error has occurred while rewriting the properties file: <i>exception</i>	558
CTGDIS219W An error has occurred while calling server hook ' <i>hook name</i> ': <i>exception</i>	558
CTGDIS220W An error has occurred while unregistering the server with the Server API: <i>exception</i>	558

CTGDIS221W An error has occurred while registering the server with the Server API: <i>exception</i>	559	CTGDIS251I Completed iterator ' <i>iterator name</i> ' is not initialized.	565
CTGDIS222W Server security has not been initialized.	559	CTGDIS253E Server Connector <i>Connector name</i> could not be terminated. Exception occurred: <i>exception</i>	565
CTGDIS223W Server PKI encryption and secure remote Server API communication cannot be used.	559	CTGDIS254I Adding reply channel for Connector: <i>Connector name</i>	565
CTGDIS224I No autoloading directory is configured (com.ibm.di.server.autoload).	559	CTGDIS255I AssemblyLine <i>AssemblyLine name</i> is started.	565
CTGDIS225I The specified path is not a directory: <i>directory</i>	559	CTGDIS256I AssemblyLine <i>AssemblyLine name</i> is started, recording to: <i>sandbox identifier</i>	565
CTGDIS226I Looking for *.xml files in directory: <i>directory</i>	560	CTGDIS257I AssemblyLine <i>AssemblyLine name</i> is started, playing back from: <i>sandbox identifier</i>	566
CTGDIS227I Autoloading Config file: <i>file name</i>	560	CTGDIS258I AssemblyLine <i>AssemblyLine name</i> is started in manual mode.	566
CTGDIS228I Unregister server: <i>server name</i>	560	CTGDIS263E Only callable when AssemblyLine was started in Cycle mode.	566
CTGDIS229I Register server: <i>server name</i>	560	CTGDIS264E This AssemblyLine was not started in 'Cycle' mode.	566
CTGDIS230I JVM ShutDown Hook has been added: ' <i>hook</i> '.	560	CTGDIS265E Cannot execute beyond end-of-iteration.	567
CTGDIS231I Server is running in secure mode.	561	CTGDIS266E Error in <i>AssemblyLine step</i> . Exception occurred: <i>exception</i>	567
CTGDIS232I Server is running in standard mode.	561	CTGDIS269I Skipping to response section.	567
CTGDIS233I Server instance for the following configuration is starting: <i>Config name</i>	561	CTGDIS271I Restarting entry from <i>message</i>	567
CTGDIS234I IDI Server is entering daemon mode.	561	CTGDIS272I Retrying operation in <i>message</i>	567
CTGDIS235I An error has occurred while sending server shutdown event: <i>exception</i>	561	CTGDIS273I Ignoring entry in <i>message</i>	568
CTGDIS236I The stash file has been successfully read.	562	CTGDIS274I Skipping entry from <i>message</i>	568
CTGDIS237I The key password is not present in the stash file. The keystore password will be used.	562	CTGDIS275I Inside exitBranch method: current component= <i>component name</i> ; branch= <i>branch name</i> ; data flow= <i>boolean</i>	568
CTGDIS238I Server security has been successfully initialized.	562	CTGDIS276I exitBranch: exitFlow	568
CTGDIS239I ' <i>file</i> ' was created from ' <i>source</i> '.	562	CTGDIS277I Exit AssemblyLine requested.	568
CTGDIS240I Copying SERVERAPI files from ' <i>directory</i> '.	562	CTGDIS278E Cannot locate branch <i>branch name</i> in the context of component <i>component name</i>	569
CTGDIS241I All threads have been stopped.	563	CTGDIS279E Cannot locate loop <i>loop name</i> in the context of component <i>component name</i>	569
CTGDIS242I User: <i>object</i>	563	CTGDIS280I Switch to next iterator.	569
CTGDIS243I Loaded EventHandler <i>class name</i> : <i>version</i>	563	CTGDIS281E Error caused by: <i>exception</i>	569
CTGDIS244E Bad run mode value: <i>run mode</i>	563	CTGDIS283E EventHandlers are no longer a feature of 6.0. Remove them for your solution.	569
CTGDIS245E Unable to interpret ' <i>parameter</i> ' as a run AssemblyLine parameter.	563	CTGDIS284I Draining Connector: <i>Connector name</i>	570
CTGDIS246W Unknown object class passed as parameter to start AssemblyLine: <i>class name</i>	564	CTGDIS285I Connector drained: <i>Connector name</i>	570
CTGDIS247E Connector not defined: ' <i>Connector name</i> '.	564	CTGDIS286I Waiting for AssemblyLine pool to terminate.	570
CTGDIS248E Not an EntryFeed mode Connector: <i>Connector name</i> : <i>Connector mode</i>	564	CTGDIS287I [Performance]: <i>performance record</i>	570
CTGDIS249E Unknown Connector name: <i>Connector name</i>	564	CTGDIS288I Draining the Connector. The entry mode is set to <i>boolean</i>	570
CTGDIS250W Problem when declaring <i>name</i> , possibly illegal name.	564	CTGDIS290I Property ' <i>property name</i> ' is undefined, using: <i>property name</i>	571
		CTGDIS291E Invalid thread mode value: <i>thread mode (integer-integer)</i>	571

CTGDIS292I AssemblyLine pool: initialize:
 preload=*preloaded AssemblyLine*, max
 concurrent=*integer*. 571
 CTGDIS293I AssemblyLine pool: Connector
 pool timeout: *timeout*. 571
 CTGDIS294I AssemblyLine pool: Connector
 pooling is disabled. 571
 CTGDIS295I AssemblyLine pool: Save runtime
 Connectors: *AssemblyLine*. 572
 CTGDIS296I AssemblyLine pool: null function
 not pooled. 572
 CTGDIS297I AssemblyLine pool: null
 Connector not pooled. 572
 CTGDIS298I AssemblyLine pool: Connector
 type *class name* is excluded. 572
 CTGDIS299I AssemblyLine pool: adding to
 pool: name=*component name*; type=*class name*. 572
 CTGDIS300I AssemblyLine pool: reuse
 PooledConnectorSet object. 573
 CTGDIS301I AssemblyLine pool:
 garbageCollectPool: pool timeout disabled. . 573
 CTGDIS302I AssemblyLine pool: Connector
 pool size = *size*. 573
 CTGDIS303I AssemblyLine pool: removing
 PooledConnectorSet object. 573
 CTGDIS304I AssemblyLine pool:
 getAssemblyline: wait for release. 574
 CTGDIS305I AssemblyLine pool: preparing
 AssemblyLine: *AssemblyLine*. 574
 CTGDIS306I AssemblyLine pool: Adding pooled
 runtime Connector: *Connector name*. 574
 CTGDIS307I AssemblyLine pool: AssemblyLine
 worker thread: *worker name*: active=*boolean*. 574
 CTGDIS308E AssemblyLine pool termination
 is pending. 574
 CTGDIS309I executeEvent: *hash code*, event:
event, threadMode: *thread mode*. 575
 CTGDIS310I AssemblyLine worker thread:
thread name is started. 575
 CTGDIS311I -- add runtime Connector:
Connector name. 575
 CTGDIS312I -- add runtime Connector config:
Config name. 575
 CTGDIS313I exitBranch: skipping to:
AssemblyLine component 575
 CTGDIS314I -- executeCycle: *work entry*. . . 576
 CTGDIS315I AssemblyLine worker thread:
thread name is stopped. 576
 CTGDIS316I AssemblyLine pool:
 ConnectorPool: close Connector: *Connector
 name*; *class name*. 576
 CTGDIS317I AssemblyLine pool:
 ConnectorPool: close function: *Connector
 name*; *class name*. 576
 CTGDIS318I AssemblyLine pool: PoolTimer:
 garbageCollectPool. 577
 CTGDIS319E Connector Library name is NULL. 577
 CTGDIS320E Connector Pool Definition
 Config is NULL for Connector: *Connector
 name*. 577

CTGDIS321E Connector Pool is not enabled
 for Connector: *Connector name*. 577
 CTGDIS322E Connector Pool Log is NULL for
 Connector: *Connector name*. 577
 CTGDIS323E Invalid max pool size for
 Connector *Connector name*: *pool size*. . . . 578
 CTGDIS324W Minimum Connector pool size
 exceeds the maximum size: *pool size*;
Connector name. 578
 CTGDIS325W Minimum Connector pool size is
 set to the maximum value: *pool size*;
Connector name. 578
 CTGDIS326W Invalid initialize attempts
 number: *number of attempts*; *Connector name*. 578
 CTGDIS327W Initialize attempts set to:
number of attempts; *Connector name*. . . . 578
 CTGDIS328W Invalid initialize sleep
 interval: *time interval*; *Connector name*. . 579
 CTGDIS329W Initialize sleep interval set
 to: *time interval*; *Connector name*. 579
 CTGDIS330E Error on preparing Connector
 Pool instance for Connector *Connector name*.
 Exception occurred: *exception* 579
 CTGDIS331I Pool shrinker thread started
 for: *Connector name*; purge interval: *time
 interval*. 579
 CTGDIS332I *Connector name* Connector Pool is
 initialized. Prepared instances: *pool size*. 580
 CTGDIS333E Error terminating Connector:
exception 580
 CTGDIS334I *Connector name* Connector Pool is
 terminated. 580
 CTGDIS335E Connector Pool is not
 initialized: *Connector name*. 580
 CTGDIS336E Connector Pool reached its
 maximum size: *Connector name*. 580
 CTGDIS337I Connector added to pool:
Connector name; new pool size: *pool size*;
 free Connectors: *integer*. 581
 CTGDIS338I InterruptedException while
 waiting for free Connector: *exception* . . . 581
 CTGDIS339I Connector taken from pool:
Connector name; pool size: *pool size*; free
 Connectors: *integer*. 581
 CTGDIS340I Connector added to pool on
 request: *Connector name*; pool size: *pool
 size*; free Connectors: *integer*. 581
 CTGDIS341I Connector returned to pool:
Connector name; pool size: *pool size*; free
 Connectors: *integer*. 581
 CTGDIS342I Connector returned to pool after
 pool termination: *Connector name*; pool size:
pool size. 582
 CTGDIS343E Error initializing Connector on
 attempt *attempt number*: *exception* 582
 CTGDIS344I InterruptedException on
 Connector initialize attempt: *exception* . . 582
 CTGDIS345E Could not initialize pooled
 Connector *Connector Name* after *number of
 attempts* attempts. 582

CTGDIS346I New pooled Connector created: <i>Connector name</i>	582	CTGDIS378I Error in migratetable.syspros. Exception occurred: <i>exception</i>	589
CTGDIS347I Connector pool purge: <i>Connector name</i> ; old size/free: <i>pool size/integer</i> ; new size/free: <i>pool size/integer</i>	583	CTGDIS379I Exception occurred while migrating delta tables: <i>exception</i>	589
CTGDIS348E Null configuration for attribute map.	583	CTGDIS380I Migrating Delta Tables.	589
CTGDIS349E Null configuration for Hooks.	583	CTGDIS381I Error in renaming table. The table does not exist. Exception occurred: <i>exception</i>	590
CTGDIS350I Hook <i>hook name</i> [<i>counter</i>].	583	CTGDIS382I Finished Migrating Delta Tables.	590
CTGDIS351I Map Attribute <i>attribute name</i> [<i>counter</i>].	583	CTGDIS383E Cannot get local namespace for: <i>namespace</i>	590
CTGDIS352I Use null Behavior for <i>attribute name</i>	584	CTGDIS384I Finished including all scripts from the script library where auto-include is true in the <i>Config name</i> Config.	590
CTGDIS353I Script is: <i>script_mapping</i>	584	CTGDIS385I -- Include script: <i>script</i>	590
CTGDIS354E The key store password is NULL or empty.	584	CTGDIS386I Including all scripts from the script library where auto-include is true in the <i>Config name</i> config.	591
CTGDIS355E Stash file already read.	584	CTGDIS387E No such script: <i>script</i> (included by <i>context name</i>)	591
CTGDIS356E Stash file <i>file name</i> not found in solution folder.	584	CTGDIS388I Dump of JSEngine global variables	591
CTGDIS357E Input Stream is NULL.	585	CTGDIS389E ' <i>function</i> ' is not a function	591
CTGDIS358E The key password or keystore password failed a size validation check. Unable to read in the key password or the keystore password from the stash file.	585	CTGDIS390E Function <i>function name</i> not found.	591
CTGDIS359E Output Stream is NULL.	585	CTGDIS391E No functions defined.	592
CTGDIS360E Byte array is NULL.	585	CTGDIS392E The system.deleteFile(...) tried to delete a directory and failed. Supplied file path: <i>file path</i>	592
CTGDIS361E Encrypted password data too long: <i>length</i>	585	CTGDIS393I Throwing this exception to tell the AssemblyLine to skip the current Entry. If used in an EventHandler, this exception tells the EventHandler to skip the remaining actions.	592
CTGDIS362I Stash file <i>file name</i> has been created.	586	CTGDIS394I Created file <i>file name</i>	592
CTGDIS363E Could not create stash file. Exception occurred: <i>exception</i>	586	CTGDIS395I Do not overwrite existing file <i>file name</i>	592
CTGDIS364I Usage: createstash keyStorePassword [<i>keyPassword</i> [<i>securityProviderClass</i>]]	586	CTGDIS396I Do not copy directory <i>directory</i>	593
CTGDIS365E Expecting CRLF after javascript expression start.	586	CTGDIS397E Cannot create directory: <i>directory</i>	593
CTGDIS366E Cannot find javascript terminator line: <i>string</i>	586	CTGDIS398I Created directory: <i>directory</i>	593
CTGDIS367E Bad index specification (missing end bracket) in: <i>name</i>	587	CTGDIS399I Unable to send mail.Exception occurred: <i>messaging_exception</i>	593
CTGDIS368E Unable to index the class <i>class name</i>	587	CTGDIS400E Bad number in com.ibm.di.server.rotatologs: ' <i>parameter value</i> '.	593
CTGDIS369E No MetamergeConfig (mc) or Config object provided.	587	CTGDIS401I declareUserFunctions: <i>key</i> as <i>class name</i>	594
CTGDIS370I Error decrypting password. Exception occurred: <i>exception</i>	587	CTGDIS402E No 'class' parameter in EventHandler configuration.	594
CTGDIS371I Table <i>table name</i> does not exist. Will try to create.	588	CTGDIS403I Function ' <i>Config name</i> ' in ' <i>thread name</i> ' will be state.	594
CTGDIS372I Table <i>table name</i> has been successfully created.	588	CTGDIS404I Connector ' <i>Config name</i> ' in ' <i>thread name</i> ' will be state.	594
CTGDIS373I Database shutdown not performed (non-embedded database).	588	CTGDIS405E Deprecated Connector: com.ibm.di.connector.ConsumerProducer.	594
CTGDIS374I Database shutdown ignored for: <i>database name</i>	588	CTGDIS406E The loadConnector method cannot find 'connectorType' or 'class' parameter in configuration.	595
CTGDIS375I Database <i>database name</i> retained.	588	CTGDIS407E Cannot get configuration for Connector: <i>Connector name</i>	595
CTGDIS376I Shutting down database: <i>database name</i>	589		
CTGDIS377I Renamed table IDI_SYSPROPS to IDI_PS_DEFAULT.	589		

CTGDIS408E The loadParser method cannot find 'class' parameter in configuration.	595	CTGDIS444I Applying Parser: input stream <i>class name</i>	602
CTGDIS409E Cannot get configuration for Parser: <i>Parser name</i>	595	CTGDIS445I Applying Parser: <i>Parser name</i>	603
CTGDIS410I Creating sandbox store: <i>identifier</i>	596	CTGDIS446E No EventHandler specified for this action.	603
CTGDIS411W Error on firing eventProcessed method on EventHandler Listener: <i>exception</i>	596	CTGDIS447E No AssemblyLine specified for this action.	603
CTGDIS412W Exception in dispatchEvent: <i>exception</i>	596	CTGDIS448I The executeAction will execute action <i>action</i>	603
CTGDIS413I Terminate Signal: skip all actions and terminate Handler.	596	CTGDIS449I Execute actions in Condition <i>condition</i>	603
CTGDIS414E Action not found. SkipToException occurred: <i>exception</i>	596	CTGDIS450I Switchboard Action: Execute error handlers.	603
CTGDIS415I SkipToException <i>exception</i> found at index <i>index</i>	597	CTGDIS451W Switchboard Action: No error handlers.	604
CTGDIS416I SkipToException occurred: <i>exception</i>	597	CTGDIS452E Key not found: <i>key</i>	604
CTGDIS417I Ignore Entry: continue with next action.	597	CTGDIS453E Bad node index <i>index</i>	604
CTGDIS418I Restart Entry.	597	CTGDIS454E Expected a DBNode object but the following object was encountered: <i>node name</i>	604
CTGDIS419I Skip Entry: skip rest of actions.	597	CTGDIS455E Duplicate key: <i>key</i>	604
CTGDIS420I Action did not match criteria.	598	CTGDIS456W Failed to write entry to the B-Tree database.	605
CTGDIS421I Action: <i>Switchboard Action</i> not matched.	598	CTGDIS457E Undefined type of interface.	605
CTGDIS422I Execute Action.	598	CTGDIS458E Cannot convert to VARIANT.	605
CTGDIS423I Unable to dispatch the event because the <i>component type</i> is not initialized and is NULL.	598	CTGDIS459E IDispatch object expected.	605
CTGDIS424W Error on firing eventCaptured method on EventHandler Listener: <i>exception</i>	598	CTGDIS480E EntryFilter has no script engine instance to execute scripts.	605
CTGDIS425I Finished dumping EventHandler properties.	599	CTGDIS481E 'fmatch' function did not return a boolean value.	606
CTGDIS426I key: <i>key</i> , <i>property</i>	599	CTGDIS482E No such method ' <i>method name</i> '.	606
CTGDIS427I Dumping EventHandler properties.	599	CTGDIS483E Function has not been initialized.	606
CTGDIS428I Finished including Script Library.	599	CTGDIS484I Connector <i>class name: version</i>	606
CTGDIS429I Including Script Library.	599	CTGDIS485I Parser <i>class name: version number</i>	606
CTGDIS430W Cannot load script engine. Exception occurred: <i>exception</i>	600	CTGDIS486I Do not initialize a (runtime provided) Connector.	607
CTGDIS431W Error creating logger in <i>parameter name</i> . Exception occurred: <i>exception</i>	600	CTGDIS487I Skipping <i>number of entries</i> entries for iterator: <i>Connector name</i>	607
CTGDIS432I Normal Termination.	600	CTGDIS488E Non delta entry received in Delta mode.	607
CTGDIS433I Terminated with errors.	600	CTGDIS489I Ignoring non-delta entry in Delta mode.	607
CTGDIS434W Debugger: <i>exception</i>	600	CTGDIS490I Generated new-style delta entry from delta.old property.	607
CTGDIS435I EventHandler Terminating.	601	CTGDIS491I Original delta entry	608
CTGDIS436I ExitHook: <i>exception</i>	601	CTGDIS492I New delta entry	608
CTGDIS437I Interceptor.stop: <i>exception</i>	601	CTGDIS493I Delta Operation: <i>operation</i>	608
CTGDIS438I <i>thread name</i> will record all events.	601	CTGDIS494I Entry found, calling delete method.	608
CTGDIS439I Parser output stream class: <i>class name</i>	601	CTGDIS495I handleException , <i>operation</i> , <i>exception</i>	608
CTGDIS440I Null value for Parser output stream.	602	CTGDIS496E Automatic Reconnect.	609
CTGDIS441I Parser input stream class: <i>class name</i>	602	CTGDIS497W Cannot find the java class for <i>component</i> . The jar file may be corrupted, or a file may have been deleted.	609
CTGDIS442I Call Parser for: <i>Parser mode</i>	602	CTGDIS498I Using provided parameter.	609
CTGDIS443I Applying Parser: output stream <i>class name</i>	602	CTGDIS503E No values to add.	609
		CTGDIS504I *Result of attribute mapping*	609
		CTGDIS505I The 'conn' object	610

CTGDIS506I The 'work' object	610	CTGDIS535E Unable to decrypt the string because it was not in the proper format. The required string format is 'length of encrypted data/space_character/encrypted data'.	616
CTGDIS507I The 'current' object	610	CTGDIS536E Conditional script did not do 'ret.value=true false'.	616
CTGDIS508E Invalid component type specified for JLOGAppender: ' <i>component type</i> '. The only valid values are 'AL' and 'EH'.	610	CTGDIS537E Invalid return value: <i>value (class name)</i>	616
CTGDIS509E No component type assigned to MOBJ appender.	610	CTGDIS538E NULL attribute name in condition number + index ' <i>index</i> '.	616
CTGDIS510I Activate the jlog options...	611	CTGDIS541I branch-end: setNextConnector: <i>branch component</i>	617
CTGDIS511I Component type has not been specified.	611	CTGDIS542I loop-end: setNextConnector: <i>component</i>	617
CTGDIS512I JLogHandler: component name has not been specified.	611	CTGDIS543E Cannot set next Connector.	617
CTGDIS513I JLogHandler: log pattern has not been specified.	611	CTGDIS544E Parsing error on line <i>line_number</i> . Last line was: <i>line</i> . Error is <i>error</i>	617
CTGDIS514W Could not generate log file name. Exception occurred: <i>exception</i>	611	CTGDIS545E Parsing error at <i>URL</i> on line <i>line_number</i> . Last line was: <i>line</i> . Error is <i>error</i>	617
CTGDIS515W Exception occurred while saving jlog.properties: <i>exception</i>	612	CTGDIS546E Unexpected line: <i>line</i>	618
CTGDIS516E No component type assigned to JLOG appender.	612	CTGDIS547I Do not initialize a (runtime provided) function	618
CTGDIS517E Unsupported appender: <i>appender</i>	612	CTGDIS548E Function returned non-Entry/Attribute object in AssemblyLine and no default attribute name defined: <i>class name=object</i>	618
CTGDIS518W Cannot create appender: <i>appender</i> Exception occurred: <i>exception</i>	612	CTGDIS549I Initialize loop component: <i>loop type</i>	618
CTGDIS519W Error initializing custom appender: <i>appender</i> Exception occurred: <i>exception</i>	612	CTGDIS550E No work Entry Attribute name specified for the Attribute Loop.	618
CTGDIS520W <i>appender</i> : Parameter value for <i>parameter ('value')</i> must be a positive integer.	613	CTGDIS551E No loop Entry Attribute name specified for attribute loop	619
CTGDIS521W <i>appender</i> : Parameter value for <i>parameter ('value')</i> must be a known hostname.	613	CTGDIS552I checkConnectorInit: <i>work entry</i>	619
CTGDIS522W <i>appender</i> : No method to set Parameter value for <i>parameter ('value')</i>	613	CTGDIS553I Begining of setConnectorParams method	619
CTGDIS523W Parser will use default encoding. UnsupportedEncodingException occurred while setting the character set: <i>exception</i>	613	CTGDIS554I -- setting Connector parameter: name= <i>parameter name</i> , value= <i>parameter value</i>	619
CTGDIS524I Closing Parser on input stream.	613	CTGDIS555E Reply Channel: Target component is null.	620
CTGDIS525I Closing Parser on output stream.	614	CTGDIS556I SWITCH <i>component name</i> : ' <i>expression</i> '.	620
CTGDIS526W Closing Parser: <i>exception</i>	614	CTGDIS557I CASE: <i>component name''expression''</i> == ' <i>expression</i> '.	620
CTGDIS527W EntryList::AddEntry: PerfEntry null.	614	CTGDIS564I The delta SQL1 is: <i>SQL statement</i>	620
CTGDIS528W Entry Already Exists. Entry Not added <i>entry</i>	614	CTGDIS565E Invalid DeltaStore identifier: <i>ID</i>	620
CTGDIS529I *****	614	CTGDIS566E Update sequence for key: <i>key</i> , update count != 1 (count = <i>count</i>).	621
CTGDIS530I Current instance name: <i>instance name</i>	615	CTGDIS567E Update entry for key: <i>key</i> , update count != 1 (count = <i>count</i>)	621
CTGDIS531I Not all required system store properties have been defined. The memory queue initialization will be done using system store default values.	615	CTGDIS568E Insert entry for key: <i>key</i> , update count != 1 (count = <i>count</i>).	621
CTGDIS532E Bad signature in input stream.	615	CTGDIS569E Duplicate delta key: <i>key</i>	621
CTGDIS533E Invalid encrypted signature in input stream.	615	CTGDIS570E Delete entry for key: <i>key</i> , update count != 1 (count = <i>count</i>).	621
CTGDIS534E Exception occurred while reading line: <i>exception</i>	616		

CTGDIS571E The getNextDeletedEntry method was called without prior selectDeletedEntries method call.	622
CTGDIS572E Incompatible version in <i>table name</i>	622
CTGDIS573E Must specify table.	622
CTGDIS574E Cannot put NULL value for key: <i>key</i>	622
CTGDIS582E <i>name: exception</i>	622
CTGDIS583W Initializing script engine.	623
CTGDIS584I Cannot load log-appender: <i>error</i>	623
CTGDIS585I Including all scripts from the Script Library marked for auto-include.	623
CTGDIS586I Finished including all scripts from the Script Library marked for auto-include.	623
CTGDIS587E XML document has no root.	623
CTGDIS588E Expected child item at index <i>index</i>	624
CTGDIS589I Connect to <i>server name: port</i>	624
CTGDIS590E Process stopped by debugger.	624
CTGDIS591E Call to <i>name</i> but no more calls recorded in table <i>table</i>	624
CTGDIS592E Call to <i>name</i> but next recorded method was: <i>method</i>	624
CTGDIS593E Internal IDI proxy object exception: <i>exception</i>	625
CTGDIS594I Recording Connector calls to table <i>table name</i> in database <i>database name</i>	625
CTGDIS595I Reading Connector calls from table <i>table name</i> in database <i>database name</i>	625
CTGDIS596E The nibble was unable to parse a hexadecimal digit: ' <i>symbol</i> '.	625
CTGDIS597E Error in releasing License: <i>exception</i>	625
CTGDIS598E No Valid License was found. Server exiting...	626
CTGDIS599E Not enough capacity was found. Server exiting...	626
CTGDIS600E Cannot contact IBM Tivoli License Manager Server. Server exiting...	626
CTGDIS601E An internal error occurred while using the IBM Tivoli License Manager Toolkit. Contact IBM support.	626
CTGDIS602E Invalid parameter exception occurred while using the IBM Tivoli License Manager Toolkit. The server is exiting...	627
CTGDIS603E Error in retrieving License : <i>exception</i>	627
CTGDIS604I ***	627

CTGDIS605I Usage: ibmdisrv [OPTION]... Allowable options are: -c <file ...> Configuration files. Loading multiple files requires the -d option. -d Run in daemon mode -d close Run in daemon mode, and close standard output and standard error when ready to accept commands -e Start the Server in secure mode. -f <extProp1=file1,extProp2=file2 ...> External property files. -g Create solution directory files and exit. -i Ignore global properties file and read from solution properties file. -j <file> Read AssemblyLine regression info from the named file. -k Ignore the work Entry when reading or writing regression info. -l <file ...> Redirect Console output to specified log file. -n <encoding> Encoding to be used when writing configuration files. -p Dump java properties on startup. -q <mode> mode=1 Run in record mode, mode=2 Run in playback mode, mode=4 Run in simulate mode -r <a1 ...> List of AssemblyLine names to start. To start AssemblyLine a and b, use the command -r a b. -s <dir> Specifies the working directory where the solution is located. Must be first option. -v Show version information and exit. This is logged only in the logfile. -w Wait for each AssemblyLine to complete before starting the next. -D Disable startup of auto-started AssemblyLines. -J <file> Write AssemblyLine regression info to the named file. -M Make no modifications on the external systems. (a.k.a. Simulation Mode) -P <password> Password if configuration file is encrypted. -R Disable Remote API, ignoring the setting in global.properties. -T Enable Performance logging -W Never terminate the server -X Start Derby Network Server and exit -Y Stop Derby Network Server and exit -? This message -0 to -9 for user-defined parameters	628
CTGDIS626I Copying etc files from ' <i>directory</i> '.	628
CTGDIS627I IBM Security Directory Integrator Shutdown.	629
CTGDIS628E Error in COMProxy.dll: <i>description</i>	629
CTGDIS629I Entry found in BTree database: <i>object</i>	629
CTGDIS630I Dumping BTree database at offset <i>offset</i>	629
CTGDIS631I Btree database is empty at this offset. Total bytes used: <i>number of bytes</i>	629
CTGDIS632I Btree database size: <i>number of bytes</i>	630
CTGDIS633I Total number of bytes used: <i>number of bytes</i>	630
CTGDIS634I Btree class name: <i>class name</i>	630
CTGDIS635I Btree object string: <i>object string</i>	630

CTGDIS636I Btree database statistics for file <i>file name</i> .	630
CTGDIS637I Records in database: <i>number of records</i> .	631
CTGDIS638I Size of records: <i>record size</i> .	631
CTGDIS639I Size of smallest database record: <i>record size</i> .	631
CTGDIS640I Size of largest database record: <i>record size</i> .	631
CTGDIS641I Number of empty blocks: <i>number of blocks</i> .	631
CTGDIS642I Empty blocks size: <i>number of bytes</i> .	632
CTGDIS643I Size of smallest empty block: <i>number of bytes</i> .	632
CTGDIS644I Size of largest empty block: <i>number of bytes</i> .	632
CTGDIS645I <i>indentation white space</i> Dumping database structure. Start of a node at offset: <i>node offset</i> .	632
CTGDIS646I <i>Indentation white spaceLeft</i> node: <i>node</i> .	632
CTGDIS647I <i>Indentation white spaceLeaf</i> key: <i>leaf key</i> .	633
CTGDIS648I Database header: [Version= <i>version number</i> , Root node= <i>node</i> , Properties= <i>properties</i> , Database last modified= <i>time stamp</i>]	633
CTGDIS649E Cannot compare at level 1 without a key attribute.	633
CTGDIS650E Key attributes at level 1 are both null.	633
CTGDIS651I Dumping EventHandler event properties.	633
CTGDIS652I key: <i>key</i> , <i>property</i> .	634
CTGDIS653I Finished dumping EventHandler event properties.	634
CTGDIS654I GSM07_05: parseEntry: ' <i>entry</i> '	634
CTGDIS655I Mapping the substring <i>string</i> to the character <i>char</i> .	634
CTGDIS656I Mapped the string <i>string</i> to value <i>string</i> .	634
CTGDIS657E FileRollerAppender: Cannot delete file: <i>next</i>	635
CTGDIS658E Cannot rename file: <i>file name</i> .	635
CTGDIS659W Exception occurred while using EncryptedReader: <i>exception</i>	635
CTGDIS660W Exception occurred while using EncryptedWriter: <i>exception</i>	635
CTGDIS661I [FTPClient] Connect to <i>hostname:port</i> .	635
CTGDIS662W Exception occurred while parsing the PASV command reply: <i>exception</i>	636
CTGDIS663E Unable to retrieve the file. The file <i>file name</i> is a directory.	636
CTGDIS664E <i>file name</i> does not exist or is a directory.	636
CTGDIS665I [FTPClient] Reading directory listing.	636
CTGDIS666I [FTPClient] Directory: <i>directory name</i> .	636

CTGDIS667E The connect object is null in the run method.	637
CTGDIS668I System store not initialized...	637
CTGDIS669I [ScriptEngine] RegEx library: <i>library name</i> library.	637
CTGDIS670I [ScriptEngine] Engine last modified date: <i>date</i> .	637
CTGDIS671E Hierarchical search criteria not supported for SQL.	637
CTGDIS672E Hierarchical search criteria not supported for SimpleFilter.	638
CTGDIS673E Hierarchical search criteria not supported for Notes.	638
CTGDIS674I Main Step: <i>MAIN_STEPS[mainStep]</i> , Connector Index: <i>connectorIndex</i> , Iterator: <i>iteratorIndex</i> , Cycle: <i>cycleCounter</i>	638
CTGDIS675I Licensed Materials - Property of IBM (c) Copyright IBM Corp. 2003, 2003,2006 All Rights Reserved. US Government Users Restricted Rights - Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.	638
CTGDIS676E Branch component with no preceding IF/SWITCH component: <i>component name</i> .	639
CTGDIS677E CASE branch without preceding SWITCH or CASE component: <i>component name</i> .	639
CTGDIS678E ELSE branch without preceding IF/ELSEIF component: <i>component name</i> .	639
CTGDIS679E ELSEIF branch without preceding IF/ELSEIF component: <i>component name</i> .	639
CTGDIS680E The System Queue was not able to obtain a JMS Driver with name ' <i>driver name</i> '.	639
CTGDIS681E The System Queue was not able to obtain a Queue Connection Factory.	640
CTGDIS682E An error occurred while getting a Queue Connection Factory: <i>exception</i>	640
CTGDIS683E The System Queue was not able to obtain a queue with name ' <i>queue name</i> '	640
CTGDIS684E An error has occurred while getting a queue with name ' <i>queue name</i> ': <i>exception</i>	640
CTGDIS685E An error has occurred while receiving a message from the queue with name ' <i>queue name</i> ': <i>exception</i>	640
CTGDIS686E The object received from queue with name ' <i>queue name</i> ' is not a com.ibm.di.entry.Entry object.	641
CTGDIS687E The message received from queue with name ' <i>queue name</i> ' is not a Text Message (javax.jms.TextMessage).	641
CTGDIS688E The message received from queue with name ' <i>queue name</i> ' is not a Bytes Message (javax.jms.BytesMessage).	641
CTGDIS689E The message received from queue with name ' <i>queue name</i> ' is not an Object Message (javax.jms.ObjectMessage).	641

CTGDIS690E An error has occurred while sending a message to the queue with name 'queue name': exception	642	CTGDIS725I Usage: IDIpkcs7Crypto [-receivecertKeystore=receiverCertificateKeystoreFileName] [-receivecertKeystorePW=receiverCertificateKeystorePassword] [-receivecertAlias=receiverCertificateAlias] [-receivecertPW=receiverCertificatePassword] [-signercertKeystore=signerCertificateKeystoreFileName] [-signercertKeystorePW=signerCertificateKeystorePassword] [-signercertAlias=signerCertificateAlias] [-envelope=pkcs7EnvelopeFileName]	647
CTGDIS691E An error has occurred while creating receiver for the queue with name 'queue name': exception	642	CTGDIS726E Unknown parameter <i>parameter name</i>	647
CTGDIS692E An error has occurred while creating sender for the queue with name 'queue name': exception	642	CTGDIS727I Password Envelope specified: <i>file name</i>	647
CTGDIS693E Cannot initialize Default System Queue : exception	642	CTGDIS728I Recipient certificate keystore specified: <i>file name</i>	648
CTGDIS694E Default System Queue is not initialized.	643	CTGDIS729I Recipient Certificate Keystore Password specified: <i>keystore password</i>	648
CTGDIS695E Cannot initialize MQe System Queue.	643	CTGDIS730I Recipient Certificate Alias specified: <i>\tralias</i>	648
CTGDIS696E MQe System Queue is not initialized.	643	CTGDIS731I Recipient Certificate password specified: <i>\tpassword</i>	648
CTGDIS697E The System Queue has not been started. The IBM Security Directory Integrator server has been configured to not start the System Queue.	643	CTGDIS732I Signer Certificate Alias specified: <i>\talias</i>	648
CTGDIS698W Default System Queue is not initialized. Required property 'systemqueue.jmsdriver.name' is not set.	643	CTGDIS733I Password Value obtained: <i>password</i>	649
CTGDIS699W MQe System Queue is not initialized. Required property ' <i>parameter value</i> ' is not set.	644	CTGDIS734I Password Object Contents: <i>object</i>	649
CTGDIS705E ERROR : error	644	CTGDIS735E Exception getting ContentInfo from bytes. Detail: <i>exception</i>	649
CTGDIS706I XML document has no children: <i>tag name</i>	644	CTGDIS736I Obtaining EnvelopedData content from ContentInfo...	649
CTGDIS707I XML document has <i>number of children</i> children.	644	CTGDIS737E Error in packaged information. Expecting EnvelopedData.	649
CTGDIS708I XML Child node has no children (skipped).	644	CTGDIS738E Error in packaged information. Expecting SignedData.	650
CTGDIS709I XML Child node has no children (skipped).	644	CTGDIS739E No KeyStore certificate returned because alias specified may be invalid. Alias: <i>alias</i> KeyStore File.	650
CTGDIS710I The node does not exist. Creating a new one.	645	CTGDIS740E Error encountered while obtaining KeyStore certificate. Alias specified may be invalid. Alias: <i>alias</i> KeyStore File. Detail: <i>exception</i>	650
CTGDIS711I XML Child node has no children (skipped).	645	CTGDIS741E Error decoding password payload while obtaining sequence for DerInputStream Detail: <i>exception</i>	650
CTGDIS712E Failed to delete node. Exception occurred: <i>exception</i>	645	CTGDIS742E Error searching Recipient keystore certificates Detail: <i>exception</i>	650
CTGDIS714W SAX Parse Warning: line: <i>line number</i> , ID: <i>ID</i>	645	CTGDIS743E Exception decrypting envelopedData. Detail: <i>exception</i>	651
CTGDIS715I Usage: com.ibm.di.util.ConvertEncoding srcFile destFile srcEncoding [destEncoding]. Where destEncoding is optional; if not specified the default encoding is used.	645	CTGDIS744E Error opening signer certificate file: <i>file name</i> Detail: <i>exception</i>	651
CTGDIS718E The number of source files does not match the number of destination files.	646	CTGDIS745E Exception decrypting envelopedData obtaining aliases from KeyStore object: <i>exception</i>	651
CTGDIS719E Error constructing RacfCredential object: <i>exception</i>	646	CTGDIS746E Exception decrypting envelopedData obtaining key from KeyStore object: <i>exception</i>	651
CTGDIS720I Credential: <i>password</i> , Version: <i>version</i> , Change Time: <i>timestamp</i> , Language: <i>language</i> , Expired: <i>date</i>	646	CTGDIS747E Exception decrypting envelopedData obtaining key from KeyStore object: <i>exception</i>	651
CTGDIS721I No Connector list in task.	646		
CTGDIS724I Test program to test PKCS7 SignedData methods.	647		

CTGDIS748E SignedData does not have certificate: <i>type</i>	652	CTGDIS783I Dumping performance entry: <i>additional information: entry</i>	658
CTGDIS749E SignedData not verified with public key from certificate: <i>type</i>	652	CTGDIS784I Method parameters: <i>method parameters</i>	658
CTGDIS750E Exception occurred while verifying SignedData: <i>exception</i>	652	CTGDIS785I ---	658
CTGDIS751E Exception occurred while verifying SignedData: <i>exception</i>	652	CTGDIS786I <i>entry</i>	658
CTGDIS752E Exception occurred while verifying SignedData: <i>exception</i>	652	CTGDIS787W The AssemblyLine could not be set up.	658
CTGDIS753E Key file not found for load: <i>path</i>	653	CTGDIS788I Throwing this exception to tell the AssemblyLine to skip the current Connector and continue with the next Connector in the AssemblyLine. If used in an EventHandler, this exception tells the EventHandler to skip to the next action.	659
CTGDIS754E Error processing key file during load: <i>path</i> Verify keystore password is correctly specified. Detail: <i>exception</i>	653	CTGDIS789I Throwing this exception to tell the AssemblyLine to restart. The AssemblyLine will continue at the first non-Iterator Connector in the AssemblyLine, using the current work object. If used in an EventHandler, this exception tells the EventHandler to skip to the first action.	659
CTGDIS755E Error processing key file while obtainin KeyStore instance: Provider: <i>provider name</i> Type: <i>store type</i> Detail: <i>exception</i>	653	CTGDIS790I Throwing this exception to tell the AssemblyLine to retry this Connector. The AssemblyLine will perform the operation of the current Connector again, using the current work object.	659
CTGDIS756E The algorithm used to check the integrity of the keystore cannot be found. Detail: <i>exception</i>	653	CTGDIS791I <i>property name</i>	659
CTGDIS757E Keystore could not be loaded because the provider ' <i>provider name</i> ' was not found. Encountered an exception: <i>exception</i>	654	CTGDIS792I <i>property value</i>	660
CTGDIS758E Certificates in the keystore could not be loaded. Exception occurred: <i>exception</i>	654	CTGDIS793E Connector class is missing on the following line of the reconnect rules configuration file: <i>line</i>	660
CTGDIS761E The substitution method failed. A circular reference was found a parameter: ' <i>parameter object.parameter name</i> '.	654	CTGDIS794E Connector name is missing on the following line of the reconnect rules configuration file: <i>line</i>	660
CTGDIS766I Parameter { Pattern: <i>pattern</i> Object: <i>object</i> Name: <i>name</i> Qualifier: <i>name</i> <i>qualifier</i> Index: <i>index</i> MF Params: <i>params</i> }	654	CTGDIS795E Exception class is missing in the reconnect rules file on the following line: <i>line</i>	660
CTGDIS769I Next Parameter: <i>parameter name</i>	654	CTGDIS796E Action is missing in the reconnect rules file on the following line: <i>line</i>	661
CTGDIS770I -- <i>object</i>	655	CTGDIS797E Error while loading reconnect rules	661
CTGDIS771I <i>id: error</i>	655	CTGDIS798I Reconnect rule: connector class = <i>connectorClass</i> , connector name = <i>connectorName</i> , exception class = <i>exceptionClass</i> , regular expression = <i>exceptionMessageRegExp</i> , action = <i>action</i>	661
CTGDIS772I --> <i>string</i>	655	CTGDIS800I User-defined reconnect rules:	661
CTGDIS773I <i>name: exception</i>	655	CTGDIS801I Getting reconnect choice for: connector class = <i>connectorClass</i> , connector name = <i>connectorName</i> , error = <i>error</i> . Selected rule: connector class = <i>rule.connectorClass</i> , connector name = <i>rule.connectorName</i> , exception class = <i>rule.exceptionClass</i> , regular expression = <i>rule.exceptionMessageRegExp</i> , action = <i>rule.getAction()</i>	662
CTGDIS774E The version number of the Parser is undefined.	655		
CTGDIS775E The version number of the Function Component is undefined.	656		
CTGDIS776E The version number of the EventHandler is undefined.	656		
CTGDIS777I Exception occurred in debugConnect method: <i>exception</i>	656		
CTGDIS778I The following SQL statement is to be executed: <i>sql statement</i>	657		
CTGDIS779E The following error occurred during method invocation, performed by Connector: <i>error message</i>	657		
CTGDIS780I The result from method invocation, performed by Connector is: <i>error message</i>	657		
CTGDIS781I Dumping the Performance Entry: <i>entry</i>	657		
CTGDIS782I Dumping performance entry: <i>additional information: entry</i>	657		

CTGDIS802I Getting reconnect choice for connector class = <i>connectorClass</i> , connector name = <i>connectorName</i> , error = <i>error</i> . No matching rule found. Using default action - <i>defaultAction</i>	662	CTGDIS833I Executing empty system store method. All contents of table associated with queue will be deleted.	668
CTGDIS803E Invalid action encountered in the reconnect rules file on the following line: <i>line</i>	662	CTGDIS834E SAX Parse error message: <i>message</i>	668
CTGDIS805E Problems were encountered while parsing the file with user-defined reconnect rules. The rules with errors were not loaded. Total count of rules with errors: <i>error count</i>	662	CTGDIS835I The memory buffer store thread is alive and an interrupt request was sent to it.	668
CTGDIS806E User-defined rule with error has been encountered: <i>exception error message</i>	663	CTGDIS836I The memory buffer load thread is alive and an interrupt request was sent to it.	668
CTGDIS807E Queue with the name <i>name</i> does not exist.	663	CTGDIS837E Exception occurred while trying to evaluate script expression: <i>exception</i>	668
CTGDIS808E Problem encountered while running AssemblyLine Pool	663	CTGDIS840W The size of the AssemblyLine Pool has been reset to 1 because debugging is enabled.	669
CTGDIS809E handleException - cannot handle exception, <i>operation</i>	663	CTGDIS841W AssemblyLine pool: The maximum number of concurrent instances has been reset to the number of prepared instances, <i>number of prepared instances</i> , because the configured value, <i>maximum number of concurrent instances</i> , is less than the number of prepared instances.	669
CTGDIS810E handleException - cannot handle exception, <i>operation</i>	663	CTGDIS845E No config object provided, cannot evaluate <i>expression</i>	669
CTGDIS811E Cannot insert new Entry in Delta Table, the original Exception was <i>sqlException</i>	664	CTGDIS846E Cannot evaluate <i>expression</i> , no AssemblyLine Component found.	669
CTGDIS812E Cannot create table. The SQL statements on which the error occurred are: <i>sql statements</i> . The Exception is: <i>exception</i>	664	CTGDIS847W Could not recognize value <i>value</i> for Global Property <i>property</i> , <i>default value</i> will be used.	670
CTGDIS813W The AssemblyLine could not be set up due to problem with the Script Engine.	664	CTGDIS848E FIPS Mode failed to initialize. Exception: <i>exception</i>	670
CTGDIS814E An exception occurred while starting an AssemblyLine: <i>exception</i>	664	CTGDIS849I FIPS Mode successfully initialized.	670
CTGDIS818I Next Parameter Expanded: <i>parameter value</i>	665	CTGDIS850E An Error occurred while trying to remove the IBMJCEFIPS security provider from the providers list. Exception: <i>exception</i>	670
CTGDIS819E Error occurred in starting Event Handler: <i>exception</i>	665	CTGDIS851E An Error occurred while trying to install the security providers. Exception: <i>exception</i>	670
CTGDIS820E Error occurred in initializing server' security when the server runs in secure mode: <i>exception</i>	665	CTGDIS852E An Error occurred while trying to install the IBMJCEFIPS security provider in the correct place in the security providers list.	671
CTGDIS821I <i>version information</i>	665	CTGDIS853E An Error occurred while trying to set the default JSSE socket factories, the IBM Security Directory Integrator security provider System property and the FIPS enabling property in IBMJSSE2 provider. Exception: <i>exception</i>	671
CTGDIS822E Error occurred getting version information: <i>exception</i>	665	CTGDIS854E The ' <i>property name</i> ' property is read-only and its value could not be changed.	671
CTGDIS823I The command is: <i>command</i>	666	CTGDIS855I A property with the name <i>property name</i> does not exist.	671
CTGDIS824I Sending password...	666	CTGDIS859E A required parameter is missing: <i>parameter name</i>	672
CTGDIS825I Read line: <i>line</i>	666		
CTGDIS826I Line included in the reply: <i>line</i>	666		
CTGDIS827I Class name: <i>class name</i>	666		
CTGDIS828I Superclass / Interface	667		
CTGDIS829E Exception occurred while creating the database file: <i>exception</i>	667		
CTGDIS830I <i>formatting message</i>	667		
CTGDIS831I Next database element: <i>database element</i>	667		
CTGDIS832W Database element information: <i>element information</i>	667		

CTGDIS860E Unexpected token: <i>parameter name</i> If the token is intended to be a parameter value, provide a parameter name for it. If the token is intended to be a parameter name, prefix it with <->.	672	CTGDIS873E The key pair under alias ' <i>key alias</i> ' is for algorithm ' <i>algorithm name</i> '. RSA keys are required for transformation ' <i>transformation name</i> '.	675
CTGDIS861I Usage: -genseckey -alias <key alias> -keyalg <key algorithm> -keysize <key size> -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> [-keypass <key password>] [-keygenproviderclass <security provider for key generation>] -delete -alias <key alias> -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> -importkey -srcalias <key alias in the source keystore> -srckeystore <source keystore file> -srcstorepass <source keystore password> -srcstoretype <type of the source keystore> [-srckeypass <password for the key in the source keystore>] -destalias <key alias in the destination keystore> -destkeystore <destination keystore file> -deststorepass <destination keystore password> -deststoretype <destination keystore type> [-destkeypass <password for the key in the destination keystore>] -list -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> -printseckey -alias <key alias> -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> [-keypass <key password>]	672	CTGDIS874E The keystore does not contain a secret key under alias ' <i>key alias</i> '. Transformation ' <i>transformation name</i> ' requires a secret key.	675
CTGDIS862E The tool could not determine the operation you would like to execute. Verify that your syntax is correct. Currently supported operations are : <i>parameter name</i> , <i>parameter name</i> and <i>parameter name</i> . Call the tool without parameters to see the usage manual.	673	CTGDIS875E The required system property ' <i>property name</i> ' has not been set.	675
CTGDIS863E Cannot read keystore file <i>file name</i> : <i>exception</i>	673	CTGDIS876E Cannot load keystore file ' <i>file name</i> ' of type ' <i>keystore format</i> ': <i>exception</i>	676
CTGDIS864E Key generation failed for algorithm ' <i>algorithm name</i> ' and key size <i>number</i> : <i>exception</i>	673	CTGDIS877E Cannot write keystore file ' <i>file name</i> ' of type ' <i>keystore format</i> ': <i>exception</i>	676
CTGDIS865I Key algorithm: <i>algorithm name</i> Key size: <i>number</i> Raw key: <i>raw binary data</i>	673	CTGDIS878E No entry exists under alias ' <i>alias</i> ' in the source keystore ' <i>file name</i> '	676
CTGDIS866E No secret key has been found under alias ' <i>alias</i> ' in keystore ' <i>alias</i> '.	674	CTGDIS879E The provided password for the entry under alias ' <i>alias</i> ' is incorrect: ' <i>exception</i> '	676
CTGDIS867I <i>alias</i> : private key entry	674	CTGDIS880I Started Derby in Network mode on host ' <i>host name</i> ' and port ' <i>port number</i> '.	676
CTGDIS868I <i>alias</i> : trusted certificate entry	674	CTGDIS881E Not able to start Derby server in Network mode. An exception occurred while starting Derby server in Network mode: <i>exception</i>	677
CTGDIS869I <i>alias</i> : secret key entry	674	CTGDIS882E Derby server Host name is not specified, hence starting Derby server on localhost.	677
CTGDIS870E No entry exists under alias ' <i>alias</i> ' in keystore ' <i>file name</i> '	674	CTGDIS883E Derby server port number is not specified, hence starting Derby server on default port 1527.	677
CTGDIS871E Operation failed with error: <i>exceptions</i>	675	CTGDIS884I AssemblyLine <i>AssemblyLine name</i> is started in simulate mode.	677
CTGDIS872E The keystore does not contain a private key entry under alias ' <i>key alias</i> '. Transformation ' <i>transformation name</i> ' requires a public/private key pair.	675	CTGDIS885E The 'key' or 'value' the desired entry is null.	678
		CTGDIS886E Line <i>line number</i> is incorrectly formatted in the properties file: <i>line information</i>	678
		CTGDIS888E The values in the result entry should be of type com.ibm.di.entry.Entry. The value found is: <i>Java Object</i>	678
		CTGDIS889E Checkpoint/Restart is no longer supported. Edit the configuration file so that it does not depend on the Checkpoint/Restart functionality.	678
		CTGDIS890E The system store 'username' is null.	678
		CTGDIS891E The system store 'jdbcdriver' is null.	679
		CTGDIS892E Error calling method ' <i>Method Name</i> '. Expected ' <i>Java Object</i> ' object for parameter ' <i>Parameter Name</i> '.	679
		CTGDIS893E The entry already contains an Attribute object with the name: ' <i>Attribute Name</i> '.	679
		CTGDIS895E Invalid Property name passed to the constructor.	679

CTGDIS896I Using configuration id ' <i>name</i> ' for a configuration instance loaded from file ' <i>file name</i> '.	680	CTGDIS926E Expected 'Entry' root tag got ' <i>tag</i> '.	685
CTGDIS897I The memory queue <i>queue name</i> is being deleted.	680	CTGDIS927I Calling the startAssemblyLine method...	686
CTGDIS898E The memory queue was unable to store data to the system store.	680	CTGDIS928E Entry does not contain a valid changelog entry (changes attribute missing) for operation: <i>type</i>	686
CTGDIS899E Memory queue was unable to connect to the system store.	680	CTGDIS929E Unable to parse changes attribute.	686
CTGDIS900E Memory queue was unable to empty the system store table.	680	CTGDIS930W Error creating directory: <i>directory name</i>	686
CTGDIS901E Memory queue was unable to create an instance of the system store connector.	681	CTGDIS931W Error creating directory: <i>directory name</i>	686
CTGDIS902E Memory queue was unable to read data from the system store.	681	CTGDIS932W Cannot delete file: <i>file name</i>	687
CTGDIS903E The value specified for parameter Timeout is invalid.	681	CTGDIS933W Cannot rename file: <i>file name</i>	687
CTGDIS904E The value specified for parameter Watermark is invalid.	681	CTGDIS934W Cannot rename file: <i>file name</i>	687
CTGDIS905E The value specified for parameter Page size is invalid.	681	CTGDIS935W An Exception occurred while trying to close the debugger connection. Exception: <i>exception</i>	687
CTGDIS906E The value specified for parameter Percentage memory to use is invalid.	682	CTGDIS936W An Exception occurred while declaring the ' <i>work</i> ' script object. Exception: <i>exception</i>	687
CTGDIS907E The value specified for parameter Percentage memory to use is invalid.	682	CTGDIS937W An Exception occurred while executing the ' <i>On Failure</i> ' AssemblyLine hook. Exception: <i>exception</i>	688
CTGDIS908E The HAttribute object cannot have for a child itself or a HAttribute object which is a parent of it.	682	CTGDIS938W An Exception occurred while building the Link Criteria from the work Entry object. Exception: <i>exception</i>	688
CTGDIS909E Error deleting file: <i>file name</i>	682	CTGDIS939W Cannot declare the name of the AssemblyLine Pool instance as a bean in the Javascript engine. Exception: <i>exception</i>	688
CTGDIS910E Error creating directory: <i>directory name</i>	682	CTGDIS940E The AssemblyLine is already being debugged.	688
CTGDIS911E Error renaming file: <i>file name</i>	683	CTGDIS941E Cannot connect to the debugger on host <i>ip address</i> or <i>host name</i> and port <i>TCP port number</i>	688
CTGDIS912E Invalid JavaString extension call: <i>function name</i>	683	CTGDIS942E The argument is not recognized as a document: <i>object document</i>	689
CTGDIS913E ALComponent returns bad value for branchType: <i>AssemblyLine Component</i>	683	CTGDIS943W The component ' <i>name</i> ' is erroneously placed in the Feed Folder. It will be temporarily moved to the Data Flow Folder.	689
CTGDIS914E Unable to add object to the end of the queue.	683	CTGDIS944E The provided Property object (" <i>property name</i> ") is not owned by this Attribute object.	689
CTGDIS915I config	683	CTGDIS946E Cannot set debug mode for component ' <i>component name</i> '. There is no such component in AssemblyLine ' <i>AssemblyLine name</i> '.	689
CTGDIS916I DebugServer : Error sending config : <i>exception</i>	684	CTGDIS947E Cannot retrieve debug mode for component ' <i>component name</i> '. There is no such component in AssemblyLine ' <i>AssemblyLine name</i> '.	690
CTGDIS917I ERROR	684	CTGDIS948E Cannot set debug mode for component ' <i>component name</i> '. There is no such component in AssemblyLine ' <i>AssemblyLine name</i> '.	690
CTGDIS918I switch	684	CTGDIS949E Cannot retrieve debug mode for component ' <i>component name</i> '. There is no such component in AssemblyLine ' <i>AssemblyLine name</i> '.	690
CTGDIS919E Unable to process the command because the required Config ID was not specified.	684		
CTGDIS920E Unable to process the command. A Config name must be specified.	684		
CTGDIS921E Sub command required	685		
CTGDIS922E Must post configuration file to load.	685		
CTGDIS923E Unknown command was encountered: <i>command</i>	685		
CTGDIS924E Configuration file not found: <i>file name</i>	685		
CTGDIS925E Unknown property store name: <i>property store name</i>	685		

CTGDIS950I Delta Statistics: Sequence ID: <i>sequence number</i> Number of Entries: <i>number of entries</i> Number of old Entries: <i>number old entries</i>	690	CTGDIS1890E The AssemblyLine did not run long enough, terminating.	696
CTGDIS951E While getting delta statistics: <i>error</i>	690	CTGDIS1891E Cannot find config instance <i>id.</i>	697
CTGDIS952I Calls: <i>number of calls</i> , Errors: <i>number of errors</i>	691	CTGDIS1892E Problem while starting the Failure AssemblyLine: <i>exception</i>	697
CTGDIS953I Calls: <i>number of calls</i>	691	CTGDIS1893W Cannot locate file <i>file name</i> referenced by <i>component</i>	697
CTGDIS954E Error loading configuration files <i>file names</i> . Specifying multiple files requires the -d option.	691	CTGDIS1894E Schedule: Incorrect number of fields in <i>string</i>	697
CTGDIS955E Error while registering cryptographic provider ' <i>provider name</i> '.	691	CTGDIS1895E Schedule field value too large: <i>value</i>	697
CTGDIS956E Cannot use SSL on data channel if SSL on the command channel is not enabled.	692	CTGDIS1896E No AssemblyLine specified.	698
CTGDIS957E The system encountered an internal error while trying to validate a product license. Message: <i>message</i>	692	CTGDIS1897I Sequence <i>name</i> started.	698
CTGDIS958E The system cannot find an enrolled product license.	692	CTGDIS1898I Sequence started by <i>thread name</i>	698
CTGDIS959E The evaluation period has expired.	692	CTGDIS1899I Rule with priority ' <i>priority</i> ' and name ' <i>name</i> ' requires: <i>attr names</i> (+ add, - remove).	698
CTGDIS960W There are <i>number of days</i> days left in the evaluation period.	693	CTGDIS1900I Rule with priority ' <i>priority</i> ' and name ' <i>name</i> ' is satisfied.	698
CTGDIS961E The evaluation period is invalid.	693	CTGDIS1901I Rule with priority ' <i>priority</i> ' requires: <i>attr names</i> (+ add, - remove).	699
CTGDIS962W Running the AssemblyLine in Simulation mode	693	CTGDIS1902I Rule with priority ' <i>priority</i> ' is satisfied.	699
CTGDIS963W AssemblyLine <i>name</i> cannot be started, because the Config Instance is shutting down.	693	CTGDIS1903E Class type is not provided.	699
CTGDIS964I Shutting down the AssemblyLine.	693	CTGDIS1904E The IT registry meta data is not supported for Naming Rule validation.	699
CTGDIS965W AssemblyLine <i>name</i> could not be stopped.	694	CTGDIS1905E Unable to find configuration for Sequence <i>name</i>	699
CTGDIS966E The keystore file ' <i>file name</i> ' had the following problem: <i>error message</i>	694	CTGDIS1906E An error has occurred while decrypting protected property: <i>exception</i>	700
CTGDIS967I AssemblyLine started by <i>thread name</i>	694	CTGDIS1907I Compute changes is not supported for hierarchical entries.	700
CTGDIS968E No Failover Connector Name provided	694	CTGDIS1908E Cannot read regression info: <i>exception</i>	700
CTGDIS969E Changelog Entry does not contain a changetype Attribute. The Entry is: <i>entry</i>	694	CTGDIS1909E Cannot write regression info: <i>exception</i>	700
CTGDIS1880W Transactions are not supported by the database.	695	CTGDIS1910W The regression file does not contain information about this AssemblyLine	700
CTGDIS1881W The specified row locking is not supported by the database.	695	CTGDIS1911W Premature end of regression file at cycle <i>number</i>	701
CTGDIS1882E Error while loading script <i>name</i>	695	CTGDIS1912W Not the same information in <i>Entry name</i> at <i>component</i> , cycle <i>number</i> . Old info: <i>oldinfo</i> , new info: <i>newinfo</i>	701
CTGDIS1884E Cannot compute the next date	695	CTGDIS1913W This run of the AssemblyLine stopped earlier than the previous run, only <i>number</i> cycles completed.	701
CTGDIS1885E No AssemblyLine specified.	695	CTGDIS1914I Not initializing a re-used Connector.	701
CTGDIS1886I Scheduler started by <i>thread name</i>	696	CTGDIS1915I Derby Network Server started.	701
CTGDIS1887I Finished.	696	CTGDIS1916W Only able to start or stop Derby Network Server.	702
CTGDIS1888E No config instance name specified.	696	CTGDIS1917I Derby Network Server stopped.	702
CTGDIS1889E Problem while starting the AssemblyLine: <i>exception</i>	696	CTGDIS1918W Unable to stop Derby Network Server.	702
		CTGDIS1919E No path was found in the SCIM request.	702
		CTGDIS1920E XML is not supported.	702
		CTGDIS1921E Cannot change <i>endPoint</i>	703
		CTGDIS1922E Unknown schema <i>schema</i>	703

CTGDIS1923E Unknown endpoint <i>endPoint</i>	703
CTGDIS1924E The <i>name</i> attribute was not specified.	703
CTGDIS1925E A resource with that <i>name</i> attribute already exists.	703
CTGDIS1926E Could not find the new resource after adding it.	704
CTGDIS1927E Unable to find ID: <i>ID</i>	704
CTGDIS1928E The ID was not specified.	704
CTGDIS1929E The file <i>fileName</i> was not found.	704
CTGDIS1930E Cannot connect to the LDAP server.	704
CTGDIS1931E The request did not have a body.	704
CTGDIS1932E The information in the request body could not be parsed: <i>exception</i>	705
CTGDIS1933E An error occurred while parsing JSON in the file <i>file name</i>	705
CTGDIS1934I No resource was found using the filter: <i>filterString</i>	705
CTGDIS1935W No resource was found using the search base <i>base</i>	705
CTGDIS1936E No CreatedN mapping was found in the mapping file.	706
CTGDIS1937E Unable to parse filter at column <i>number</i>	706
CTGDIS1938I Unknown attribute: <i>name</i>	706
CTGDIS1939I Additional text after end of expression: <i>text</i>	706
CTGDIS1940I An operator was expected.	706
CTGDIS1941I Unsupported operator: <i>name</i>	707
CTGDIS1942I A closing parenthesis was expected, but found: <i>token</i>	707
CTGDIS1943I The value is missing for operator: <i>operator</i>	707
CTGDIS1944I A string value was expected, but found: <i>token</i>	707
CTGDIS1945I Unknown Unicode character expression: <i>token</i>	707
CTGDIS1946I Unexpected end of string value.	708
CTGDIS1947I <i>attribute name</i> cannot have the value <i>value</i>	708
CTGDIS1948I Unsupported operator <i>operator</i> for <i>attribute name</i>	708
CTGDIS1949W Cannot parse URL: <i>url</i>	708
CTGDIS1950W Cannot read truststore <i>filename</i> . The following error occurred: <i>exception</i>	708
CTGDIS1951W Cannot create SSLContext. The following error occurred: <i>exception</i>	709
CTGDIS1952W Cannot connect to host <i>host</i> on port <i>number</i> . The following error occurred: <i>exception</i>	709
CTGDIS1953I The connection is already trusted.	709
CTGDIS1954W The following socket exception occurred: <i>exception</i>	709
CTGDIS1955W Did not receive any certificate.	709

CTGDIS1956W Unable to add certificate to truststore. The following error occurred: <i>exception</i>	710
CTGDIS1957I Added certificate with subject: <i>subject</i>	710
CTGDKE101E Constructed with non-TreeMap object: <i>data</i>	710
CTGDKE102E <i>Component name</i> Cannot setup inheritance: <i>parameter</i>	710
CTGDKE103E Cannot inherit from itself: <i>component name?</i>	710
CTGDKE104E <i>component name</i> : This object has no MetamergeConfig object.	711
CTGDKE105E <i>component name</i> cannot inherit from self.	711
CTGDKE106I this class is no longer in use: ConnectorSchemaConfigImpl.	711
CTGDKE107E Unknown property line: <i>string</i>	711
CTGDKE108E No filename specified for <i>component name</i>	711
CTGDKE109I EXTPROP: getParameter: <i>name</i>	712
CTGDKE110I EXTPROP: setValue: <i>name = value</i>	712
CTGDKE111E No metamerge Config in this or parents object for: <i>object</i>	712
CTGDKE112E Loading configuration in server secure mode combined with password is not allowed	712
CTGDKE113I Convert old style CFG file.	712
CTGDKE114I Using new style CFG file.	713
CTGDKE115E FileConfig Data is NULL.	713
CTGDKE116I Ignoring create of forms folder.	713
CTGDKE117I Move folder from <i>name</i> to <i>name</i>	713
CTGDKE118I convertNames: fixHooks for AssemblyLine <i>AssemblyLine name</i> . Exception occurred: <i>exception</i>	713
CTGDKE119I convertNames: fixHooks for Connectors. Exception occurred: <i>exception</i>	714
CTGDKE120I fixIncludes: <i>ignore</i>	714
CTGDKE122I LOOKUP: <i>name, class name</i>	714
CTGDKE123I Cache hit for: <i>name, class name@hash code</i>	714
CTGDKE124E Not a context/treemap: <i>name</i>	714
CTGDKE125I Add baseconfig cache: <i>name, class name@obj.hashCode()</i>	715
CTGDKE126I Add object cache: <i>name, class name@ hash code</i>	715
CTGDKE127E Cannot save to: <i>class name</i>	715
CTGDKE128E Creating a folder is not supported by this config driver.	715
CTGDKE129E Bind not supported by this Config driver.	715
CTGDKE130E Rename not supported by this Config driver.	716
CTGDKE131I AssemblyLine <i>name</i> found in <i>folder name</i>	716
CTGDKE132E <i>name</i> is not an AssemblyLineConfig.	716
CTGDKE133I ConnectorConfig <i>name</i> found in <i>folder name</i>	716
CTGDKE134E <i>name</i> is not a ConnectorConfig.	716

CTGDKE135I ParserConfig <i>name</i> found in <i>folder name</i>	716	CTGDKE170E Only one Config item allowed: <i>Config object</i>	724
CTGDKE136E <i>name</i> is not a Parser.	717	CTGDKE171I External lookup in: <i>base</i> ; for <i>name</i>	724
CTGDKE137I EventHandlerConfig <i>name</i> found in <i>folder name</i>	717	CTGDKE172I Setting base: <i>base name</i>	724
CTGDKE138E <i>name</i> is not an EventHandler	717	CTGDKE173I MetamergeConfigFS Commit Changes.	724
CTGDKE139I Script <i>name</i> found in <i>folder</i> <i>name</i>	717	CTGDKE174I - Commit Changes: Process dirty list.	724
CTGDKE140E <i>name</i> is not a Script.	717	CTGDKE175I - Commit Changes: next dirty: <i>name</i>	725
CTGDKE141I Function <i>name</i> found in <i>folder</i> <i>name</i>	718	CTGDKE176I - Commit Changes: Update modified flags.	725
CTGDKE142E <i>name</i> is not a Function object.	718	CTGDKE177E No such file: <i>file name</i>	725
CTGDKE143E <i>name</i> is not a NamespaceConfig.	718	CTGDKE178I Create new File: <i>path</i>	725
CTGDKE144E Cannot recursively create folders.	718	CTGDKE179E Cannot load client encrypted file in server secure mode.	725
CTGDKE145E Single name component required.	718	CTGDKE180E Missing password for Encrypted file.	725
CTGDKE146I CREATE FOLDER: <i>foldr name</i>	718	CTGDKE181I Read current File (encrypted).	726
CTGDKE147E Invalid behavior on exhausted pool vallue passed: <i>integer</i>	719	CTGDKE182I Read current File.	726
CTGDKE148I Found existing attribute for ' <i>attribute name</i> .' while migrating 5.2 call parameters.	719	CTGDKE183I Read input stream.	726
CTGDKE149E No name for CallParam	719	CTGDKE184I Read byte array.	726
CTGDKE150I AssemblyLineFactory: build <i>class name</i>	719	CTGDKE185I Read URL.	726
CTGDKE151I AssemblyLineFactory: end build	719	CTGDKE186I Path is a RemoteConfigURL.	727
CTGDKE152E Cannot parse: <i>class name</i>	720	CTGDKE187E Unknown PROVIDER_URL: <i>path</i> .	727
CTGDKE153E Cannot serialize: <i>class name</i> .	720	CTGDKE188E Config file is not PKI encrypted (not allowed in server secure mode).	727
CTGDKE154E Cannot serialize <i>class name</i> .	720	CTGDKE189I <i>name</i> >> found cached object.	727
CTGDKE155I XML ConnectorFactory: migrating version 1.0 config to 1.1 (schema configuration).	720	CTGDKE190E Single name component required.	727
CTGDKE156E Cannot serialize <i>class name</i> ..	720	CTGDKE191E Cannot recursively create folders.	727
CTGDKE157I parse: <i>tag name</i>	721	CTGDKE192E Move not supported.	728
CTGDKE158I EventHandler: <i>Config name</i> , actionCount= <i>integer</i>	721	CTGDKE193E Internal error: The XML element not found for rename operation.	728
CTGDKE159E ACTION_MAP_TAG with no ACTION_MAP_NAME_TAG child element.	721	CTGDKE194E Cannot remove standard object.	728
CTGDKE160I Created EventHandlerActionConfig: <i>name</i>	721	CTGDKE195E Cannot remove top level element.	728
CTGDKE161I build: <i>Config name</i>	721	CTGDKE196I InternalBind: <i>object name</i> , <i>size</i> --> <i>object</i>	728
CTGDKE162E No XML factory defined for tag: <i>tag</i>	722	CTGDKE197E No XML Factory for object: <i>name</i> , class: <i>class name</i>	729
CTGDKE163I getImpl: tag= <i>tag</i> , class= <i>class</i> <i>name</i>	722	CTGDKE198I transformObject: Name= <i>name</i> , class= <i>class name</i> , tag= <i>tag</i>	729
CTGDKE164E No configuration implementation defined for tag: <i>tag</i>	722	CTGDKE199I MetamergeXML Commit Changes.	729
CTGDKE165I Dumping Config...	722	CTGDKE200E Saving configuration in server secure mode combined with password is not allowed.	729
CTGDKE166I >> Config parameter: <i>parameter</i> <i>name</i> : <i>parameter value</i>	722	CTGDKE202I - Commit Changes: Process dirty list.	729
CTGDKE167I HookFactory parse: <i>tag name</i> .	723	CTGDKE203I - Commit Changes: next dirty: <i>name</i>	730
CTGDKE168I HookFactory getItem: <i>tag name</i> .	723	CTGDKE204I - Commit Changes: Update modified flags.	730
CTGDKE169I HOOK: name= <i>name</i> , enabled= <i>string</i> , debug= <i>debug</i>	723	CTGDKE205W Restoring <i>file name</i> as <i>file</i> <i>name</i>	730
CTGDKE167E 'Hook' encountered without a name.	723	CTGDKE206E Cannot save because no output was specified.	730
CTGDKE168E No loop type tag in config.	723		
CTGDKE169E Multiple nodes: <i>node name</i> ; <i>node name</i>	723		

CTGDKE207E Unknown output object class: <i>class name</i>	730
CTGDKE208I SchemaFactory parse method: <i>tag name</i>	730
CTGDKE209I SchemaFactory migrateSchemaItem method: <i>tag name</i>	731
CTGDKE210I SchemaFactory getItem method: <i>tag name</i>	731
CTGDKE211E Cannot rename standard folder.	731
CTGDKE212E Could not obtain remote Session: Session object is null.	731
CTGDKE213E The XML document <i>filename</i> does not have a root tag of <i>tag name</i>	731
CTGDKE214E The XML document <i>filename</i> is newer than version <i>version number</i>	732
CTGDKE215W The XML document <i>filename</i> is old. Version <i>version number</i> expected, version <i>version number</i> found. The configuration will be upgraded in memory and used.	732
CTGDKE216I The old version of the file saved as <i>file name</i>	732
CTGDKE217E <i>compound name</i> could not be found at <i>context</i>	732
CTGDKE218E <i>compound name</i> could not be found.	733
CTGDKE219E Parent from which AssemblyLine Component inherits is not present.	733
CTGDKE220E <i>name</i> is already used as operation name.	733
CTGDKE220I Inheriting from <i>name</i>	733
CTGDKE221W The component name is invalid: <i>name</i> . An exception occurred: <i>exception</i>	733
CTGDKE222W Component <i>component name</i> has been renamed to <i>component name</i> . This has been corrected in your Config file.	734
CTGDKE223W The old Component name <i>component name</i> has been resolved to <i>component name</i>	734
CTGDKE224W The evaluation of parameter <i>parameter name</i> in <i>config item</i> using expression ' <i>expression</i> ' did not return any value.	734
CTGDKE225E The evaluation of parameter <i>parameter name</i> in <i>config item</i> using expression ' <i>expression</i> ' caused an error.	734
CTGDKE226E Cannot read the config file <i>file path</i>	734
CTGDKE227E Translation file <i>file path</i> not found.	735
CTGDKE228E Cannot find the Java class, which the reconnect rule refers to. The error is: <i>exception</i>	735
CTGDKE229E ' <i>action name</i> ' is not valid for a value of the 'action' parameter of the reconnect rule. Must be either 'error' or 'reconnect'.	735

CTGDKE230E Cannot find configuration for component ' <i>component name</i> ' inside the configuration of AssemblyLine ' <i>AssemblyLine name</i> '.	735
CTGDKE231E The provided path : ' <i>path</i> ' does not contain a configuration object.	735
CTGDKE232E The provided path : ' <i>path</i> ' does not contain configuration a object.	736
CTGDKE233E The provided path : ' <i>path</i> ' does not contain a configuration object.	736
CTGDKE234W <i>Exception message</i>	736
CTGDKE235E <i>name</i> is not an Attribute Map.	736
CTGDKN501E Could not load configuration file ' <i>file name</i> '.	736
CTGDKN502E Invalid mode: ' <i>mode</i> '.	737
CTGDKN503E Invalid type: ' <i>type</i> '.	737
CTGDKN504I Property ' <i>property name</i> ' is NULL or empty.	737
CTGDKN505E Client QueueManager root folder property ' <i>property name</i> ' not specified in the configuration file.	737
CTGDKN506I Client MQe configuration successfully completed.	737
CTGDKN507E Client MQe configuration failed.	738
CTGDKN508I Certificate renewal for entity ' <i>entity name</i> ' completed successfully.	738
CTGDKN509E Client MQe certificate renewal failed.	738
CTGDKN510E Server QueueManager root folder property ' <i>property name</i> ' was not specified in the configuration file.	738
CTGDKN511I Server MQe configuration successfully completed.	738
CTGDKN512E Server MQe configuration failed.	739
CTGDKN513I Queue operation successfully completed.	739
CTGDKN514E The queue operation failed.	739
CTGDKN515I Will create Connection for: ' <i>adapter</i> '.	739
CTGDKN516I A Connection definition with that name is already registered.	739
CTGDKN517E Invalid numeric value for property ' <i>property name</i> ': <i>property value</i> '.	740
CTGDKN518I Building connection admin message...	740
CTGDKN519I MQeConfig <configuration file> <mode: <i>mode1</i> <i>mode2</i> <i>mode3</i> <i>mode4</i> > <type: <i>type1</i> <i>type2</i> <i>type3</i> <i>type4</i> > [queuname [targetQMname [QM_ip_or_hostname comm_port]]]	740
CTGDKN520I Building admin message to create remote queue: ' <i>queue</i> '; on QM: apos; <i>QM</i> '; adapter: apos; <i>adapter</i> '.	740
CTGDKN521E Listener section not specified in QueueManager config.	740
CTGDKN522I Building admin message to create a listener.	741
CTGDKN523I Press Enter to send test message...	741

CTGDKN524I Message sent.	741
CTGDKN525E Could not send test message.	741
CTGDKN526I QueueManager terminated.	741
CTGDKN527E An unexpected exception occurred.	741
CTGDKN528I Press Enter to receive test message...	742
CTGDKN529I Test Failed. Could not receive MQe message. Queue is empty.	742
CTGDKN530I Test failed: message received but not of expected type 'TextMessage'.	742
CTGDKN531I Test failed: message received but text does not match - expected 'msg', received 'msgTxt'.	742
CTGDKN532I Test MQe message successfully received.	742
CTGDKN533E Could not receive test message.	743
CTGDKN534I Built an admin message to delete a queue.	743
CTGDKN535I Queue deleted successfully.	743
CTGDKN536I Sending an admin message to QM/queue: <i>onQMgr/ AdminQName</i> ; using QM: <i>QMgrName</i>	743
CTGDKN537I Waiting for a response to the admin message...	743
CTGDKN538E No response message received.	744
CTGDKN539I Action failed: ' <i>error message</i> '.	744
CTGDKN540I Error information: ' <i>error message</i> '.	744
CTGDKN541I Problematic field: ' <i>field name</i> ' ' <i>field value</i> '.	744
CTGDKN542E The QueueManager is already running.	744
CTGDKN543I QueueManager config fields:	745
CTGDKN544E Failed to add the QM Alias name: ' <i>alias</i> '.	745
CTGDKN545I Listener port is ' <i>port number</i> '.	745
CTGDKN546I Listener port was not specified. Using the default value of ' <i>port number</i> '.	745
CTGDKN547E Unable to create destination directory: ' <i>directory name</i> '.	745
CTGDKN548I MQe QueueManager .ini file was not specified.	746
CTGDKN549I MQe QueueManager Queues folder was not specified.	746
CTGDKN550E The file ' <i>file name</i> ' is not a valid MQe configuration file, or does not exist.	746
CTGDKN551W Unable to delete the directory: ' <i>directory name</i> '.	746
CTGDKN552I Admin request was successful.	746
CTGDJM003I KeyStore certificate password is NULL or empty. Will use keystore password to get private key.	747
CTGDJM004I The parameter 'storageNotification' was not specified so no notification servers will be set.	747

CTGDJM005E Unable to notify Storage notification server ' <i>server URL</i> ' because the format is not valid. The expected format is '<host>:<port>'.	747
CTGDJM006E Unable to notify Storage notification server ' <i>server URL</i> ' because the port ' <i>server URL</i> ' in the URL is not valid.	747
CTGDJM007E Could not notify the Storage Component at <i>notification server</i> . Exception occurred: <i>exception</i>	747
CTGDJM008W JMS Password Store Connector will start in 'offline' mode: - messages already transferred to the local MQe QueueManager will be retrieved; - if in the meantime the JMS Storage Component is started, any new messages will be transferred and delivered by the Connector.	748
CTGDJM009I The Storage Component at <i>notification server</i> is successfully notified for the Connector startup.	748
CTGDJM010E Error closing the notification connection to the Storage Component: <i>exception</i>	748
CTGDJM014I The getNextEntry method received message of type: <i>class name</i>	748
CTGDJM015E Exception while closing queue connection: <i>exception</i>	749
CTGDJM016E Invalid message type. Received message type of class <i>class name</i> but expected class type was TextMessage.	749
CTGDJM017I 'UpdateType' field retrieved from message.	749
CTGDJM018I 'UserId' field retrieved from message.	749
CTGDJM019I 'PasswordCount' field retrieved from message.	749
CTGDJM020E Incorrect password update message format. Exception occurred: <i>exception</i>	750
CTGDJM021I 'Passwords' value retrieved from message.	750
CTGDJM022I Attribute 'Passwords' created with no values.	750
CTGDJM023E Could not parse password update message. Exception occurred: <i>exception</i>	750
CTGDJM024E Message contains invalid update type: <i>type</i>	750
CTGDJM025E Unable to use both PKCS7 and the encryption from releases prior to IBM Security Directory Integrator 6.1.1 at the same time.	751
CTGDJZ501E Open IdML Function Component accepts only a IBM Security Directory Integrator Entry as input.	751
CTGDJZ502E The book ' <i>book name</i> ' is currently in use. Release it, before attempting to use it again.	751
CTGDJZ503E Not all CDM attributes needed for registering an MSS are provided.	751

CTGDJZ504E Both a target and a source must be provided, in order to create a relationship.	752	CTGDKN003E Proxy stop request failed! The server is probably already stopped.	757
CTGDJZ505E The IBM DL Certification Tool assessed that book ' <i>book name</i> ' is not a valid IdML document (file name: ' <i>file name</i> ').	752	CTGDKN004I Waiting for ' <i>number of threads</i> ' threads to die.	757
CTGDJZ506E A valid CDM version and MSS's Application Code and Hostname are mandatory for the MSS creation.	752	CTGDKN005I Interrupted while waiting for the other threads to die.	757
CTGDJZ507E Class ' <i>class name</i> ' cannot be found.	752	CTGDKN006E Unable to start the Java Proxy because the Java property ' <i>property name</i> ' was not specified.	757
CTGDJZ508I Open IdML Function Component has already opened book ' <i>book name</i> '.	752	CTGDKN007E Unable to start the Java Proxy. The path to the Java Proxy configuration file is not valid.	758
CTGDJZ509I The parameter <i>param name</i> was initialized with the value: ' <i>value</i> '.	753	CTGDKN008E Unable to start the Java Proxy. The proxy configuration file property was not specified.	758
CTGDJZ510I Open IdML Function Component will work with book: ' <i>book name</i> '.	753	CTGDKN009E Unable to start the Java Proxy. The server socket could not be created.	758
CTGDJZ511I The name of the currently used book ' <i>book name</i> ' has been overridden to ' <i>new name</i> '.	753	CTGDKN010I The authentication folder is: ' <i>directory name</i> '.	758
CTGDJZ512I Use an IT registry for the needed meta-data: ' <i>use it registry</i> '.	753	CTGDKN011I Plug-in/Proxy authentication successful.	758
CTGDJZ513I Open IdML Function Component will create a <i>idml mode</i> IdML.	754	CTGDKN012I Plug-in/Proxy authentication failed.	759
CTGDJZ514I The generated IdML will be validated.	754	CTGDKN013E An unexpected Input/Output Exception occurred.	759
CTGDJZ515I The MSS's <i>param name</i> has value: ' <i>value</i> '.	754	CTGDKN014I The Java Proxy is shutting down...	759
CTGDJZ516I The MSS's <i>param name</i> has been overridden to value: ' <i>value</i> '.	754	CTGDKN015E An unexpected exception occurred.	759
CTGDJZ517I The Common Data Model version of the generated IdML will be ' <i>cdm version</i> '.	754	CTGDKN016E Unable to start the Java Proxy. The configuration property ' <i>syncClass</i> ' is missing.	759
CTGDJZ518I Open IdML Function Component opened book ' <i>value</i> '.	755	CTGDKN017E Unable to start the Java Proxy. The Password Store class could not be instantiated.	760
CTGDJZ519E Parameter ' <i>param name</i> ' is not provided.	755	CTGDKN018I Invalid value for ' <i>property name</i> ' property, falling back to the default port ' <i>port number</i> '.	760
CTGDJU101E Unable to read the entry because the 'defaultAttribute' ' <i>attribute value</i> ' value was not set in the Entry object.	755	CTGDKN019I Sending Proxy Stop request.	760
CTGDJU102E Unable to read the entry because the Entry object is of an unknown type: ' <i>object type</i> '. Specify an object of type 'String', 'File', 'InputStream', or 'Reader'.	755	CTGDKN020E Could not connect to ' <i>hostname</i> ' :' <i>port number</i> '.	760
CTGDIR101I The properties file ' <i>file name</i> ' does not exist and will be ignored.	755	CTGDKN021I The Java Proxy does not recognize the byte-order mark.	760
CTGDIR102E Unable to modify entry because no key value was provided.	756	CTGDKN022W The Proxy Stop request was rejected by the Java Proxy.	761
CTGDIR103W The properties file ' <i>file name</i> ' for <i>property store name</i> was not found, and will be created if anything is written to it.	756	CTGDKN023I The Proxy stop request was sent successfully. The Proxy will react in less than <i>number of seconds</i> seconds.	761
CTGDIR104E The Certificate ' <i>certificate name</i> ' for property file <i>file name</i> was not found.	756	CTGDKN024I Usage of the StopProxy program:	761
CTGDKN001I Proxy stop requested.	756	CTGDKN025I stopProxy <full path to the configuration file of the Password Synchronizer>	761
CTGDKN002E Encountered an unknown hostname or IP address.	757	CTGDKN026I Received operational code: ' <i>operational code</i> '.	761
		CTGDKN027I Invalid operational code: ' <i>operational code</i> '.	762
		CTGDKN028I Rejecting operation.	762

CTGDKN029I Invalid data received. The data might contain null characters. The operation for ' <i>operation name</i> ' will be rejected.	762
CTGDKN030E Invalid protocol data. Expected 0x00, received: <i>byte</i>	762
CTGDKN031I Reading BOM.	762
CTGDKN032I Encoding not found. Using default encoding (' <i>character set</i> ').	763
CTGDKN033I Found encoding ' <i>character set</i> '.	763
CTGDKN034I Sending positive response to the client plug-in.	763
CTGDKN035I Insufficient input data.	763
CTGDKN037E A password file was not created successfully.	763
CTGDKN040I Both password files were successfully read.	764
CTGDKN041I Sending proxy password.	764
CTGDKN044E The authentication process failed. The proxy did not respond as expected.	764
CTGDKN045I The password sent by the proxy is valid.	764
CTGDKN046E Authentication failed. The password sent by the proxy is not the same as the one that the client generated at the beginning of the authentication process.	764
CTGDKN047E The authentication failed: <i>exception</i>	765
CTGDKN049E The password file ' <i>file name</i> ' is missing.	765
CTGDKN050E The password file ' <i>file name</i> ' is of unexpected format.	765
CTGDKN051E Authentication failed because a password file could not be created: <i>exception</i>	765
CTGDKN052W Could not delete proxy password file ' <i>file name</i> '.	765
CTGDKN053I Proxy password file deleted successfully.	766
CTGDKN054E The client did not respond as expected.	766
CTGDKN055E The password received from the client does not match the password generated by the proxy in the beginning of the authentication process.	766
CTGDKN056I Received correct password from client.	766
CTGDKN057I Sending password to client.	766
CTGDKN059W Could not delete client password file ' <i>file name</i> '.	767
CTGDKN060I Client password file deleted successfully.	767
CTGDKN061E The client did not respond as expected.	767
CTGDKN062E The client rejected the password sent by the proxy.	767
CTGDKN063I The client accepted the password sent by the proxy.	768

CTGDKN064E The authentication failed. An exception occurred: <i>exception</i>	768
CTGDKN067E The client password file ' <i>file name</i> ' is missing.	768
CTGDKN068E The authentication failed. The proxy does not recognize the format of the client password file.	768
CTGDKN069E Cannot install IBMJCE provider. An exception occurred: <i>exception</i>	768
CTGDKN070E Could not obtain cipher ' <i>cipher name</i> ' implementation from provider ' <i>provider name</i> ': <i>exception</i>	769
CTGDKN071E Key store file ' <i>file name</i> ' does not exist.	769
CTGDKN072E Failed to open key store file ' <i>file name</i> ': <i>exception</i>	769
CTGDKN073E Could not find certificate with alias ' <i>certificate alias</i> ' in key store file ' <i>file name</i> '.	769
CTGDKN074E Failed to retrieve certificate with alias ' <i>certificate alias</i> ' from key store file ' <i>file name</i> ': <i>exception</i>	769
CTGDKN075E Failed to retrieve private key with alias ' <i>private key alias</i> ' from key store file ' <i>file name</i> ': <i>exception</i>	770
CTGDKN076E Failed to retrieve public key with alias ' <i>alias name</i> ' from key store file ' <i>file name</i> ': <i>exception</i>	770
CTGDKN077E An exception occurred during the encryption operation: <i>exception</i>	770
CTGDKN078E An exception occurred during the decryption operation: <i>exception</i>	770
CTGDKN079I Usage: java com.ibm.di.plugin.idipwsync.EncodePW <password>	770
CTGDKN080E An unexpected error occurred.	771
CTGDKN081E Incorrect class specified in the syncClass property.	771
CTGDKN082I Invalid value for ' <i>property name</i> ' property, falling back to the default retry attempts ' <i>retry attempt</i> '.	771
CTGDKK001E Missing required parameter: <i>parameter name</i>	771
CTGDKK002E Parameter <i>parameter name</i> must be a number greater than <i>number</i>	771
CTGDKK003E Parameter <i>parameter name</i> must be a number greater than or equal to <i>number</i>	772
CTGDKK004E Parameter <i>parameter name</i> must be a number less than or equal to <i>number</i>	772
CTGDKK005E Parameter <i>parameter name</i> must be a number.	772
CTGDKK006E Cannot create connection to Agent Controller.	772
CTGDKK007I Waiting <i>number of milliseconds</i> milliseconds for monitoring client...	772
CTGDKK008I Monitoring client has arrived.	773
CTGDKK009E No monitoring client has arrived.	773
CTGDKK010I Waiting for monitoring client...	773
CTGDKK011I Monitoring client has arrived.	773

CTGDKK012I Started monitoring remote agent. 773

CTGDKK013I Remote Logging Agent is dead. 774

CTGDKK014I Data from dead agent depleted. 774

CTGDKK015I Logging Agent Life Monitoring thread interrupted. 774

CTGDKK016I Connection to remote AgentController disrupted. 774

CTGDKK017E Error while processing incoming data from the Logging Agent: *exception* 774

CTGDKK018E Error while processing incoming data from the Logging Agent: *exception* 775

CTGDKK019W Received invalid data from the remote Logging Agent. 775

CTGDKK020I Data Processor waiting for data... 775

CTGDKK021E Cannot parse the ConnectionTimeout parameter. 775

CTGDJG001I Connector will restart with restored change token: '*change token*'. 775

CTGDJG002I Removing processed rows before '*change token*'. 776

CTGDJG003I Removed *number of rows* processed rows. 776

CTGDJG004I Connector will wait for '*seconds*' seconds. First wait was at '*number of seconds*' seconds and last wait was at '*number of seconds*' seconds. . . . 776

CTGDJG005I RDBMS Changelog Connector restarting with changeToken *change token*. 776

CTGDJG006I RDBMS Changelog Connector restarting at point *restart point*. . . . 776

CTGDJG007E The 'Start at' parameter is set to an invalid value '*parameter value*'.\n The parameter must be greater than 0 and less than *Integer*. 777

CTGDJG008E The 'Start at' parameter is set to an invalid value '*parameter value*'.\n The parameter must be greater than 0 and less than *Integer*. 777

CTGDJG009E The 'Start at' parameter is set to an invalid value '*parameter value*'.\n The parameter must be greater than 0 and less than *Integer*. 777

CTGDJG001E The Function Component could not establish a connection to the host. . . 777

CTGDJG002E The remote pathname specified could not be found. 778

CTGDJG003E An error occurred when reading from the local file 778

CTGDJG004E Pathname cannot be removed. . . 778

CTGDJG005E An error occurred when accessing the remote filesystem. 778

CTGDJG006E A unique service name cannot be found on the target machine. 778

CTGDJG007E The native Windows service binary cannot be read. 779

CTGDJG008E RSH could not bind to any local privileged port. 779

CTGDJG009E Could not find the remote user RemoteUser. 779

CTGDJG010E The specified username is not authorized to run shutdown. 779

CTGDJG011E An error occurred when executing the remote command. 780

CTGDJG012E Unable to execute the command remotely since the Remote Command Line Function Component has not been initialized. 780

CTGDJG013E The Function Component can no longer be used as it has been terminated. . 780

CTGDJG014E No command has been specified to execute. Provide a command on the IBM Security Directory Integrator GUI or as an attribute called 'command.line' in the provided Entry object. 780

CTGDJG015E Not all parameters have been provided. Ensure you have provided a hostname and username. For an REXEC or Windows connection you will also need to provide a password. For an SSH connection you have the option of providing a password OR a keystore (with associated passphrase if applicable). 781

CTGDJG016E The target machine's remote service could not be started. 781

CTGDJG017E The following internal RXA error message was generated: {0} 781

CTGDJG018E An Entry object is expected. 781

CTGDJG019E An error occurred when reading the remote file. 782

CTGDJG020E The execution of the requested command has timed out. 782

CTGDJG021E The specified standard input file does not exist. 782

CTGDJG022E An invalid connection type has been specified. The valid values for the 'connectionType' parameter are: 'ANY', 'RSH', 'SSH', 'REXEC' and 'WIN'. 782

CTGDJG023E Could not establish a connection to the target machine with the authorization credentials that were provided. 783

CTGDJG024I An attribute called 'command.line' has been provided in the Input Entry. The value entered for 'command' provided on the configuration screen, '*value*', will be disregarded. 783

CTGDJG025I Using the remote configuration option '*option*' = '*value*'. 783

CTGDJG026I About to remotely execute the command: '*command*'. 783

CTGDJG027I The command has been executed remotely. 783

CTGDJG028I No connection exists. 784

CTGDJG029I Starting Initialization of Function Component, '*class name*'. . . . 784

CTGDJG030I Finished initialization of Function Component, '*class name*'.
Initialized with value of: '*boolean*'. . . 784

CTGDJC031I Initializing the Function Component parameters.	784	CTGDJC052I The value provided for the input Entry attribute, ' <i>attribute value</i> ', is not of the correct type. Therefore, this entry attribute will be disregarded. The value provided should be of type <code>java.lang.String</code>	789
CTGDJC032I Initializing the Function Component option ' <i>name</i> ' = ' <i>value</i> '.	784	CTGDJC053I A port number has been provided when attempting to create a Windows connection. It is not possible to specify a port number for this type of connection. Therefore, the supplied port will be disregarded.	789
CTGDJC033I Finding a suitable protocol to create a connection.	785	CTGDJC054I Internal RXA Debug Message from RXA method <i>method name</i> : ' <i>message</i> '.	789
CTGDJC034I Protocol chosen ' <i>protocol name</i> '.	785	CTGDJC055I Internal RXA Info Message from RXA method <i>method name</i> : ' <i>message</i> '.	790
CTGDJC035I A connection could not be established using the provided parameters. Check the values and try again.	785	CTGDJC056I Internal RXA Warning Message from RXA method <i>method name</i> : ' <i>message</i> '.	790
CTGDJC036I Initializing Function Component parameters done.	785	CTGDJC057E Internal RXA Error Message from RXA method <i>method name</i> : ' <i>message</i> '.	790
CTGDJC037E A connection to the remote machine does not exist so the specified command cannot be executed.	786	CTGDJC058I Creating the directory: ' <i>directory name</i> ' on the target computer.	790
CTGDJC038I Creating a connection using the ' <i>protocol name</i> ' protocol to host ' <i>host name</i> ' for user ' <i>user name</i> '.	786	CTGDIH301E AL Overview Report v.1.5	791
CTGDJC039I Beginning the ' <i>session name</i> ' session.	786	CTGDIH302E Expand All	791
CTGDJC040I Session started successfully.	786	CTGDIH303E Hide All	791
CTGDJC041I A suitable protocol could not be found. No connection has been made.	786	CTGDIH304E Resources	791
CTGDJC042I Creating a connection using the RSH protocol with the provided username on the specified host.	787	CTGDIH305E Script	791
CTGDJC043I Creating a connection using the SSH protocol with the provided username, keystore and passphrase on the specified host.	787	CTGDIH306E Configuration	792
CTGDJC044I The file ' <i>file name</i> ' could not be found.	787	CTGDIH307E Output Attribute Map	792
CTGDJC045I You have selected to use 'any' protocol, but no password has been provided. Therefore, only SSH or RSH connections will be attempted.	787	CTGDIH308E Input Attribute Map	792
CTGDJC046I You have selected to use 'any' protocol, but no password or SSH keystore details have been provided. Therefore, only an RSH connection will be attempted.	788	CTGDIH309E Link Criteria	792
CTGDJC047I The standard input destination directory on the target machine has been set to ' <i>directory name</i> '.	788	CTGDIH310E Reconnect Settings	792
CTGDJC048I The specified standard input will be used.	788	CTGDIH311E Delta Settings	793
CTGDJC049I Standard input has been appended to the specified command. The complete command that will be executed on the remote machine is: ' <i>command</i> '.	788	CTGDIH312E Parser	793
CTGDJC050I The standard input file ' <i>file name</i> ' has been successfully transferred to the destination directory ' <i>directory name</i> '.	788	CTGDIH313E Hooks	793
CTGDJC051I Removing the temporary directory: ' <i>directory name</i> '.	789	CTGDIH314E Entry Feed Container	793
		CTGDIH315E Data Flow Container	793
		CTGDIH316E Proxy Settings	794
		CTGDIH317E Settings	794
		CTGDIH318E Enabled	794
		CTGDIH319E Mode	794
		CTGDIH320E Type	794
		CTGDIH321E Match Any	795
		CTGDIH322E Operations	795
		CTGDKH001E Exception occurred while trying to read property file: <i>exception</i>	795
		CTGDJZ601E Rolling IdML Function Component accepts only a IBM Security Directory Integrator Entry as input.	795
		CTGDJZ602E Rolling IdML Function Component can be used only for IdML books stored as files (in-memory books are not allowed).	795
		CTGDJZ603I The book ' <i>book name</i> ' does not exist or is already closed.	796
		CTGDJZ604I The parameter <i>param name</i> was initialized with the value: ' <i>value</i> '.	796
		CTGDJZ605I Rolling IdML Function Component will work with book: ' <i>book name</i> '.	796
		CTGDJZ606I The name of the currently used book ' <i>book name</i> ' has been overridden to ' <i>new name</i> '.	796

CTGDJZ607E Parameter '*param name*' is not provided. 797

CTGDIK101E The SAP ABAP AS BOR Connector has failed to create an instance of the IBM Security Directory Integrator Function Component named '*Function Component name*'. This failure may have been caused by incorrect installation of the Function Component or incorrect Function Component name. 797

CTGDIK102E An error has been detected while initializing the Function Component named '*Function Component name*'. 797

CTGDIK103E An XSL transformation has failed. Ensure that a valid XML value has been supplied for the '*sapXml*' attribute. The source XSL file name is '*file name*'. 797

CTGDIK105E The XSL files for the Connector's putEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode. 798

CTGDIK106E The XSL files for the Connectors' modEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode. 798

CTGDIK107E The XSL files for the Connectors' deleteEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode. 799

CTGDIK108E The configured XSL file named '*file name*' does not exist. 799

CTGDIK109E The configured XSL file named '*file name*' is not a valid file. A possible cause of this error might be that the configured name is actually a directory. 799

CTGDIK110E The configured XSL file named '*file name*' is not readable. 799

CTGDIK111E The configuration parameter named '*parameter name*' is missing 800

CTGDIK112E The Attribute named '*file name*' is not present, or does not have a value in the Entry supplied. This attribute must be present in the Connector entry. 800

CTGDIK113W No search criteria have been defined for the Connectors' findEntry method. This method will return null to indicate no objects found. 800

CTGDIK114W An XSL transform was performed before calling an SAP RFC. The result of the XSL transform was an empty document. An empty transform result typically occurs when mandatory XPath or Parameters are missing. The RFC call will not be performed. 800

CTGDIK115W The XSL transform defined in file '*file name*' resulted in an empty XML document. An empty transform result typically occurs when mandatory XPath or Parameters are missing. The RFC call was not performed. 801

CTGDIK116W Some application level errors and warnings have been detected while creating the ABAP AS user. The operation may be incomplete. 801

CTGDIK117W Some application level errors and warnings have been detected while deleting the ABAP AS user. The operation may be incomplete. 801

CTGDIK118W Some application level errors and warnings have been detected while updating the ABAP AS user. The operation may be incomplete. 802

CTGDIK119E The Connector detected an exception during initialization. The message is: '*exception*'. 802

CTGDIK120E The Connector detected an exception while performing a schema query. The message is: '*exception*'. 802

CTGDIK121E The Connector detected an exception while adding an entry. The message is: '*exception*'. 802

CTGDIK122E The Connector detected an exception while deleting an entry. The message is: '*exception*'. 802

CTGDIK123E The Connector detected an exception while modifying an entry. The message is: '*exception*'. 803

CTGDIK124E The Connector detected an exception while attempting to find an entry. The message is: '*exception*'. 803

CTGDIK125E The Connector detected an exception while selecting entries in preparation for iterator mode processing. The message is: '*exception*'. 803

CTGDIK126E The Connector detected an exception while iterating through the known entries. The number of entries successfully processed before the exception was *number of entries*. The message is: '*exception*'. 803

CTGDIK127E No XSL style sheet files have been configured for the Connector running in '*Connector mode*' mode. This mode requires XSL style sheets to be defined. See the IBM Security Directory Integrator Users Guide for specific details. 804

CTGDIK128E Delete mode requires the attribute named '*sapXml*' to present if no Link Criteria have been defined. 804

CTGDIK129I Adding message to error list: '*message*'. 804

CTGDIK130I Adding message to warning list: '*message*'. 804

CTGDIK131I Extracting the return data from element named '*tag name*'. 804

CTGDIK132I Creating AbapErrorInfo object: message='message', error number='error number', error flag='error flag'.	805	CTGDIK320E Unable to parse the XML. Exception occurred: <i>exception</i>	810
CTGDIK133I The XML element to return is a table style element: 'boolean'.	805	CTGDIK321W Exception occurred while generating schema: <i>exception</i>	811
CTGDIK134I The result of pre RFC XSL call is: 'string'.	805	CTGDIK322E Unable to start the JCo IDoc Server.	811
CTGDIK135I The result of RFC call is: 'string'.	805	CTGDIK323I Polling for next IDoc request in getNextClient method.	811
CTGDIK136I Executing function for XSL file: 'file'.	805	CTGDIK324I The onCheckTID method was called for TID 'TID'. TID Management already in progress for this TID.	811
CTGDIK137I The findEntry method is returning the initialized entry.	806	CTGDIK325I The onCheckTID method was called for TID 'TID'. TID Management beginning now for this TID. Next handleRequest method call will begin the inbound processing.	811
CTGDIK138I The findEntry method is returning null.	806	CTGDIK326I TID Manager for TID 'TID' is not yet confirmed. Current status is 'status'.	812
CTGDIK300I Started JCo IDoc Server and listening for requests.	806	CTGDIK327I TID Manager for TID 'TID' is now confirmed.	812
CTGDIK302E Unable to initialize the Connector. Exception occurred: <i>exception</i>	806	CTGDIK328I The handleRequest method was invoked. Current TID value is 'TID'. Incoming IDoc list request contains 'number of IDocs' IDocs.	812
CTGDIK303E The 'parameter name' parameter must be set to use the SAP IDocs Connector.	807	CTGDIK329E Unable to convert IDoc request into a IBM Security Directory Integrator entry. The writeIDocToTDIEntry method returned null IDoc Entry.	812
CTGDIK304I Optional RFC Connection parameter 'parameter name' set with the value 'parameter value'.	807	CTGDIK330E No value provided for current transaction identifier. This list of IDocs will not be processed.	813
CTGDIK305I Connector configuration parameter 'parameter name' set with the value 'parameter value'.	807	CTGDIK331E Current TID 'TID' already has a TID Manager and is being processed. Ignoring this request.	813
CTGDIK306I Checking if TID Manager for TID 'TID' is available for processing.	807	CTGDIK332E No IDoc Entries available. Ignoring request for TID 'TID'.	813
CTGDIK307E No TID Manager found for TID 'TID'.	807	CTGDIK333I Created TID Manager for TID 'TID' with 'number of IDoc entries' IDoc entries for processing.	813
CTGDIK308I TID Manager for TID 'TID' is available for processing.	808	CTGDIK334E Unable to convert IDoc request into a IBM Security Directory Integrator entry. The Connector received a null JCoIDoc.Document object.	814
CTGDIK309W Provided poll time value is 0 or less. Single request will be processed only.	808	CTGDIK335I The handleRequest method was invoked. Current TID value is 'TID value'. Incoming RFM request is 'RFM name'.	814
CTGDIK310I Polling for next the IDoc request in getNextEntry method.	808	CTGDIK336W No TID received with this RFM request. Defaulting for TID Management processing.	814
CTGDIK311E Exception generated while polling.	808	CTGDIK337I RFM as XML: ['TID'].	814
CTGDIK312E Null Entry found in the Entry list of the TID Manager for TID 'TID'.	809	CTGDIK338E Unable to convert RFM request into a IBM Security Directory Integrator entry. No RFMs provided in request.	815
CTGDIK313W No TID provided with this RFM call. Manually removing the TID Manager to complete the TID Management cycle.	809	CTGDIK339E Unable to convert RFM request into a IBM Security Directory Integrator entry. The JCo.Function object received was null.	815
CTGDIK314I No Parser Attached to the Connector.	809	CTGDIK340I Storing RFM request as XML file 'file name'.	815
CTGDIK315I Finished processing TID Manager for TID 'TID'. TID ready for confirmation.	809		
CTGDIK316E The getNextEntry method returned null in Iterator mode with a valid poll time.	809		
CTGDIK317W Entry contains no XML attributes to parse.	810		
CTGDIK318I Attempting to parse XML content with attached Parser.	810		
CTGDIK319W The attached Parser returned a null Entry.	810		

CTGDIK341E Failed to read RFM request XML file ' <i>file name</i> ' into IBM Security Directory Integrator Entry. No contents found in file.	815	CTGDIK203E Entry Attribute ' <i>attribute name</i> ' missing value or value does not match expected type. Expected type: ' <i>document type</i> '.	821
CTGDIK342E Failed to process RFM XML file. Exception occurred: <i>exception</i>	816	CTGDIK204E Entry attribute ' <i>attribute name</i> ' must be one of 'xmlDomDocument', 'xmlString', or 'multiValuedAttributes'.	822
CTGDIK343E An exception occurred. Exception trapped from JCo Server with Program ID of ' <i>Program ID</i> ': <i>exception</i>	816	CTGDIK205E Entry object expected.	822
CTGDIK344E An error was encountered. An error message was trapped from JCo Server with Program ID of ' <i>Program ID</i> ': <i>error message</i>	816	CTGDIK206E Must call initialize() first.	822
CTGDIK345I State Change occurred for JCo Server with Program ID of ' <i>Program ID</i> '. Previous State: ' <i>old state</i> '. New State: ' <i>new state</i> '.	816	CTGDIK207E Function cannot be reused once terminate() has been called.	822
CTGDIK346I Trace message trapped from JCo Server. Trace Level: ' <i>trace level</i> '. Trace Message: ' <i>trace message</i> '.	817	CTGDIK208E ' <i>class name</i> ' != ' <i>class name</i> '.	822
CTGDIK347W File was not able to be deleted: ' <i>file name</i> '.	817	CTGDIK209E Mandatory RFC parameter named ' <i>field name</i> ' has not been supplied.	823
CTGDIK348I Import parameter: ' <i>value</i> '.	817	CTGDIK210E Length of supplied value for field ' <i>field name</i> ' exceeds maximum length ' <i>field length</i> '.	823
CTGDIK349I The import parameter is a structure.	817	CTGDIK211E ' <i>class name</i> ' does not equal ' <i>class name</i> '.	823
CTGDIK350I The import parameter is a table.	817	CTGDIK212E Mandatory RFC parameter named ' <i>field name</i> ' has not been supplied.	823
CTGDIK351I The import parameter is a simple field.	818	CTGDIK213E No such function named ' <i>function name</i> '.	824
CTGDIK352I No Input Fields required for this RFM.	818	CTGDIK214E The remove method is not implemented.	824
CTGDIK353I RFM export Parameters:-----	818	CTGDIK215E The Function Component detected an exception while attempting to disconnect. The message is: ' <i>exception</i> '.	824
CTGDIK354I The export parameter is a structure.	818	CTGDIK216E Connection pool ' <i>pool name</i> ' already exists. The message is: ' <i>exception</i> '.	824
CTGDIK355I The export parameter is a simple field.	818	CTGDIK217E No more connections available in ' <i>pool name</i> '. The message is: ' <i>exception</i> '.	824
CTGDIK356I No Export Fields returned for this RFM.	819	CTGDIK218E Unable to establish a connection using ' <i>pool name</i> '. The message is: ' <i>exception</i> '.	825
CTGDIK357I RFM table Parameters:-----	819	CTGDIK219E Unable to execute RFC ' <i>function name</i> '. The message is: ' <i>exception</i> '.	825
CTGDIK358I Rows found for table: ' <i>table name</i> '.	819	CTGDIK220E Communication error with SAP ABAP Application Server. The message is: ' <i>exception</i> '.	825
CTGDIK359I No rows found for table: ' <i>table name</i> '.	819	CTGDIK221W Trouble invoking ' <i>function name</i> '. The function has been retried apos;'number of retries' times.	825
CTGDIK360I Field ' <i>field name</i> ' has string value ' <i>value</i> '.	819	CTGDIK222E Trouble invoking ' <i>function name</i> '. The function has been retried apos;'number of retries' times. The message is: ' <i>exception</i> '.	825
CTGDIK362I Field ' <i>field name</i> ' has raw value ' <i>value</i> '.	820	CTGDIK223E Unable to create DOM parser. The message is: ' <i>exception</i> '.	826
CTGDIK364I A bad field value passed.	820	CTGDIK224E Unable to parse DOM parser. The message is: ' <i>exception</i> '.	826
CTGDIK365I Input is a Record. Record fields are as follows:	820	CTGDIK225E Unable to read DOM parser. The message is: ' <i>exception</i> '.	826
CTGDIK366I Record field: ' <i>value</i> '.	820	CTGDIK226E Failed to prepare parameters for RFC. The message is: ' <i>exception</i> '.	826
CTGDIK367I Input is a table. Table records are as follows:	820		
CTGDIK368I Input is a structure. Structure records are as follows:	821		
CTGDIK201E Must call the initialize method first!	821		
CTGDIK202E Entry Attribute ' <i>attribute name</i> ' missing value.	821		

CTGDIK227I Executing function for XSL file:: ' <i>file</i> '. Multiple elements with name ' <i>element name</i> ' are present in the structure type. Using the element in first position following the preorder traversal.	826
CTGDIK228I DOM: Connecting to SAP ABAP Application Server...	827
CTGDIK229I DOM: Connecting to SAP ABAP Application Server...	827
CTGDIK230I DOM: Getting the dynamic proxy.	827
CTGDIK231I DOM: Getting the importer.	827
CTGDIK232I DOM: Populating the request with data values.	827
CTGDIK233I DOM: Executing RFC: ' <i>function name</i> '.	828
CTGDIK234I DOM: Exporting RFC results.	828
CTGDIK235I DOM: Disconnecting...	828
CTGDIK236I XSchema: Connecting to the SAP system.	828
CTGDIK237I XSchema: Getting the dynamic proxy.	828
CTGDIK238I XSchema: Creating the importer.	829
CTGDIK239I XSchema: Populating the request with data values.	829
CTGDIK240I XSchema: Disconnecting...	829
CTGDIK241I XSchema: Getting the importer.	829
CTGDIK242I Entry: Connecting to SAP system...	829
CTGDIK243I Entry: Getting the dynamic proxy..	830
CTGDIK244I Entry: Disconnecting...	830
CTGDIK245I The input entry is: ' <i>entry</i> '.	830
CTGDIK246I Obtaining RFC request from DOM Document.	830
CTGDIK247I Invoking RFC from DOM Document.	830
CTGDIK248I Obtaining RFC request from XML string.	831
CTGDIK249I Invoking RFC from XML string.	831
CTGDIK250I Invoking RFC using MVA parameter.	831
CTGDIK251I Using JCo config option ' <i>option name</i> ': ' <i>option value</i> '.	831
CTGDIK252I The supplied options are not supported or were incomplete. Usage: java -cp (SAP_JCO_HOME)/sapjaco.jar;(TDI_HOME)/jars/functions/SapR3RfcFC.jar -Djava.library.path=(SAP_JCO_HOME) com.ibm.di.fc.sapr3rfc.RfcXmlInvoker-f [input XML file] -o [output XML file] -p [JCO Connection properties file] -f The name of the file containing the input RFC request as XML. -o The name of the file to be produced containing RFC response as XML. -p The JCO Connection properties file.	832
CTGDIK253I Input entry value: ' <i>entry value</i> '.	832

CTGDIK001E The SAP ABAP Application Server User Registry Connector failed to create an instance of the Security Directory Integrator Function Component ' <i>Function Component Name</i> '. This failure may have been caused by incorrect installation of the Function Component or an incorrect Function Component name.	832
CTGDIK002E An error has been detected while initializing the Function Component ' <i>Function Component name</i> '.	833
CTGDIK003E An XSL transformation has failed. Ensure that a valid XML value has been supplied for the 'sapUserXml' attribute. The source XSL file name is ' <i>file name</i> '.	833
CTGDIK005E The XSL files for the Connectors' putEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.	833
CTGDIK006E The XSL files for the Connectors' modEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.	834
CTGDIK007E The XSL files for the Connectors' deleteEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.	834
CTGDIK008E The configured XSL file named ' <i>file name</i> ' does not exist.	834
CTGDIK009E The configured XSL file named ' <i>file name</i> ' is not a valid file. A possible cause of this error might be that the configured name is actually a directory.	835
CTGDIK010E The configured XSL file named ' <i>file name</i> ' is not readable.	835
CTGDIK011E The configuration parameter named ' <i>file name</i> ' is missing. The configured Connector mode requires additional configuration of this parameter. Ensure these values have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode. See the IBM Security Directory Integrator Users Guide for specific details.	835
CTGDIK012E The Attribute named ' <i>attribute name</i> ' is not present, or does not have a value, in the Entry supplied. This attribute must be present in the Connector entry.	835
CTGDIK013W No search criteria have been defined for the Connectors' findEntry method. This method will return null to indicate no objects found.	836

CTGDIK014W An XSL transform was performed before calling an SAP RFC. The result of the XSL transform was an empty document. An empty transform result typically occurs when mandatory XPath or Parameters are missing; for example, sapUserName. The RFC call will not be performed. 836

CTGDIK015W The XSL transform defined in file '*file name*' resulted in an empty XML document. An empty transform result typically occurs when mandatory XPath or Parameters are missing, e.g. sapUserName. The RFC call was not performed. 836

CTGDIK016W Some application level errors and warnings have been detected while creating the SAP ABAP AS user. The operation may be incomplete. 837

CTGDIK017W Some application level errors and warnings have been detected while deleting the SAP ABAP AS user. The operation may be incomplete. 837

CTGDIK018W Some application level errors and warnings have been detected while updating the SAP ABAP AS user. The operation may be incomplete. 837

CTGDIK019E The Connector detected an exception during initialization. The message is: '*exception*'. 837

CTGDIK020E The Connector detected an exception while performing a schema query. The message is: '*exception*'. 838

CTGDIK021E The Connector detected an exception while adding an entry. The message is: '*exception*'. 838

CTGDIK022E The Connector detected an exception while deleting an entry. The message is: '*exception*'. 838

CTGDIK023E The Connector detected an exception while modifying an entry. The message is: '*exception*'. 838

CTGDIK024E The Connector detected an exception while attempting to find an entry. The message is: '*exception*'. 838

CTGDIK025E The Connector detected an exception while selecting entries in preparation for iterator mode processing. The message is: '*exception*'. 839

CTGDIK026E The Connector detected an exception while iterating through the known entries. The number of entries successfully processed before the exception was *number of entries*. The message is: '*exception*'. 839

CTGDIK027E No XSL style sheet files have been configured for the Connector running in '*Connector mode*' mode. This mode requires XSL style sheets to be defined. See the IBM Security Directory Integrator Users Guide for specific details. 839

CTGDIK028I The findEntry method is returning null. 839

CTGDIK029I The findEntry method is returning the initialized entry. 840

CTGDIK030I The findEntry method is returning null. 840

CTGDIK031I Adding message to error list: '*message*'. 840

CTGDIK032I Adding message to warning list: '*message*'. 840

CTGDIK033I Extracting the return data from element named '*tag name*'. 840

CTGDIK034I Creating AbapErrorInfo object: message='*message*', error number='*error number*', error flag='*error flag*'. 841

CTGDIK035I The XML element to return is a table style element: '*boolean*'. 841

CTGDIK036I The result of pre RFC XSL call is: '*string*'. 841

CTGDIK037I The result of RFC call is: '*string*'. 841

CTGDIK038I Executing function for XSL file: '*file*'. 841

CTGDIR001W Unable to load script libraries. The Script Connector has no associated MetamergeConfig object. 842

CTGDIR002E Operation 'selectEntries' failed in Script Connector: '*error message*'. 842

CTGDIR003E Operation 'getNextEntry' failed in Script Connector: '*error message*'. 842

CTGDIR004E Operation 'modEntry' failed in Script Connector: '*error message*'. 842

CTGDIR005E Operation 'deleteEntry' failed in Script Connector: '*error message*'. 842

CTGDIR006E Operation 'findEntry' failed in Script Connector: '*error message*'. 843

CTGDIR007E Operation 'putEntry' failed in Script Connector: '*error message*'. 843

CTGDIR008E Operation 'queryReply' failed in Script Connector: '*error message*'. 843

CTGDIR009E Operation 'querySchema' failed in Script Connector: '*error message*'. 843

CTGDIR010I Script Connector configured to execute script: *script* 843

CTGDIR011I The Script Connector will keep its global state. 844

CTGDJT010E The Scripted FC failed because the getUI method returned an unknown GUI object type: '*object type*'. 844

CTGDJT001I Declaring the user functions. 844

CTGDJT002I Declaring my configuration. 844

CTGDJT003I Declaring the input and output streams. 844

CTGDJT004I Executing the following script: '*script*'. 845

CTGDJT005E Required Connector parameter '*script*' is not set. 845

CTGDJT006W Unable to load script libraries. The Script Connector has no associated MetamergeConfig object. 845

CTGDJT007E Script Parser encountered error while reading entry: '*error*'. 845

CTGDJT008E Script Parser encountered error while writing entry: <i>'error'</i>	845
CTGDJT009E Script Parser encountered error while querying schema: <i>'error'</i>	846
CTGDIF001E The perform method of the Function Component was not passed an object of type <code>com.ibm.di.entry.Entry</code> . This object is not a valid parameter to pass to perform method.	846
CTGDIF002E The Entry Attribute <i>'attribute name'</i> is not present in the Entry.	846
CTGDIF003E The required Function Component parameter <i>'parameter name'</i> is not set.	846
CTGDIF004E The following Function Component parameter was not set or its corresponding Entry Attribute was not mapped: <i>'parameter name'</i>	847
CTGDIF005I The parameter <i>parameter name</i> was initialized with the value: <i>'parameter value'</i>	847
CTGDKD001E Unable to read custom script from file: <i>property</i>	847
CTGDKD002E Invalid value specified for <code>'api.remote.naming.port'</code> : <i>'parameter value'</i>	847
CTGDKD003I Will use default value for <code>'api.remote.naming.port'</code> : <i>'port'</i>	847
CTGDKD004E Could not create RMI custom socket factories. Exception occurred: <i>exception</i>	848
CTGDKD005E Could not get localhost IP address.	848
CTGDKD006E Server API not initialized.	848
CTGDKD007I Secure RMI socket factories created successfully.	848
CTGDKD008I Remote Session Factory object bound to name <code>'SessionFactory'</code>	848
CTGDKD009E Could not create SessionFactory. Exception occurred: <i>exception</i>	849
CTGDKD010E Could not bind RemoteSessionFactory.	849
CTGDKD011E Unable to get TombstonesConfig. Exception occurred: <i>exception</i>	849
CTGDKD012I RMI Registry started on port: <i>port number</i>	849
CTGDKD013I Successfully connected to RMI Registry: <i>existing registry</i>	849
CTGDKD019E Could not create RMI Registry:	850
CTGDKD020E Server cryptography is already initialized.	850
CTGDKD021E LDAP Authentication initialization error.	850
CTGDKD022E LDAP Authentication initialization error: <i>exception</i>	850
CTGDKD023I Remote API Engine successfully initialized. SSL and Client Authentication are enabled.	850

CTGDKD024I Remote API successfully started on port: <i>port</i> , bound to: <code>'SessionFactory'</code> . SSL and Client Authentication are enabled.	851
CTGDKD025E Unable to initialize ScriptEngine:	851
CTGDKD026E Custom authentication is disabled.	851
CTGDKD027E Script error:	851
CTGDKD028I Authentication failed for user: <i>username</i>	851
CTGDKD029E Missing configuration property: <code>api.config.folder</code>	852
CTGDKD030E Unable to get canonical path of the <code>'api.config.folder'</code> property value: <i>path</i> . Exception occurred: <i>exception</i>	852
CTGDKD031E Invalid value specified for <code>'api.config.lock.timeout'</code> : <i>'paramater value'</i> . Exception occurred: <i>exception</i>	852
CTGDKD032I Will use default value for <code>'api.config.lock.timeout'</code> : <i>value</i>	852
CTGDKD034E Invalid folder path: <i>'path'</i>	852
CTGDKD035E Invalid folder path: <i>'path'</i>	853
CTGDKD036E Configuration <i>'path'</i> is already checked out.	853
CTGDKD037E Configuration <i>'path'</i> is password protected.	853
CTGDKD038E Error while loading configuration <i>'path'</i>	853
CTGDKD039E Configuration <i>'path'</i> is already checked out.	853
CTGDKD041E Configuration <i>'path'</i> is not checked out.	853
CTGDKD042E Configuration <i>'path'</i> is not checked out.	854
CTGDKD043E Configuration file <i>'path'</i> already exists.	854
CTGDKD044E Configuration <i>'path'</i> is already checked out.	854
CTGDKD045E Could not load configuration <i>'path'</i>	854
CTGDKD046E recurseDirs: Invalid folder path: <i>'directory'</i>	854
CTGDKD047E Internal error: NULL user ID in configuration registry for <i>'path'</i>	855
CTGDKD048I The Config <i>'file path'</i> was locked by the user <i>'user ID'</i>	855
CTGDKD049I The Config <i>'file path'</i> lock was released.	855
CTGDKD050I The Config <i>'file path'</i> lock time was reset.	855
CTGDKD051E Unable to save the Config because the configuration path <i>'file path'</i> could not be set.	855
CTGDKD052E Unable to save the Config <i>'file path'</i>	856
CTGDKD053E Unable to save the Config <i>'file path'</i> because the Config is not committable.	856
CTGDKD054I Stopped Config instance <i>'file path'</i>	856

CTGDKD055E Unable to stop Config instance ' <i>file path</i> '. The Config instance was not found.	856	CTGDKD085E Username is null. Authentication failed.	862
CTGDKD056I Reloaded Config instance ' <i>file path</i> '.	856	CTGDKD086E Password is null. Authentication failed.	862
CTGDKD057E Unable to reload Config instance ' <i>file path</i> '. An exception was encountered: <i>exception</i>	857	CTGDKD087I Performing search for full DN for ' <i>username</i> ' with filter: <i>filter</i>	862
CTGDKD058E Unable to reload Config instance ' <i>file path</i> '. The Config instance was not found.	857	CTGDKD088I Using LDAP SSL connection.	862
CTGDKD059E Automatic unlock thread of the configuration registry was interrupted. An exception was encountered: <i>exception</i>	857	CTGDKD089E Authentication failed for ' <i>username</i> '. Exception occurred: <i>exception</i>	862
CTGDKD060E Automatic unlock thread of the configuration registry encountered a fatal exception: <i>exception</i>	857	CTGDKD090I LDAP Authentication succeeded for ' <i>username</i> '.	863
CTGDKD061E Automatic unlock thread of the configuration registry could not stop Config instance ' <i>Config instance ID</i> '. An exception was encountered: <i>exception</i>	857	CTGDKD091I LDAP Authentication module closed.	863
CTGDKD062I The Config instance ' <i>Config instance ID</i> ' was automatically unlocked.	858	CTGDKD092I Using Simple authentication for search context.	863
CTGDKD063E Absolute path provided : <i>path</i> expecting relative.	858	CTGDKD093I Using Anonymous authentication for search context.	863
CTGDKD065E Path provided : <i>path</i> is not allowed.	858	CTGDKD094I Using LDAP SSL connection.	863
CTGDKD066E Config Instance is NULL.	858	CTGDKD095I Trying to create search context	864
CTGDKD067E Config Instance is NULL.	858	CTGDKD096I Search context created.	864
CTGDKD068E AssemblyLine is NULL.	858	CTGDKD097E Error while creating search context: <i>exception</i>	864
CTGDKD069E Config Instance for AssemblyLine ' <i>AssemblyLine</i> ' not registered.	859	CTGDKD098E More than one search result found. Authentication failed for ' <i>username</i> '.	864
CTGDKD070E AssemblyLine is NULL.	859	CTGDKD099E Full DN not found. Authentication failed for ' <i>username</i> '.	864
CTGDKD071E On AL terminate: Config Instance for AssemblyLine ' <i>AssemblyLine</i> ' not registered.	859	CTGDKD100E Missing property ' <i>property</i> '.	865
CTGDKD072E EventHandler is NULL.	859	CTGDKD101E Missing property ' <i>property</i> '.	865
CTGDKD073E Config Instance for EventHandler ' <i>EventHandler</i> ' not registered.	859	CTGDKD102E Unable to create search context.	865
CTGDKD074E EventHandler is NULL.	860	CTGDKD103E AuthenticationException: Unable to parse ErrorCode : <i>error code</i>	865
CTGDKD075E On EventHandler terminate: Config Instance for EventHandler ' <i>EventHandler</i> ' not registered.	860	CTGDKD104I User not authenticated.	865
CTGDKD076E Trigger is NULL.	860	CTGDKD105I Configuration already exists.	865
CTGDKD077E Config Instance for Trigger ' <i>trigger name</i> ' not registered.	860	CTGDKD106I Configuration is not checked out.	866
CTGDKD078E Trigger is NULL.	860	CTGDKD107E Server API JMX Agent already initialized.	866
CTGDKD079E On EH terminate: Config Instance for Trigger ' <i>trigger name</i> ' not registered.	860	CTGDKD108I Server API JMX Agent successfully initialized.	866
CTGDKD080E Listener object is NULL.	861	CTGDKD109E Could not initialize Server API JMX Agent.	866
CTGDKD081E Error on handleEvent method: <i>exception</i>	861	CTGDKD110E Server API JMX Agent is not initialized. Cannot initialize JMX Remoting.	866
CTGDKD082E Error on handleEvent method: <i>exception</i>	861	CTGDKD111I JMX Remote Server Connector started at: <i>URL</i>	867
CTGDKD083E Event type is NULL.	861	CTGDKD112E Could not initialize Server API JMX Remoting.	867
CTGDKD084I Not authorized to perform this operation.	861	CTGDKD113E Server API JMX Agent not initialized.	867
		CTGDKD114I JMX MBean registered: <i>object name</i>	867
		CTGDKD115E Server API JMX Agent not initialized.	867
		CTGDKD116I JMX MBean unregistered: <i>object name</i>	867
		CTGDKD117E Server API JMX Agent not initialized.	868

CTGDKD118E Server API JMX Agent not initialized.	868	CTGDKD143E JMX Notification service could not handle custom notification event: <i>exception</i>	873
CTGDKD119E Could not initialize/register Notification service. Exception occurred: <i>exception</i>	868	CTGDKD144E Could not create AssemblyLine JMX Object Name.	873
CTGDKD120E JMX Server API Listener already initialized.	868	CTGDKD145E Could not unregister AssemblyLineHandler MBean. Exception occurred: <i>exception</i>	873
CTGDKD121E Local Session is NULL.	868	CTGDKD146E Could not create AssemblyLineHandler JMX Object Name.	873
CTGDKD122I JMX Server API Listener successfully registered.	869	CTGDKD147E Listener object is NULL.	873
CTGDKD123I DIEvent received: <i>event</i>	869	CTGDKD148E Listener object is NULL.	874
CTGDKD124E Unrecognized event type: <i>event type</i> . Event skipped.	869	CTGDKD149I JMX MBean call from remote user: <i>'userId'</i>	874
CTGDKD125E Could not register AssemblyLine MBean.	869	CTGDKD150E Error retrieving JMX remote user ID: <i>exception</i>	874
CTGDKD126E JMX Notification service could not handle event for AssemblyLine start: <i>exception</i>	869	CTGDKD151E Could not register AssemblyLineHandler MBean.	874
CTGDKD127E Could not register Config Instance MBean.	870	CTGDKD152E Exception on JMX <i>assemblyLineCycleDone(): exception</i>	874
CTGDKD128E Could not register TDIProperties MBean.	870	CTGDKD153E Exception on JMX <i>assemblyLineFinished(): exception</i>	874
CTGDKD129E Could not register TDIProperties MBean.	870	CTGDKD154E Exception on JMX <i>messageLogged method: exception</i>	875
CTGDKD130E JMX Notification service could not handle event for ConfigInstance start. Exception occurred: <i>exception</i>	870	CTGDKD155E Exception on JMX <i>eventCaptured(): exception</i>	875
CTGDKD131E Could not register EventHandler MBean.	870	CTGDKD156E Exception on JMX <i>eventProcessed method: exception</i>	875
CTGDKD132E JMX Notification service could not handle event for EventHandler start: <i>exception</i>	870	CTGDKD157E Exception on JMX <i>eventHandlerTerminated method: exception</i>	875
CTGDKD133E Could not unregister AssemblyLine MBean: <i>exception</i>	871	CTGDKD158E Exception on JMX <i>messageLogged(): exception</i>	875
CTGDKD134E JMX Notification service could not handle event for AssemblyLine stop. Exception occurred: <i>exception</i>	871	CTGDKD159E Could not create ConfigInstance JMX Object Name.	876
CTGDKD135E Could not unregister EventHandler MBean. Exception occurred: <i>exception</i>	871	CTGDKD160E Could not create EventHandler JMX Object Name.	876
CTGDKD136E JMX Notification service could not handle event for EventHandler stop. Exception occurred: <i>exception</i>	871	CTGDKD161E Listener object is NULL.	876
CTGDKD137E Could not unregister Config Instance MBean. Exception occurred: <i>exception</i>	871	CTGDKD162E Listener object is NULL.	876
CTGDKD138E Could not unregister TDIProperties MBean: <i>exception</i>	872	CTGDKD163E JMX Notification Service already initialized.	876
CTGDKD139E Could not unregister TDIProperties MBean.	872	CTGDKD164E JMX Notification service is not started (initialized).	876
CTGDKD140E JMX Notification service could not handle event for Config Instance stop. Exception occurred: <i>exception</i>	872	CTGDKD165E Could not create JMX Notifier Object Name.	877
CTGDKD141E JMX Notification service could not handle event for Config Instance file updated. Exception occurred: <i>exception</i>	872	CTGDKD166E Could not create TDIProperties JMX Object Name.	877
CTGDKD142E JMX Notification service could not handle Server stop event. Exception occurred: <i>exception</i>	872	CTGDKD167E AssemblyLine object is NULL.	877
		CTGDKD168E Raw AssemblyLine object is NULL.	877
		CTGDKD169E Session object is NULL.	877
		CTGDKD170E Could not execute AssemblyLine cycle.	878
		CTGDKD171E Could not execute AssemblyLine cycle.	878
		CTGDKD172E Could not execute AssemblyLine cycle.	878
		CTGDKD173E Could not close AssemblyLine.	878
		CTGDKD174E Raw AssemblyLine object is NULL.	878
		CTGDKD175E Config Instance object is NULL.	878

CTGDKD176E Session object is NULL.	879	CTGDKD210E Unable to obtain config object.	885
CTGDKD177E Error while obtaining SystemLog for AssemblyLine: <i>AssemblyLine name.AssemblyLine hash code</i>	879	CTGDKD211E Could not retrieve AssemblyLines Folder.	885
CTGDKD178E Could not get AssemblyLine configuration.	879	CTGDKD212E AssemblyLines Folder object is NULL.	885
CTGDKD179E Raw Config Instance is NULL.	879	CTGDKD213E getAssemblyLineCfg: Could not retrieve configuration for AssemblyLine ' <i>AssemblyLine name</i> '.	885
CTGDKD180E Session object is NULL.	879	CTGDKD214E getAssemblyLineCfg: AssemblyLine ' <i>AssemblyLine name</i> '. Configuration object is NULL.	885
CTGDKD181E Raw Config Instance is not running.	879	CTGDKD215E Could not retrieve EventHandlers Folder.	886
CTGDKD182E User ' <i>User ID</i> ' cannot set configuration for: <i>Config ID</i>	880	CTGDKD216E EventHandlers Folder object is NULL.	886
CTGDKD183E Not a supported call.	880	CTGDKD217E Error updating configuration lock time: <i>exception</i>	886
CTGDKD184E Not a supported call.	880	CTGDKD218E Raw Switchboard object is NULL.	886
CTGDKD185E Could not obtain External Properties.	880	CTGDKD219E Config Instance object is NULL.	886
CTGDKD186E Could not obtain External Properties.	880	CTGDKD220E Session object is NULL.	887
CTGDKD187E Could not obtain External Properties Keys.	881	CTGDKD221E Error while obtaining SystemLog for EventHandler: <i>Switchboard name.Switchboard hashcode</i>	887
CTGDKD188E Not a supported call.	881	CTGDKD222E Raw Trigger object is NULL.	887
CTGDKD189E Not a supported call.	881	CTGDKD223E Config Instance object is NULL.	887
CTGDKD190E Not a supported call.	881	CTGDKD224E Session object is NULL.	887
CTGDKD191E Could not retrieve AssemblyLines names.	881	CTGDKD225E Error while obtaining SystemLog for EventHandler: <i>trigger name.trigger hashcode</i>	887
CTGDKD192E Could not obtain AssemblyLine input schema.	881	CTGDKD226E Internal error: invalid EventHandler type: <i>EventHandler type</i>	888
CTGDKD193E Could not obtain AssemblyLine output schema.	882	CTGDKD227E Internal error: invalid EventHandler type: <i>EventHandler type</i>	888
CTGDKD194E Could not retrieve EventHandlers names.	882	CTGDKD228E Internal error: invalid EventHandler type: <i>EventHandler type</i>	888
CTGDKD195E Not authorized to execute AssemblyLine: <i>AssemblyLine</i>	882	CTGDKD229E Could not retrieve Connectors names.	888
CTGDKD196E Could not start AssemblyLine <i>AssemblyLine</i>	882	CTGDKD230E Could not retrieve ' <i>Connector Name</i> ' description. Exception occurred: <i>exception</i>	888
CTGDKD197E Not authorized to execute AssemblyLine: <i>AssemblyLine</i>	882	CTGDKD231E Could not retrieve ' <i>Connector name</i> ' version info. Exception occurred: <i>exception</i>	889
CTGDKD198E Could not start AssemblyLine <i>AssemblyLine</i>	882	CTGDKD232E Could not retrieve Connector's names.	889
CTGDKD199E Not authorized to execute AssemblyLine: <i>AssemblyLine</i>	883	CTGDKD233E Could not retrieve description for Connector ' <i>Connector name</i> '.	889
CTGDKD200E Could not start AssemblyLine <i>AssemblyLine</i>	883	CTGDKD234E Could not retrieve class name for Connector ' <i>Connector name</i> '.	889
CTGDKD201E Not authorized to execute AssemblyLine: <i>AssemblyLine</i>	883	CTGDKD235E Could not retrieve EventHandler's names.	889
CTGDKD202E Could not start AssemblyLine <i>AssemblyLine</i>	883	CTGDKD236E Could not retrieve ' <i>EventHandler name</i> ' description. Exception occurred: <i>exception</i>	890
CTGDKD203E Not authorized to execute EventHandler: <i>EventHandler</i>	883	CTGDKD237E Could not retrieve ' <i>EventHandler name</i> ' enabled status. Exception occurred: <i>exception</i>	890
CTGDKD204E Could not start EventHandler.	884		
CTGDKD205E Could not reload Config Instance.	884		
CTGDKD206E Connector Pool does not exist: <i>Connector Pool name</i>	884		
CTGDKD207E Connector Pool does not exist: <i>Connector Pool name</i>	884		
CTGDKD208E Connector Pool does not exist: <i>Connector Pool name</i>	884		
CTGDKD209E Connector Pool does not exist: <i>Connector Pool name</i>	885		

CTGDKD238E Could not retrieve 'EventHandler name' version info. Exception occurred: <i>exception</i>	890	CTGDKD264E Not supported Server API call: createNewConfigInstance.	895
CTGDKD239E Could not retrieve EventHandlers names.	890	CTGDKD265E InternalError: Unknown EventHandler type: <i>class name</i>	895
CTGDKD240E Could not retrieve description for EventHandler apos;'EventHandler name'.	890	CTGDKD266E User with ID: <i>user ID</i> not authorized.	895
CTGDKD241E Could not retrieve enabled status for EventHandler 'EventHandler name'.	891	CTGDKD267E Could not get default System Queue.	895
CTGDKD242E Could not retrieve class name for EventHandler 'EventHandler name'.	891	CTGDKD268E Could not getMessage. Exception occurred: <i>exception</i>	896
CTGDKD243E Could not retrieve Parsers names.	891	CTGDKD269E Could not putMessage. Exception occurred: <i>exception</i>	896
CTGDKD244E Could not retrieve 'Parser name' description. Exception occurred: <i>exception</i>	891	CTGDKD270E Could not getTextMessage. Exception occurred: <i>exception</i>	896
CTGDKD245E Could not retrieve 'Parser name' version info. Exception occurred: <i>exception</i>	891	CTGDKD271E Could not putTextMessage. Exception occurred: <i>exception</i>	896
CTGDKD246E Could not retrieve Parsers names.	892	CTGDKD272E Could not getBytesMessage. Exception occurred: <i>exception</i>	896
CTGDKD247E Could not retrieve description for Parser 'Parser name'.	892	CTGDKD273E Could not putBytesMessage. Exception occurred: <i>exception</i>	897
CTGDKD248E Could not retrieve class name for Parser 'Parser name'.	892	CTGDKD274E Could not getEntry. Exception occurred: <i>exception</i>	897
CTGDKD249E Could not retrieve Function Components names.	892	CTGDKD275E Could not putEntry. Exception occurred: <i>exception</i>	897
CTGDKD250E Could not retrieve 'Parser name' description. Exception occurred: <i>exception</i>	892	CTGDKD276E Local TDIProperties is NULL.	897
CTGDKD251E Could not retrieve 'Parser name' version info. Exception occurred: <i>exception</i>	893	CTGDKD277E Session object is NULL.	897
CTGDKD252E Could not retrieve Function Components names.	893	CTGDKD278E AssemblyLine object is NULL.	898
CTGDKD253E Could not retrieve description for Function Component 'Function Component name'.	893	CTGDKD279E Raw AssemblyLine Handler object is NULL.	898
CTGDKD254E Could not retrieve class name for Function Component 'Function Component name'.	893	CTGDKD280E Session object is NULL.	898
CTGDKD255E Component class ' <i>class name</i> ' not found.	893	CTGDKD281E Local AssemblyLine is NULL.	898
CTGDKD256E Access error on loading ' <i>class name</i> ' class.	893	CTGDKD282E Session object is NULL.	898
CTGDKD257E Could not instantiate class ' <i>class name</i> '.	894	CTGDKD283E Remote Listener object is NULL.	898
CTGDKD258E Could not retrieve version info for class ' <i>class name</i> '.	894	CTGDKD284E RemoteException on assemblyLineCycleDone method: <i>exception</i>	899
CTGDKD259E Could not retrieve password parameter names for class ' <i>class name</i> '.	894	CTGDKD285E RemoteException on assemblyLineFinished method: <i>exception</i>	899
CTGDKD260E Authentication failed for user: <i>username</i> . Exception occurred: <i>exception</i>	894	CTGDKD286E RemoteException on messageLogged method: <i>exception</i>	899
CTGDKD261E Config ID is NULL.	894	CTGDKD287E Listener object is NULL.	899
CTGDKD262E Could not start Config Instance.	895	CTGDKD288E Listener object is NULL.	899
CTGDKD263E Not supported Server API call: createNewConfigInstance.	895	CTGDKD289E Local Config Instance is NULL.	899
		CTGDKD290E Session object is NULL.	900
		CTGDKD291E MergeConfig.instantiateAllObjects method failed:	900
		CTGDKD292E Remote Listener object is NULL.	900
		CTGDKD293E RemoteException on handleEvent method.	900
		CTGDKD294E Listener object is NULL.	900
		CTGDKD295E Listener object is NULL.	901
		CTGDKD296E Local EventHandler is NULL.	901
		CTGDKD297E Session object is NULL.	901
		CTGDKD298E Remote Listener object is NULL.	901
		CTGDKD299E RemoteException on eventCaptured method.	901
		CTGDKD300E RemoteException on eventProcessed method.	901

CTGDKD301E RemoteException on eventHandlerTerminated method.	902
CTGDKD303E Listener object is NULL.	902
CTGDKD304E Listener object is NULL.	902
CTGDKD305E Local Security Registry object is NULL.	902
CTGDKD306E Session object is NULL.	902
CTGDKD307E Local Server Info object is NULL.	902
CTGDKD308E Session object is NULL.	903
CTGDKD309E SSL client authentication is disabled.	903
CTGDKD310E Unable to get userId.	903
CTGDKD311I Remote session created for user: <i>user ID</i>	903
CTGDKD312E Error in host authentication.	903
CTGDKD313E Host not allowed.	904
CTGDKD314I Remote session created with local Identity.	904
CTGDKD315I Remote session created for user: <i>username</i>	904
CTGDKD316E Authentication failed for user: <i>username</i> . Exception occurred: <i>exception</i>	904
CTGDKD317E Local System Log is NULL.	904
CTGDKD318E Session object is NULL.	905
CTGDKD319E Local TDIProperties is NULL.	905
CTGDKD320E Session object is NULL.	905
CTGDKD321E Local TombstoneManager is NULL.	905
CTGDKD322E Session object is NULL.	905
CTGDKD323E No Socket is associated with the current thread.	905
CTGDKD324E Unable to create socket. Exception occurred: <i>exception</i>	906
CTGDKD325E Required property is missing: <i>key</i>	906
CTGDKD326E Invalid type for property <i>'key'</i> : <i>class name</i>	906
CTGDKD328E No SSL socket is associated with the current thread.	906
CTGDKD329E SSL socket session is NULL.	906
CTGDKD330E SSL session certificate chain is empty.	907
CTGDKD331E Required property is missing: <i>key</i>	907
CTGDKD332E Invalid type for property <i>'key'</i> : <i>class name</i>	907
CTGDKD335E Input file ' <i>file name</i> ' does not exist.	907
CTGDKD336E Server cryptography is not initialized.	907
CTGDKD337E Illegal value ' <i>mode</i> ' for mode parameter.	907
CTGDKD346E Registry already initialized.	908
CTGDKD347E Registry file name is NULL.	908
CTGDKD348E Registry file ' <i>file name</i> ' does not exist.	908
CTGDKD349I Reading security registry	908
CTGDKD350I Decrypting security registry	908

CTGDKD351E Error while decrypting registry file.	908
CTGDKD352E Registry file not found.	909
CTGDKD353E Error while reading registry file.	909
CTGDKD354I Security registry successfully read.	909
CTGDKD355E Invalid tag at line <i>line</i> <i>number</i> : <i>line</i> . Expected '[USER]'.	909
CTGDKD356E No user ID specified.	909
CTGDKD357E Invalid tag at line <i>line</i> <i>number</i> : <i>line</i> . Expected '[ID]:'.	910
CTGDKD358E Empty user ID specified at line <i>line number</i>	910
CTGDKD359E Invalid User definition. User ID ' <i>user ID</i> ' at line <i>line number</i> has already been defined in the registry file.	910
CTGDKD360E User definition not closed at end of file.	910
CTGDKD361E Invalid tag at line <i>line</i> <i>number</i> : <i>line</i> . Expected '[ROLE]:' or '[ENDUSER]'.	910
CTGDKD362E Empty ROLE specified at line <i>line number</i>	911
CTGDKD363E Invalid ROLE specified at line <i>line number</i> : <i>role name</i>	911
CTGDKD364E User definition not closed at end of file.	911
CTGDKD365E Invalid tag at line <i>line</i> <i>number</i> : <i>line</i> . Expected '[CONFIG]:' or '[ROLE]:' or '[ENDUSER]'.	911
CTGDKD366E Empty CONFIG specified at line <i>line number</i>	911
CTGDKD367E User definition not closed at end of file.	911
CTGDKD368E Empty AL specified at line <i>line number</i>	912
CTGDKD369E Empty EH specified at line <i>line number</i>	912
CTGDKD370E Invalid tag at line <i>line</i> <i>number</i> : <i>line</i> . Expected '[AL]:' or '[EH]:' or '[CONFIG]:' or '[ROLE]:' or '[ENDUSER]'.	912
CTGDKD371E Role is NULL.	912
CTGDKD372E Invalid role: <i>aRole</i>	912
CTGDKD373E Log Listener is NULL.	913
CTGDKD374E Exception caught on messageLogged method: <i>exception</i>	913
CTGDKD375E The getSystemLogAppender method called with a NULL log; will return NULL.	913
CTGDKD376E GetComponentLog: LogFileName parameter is NULL or empty.	913
CTGDKD377E Error while reading ' <i>file</i> <i>name</i> ' log file.	913
CTGDKD378E LogFileName parameter is NULL or empty.	913
CTGDKD379E GetComponentLogLastChunk: Error while reading ' <i>file name</i> ' log file.	914
CTGDKD380E Component name parameter is NULL.	914

CTGDKD381E Component name parameter is NULL.	914	CTGDKD408E Error in retrieving last record to keep:	919
CTGDKD382E Min date parameter is NULL.	914	CTGDKD409E Error in deleting tombstone records:	919
CTGDKD383E Internal error: deleteAllOldCompLogs: Invalid component type: <i>component type</i>	914	CTGDKD410E Error in object deserialization:	920
CTGDKD384E Internal error: deleteAllOldCompLogs: Invalid component type: <i>component type</i>	915	CTGDKD411I Tombstones record count: <i>count</i>	920
CTGDKD385E Invalid component type specified for SystemLogAppender: ' <i>component type</i> '. The only valid values are 'AL' and 'EH'.	915	CTGDKD412E Error in count Tombstone records:	920
CTGDKD386E No component type assigned to SystemLog Appender.	915	CTGDKD413E Insert operation of tombstone record in database failed.	920
CTGDKD387E SystemLogAppender: component type has not been specified.	915	CTGDKD414E Tombstone Manager Listener already initialized.	920
CTGDKD388E SystemLogAppender: component name has not been specified.	915	CTGDKD415E Local Session is NULL.	920
CTGDKD389E SystemLogAppender: log pattern has not been specified.	916	CTGDKD416E Tombstone Manager Server API Listener successfully registered.	921
CTGDKD390E SystemLogAppender: could not generate log file name. Exception occurred: <i>exception</i>	916	CTGDKD417I Tombstone created for event: <i>event</i>	921
CTGDKD391E No component type assigned to SystemLog Appender.	916	CTGDKD418I Current record count: <i>number of records</i>	921
CTGDKD392I TombstoneAutoCleaner started. Will delete Tombstones older than <i>number of days</i> days.	916	CTGDKD419I Initiating record deletion to max records: <i>integer</i>	921
CTGDKD393I TombstoneAutoCleaner: initial run performed. Deleted: <i>number of tombstones</i> tombstones.	916	CTGDKD420I Finished record deletion.	921
CTGDKD394I TombstoneAutoCleaner: scheduled run performed. Deleted: <i>number of tombstones</i> tombstones.	917	CTGDKD421E Tombstone statistics serialization error.	922
CTGDKD395E TombstoneAutoCleaner: thread interrupted.	917	CTGDKD422E Object serialization failed.	922
CTGDKD396E TombstoneAutoCleaner error: <i>exception</i>	917	CTGDKD423E Unable to get AssemblyLineConfig for AssemblyLine: <i>event ID</i>	922
CTGDKD397I TombstoneAutoCleaner: time to next run: <i>timestamp</i>	917	CTGDKD424E Unable to get TombstonesConfig for EventHandler: <i>event ID</i>	922
CTGDKD398I TombstoneAutoCleaner: next run is scheduled for <i>timestamp</i>	917	CTGDKD425I initRecordCounters: recordsTrigger: <i>boolean</i>	922
CTGDKD399E Could not initialize Tombstone Manager database connection.	918	CTGDKD426I initRecordCounters: recordsMax: <i>integer</i>	923
CTGDKD400E Could not initialize Tombstone Manager Listener.	918	CTGDKD427I initRecordCounters: recordsCount: <i>integer</i>	923
CTGDKD401E Error in checking for tombstone records table.	918	CTGDKD428I Records count monitoring is turned on.	923
CTGDKD402I ' <i>table name</i> ' CREATE: <i>SQL statement</i>	918	CTGDKD429I Records count monitoring is disabled.	923
CTGDKD403E Error in creating tombstone table.	918	CTGDKD430I <i>line number</i> : <i>inputLine</i>	923
CTGDKD404E Error in getting tombstone record by GUID.	918	CTGDKD431E The IBM Security Directory Integrator property store <i>property store name</i> does not exist.	924
CTGDKD405E Error in deleting tombstone record by GUID.	919	CTGDKD432I Remote API Engine successfully initialized. SSL is enabled and Client Authentication is disabled.	924
CTGDKD406E Error in constructing tombstone from database record.	919	CTGDKD433I Remote API successfully started on port: <i>port</i> , bound to:'SessionFactory'. SSL is enabled and Client Authentication is disabled.	924
CTGDKD407E Error on retrieving tombstone records:	919	CTGDKD434I Remote API Engine successfully initialized. SSL and Client Authentication are disabled.	924
		CTGDKD435I Remote API successfully started on port: <i>port</i> , bound to:'SessionFactory'. SSL and Client Authentication is disabled.	924
		CTGDKD436E The desired custom class can not be found.	925

CTGDKD437E The desired custom method can not be found. 925

CTGDKD438E Exception occurred in the invoked custom method. 925

CTGDKD439E Method does not have access to the definition of the specified custom class. 925

CTGDKD440E This method does not support invocations of methods with null value parameters. 925

CTGDKD441E The custom method invocation is not turned on. 926

CTGDKD442E No classes are allowed for custom invocation. 926

CTGDKD443E The desired class is not allowed for invocation: *class name*. . . . 926

CTGDKD444I Allowed classes for custom invocation: *class names*. 926

CTGDKD445I Custom method invocation is set to *boolean value*. 926

CTGDKD446I Usage: -input <input file> -output <output file> -mode <operation mode>|<operation mode>|<operation mode>|<operation mode> -keystore <keystore file> -storepass <keystore password> -alias <encryption key alias> [-keypass <key password>] [-transformation <encryption transformation>] [-storetype <keystore type>] [-cryptoproviderclass <security provider used for encryption>] 927

CTGDKD447E The provided file is not an encrypted IBM Security Directory Integrator Config file. 927

CTGDKD458E Error on retrieving tombstone records: 927

CTGDKD459W The Solution Name '*Solution Name*' of the configuration '*file name*' is not a valid file name. The configuration instance id and Solution Name will be changed to: '*Solution Name*'. 927

CTGDKD461I The Configuration Registry parsed file '*file name*' and found Solution Name '*name*'. 928

CTGDKD462E Solution Name '*Solution Name*' is already in use by configuration '*file name*'. 928

CTGDKD463W The IBM Security Directory Integrator Server detected the Solution Name '*Solution Name*' from a client in the token '*token name*'. 928

CTGDKD464E Solution Name '*name*' of configuration '*file name*' coincides with the name of file '*file name*'. 928

CTGDKD465W Password protected configuration detected in file '*file name*'. The configuration will be only be accessible through its file name. 929

CTGDKD466I Unable to parse the file '*file name*'. The file will processed as a valid configuration file and added it to the list of configurations. 929

CTGDKD467W Password protected configuration detected '*name*'. The Solution Name will be ignored and may already be used by another configuration. 929

CTGDKD468E Invalid value specified for '*api.config.load.timeout*': '*paramater value*'. Server API will use the default value of this property. 929

CTGDKD469W The configuration could not be loaded in the time specified in '*api.config.load.timeout*': property. . . . 930

CTGDKD470E Error while broadcasting audit notification. The event type was not specified in the event. 930

CTGDKD471E A password was not specified or was invalid for the encrypted file. . . 930

CTGDKD472E The specified Run Name '*name*' cannot be used as a configuration instance id because it contains one or more of the following symbols: \ / : * ? ' ' < > |. 930

CTGDKD473I User '*user name*' cannot be successfully looked up in the directory context. No group search was performed. . . 930

CTGDKD474E The required attribute '*attribute name*' is not specified. . . . 931

CTGDKD475E No search base was specified for the group search option. Assign a value to the property '*property name*'. 931

CTGDKD476I The attempt at direct binding for the LDAP group '*group name*' has failed. 931

CTGDKD477I The value for '*api.remote.naming.port*': '*port*' is in the reserved range of port numbers. 931

CTGDKD478E User Registry could not parse CONFIG identifier '*name*'. Exception occurred: *exception* 932

CTGDKD479E The file cannot be deleted, because it is currently checked out. . . . 932

CTGDKD480E Cannot delete file '*file name*'. 932

CTGDKD481E Error occurred while reading the configuration: *exception* 932

CTGDKD482E No SSL socket is associated with the current thread. 932

CTGDKD483E SSL socket session is NULL. . . 933

CTGDKD484E SSL session certificate chain is empty. 933

CTGDKD486E Required property is missing: *property key* 933

CTGDKD489E Unable to create socket: *exception* 933

CTGDKD492E No socket is associated with the current thread. 933

CTGDKD493E Unrecognized Callback. . . . 934

CTGDKD494E One of the listeners for AssemblyLine events threw an exception: '*exception*'. 934

CTGDKD495E One of the listeners for AssemblyLine events threw an unexpected exception: 'exception'. Will unregister that listener.	934	CTGDJP507I New MxConnDelete instance created.	939
CTGDKD496W One of the listeners for logged messages threw an unexpected exception: 'exception'. Will unregister that listener.	934	CTGDJP508I Selecting entries.	939
CTGDKD497E Listener object is NULL.	934	CTGDJP509I Creating entry.	940
CTGDKD498E Listener object is NULL.	935	CTGDJP510I Performing search.	940
CTGDKD499E Cannot unregister the specified listener because it has not been registered.	935	CTGDJP511I Updating entry.	940
CTGDKD500E Listener object is NULL.	935	CTGDJP512I Deleting entry.	940
CTGDKD501E Cannot unregister the specified listener because it has not been registered.	935	CTGDJP513I Receiving HTTP response message.	940
CTGDKD502E Listener object is NULL.	935	CTGDJP514I XML character validation enabled.	941
CTGDKD503E Cannot unregister the specified listener because it has not been registered.	936	CTGDJP515I Sending HTTP message: <i>message</i>	941
CTGDKD504E Listener object is NULL.	936	CTGDJP516I XML message after validation: <i>message</i>	941
CTGDKD505E Cannot unregister the specified listener because it has not been registered.	936	CTGDJP517I Can not close file stream.	941
CTGDKD506E A communication error occurred while sending a log message to remote listener: <i>exception</i>	936	CTGDJP518I Can not load properties from file: <i>file</i>	941
CTGDKD507E Out of Server Ports	936	CTGDJP519I Configuration parameters from file on classpath: <i>params</i>	942
CTGDKD508I Remote API successfully started on port: <i>port</i> IP: <i>ip</i> , bound to:'SessionFactory'. SSL and Client Authentication are enabled.	937	CTGDJP520I Loading properties from file: <i>file</i>	942
CTGDKD509I Remote API successfully started on port: <i>port</i> IP: <i>ip</i> , bound to:'SessionFactory'. SSL is enabled and Client Authentication is disabled.	937	CTGDJP521I Configuration parameters from file in solution folder: <i>params</i>	942
CTGDKD510I Remote API successfully started on port: <i>port</i> IP: <i>ip</i> , bound to:'SessionFactory'. SSL and Client Authentication are disabled.	937	CTGDJP522I Configuration parameters from file specified as system property: <i>params</i>	942
CTGDJU001I Simple Parser read in an entry: ' <i>entry value</i> '.	937	CTGDJP523I Clearing configuration parameters.	942
CTGDJU002I Simple Parser wrote out a string: ' <i>entry value</i> '.	938	CTGDJP524I Select MBO	943
CTGDJU003E Unable to process entry read because a line read in was not in the key:value pair format: ' <i>line</i> '	938	CTGDJP525I Schema cache has been cleared.	943
CTGDJP501I Parsing XML response from the server.	938	CTGDJP526E Unsupported Link criteria operator.	943
CTGDJP502I Configuration parameters: <i>params</i>	938	CTGDJP527E The following unique keys are not specified: <i>keys</i>	943
CTGDJP503I New MxConnIterator instance created.	938	CTGDJP528E The HTTP server did not returned "HTTP OK".	943
CTGDJP504I New MxConnAddOnly instance created.	939	CTGDJP529E Sending message timed out.	943
CTGDJP505I New MxConnLookup instance created.	939	CTGDJP530E Can not send HTTP request.	944
CTGDJP506I New MxConnUpdate instance created.	939	CTGDJP531E Invalid value for Timeout parameter.	944
		CTGDJP532E List of target URLs is empty.	944
		CTGDJP533E Parameter not defined: <i>param</i>	944
		CTGDJP534W Unable to send HTTP request.	944
		CTGDJP535E Not supported encoding: <i>encoding</i>	944
		CTGDJP536W Can not read the HTTP error message.	945
		CTGDJP537E Can not load XML template.	945
		CTGDJP538E Can not parse received XML.	945
		CTGDJP539E Parameter not defined: <i>param</i>	945
		CTGDJP540W Can not read file: <i>file</i> . Exception occurred: <i>exception</i>	945
		CTGDJP541W Can not load resource: <i>resource</i> . Exception occurred: <i>exception</i>	946
		CTGDJP542E Schema does not contain MBO: <i>mbo</i>	946
		CTGDJP543E Can not obtain schema for object structure: <i>mos</i>	946
		CTGDJP544E Illegal schema element: <i>name</i>	946
		CTGDJP545E Illegal schema element for Link criteria: <i>name</i>	946
		CTGDJP546E Element not found: <i>name</i>	946
		CTGDJP547E No configuration is specified.	947

CTGDP548E Unsupported Link criteria type.	947
CTGDP549E Invalid value for Page size parameter.	947
CTGDP550E The 'name' attribute exceeds the maximum allowed size: size.	947
CTGDP551E The value is not a valid boolean: value.	947
CTGDP552E The string does not contain a boolean: value.	948
CTGDP553E The value is not a valid date: value.	948
CTGDP554E The string does not contain a parsable date: value.	948
CTGDP555E The value is not a valid double: value.	948
CTGDP556E The string does not contain a parsable double: value.	948
CTGDP557E The value is not a valid integer: value.	948
CTGDP558E The string does not contain a parsable integer: value.	949
CTGDP559E The value is not a valid long: value.	949
CTGDP560E The string does not contain a parsable long: value.	949
CTGDP561I Can not find a Maximo exception.	949
CTGDP562I The unique attribute: <i>attributeName</i> has a value of ' <i>originalValue</i> '. It cannot be changed to <i>userValue</i> .	949
CTGDP563E Unique attribute ' <i>attribute</i> ' is not provided.	950
CTGDP564I Target URL: <i>url</i>	950
CTGDPJ001I Simple XML Parser will request validating Parser.	950
CTGDPJ002I Simple XML Parser will request namespace aware Parser.	950
CTGDPJ003I Simple XML Parser will not indent output.	950
CTGDPJ004I Simple XML Parser turned off Deferred DOM.	951
CTGDPJ005I Simple XML Parser could not turned off Deferred DOM.	951
CTGDPJ006E Failed to read XML because input stream was not found. The input or output modes of the Simple XML Parser may not be valid.	951
CTGDPJ007E Failed to write XML because output stream was not found. The input or output modes of the Simple XML Parser may not be valid.	951
CTGDPJ008I Initializing XML Input Document.	951
CTGDPJ009I Initializing XML Output Document.	952
CTGDPJ010I The XML document has no children. The top level tag name in the document is ' <i>tag name</i> '.	952
CTGDPJ011I The XML document has ' <i>number of children</i> ' children.	952

CTGDPJ012E Simple XML Parser failed to initialize because XML document read in has no document root.	952
CTGDPJ013E Expected child item at index ' <i>index number</i> '.	952
CTGDPJ014I The XML Child node has no children so its being skipped.	953
CTGDPJ015W SAX Parse Warning: line: <i>line number</i> , uri: <i>uri</i> , message: <i>message</i> .	953
CTGDPJH001E Connector could not return entry because an unknown class type was encountered: ' <i>object type</i> '	953
CTGDPJH002I Connector listening for SNMP traps only.	953
CTGDPJH003E The 'snmpOID' parameter must be set to use the SNMP Connector.	953
CTGDPJH004I Getting the next SNMP entry. Comparing response OID ' <i>OID</i> ' of the entry with configured walkOID parameter ' <i>OID</i> '.	954
CTGDPJH005E Connector could not get next SNMP entry because a bad PDU was received from the SNMP Server. Error occurred: <i>exception</i>	954
CTGDPJH006I Ignoring unsupported link criteria name: ' <i>link criteria</i> '.	954
CTGDPJH007I Search criteria for entry search: OID=' <i>OID</i> ' version=' <i>version</i> ' host=' <i>hostname</i> ' port=' <i>port number</i> '.	954
CTGDPJH008E Connector could not add entry because set request to SNMP Server failed. Error occurred: <i>error message</i>	955
CTGDPJH009I Will send request to get entry with OID ' <i>OID</i> '.	955
CTGDPJH010E Connector could not get next SNMP entry because a bad PDU was received from the SNMP Server. Error occurred: <i>exception</i>	955
CTGDPJH011I Empty queue, waiting for data for ' <i>number of seconds</i> ' seconds.	955
CTGDPJH012I Empty queue, waiting for data with no timeout value.	956
CTGDPJH013I Trap received: <i>trap</i> .	956
CTGDPJH010I Initializing with the provided java.net.DatagramPacket object.	956
CTGDPJH012E The 'udp.port' parameter must be set to use the SNMP Server Connector.	956
CTGDPJH013E Invalid 'udp.port' parameter set in the the SNMP Server Connector: ' <i>parameter value</i> '.	956
CTGDPJH014I Waiting for SNMP packets on UDP port ' <i>port number</i> '.	957
CTGDPJH015I Connector terminated by external request.	957
CTGDPJH016I Connector terminating by external request.	957
CTGDPJH017I Receiving Connection from ' <i>hostname</i> '.	957
CTGDPJH018I Receiving Connection from ' <i>hostname</i> '.	957
CTGDPJH019I Ignoring add request for community ' <i>community name</i> '.	958

CTGDJH110I Response PDU on add entry request i ' <i>PDU</i> '.	958	CTGDKL008E Unable to process the request because an unknown request was received: <i>SPML v2 request</i>	963
CTGDJH111I The SNMP error code ' <i>error code</i> ' has an illegal value. The error code value will be changed to 5.	958	CTGDKL009E Unknown response : <i>SPML v2 response</i>	963
CTGDJH112I Terminate server request received.	958	CTGDKL010W An error occurred while flushing the batch message: <i>exception</i>	963
CTGDJH113I Creating dummy connection using IP Address ' <i>IP Address</i> ' and port ' <i>port number</i> '.	958	CTGDKL011I Base64 decoding attribute: <i>attribute name</i>	964
CTGDJH114W Encountered an IOException on unblocking the SNMP Server Connector's server socket: <i>exception</i>	959	CTGDKL012I Base64 decoding attribute: <i>attribute name</i>	964
CTGDJH115I SNMP Server Connector is already terminating. Not sending termination request.	959	CTGDKL013E Unable to complete the <i>operation name</i> request. The <i>operation name</i> request must contain a <psoid ID> attribute.	964
CTGDJH116I Sending termination request to SNMP Server Connector.	959	CTGDID001E Required Connector parameter ' <i>connectionType</i> ' is not set.	964
CTGDJH117W Unable to add one or more attributes to the entry. Exception occurred: <i>exception</i>	959	CTGDID002E Required Connector parameter ' <i>url</i> ' is not set.	964
CTGDJV001E Failed to read XML because input stream was not found. The input or output modes of the SOAP Parser may not be valid.	959	CTGDID003E The ' <i>connectionType</i> ' parameter is set to an invalid value ' <i>parameter value</i> '.	965
CTGDJV002E XML document has no <SOAP-ENV:Body> element.	960	CTGDID004I Server Notification Event received: ' <i>event name</i> '.	965
CTGDJV003E <SOAP-ENV:Body> tag has no elements.	960	CTGDID005E Unable to add entry. Entry missing required attribute ' <i>event.type</i> '.	965
CTGDJV004I The method parseXML returns: <i>node name</i>	960	CTGDID006E Unable to add entry. Entry missing required attribute ' <i>event.id</i> '.	965
CTGDJV005I SOAP Call: <i>node name</i>	960	CTGDJO001I The ' <i>deliveryMode</i> ' parameter is set to <i>delivery mode</i>	965
CTGDJV006I The element <i>node name</i> has no value.	960	CTGDJO002E Unable to initialize Connector because a connection to the directory server could not be established or the search at base DN <i>DN</i> was not valid.	966
CTGDJV007I The element <i>node name</i> has no value.	961	CTGDJO003W Cannot set starting change number to ' <i>change number</i> '.	966
CTGDJV008I <i>prefix</i> DOCUMENT node type.	961	CTGDJO004I Starting with change number set to ' <i>change number</i> ' and the ' <i>iteratorStateKey</i> ' was set to ' <i>state value</i> '.	966
CTGDJV009I <i>prefix</i> Node Name: <i>node name</i>	961	CTGDJO005I Connector has timed out and is waiting for next changed entry.	966
CTGDJV010I <i>prefix</i> Node Value: <i>node value</i>	961	CTGDJO006I LDAP search query set to ' <i>filter</i> '.	967
CTGDJV011I <i>prefix</i> Node type is not recognized.	961	CTGDJO007I Attempting to find entry with attribute changenumber equal to ' <i>change number</i> ' using the LDAP base DN of ' <i>DN</i> '.	967
CTGDKL001E Unable to process the batch message because an unknown type was encountered: <i>class name</i>	962	CTGDJO008I Found entry with attribute changenumber equal to ' <i>change number</i> ' using the LDAP base DN of ' <i>DN</i> '.	967
CTGDKL002W The Base64 decoding has not finished successfully for the entry with the following attributes: <i>entry attributes</i>	962	CTGDJO009I Unable to find entry with attribute change number equal to ' <i>change number</i> ' using the LDAP base DN of ' <i>DN</i> '. Skipping to try the next entry.	967
CTGDKL003E Unable to process the request because an unknown request type was received: <i>class name</i>	962	CTGDJO010I Will continue but caught a PartialResultException while getting the next search result: <i>exception</i>	967
CTGDKL004E Unknown response type: <i>class name</i>	962	CTGDJO011E Entry does not contain a valid changelog entry (changes attribute missing) for operation: <i>type</i>	968
CTGDKL005E Unable to complete the <i>operation name</i> request. The <i>operation name</i> request must contain exactly one <psoid> element.	962	CTGDJO012E Unable to parse changes attribute.	968
CTGDKL006E Unable to process the entry. The entry is missing required Attribute: <i>attribute name</i>	963		
CTGDKL007E Unknown operation type: <i>SPML v2 operation</i>	963		

CTGDJO014E Could not retrieve last change number. 968

CTGDJO015E Could not store the change number value in System Store: *exception* . . . 968

CTGDJO016I Current change number value is: *change number*. 968

CTGDJO017I A namingException is thrown: *xxception*. 969

CTGDJO018I notificationReceived: *event* . . . 969

CTGDJO019E An exception is encountered when executing the method 'callEventFunction': *exception* 969

CTGDJO020I Block for notifications 969

CTGDJO021W Thread interrupted: *exception* . . . 969

CTGDJO022E Restart info does not contain 'changeNumber' attribute. 970

CTGDJO023W Exception occurred while terminating the Connector: *exception* . . . 970

CTGDJO024W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used. . . 970

CTGDIH001E Required Connector parameter '*parameter name*' is not set. 970

CTGDIH002E The 'connectionType' parameter is set to an invalid value '*parameter value*'. 970

CTGDIH101E The System Store Connector cannot initialize because the create table statement is missing. 971

CTGDIH102W Unable to set the commit mode in the System Store Connector to '*commit mode*'. Continuing, but a valid value should be set for the 'pesCommit' parameter. . . . 971

CTGDIH103W An exception was encountered while terminating the System Store Connector: *exception* 971

CTGDIH104I Entry found without a value for the key attribute '*attribute name*'. 971

CTGDIH105E Required Connector parameter 'keyAttribute' is not set. 971

CTGDIH106E Unable to add the entry because a null Entry object was passed into the putEntry method. 972

CTGDIH107E Unable to add entry because DML Operations are not allowed on the table '*table name*'. 972

CTGDIH108E Unable to modify entry because DML Operations are not allowed on the table '*table name*'. 972

CTGDIH109E Unable to delete entry because DML Operations are not allowed on the table '*table name*'. 972

CTGDIH110E Unable to modify the entry because a null Entry object was passed into the modEntry method. 973

CTGDIH111E The entry cannot be added because the keyAttribute attribute '*attribute name*' in the entry has a value of NULL. 973

CTGDIH112E The entry cannot be modified because the keyAttribute attribute '*attribute name*' in the entry has a value of NULL. 973

CTGDIH113E Unable to modify the entry because of a search key mismatch. The search criteria supplied was '*attribute name*' and the keyAttribute configured in the Connector is '*attribute name*'. 974

CTGDIH114I Preparing and executing the query SQL statement to find an entry: *SQL statement*. 974

CTGDIH115W Prepared SQL statement to find entry failed: *exception* 974

CTGDIH116W The prepared SQL statement to delete an entry will not be used. Exception encountered: *exception* 974

CTGDIH117E The selectEntries method failed. Cannot execute SQL Statement: *SQL statement*. 974

CTGDIH118I No more entries to retrieve from SQL search results. 975

CTGDIH119E Cannot build where clause (Advanced Link Mode). 975

CTGDIH120I Attempting to build an entry in the System Store Connector. 975

CTGDIH121I Saving Meta Data. Saving column '*column name*' of column type '*column type*'. 975

CTGDIH122I Retrieving attribute value based on the column name '*column name*'. . . 975

CTGDIH123I Retrieved attribute of type 'CHAR/VARCHAR': '*value*'. 976

CTGDIH124I Retrieved attribute of type 'LONGVARIABLE'. 976

CTGDIH125I Retrieved attribute of type 'DECIMAL/INTEGER': '*value*'. 976

CTGDIH126I Retrieved NULL value for INT: '*value*'. 976

CTGDIH127I Retrieved attribute value of type 'OBJECT': '*class name*'. 976

CTGDIH128I Set value of attribute '*attribute name*' to '*attribute value*'. The class type of the attribute is '*class name*'. 977

CTGDIH129I Set value of attribute '*attribute name*' to '*attribute value*'. The class type of the attribute is 'basic'. . . 977

CTGDIH130I Set value of attribute '*attribute name*' to 'null'. 977

CTGDIH131I Successfully built an entry in the System Store Connector. 977

CTGDIH132I Preparing to set prepared SQL statement value with attribute name '*attribute name*' and attribute value '*attribute value*'. The index is set to '*index*'. 978

CTGDIH133E No Meta Data description for attribute being set in the prepared SQL statement: '*attribute name*'. 978

CTGDIH134W Set prepared SQL statement value for attribute to null: index='index'.	978	CTGDIK409E Could not find entries for: <i>object name</i> .	984
CTGDIH135W Java Class name of attribute value: ' <i>class name</i> '.	978	CTGDIK410E There was an error while creating: <i>object name</i> .	984
CTGDIH136I Type of attribute value: ' <i>attribute value type</i> '.	978	CTGDIK411E There was an error while updating: <i>entry name</i> .	984
CTGDIH137I Set 'LONGVARCHAR' value: ' <i>value</i> '.	979	CTGDIK412E Could not delete entry for: <i>entry name</i> .	984
CTGDIH138I Set 'VARCHAR' value: ' <i>value</i> '.	979	CTGDIK413E Unable to interface with the TAM server. The following invalid message was retrieved by TAM while processing an exception thrown by TAM: <i>invalid message</i> .	985
CTGDIH139I Set 'OTHER' value: ' <i>value</i> '.	979	CTGDIK414E Unable to interface with the TAM server. The following error message was retrieved by TAM while processing an exception thrown by TAM: <i>error message</i> .	985
CTGDIH140I Set 'INTEGER/TINYINT/SMALLINT' value: ' <i>value</i> '.	979	CTGDIK415E Unable to interface with the TAM server. While retrieving the cause of an exception thrown by TAM, an internal exception has occurred.	985
CTGDIH141W Exception caught while parsing Integer from 'INTEGER/TINYINT/SMALLINT' value: ' <i>exception</i> '.	979	CTGDIK416E Unable to complete the operation. The attribute <i>attribute name</i> was missing.	985
CTGDIH142I Set value for an unhandled type ' <i>type</i> ' as a string on column ' <i>column name</i> '.	980	CTGDIK417E Connector search failed. An unsupported search criteria was specified.	986
CTGDIH143W SQL warning encountered from prepared SQL statement: <i>warning message</i> .	980	CTGDIK418E Deleting policy failed. User name is not specified.	986
CTGDIH144I findEntry method will use SQL statement: <i>SQL statement</i> .	980	CTGDIK419E Invalid Resource Type: <i>resource type</i> .	986
CTGDIH145I deleteEntry method will use SQL statement: <i>SQL statement</i> .	980	CTGDIK420E Admin Group <i>group name</i> is reserved and cannot be deleted.	986
CTGDIH146I The delete operation returned <i>return code</i> .	980	CTGDIK421E Admin User <i>user name</i> is reserved and cannot be deleted.	986
CTGDIH147I selectEntries method will use SQL statement: <i>SQL statement</i> .	981	CTGDIK422E Error while loading the group <i>group name</i> .	987
CTGDIH148I No entries from selectEntries method.	981	CTGDIK423E No Credentials Exist for User: <i>user name</i> .	987
CTGDIH149I Prepared statement: <i>SQL statement</i> .	981	CTGDIK424E Operation Code <i>operation code</i> not supported.	987
CTGDIH150E The table name is not specified.	981	CTGDIK425I Shutting down connection to TAM.	987
CTGDIH151E Error: <i>error message</i> occurred while creating the table <i>Table Name</i> .	981	CTGDIK426I Initializing PDAAdmin for application: <i>TAM program ID</i> .	987
CTGDIH152E The table name does not begin with a letter.	982	CTGDIK427I Creating a TAM Context: <i>context name</i> .	988
CTGDIH153E The table name is not alphanumeric.	982	CTGDIK428I Retrieving data for entries with the entry type <i>entry type</i> and the attribute value <i>attribute value</i> .	988
CTGDIH154W An exception occurred while trying to close the database connection: <i>exception message</i> .	982	CTGDIK429I The groups for the user: <i>group names</i> .	988
CTGDIH155W The following sql exception has occurred while using PreparedStatement <i>exception message</i> .	982	CTGDIK430I Importing User: <i>user name</i> .	988
CTGDIK401E Invalid ENTRY type: <i>Entry Type</i> .	982	CTGDIK431I Adding User: <i>user name</i> .	988
CTGDIK402E Missing ENTRY type. Entry type is null.	983	CTGDIK432I The groups to add: <i>group names</i> .	989
CTGDIK403E Invalid TAM configuration file: <i>file name</i> .	983	CTGDIK433I The groups to delete: <i>group names</i> .	989
CTGDIK404E Could not log on to TAM.	983	CTGDIK434I Removing User: <i>user name</i> .	989
CTGDIK405E Could not query TAM Domains.	983	CTGDIK435I The users to add: <i>user names</i> .	989
CTGDIK406E Could not shutdown TAM <i>object name</i> .	983	CTGDIK436I The users to delete: <i>user names</i> .	989
CTGDIK407E Could not retrieve entries for: <i>object name</i> .	983	CTGDIK437I Removing members from Group: <i>group name</i> .	990
CTGDIK408E Could not retrieve next entry for: <i>object name</i> .	984		

CTGDIK438I Adding members to Group: <i>group name</i>	990
CTGDIK439I Removing Group: <i>group name</i>	990
CTGDIK440I Removing User: <i>user name</i>	990
CTGDIK441I Creating Policy for User: <i>user name</i>	990
CTGDIK442I Removing Policy for User: <i>user name</i>	991
CTGDIK443I Creating Domain: <i>domain name</i>	991
CTGDIK444I Removing Domain: <i>domain name</i>	991
CTGDIK445I Creating SSO Credential: <i>credential name</i>	991
CTGDIK446I Deleteing SSO Credential: <i>credential name</i>	991
CTGDIK447I Refer to Users Guide, or initialize the Connector first.	992
CTGDIK448E No valid value found for the following Connector Configuration Parameter: <i>Config Param Name</i>	992
CTGDIK449E Unable to interface with the TAM server. The following invalid context message was retrieved by TAM while processing an exception thrown by TAM: <i>invalid context message</i>	992
CTGDIK450E Unable to interface with the TAM server. The following unknown message type was retrieved by TAM while processing an exception thrown by TAM: <i>unknown message</i>	992
CTGDJI001I Listening for TCP SSL connections on port ' <i>port number</i> '.	993
CTGDJI002I Listening for TCP connections on port ' <i>port number</i> '.	993
CTGDJI003E The 'tcpHost' parameter must be set to use the TCP Connector in client mode.	993
CTGDJI004I Connecting to TCP host ' <i>hostname</i> ' over SSL on port ' <i>port number</i> '.	993
CTGDJI005I Connecting to TCP host ' <i>hostname</i> ' on port ' <i>port number</i> '.	993
CTGDJI006I Waiting for incoming connection on port ' <i>port number</i> '.	994
CTGDJI007I Incoming connection established from ' <i>IP Address</i> '.	994
CTGDJI008E The 'tcpPort' parameter must be set to use the TCP Connector in client mode.	994
CTGDJI009I Interrupted while waiting for incoming connection. Closing the server socket.	994
CTGDJI101E The 'tcp.port' parameter must be set to use the TCP Server Connector.	995
CTGDJI102I Exiting initialization early because Connector already initialized with a java.net.Socket object.	995
CTGDJI103I Using the provided java.net.Socket object for TCP client session.	995
CTGDJI104I Listening for TCP SSL connections on port ' <i>port number</i> '. The backlog connections allowed is set to ' <i>number of connections</i> ' connections and client authentication is set to ' <i>boolean</i> '.	995

CTGDJI105I Listening for TCP connections on port ' <i>port number</i> '. The backlog connections allowed is set to ' <i>number of connections</i> ' connections.	995
CTGDJI106I Connector terminated by external request.	996
CTGDJI107I Connector terminating by external request.	996
CTGDJI108I Incoming connection established from ' <i>IP Address</i> '.	996
CTGDJI109I Terminate server request received.	996
CTGDJI110I Creating dummy connection using IP Address ' <i>IP Address</i> ' and port ' <i>port number</i> '.	996
CTGDJI111W Encountered an IOException on unblocking the TCP Server Connector's server socket: <i>exception</i>	997
CTGDJI112I TCP Server Connector is already terminating. Not sending termination request.	997
CTGDJI113I Sending termination request to TCP Server Connector.	997
CTGDWI001E Select a Solution View to delete.	997
CTGDWI002W Delete Solution View <i>Solution View name?</i>	997
CTGDWI003E Unable to delete Solution View <i>Solution View name</i> . This might happen if Action Manager rules are configured for this Solution View. See error logs for more details.	998
CTGDWI004E Select a Solution View to manage.	998
CTGDWI005E Select a Solution View to modify.	998
CTGDWI006E The session with remote server for the Solution View could not be established.	998
CTGDWI007E The Config instance associated with the Solution View is not loaded on the server.	999
CTGDWI008E The Solution View <i>Solution View name</i> already exists.	999
CTGDWI009E It is mandatory to select a Config instance.	999
CTGDWI010E It is mandatory to select at least one AssemblyLine.	999
CTGDWI011E Select a Health AssemblyLine or check the None checkbox.	1000
CTGDWI012I The Solution View <i>Solution View name</i> has been successfully created.	1000
CTGDWI013E The Solution View could not be created. Check the logs for errors.	1000
CTGDWI014E The Config instance associated with the Solution View <i>Solution View name</i> is not loaded on the server.	1000
CTGDWI015I The current Solution View has been set to: <i>Solution View name</i>	1001
CTGDWI016E Select a Config instance to reload.	1001

CTGDIW017I Config Instance <i>Config instance ID</i> successfully reloaded.	1001	CTGDIW048E Select a property to modify.	1008
CTGDIW018E Error occurred while reloading Config instance <i>Config instance ID</i>	1001	CTGDIW049E Select a property to delete.	1008
CTGDIW019E The Config <i>Config path</i> is not loaded on the server. Only loaded Configs can be reloaded.	1002	CTGDIW050W Delete property <i>property name?</i>	1008
CTGDIW020E Select a Config to load.	1002	CTGDIW051E Select a property to modify.	1008
CTGDIW021E Select a Config instance to unload.	1002	CTGDIW052E Select a property to delete.	1009
CTGDIW022E Error occurred while trying to unload the Config instance <i>Config instance ID</i>	1002	CTGDIW053W Delete property <i>property name?</i>	1009
CTGDIW023E The Config <i>Config instance ID</i> is not loaded on the server. Only a loaded Config can be unloaded.	1002	CTGDIW054E Select a property to modify.	1009
CTGDIW024E Error occurred while trying to load the Config <i>Config path</i>	1003	CTGDIW055E Select a property to delete.	1009
CTGDIW025E The Config <i>Config instance ID</i> is already loaded on the server.	1003	CTGDIW056W Delete property <i>property name?</i>	1009
CTGDIW026E Select a group.	1003	CTGDIW057E Select a property to modify.	1009
CTGDIW027E Select a role.	1003	CTGDIW058E Select a property to delete.	1010
CTGDIW028E Unable to set role for group <i>group name</i>	1004	CTGDIW059W Delete property <i>property name?</i>	1010
CTGDIW029I The role for group <i>group name</i> has been successfully updated.	1004	CTGDIW060E The current password for user <i>user name</i> is incorrectly entered.	1010
CTGDIW030E Select a user.	1004	CTGDIW061E The new passwords do not match.	1010
CTGDIW031E Select a role.	1004	CTGDIW062E Unable to change password.	1010
CTGDIW032E Unable to set role for user <i>user name</i>	1004	CTGDIW063E Unable to change password. User <i>user name</i> not found.	1011
CTGDIW033I The role for user <i>user name</i> has been successfully updated.	1005	CTGDIW064I Password for user <i>user name</i> changed successfully.	1011
CTGDIW034E Select a Health AssemblyLine or check the None checkbox.	1005	CTGDIW065E Group already exists: <i>group name</i>	1011
CTGDIW035I The Solution View has been successfully updated.	1005	CTGDIW066E Illegal character encountered in group name.	1011
CTGDIW036E The Solution View could not be updated. Check the logs for errors.	1005	CTGDIW067E Unable to add group. Check the logs for errors.	1011
CTGDIW037E It is mandatory to select at least one AssemblyLine.	1005	CTGDIW068E No users selected.	1012
CTGDIW038E Select members to remove access.	1006	CTGDIW069E Group <i>group name</i> does not exist.	1012
CTGDIW039E Unable to remove members. See error logs for details.	1006	CTGDIW070E Select a group to modify.	1012
CTGDIW040E Select a server to delete.	1006	CTGDIW071E Select a group to delete.	1012
CTGDIW041W Deleting a server will also delete all Solution Views and other information associated with this server. Do you really want to delete the server <i>server name</i> ?	1006	CTGDIW072W Delete group <i>group name?</i>	1012
CTGDIW042E Unable to delete server <i>server name</i> . Check the logs for errors.	1007	CTGDIW073E Group <i>group name</i> does not exist.	1013
CTGDIW043E Update failed for property <i>property name</i>	1007	CTGDIW074E Group <i>group name</i> does not exist.	1013
CTGDIW044E Unable to add property <i>property name</i>	1007	CTGDIW075E No members selected.	1013
CTGDIW045E Select a property to delete.	1007	CTGDIW076W Remove selected members from group?	1013
CTGDIW046W Delete property <i>property name?</i>	1007	CTGDIW077E Group <i>group name</i> does not exist.	1013
CTGDIW047E Select a property to modify.	1008	CTGDIW078E Passwords do not match.	1014
		CTGDIW079E User already exists: <i>user name</i>	1014
		CTGDIW080E Illegal character encountered in user name.	1014
		CTGDIW081E Unable to add user. Check the logs for errors.	1014
		CTGDIW082E Select a user to modify.	1014
		CTGDIW083E Select a user to delete.	1015
		CTGDIW084W Delete user <i>user name?</i>	1015
		CTGDIW085E User <i>user name</i> does not exist.	1015
		CTGDIW086E Passwords do not match.	1015
		CTGDIW087E User <i>user name</i> does not exist.	1015

CTGDIW088E Unable to modify user. Check the logs for errors.	1016	CTGDIW114E Select a Solution View to view its details.	1021
CTGDIW089E SSL Key store file is not specified.	1016	CTGDIW115W The Config instance associated with the Solution View <i>Solution View name</i> is not loaded on the server. . .	1021
CTGDIW090E SSL Trust store file is not specified.	1016	CTGDIW116E Select an AssemblyLine to view Tombstones.	1022
CTGDIW091E Unable to add the server. The IBM Security Directory Integrator Server ID <i>Server ID</i> duplicates the Server ID already assigned to another server having the same hostname and port number.	1016	CTGDIW117E Could not obtain an instance of Tombstone Manager. It might not be running on the remote server.	1022
CTGDIW092E Unable to establish connection with the server.	1017	CTGDIW118E Select a log file to view.	1022
CTGDIW093I Connection successfully established.	1017	CTGDIW119E Unable to connect to IBM Security Directory Integrator server associated with Solution View <i>Solution View name</i> . Cannot clean up logs for this Solution View.	1022
CTGDIW094E Select a server to shutdown.	1017	CTGDIW120E There were errors while cleaning up logs for Solution view <i>Solution View name</i>	1023
CTGDIW095W If this server is shut down, then all users connected or working with this server will get disconnected. Also, any AssemblyLines or Config instances on this server will be shut down. Do you really want to shutdown the server <i>server name</i> ?	1017	CTGDIW121I Cleanup logs for Solution View <i>Solution View name</i> completed successfully.	1023
CTGDIW096E Unable to shutdown server <i>server name</i>	1017	CTGDIW122E An error occurred while saving your preferences.	1023
CTGDIW097E The Config instance associated with the Solution View <i>Solution View name</i> is not loaded on the server. . .	1018	CTGDIW123I Your preferences have been successfully saved.	1023
CTGDIW098E Select an AssemblyLine to start.	1018	CTGDIW124E Unable to create a rule in database. See error logs for details. . .	1024
CTGDIW099E The AssemblyLine <i>AssemblyLine name</i> is already running.	1018	CTGDIW125E Unable to create/update rule in database. See error logs for details. .	1024
CTGDIW100E The AssemblyLine <i>AssemblyLine name</i> could not be started. Check the logs for errors.	1018	CTGDIW126E No Property name specified for trigger.	1024
CTGDIW101E Select an AssemblyLine to stop.	1019	CTGDIW127E No Rule selected for delete.	1024
CTGDIW102E The AssemblyLine <i>AssemblyLine name</i> is already stopped.	1019	CTGDIW128W Deleting a rule will delete all information associated with this rule, including the run history of this rule from database. Do you really want to delete the <i>rule name</i> rule?	1024
CTGDIW103W Stop AssemblyLine <i>AssemblyLine name</i> ?	1019	CTGDIW129E Unable to delete the rule from database. Ensure that some other rule is not associated with this rule. Also, check the error logs.	1025
CTGDIW104E The AssemblyLine <i>AssemblyLine name</i> could not be stopped. Check the logs for errors.	1019	CTGDIW130E It is mandatory to select at least one Action.	1025
CTGDIW105E Select an AssemblyLine to view component information.	1019	CTGDIW131E For the Copy property action, the source and destination properties are the same: <i>property name</i> . Select different property names.	1025
CTGDIW106E Unable to obtain Connector information for AssemblyLine <i>AssemblyLine name</i>	1020	CTGDIW132E One or more actions could not be stored. See the logs for errors. . . .	1025
CTGDIW107E Select a property to modify.	1020	CTGDIW133E Select an Action to move.	1026
CTGDIW108E Select a property to delete.	1020	CTGDIW134E Unable to move the chosen action. See logs for more information. . .	1026
CTGDIW109W Delete property <i>property name</i> ?	1020	CTGDIW135E Select an Action to delete.	1026
CTGDIW110E Select a Solution View to view its server information.	1020	CTGDIW136E Unable to delete the chosen action. See logs for more information. . .	1026
CTGDIW111E The session with remote server for the Solution View could not be established.	1021	CTGDIW137W Delete action <i>action name</i> ?	1026
CTGDIW112I Server shutdown successful.	1021	CTGDIW138E Either an event type or an event source must be specified.	1027
CTGDIW113E Could not shutdown server.	1021	CTGDIW139E Value for the property has not been specified in trigger.	1027

CTGDIW140E Attribute name or value not specified.	1027	CTGDIW161I Deleting IBM Security Directory Integrator Properties.	1032
CTGDIW141E Illegal interval value specified. Value must be greater than zero.	1027	CTGDIW162I Deleting Health AssemblyLine details.	1032
CTGDIW142E Insufficient rights to perform Solution View management for the selected Solution View.	1027	CTGDIW163I Insert into CONFIG_VIEW_AL_DETAILS table the exposed AssemblyLines.	1032
CTGDIW143E Insufficient rights to perform Config administration (load/unload/reload) task for the selected Config instance <i>Config instance</i>	1028	CTGDIW164E Unable to insert into CONFIG_VIEW_HEALTH_AL_DETAILS table in database.	1032
CTGDIW144E Insufficient rights to view details for Solution View <i>Solution View name</i>	1028	CTGDIW165E Unable to insert into CONFIG_VIEW_HEALTH_AL_DETAILS table in database.	1033
CTGDIW145E Insufficient rights to view server information for Solution View <i>Solution View name</i>	1028	CTGDIW166I Instance of AMCTDIServerManager class created.	1033
CTGDIW146I The Administration and Monitoring Console has been set up for LDAP Authentication. User and Group addition (or modification) is not supported via the Administration and Monitoring Console for external LDAP servers.	1029	CTGDIW167E Unable to delete server from TDI_SERVER_MASTER table from database.	1033
CTGDIW147E Illegal value specified for Action Manager Log Rotate rate (days). Minimum is 1 day.	1029	CTGDIW168W Unable to set the amc.session.timeout value. Value obtained from amc.properties file: <i>session timeout value</i>	1033
CTGDIW148E Select an Action to modify.	1029	CTGDIW169W Unable to set the monitor.refresh.rate value. Value obtained from amc.properties file: <i>monitor refresh rate</i>	1034
CTGDIW149E The action could not be updated. See the logs for errors.	1029	CTGDIW170W Unable to determine the monitor.startup value. Value obtained from amc.properties file: <i>boolean</i>	1034
CTGDIW150E No Rule selected for modify.	1029	CTGDIW171E An error occurred while attempting to read the amc.properties file.	1034
CTGDIW151E The Action Manager Rule status could not be updated. See the logs for errors.	1030	CTGDIW172E An error occurred while attempting to read the amc.properties file.	1034
CTGDIW153I Instance of AMConfigManager class created.	1030	CTGDIW173E An error occurred while attempting to read the amc.properties file.	1035
CTGDIW154I In createConfigViewMethod(). Parameters received: Solution View Name: <i>Solution view name</i> Solution View Desc: <i>description</i> Server ID: <i>server ID</i> Exposed AssemblyLines: <i>list of AssemblyLines</i> Is Health AssemblyLine specified: <i>boolean</i> Selected Health AssemblyLine: <i>Health AssemblyLine name</i>	1030	CTGDIW174E An error occurred while attempting to read the amc.properties file.	1035
CTGDIW155E Unable to insert into CONFIG_VIEW_MASTER table in database.	1030	CTGDIW175E An error occurred while attempting to write to the amc.properties file.	1035
CTGDIW156E Unable to obtain CV_ID (primary key) value for Solution view <i>Solution view name</i>	1031	CTGDIW176E Unable to clear logs for AssemblyLine <i>AssemblyLine name</i> in Config <i>Config</i>	1035
CTGDIW157E Unable to insert into CONFIG_VIEW_AL_DETAILS table in database.	1031	CTGDIW177E Unable to clear logs for AssemblyLine <i>AssemblyLine name</i> in Config <i>Config</i>	1035
CTGDIW158E Unable to insert into CONFIG_VIEW_HEALTH_AL_DETAILS table in database.	1031	CTGDIW178E Unable to get system log for Solution view: <i>Solution View ID</i>	1036
CTGDIW159I In updateConfigView() method. Parameters received: Solution View ID: <i>Solution view ID</i> Exposed AssemblyLines: <i>list of AssemblyLines</i> Is Health AssemblyLine specified: <i>boolean</i> Selected Health AssemblyLine: <i>Health AssemblyLine name</i>	1031	CTGDIW179W Unable to get status of Action Mangaer Rules for Solution view id: <i>Solution View ID</i>	1036
CTGDIW160I Deleting AssemblyLine details.	1031	CTGDIW180E Unable to update AM_RULES_MASTER while trying to update status.	1036
		CTGDIW181E Unable to update AM_RULES_MASTER while trying to update status.	1036
		CTGDIW182E Unable to add Action Manager rule into database. Rule Name: <i>Rule Name</i> Rule Description: <i>Description</i> Solution View ID: <i>Solution View ID</i>	1037

CTGDIW183E Unable to obtain the AM_ID (primary key) for the recently added rule.	1037	CTGDIW202E Unable to obtain rule details for rule: <i>Rule ID</i>	1042
CTGDIW184E Unable to add Action Manager rule into database. Rule Name: <i>Rule Name</i> Rule Description: <i>Description</i> Solution View ID: <i>Solution View ID</i>	1037	CTGDIW203E Error while obtaining Solution View Status.	1042
CTGDIW185E Unable to read Action Manager rule from AM_RULES_MASTER table for rule: <i>Rule Name</i>	1037	CTGDIW204E Error while obtaining status of AssemblyLines.	1042
CTGDIW186E No rows were updated in AM_RULES_MASTER while trying to update trigger type.	1038	CTGDIW205E Unable to store user preferences for user: <i>user name</i>	1042
CTGDIW187E No rows were updated in AM_RULES_MASTER while trying to update trigger type.	1038	CTGDIW206E Unable to get Action Manager Details for Solution View: <i>Solution View ID</i>	1043
CTGDIW188E Unable to read Action Manager rule from AM_RULES_MASTER table for rule: <i>Rule ID</i>	1038	CTGDIW207E Unable to delete data from AM_LOGS table.	1043
CTGDIW189E No rows were updated in AM_RULES_MASTER while trying to update Rule name: <i>Rule Name</i> Rule Description: <i>Description</i> Trigger type: <i>Trigger type</i>	1038	CTGDIW208W Unable to convert the monitor.refresh.rate value to integer.	1043
CTGDIW190E Unable to insert data into trigger configuration tables.	1039	CTGDIW209E Could not obtain an instance of Tombstone Manager for Solution View: <i>Solution View name</i> . It might not be running on the remote server.	1043
CTGDIW191E Unable to store rule or trigger information.	1039	CTGDIW210E No log files found for AssemblyLine: <i>AssemblyLine name</i> and Config: <i>Config</i>	1044
CTGDIW192E Unable to store rule or trigger information. Some error occurred. The parameters passed to code were: Rule ID: <i>Rule ID</i> Rule Name: <i>Rule Name</i> Rule Description: <i>Description</i> Trigger Type: <i>Trigger Type</i> Parameter 1: <i>value</i> Parameter 2: <i>value</i> Parameter 3: <i>value</i> Parameter 4: <i>value</i>	1039	CTGDIW211E No log files found for AssemblyLine: <i>AssemblyLine name</i> and Config: <i>Config</i>	1044
CTGDIW193E Unable to Delete rule: <i>Rule ID</i>	1039	CTGDIW212E Unable to display contents of Log File: <i>Log file name</i> of AssemblyLine: <i>AssemblyLine name</i> in Config: <i>Config</i>	1044
CTGDIW194E Some error occurred while attempting to delete rule: <i>Rule ID</i>	1040	CTGDIW213E Unable to retrieve tombstones for AssemblyLine: <i>AssemblyLine</i> in Config: <i>Config</i>	1044
CTGDIW195E Unable to store Action information. Some error occurred. The parameters passed to code were: Rule ID: <i>Rule ID</i> Action Type: <i>Action Type</i> Parameter 1: <i>value</i> Parameter 2: <i>value</i> Parameter 3: <i>value</i> Parameter 4: <i>value</i>	1040	CTGDIW214W Unable to find group: <i>group name</i>	1045
CTGDIW196E Unable to read action information for rule: <i>Rule ID</i>	1040	CTGDIW215W Error closing database statement.	1045
CTGDIW197E Unable to modify execution order of specified action.	1040	CTGDIW216W Error closing database ResultSet.	1045
CTGDIW198E Unable to modify execution order of specified action. The parameters passed were: Rule ID: <i>Rule ID</i> Direction: <i>Direction</i> Action ID: <i>Action ID</i>	1041	CTGDIW217W Error closing database connection.	1045
CTGDIW199E Unable to delete the specified action. The parameters passed were: Rule ID: <i>Rule ID</i> Action ID: <i>Action ID</i>	1041	CTGDIW218W Message with programmer's Key: <i>key string</i> not found.	1045
CTGDIW200E Unable to insert row into AM_UPDATE_DETAILS table.	1041	CTGDIW219W Some error occurred while evaluating the user's role. User: <i>User Name</i> Solution View ID: <i>Solution View ID</i>	1046
CTGDIW201E Unable to obtain action details for Rule: <i>Rule ID</i> and Action: <i>Action ID</i>	1041	CTGDIW220W Some error occurred while evaluating the user's role. User: <i>User Name</i>	1046
		CTGDIW221W Unable to obtain authorized Config instances. User: <i>User ID</i>	1046
		CTGDIW222I An instance of DBConnectionFactory class created.	1046
		CTGDIW223W Illegal value specified for Action Manager Log Rotate rate (days). Unable to convert to integer. Current value specified for am.logrotate: <i>value</i>	1047
		CTGDIW224I The Administration and Monitoring Console database: <i>database details</i>	1047
		CTGDIW225I Derby network server already running.	1047
		CTGDIW226I Unable to ping Derby network server. Attempting to start.	1047

CTGDIW227W Table does not exist: <i>table name</i>	1047	CTGDIW252E LDAPBindID attribute value not specified in amc.properties or is invalid.	1053
CTGDIW228W Table created: <i>table name</i>	1048	CTGDIW253E LDAPBindPassword attribute value not specified in amc.properties or is invalid.	1053
CTGDIW229I The Administration and Monitoring Console Database has been shutdown.	1048	CTGDIW254E LDAPSuffix attribute value not specified in amc.properties or is invalid.	1053
CTGDIW230W An error occurred while attempting the Administration and Monitoring Console DB shutdown.	1048	CTGDIW255E LdapUserPrefix attribute value not specified in amc.properties or is invalid.	1054
CTGDIW231I LDAP user filter: <i>search filter string</i>	1048	CTGDIW256E LDAPUserSuffix attribute value not specified in amc.properties or is invalid.	1054
CTGDIW232I LDAP user tree base DN: <i>base DN</i>	1049	CTGDIW257W LDAPsslEnabled attribute value not specified in amc.properties or is invalid. Setting SSL to false.	1054
CTGDIW233E An error occurred while attempting to obtain all LDAP users for the Administration and Monitoring Console.	1049	CTGDIW258W Unable to obtain membership for user: <i>user DN</i>	1054
CTGDIW234I LDAP user filter: <i>search filter string</i>	1049	CTGDIW259I Instance of TDISessionFactory class created.	1054
CTGDIW235I LDAP user tree base DN: <i>base DN</i>	1049	CTGDIW260W The api.Config.folder property is not set on the remote server.	1055
CTGDIW236W More than one result obtained for username: <i>user name</i>	1050	CTGDIW261I Trying to establish connection to: Server: <i>hostname</i> Port: <i>port</i>	1055
CTGDIW237E Valid user not found (in LDAP): <i>user name</i>	1050	CTGDIW262I Attempting to use Custom Authentication with username: <i>username</i>	1055
CTGDIW238E Unable to bind to LDAP server with user: <i>user name</i>	1050	CTGDIW263I Unable to establish connection to: Server: <i>hostname</i> Port: <i>port</i>	1055
CTGDIW239I LDAP group filter: <i>search filter string</i>	1050	CTGDIW264W Console administrator <i>username</i> login failed.	1055
CTGDIW240I LDAP group tree base DN: <i>base DN</i>	1050	CTGDIW265W User <i>username</i> login failed.	1056
CTGDIW241E An error occurred while attempting to obtain all LDAP groups for the Administration and Monitoring Console.	1051	CTGDIW266E An error occurred while loading Navigation XML file.	1056
CTGDIW242I Obtaining members of group <i>Group DN</i>	1051	CTGDIW267W Unable to set the amc.session.timeout value. Value obtained from amc.properties file: <i>session timeout value</i> . Web server's default value will be applicable.	1056
CTGDIW243E An error occurred while attempting to obtain all members of LDAP group: <i>Group DN</i>	1051	CTGDIW268E An error occurred while trying to read the Console Admin Password file.	1056
CTGDIW244E LDAPHostname attribute not specified in amc.properties.	1051	CTGDIW269I Obtaining handle to amc.properties file.	1056
CTGDIW245W No value specified for LDAPBindID variable in amc.properties file. Attempting to bind as anonymous user.	1052	CTGDIW270E Unable to initialize LDAP properties. Switching to the Administration and Monitoring Console database based authentication.	1057
CTGDIW246E An error occurred while creating LDAP search context.	1052	CTGDIW271I LDAP properties initialized. The Administration and Monitoring Console authentication source is set to LDAP.	1057
CTGDIW247E LDAPHostname attribute value not specified in amc.properties or is invalid. Value: <i>Attribute value</i>	1052	CTGDIW272E An error occurred while attempting to read the amc.properties file.	1057
CTGDIW248E LDAPPport attribute value not specified in amc.properties or is invalid. Value: <i>Attribute value</i>	1052	CTGDIW273E Unable to initialize DBConnectionFactory.	1057
CTGDIW249E LDAPAdminUId attribute value not specified in amc.properties or is invalid. Value: <i>Attribute value</i>	1052	CTGDIW274I Administration and Monitoring Console initialization complete.	1058
CTGDIW250E LDAPAdminPwd attribute value not specified in amc.properties or is invalid.	1053	CTGDIW275I Administration and Monitoring Console Shutdown.	1058
CTGDIW251E LDAPServerType attribute value not specified in amc.properties or is invalid.	1053		

CTGDIW276I Calling CSA render with URL: <i>URL</i>	1058	CTGDIW298E The Copy property Value action could not be updated. See the logs for errors.	1063
CTGDIW277E Select a server to modify.	1058	CTGDIW299E Select a Tombstone entry from the table to view Tombstone details.	1064
CTGDIW278E Incompatible version of remote IBM Security Directory Integrator server. Remote server version: <i>version number</i>	1058	CTGDIW300E Unable to determine Action Manager Status.	1064
CTGDIW279W The remote IBM Security Directory Integrator server is of version <i>version number</i> . Some of the features of the Administration and Monitoring Console will not be available or will not work correctly with this server version.	1059	CTGDIW301E Click on Clear menu option to clear Action Manager Triggered Status.	1064
CTGDIW280I Thread created for cleanup of Action Manager related logs.	1059	CTGDIW302E Unable to obtain input parameters for AssemblyLine <i>AssemblyLine name</i>	1064
CTGDIW281E AssemblyLine required to create or update the Start AssemblyLine Action.	1059	CTGDIW303I There are no input parameters needed for the chosen AssemblyLine Operation.	1064
CTGDIW282E AssemblyLine is required to create or update the Stop AssemblyLine Action.	1059	CTGDIW304E The AssemblyLine <i>AssemblyLine name</i> could not be started. Check the logs for errors.	1065
CTGDIW283E Notify event actions could not be stored. See the logs for errors.	1060	CTGDIW305E The specified Entry string in AssemblyLine Input parameter panel is incorrectly constructed: <i>string</i>	1065
CTGDIW284E Enable/Disable rule action could not be stored. See the logs for errors.	1060	CTGDIW306E An error occurred while attempting to parse the string: <i>string</i>	1065
CTGDIW285E Start AssemblyLine action could not be stored. See the logs for errors.	1060	CTGDIW307E An error occurred while attempting to parse the string: <i>string</i>	1066
CTGDIW286E Stop AssemblyLine action could not be stored. See the logs for errors.	1060	CTGDIW308E Unable to obtain input parameters for AssemblyLine <i>AssemblyLine name</i>	1066
CTGDIW287E Modify Property action could not be stored. See the logs for errors.	1061	CTGDIW309E AssemblyLine required to create or update Start AssemblyLine Action.	1066
CTGDIW288E Write Log action could not be stored. See the logs for errors.	1061	CTGDIW310E The session with the chosen remote server could not be established.	1066
CTGDIW289E Execute rule action could not be stored. See the logs for errors.	1061	CTGDIW311E The Config <i>Config</i> is not loaded on the server. The Config needs to be loaded for the Administration and Monitoring Console to discover the AssemblyLine operations. Do you want to Load the Config?	1067
CTGDIW290E Copy property value action could not be stored. See the logs for errors.	1061	CTGDIW312E Error occurred while trying to start the Config <i>Config path</i>	1067
CTGDIW291E The Notify event action could not be updated. See the logs for errors.	1062	CTGDIW313E The AssemblyLine <i>AssemblyLine name</i> is not present in the specified Config. Available AssemblyLines: <i>AssemblyLine list</i>	1067
CTGDIW292E The Enable/Disable Rule action could not be updated. See the logs for errors.	1062	CTGDIW314E No operations exposed in AssemblyLine <i>AssemblyLine name</i>	1068
CTGDIW293E The Start AssemblyLine action could not be updated. See the logs for errors.	1062	CTGDIW315E Select an operation from the list.	1068
CTGDIW294E The Stop AssemblyLine action could not be updated. See the logs for errors.	1062	CTGDIW316I There are no input parameters needed for the chosen AssemblyLine Operation.	1068
CTGDIW295E The Modify Property action could not be updated. See the logs for errors.	1063	CTGDIW317E An error occurred while attempting to parse the string: <i>string</i>	1068
CTGDIW296E The Write Log action could not be updated. See the Administration and Monitoring Console logs for errors.	1063	CTGDIW318E An error occurred while attempting to parse the string: <i>string</i>	1069
CTGDIW297E The Execute Rule action could not be updated. See the logs for errors.	1063	CTGDIW319E A Config is required to create or update Start AssemblyLine Action.	1069
		CTGDIW320E A Config is required to create or update Stop AssemblyLine Action.	1069
		CTGDIW321E Select an AssemblyLine to view Logs.	1069

CTGDIW322E The On property trigger is not supported for Solution Views on IBM Security Directory Integrator 6.0 servers. Select a different trigger.	1070	CTGDIW340E No AssemblyLines found in solution. Cannot create Solution View from solution.	1075
CTGDIW323E The Copy IBM Security Directory Integrator Property value Action is not supported for Solution Views on IBM Security Directory Integrator 6.0 servers.	1070	CTGDIW341E None of the AssemblyLines exposed in the solution exist in Config. Cannot create Solution View from solution.	1075
CTGDIW324E The Modify IBM Security Directory Integrator Property Action is not supported for Solution Views on IBM Security Directory Integrator 6.0 servers.	1070	CTGDIW342E Unable to insert into CONFIG_VIEW_MASTER table in database.	1075
CTGDIW325E The Notify event Action is not supported for IBM Security Directory Integrator 6.0 Solution Views.	1070	CTGDIW343E Unable to obtain CV_ID (primary key) value for Solution View <i>Solution View name</i>	1075
CTGDIW326E The IBM Security Directory Integrator server corresponding to the selected Solution View is not running. It is mandatory for the remote IBM Security Directory Integrator server to be running for adding rules.	1071	CTGDIW344E Unable to insert into CONFIG_VIEW_AL_DETAILS table in database.	1076
CTGDIW327E The IBM Security Directory Integrator server corresponding to the selected Solution View is not running. It is mandatory for the remote IBM Security Directory Integrator server to be running for editing rules.	1071	CTGDIW345E Unable to obtain handle to IBM Security Directory Integrator Properties objects.	1076
CTGDIW328E The IBM Security Directory Integrator server corresponding to the selected Solution View is a IBM Security Directory Integrator 6.0 server. IBM Security Directory Integrator Properties feature is not available in IBM Security Directory Integrator 6.0 Solution Views.	1072	CTGDIW346E Unable to insert into CONFIG_VIEW_HEALTH_AL_DETAILS table in database.	1076
CTGDIW329E Unable to obtain the SERVER_ID (primary key) for the recently added server.	1072	CTGDIW347E Unable to determine AssemblyLines in Config.	1076
CTGDIW330E Unable to insert row into AM_SERVER_UPDATE_DETAILS table.	1072	CTGDIW348E Unable to insert into CONFIG_VIEW_MASTER table in database.	1076
CTGDIW331E Could not obtain an instance of Tombstone Manager. It might not be running on the remote server.	1072	CTGDIW349E Unable to obtain CV_ID (primary key) value for Solution View <i>Solution View name</i>	1077
CTGDIW332E No AssemblyLines found in Config. Atleast one AssemblyLine must be present to create a Solution View.	1073	CTGDIW350E Unable to insert into CONFIG_VIEW_AL_DETAILS table in database.	1077
CTGDIW333E Unable to read the AssemblyLine information from Config.	1073	CTGDIW351E Unable to get a handle to IBM Security Directory Integrator Properties object.	1077
CTGDIW334E Unable to get published Solution details from Config.	1073	CTGDIW352E Unable to establish connection to the remote IBM Security Directory Integrator Server. Viewing of AssemblyLine tombstones, AssemblyLine Logs and Manage Properties functionality will not be available.	1077
CTGDIW335I Simple create of Solution View <i>Solution View name</i> successful.	1073	CTGDIW353W Solution is disabled in Config <i>config instance</i>	1078
CTGDIW336E The Solution View could not be created. Check the logs for errors.	1074	CTGDIW354E Rule with name <i>Rule Name</i> already exists for this Solution View.	1078
CTGDIW337I Detected remote IBM Security Directory Integrator Server version <i>version number</i> . Skipping Select Properties step.	1074	CTGDIW355E Polling Interval not specified.	1078
CTGDIW338I Creating Solution View <i>Solution View name</i> from Published Solution. Config Instance ID: <i>Config ID</i>	1074	CTGDIW356W Select the log file(s) to delete.	1078
CTGDIW339E Unable to determine AssemblyLines in Config.	1074	CTGDIW357W Delete the selected logs?	1079
		CTGDIW358E Error occurred while deleting the log files.	1079
		CTGDIW359E Error <i>error message</i> occurred while deleting the log files.	1079
		CTGDIW360W All the selected log files were not deleted.	1079
		CTGDIW361W The log files which were not deleted are : <i>log file names</i>	1079
		CTGDIW362W Delete log is not supported for IBM Security Directory Integrator Server version <i>version number</i>	1080

CTGDIW363W A session could not be established with the remote IBM Security Directory Integrator server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.	1080	CTGDIW382E Unable to recover the key from the keystore <i>keystore</i> . Exception occurred: <i>exception</i>	1084
CTGDIW364W A session could not be established with the remote IBM Security Directory Integrator server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.	1080	CTGDIW383E The keystore <i>keystore</i> has no entry for the alias <i>alias</i>	1085
CTGDIW365W Decimal digits cannot be entered in the field <i>filed name</i>	1081	CTGDIW384E The key store password is NULL or empty.	1085
CTGDIW366W Do you want to change the ServerID of <i>server name</i> from <i>Old Server ID</i> to <i>server id</i> ?	1081	CTGDIW385E Stash file already read.	1085
CTGDIW367E Unable to change the ServerID. A IBM Security Directory Integrator Server entry with the same Server ID, Hostname and Port has been already added. Check the logs for errors.	1081	CTGDIW386E Stash file <i>file name</i> not found.	1085
CTGDIW368E Incorrect config password. Could not load the Config <i>Config path</i>	1081	CTGDIW387E Input Stream is NULL.	1085
CTGDIW369E The Administration and Monitoring Console is unable to obtain ISC role information.	1082	CTGDIW388E The key password or keystore password failed a size validation check. Unable to read in the key password or the keystore password from the stash file.	1086
CTGDIW370E The AssemblyLine <i>AssemblyLine name</i> is already running.	1082	CTGDIW389E Output Stream is NULL.	1086
CTGDIW371E The AssemblyLine <i>AssemblyLine name</i> could not be started. Check the logs for errors.	1082	CTGDIW390E Byte array is NULL.	1086
CTGDIW372E Select an AssemblyLine to start.	1082	CTGDIW391E Encrypted password data too long: <i>length</i>	1086
CTGDIW373E The AssemblyLine <i>AssemblyLine name</i> is already running.	1083	CTGDIW392E No Provider specified for the stash file.	1086
CTGDIW374E The AssemblyLine <i>AssemblyLine name</i> could not be started. Check the logs for errors.	1083	CTGDIW393I Stash file <i>file name</i> has been created.	1087
CTGDIW375E Select an AssemblyLine to start.	1083	CTGDIW394I Could not create stash file. Exception occurred: <i>exception</i>	1087
CTGDIW376E The AssemblyLine <i>AssemblyLine name</i> is already running.	1083	CTGDIW395I Usage: StashFile keyStorePassword [keyPassword [securityProviderClass]]	1087
CTGDIW377E The AssemblyLine <i>AssemblyLine name</i> could not be started. Check the logs for errors.	1083	CTGDIW396E The Administration and Monitoring Console failed to initialize the encrypt/decrypt keystore.	1087
CTGDIW378E Select an AssemblyLine to start.	1084	CTGDIW397E Select a property to modify.	1087
CTGDIW379E An error has occurred while reading the stash file: <i>exception</i>	1084	CTGDIW398E Select a property to delete.	1088
CTGDIW380E No password has been found in the Administration and Monitoring Console stash file.	1084	CTGDIW399E Delete property <i>property name</i> ?	1088
CTGDIW381I The key password is not present in the stash file. The keystore password will be used.	1084	CTGDIW400E Config is not specified for the config load trigger.	1088
		CTGDIW401E Config is not specified for the Config unload trigger.	1088
		CTGDIW402E Decimal digits cannot be entered in the <i>Interval</i> field.	1088
		CTGDIW403E Illegal interval value specified. Value must be greater than zero.	1089
		CTGDIW404E Failed to retrieve trigger details. Refer to the logs for additional information.	1089
		CTGDIW405E Failed to retrieve trigger thread details. Refer to the logs for additional information	1089
		CTGDIW406E Not able to establish session with the action manager.	1089
		CTGDIW407E Failed to retrieve the Acton Manager boot time. Refer to the logs for additional information.	1089
		CTGDIW408E The selected Solution View is marked for auto update. Ensure that auto update is disabled to modify the Solution View.	1090
		CTGDIW409I The selected Solution View has been refreshed.	1090

CTGDIW410E The selected Solution View could not be refreshed. Check the logs for errors.	1090	CTGDIW431E The RMI object <i>remote object name</i> is not bound to the RMI Registry.	1095
CTGDIW411E The trigger value for the local Action Manager variable has not been specified.	1090	CTGDIW432E The RMI registry is not reachable on host: <i>host</i> and port: <i>port</i> . The error message is <i>error</i>	1095
CTGDIW412E Modify local variable action could not be stored. See the logs for errors.	1091	CTGDIW433E The RMI URL is malformed: <i>url</i>	1095
CTGDIW413E The Modify local variable action could not be updated. See the logs for errors.	1091	CTGDIW434I The rollback action for the rule <i>rule name</i> has completed successfully.	1096
CTGDIW414E Name or value for the local variable has not been specified in trigger.	1091	CTGDIW435I The rollback action for the rule <i>rule name</i> failed.	1096
CTGDIW415E The local variable name already exists.	1091	CTGDIW436E The rollback action for the rule <i>rule name</i> failed. Refer to the logs for additional information.	1096
CTGDIW416E Select a local variable to delete.	1092	CTGDIW437E A config file is required to start a config using the run name.	1096
CTGDIW417E Select a local variable to modify.	1092	CTGDIW438E Error occurred while trying to load the config <i>Config path</i>	1096
CTGDIW418I Rule <i>rule Name</i> executed successfully. The following actions were executed: <i>actions list</i>	1092	CTGDIW439E Incorrect or no config password. Could not load the property stores associated with config <i>Config path</i>	1097
CTGDIW419E Rule <i>rule Name</i> execution failed. Refer to the logs for additional information.	1092	CTGDIW440E Error occurred while trying to load the config <i>Config path</i> to display the property stores associated with it.. . . .	1097
CTGDIW420E The Administration and Monitoring Console was unable to obtain running config instances for the local IBM Security Directory Integrator Server.	1092	CTGDIW441E Insufficient rights to perform config load task. for the selected Config instance <i>Config instance</i>	1097
CTGDIW421I Solution View <i>Solution View name</i> created successfully.	1093	CTGDIW442E Action of type 'Send email' could not be stored. See the logs for errors.	1098
CTGDIW422E A unknwn error has occurred. See error logs for more details.	1093	CTGDIW443E Action of type 'Send email' could not be updated. See the logs for errors.	1098
CTGDIW423E An exception occurred while verifying the Action Manager status. Refer to the logs for additional information.	1093	CTGDIW444E The recipient email address is invalid.	1098
CTGDIW424I No thread statistics data were retrieved from Action Manager. This could occur because there are no rules configured in Action Manager.	1093	CTGDIW445W Do you want to delete the tombstones for the AssemblyLine <i>AssemblyLine name</i> ?	1098
CTGDIW425I None of the Action Manager rules was triggered in the time interval <i>time interval</i>	1094	CTGDIW446E Unable to load the amc.properties file.	1098
CTGDIW426W The Action Manager RMI Host is not set in the amc.properties file. As a result the default host <i>hostname</i> will be used.	1094	CTGDIW447E The Administration and Monitoring Console is unable to delete AssemblyLines associated with the Solution View.	1099
CTGDIW427W The Action Manager RMI Port is not set in the amc.properties file. As a result the default port <i>port number</i> will be used.	1094	CTGDIW448W Do you want to delete the tombstones with GUID <i>GUID</i> ?	1099
CTGDIW428W Not able to establish a connection with the Action Manager. Action Manager Session is null.	1094	CTGDIW449E An error occurred while deleting the tombstones: <i>error</i> . Refer to the exception stack trace for more details.	1099
CTGDIW429E An exception occurred while triggering the rule <i>rule name</i> . Refer to the logs for additional information.	1095	CTGDIW450I The properties file <i>file name</i> loaded successfully.	1099
CTGDIW430E An exception occurred while initializing the AMStatus Bean. Refer to the logs for additional information.	1095	CTGDIW451I Administration and Monitoring Console database type property set to <i>database type</i>	1100
		CTGDIW452I The Administration and Monitoring Console is connected to database <i>database name</i> on host <i>host name</i> using port <i>port number</i>	1100
		CTGDIW453I The jdbc driver <i>driver name</i> is loaded successfully.	1100

CTGDIW454I The conf directory path: <i>directory path</i>	1100	CTGDIW479W No log files found for AssemblyLine: <i>AssemblyLine name</i> and Config: <i>Config name</i>	1105
CTGDIW455I Loading schema file <i>file name</i>	1100	CTGDIW480W Select the log file(s) to delete.	1106
CTGDIW456W The property <i>amc.db.type</i> is not set and hence setting the database type to <i>file name</i>	1101	CTGDIW481W Unable to delete the following log files: <i>file names</i>	1106
CTGDIW457W The properties file <i>file name</i> does not exist.	1101	CTGDIW482E An error occurred while deleting the log files.	1106
CTGDIW458I The database handler class <i>class name</i> is used for parsing the XML file and constructing the SQL queries.	1101	CTGDIW483E An error occurred while deleting the log files: <i>error message</i>	1106
CTGDIW459E No handler found for database <i>database type</i> in the properties file <i>file name</i>	1101	CTGDIW484W Delete the selected logs?	1107
CTGDIW460I DBUtils initialized successfully.	1101	CTGDIW485W An error occurred while displaying the log files.	1107
CTGDIW461I The handler class <i>class name</i> is initialized successfully.	1102	CTGDIW486W An error occurred while displaying the log files.	1107
CTGDIW462E The handler class <i>class name</i> cannot be found.	1102	CTGDIW487E Unable to establish connection to the remote IBM Security Directory Integrator Server. Log management functionality is not available for the selected Solution View.	1107
CTGDIW463E The handler class <i>class name</i> cannot be accessed.	1102	CTGDIW488I This Solution View belongs to a server prior to IBM Security Directory Integrator version 7.0. The user cannot see the log file listing. All log files satisfying the deletion criteria will be deleted when you click delete.	1108
CTGDIW464E The handler class <i>class name</i> cannot be initialized.	1102	CTGDIW489W A username and password or keystore and keystore password must be specified in order to log into the remote computer.	1108
CTGDIW465E An error occurred while parsing the XML file: <i>error message</i>	1102	CTGDIW490W The selected action <i>action name</i> is not supported.	1108
CTGDIW466E The XML file <i>file name</i> cannot be found.	1103	CTGDIW491E The Solution View could not be created. Check the logs for errors.	1108
CTGDIW467I The SQL Query executed successfully: <i>SQL query</i>	1103	CTGDIW492W The Parent User Task manager object is null and cannot display the panels.	1109
CTGDIW468W The SQL query execution failed: <i>SQL query</i>	1103	CTGDIW493E The sender email address is invalid.	1109
CTGDIW469I SQL query <i>SQL query</i> not executed as the database object already exists.	1103	CTGDIW494I No healthAL details for Solution View: <i>Solution View name</i>	1109
CTGDIW470E An rror occurred while initializing the Administration and Monitoring Console database.	1103	CTGDIW495E An error while rolling back database transaction : <i>error</i>	1109
CTGDIW471E An error occurred while inserting the default local server. Refer to the stack trace for more details.	1104	CTGDIW496E The command length exceeds the database column width.	1109
CTGDIW472E An exception was encountered while processing the XML data.	1104	CTGDIW497I The AssemblyLine <i>Solution View name</i> has no tombstones to be deleted.	1110
CTGDIW473E None of the tombstones have been deleted from the selected delete criteria.	1104	CTGDIW498E An error <i>error</i> occurred while initializing the Adinistration and Monitoring Console security.	1110
CTGDIW474I Number of tombstones deleted successfully : <i>number of tombstones</i>	1104	CTGDIW499E An error <i>error</i> occurred while connecting to Action Manager.	1110
CTGDIW475I The Administration and Monitoring Console database XML file path is <i>file path</i>	1104	CTGDIW500E An error <i>error</i> occurred while writing the SQL file.	1110
CTGDIW476I Successfully loaded the jdbc driver <i>class name</i>	1105	CTGDIW501I Inside the tokenizeSQLCommands method.	1110
CTGDIW477I The property <i>amc.db.type</i> is not set in the <i>amc.properties</i> file. Defaulting to Derby Database type.	1105	CTGDIW502I The total number of sql queries generated is <i>number of sql queries</i>	1111
CTGDIW478I The database type is set to <i>type name</i>	1105	CTGDIW503I The handler property name for getting the handler class is <i>property name</i>	1111
CTGDIW478E Unable to update the database with the values specified in the checkboxes.	1105		

CTGDIW504I Loaded the <i>file name</i> file.	1111	CTGDIW530E An error occurred while creating a solution view from a published solution: <i>error</i>	1116
CTGDIW505W The configuration file <i>file name</i> does not exist.	1111	CTGDIW531E An error occurred while deleting AssemblyLine details: <i>error</i>	1117
CTGDIW506E An error occurred while reading the configuration XML file <i>file name</i>	1112	CTGDIW532E An error occurred while adding AssemblyLine details: <i>error</i>	1117
CTGDIW507E An error occurred while closing the input stream.	1112	CTGDIW533E An error occurred while updating Solution View properties: <i>error</i>	1117
CTGDIW508I Inside the parseXML(InputStream, String) method of DBUtils.	1112	CTGDIW534E An error occurred while retrieving Solution Views for user <i>user id</i> : <i>error</i>	1117
CTGDIW509I Started parsing the XML file.	1112	CTGDIW535W Invalid integer Solution View ID: <i>Solution View id</i>	1117
CTGDIW510I Completed parsing the XML file.	1112	CTGDIW536E An error occurred while deleting Solution View: <i>error</i>	1118
CTGDIW511I Inside the parseXML() method of DBUtils.	1113	CTGDIW537E An error occurred while executing the SQL query <i>SQL query</i> : <i>error</i>	1118
CTGDIW512I Reading the XML file <i>file name</i> into the input stream.	1113	CTGDIW538E An error occurred while retrieving the ACL information: <i>error</i>	1118
CTGDIW513I Parsing the XML file <i>file name</i> using the Handler <i>Handler name</i>	1113	CTGDIW539E An error occurred while retrieving user information for Solution View <i>solution view id</i> : <i>error</i>	1118
CTGDIW514E Error closing the input stream.	1113	CTGDIW540E An error occurred while retrieving groups with no access to Solution View <i>solution view id</i> : <i>error</i>	1118
CTGDIW515E An error <i>error</i> occurred while connecting to Action Manager.	1113	CTGDIW541E An error occurred while storing user <i>user name</i> with role <i>role</i> for Solution View <i>solution view id</i> : <i>error</i>	1119
CTGDIW516I Unencrypted string is null or empty	1114	CTGDIW542E An error occurred while deleting user groups: <i>error</i>	1119
CTGDIW517I Encrypted string was null or empty.	1114	CTGDIW543E An error occurred while retrieving ACL information for Solution View <i>Solution view id</i> : <i>error</i>	1119
CTGDIW518E An error occurred while decrypting property: <i>error</i>	1114	CTGDIW544E An error occurred while retrieving the Solution View properties: <i>error</i>	1119
CTGDIW519E An error occurred while initializing of String encryption decryption utility: <i>error</i>	1114	CTGDIW545E An error occurred while retrieving the Health AssemblyLine details for Solution View id <i>solution view id</i> : <i>error</i>	1119
CTGDIW520E An error occurred while encrypting property: <i>error</i>	1114	CTGDIW546E An error occurred while retrieving the Local Action Manager Variables for Solution View id <i>solution view id</i> : <i>error</i>	1120
CTGDIW521E An error occurred while retrieving the information of <i>Solution View name</i> solution view: <i>error</i>	1115	CTGDIW547E An error occurred while disabling auto update for Solution View id <i>solution view id</i> : <i>error</i>	1120
CTGDIW522E An error occurred while retrieving the Server information: <i>error</i>	1115	CTGDIW548E An error occurred while adding the local variable <i>variable name</i> : <i>error</i>	1120
CTGDIW523E An error occurred while creating the Solution View <i>solution view name</i> : <i>error</i>	1115	CTGDIW549E An error occurred while updating the local variable <i>variable name</i> : <i>error</i>	1120
CTGDIW524E An error occurred while rolling back the database transaction: <i>error</i>	1115	CTGDIW550E An error occurred while deleting the local variable <i>variable name</i> : <i>error</i>	1120
CTGDIW525E An error occurred while retrieving the latest Solution View ID: <i>error</i>	1115	CTGDIW551E An error occurred while verifying if the local variable <i>variable name</i> exists: <i>error</i>	1121
CTGDIW526E An error occurred while adding the Solution View details in database: <i>error</i>	1116		
CTGDIW527E An error occurred while adding the Solution View properties in database: <i>error</i>	1116		
CTGDIW528E An error occurred while adding the Health AssemblyLine details: <i>error</i>	1116		
CTGDIW529E An error occurred while committing changes to the database: <i>error</i>	1116		

CTGDIW552E An error occurred while refreshing the Solution View: *error* . . . 1121

CTGDIW553E An error occurred while deleting the AssemblyLines for Solution View id *solution view id: error* . . . 1121

CTGDIW554E An error occurred while deleting the properties for Solution View id *solution view id: error* . . . 1121

CTGDIW555E An error occurred while retrieving properties for property store *Property Store name: error* . . . 1121

CTGDIW556E An error occurred while refreshing published solution: *error* . . . 1122

CTGDIW557E An error occurred while initializing the ManageTDisrvBean: *error* . 1122

CTGDIW558E An error *error* occurred while verifying the Local Server. . . . 1122

CTGDIW559E An error occurred while initializing ViewMonitorBean: *error* . . . 1122

CTGDIW560E An error occurred while initializing the QuickCreateBean: *error* . 1122

CTGDIW561E An error occurred while getting the start time for AssemblyLine *AssemblyLine name: error* 1123

CTGDIW562E An error occurred while retrieving the AssemblyLine details: *error* 1123

CTGDIW563E An error occurred while retrieving the Config for AssemblyLine *AssemblyLine name: error* 1123

CTGDIW564E An error occurred while initializing the *class name* class: *error* . 1123

CTGDIW565E An error occurred while stopping the AssemblyLine *AssemblyLine name: error* 1123

CTGDIW566E An error occurred while starting the AssemblyLine *AssemblyLine name: error* 1124

CTGDIW567E An error occurred while starting the AssemblyLine *AssemblyLine name* in simulate mode: *error* 1124

CTGDIW568E An error occurred while retrieving the AssemblyLine details: *error* 1124

CTGDIW569E An error occurred while retrieving properties: *error* 1124

CTGDIW570E An error occurred while populating the AssemblyLine table for AssemblyLine *AssemblyLine name: error* . . 1124

CTGDIW571E An error occurred while populating the Health AssemblyLine table for Health AssemblyLine *Health AssemblyLine name: error* 1125

CTGDIW572E An error occurred while retrieving the AssemblyLines for the Solution View *Solution view name: error* . 1125

CTGDIW573E An error occurred while preparing the Properties panel: *error* . . 1125

CTGDIW574E An error occurred while refreshing the Properties panel: *error* . . 1125

CTGDIW575E An error occurred while retrieving the last stop time for the AssemblyLine *AssemblyLine name: error* . . 1125

CTGDIW576E An error occurred while obtaining the *AssemblyLine name* AssemblyLine statistics: *error* 1126

CTGDIW577E An error occurred while getting the AssemblyLine status: *error* . . 1126

CTGDIW578E An error occurred while getting the preferred Solution Views: *error* 1126

CTGDIW579E An error occurred while getting the Solution Views for *user name* user: *error* 1126

CTGDIW580E An error occurred while getting the IBM Security Directory Integrator port: *error* 1126

CTGDIW581E An error occurred while deleting the AM_LOGS_HISTORY for Solution View ID *Solution View id: error* 1127

CTGDIW582E An error occurred while getting the Solution View ID for *Solution View* Solution View: *error* 1127

CTGDIW583E An error *error* occurred while closing the Statement object. . . . 1127

CTGDIW584E An error occurred while stopping a Config Instance: *error* 1127

CTGDIW585I An error occurred while executing the SQL query *SQL query: error* . 1127

CTGDIW586E An error occurred while creating the table *table name: error* . . . 1128

CTGDIW587E An error *error* occurred while getting the connector. 1128

CTGDIW588E An error occurred while getting the parserConfig for Connector: *error* 1128

CTGDIW589E An error occurred while getting the Connector name: *error* 1128

CTGDIW590E An error occurred while getting the Connector mode: *error* 1128

CTGDIW591E An error occurred while getting the parser type associated with Connector: *error* 1129

CTGDIW592E The Connector Config instance is null. 1129

CTGDIW593E An error occurred while getting the connector status and will assume its enabled: *error* 1129

CTGDIW594E An error occurred while getting the connector information on inheritance: *error* 1129

CTGDIW595E An error *error* occurred while getting the connector information. . . . 1129

CTGDIW596I Completed processing the Administration and Monitoring Console XML document. 1130

CTGDIW597I Processing the Primary Key instruction. 1130

CTGDIW598I Processing the Foreign Key instruction. 1130

CTGDIW599I Processing the Unique Key instruction. 1130

CTGDIW600I Constructing the CREATE TABLE SQL query for *table name* table. . . . 1130

CTGDIW601I Processing the column tag for table for <i>table name</i> table.	1131	CTGDIW625E Select an Action Manager log to delete.	1135
CTGDIW602I Processing the autoincrement instruction.	1131	CTGDIW626E The End Date is earlier than the Start Date.	1136
CTGDIW603I Processing the constraint <i>constraint type</i> for <i>column</i> column.	1131	CTGDIW627E Unable to find group: <i>string</i>	1136
CTGDIW604I The primary key name is <i>primary key name</i>	1131	CTGDIW628I SDI servers earlier than 7.1 version does not support graceful shutdown.	1136
CTGDIW605I The foreign key name is <i>key name</i>	1131	CTGDJB001W The command did not complete successfully. See previous messages or error logs for details.	1136
CTGDIW606I Detected remote server version: <i>server version</i> . Disabling tombstone button and Manage properties button.	1132	CTGDJB002E Unknown value passed for '-op' option.	1136
CTGDIW607E An error occurred while getting the meta merge config: <i>error</i>	1132	CTGDJB003E The server <i>hostname</i> does not support Tombstones. Tombstone support is not available in pre-6.1 servers.	1137
CTGDIW608I No action to be performed for the command <i>command name</i>	1132	CTGDJB004E Incorrect command usage.	1137
CTGDIW609E An error occurred while deleting the rule with Rule ID <i>rule id</i> : <i>error</i>	1132	CTGDJB005E Unable to get Tombstone manager.	1137
CTGDIW610W An error occurred while deleting the file <i>file name</i> :	1132	CTGDJB006E Only a single Config can be specified.	1137
CTGDIW611E The string <i>path</i> is not a valid URL. Malformed Url exception occurred while converting the string to URL.	1133	CTGDJB007E No value specified for <i>option name</i> option.	1137
CTGDIW612E An error occurred while closing the output stream.	1133	CTGDJB008E Only a single AssemblyLine can be specified.	1138
CTGDIW613E The selected tombstone entry does not exist.	1133	CTGDJB010E The value for the age option has to be an integer greater than zero (days).	1138
CTGDIW614E A thread in waiting/sleeping/paused state is interrupted by another thread.	1133	CTGDJB011E Conflicting Tombstone option passed. Use keyword 'all' or specify a set of Tombstone attributes.	1138
CTGDIW615E An error occurred while getting the server id for IBM Security Directory Integrator server on host <i>host</i> and port <i>port</i> : <i>error</i>	1133	CTGDJB012E The 'all' keyword should be the last argument passed.	1138
CTGDIW616E Conversion of string <i>string</i> to <i>number type</i> failed	1134	CTGDJB014E The <i>option switch</i> option is mandatory.	1139
CTGDIW617E An error occurred while deleting the tombstones.	1134	CTGDJB015E Could not locate Config <i>Config name</i>	1139
CTGDIW618W Any changes to JDBC or SSL properties will need require a manual restart of the Administration and Monitoring Console. Apply changes to console properties?	1134	CTGDJB016I Connected to server <i>hostname</i> and <i>port</i>	1139
CTGDIW619E An error occurred while reading properties using Server API.	1134	CTGDJB017I Config started: <i>Config name</i>	1139
CTGDIW620E An error occurred while accessing AssemblyLine information using Server API.	1134	CTGDJB018I Config already running: <i>Config name</i>	1139
CTGDIW621E An error occurred while accessing Config information using Server API.	1135	CTGDJB019E Could not start Config: <i>Config name</i>	1140
CTGDIW622E An error occurred while closing file stream.	1135	CTGDJB020I AssemblyLine running: <i>AssemblyLine name</i>	1140
CTGDIW623E An error occurred while rolling back database transaction : <i>error</i>	1135	CTGDJB021I AssemblyLine started: <i>AssemblyLine name</i>	1140
CTGDIW624E An error while rolling back database transaction : <i>error</i>	1135	CTGDJB022E AssemblyLine <i>AssemblyLine name</i> not found.	1140
		CTGDJB023E Could not start AssemblyLines on the server <i>hostname</i> and <i>port</i>	1141
		CTGDJB028E The Config <i>Config name</i> is not loaded.	1141
		CTGDJB029I Config stopped: <i>Config name</i>	1141
		CTGDJB030E Could not stop Config: <i>Config name</i>	1141
		CTGDJB031I AssemblyLine stopped: <i>AssemblyLine name</i>	1141
		CTGDJB032E Could not stop AssemblyLine: <i>AssemblyLine name</i>	1142

CTGDJB033E AssemblyLine already stopped:
AssemblyLine name. 1142

CTGDJB034E Error occurred while stopping
 AssemblyLines. 1142

CTGDJB039E Cannot connect to server
hostname and port. 1142

CTGDJB040I The server *hostname and port*
 has been shutdown. 1142

CTGDJB041I Config *Config name* reloaded. 1143

CTGDJB042E Config *Config name* is not
 running. 1143

CTGDJB043E One or more Configs could not
 be reloaded on the server *hostname and
 port*. Check the previous messages or error
 logs for details. 1143

CTGDJB044I All the specified Configs have
 been successfully reloaded on the server
hostname and port. 1143

CTGDJB045E The *operator switch* option
 occurred more than once. 1143

CTGDJB046E Unknown option *operator switch*
 encountered. 1144

CTGDJB047E The *operator switch* option was
 not specified. This is a mandatory option. 1144

CTGDJB048E It is mandatory to specify
 Config. 'all' keyword is not allowed with
 -c option. 1144

CTGDJB049I Usage: tdisrvctl
 [general_options] -op operation
 [operation_specific_options]
 general_options: -h host remote server IP
 address or hostname(default is localhost)
 -K keystore name of the SSL key database
 file -p port port number(default is 1099)
 -P key_pwd key file password -s dir
 Specifies the working directory where the
 solution directory is located. -T
 truststore name of the SSL trust store
 database file -u userID username(for custom
 authentication) -v run in verbose mode -w
 user_pwd user password(for custom
 authentication) -W trust_pwd trust file
 password -? display command usage
 operation: event send custom notification
 event prop manage Config properties queryop
 query an AssemblyLine for operations reload
 reload running Configs report generate
 Config report or list Configs on remote
 server shutdown shut down the server
 srvinfo view IBM Security Directory
 Integrator server information status view
 status of Configs or AssemblyLines start
 start specific Config or AssemblyLines stop
 stop specific Config or AssemblyLine
 tombstone view Tombstone entries for
 specific Config or AssemblyLine
 deletetombstone delete a tombstone entry
 debug debug components in a running
 AssemblyLine To get help for a specific
 operation: tdisrvctl -op operation -? . . 1145

CTGDJB050I The usage for reload operation
 is: tdisrvctl [general_options] -op reload
 -c config_list where: -c config_list comma
 separated list of Configs to reload . . . 1145

CTGDJB051I The usage for shutdown
 operation is: tdisrvctl [general_options]
 -op shutdown [-o return_code] [-f] where:
 -o return_code shutdown server with
 specified return code -f force a controlled
 shutdown and exit all AssemblyLines . . . 1146

CTGDJB052I The usage for srvinfo operation
 is: tdisrvctl [general_options] -op srvinfo 1146

CTGDJB053I The usage for status operation
 is: tdisrvctl [general_options] -op status
 [-c config_list | all] [-r AL_list | all]
 [-listen] where: -c config_list comma
 separated list of Configs or keyword 'all'
 -r AL_list comma separated list of ALs or
 keyword 'all' -listen start receiving the
 logs of a running Config or AssemblyLine
 Example: To see the status of all loaded
 Configs and ALs tdisrvctl [general_options]
 -op status To see the status of all running
 ALs tdisrvctl [general_options] -op status
 -r all To see the status of all components
 of a particular loaded Config tdisrvctl
 [general_options] -op status -c Config.xml
 -r all Note: - The keyword 'all' indicates
 all Configs or AssemblyLines. - The -listen
 option requires exactly one Config or
 AssemblyLine to be specified. 1146

CTGDJB054I The usage for the start operation is: `tdisrvctl [general_options] -op start -c config [-e password] [-r AL_list | all] [-s] [-r AL_list -alop opname [{attr1:value1;attr2:value2;attrN:valueN}]] -f filename] [-m config_run_name -o storeName1=value1, storeName2=value2, storeNameN=valueN] [-t] [-listen] [-sync]` where: `-c` config name of config to start `-e` password password of the config file if it is password protected `-r AL_list` comma separated list of AssemblyLines to start or keyword 'all' `-s` simulate mode run AssemblyLine in simulate mode `-alop opname` AssemblyLine operation with required attributes and their values `-f filename` filename to specify the operations `-m config run name` run name of config `-o property file list` comma separated list of property store names and values `-t` start a temporary Config `-listen` receive the logs of the specified Config or AssemblyLine `-sync` execute AssemblyLine synchronously
 Note: - The `-c` option is mandatory. - The keyword 'all' indicates all AssemblyLines. - The `-t` option expects the Config specified in the `-c` option to be located on the client machine. - The `-listen` option requires exactly one Config or AssemblyLine to be specified. - The `-listen` option executes an AssemblyLine synchronously. There is no need to combine it with the `-sync` option. - The `-sync` option requires exactly one AssemblyLine to be specified. . 1147

CTGDJB055I The usage for stop operation is: `tdisrvctl [general_options] -op stop -c config [-r AL_list | all] [-f]` where: `-c` config name of Config `-r AL_list` comma separated list of ALs to stop or keyword 'all' `-f` force a controlled shutdown of AssemblyLines
 Note: - The `-c` option is mandatory. - The keyword 'all' indicates all AssemblyLines. 1147

CTGDJB056I The usage for tombstone operation is: `tdisrvctl [general_options] -op tombstone -c config [-r AL_name] [-age n] [[attribute_list] | all]` where: `-age n` display tombstone record for the last 'n' days (default is 1 day) `-c config` name of Config `-r AL_name` name of Asembly Line all show all Tombstone attributes
`attribute_list`: `-ct` component type `-cn` component name `-cfg` configuration name `-guid` Tombstone entry's guid `-et` event type `-ex` exit code `-stime` component's start time `-ctime` Tombstone create time `-desc` error description `-um` user message `-stat` statistics (valid for ALs only)
 Example: To see the last 2 days Tombstone entries (all attributes) for Config C1.xml `tdisrvctl [general_options] -op tombstone -c C1.xml -age 2 all`
 Note: - The `-c` option is mandatory. - Only one of the `-r` or `-t` option is allowed. Not both. 1148

CTGDJB057E The Config *Config name* is not loaded on the server *hostname and port*. . 1148

CTGDJB058I The Config folder on server *hostname and port* is empty. 1148

CTGDJB059I The usage for report operation is: `tdisrvctl [general_options] -op report [-c config | -l]` where: `-c config` name of the Config whose report is to be generated `-l` list the Configs in the remote server's Config folder
 Note: - The specified Config must be already loaded on the remote server. - Only one of the `-c` or `-l` option is allowed. Not both. 1149

CTGDJB060E The server *hostname* does not support 'config' folder. The 'config' folder support is not available in pre-6.1 servers. 1149

CTGDJB061I The usage for event operation is: `tdisrvctl [general_options] -op event -e event_name [-s source] [-d data]` where: `-e event_name` name of the event to send `-s source` the name of the source invoking the event (default `tdisrvctl`) `-d data` the data (message) to be passed to an event listener (default is null)
 Note: - All events sent from `tdisrvctl` (`-e` option) are automatically prefixed by the string "user".
 Example: To send an event "user.process.X.completed" from "admin"
`tdisrvctl -h hostname -op event -e "process.X.completed" -s admin -d "Admin triggered event"`. 1149

CTGDJB062I The event *event name* successfully sent. 1150

CTGDJB063I The usage for prop operation is: `tdisrvctl [general_options] -op prop -c config [-l] | [[-o store] [[-g key | all] | [-s key=value [-e]] | [-d key]]]` where: `-c` config name of the Config to use `-l` list all the configured property stores `-o` name of the property store to use `-g` key get the value of the specified key (or keyword 'all' implying get all keys) `-s` key=value set the key to the specified value `-e` encrypt the value when putting in the store (can be used with `-s` option only) `-d` key delete the specified key from the store
 Note: - The `-c` option is mandatory. The specified Config should be a loaded Config on the remote server. - The `-l`, `-g`, `-s`, and `-d` options are mutually exclusive, and cannot be used together. - The `-e` option can be used with only the `-s` option. - The `-o` option is mandatory when using the `-d` option. Examples: To list all property stores for Config C1.xml `tdisrvctl -op prop -c C1.xml -l` To get all properties for Config C1.xml `tdisrvctl -op prop -c C1.xml -g all` To get all properties for Config C1.xml from store MyStore `tdisrvctl -op prop -c C1.xml -o MyStore -g all` To set a property MY_PROP to value MY_VALUE for Config C1.xml in store MyStore and mark it as protected `tdisrvctl -op prop -c C1.xml -o MyStore -s "MY_PROP=MY_VALUE" -e` . . . 1150
 CTGDJB064E Only one of the options `-l`, `-g`, `-s`, and `-d` can be specified. They cannot occur together. 1151
 CTGDJB065E The property store (`-o` option) is not specified. 1151
 CTGDJB066E Property store *property store name* does not exist. 1151
 CTGDJB067I The property key *property key* does not exist. 1151
 CTGDJB068E The server *hostname* does not support remote client event notification. This feature is not available in pre-6.1 servers. 1152
 CTGDJB069E The server *hostname* does not support common APIs for IBM Security Directory Integrator Property management. This feature is not available in pre-6.1 servers. 1152
 CTGDJB070I The property *key name* has been set and committed. 1152
 CTGDJB071I The property *key name* successfully deleted. 1152
 CTGDJB072I The usage for query operation is: `tdisrvctl [general_options] -op queryop -c config -r AL_name` where: `-c` config name of a loaded configuration `-r` AL_name valid AssemblyLine in the specified configuration 1153
 CTGDJB073I Return Code: *return code*. . . 1153
 CTGDJB074I Determining whether Tombstone is supported. 1153

CTGDJB075I Server version: *version*. . . . 1153
 CTGDJB076I Start Date: *date*. 1153
 CTGDJB077I End Date : *date*. 1154
 CTGDJB078I Config ID : *Config ID*. 1154
 CTGDJB079I Number of Tombstones found: *number of tombstones*. 1154
 CTGDJB080I Determining whether remote client event notification is supported. . 1154
 CTGDJB081I Server version: *version*. . . . 1154
 CTGDJB082I Determining whether IBM Security Directory Integrator Properties is supported. 1155
 CTGDJB083I Server version: *version*. . . . 1155
 CTGDJB084I In `displayPropertyStoreList` method. 1155
 CTGDJB085I In `displayPropertyValues` method. 1155
 CTGDJB086I In `setTDIPropertyValue` method. 1155
 CTGDJB087I In `deleteTDIProperty` method. 1156
 CTGDJB088I The server is: *server name*. 1156
 CTGDJB089E Config instance not started. Exception occurred: *exception* 1156
 CTGDJB090I In `viewServerInformation` method. 1156
 CTGDJB091I In `sendEventNotification` method. 1156
 CTGDJB092I In `viewStatus` method. 1157
 CTGDJB093I In `startComponents` method. . . 1157
 CTGDJB094I In `stopComponents` method. . . 1157
 CTGDJB095I In `viewAllIALStatus` method. . . 1157
 CTGDJB096I Number of running Configs: *number of Configs*. 1157
 CTGDJB098I Number of running Configs: *number of Configs*. 1158
 CTGDJB099I Attempting to connect to IBM Security Directory Integrator server: *hostname: port*. 1158
 CTGDJB100I Using custom authentication. Username: *username*. 1158
 CTGDJB102I In `shutdownServer` method. Return code *return_code* passed to method. . 1158
 CTGDJB103I Determining whether Config folder feature is supported. 1158
 CTGDJB104I Server version: *version*. . . . 1159
 CTGDJB105I In `reloadConfigs` method. . . . 1159
 CTGDJB106W Duplicate argument: '*token*'. Argument is ignored. 1159
 CTGDJB107I Parsing general options. . . . 1159
 CTGDJB108I General Options: *options*. . . 1159
 CTGDJB109E Unable to determine server version. Cannot continue. 1160
 CTGDJB110E Unable to obtain Tombstones. 1160
 CTGDJB111E Invalid age: *age value*. . . . 1160
 CTGDJB112E Error while processing shutdown return code. 1160
 CTGDJB113E Unable to determine server version. Cannot continue. 1161
 CTGDJB114E Error while trying to obtain list of property stores for Config: *Config name*. 1161

CTGDJB115E Error while trying to obtain list of property stores for Config: <i>Config name</i>	1161
CTGDJB116E Error while trying to obtain property for Config: <i>Config name</i>	1161
CTGDJB117E Error while trying to set property for Config: <i>Config name</i>	1162
CTGDJB118E Error while trying to delete property ' <i>key name</i> ' for Config: <i>Config name</i>	1162
CTGDJB119E The KEY=VALUE format should have been specified for <i>property key and value</i>	1163
CTGDJB120E Unable to retrieve server information.	1163
CTGDJB121E Error while sending custom event notification: event name= <i>event name</i> , event source= <i>event source</i> , event data= <i>event data</i>	1163
CTGDJB122E Unable to get the Config info or stop the Config.	1163
CTGDJB123E Unable to get details for AssemblyLines.	1164
CTGDJB125E Unable to get list of all running Configs.	1164
CTGDJB126E Unable to get list of all Configs.	1164
CTGDJB127E Error while getting assembly line details.	1164
CTGDJB128E Error while getting Connector library details.	1165
CTGDJB129E Error while getting Parser library details.	1165
CTGDJB130E Error while getting script library details.	1165
CTGDJB131E Error while getting function library details.	1165
CTGDJB132E Unable to determine server version. Cannot continue.	1166
CTGDJB133E Unable to get list of all Configs.	1166
CTGDJB134E Error while retrieving list of loaded Configs.	1166
CTGDJB135W Already reached the end of argument list.	1166
CTGDJB136I Argument at index <i>index</i> : <i>value</i>	1166
CTGDJB137I Configuration: <i>configuration name</i>	1167
CTGDJB138E AssemblyLine <i>AssemblyLine name</i> not found.	1167
CTGDJB139I No operations exposed by the AssemblyLine.	1167
CTGDJB140E The Config <i>Config name</i> is not loaded.	1167
CTGDJB141E The server <i>hostname</i> does not support deletion of tombstones. Delete tombstone support is not available in pre-7.0 servers.	1167

CTGDJB142I The usage for the tombstone deletion operation is: <code>tdisrvctl [general_options] -op deletetombstone -guid 'GUID #'</code> where: <code>-guid 'GUID #'</code> is the unique identifier for the tombstone to be deleted. Note: <code>-</code> GUID for a tombstone can be obtained by viewing a tombstone	1168
CTGDJB143I Tombstone with guid <i>GUID</i> successfully deleted.	1168
CTGDJB144I Temp configs cannot be run with password specified.	1168
CTGDJB145E It is mandatory to specify an AssemblyLine name. ' <i>keyword</i> ' keyword is not allowed.	1168
CTGDJB146E Option ' <i>option</i> ' is not allowed for operation ' <i>option</i> '.	1169
CTGDJB147I Listening for AssemblyLine messages...	1169
CTGDJB148I Listening for Config messages...	1169
CTGDJB149I In debugComponents method.	1169
CTGDJB150E The AssemblyLine <i>AL name</i> is not running.	1169
CTGDJB151E Could not set debug mode to <i>component name</i> component.	1170
CTGDJB152I The usage for the debug operation is: <code>tdisrvctl [general_options] -op debug -c config -r assembly_line [-alc al_component] -on/off</code> where: <code>-c config</code> config instance ID <code>-r assembly_line</code> name of the AssemblyLine <code>-alc al_component</code> name of the AssemblyLine component <code>-on</code> flag to enable debug mode <code>-off</code> flag to disable debug mode Note: <code>-</code> The <code>-c</code> and <code>-r</code> options are mandatory and require exactly one Config/AssemblyLine to be specified. <code>-</code> If <code>-alc</code> option is not specified all components in the specified AssemblyLine will be affected. Examples: To view the Debug mode value of the components in the AssemblyLines of a specified Config <code>tdisrvctl -op report -c config</code> To enable the debug mode for all components in the running AssemblyLine <code>al2 tdisrvctl -op debug -c config_name -r al2 -on</code> To disable the debug mode for specified components in the running AssemblyLine <code>al3 tdisrvctl -op debug -c config_name -r al3 -alc fread,httpServer,myconn -off</code>	1170
CTGDJB153I AssemblyLine <i>AssemblyLine name</i> completed successfully. Statistics: <i>AssemblyLine statistics</i>	1170
CTGDJB154I AssemblyLine <i>AssemblyLine name</i> failed with exception: <i>exception</i> Statistics: <i>AssemblyLine statistics</i>	1171
CTGDJB155I Last AssemblyLine Entry: <i>Entry object</i>	1171
CTGDJB156W Could not retrieve last AssemblyLine Entry: <i>exception</i>	1171

CTGDKI001I The 'java.naming.factory.initial' is set to 'com.ibm.dsml2.jndi.DSML2InitialContextFactory'	1171	CTGDJP601I New MxConnIterator instance created.	1176
CTGDIU001E Invalid day of the month, 'day', was entered for the schedule time. Only 1-31 are valid days of the month.	1171	CTGDJP602I New MxConnSync instance created.	1177
CTGDIU002E Invalid day of month, 'day', was entered for the schedule time in February. Only 1-29 are valid days of the month in February.	1172	CTGDJP603I New MxConnDelete instance created.	1177
CTGDIU003E Invalid day of month, 'day', was entered for the schedule time in month 'month'. Only 1-30 are valid days of the months in April, June, September, or November.	1172	CTGDJP604I Performing search.	1177
CTGDIU004E Invalid day of the month, 'day', was entered for the schedule time. Only 1-31 are valid days of the month.	1172	CTGDJP605E Missing attribute for root MBO: mboName.	1177
CTGDIU005E Invalid month, 'month', was entered for the schedule time. Only 0-11 are valid months.	1173	CTGDKO001E Unable to open 'file name' for modification. An exception occurred: <i>exception info</i>	1177
CTGDIU006E Invalid day of week, 'day of week', was entered for the schedule time. Only 1-7 are valid days of the week.	1173	CTGDKO002E Error closing 'file name'. An exception occurred: <i>exception info</i>	1178
CTGDIU007E Invalid hour, 'hour', was entered for the schedule time. Only 0-23 are valid hours.	1173	CTGDKO003E Usage: ACSIIFileUpdate file search replacement [LINE TEXT]	1178
CTGDIU008E Invalid minute, 'minute', was entered for the schedule time. Only 0-59 are valid minutes.	1173	CTGDKO004E Unable to find 'file name'.	1178
CTGDIU009I The 'schedule' parameter converted to the masked format: 'masked schedule'.	1174	CTGDKO005E Error reading 'file name'. An exception occurred: <i>exception info</i>	1178
CTGDIU010E The 'schedule' parameter must be set to use the Timer Connector.	1174	CTGDKO006E Error reading from input stream. An exception occurred: <i>exception info</i>	1178
CTGDIU011E Bad syntax for specified for the schedule. Valid syntax: <month> <mday> <dayofweek> <hour> <minute>	1174	CTGDKO007E Error processing file 'file name'. An exception occurred: <i>exception info</i>	1179
CTGDIU012I Next run of Timer Connector will be at 'timestamp'.	1174	CTGDKO008E Unable to create script file 'file name'. An exception occurred: <i>exception info</i>	1179
CTGDIU013I Sleeping for <i>number of seconds</i> seconds. Will wake up at 'timestamp'.	1174	CTGDKO009E Error while executing an operating system command. An exception occurred: <i>exception info</i>	1179
CTGDIU014I Sleeping for <i>number of seconds</i> seconds.	1175	CTGDKO010W While executing an operating system command, a non-zero return code was returned. Return code= <i>return code</i> ; Message: <i>message</i>	1179
CTGDJP651I The connector will try to reprocess message: <i>msgID</i>	1175	CTGDKO011I <i>component</i> already has this fix applied and will not be updated.	1180
CTGDJP652I The connector will delete message: <i>msgID</i>	1175	CTGDKO012E Unable to process fix file 'file name'.	1180
CTGDJP653I An HTTP client connection failed with error: <i>exception</i>	1175	CTGDKO013E The specified install directory 'directory' does not exist.	1180
CTGDJP654I Error checking task failed with error: <i>exception</i>	1175	CTGDKO014E No .registry file was found in the install directory, the file was empty, or it could not be read.	1180
CTGDJP655W Message: <i>msgID</i> from External system: <i>extSys</i> is with status 'HOLD'.	1176	CTGDKO015E Unable to open the .registry file for writing.	1180
CTGDJP656E The <i>variable name</i> parameter must be set to use the Connector.	1176	CTGDKO016E Unable to create file or directory 'file or directory name' when extracting from 'file name'.	1181
CTGDJP657E The <i>variable name</i> parameter must be set to a valid number.	1176	CTGDKO017E Unable to extract 'file name' from 'zip file'. An exception occurred: <i>exception info</i>	1181
CTGDJP658E The <i>variable name</i> parameter value must be within <i>Minimum Value</i> to <i>Maximum Value</i>	1176	CTGDKO018E File 'file name' does not exist in archive 'zip file'.	1181
		CTGDKO019E Unable to process .registry file in install directory 'directory'.	1181
		CTGDKO020I Unable to rollback; there are no fixes applied to this installation.	1181
		CTGDKO021I Rolling back 'fix name' using backup directory 'directory'.	1182

CTGDKO022E Unable to create backup directory ' <i>directory</i> ' for fix ' <i>fix name</i> '.	1182	CTGDKO054I Creating directory <i>directory</i>	1188
CTGDKO023I Applying fix ' <i>fix name</i> ' using backup directory ' <i>directory</i> '.	1182	CTGDKO055I Applying fix, but it may be necessary to rollback and run <code>ibmditk -tdishutdown</code> before fix is applied correctly.	1189
CTGDKO024E The current fix cannot be applied because ' <i>prereq</i> ' is a pre-requisite.	1182	CTGDKO056I No license to enroll.	1189
CTGDKO025I The fix specified is already installed.	1182	CTGDKO057I The full license is already enrolled.	1189
CTGDKO026I Backup directories will not be cleared, because the current fix is being applied to previously missing components.	1183	CTGDKO058I The trial license is already enrolled.	1189
CTGDKO027I Updating <i>component</i>	1183	CTGDKO059I Trial license successfully enrolled.	1189
CTGDKO028E Unrecognized component ' <i>component</i> ' in fix.	1183	CTGDKO060E The trial license failed to enroll due to an internal error.	1190
CTGDKO029E During application of a fix to the Embedded Web Platform component, a required JAR file was not found.	1183	CTGDKO061I Enrolling the full license requires that the trial license already be enrolled.	1190
CTGDKO030I Usage: <code>applyUpdates (-queryreg -rollback -update fix_file.zip [-clean [-silent]] -queryfix fix_file.zip -enroll lum_file.zip -?)</code>	1183	CTGDKO062I Full license successfully enrolled.	1190
CTGDKO031I Backup directories will not be cleared, because this fix is not a fixpack.	1184	CTGDKO063E Full license failed to enroll due to an internal error.	1190
CTGDKO032E The level of the current installation is ' <i>level</i> '. The level must be between ' <i>number</i> ' and ' <i>number</i> ' to apply this fix.	1184	CTGDKO064E Unrecognized license type: <i>license type</i>	1190
CTGDKO033I During installation of this fixpack, existing backup directories will be deleted. Are you sure you want to continue? [Y/N]:	1184	CTGDKO065E An internal license enrollment error has occurred. Message: <i>message</i>	1191
CTGDKO034I Argument <i>name value</i>	1184	CTGDKO066E An internal license enrollment error has occurred. An exception occurred: <i>exception info</i>	1191
CTGDKO035I The name of the LWI jar is: <i>jar name</i> ; Configuration ID is: <i>Configuration ID</i>	1185	CTGDKO067E Cannot find the full license file: <i>file name</i>	1191
CTGDKO036I The fix will not be installed.	1185	CTGDKO068E The license nodelock file ' <i>file name</i> ' does not contain valid license data.	1191
CTGDKO037I Final backup directory is: <i>directory</i>	1185	CTGDKO069E Fix pack installation has been rolled back as an error has occurred while installing the fix pack.	1191
CTGDKO038I Reading manifest file...	1185	CTGDKO070E Unable to delete file or directory ' <i>file or directory name</i> '.	1192
CTGDKO039I Reading .registry file...	1185	CTGDIR201E Either the ' <i>url</i> ' or ' <i>puturl</i> ' parameter must be set to use the URL Connector.	1192
CTGDKO040I LWI JAR name: <i>jar_name</i>	1186	CTGDIZ801E SOAPHeaderOutputAttributes class constructor failed.	1192
CTGDKO041I LWI Service name: <i>service_name</i>	1186	CTGDIZ802E Could not create Document Builder. Exception occurred: <i>exception</i>	1192
CTGDKO042I Call <code>amcmigrate: boolean</code>	1186	CTGDIZ803E The <code>java.lang.String</code> passed is null.	1192
CTGDKO043I Unable to populate registry.	1186	CTGDIZ804E Exception occurred while transforming DOM to String: <i>exception</i>	1193
CTGDKO044I Found applied fix: <i>fix_name</i>	1186	CTGDIZ805E The <code>org.w3c.dom.Node</code> passed is null.	1193
CTGDKO045I Updating .registry file...	1187	CTGDIZ806I Registered class ' <i>class name</i> ' for ' <i>queue name</i> '.	1193
CTGDKO046I The file <i>file name</i> in the archive <i>zip file</i> is empty.	1187	CTGDIZ807E Invalid style ' <i>style name</i> '. The supported styles are <code>Style.RPC</code> and <code>Style.DOCUMENT</code>	1193
CTGDKO047I Fix file is empty, unable to continue.	1187	CTGDIZ808I The operation has <i>number of parameters</i> parameters.	1193
CTGDKO048I Unable to read fix file ' <i>file name</i> '.	1187		
CTGDKO049I File not found: <i>file name</i>	1187		
CTGDKO050I Unknown operating system: <i>operating system</i>	1188		
CTGDKO051I Backing up <i>source file</i> to <i>target file</i>	1188		
CTGDKO052I Looking at <i>file name</i>	1188		
CTGDKO053I Writing <i>file name</i>	1188		

CTGDIZ809E Number of parameters does not match WSDL. Expected <i>number of parameters</i> parameters, but received <i>number of parameters</i> parameters.	1194	CTGDIZ301I SOAP Body: ' <i>SOAP body</i> '. . .	1199
CTGDIZ810I Number of parameters to retrieve: <i>number of parameters</i>	1194	CTGDIZ302E Invalid value for ' <i>returnXMLType</i> ': <i>parameter value</i>	1199
CTGDIZ811I Starting to serialize the SOAP message Body.	1194	CTGDIZ303E Invalid value for ' <i>inputXMLType</i> ': <i>parameter value</i>	1199
CTGDIZ812I Must specify return type.	1194	CTGDIZ304E The required parameter ' <i>headerAndBodyTagsPresent</i> ' is missing.	1199
CTGDIZ813I Completed serializing the SOAP message Body.	1194	CTGDIZ305E Entry Attribute ' <i>attribute name</i> ' is missing.	1200
CTGDIZ814I About to register class ' <i>class name</i> ' for XML QName.	1195	CTGDIZ306I Unwrapped SOAP Body Object: <i>object</i>	1200
CTGDIZ815I Registering class for XML QName ' <i>XML qualified name</i> '...	1195	CTGDIZ307I Unwrapped SOAP Header Object: <i>object</i>	1200
CTGDIZ816I Completed registering class for XML QName.	1195	CTGDIZ308I SOAP Header: <i>SOAP Header</i>	1200
CTGDIZ817E Cannot process SOAP response message: HTTP Content-type header is missing.	1195	CTGDIZ309E Could not parse unwrapped SOAP Body.	1200
CTGDIZ818E Unsupported content type <i>content type</i>	1195	CTGDIZ310E The SOAP Header element must be namespace qualified.	1201
CTGDIZ819E The org.w3c.dom.Node passed is null.	1196	CTGDIZ311I The namespace URI of the DOM Element: <i>namespaceURI</i>	1201
CTGDIZ820E Parameters must not be empty.	1196	CTGDIZ312I The name of the DOM Element: <i>elementName</i>	1201
CTGDIZ821E SOAP operation ' <i>operation name</i> ' not found in WSDL ' <i>WSDL URL</i> '.	1196	CTGDIZ313I The value of the DOM Element: <i>elementValue</i>	1201
CTGDIZ822E WSDL filename must not be empty!	1196	CTGDIZ314I SOAP Message: <i>SOAP message</i>	1201
CTGDIZ823E Could not close file stream.	1196	CTGDIZ315E The WrapSoap Function Component received an invalid object: <i>object</i>	1202
CTGDIZ824E The object has not been created properly.	1197	CTGDIZ316E The WrapSoap Function Component was passed an object of incorrect type. Exception occurred: <i>exception</i>	1202
CTGDIZ825E Parameter ' <i>parameter name</i> ' of operation ' <i>operation name</i> ' is of an unsupported type: ' <i>parameter type</i> '.	1197	CTGDIZ101I Exiting initialization early because Connector already initialized with a java.net.Socket object.	1202
CTGDIZ826E Great-Grandparent config is not an instance of AssemblyLineConfig: <i>class name</i>	1197	CTGDIZ102I Using the provided java.net.Socket object for client session.	1202
CTGDIZ827I The web service operation is <i>name of operation</i>	1197	CTGDIZ103E The ' <i>inputType</i> ' parameter is set to an invalid value ' <i>parameter value</i> '.	1202
CTGDIZ828E Error response received while invoking SOAP web service. The server returned: <i>HTTP response code</i>	1197	CTGDIZ104I The parameter ' <i>inputType</i> ' is set to ' <i>parameter value</i> '.	1203
CTGDJL001W The ' <i>PageSize</i> ' parameter set to an invalid value ' <i>parameter value</i> '. The default value ' <i>parameter value</i> ' will be used instead.	1198	CTGDIZ105E The ' <i>returnXMLType</i> ' parameter is set to an invalid value ' <i>parameter value</i> '.	1203
CTGDJL002W The ' <i>PageSize</i> ' parameter was missing. The default value ' <i>parameter value</i> ' will be used instead.	1198	CTGDIZ106I The parameter ' <i>returnXMLType</i> ' is set to ' <i>parameter value</i> '.	1203
CTGDJL003W The ' <i>PageSize</i> ' parameter is set to ' <i>parameter value</i> ' which is out of range. Valid range is between 1-' <i>number</i> '. The default value ' <i>parameter value</i> ' will be used instead.	1198	CTGDIZ107E Required Connector parameter ' <i>useSSL</i> ' is not set.	1203
CTGDJL004I Modifying global group entry. The supplied member list is empty so all group members will be removed.	1198	CTGDIZ108E Required Connector parameter ' <i>tcpPort</i> ' is not set.	1203
CTGDJL005I Modifying local group entry. The supplied member list is empty so all group members will be removed.	1199	CTGDIZ109I The parameter ' <i>useSSL</i> ' is set to ' <i>parameter value</i> '.	1204
		CTGDIZ110I The parameter ' <i>tcpPort</i> ' is set to ' <i>parameter value</i> '.	1204
		CTGDIZ111I The parameter ' <i>requireClientAuth</i> ' is set to ' <i>parameter value</i> '.	1204
		CTGDIZ113E Called the getNextClient method and Connector is not configured as a server session. Use the getNextEntry method to retrieve the next client request.	1204

CTGDIZ114I Connector terminated by external request.	1204	CTGDIZ141E Unexpected end of data while reading.	1210
CTGDIZ115I Connector terminating by external request.	1205	CTGDIZ142E Bad Request.	1210
CTGDIZ116I Terminate server request received.	1205	CTGDIZ143E The authentication method is not recognized.	1210
CTGDIZ117I Creating dummy connection using IP Address ' <i>IP Address</i> ' and port ' <i>port number</i> '.	1205	CTGDIZ144W The parameter ' <i>requireClientAuth</i> ' is missing and is set to its default value: ' <i>parameter value</i> '.	1211
CTGDIZ118I Connector is already terminating. Not sending termination request.	1205	CTGDJZ101I XML SAX Parser thread running.	1211
CTGDIZ119I Sending termination request to Connector.	1205	CTGDJZ102E XML SAX Parser only supports input.	1211
CTGDIZ120E Unable to terminate the Connector. No server Connector available or this Connector is no longer accepting connections.	1206	CTGDJZ103E There is no input stream provided to XML SAX Parser.	1211
CTGDIZ121E Called the getNextEntry and Connector is not configured as server session. Use the getNextClient method to retrieve the next client request.	1206	CTGDJZ104E The XML SAX Parser parameter Read Timeout value has to be a positive number.	1211
CTGDIZ122I Processing a request for the hosted WSDL.	1206	CTGDJZ105E The XML SAX Parser parameter Read Timeout value has to be number.	1212
CTGDIZ123I Processing a SOAP request.	1206	CTGDJZ106E Unable to read the Entry. Exception <i>exception class</i> occurred: <i>exception</i>	1212
CTGDIZ124I Processed SOAP request: ' <i>SOAP request</i> '.	1206	CTGDJZ107E Exceeded the stipulated wait period.	1212
CTGDIZ125W The '\$operation' Attribute of the op-entry has not been set because there is no context or the context is not an AssemblyLine object.	1207	CTGDJZ108E The Entry from the queue is a message.class = <i>class name</i> , message = <i>message</i>	1212
CTGDIZ126W The operation name cannot be extracted from the SOAP request message.	1207	CTGDJZ109E The method WriteEntry is not supported by the XML SAX Parser.	1212
CTGDIZ127I Connector response HTTP status code set to ' <i>status code</i> '.	1207	CTGDJZ110I XML SAX Parser terminated.	1213
CTGDIZ128I Connector response content type set to ' <i>content typet</i> '.	1207	CTGDJZ111I Inside the isGroupTag method: tag= <i>tag</i> , groupTag= <i>group tag</i>	1213
CTGDIZ129I Connector response content length set to ' <i>content length</i> '.	1208	CTGDJZ112I Inside the characters method: <i>string</i>	1213
CTGDIZ130I Connector response set to ' <i>response value</i> '.	1208	CTGDJZ114I The method endDocument is invoked.	1213
CTGDIZ131E Child of the Body element has not been found.	1208	CTGDJZ115E XMLSAX Parser encountered an InterruptedException in the endDocument method while trying to receive notification of the end of the document: <i>exception</i>	1213
CTGDIZ132I Starting output of HTTP request headers...	1208	CTGDJZ116I Inside the endElement method: <i>queue name</i>	1214
CTGDIZ133I <i>content length</i> set to ' <i>content length value</i> '.	1208	CTGDJZ117I Inside the endPrefixMapping method: <i>prefix</i>	1214
CTGDIZ134I <i>content type</i> set to ' <i>content type value</i> '.	1209	CTGDJZ118I Inside the ignorableWhitespace method: length= <i>length</i>	1214
CTGDIZ135I <i>content location</i> set to ' <i>content location value</i> '.	1209	CTGDJZ119I Inside the processingInstruction method.	1214
CTGDIZ136I <i>soap action</i> set to ' <i>soap action value</i> '.	1209	CTGDJZ120I Inside the setDocumentLocator method.	1214
CTGDIZ137I <i>host name</i> set to ' <i>host name value</i> '.	1209	CTGDJZ121I Inside the skippedEntity method.	1215
CTGDIZ138I End of output of HTTP request headers.	1209	CTGDJZ122I Inside the startDocument method.	1215
CTGDIZ139I HTTP method set to ' <i>HTTP Request</i> '.	1210	CTGDJZ123I Inside the startElement method: local name= <i>local name</i> , queue name= <i>queue name</i>	1215
CTGDIZ140I Requested HTTP resource set to ' <i>file name</i> '.	1210	CTGDJZ124E The method startElement encountered an InterruptedException: <i>exception</i>	1215
		CTGDJZ125I Inside the startPrefixMapping method: prefix= <i>prefix</i> , uri= <i>uri</i>	1215

CTGDJZ126I Inside the fatalError method: <i>exception</i>	1216	CTGDIE008E Unable to parse entry because the entry is not a valid change log entry. The 'changes' and 'newrdn' attributes are missing. The entry operation was set to ' <i>operation type</i> '.	1221
CTGDJZ127I Inside the error method.	1216	CTGDIE009E Unable to parse the change log 'changes' attribute. See the exception message for more information.	1222
CTGDJZ128I SAX Parse Warning:line: <i>line</i> number, ID: <i>ID</i>	1216	CTGDIE010E Restart info does not contain the attribute 'changeNumber'.	1222
CTGDJZ201I Parser will request namespace aware Parser.	1216	CTGDIE011I Reading entry in change log with change number of ' <i>change number</i> ' and the 'ldapSearchBase' set to ' <i>parameter</i> <i>value</i> '.	1222
CTGDJZ202I Parser will request validating Parser.	1216	CTGDIE012I Found entry in change log with change number of ' <i>change number</i> ' and the 'ldapSearchBase' set to ' <i>parameter</i> <i>value</i> '.	1222
CTGDJZ203I Parser will not indent output.	1217	CTGDIE013W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used.	1223
CTGDJZ204E No output XSL file specified.	1217	CTGDKB001I Parameter ' <i>parameter name</i> ': <i>parameter value</i>	1223
CTGDJZ205E Trying to write XML with no output stream.	1217	CTGDKB002E Required parameter missing: ' <i>parameter name</i> '.	1223
CTGDJZ206I Initialize Output Document.	1217	CTGDKB003E Parameter ' <i>parameter name</i> ' is too long: ' <i>parameter value</i> '. The maximum length of the parameter is <i>length</i>	1223
CTGDJZ207E Trying to read XML with no input stream.	1217	CTGDKB004I ATB_OK code is: <i>integer</i>	1223
CTGDJZ208I Initialize Input Document.	1217	CTGDKB005I APPC conversation successfully allocated.	1224
CTGDJZ209E No input XSL file specified.	1218	CTGDKB006E Could not allocate APPC conversation; return code: <i>return code</i>	1224
CTGDJZ210E The input XSL document has no root.	1218	CTGDKB007E The perform method of the Function Component failed because the method was not passed an Entry object. Non-Entry objects are not supported.	1224
CTGDJZ211E The XSL document has no children: <i>tag name</i>	1218	CTGDKB008E Unable to retrieve the command output of the TSO command. The conversion failed and the C layer execute returned NULL.	1224
CTGDJZ212I The XSL document has <i>number of</i> <i>children</i> children elements.	1218	CTGDKB009E Invalid data returned from C layer: <i>output</i>	1224
CTGDJZ213E Cannot parse the input XSL.	1218	CTGDKB010I No output returned by the TSO command.	1225
CTGDJZ214E DOM node processing not supported.	1219	CTGDKB011I Command to execute: <i>command</i>	1225
CTGDJZ215E Expected child item at index ' <i>index number</i> '.	1219	CTGDKB012E Could not execute TSO command. The command returned return code: <i>return code</i>	1225
CTGDJZ216I The XML Child node has no children so its being skipped.	1219	CTGDKB013I TSO command output: <i>command</i> <i>output</i>	1225
CTGDJZ217E The XSL does not conform to the defined format.	1219	CTGDKB014I Conversation deallocated successfully.	1225
CTGDJZ218E XSL does not conform to the defined format.	1219	CTGDKB015W Error on deallocating the conversation during termination: <i>error</i> <i>code</i>	1226
CTGDJZ220E Incorrect node type.	1219	CTGDKB016E Error message: <i>error message</i>	1226
CTGDJZ221I SAX Parse Warning: line: <i>line</i> number, ID: <i>ID</i> , message: <i>message</i>	1220	CTGDKB017I Parameter ' <i>parameter name</i> ' was transformed from ' <i>parameter value</i> ' to ' <i>parameter value</i> '.	1226
CTGDIE001I Connector could not set the starting change number to ' <i>change</i> <i>number</i> '. The 'nsChangenummer' parameter will be ignored.	1220		
CTGDIE002I The starting change number is ' <i>change number</i> ' and the 'iteratorStateKey' parameter is set to ' <i>parameter value</i> '.	1220		
CTGDIE003I Entry not found in change log with change number of ' <i>change number</i> ' and the 'ldapSearchBase' set to ' <i>parameter</i> <i>value</i> '.	1220		
CTGDIE004I Skipping entry with change number of ' <i>change number</i> ' and will try next entry.	1221		
CTGDIE005I Timeout waiting for next changed entry.	1221		
CTGDIE006E Could not retrieve last change number.	1221		
CTGDIE007W Unable to store the change number value ' <i>change number</i> ' in the System Store. Exception encountered: <i>exception</i>	1221		

CTGDKB018I Parameter '*parameter value*'
transformed to upper case. 1226

Notices 1227

Index 1231

About this publication

This publication contains the information that you require to develop solutions by using components that are part of IBM® Security Directory Integrator.

IBM Security Directory Integrator components are designed for network administrators who are responsible for maintaining user directories and other resources. It is assumed that you have practical experience with installation and usage of both IBM Security Directory Integrator and IBM Security Directory Server.

The information is also intended for users who are responsible for the development, installation, and administration of solutions by using IBM Security Directory Integrator. The reader must be familiar with the concepts and the administration of the systems that the developed solution would connect to. Depending on the solution, these systems might include, but are not limited to, one or more of the following products, systems, and concepts:

- IBM Security Directory Server
- IBM Security Identity Manager
- IBM Java™ runtime environment (JRE) or Oracle Java runtime environment
- Microsoft Active Directory
- Windows and UNIX operating systems
- Security management
- Internet protocols, including HyperText Transfer Protocol (HTTP), HyperText Transfer Protocol Secure (HTTPS) and Transmission Control Protocol/Internet Protocol (TCP/IP)
- Lightweight Directory Access Protocol (LDAP) and directory services
- A supported user registry
- Authentication and authorization concepts
- SAP ABAP Application Server

Access to publications and terminology

Read the descriptions of the IBM Security Directory Integrator Version 7.2 library and the related publications that you can access online.

This section provides:

- A list of publications in the “IBM Security Directory Integrator library.”
- Links to “Online publications” on page cxviii.
- A link to the “IBM Terminology website” on page cxix.

IBM Security Directory Integrator library

The following documents are available in the IBM Security Directory Integrator library:

- *IBM Security Directory Integrator Version 7.2 Federated Directory Integrator Administration Guide*

Contains information about using the Federated Directory Server console to design, implement, and administer data integration solutions. Also contains

information about using the System for Cross-Domain Identity Management (SCIM) protocol and interface for identity management.

- *IBM Security Directory Integrator Version 7.2 Getting Started Guide*
Contains a brief tutorial and introduction to IBM Security Directory Integrator. Includes examples to create interaction and hands-on learning of IBM Security Directory Integrator.
- *IBM Security Directory Integrator Version 7.2 Users Guide*
Contains information about using IBM Security Directory Integrator. Contains instructions for designing solutions using the Security Directory Integrator designer tool (the Configuration Editor) or running the ready-made solutions from the command line. Also provides information about interfaces, concepts and AssemblyLine creation.
- *IBM Security Directory Integrator Version 7.2 Installation and Administrator Guide*
Includes complete information about installing, migrating from a previous version, configuring the logging functionality, and the security model underlying the Remote Server API of IBM Security Directory Integrator. Contains information on how to deploy and manage solutions.
- *IBM Security Directory Integrator Version 7.2 Reference Guide*
Contains detailed information about the individual components of IBM Security Directory Integrator: Connectors, Function Components, Parsers, Objects and so forth – the building blocks of the AssemblyLine.
- *IBM Security Directory Integrator Version 7.2 Problem Determination Guide*
Provides information about IBM Security Directory Integrator tools, resources, and techniques that can aid in the identification and resolution of problems.
- *IBM Security Directory Integrator Version 7.2 Message Guide*
Provides a list of all informational, warning and error messages associated with the IBM Security Directory Integrator.
- *IBM Security Directory Integrator Version 7.2 Password Synchronization Plug-ins Guide*
Includes complete information for installing and configuring each of the five IBM Password Synchronization Plug-ins: Windows Password Synchronizer, Sun Directory Server Password Synchronizer, IBM Security Directory Server Password Synchronizer, Domino® Password Synchronizer and Password Synchronizer for UNIX and Linux. Also provides configuration instructions for the LDAP Password Store and JMS Password Store.
- *IBM Security Directory Integrator Version 7.2 Release Notes*
Describes new features and late-breaking information about IBM Security Directory Integrator that did not get included in the documentation.

Online publications

IBM posts product publications when the product is released and when the publications are updated at the following locations:

IBM Security Directory Integrator Library

The product documentation site (http://pic.dhe.ibm.com/infocenter/tivihelp/v2r1/topic/com.ibm.IBMDI.doc_7.2/welcome.htm) displays the welcome page and navigation for this library.

IBM Security Systems Documentation Central

IBM Security Systems Documentation Central provides an alphabetical list of all IBM Security Systems product libraries and links to the online documentation for specific versions of each product.

IBM Publications Center

The IBM Publications Center site (<http://www-05.ibm.com/e-business/linkweb/publications/servlet/pbi.wss>) offers customized search functions to help you find all the IBM publications you need.

Related information

Information related to IBM Security Directory Integrator is available at the following locations:

- IBM Security Directory Integrator Version 7.2 uses the JNDI client from Oracle. For information about the JNDI client, see the *Java Naming and Directory Interface™ Specification* at <http://download.oracle.com/javase/7/docs/technotes/guides/jndi/index.html>.
- Information that might help to answer your questions related to IBM Security Directory Integrator can be found at https://www-947.ibm.com/support/entry/myportal/overview/software/security_systems/tivoli_directory_integrator.

IBM Terminology website

The IBM Terminology website consolidates terminology for product libraries in one location. You can access the Terminology website at <http://www.ibm.com/software/globalization/terminology>.

Accessibility

Accessibility features help users with a physical disability, such as restricted mobility or limited vision, to use software products successfully. With this product, you can use assistive technologies to hear and navigate the interface. You can also use the keyboard instead of the mouse to operate all features of the graphical user interface.

For additional information, see the Accessibility Appendix in *IBM Security Directory Integrator Version 7.2 Users Guide*.

Technical training

For technical training information, see the following IBM Education website at <http://www.ibm.com/software/tivoli/education>.

Support information

IBM Support provides assistance with code-related problems and routine, short duration installation or usage questions. You can directly access the IBM Software Support site at <http://www.ibm.com/software/support/probsub.html>.

IBM Security Directory Integrator Version 7.2 Problem Determination Guide provides details about:

- What information to collect before contacting IBM Support.
- The various methods for contacting IBM Support.
- How to use IBM Support Assistant.
- Instructions and problem-determination resources to isolate and fix the problem yourself.

Statement of Good Security Practices

IT system security involves protecting systems and information through prevention, detection and response to improper access from within and outside your enterprise. Improper access can result in information being altered, destroyed, misappropriated or misused or can result in damage to or misuse of your systems, including for use in attacks on others. No IT system or product should be considered completely secure and no single product, service or security measure can be completely effective in preventing improper use or access. IBM systems, products and services are designed to be part of a comprehensive security approach, which will necessarily involve additional operational procedures, and may require other systems, products or services to be most effective. IBM DOES NOT WARRANT THAT ANY SYSTEMS, PRODUCTS OR SERVICES ARE IMMUNE FROM, OR WILL MAKE YOUR ENTERPRISE IMMUNE FROM, THE MALICIOUS OR ILLEGAL CONDUCT OF ANY PARTY.

Error Message Reference

Overview

The message reference provides a list of all informational, warning, and error messages that are associated with the IBM Security Directory Integrator. Messages that are returned by third-party software or other IBM product software are not listed here.

Message format

A displayed or printed message can appear by itself or with other information, such as a time stamp. A message consists of a message identifier (ID) and message text. A message number is also associated with each message.

Message ID format

A message ID consists of 10 alphanumeric characters that uniquely identify the message. The message ID is composed of:

- a 5-character product identifier
- a 1-character component or subsystem identifier
- a 3-digit serial number
- a 1-character type code indicating the severity of the message

The product identifiers for IBM Security Directory Integrator are CTGDI, CTGDJ and CTGDK.

Some valid message IDs are:

```
CTGDIS568E
CTGDIV018W
CTGDIZ709I
CTGDJN004E
```

Component identifiers

Messages that are associated with IBM Security Directory Integrator contain the component or subsystem identifiers that are shown in the following tables:

Table 1. CTGDI Component Table

Component identifier	Component
A	EmfSdoToXml FC, Axis2 WS Server Connector, Axis2 WS Client FC, Server API RMI, Security
B	EmfXmlToSdo FC, TP Server, JAX-RS, AtomStorage, API Connection, REST Server, Webcommon
C	Config Editor
D	Server Notification Listener Connector
E	z/OS® Changelog Connector, zOS LDAP Changelog Connector
F	SendMail FC
G	System Queue
H	System Queue Connector/System Store Connector /CCMDBConnector/DPAConnector/Report

Table 1. CTGDI Component Table (continued)

Component identifier	Component
I	JMS Connector
J	JDBC Connector
K	SAP ABAP Application Server Component Suite/TAM Connector
L	JNDI Connector
M	DSMLv2 Parser DSML Parser
N	DSMLv2SOAP Connector
O	DSMLv2SOAP Server Connector
P	FTP Client Connector
Q	Memory Stream Connector/Memory Queue Connector/Memory Buffer FC
R	Script Connector Properties Connector/URL Connector/ITIM Agent Connector
S	Server
T	File Connector, File Management Connector
U	Timer Connector
V	Notes [®] Connector, Domino AdminP Connector
W	Web Admin (AMC)
X	Command Line Connector
Y	AssemblyLine (Iterator) Connector/AssemblyLine FC
Z	Axis Easy Web Service Server Connector/Web Service Receiver Connector/Axis Java To Soap FC/WrapSoap FC/InvokeSoap WS FC/Axis Soap to Java FC/Axis Easy Invoke Soap WS FC/Complex TypesGenerator FC/webservice.util/DeltaFC

Table 2. CTGDJ Component Table

Component identifier	Component
A	CBE FC
B	CommandLine Util - TDISrvCtl/Action Manager
C	Remote Command Line FC
E	Domino Change Detection Connector
F	Active Directory Change Detection Connector
G	RDBMS Change Detection Connector
H	SNMP Connector/SNMP Server Connector
I	TCP Connector/TCP Server Connector
J	JavaClass FC
K	JMX Connector, EIF Connector
L	Windows Users and Groups Connector
M	JMS Password Store Connector
N	Mailbox Connector/TADDM Connector/TADDM Change Detection Connector

Table 2. CTGDJ Component Table (continued)

Component identifier	Component
O	Sun Directory Change Detection Connector
P	Old HTTP Client Connector/HTTP Client Connector/Old HTTP Server Connector/HTTP Server Connector/HTTP Parser/Simple Tpaef IF Connector/Tpaef IF Connector/Tpaef IF Change Detection Connector
Q	LDAP Connector/LDAP Server Connector
R	IBM Directory Server Changelog Connector
T	Script Parser/Scripted FC
U	Simple Parser/Parser FC
V	SOAP Parser
W	CSV Parser
X	LDIF Parser
Y	Line Reader Parser/Fixed Parser
Z	Simple XML Parser/XML Parser/XML SAX Parser/XSL based XML Parser/Init IT Registry FC/IT Registry Ci and Relationship Connector/IdML FC suite/IdML Connector/Data Cleanser Service FC/IdML Parser/File Transfer FC

Table 3. CTGDK Component Table

Component identifier	Component
B	zOS TSO Command Line FC
C	Domino Users Connector
D	Server API Engine
E	miconfig/mmconfig
G	IDI Loader
H	Resource Hash
I	TIM DSMLv2 Connector
J	CastorJavaToXML FC/CastorXMLToJava FC
K	RAC Connector/GLA Connector/Log Connector
L	CBE Parser, SPML v2 Parser
M	IBM Security Directory Integrator Installer migration commands
N	Java Proxy, Password Stores and Password Plug-ins, JMS Drivers
O	Update Installer

Severity

The severity is indicated by the last character in the message ID.

I Informational

Provides information or feedback about normal events that occur.

```
CTGDIZ707I Deleting JAR file...
CTGDJC0036I Initializing Remote Command Line Function Component
parameters done.
CTGDJF007I Synchronization from End Of Data will be performed: the
Connector will only report changes that occur after it is started.
```

W Warning

Indicates that potentially undesirable conditions have occurred, but processing can continue; for example:

```
CTGDJT006W Unable to load script libraries. The Script Connector has no
associated MetamergeConfig object.
CTGDIC019W Your solution directory {0} does not contain solution files.
Do you want to create them?
CTGDIC066W Please establish a connection first.
```

E Error

Indicates that a problem has occurred that requires intervention or correction before processing can continue; for example:

```
CTGDIC078E Could not read WSDL file.
CTGDIG015E Default System Queue is not initialized.
CTGDJE008E No documents in the list of UnIDs, or the list is null.
```

Presentation of messages

The following list describes the different parts of the message explanations that are presented in this message reference documentation.

Explanation

Describes the meaning of the message, including why the message was issued. Might describe what system actions were taken as a result of the message.

Operator Response

Provides information on how to correct the problem.

Administrator Response

Provides information on how to correct the problem if System Administrator authority is required.

Programmer Response

Describes the corrective actions the System Programmer should take.

Messages

The IBM Security Directory Integrator messages are listed in alphabetical order according to their component identifiers.

CTGDJB501I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB502E Unable to create Action Manager Thread for [AM_ID]: Action Manager Rule ID [Rule]: rule name [Solution View]: Solution View name.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for AssemblyLine Not Executed For Specified Time type of trigger).

Action

Check the exception trace following this message in the logs. Ensure that the time units were correctly specified.

CTGDJB503E Unable to create Action Manager Thread for [Action Manager Rule Id]: Action Manager Rule ID [Rule]: rule name [Solution View]: Solution View name. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution view.

Action

Verify that the remote Security Directory Integrator server associated with this Solution view is running, and remote Server API engine is enabled on that server. If SSL is not enabled at the remote Security Directory Integrator Server end, then ensure that the IP address of the machine running Action Manager is mentioned in the `api.remote.nonssl.hosts` property in the `global.properties` or `solution.properties` file of the remote Security Directory Integrator Server. If SSL is enabled at the remote Security Directory Integrator Server end, then ensure that the Action Manager key store and trust store are set up correctly. Refer to the Security Directory Integrator Installation and Administrator Guide for steps on how to configure Security Directory Integrator for SSL.

CTGDJB504E Unable to create Action Manager Thread for [Action Manager Rule Id]: Action Manager Rule ID [Rule]: rule name [Solution View]: Solution View name. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a `DIEventListener`.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB505E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register an AssemblyLine terminate listener.

Explanation

The Action Manager was unable to create a thread because it could not register an AssemblyLine terminate listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB506I Created Action Manager thread for [Config]: *Config instance* [AssemblyLine]: *AssemblyLine*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB507I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB508I AssemblyLine *AssemblyLine name* has not run since *time* seconds. Starting execution of associated actions.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB509I Rule *rule name* has already been triggered earlier. Awaiting the next run of AssemblyLine *AssemblyLine name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB510I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB511I Action Manager initialization completed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB512I Started Health AssemblyLine Manager.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB513I Action Manager initialization started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB514E Property *property name* is not set.

Explanation

The Action Manager was unable to initialize because the required property `action.manager.prop.file` was not set. This property is required for finding the location of the Action Manager configuration file `am_config.properties`.

Action

Ensure that in the `startAM.bat(sh)` file the `action.manager.prop.file` property is being set to point to the location of the `am_config.properties` file.

CTGDJB515E Unable to load the `am_config.properties` file. Check the value of `action.manager.prop.file` property.

Current value is: *file path*

Explanation

The Action Manager was unable to initialize because the property `action.manager.prop.file` in the `startAM.bat(sh)` file is pointing to an invalid location of `am_config.properties`.

Action

Ensure that in the `startAM.bat(sh)` file the `action.manager.prop.file` property is being set to point to the location of the `am_config.properties` file. See the associated exception trace.

CTGDJB516E Unable to load the `amc.properties` file. Current value of `com.ibm.di.amc.properties.file.location` property is: *file path*

Explanation

The Action Manager was unable to initialize because the property `com.ibm.di.amc.properties.file.location` in the `am_config.properties` file is pointing to an invalid location of `amc.properties`. The Action Manager needs to load the `amc.properties` to obtain SSL (and other) details of the Administration and Monitoring Console.

Action

Ensure that in the `am_config.properties` file the `com.ibm.di.amc.properties.file` property is being set to point to the location of the `amc.properties` file. See the associated exception trace. Also ensure that forward slashes are used in specifying the path.

CTGDJB517I SSL Trust Store: *trust store path*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB518I SSL Key Store: *key store path*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB519I Initializing connection to database.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB520E Unable to initialize database.

Explanation

The Action Manager was unable to initialize connection to database. This may occur if there is an error in the JDBC URLs specified in the `am_config.properties`. The Action Manager connects to the Administration and Monitoring Console's database using Derby in network mode. If the specified Derby database does not exist, or is booted in embedded mode, then Action Manager cannot connect to the database. To create the database, the Administration and Monitoring Console must have been started at least once. Action Manager will start the database in network mode, in case its not running in network mode already.

Action

Ensure that the JDBC settings in the `am_config.properties` file are correct, and pointing to the Administration and Monitoring Console's Derby database. Ensure that the Administration and Monitoring Console is not already connected to the database in Embedded mode. The recommended procedure is as follows: 1) Ensure that the Administration and Monitoring Console's database exists. If not, start the Administration and Monitoring Console. On starting the Administration and Monitoring Console for the first time, the Derby database is automatically created. 2) Shutdown the Administration and Monitoring Console and reconfigure it to connect to the database in network mode (if not already configured for network mode). 3) Start Action Manager. Action Manager will start the database in network mode. 4) Start the Administration and Monitoring Console, which will also connect to the same database over network mode.

CTGDJB521W Action Manager was unable to read property com.ibm.di.amc.am.healthAL.interval.time. Health AssemblyLine triggering interval set to a default value of 30 minutes.

Explanation

The Action Manager was unable to read the com.ibm.di.amc.am.healthAL.interval.time property from the am_config.properties file. This property is used to determine the triggering interval for Health AssemblyLines of Solution Views. If this property is not defined, then Action Manager will attempt to trigger all configured Health AssemblyLines every 30 minutes (unless the Health AssemblyLine is not running already, in which case it will not trigger a new run of the Health AssemblyLine).

Action

Ensure that there is a valid time value (in seconds) specified for the com.ibm.di.amc.am.healthAL.interval.time property in the am_config.properties file.

CTGDJB522I Creating Action Manager threads.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB523E Unable to obtain connection to database.

Explanation

The Action Manager was unable to obtain a connection to database. This may occur if there is an error in the JDBC URLs specified in the am_config.properties. The Action Manager connects to the Administration and Monitoring Console's database using Derby in network mode. If the specified Derby database does not exist, or is booted in embedded mode, then Action Manager cannot connect to the database. To create the database, the Administration and Monitoring Console must have been started at least once. Action Manager will start the database in network mode, in case its not running in network mode already. This could also happen, if the database shutdown (maybe because the Administration and Monitoring Console was shutdown). This will happen, only if the Administration and Monitoring Console had booted the database, and now the Administration and Monitoring Console has been shutdown. It is recommended that to avoid this situation, start Action Manager first, and then start the Administration and Monitoring Console.

Action

Ensure that the JDBC settings in the am_config.properties file are correct, and pointing to the Administration and Monitoring Console's Derby database. Ensure that the Administration and Monitoring Console is not already connected to the

database in Embedded mode. The recommended procedure is as follows: 1) Ensure that the Administration and Monitoring Console's database exists. If not, start the Administration and Monitoring Console. On starting the Administration and Monitoring Console for the first time, the Derby database is automatically created. 2) Shutdown the Administration and Monitoring Console and reconfigure it to connect to the database in network mode (if not already configured for network mode). 3) Start Action Manager. Action Manager will start the database in network mode. 4) Start the Administration and Monitoring Console, which will also connect to the same database over network mode.

CTGDJB524I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On termination of AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB525I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On receiving Event.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB526I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On specific property value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB527I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On query of AssemblyLine result.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB528I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On server API failure.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB529I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On elapsed time interval since last execution of AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB530E Exception while constructing Action Manager threads.

Explanation

The Action Manager was unable to create listener threads because some internal error occurred. See the logs, or accompanying exception trace for more information.

Action

See the associated exception trace for reasons of error. Try running Action Manager again.

CTGDJB531I Action Manager threads created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB532I Database modification listener started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB533I Checking for any Action Manager rule updates.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB534E Error occurred while running Database modification listener.

Explanation

The Action Manager's database listener thread, that checks if any Action Manager rule has been modified from the Administration and Monitoring Console, encountered a database exception while trying to read data from the database. This could have happened if the database has been shutdown, or some other internal error occurred.

Action

Verify that the database is running. Look at the exception trace in the log.

CTGDJB535E Error occurred while trying to delete data from the AM_UPDATE_DETAILS table.

Explanation

The Action Manager's database listener thread, that checks if any Action Manager rule has been modified from the Administration and Monitoring Console, encountered a database exception while trying to delete data from the AM_UPDATE_DETAILS table in the database. This could have happened if the database has been shutdown, or some other internal error occurred.

Action

Verify that the database is running. Look at the exception trace in the log.

CTGDJB536I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On termination of AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB537I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On receiving Event.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB538I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On specific property value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB539I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On query of AssemblyLine result.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB540I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On server API failure.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB541I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On elapsed time interval since last execution of AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB542E Error occurred while constructing Action Manager thread for rule: *rule name*

Explanation

The Action Manager's real time listener thread, that checks if any Action Manager rule has been modified from the Administration and Monitoring Console, encountered an exception while trying to create an Action Manager thread for the modified rule. See the associated log messages and exception trace for more information.

Action

Look into the log messages and exception trace for more information. Modify the particular rule again using the Administration and Monitoring Console.

CTGDJB543E Error occurred while trying to insert data into the AM_UPDATE_DETAILS table.

Explanation

Action Manager writes into the AM_UPDATE_DETAILS table, to indicate that a rule has been modified, so that the database modification listener thread can pick up this modification notification, and appropriately modify listener threads. An error occurred while trying to insert information in the AM_UPDATE_DETAILS table. This may have occurred if the database is down, or due to some other internal error.

Action

Verify that the database is running. Look at the exception trace in the log.

CTGDJB544E Error occurred while trying to delete all data from the AM_UPDATE_DETAILS table.

Explanation

On startup, the Action Manager clears all the data from the AM_UPDATE_DETAILS table, since it is anyways going to construct all threads again. Due to some database error, Action Manager was unable to clear the data from this table.

Action

Verify that the database is running. Look at the exception trace in the log.

CTGDJB545I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB546I Created Action Manager thread for [Config]: *Config instance*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB547I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB548I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB549I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB550E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for AssemblyLine Terminated type of trigger). This may occur, because the database is down, or some internal database related error occurred.

Action

Check the exception trace following this message in the logs. Ensure that the database is running in network mode. It is recommended to start Action Manager first, and the Administration and Monitoring Console later. Action Manager will start the database in network mode, to which the Administration and Monitoring Console can later connect.

CTGDJB551E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and remote Server API engine is enabled on that server.

CTGDJB552E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a DIEventListener for registering an AssemblyLine terminate listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB553E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register AssemblyLine terminate listener.

Explanation

The Action Manager was unable to create a thread because it could not register an AssemblyLine terminate listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB554I Created Action Manager thread for [Config]: *Config instance* [AssemblyLine]: *AssemblyLine*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB555I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB556I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB557I DBConnectionFactory instance created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB558I Derby network server already running.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB559I Unable to ping Derby network server. Attempting to start.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB560I Started Derby network server.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB561E Unable to start Derby network server. Database unavailable.

Explanation

The Action Manager was unable to start Derby network server. This may occur if there is an error in the JDBC URLs specified in the `am_config.properties`. The Action Manager connects to the Administration and Monitoring Console's database using Derby in network mode. If the specified Derby database does not exist, or is booted in embedded mode, then Action Manager cannot connect to the database or start the database in network mode. To create the database, the Administration and Monitoring Console must have been started at least once. Action Manager will start the database in network mode, in case its not running in network mode already.

Action

Ensure that the JDBC settings in the `am_config.properties` file are correct, and pointing to the Administration and Monitoring Console's Derby database. Ensure that the Administration and Monitoring Console is not already connected to the database in Embedded mode. The recommended procedure is as follows: 1) Ensure that the Administration and Monitoring Console's database exists. If not, start the Administration and Monitoring Console. On starting the Administration and Monitoring Console for the first time, the Derby database is automatically created. 2) Shutdown the Administration and Monitoring Console and reconfigure it to connect to the database in network mode (if not already configured for network mode). 3) Start Action Manager. Action Manager will start the database in network mode. 4) Start the Administration and Monitoring Console, which will also connect to the same database over network mode.

CTGDJB561W Error while closing database Statement.

Explanation

Action Manager encountered some database error which caused `statement.close()` API to fail.

Action

Ensure that the database is running in network mode, and see the exception trace for more details.

CTGDJB562W Error while closing database ResultSet.

Explanation

Action Manager encountered some database error which caused `resultSet.close()` API to fail.

Action

Ensure that the database is running in network mode, and see the exception trace for more details.

CTGDJB563W Error while closing database Connection.

Explanation

Action Manager encountered some database error which caused connection.close() API to fail.

Action

Ensure that the database is running in network mode, and see the exception trace for more details.

CTGDJB564I Rule *rule name* not triggered since event data did not match.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB565I Rule *rule name* not triggered since event source did not match.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB566I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB567E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for Event Received type of trigger). This may occur, because the database is down, or some internal database related error occurred.

Action

Check the exception trace following this message in the logs. Ensure that the database is running in network mode. It is recommended to start Action Manager first, and the Administration and Monitoring Console later. Action Manager will start the database in network mode, to which the Administration and Monitoring Console can later connect.

CTGDJB568E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and remote Server API engine is enabled on that server.

CTGDJB569E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a `DIEventListener` for registering an `AssemblyLine` terminate listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB570E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register specified Event listener.

Explanation

The Action Manager was unable to create a thread because it could not register an event listener as per the user specified parameters.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB571I Created Action Manager thread for [Config]:
Config instance [AssemblyLine]: AssemblyLine

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB572I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID [Rule]: rule name*
[Solution View]: *Solution View name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB573I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB574W Unable to get list of running AssemblyLines for Solution View: *Solution View. Ignoring Health AssemblyLine for this Solution view.*

Explanation

The Action Manager was unable to determine the list of running AssemblyLines for this Solution view. For this reason, it ignored any health AssemblyLine defined for this Solution view. This may happen if there is an error in the Config instance associated with this Solution view.

Action

Ensure the remote server API is on. Verify that the Config instance associated with this Solution view is running. Action Manager will ignore the Health AssemblyLine for this Solution view, until the next interval.

CTGDJB575W Unable to obtain Config Instance associated with the Solution View: *Solution View*. Ignoring Health AssemblyLine for this Solution view.

Explanation

The Action Manager was unable to obtain a handle to the Config instance associated with this Solution view. This may happen because the Config is not loaded on the server.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. Also, Verify that the Config instance associated with this Solution view is running. No action required, if the user does not expect the Config to be loaded currently. Action Manager will ignore the Health AssemblyLine for this Solution view, until the next interval.

CTGDJB576E Unable to obtain list of Health AssemblyLines for Solution Views.

Explanation

The Action Manager was unable to read the list of Health AssemblyLines from the CONFIG_VIEW_HEALTH_AL_DETAILS table in database. Some internal database error may have occurred.

Action

Ensure that the database is running in network mode, and the CONFIG_VIEW_HEALTH_AL_DETAILS table is not corrupted. Try again.

CTGDJB577I Updating Health AssemblyLine status in database for Solution view *Solution View ID*. [HealthAL Result]: *result*. [HealthAL Status]: *status_description*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB578E Error updating Health AssemblyLine status in database for Solution view *Solution View ID*. [HealthAL Result]: *result*. [HealthAL Status]: *status_description*.

Explanation

The Action Manager was unable to update the Health AssemblyLine status in CONFIG_VIEW_HEALTH_STATUS table in database. Some internal database error may have occurred.

Action

Ensure that the database is running in network mode, and the CONFIG_VIEW_HEALTH_STATUS table is not corrupted / locked. See accompanying exception trace.

CTGDJB579I Creating Health AssemblyLine Listener thread for [Solution View]: *Solution View ID.* **[Config]:** *Config instance.* **[AssemblyLine]:** *AssemblyLine name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB580W Unable to obtain session with remote Security Directory Integrator server for Health AssemblyLine: *AssemblyLine name.*

Explanation

The Action Manager was unable to obtain a session with the remote Security Directory Integrator server for the Solution view associated with this Health AssemblyLine. The remote Security Directory Integrator server may have shut down.

Action

Ensure that the remote Security Directory Integrator server is running, and the remote server API is on. Action Manager will ignore the Health AssemblyLine for this Solution view, until the next interval.

CTGDJB581E Unable to create base listener for Health AssemblyLine: *AssemblyLine name.*

Explanation

The Action Manager was unable to create a Health AssemblyLine terminate listener thread because it could not create a DIEventListener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB582E Unable to register stop AssemblyLine listener for Health AssemblyLine: *AssemblyLine name.*

Explanation

The Action Manager was unable to create a Health AssemblyLine terminate listener thread because it could not register an Health AssemblyLine stop listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB583E Unable to start Health

AssemblyLine: *AssemblyLine name*

Explanation

The Action Manager was unable to run the Health AssemblyLine because of some internal error. See exception trace.

Action

See the accompanying exception trace.

CTGDJB584E Result work entry is null in Health

AssemblyLine: *AssemblyLine name*. **No Health status update will be done in database.**

Explanation

The Health AssemblyLine returned a null work entry object.

Action

Check the Health AssemblyLine.

CTGDJB585I In Health AssemblyLine *AssemblyLine name* healthAL.result attribute value is: *attribute_value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB586I In Health AssemblyLine *AssemblyLine name* healthAL.status attribute value is: *attribute_value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB587I Terminating Health AssemblyLine thread for
[Solution View]: *Solution View ID* **[Config]:** *Config instance*
[AssemblyLine]: *AssemblyLine name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB588W Unable to remove event listener registered for
AssemblyLine terminate events for [Solution View]: *Solution*
View ID **[Config]:** *Config instance* **[AssemblyLine]:**
AssemblyLine name

Explanation

Due to an internal error, Action Manager was unable to remove event listener configured for listening to Health AssemblyLine termination events.

Action

Ensure that the remote Security Directory Integrator server is of the version 6.1.1 or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB588E Unable to obtain handle to AssemblyLine object
for Health AssemblyLine: *AssemblyLine name*

Explanation

The Action Manager was unable to obtain a handle to Health AssemblyLine. This may have occurred because the Health AssemblyLine terminated before the Stop Event listener was registered, or the AssemblyLine does not exist.

Action

Put a sleep() of about 5 to 10 seconds to slow down the execution of the Health AssemblyLine and try again. Ensure the health AssemblyLine exists in the specified Config.

CTGDJB589I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB590E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for Property Value listener type of trigger).

Action

Check the exception trace following this message in the logs. Ensure that the time units were correctly specified.

CTGDJB591E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and remote Server API engine is enabled on that server.

CTGDJB592E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to obtain Config Instance: *Config Instance*.

Explanation

The Action Manager was unable to create a thread because it could not obtain a handle to the Config instance on the remote server.

Action

Verify that the Config Instance associated with this Solution View is loaded.

CTGDJB593E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. [Config Instance]: *Config Instance*. Unable to obtain handle to Security Directory Integrator Properties object.

Explanation

The Action Manager was unable to create a thread because it could not obtain a handle to the Security Directory Integrator Properties object.

Action

Verify that the remote Security Directory Integrator Server is of version 6.1.1 or higher. Try reloading the Config and try again.

CTGDJB594I Created Action Manager thread for [Config]: *Config instance*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB595I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB596E Error in [Rule]: *rule name* [Solution View]: *Solution View name* The property values cannot be compared since one of the property is not a valid integer. [Key]: *property name* [Current Value]: *property value* [Compared to value]: *value*

Explanation

The Action Manager was unable to check triggering condition because the property value or the value to be compared to are not integers.

Action

Ensure that the specified property has an integer value, and that the value to be compared to is also a valid integer.

CTGDJB597E Error in [Rule]: *rule name* [Solution View]: *Solution View name* Unable to determine triggering condition.

Explanation

The Action Manager was unable to determine triggering condition because an error occurred. Check the exception trace for more details.

Action

See the accompanying exception for more details.

CTGDJB598I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB599I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB600E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for Query AssemblyLine result type of trigger).

Action

Check the exception trace following this message in the logs. Ensure that the time units were correctly specified.

CTGDJB601E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and remote Server API engine is enabled on that server.

CTGDJB602I The Config instance *Config instance* is not running. Will obtain handle to AssemblyLine later.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB603E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a DIEventListener for registering an AssemblyLine listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB604E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register AssemblyLine listener.

Explanation

The Action Manager was unable to create a thread because it could not create a DIEventListener for registering an AssemblyLine listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and the remote server API is on. See the accompanying exception trace.

CTGDJB605I Created Action Manager thread for [Config]: *Config instance* [AssemblyLine]: *AssemblyLine*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB606I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB607I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB608W Unable to obtain handle to AssemblyLine object for AssemblyLine: *AssemblyLine name*

Explanation

This may have happened because the AssemblyLine does not exist, or some internal error occurred.

Action

Check the AssemblyLine and the accompanying exception trace.

CTGDJB609E Result work entry is null in AssemblyLine: *AssemblyLine name*. Rule will not be triggered.

Explanation

The AssemblyLine returned a null work entry object.

Action

Check the AssemblyLine.

CTGDJB610E No value found for attribute *attribute name*. in result work entry. Rule will not be triggered.

Explanation

The AssemblyLine work entry does not contain a value for the specified attribute.

Action

Check the AssemblyLine.

CTGDJB611I Attribute *attribute name* value is *attribute value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB612E Error in [Rule]: *rule name* [Solution View]: *Solution View name* The attribute values cannot be compared since one of the values is not a valid integer. [Attribute]: *Attribute name* [Current Value]: *Attribute value* [Compared to value]: *value*

Explanation

The Action Manager was unable to check triggering condition because the attribute value or the value to be compared to are not integers.

Action

Ensure that the specified attribute has an integer value, and that the value to be compared to is also a valid integer. Check the AssemblyLine and the Action Manager rule definition.

CTGDJB613W Unable to obtain handle to AssemblyLine object for AssemblyLine: *AssemblyLine name* Cannot obtain result work entry.

Explanation

This may have happened because the AssemblyLine does not exist, or some internal error occurred.

Action

Check the AssemblyLine and the accompanying exception trace.

CTGDJB614E An error occurred while executing an action. [Solution View]: *Solution View name* [Rule]: *Rule name* [Action Order]: *sequence order* [Action Type]: *action type*

Explanation

Action Manager encountered an error when executing actions. See the accompanying messages or exception trace to get more details.

Action

See the error messages or exception trace.

CTGDJB615I Action successfully executed. [Solution View]:
Solution View name [Rule]: Rule Name [Action Order]:
sequence_order [Action Type]: action_type

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB616E An error occurred while executing an action.
[Solution View]: *Solution View name [Rule]: Rule Name*

Explanation

Action Manager encountered an error when executing actions. See the accompanying messages or exception trace to get more details.

Action

See the error messages or exception trace.

CTGDJB617E Unable to insert/commit into AM_RUN_HISTORY table.

Explanation

Action Manager encountered an error when storing the action execution details into AM_RUN_HISTORY table.

Action

See the error messages or exception trace.

CTGDJB618E Unable to obtain rule information from AM_ACTION_DETAILS_RULE table.

Explanation

Action Manager encountered an error when reading the action details from AM_ACTION_DETAILS_RULE table in database.

Action

See the error messages or exception trace.

CTGDJB619E Unable to obtain rule information from AM_RULES_MASTER table.

Explanation

Action Manager encountered an error when reading the action details from AM_RULES_MASTER table in database.

Action

See the error messages or exception trace.

CTGDJB620I Triggering rule *rule name* of Solution view *Solution View*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB621E Unable to obtain log information from AM_ACTION_DETAILS_WRITE_LOG table.

Explanation

Action Manager encountered an error when reading the log action details from AM_ACTION_DETAILS_WRITE_LOG table in database.

Action

See the error messages or exception trace.

CTGDJB622I [Message]: *log message* [Description]: *log description*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB623E Unable to write log information to AM_LOGS table.

Explanation

Action Manager encountered an error when writing the log action to AM_LOGS table in database.

Action

See the error messages or exception trace.

CTGDJB624E Unable to read action information from AM_ACTION_DETAILS_COPY_PROPERTY table.

Explanation

Action Manager encountered an error when reading action information from AM_ACTION_DETAILS_COPY_PROPERTY table in database.

Action

See the error messages or exception trace.

CTGDJB625E Unable to obtain Config instance for Config: Config instance.

Explanation

Action Manager could not obtain Config instance for Copy Property Action. Check if the specified Config instance is loaded on the Security Directory Integrator Server.

Action

See the error messages or exception trace.

CTGDJB626E Unable to copy properties.

Explanation

Action Manager could not execute the copy property action. See accompanying exception.

Action

See the error messages or exception trace. Verify that the destination property store is not read-only.

CTGDJB627E Unable to obtain property information.

Explanation

Action Manager encountered an error when reading action information from AM_ACTION_DETAILS_PROPERTY_MODIFY table in database.

Action

See the error messages or exception trace.

CTGDJB628E Unable to obtain Config instance for Config: Config instance.

Explanation

Action Manager could not obtain Config instance for Modify Property Action. Check if the specified Config instance is loaded on the Security Directory Integrator Server.

Action

See the error messages or exception trace.

**CTGDJB629E Unable to modify property to new value: *value*.
Explanation**

Action Manager could not execute the modify property action. See accompanying exception.

Action

See the error messages or exception trace. Verify that the destination property store is not read-only.

**CTGDJB630E Unable to obtain Event information.
Explanation**

Action Manager encountered an error when reading action information from AM_ACTION_DETAILS_NOTIFY_EVENT table in database.

Action

See the error messages or exception trace.

**CTGDJB631E Unable to send Event notification.
Explanation**

Action Manager encountered an error when trying to send an Event notification.

Action

See the error messages or exception trace.

**CTGDJB632E Unable to enable rule.
Explanation**

Action Manager encountered an error when trying to read rule information from database.

Action

See the error messages or exception trace.

**CTGDJB633E Unable to disable rule.
Explanation**

Action Manager encountered an error when trying to read rule information from database.

Action

See the error messages or exception trace.

CTGDJB634E Unable to enable rule *rule name*

Explanation

Action Manager encountered an error when trying to update rule information in AM_RULES_MASTER table in database.

Action

See the error messages or exception trace.

CTGDJB635E Unable to disable rule *rule name*

Explanation

Action Manager encountered an error when trying to update rule information in AM_RULES_MASTER table in database.

Action

See the error messages or exception trace.

CTGDJB636E Unable to enable rule.

Explanation

Action Manager encountered an error when trying to update rule information in database.

Action

See the error messages or exception trace.

CTGDJB637E Unable to disable rule.

Explanation

Action Manager encountered an error when trying to update rule information in database.

Action

See the error messages or exception trace.

CTGDJB638E Unable to obtain AssemblyLine information.

Explanation

Action Manager encountered an error when trying to read AssemblyLine information from AM_ACTION_DETAILS_AL table in database.

Action

See the error messages or exception trace.

CTGDJB639E Unable to obtain session for stopping AssemblyLine *AssemblyLine name* with remote Security Directory Integrator server.

Explanation

Action Manager encountered an error when trying to obtain session for remote Security Directory Integrator server associated with this AssemblyLine.

Action

The remote Security Directory Integrator server may be down, or remote server API engine may not be running.

CTGDJB640E Config *Config instance* is not loaded on the remote server.

Explanation

Action Manager could not obtain Config instance while attempting to stop the specified AssemblyLine (Stop AssemblyLine Action). Since, Config is not loaded, the AssemblyLine cannot be running. Action Manager has ignored this action.

Action

See explanation. Check the action information.

CTGDJB641E Unable to stop AssemblyLine: *AssemblyLine name*.

Explanation

Action Manager could not stop the specified AssemblyLine. See the associated exception for details.

Action

See associated exception trace.

CTGDJB642E AssemblyLine: *AssemblyLine name* is not running on the Config instance: *Config instance*

Explanation

Action Manager could not stop the specified AssemblyLine since it was already not running on the specified Config instance.

Action

See explanation.

CTGDJB643E Unable to obtain AssemblyLine information.

Explanation

Action Manager encountered an error when trying to read AssemblyLine information from AM_ACTION_DETAILS_AL table in database.

Action

See the error messages or exception trace.

CTGDJB644E Unable to obtain session for starting AssemblyLine *AssemblyLine name* with remote Security Directory Integrator server.

Explanation

Action Manager encountered an error when trying to obtain session for remote Security Directory Integrator server associated with this AssemblyLine.

Action

The remote Security Directory Integrator server may be down, or remote server API engine may not be running.

CTGDJB645I Config *Config instance* is not loaded on the remote server. Attempting to load it now.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB646E Unable to start Config instance *Config instance*

Explanation

Action Manager encountered an error when trying to load Config on the remote machine.

Action

Ensure that the complete path of the Config was specified (forward slashes), and it exists on the remote machine.

CTGDJB647E Unable to start AssemblyLine *AssemblyLine name*

Explanation

Action Manager encountered an error when trying to start AssemblyLine on the remote machine.

Action

Ensure that the AssemblyLine exists in the specified Config.

CTGDJB648I Security Directory Integrator Session Generator Created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB649I Trying to establish connection to: *server* : *port*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB650I Custom Authentication with username: *username*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB651E Unable to obtain session with remote Security Directory Integrator Server: *server* : *port*.

Explanation

Action Manager was unable to obtain session with remote Security Directory Integrator server. The server may be down, or the remote server API engine may be OFF. Also, possible that Custom Authentication is on, or SSL is on, and the configuration is incorrect.

Action

Ensure the remote Security Directory Integrator server can be contacted via remote server API. Users can check connection details with `tdisrvctl` utility.

CTGDJB652I Started Action Manager Status Update thread.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB653E Unable to update status of Action Manager.

Explanation

The Action Manager was not able to update the status of Action Manager in the FLAG_HOLDER table in database. Some internal database error may have occurred.

Action

Ensure that the database is running in network mode, and the FLAG_HOLDER table is not corrupted. Try again.

CTGDJB654I ServerConfigHandler created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB655E ServerStatusListener thread unable to update server status.

Explanation

The ServerStatusListener thread was unable to update current status of remote server.

Action

Ensure that the database is running in network mode. See accompanying exception trace.

CTGDJB656E Unable to create ConfigLoadReloadListener thread for [SERVER_ID]: *Server ID*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a DIEventListener for registering a config load reload event.

Action

Ensure the remote server API is on. See the accompanying exception trace.

CTGDJB657E Unable to create ConfigLoadReload Thread for [SERVER_ID]: *Server ID*. Unable to register ConfigLoadReloadListener.

Explanation

The Action Manager was unable to create a thread because it was unable to register a DIEventListener with remote server.

Action

Ensure the remote server API is on. See the accompanying exception trace.

CTGDJB658E Unable to remove EventListener for [SERVER_ID]: *Server ID*. Unable to remove event listener.

Explanation

The Action Manager was unable to remove event listener registered with remote server.

Action

Verify that remote server associated with the Solution view is running. See accompanying exception trace.

CTGDJB659I Started AMCServerModificationListener thread.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB660E Unable to create ServerStatusListener threads.

Explanation

The Action Manager was unable to create ServerStatusListener threads.

Action

See the accompanying exception trace. Try running Action Manager again.

CTGDJB661I Checking for any Administration and Monitoring Console Server updates.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB662E Unable to obtain connection to the Administration and Monitoring Console database.

Explanation

The Action Manager was unable to obtain a connection to the Administration and Monitoring Console database. This may occur if there is an error in the JDBC URLs specified in the `am_config.properties`. The Action Manager connects to the Administration and Monitoring Console's database using Derby in network mode. If the specified Derby database does not exist, or is booted in embedded mode, then Action Manager cannot connect to the database. To create the database, the Administration and Monitoring Console must have been started at least once. Action Manager will start the database in network mode, in case its not running in network mode already. This could also happen, if the database shutdown (maybe because the Administration and Monitoring Console was shutdown). This will happen, only if the Administration and Monitoring Console had booted the database, and now the Administration and Monitoring Console has been shutdown. It is recommended that to avoid this situation, start Action Manager first, and then start the Administration and Monitoring Console.

Action

Ensure that the JDBC settings in the `am_config.properties` file are correct, and pointing to the Administration and Monitoring Console's Derby database. Ensure that the Administration and Monitoring Console is not already connected to the database in Embedded mode. The recommended procedure is as follows: 1) Ensure that the Administration and Monitoring Console's database exists. If not, start the Administration and Monitoring Console. On starting the Administration and Monitoring Console for the first time, the Derby database is automatically created. 2) Shutdown the Administration and Monitoring Console and reconfigure it to connect to the database in network mode (if not already configured for network mode). 3) Start Action Manager. Action Manager will start the database in network mode. 4) Start the Administration and Monitoring Console, which will also connect to the same database over network mode.

CTGDJB663E Unable to obtain connection to the Administration and Monitoring Console database.

Explanation

The Action Manager was unable to obtain a connection to database. This may occur if there is an error in the JDBC URLs specified in the `am_config.properties`. The Action Manager connects to the Administration and Monitoring Console's database using Derby in network mode. If the specified Derby database does not exist, or is booted in embedded mode, then Action Manager cannot connect to the database. To create the database, the Administration and Monitoring Console must have been started at least once. Action Manager will start the database in network mode, in case its not running in network mode already. This could also happen, if the database shutdown (maybe because the Administration and Monitoring Console was shutdown). This will happen, only if the Administration and Monitoring Console had booted the database, and now the Administration and

Monitoring Console has been shutdown. It is recommended that to avoid this situation, start Action Manager first, and then start the Administration and Monitoring Console.

Action

Ensure that the JDBC settings in the `am_config.properties` file are correct, and pointing to the Administration and Monitoring Console's Derby database. Ensure that the Administration and Monitoring Console is not already connected to the database in Embedded mode. The recommended procedure is as follows: 1) Ensure that the Administration and Monitoring Console's database exists. If not, start the Administration and Monitoring Console. On starting the Administration and Monitoring Console for the first time, the Derby database is automatically created. 2) Shutdown the Administration and Monitoring Console and reconfigure it to connect to the database in network mode (if not already configured for network mode). 3) Start Action Manager. Action Manager will start the database in network mode. 4) Start the Administration and Monitoring Console, which will also connect to the same database over network mode.

CTGDJB664E Exception while constructing Action Manager threads.

Explanation

The Action Manager was unable to create listener threads because some internal error occurred. See the logs, or accompanying exception trace for more information.

Action

See the associated exception trace for reasons of error. Try running Action Manager again.

CTGDJB665I ServerStatusListener thread started for server [SERVER_NAME]: *Server Name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB666I ConfigLoadReloadListener thread started for server [SERVER_NAME]: *Server Name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB667E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and remote Server API engine is enabled on that server.

CTGDJB668E ServerStatusListener unable to check server restart status.

Explanation

The Action Manager was unable to check whether server has been restarted.

Action

Verify that the remote Security Directory Integrator server is running and remote Server API engine is enabled on that server.

CTGDJB669I [SERVER_NAME]: *Server Name* has been restarted in polling interval. Rule threads will be terminated and re-created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB670E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and remote Server API engine is enabled on that server.

CTGDJB671E Action Manager was unable to create Action Manager Thread for the following rule: [Rule]: *rule name* [Reason]: Unable to connect to server *Server Name*.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and remote Server API engine is enabled on that server.

CTGDJB672E Error occurred while trying to delete data from the AM_SERVER_UPDATE_DETAILS table.

Explanation

The ServerModificationListener thread, checks if any servers registered with the Administration and Monitoring Console has been modified. This thread has encountered a database exception while trying to delete data from the AM_SERVER_UPDATE_DETAILS table. This could have happened if the Administration and Monitoring Console database has been shutdown, or some other internal error occurred.

Action

Verify that the database is running. Look at the exception trace in the log.

CTGDJB673E Config *Config instance* is not loaded on the remote server so ActionManager cannot query the AssemblyLine result.

Explanation

The Query AssemblyLine trigger starts the AssemblyLine in the user specified time interval and on AssemblyLine termination inspects the result. Here the config associated with the AssemblyLine is not loaded on server and so ActionManager cannot start the AL.

Action

Load the config on the remote server.

CTGDJB674E Unable to start AssemblyLine *AssemblyLine name*

Explanation

Action Manager encountered an error when trying to start AssemblyLine on the remote machine.

Action

Ensure that the AssemblyLine exists in the specified config.

CTGDJB675I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB676E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for Query AssemblyLine result type of trigger).

Action

Check the exception trace following this message in the logs. Ensure that the time units were correctly specified.

CTGDJB677E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and that the remote Server API engine is enabled on that server.

CTGDJB678I The Config instance *Config instance* is not running. Will obtain handle to AssemblyLine later.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB679E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a `DIEventListener` for registering an `AssemblyLine` listener.

Action

Ensure that the remote Security Directory Integrator server is a 6.1.1 server, and that the remote server API is on. See the accompanying exception trace.

CTGDJB680E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register `AssemblyLine` listener.

Explanation

The Action Manager was unable to create a thread because it could not create a `DIEventListener` for registering an `AssemblyLine` listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 or higher server, and the remote server API is on. See the accompanying exception trace.

CTGDJB681I Created Action Manager thread for [Config]: *Config instance* [AssemblyLine]: *AssemblyLine name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB682I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB683I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB684W Unable to obtain handle to AssemblyLine object for AssemblyLine: *AssemblyLine name*

Explanation

Failure to obtain a handle for this AssemblyLine may indicate that the AssemblyLine does not exist or some internal error occurred.

Action

Check the AssemblyLine and the accompanying exception trace.

CTGDJB685E Result work entry is null in AssemblyLine: *AssemblyLine name*. Rule will not be triggered.

Explanation

The AssemblyLine returned a null work entry object.

Action

Check the AssemblyLine.

CTGDJB686E No value found for attribute *attribute name*. in result work entry. Rule will not be triggered.

Explanation

The AssemblyLine work entry does not contain a value for the specified attribute.

Action

Check the AssemblyLine.

CTGDJB687I Attribute *attribute name* value is *attribute value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB688E Error in [Rule]: *rule name* [Solution View]: *Solution View name* The attribute values cannot be compared since one of the values is not a valid integer. [Attribute]: *Attribute name* [Current Value]: *Attribute value* [Compared to value]: *value*

Explanation

The Action Manager was unable to check the triggering condition because the attribute value or the value to be compared to are not integers.

Action

Ensure that the specified attribute has an integer value, and that the value to be compared to is also a valid integer. Check the AssemblyLine and the Action Manager rule definition.

CTGDJB689W Unable to obtain handle to AssemblyLine object for AssemblyLine: *AssemblyLine name* Cannot obtain result work entry.

Explanation

This may have happened because the AssemblyLine does not exist, or some internal error occurred.

Action

Check the AssemblyLine and the accompanying exception trace.

CTGDJB690I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: *Inspect AssemblyLine* Exit code.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB691I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: *On AssemblyLine start*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJB692I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]:
On config load**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJB693I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]:
On config unload**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJB694I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]:
Timer**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB695E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (AssemblyLine start type trigger). This may occur because the database is down, or because some internal database related error occurred.

Action

Check the exception trace following this message in the logs. Ensure that the database is running in network mode.

CTGDJB696E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and that the remote Server API engine is enabled on that server.

CTGDJB697E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a `DIEventListener` for registering an `AssemblyLine` start listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and that the remote server API is on. See the accompanying exception trace.

CTGDJB698E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register `AssemblyLine` start listener.

Explanation

The Action Manager was unable to create a thread because it could not register an `AssemblyLine` start listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and that the remote server API is on. See the accompanying exception trace.

CTGDJB699I Rule *rule name* terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB700I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* **[Rule]:** *rule name* **[Solution View]:** *Solution View name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB701E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* **[Rule]:** *rule name* **[Solution View]:** *Solution View name.*

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for a config load type of trigger). This may occur, because the database is down, or because some internal database related error occurred.

Action

Check the exception trace following this message in the logs. Ensure that the database is running in network mode.

CTGDJB702E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* **[Rule]:** *rule name* **[Solution View]:** *Solution View name.* **Unable to connect to remote Security Directory Integrator server.**

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and that the remote Server API engine is enabled on that server.

CTGDJB703E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a `DIEventListener` for registering a config load listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and that the remote server API is on. See the accompanying exception trace.

CTGDJB704E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register config load listener.

Explanation

The Action Manager was unable to create a thread because it could not register a config load listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and that the remote server API is on. See the accompanying exception trace.

CTGDJB705I Created Action Manager thread for [Config]: *Config instance* [AssemblyLine]: *AssemblyLine*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB706I Created Action Manager thread for [Config]: *Config instance* [AssemblyLine]: *AssemblyLine*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB707I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB708E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (config unload type of trigger). This may occur because the database is down, or because some internal database related error occurred.

Action

Check the exception trace following this message in the logs. Ensure that the database is running in network mode.

CTGDJB709E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to connect to remote Security Directory Integrator server.

Explanation

The Action Manager was unable to create a thread because it could not connect to the remote Security Directory Integrator server associated with this Solution View.

Action

Verify that the remote Security Directory Integrator server associated with this Solution View is running, and that the remote Server API engine is enabled on that server.

CTGDJB710E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to create base listener.

Explanation

The Action Manager was unable to create a thread because it could not create a DIEventListener for registering a config unload listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and that the remote server API is on. See the accompanying exception trace.

CTGDJB711E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*. Unable to register config unload listener.

Explanation

The Action Manager was unable to create a thread because it could not register a config load listener.

Action

Ensure the remote Security Directory Integrator server is a 6.1.1 server or higher, and that the remote server API is on. See the accompanying exception trace.

CTGDJB712I Created Action Manager thread for [Config]: *Config instance* [AssemblyLine]: *AssemblyLine name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB713I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB714E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (timer type of trigger). This may occur because the database is down, or because some internal database related error occurred.

Action

Check the exception trace following this message in the logs. Ensure that the database is running in network mode.

CTGDJB715I Killing Action Manager thread for [Action Manager Rule Id]: *Action Manager Rule ID* **[Rule]:** *rule name*
[Solution View]: *Solution View name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB716I Rule *rule name* **triggered.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB717I Rule *rule name* **triggered.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB718I Rule *rule name* **triggered.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB719W The Action manager RMI Registry is starting on default port *port*

Explanation

The Action Manager registry is starting on the default port because is either not specified in the am.properties file OR the port specified is zero.

Action

Check the am_config.properties file whether a valid port is provided for Action Manager registry.

CTGDJB720I The Action Manager RMI registry is started on port *port*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB721E An exception occurred while starting the Action Manager RMI Registry: *exception*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB722W The client information provided *data value* is not sufficient for extracting the client name and client version.

Explanation

The client information should be provided as 'clientName_clientVersion'

Action

The client information is not in the expected format; therefore the client name and client version cannot be retrieved.

CTGDJB723I The System Security Manager is null. Using the Action Manager custom security manager instead.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB724I The Action manager is resetting the System Security Manager to null.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB725I Creating Action Manager thread for [Solution View]: *Solution View name* [Rule]: *rule name* [Trigger Type]: On local variable.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB726E Unable to create Action Manager Thread for [Action Manager Rule Id]: *Action Manager Rule ID* [Rule]: *rule name* [Solution View]: *Solution View name*.

Explanation

One or more errors occurred while trying to read the database for creating the Action Manager listener thread (for Action Manager local variable type of trigger). This may occur, because the database is down, or some internal database related error occurred.

Action

Check the exception trace following this message in the logs.

CTGDJB727I Rule *rule name* triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB728E Unable to modify local variable to new value:
value

Explanation

Action Manager could not execute the modify local action. See accompanying exception.

Action

See the error messages or exception trace.

CTGDJB729E An exception occurred while getting *rule name* details: *exception*

Explanation

Refer to logs for additional details.

Action

Refer to logs for additional details.

CTGDJB730E An exception occurred while executing rule *rule name*: *exception*

Explanation

Refer to logs for additional details.

Action

Refer to logs for additional details.

CTGDJB731I The rule *rule name* has no actions to be backed up.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB732E An exception occurred while backing up the original values for rule *rule name*: *exception*

Explanation

Refer to logs for additional details.

Action

Refer to logs for additional details.

CTGDJB733I The client info *client info* used for connecting with Action Manager is invalid.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB734I The table AM_ACTION_DETAILS_WRITE_LOG is empty.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB735E The API Listener is not able to create the Action Manager thread because of the exception: *exception*.

Explanation

See message.

Action

Refer to logs for additional details. Try again to create the API Failure Trigger.

CTGDJB736E Action Manager was unable to obtain the Action Manager logs to be attached with the email.

Explanation

Action Manager was unable to obtain the Action Manager logs to be attached with the email. The email will be sent without the logs.

Action

Examine the am_logging.properties for the location of the Action Manager log file. Refer to logs for additional details.

CTGDJB737E Action Manager was unable to obtain the host and port information of the SMTP server.

Explanation

Action Manager was unable to obtain the host and port information of the SMTP server. As a result, the Send email action cannot be executed.

Action

Specify the SMTP host and port information in the `am_config.properties` file. If authentication is required for the SMTP server, specify user and password properties.

CTGDJB738E Action Manager was unable to create and send an email message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB739E Action Manager was unable to obtain the host and port information of the SMTP server from the Action Manager config file.

Explanation

Action Manager was unable to obtain the host and port information of the SMTP server. As a result, the Send email action cannot be executed.

Action

Specify the SMTP host and port information in the `am_config.properties` file. If authentication is required for the SMTP server, specify user and password properties. Refer to logs for additional information.

CTGDJB740E Property `java.util.logging.config.file` is not set in `startAM.bat(sh)`.

Explanation

Action Manager was unable to initialize because the required property `java.util.logging.config.file` was not set. This property is required for finding the location of the Action Manager logging file `am_logging.properties`.

Action

Ensure that in the `startAM.bat(sh)` file the `java.util.logging.config.file` property is being set to point to the location of the `am_logging.properties` file.

CTGDJB741E Unable to load the `am_logging.properties` file. Check the value of `java.util.logging.config.file` property in the `startAM.bat(sh)`. The current value is set to *file path*.

Explanation

Action Manager was unable to initialize because the property `java.util.logging.config.file` in the `startAM.bat(sh)` file is pointing to an invalid location.

Action

Ensure that in the startAM.bat(sh) file the java.util.logging.config.file property is being set to point to the location of the am_logging.properties file. See the associated exception trace.

CTGDJB742I The target computer is the same as the Action Manager host.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB743W The user name or keystore is set to *property value* and the password or keystore password is set to *property value*.

Explanation

The target computer login details are not provided.

Action

The user name and password of the target computer or the keystore and keystore password used for authenticating a user with the target computer should be provided.

CTGDJB744E Failed to connect to the target computer using protocol *protocol*.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB745I Failed to connect to the target computer using any of the supported protocols. Action Manager is assuming that command *command* is to be executed on localhost.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB746E An error *error* occurred while executing the command *command* on action manager host *hostname*.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB747I The command *command* is executed successfully on host *hostname*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB748E The command *command* execution failed on host *hostname* with exit code *Integer*.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB749E An error occurred while executing the command *command* on host *hostname*: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB750E The command *command* is not executed.

Explanation

Verify the correctness of the command and the computer details.

Action

Verify the correctness of the command and the computer details.

CTGDJB751E An error was encountered while retrieving data from the database: *error*.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB752E Failed to establish a connection with the target computer.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB753E An error occurred while executing the command *command*.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB754W Cannot rollback the properties changes because the config instance id is null.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB755E An error occurred while rolling back the properties: *error message*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB756E An error occurred while rolling back the database changes: *error message*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB757E An error occurred while backing up the property: *error message*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB758E No command specified in the execute command action.

Explanation

The execute command action is supposed to execute a command on the target computer. There is no command specified by the user.

Action

Specify a valid command which needs to be executed on the target computer.

CTGDJB759E Action Manager was unable to obtain local variable *variable name*.

Explanation

The Action Manager was unable to obtain the specified local variable.

Action

Restart Action Manager and verify that the database is running.

CTGDJB760E Unable to obtain local variable information.

Explanation

Action Manager encountered an error when reading action information from database.

Action

See the error messages or exception trace.

CTGDJB761E An error occurred while terminating thread for rule *rule name: error*.

Explanation

Action Manager encountered an error when terminating a rule thread. from database.

Action

See the error messages or exception trace.

CTGDJB762E An error occurred while starting thread for rule *rule name: error*.

Explanation

Action Manager encountered an error when starting a rule thread. from database.

Action

See the error messages or exception trace.

CTGDJB763W An error occurred while closing the database connection: *error*.

Explanation

Action Manager encountered an error when closing a database connection. from database.

Action

See the error messages or exception trace.

CTGDJB764W An error occurred while checking for server updates: *error*

Explanation

Action Manager encountered an error while checking for server updates. from database.

Action

See the error messages or exception trace.

CTGDJB765I An error occurred while closing the input stream of file *file name: error*.

Explanation

Action Manager encountered an error while closing the input stream of a file. from database.

Action

See the error messages or exception trace.

CTGDJB766E An error occurred while starting thread: *error* **Explanation**

Action Manager encountered an error when starting a thread. from database.

Action

See the error messages or exception trace.

CTGDJB767W An error occurred while rolling back the database changes: *error*. **Explanation**

Explanation

Action Manager encountered an error when rolling back the database changes.. from database.

Action

See the error messages or exception trace.

CTGDJB768I Action Manager trying to connect to *hostname* host using protocol *protocol*. **Explanation**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB769I Action Manager failed to connect to *hostname* host using protocol *protocol*. **Explanation**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB770I Password is null, hence failed to connect to *hostname* host using protocol *protocol*. **Explanation**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB771I Failed to connect to *hostname* host using protocol *protocol* because either password or keystore or keystore password is not provided.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB772E Failed to start Action Manager because an exception occurred: *exception*

Explanation

An exception occurred while starting Action Manager. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB772I Exiting Action Manager with error code *error code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB774E An error occurred while initializing truststores: *exception*

Explanation

An exception occurred while initializing truststores. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB775E An error occurred while initializing keystores: *exception*

Explanation

An exception occurred while initializing keystores. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB776E An error occurred while initializing Action Manage RMI: *exception*

Explanation

An exception occurred while initializing RMI. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB777E Unable to establishing a connection to the database. An exception occurred: *exception*

Explanation

An exception occurred while initializing DB Connection. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB778E Unable to execute the rule *rule name*. An exception occurred: *exception*

Explanation

An exception occurred while executing the rule. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB779E An error occurred while rolling back the database changes for rule *rule name*: *exception*

Explanation

An exception occurred while rolling back db changes. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB780E An error occurred while rolling back the actions for rule *rule name: exception*

Explanation

An exception occurred while rolling back actions. Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB781E An error occurred while retrieving actions: *error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB782E An error occurred while retrieving trigger types for Rule Id *rule id: error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB783E An error occurred *error message* while retrieving rules for Server Id *server id*.

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB784E An error occurred while retrieving rules for Config URL *URL: error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB785E An error occurred while retrieving the Server version: *error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB786E An error occurred while checking the Server version: *error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB787E An error occurred while getting the Server name for Server Id *server id: error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB788E An error occurred while getting the triggered triggers: *error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB789E An error occurred while getting the Rule Id for rule *rule name: error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB790E An error occurred while getting the Config Instance for Solution View *solution view name: error message*
Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB791E An error occurred while getting the Solution Id for Solution View *solution view name: error message*
Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB792E An error occurred while getting the Solution View name for Solution Id *solution id: error message*
Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB793E An error occurred while getting the action details for Rule Id *rule id: error message*
Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB794E An error occurred while enabling/disabling a rule with Rule id *rule id: error message*
Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB795E An error occurred while retrieving actions for rule with Rule ID *rule id: error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB796E An error occurred while initializing of String encryption decryption utility: *error message*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB797I Encryption scheme *encryption scheme is not supported.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB798I The string being encrypted is empty or null.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB799E An error occurred while encrypting a string: *error*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

**CTGDJB800I The string being decrypted is empty or null.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB801E An error occurred while decrypting: *error message***Explanation**

Refer logs for additional information.

Action

Refer logs for additional information.

**CTGDJB802E An error occurred while decrypting property:
*error message*****Explanation**

Refer logs for additional information.

Action

Refer logs for additional information.

**CTGDJB803E An error occurred while encrypting property:
*error message*****Explanation**

Refer logs for additional information.

Action

Refer logs for additional information.

**CTGDJB804E An error occurred while killing Action Manager
thread: *error message*****Explanation**

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB805W An error occurred while executing command
command: error message

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB806E The hostname *hostname* is unknown. Exception
occurred: *exception*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB807E An error occurred while unregistering the
listener: *error*

Explanation

Refer logs for additional information.

Action

Refer logs for additional information.

CTGDJB808I Executing the SQL command for rolling back the
action.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB809I Rolling back the properties changes made by
force trigger.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB810E An error occurred while rolling back the database transaction: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB811E A threading exception has occurred.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB812E An error occurred while trying to kill the QueryAL listener thread.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB813E A threading exception has occurred.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB814E A threading exception has occurred.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB815W An exit code for the command execution cannot be displayed.

Explanation

The exit code for the command execution cannot be displayed since the command may have spawned a daemon process or there may have been an error during command execution. Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJB816E An error occurred while getting values for local Action Manager variable : *error message*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDJF001E The 'iteratorStateKey' parameter must be set to use the Active Directory Change Detection Connector.

Explanation

The required parameter iteratorStateKey was not specified in the Active Directory Change Detection Connector.

Action

Specify the iteratorStateKey parameter in the Connector.

CTGDJF002W An old configuration parameter 'usnFileName' is used that stores the USN in a text file. This function is no longer supported.

Explanation

Specified the parameter usnFileName is no longer supported in the Active Directory Change Detection Connector. This indicates an old configuration file was used and needs to be migrated.

Action

Consult the Reference Guide for migration information.

CTGDJF003W The 'sleepInterval' parameter set to an invalid value '*parameter value*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid sleepInterval parameter in the Connector if the default value is not wanted.

CTGDJF004W The 'timeout' parameter set to an invalid value '*parameter value*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid timeout parameter in the Connector if the default value is not wanted.

CTGDJF005W The 'pageSize' parameter set to an invalid value '*parameter value*'. Will not use paging.

Explanation

See message.

Action

Specify a valid pageSize parameter in the Connector if paging needs to be enabled.

CTGDJF006W The 'pageSize' parameter set to a negative value '*parameter value*'. Will not use paging.

Explanation

See message.

Action

Specify a valid pageSize parameter in the Connector if paging needs to be enabled.

CTGDJF007I Synchronization from End Of Data will be performed: the Connector will only report changes that occur after it is started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF008E Unable to retrieve the USN value from the given object.**Explanation**

USN value object is NULL. This is an internal error.

Action

Contact IBM support.

CTGDJF009E Synchronization from End Of Data requested, but can't retrieve the highest committed USN number. Exception occurred: *exception***Explanation**

See the next exception.

Action

No action is required.

CTGDJF010E Invalid numeric USN value: *USN value*.**Explanation**

Unable to parse String USN value to Long. This is an internal error.

Action

Contact IBM support.

CTGDJF011E Invalid type for USN value object: *class name*.**Explanation**

The type of the USN object must be Entry, String or Number. This is an internal error.

Action

Contact IBM support.

CTGDJF012I Connector is restarting. Will get start USN value from restart data.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJF013E Could not retrieve USN value from restart data.
Exception occurred: *exception***

Explanation

An internal error has occurred.

Action

Contact IBM support.

CTGDJF014E Error on access to the System Store: *exception*

Explanation

Could not read the USN values from the System Store.

Action

Inspect the error message for more details on the error.

**CTGDJF015I Will read start USN values from System Store.
Parameter: *parameter name*.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJF016I Parameter '*parameter name*' not found in the
System Store. Will use the 'Start at' parameter value for
start USN.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF017E The 'Start at' parameter was not specified.

Explanation

'Start at' parameter is null.

Action

Specify the startAt parameter in the Connector.

CTGDJF018I Start USN value: *USN value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF019E The method `getHighestCommittedUsn` could not retrieve the highest committed USN number from the Active Directory.

Explanation

The highest committed USN number is -1.

Action

No action is required.

CTGDJF020W The method `getNextSearchResult` encountered a `PartialResultException` which typically occurs when reaching the last element in the result set. No action is required. The exception is: *exception*

Explanation

See method `hasMore()` of `NamingEnumeration` class for more detailed description of this exception.

Action

No action is required.

CTGDJF021I Timeout waiting for the next changed entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF022I LDAP search query: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF023E The method storeUSNForNextSynch could not store the USN value in the System Store. Exception occurred:
exception

Explanation

Error occurs when trying to store the USN values for the next synchronization.

Action

Check the database store.

CTGDJF024I Current USN value is *USN value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF025E The restart info is NULL. Cannot restart.

Explanation

There is no restart information in the entry.

Action

Check the checkpoint configuration.

CTGDJF026I Blocking for new changes...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF027W Invalid 'Sleep Interval' value specified:
parameter value. Will use default value of interval in seconds.

Explanation

See message.

Action

No action is required.

CTGDJF028W Invalid 'Timeout' value specified: *parameter value*. Will use default value of *timeout value*.

Explanation

See message.

Action

No action is required.

CTGDJF029W Invalid 'Page Size' value specified: *parameter value*. Will not use paging.

Explanation

See message.

Action

No action is required.

CTGDJF030E Invalid 'START_USN' value: *USN value*. 'START_USN' value will be set to 0.

Explanation

See message.

Action

No action is required.

CTGDJF031I Get next page: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJF032E Could not store the USN value in System Store.

Explanation

See message.

Action

No action is required.

CTGDJF033W The 'iteratorStateKey' parameter is not specified in the Active Directory Change Detection Connector. The Connector will not persist state.

Explanation

The parameter iteratorStateKey is not specified in the Active Directory Change Detection Connector.

Action

Specify the iteratorStateKey parameter in the Connector configuration to enable state persistence.

CTGDKF001W Invalid 'Sleep Interval' value specified: *interval in seconds*. Will use default value of *interval in seconds*.

Explanation

See message.

Action

No action is required.

CTGDKF002W Invalid 'Timeout' value specified: *parameter value*. Will use default value of *integer*.

Explanation

See message.

Action

No action is required.

CTGDKF003E USN Entry does not contain '*attribute name*' attribute.

Explanation

See message.

Action

No action is required.

CTGDKF004I USN values set to zero. Full synchronization will be performed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF005I Connector is restarting. Will get start USN values from restart data.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF006E Could not retrieve USN values from restart data. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDKF007I Will read start USN values from file: *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF008E Could not close USN properties file '*file name*'. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDKF009E Error: Could not read start USN values from file '*file name*'. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDKF010E Error: 'Iterator State Store' parameter not specified.**Explanation**

See message.

Action

No action is required.

CTGDKF011E At least one of the parameters 'Iterator State Store' or 'USN Filename' (backward compatibility mode) should be specified.**Explanation**

See message.

Action

No action is required.

CTGDKF012E USN storage not specified.**Explanation**

See message.

Action

No action is required.

CTGDKF013E Error on access to the Persistent Parameter Store. Exception occurred: *exception***Explanation**

See message.

Action

No action is required.

CTGDKF014I Will read start USN values from Persistent Parameter Store; parameter: *parameter name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF015E Could not retrieve start USN values from persistent parameter '*parameter name*'. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDKF016W Parameter '*parameter name*' not found in Persistent Parameter Store. The startAt's value will be used.

Explanation

See message.

Action

No action is required.

CTGDKF017I Will use the 'Start at' parameter value for construction of the start USN values.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF018E The 'Start at' parameter not specified.

Explanation

See message.

Action

Specify the Start at parameter in the Connector.

CTGDKF019I Synchronization from End Of Data will be performed: the Connector will only report changes that occur after it is started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF020E Error: Synchronization from End Of Data requested, but can't find highest committed USN number: exception

Explanation

See message.

Action

No action is required.

CTGDKF021E Invalid 'Start at' value specified: *mStartAt*.

Explanation

See message.

Action

No action is required.

CTGDKF022I Start USN values:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF023I Initial 'CURRENT_USN_CREATED' parameter is greater than the 'END_USN' parameter. Setting 'CURRENT_USN_CREATED' parameter to the value of the 'START_USN' parameter.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF024I Both the 'CURRENT_USN_CREATED' and 'CURRENT_USN_CHANGED' parameters are smaller than the 'START_USN' parameter. Setting the 'CURRENT_USN_CREATED' parameter to the value of 'START_USN' parameter.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF025I Start USN values internally adjusted to:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF026E Could not retrieve highest committed USN number.

Explanation

The highest committed USN number is an attribute specific to Active Directory.

Action

Make sure that the Connector is accessing Active Directory and not some other LDAP server.

CTGDKF027E Could not retrieve highest committed USN number.

Explanation

The highest committed USN number is an attribute specific to Active Directory.

Action

Make sure that the Connector is accessing Active Directory and not some other LDAP server.

CTGDKF028I LDAP search query: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF029E An PartialResultException caught when retrieving an Entry from the Active Directory Server based on the given filter: *exception*

Explanation

In some cases when there are no Exchange Directory Service objects that match, the filter PartialResultException is thrown.

Action

Check the filter.

CTGDKF030I Timeout waiting for next changed entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF031E Could not store USN values in file '*file name*'. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDKF032I Current USN values are:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF033E Could not store USN values in Persistent Parameter Store. Exception occurred: *exception*

Explanation

System Store might not be configured properly.

Action

Make sure that the System Store configuration settings are correct.

CTGDKF034I Current USN values are:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF035E Restart info is NULL. Cannot restart.

Explanation

An internal error occurred. The Checkpoint/Restart feature failed.

Action

Contact IBM support.

CTGDKF036I USN values needed for the next synchronization with Active Directory.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKF037I USN attribute *name: value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIY001E Unable to get next entry. No AssemblyLine to execute.

Explanation

The AssemblyLine Connector could not get the next entry because there were no AssemblyLines to execute/retrieve.

Action

The method initialize should be invoked first.

**CTGDIY002E Expecting com.ibm.di.entry.Entry, object found
*Java class name.***

Explanation

If the work Entry of the adapted Assembly Line has an attribute named conn, that attribute must contain values of type com.ibm.di.entry.Entry only.

Action

Verify the logic of the adapted Assembly Line.

CTGDIY003I Computed modes for *Connector name* :

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIY004I Operations for *Assembly Line name* :

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIY005I Standard modes recorded :

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIY006E Unable to connect to server/config: *server host / Config instance id.*

Explanation

Cannot find the specified configuration instance on the specified Security Directory Integrator server.

Action

Verify that the specified server is running. Verify that the specified configuration is running on the specified server.

CTGDIY007I Performing operation: *operation name, work Entry: entry name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIY008I Operation *operation name* returned *Java object.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIY101E Unable to select AssemblyLine operation. The remote Config '*Config name*' cannot be found on server '*server name*'.

Explanation

The configuration instance specified in the AssemblyLine Function Component's Config parameter could not be found on the remote server.

Action

Verify the specified Config parameter exists on the remote server.

CTGDIY102E Unable to select AssemblyLine operation. Connection to server '*server name*' cannot be obtained.

Explanation

The remote server instance specified in the AssemblyLine Function component's server parameter may not be currently active.

Action

Verify the specified server instance [hostname:port] combination is active on the remote server and then try to establish a connection again.

CTGDIY103E No server configured.

Explanation

The Server configuration parameter is required for the query configuration operation to work.

Action

Enter a valid remote Security Directory Integrator server information [hostname:port] in the AssemblyLine Function Component server parameter fields and then perform the query configuration operation.

CTGDIY104E Unable to retrieve initialized schema. The remote Config '*Config name*' cannot be found on server '*server name*'.

Explanation

The configuration instance specified in the AssemblyLine Function Component's Config parameter could not be found on the remote server.

Action

Verify the specified Config parameter exists on the remote server.

CTGDIY105E Unable to select AssemblyLine. The remote Config '*Config name*' cannot be found on server '*server name*'.

Explanation

The configuration instance specified in the AssemblyLine Function Component's Config parameter could not be found on the remote server.

Action

Verify the specified Config parameter exists on the remote server.

CTGDIY106E Unable to retrieve initialized schema. Connection to server '*server name*' cannot be obtained.

Explanation

The remote server instance specified in the AssemblyLine Function component's server parameter may not be currently active.

Action

Verify the specified server instance [hostname:port] combination is active on the remote server and then try to establish a connection again.

CTGDIY107E Unable to select AssemblyLine. Connection to server '*server name*' cannot be obtained.

Explanation

The remote server instance specified in the AssemblyLine Function component's server parameter may not be currently active.

Action

Verify the specified server instance [hostname:port] combination is active on the remote server and then try to establish a connection again.

CTGDIY108I Waiting 2 seconds for remote AssemblyLine to complete: '*AssemblyLine Name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIY109E The Config instance not specified for server '*server name*'.

Explanation

See message.

Action

Verify the specified Config parameter exists on the remote server.

CTGDIY110E The '*assemblyLine*' parameter must be set to use the AssemblyLine Function Component.

Explanation

The required parameter *assemblyLine* was not specified in the AssemblyLine Function Component.

Action

Specify the *assemblyLine* parameter in the Function Component.

CTGDIY111E Unable to parse attributes in the entry. Encountered an unknown TCB parameter '*parameter name*'.

Explanation

There is no dot symbol in the attribute name.

Action

Check the attribute names prefix must be '\$tcb.'.

CTGDIY112E Exception occurred while retrieving configuration: *exception***Explanation**

Cannot get the specified configuration.

Action

Contact IBM support.

CTGDIY113W Warning: Cannot run local AssemblyLines.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA201E The required WSDL file location was not provided.**Explanation**

The Axis2 Web Service Client Function Component requires a WSDL file in order to generate all the required elements for the request message.

Action

Provide a valid path to the WSDL file. It can point to a local file or remote URL.

CTGDIA202E No service specified in the Function Component's configuration.**Explanation**

The Axis2 Web Service Client Function Component requires a service name which corresponds to the service which will be invoked.

Action

Provide a valid service name. Use the button next to it to see all services in the WSDL file.

CTGDIA203E No endpoint specified in the Function Component's configuration.

Explanation

The Axis2 Web Service Client Function Component requires an endpoint name which corresponds to the Web Service's listening URL.

Action

Provide a valid endpoint name. Use the button next to it to see all endpoints in the WSDL file.

CTGDIA204E No operation specified in the Function Component's configuration.

Explanation

The Axis2 Web Service Client Function Component requires an operation name which corresponds to the operation which will be invoked.

Action

Provide a valid operation name. Use the button next to it to see all operations in the WSDL file.

CTGDIA205I Setting HTTP Basic Authentication headers. The username is: *username*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA206E The Axis2 Web Service Client Function Component accepts only a IBM Security Directory Integrator Entry for input.

Explanation

At the beginning of the Function Component's execution cycle the input data passed was not a IBM Security Directory Integrator Entry.

Action

The Axis2 Web Service Client Function Component expects only a IBM Security Directory Integrator Entry for input. Check the AL logic and try again.

CTGDIA207E An Exception occurred while trying to invoke the Web Service. Exception message: *exception*

Explanation

Axis specific fault occurred. Check the Exception message for more details.

Action

Axis specific fault occurred. Check the Exception message for more details.

CTGDIA208E The input operation message parameter was not found in the provided input entry. The required input parameter is: *exception*

Explanation

The Axis2 Web Service Client Function Component requires the input operation message parameter to be provided in the input entry.

Action

Try mapping the required message parameter to the input entry.

CTGDIA101E There are multiple services described in the WSDL document at '*URL*'. Select one of them.

Explanation

When there are multiple services described in the WSDL document, you must specify a service name.

Action

Verify that a valid service name is provided in the Connector configuration.

CTGDIA102E The WSDL document at '*URL*' does not contain a description of service '*service name*'.

Explanation

The Connector could not find a service with the specified name in the WSDL document.

Action

Verify that the specified service name is correct.

CTGDIA103I An HTTP client connection failed with error: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA104E A problem was encountered while parsing the SOAP request 'SOAP request'. The error is: *exception*

Explanation

The Connector could not process the specified SOAP request message.

Action

Verify that the SOAP message is correct.

CTGDIA105I The response payload is expected in an Attribute with name '*attribute name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA106E The Connector has been passed both a normal message and a fault message. Only one outgoing message is allowed.

Explanation

The web service cannot return both a normal SOAP message and a SOAP fault. Modify the AssemblyLine logic so that it constructs either a normal response or a fault response, but not both at the same time.

Action

Verify that the logic of the associated AssemblyLine is correct.

CTGDIA107E A problem was encountered while constructing the SOAP response message. The error is: *exception*

Explanation

See the exception message.

Action

Verify that the AssemblyLine logic is correct.

CTGDIA108I Neither a normal response payload, nor a fault has been passed to the Connector. Will not generate a SOAP response.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA109E Provide a \$faultReason Attribute.

Explanation

The fault reason is a mandatory field of a SOAP fault. When you set the \$faultCode Attribute at run-time, you must also set the \$faultReason Attribute.

Action

Verify that the AssemblyLine logic is correct.

CTGDIA110E A problem was encountered while constructing the SOAP fault message. The error is: *exception*

Explanation

See the exception message.

Action

Verify that the AssemblyLine logic is correct.

CTGDIA111E A problem was encountered while configuring the underlying Axis2 library. The error is: *exception*

Explanation

See the exception message.

Action

Verify that the Security Directory Integrator installation is not corrupt.

CTGDIA112E A problem was encountered while reading the WSDL document at 'URL'. The error is: *exception*

Explanation

See the exception message.

Action

Verify that the WSDL document exists and is valid.

**CTGDIA113E Unknown SOAP version: 'SOAP namespace URI'.
Explanation**

The Connector could not determine the SOAP version based on the specified namespace URI.

Action

Verify that the SOAP namespace URI is valid.

**CTGDIA114E Missing 'wsdlUrl' parameter.
Explanation**

The WSDL URL is a mandatory parameter.

Action

Verify that the configuration is correct.

**CTGDIA115E Could not obtain AssemblyLine configuration.
Explanation**

The WSDL generation process uses the configuration of the AssemblyLine that contains the current Connector.

Action

Verify that the Connector is part of an AssemblyLine.

**CTGDIA116E Cannot derive a web service description from the AssemblyLine configuration. The error is: *exception*
Explanation**

See the exception message.

Action

Verify that the AssemblyLine configuration is correct.

**CTGDIA117E A problem was encountered while writing the WSDL document to file '*file name*'. The error is: *exception*
Explanation**

See the exception message.

Action

Verify that the file name is correct. Verify that the file system permissions allow the file to be written.

CTGDIA118E The message exchange pattern '*URL*' of operation '*operation name*' does not allow a SOAP fault response.

Explanation

A SOAP fault has been passed to the Connector, but the WSDL operation does not allow a fault response.

Action

Verify that the AssemblyLine logic is correct.

CTGDIA119E The message exchange pattern '*URL*' of operation '*operation name*' requires a response. Either provide a normal response in an Attribute named '*Attribute name*' or provide a SOAP fault.

Explanation

A SOAP fault has been passed to the Connector, but the WSDL operation does not allow a fault response.

Action

Verify that the AssemblyLine logic is correct.

CTGDIA120I Will not generate a SOAP response, because an HTTP body is provided in the '*conn*' Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA121I WSDL file generated successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ601I Web service called successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ602I Parameter 'wsdlUrl': *parameter value*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ603E Parameter 'wsdlUrl' is empty.**Explanation**

See message.

Action

Specify a valid 'wsdlUrl' parameter in the Function Component.

CTGDIZ604I Parameter 'soapOperation': *parameter value*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ605E Parameter 'soapOperation' is empty.**Explanation**

See message.

Action

Specify a valid 'soapOperation' parameter in the Function Component.

CTGDIZ606I Parameter 'complexType': *parameter value*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ607I Parameter 'operationParamList': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ608I WSDL service QName: *service queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ609I WSDL port QName: *port queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ610I WSDL operation style: *operation style*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ611I Registered class '*class name*' for '*queue name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ612E Entry Attribute '*attribute*' is missing.

Explanation

See message.

Action

Check the attributes in the entry.

CTGDIZ613I About to call web service...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ614I SOAP response Java Object: *response Java Object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIZ615W This web service returned a SOAP Fault message.
Fault string is: *axisFault string*.**

Explanation

In this case axisFault represents a SOAP Fault message received from the web service.

Action

No action is required.

**CTGDIZ617E The invocation of this web service failed for
the following reason: *class name: message*.**

Explanation

In this case axisFault represents an Exception which has occurred on the local machine, and not a SOAP Fault message received from the web service.

Action

No action is required.

CTGDIZ619I Additional output parameter: parameter name:parameter name, parameter value: parameter value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ620I Additional output parameter: parameter name:parameter name, parameter value: parameter value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ621E Axis EasyInvoke Soap WS Function Component expected either an Entry or an Object[], but received ''class'' instead.

Explanation

The method perform of the Function Component expected an Entry or an Object as a parameter.

Action

Invoke the perform method with the correct parameter.

CTGDIZ622w The value ''value'' is invalid for the ''timeOut'' parameter.

Explanation

A numerical value is expected.

Action

Check the "timeOut" parameter.

CTGDIZ623I The invocation of a service will wait forever for a response.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ001E The 'wsdlFile' parameter must be set to use the Axis Easy Web Service Server Connector.

Explanation

The required parameter wsdlFile was not specified in the Axis Easy Web Service Server Connector.

Action

Specify the wsdlFile parameter in the Connector.

CTGDIZ002I The 'wsdlFile' parameter is set to *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ003E The 'soapOperation' parameter must be set to use the Axis Easy Web Service Server Connector.

Explanation

The required parameter soapOperation was not specified in the Axis Easy Web Service Server Connector.

Action

Specify the soapOperation parameter in the Connector.

CTGDIZ004I The 'soapOperation' parameter is set to *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ005I The '**complexType**' parameter is set to *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ006E Cannot find the *attribute name* attribute of the **op-entry**.

Explanation

The attribute does not exist or the attribute does not have any values.

Action

No action is required.

CTGDIZ007E The operation name '*operation name*' extracted from the SOAP request is not valid operation name.

Explanation

See message.

Action

Ensure the operation name is valid.

CTGDIZ008I Response Object values: *array of values*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ009I Request Object array: *array of values*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ201I Successfully generated a SOAP message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ202E Parameter 'wsdlUrl' is empty.

Explanation

See message.

Action

Specify a valid 'wsdlUrl' parameter in the Connector.

CTGDIZ203I Parameter 'wsdlUrl': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ204E Parameter 'soapOperation' is empty.

Explanation

See message.

Action

Specify a valid 'soapOperation' parameter in the Connector.

CTGDIZ205I Parameter 'soapOperation': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ206I Parameter 'complexType': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ207E Parameter 'mode' is empty.

Explanation

See message.

Action

Specify a valid 'mode' parameter in the Connector.

CTGDIZ208I Parameter 'mode': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ209E Parameter 'mode' has invalid value: '*parameter value*'.

Explanation

See message.

Action

Specify a valid 'mode' parameter in the Connector.

CTGDIZ210I Parameter 'operationParamList': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ211I Parameter 'returnXMLType': *mReturnXMLType*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ212E Invalid value for 'returnXMLType': *parameter value*.

Explanation

See message.

Action

Specify a valid 'returnXMLType' parameter in the Connector.

CTGDIZ213I Generated SOAP message Attribute: *attribute*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ214I WSDL service QName: *service queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ215I WSDL port QName: *port queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ216I WSDL operation style: *operationStyle*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ217I AXIS href/multiRef is to *boolean*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ218E The value of the 'soapFault' attribute has an invalid type: *attribute value*.

Explanation

The value of the soapFault attribute must be of type org.apache.axis.AxisFault.

Action

Check the SOAP message.

CTGDIZ219E Entry Attribute '*attribute name*' is missing.

Explanation

See message.

Action

Check the attributes in the entry.

CTGDIZ220I About to generate a SOAP message using the following parameters:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ221I Target namespace: *namespace*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ222I SOAP operation: *operation*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ223I Complex types: *types*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ224I SOAP operation parameters: *parameters*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ225I This is a *message type* message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ226I Generated SOAP message: *SOAP message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ227E The Function Component expected either an Entry or an Object[], but received the class '*class*' instead.

Explanation

The method perform of the Function Component expected an Entry or an Object as a parameter.

Action

Invoke the perform method with correct parameter.

CTGDIZ228I Registered type mapping: Java type: *Java class name* XML type: *XML qualified name* Serializer Factory: *Java class name* Deserializer Factory: *Java class name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ501I Parsed a SOAP message successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ502I Parameter '*wsdlUrl*': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ503E Parameter '*wsdlUrl*' is empty.

Explanation

See message.

Action

Specify a valid '*wsdlUrl*' parameter in the Function Component.

CTGDIZ504I Parameter 'soapOperation': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ505E Parameter 'soapOperation' is empty.

Explanation

See message.

Action

Specify a valid 'soapOperation' parameter in the Function Component.

CTGDIZ506I Parameter 'complexType': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ507I Parameter 'mode': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ508E Parameter 'mode' is empty.

Explanation

See message.

Action

Specify a valid 'mode' parameter in the Function Component.

CTGDIZ509E Parameter 'mode' has invalid value: '*parameter value*'.

Explanation

See message.

Action

Specify a valid 'mode' parameter in the Function Component.

CTGDIZ510I Parameter 'inputType': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ511E Invalid value for 'inputType': *parameter value*.

Explanation

See message.

Action

Specify a valid 'inputType' parameter in the Function Component.

CTGDIZ512I Parsed Java Object Attribute: *attribute*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ513I WSDL service QName: *service queue name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ514I WSDL port QName: *port queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ515E Entry Attribute '*attribute*' is missing.

Explanation

The value of the entry attribute must be xmlDOMELEMENT or xmlString.

Action

Check the parameter 'inputType' in the Function Component.

CTGDIZ516I About to parse a SOAP message using the following parameters:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ517I Complex types: *complex type*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ518I SOAP message: *SOAP message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ519I Parsed Java Object: *Java object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ520E The message parsed is a SOAP Fault message. The fault string is: *fault string*.

Explanation

The result object from parsing is an instance of AxisFault object.

Action

Check the SOAP message.

CTGDIZ521I Additional output parameter: parameter name: *parameter name*, parameter value: *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ522I Additional output parameter: parameter name: *parameter name*, parameter value: *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ523I Registered type mapping: Java type: *Java class name* XML type: *XML qualified name* Serializer Factory: *Java class name* Deserializer Factory: *Java class name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ524E Invalid object recieved: *object*.

Explanation

The Function Component has not received a SOAP request message. It must receive the message either as XML DOM Element or as XML String Java object.

Action

Check the AssemblyLine logic and try again.

CTGDKM401E Missing source file. Use "command line switch" to specify it.

Explanation

The user has not provided valid source file.

Action

See error message.

CTGDKM402E Cannot read file: "file which was unable to read"

Explanation

Either the specified path is invalid or the application has no rights to read the file.

Action

Make sure the provided path is valid and that the user you execute the application with, has sufficient rights to read the file.

CTGDKM403E Duplicate files specified!

Explanation

The user has specified the same files for both input and output.

Action

Make sure the two files are different.

CTGDKM404E Cannot write file: "file which was unable to write"

Explanation

Either the specified path is invalid or the application has no rights to write to the file.

Action

Make sure the provided path is valid and that the user you execute the application with, has sufficient rights to write to it.

CTGDKM405E Cannot delete file: "file which was unable to delete"

Explanation

Either the specified path is invalid or the application has no rights to delete the file.

Action

Make sure the provided path is valid and that the user you execute the application with, has sufficient rights to delete the file.

CTGDKM406E Cannot rename file "*filename of source file*" to "*filename of destination file*"

Explanation

Either the specified path is invalid or the application has no rights to rename the file.

Action

Make sure the provided path is valid and that the user you execute the application with, has sufficient rights to rename the file.

CTGDKM407I Usage: <migration command> -f source_file [-b backup_file] [-n dest_file] [-?][-v]... -? Shows this help. -v Print more verbose information to the standard output. -f source_file Specifies the file to migrate. -b backup_file Specifies the file to use as backup. -n dest_file Specifies the file to output the migration result to.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM408E Error migrating file.

Explanation

See the error message and the produced log.

Action

Check the exception message for more information.

CTGDKM409I File successfully migrated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKJ001E Castor mapping file not specified.

Explanation

The 'mappingFile' Function Component parameter is not set.

Action

Specify the mappingFile parameter.

CTGDKJ002E Invalid value for 'parameter name': parameter value.

Explanation

The return type value is incorrect.

Action

Set a proper value to the return type parameter.

CTGDKJ003E Could not load mapping file: Exception message

Explanation

An Exception occurred while trying to load the mapping file.

Action

Check the mapping file and try again.

CTGDKJ004E Could not create Document Builder: exception message

Explanation

An exception occurred while the Factory was trying to create a new document builder.

Action

DocumentBuilder which satisfies the configuration requested cannot be created.

CTGDKJ005E Invalid root element name: Exception message

Explanation

There are several possible reasons for this Exception: while creating the DOMELEMENT, if an illegal character is in the specified name; or the parent node is of a type that does not allow children of the type of the newChild node while appending the child node ; or the parent node is created from a different document than the one which created the child node while appending the child node; or the parent node is read-only or if the previous parent of the node being inserted is read-only while appending the child node.

Action

Verify that the name of the root element does not contain invalid characters.

CTGDKJ006E Error on marshalling Entry attributes:

Exception message

Explanation

There are several possible reasons for this Exception: while creating the DOMELEMENT, if an illegal character is in the specified name; or the parent node is of a type that does not allow children of the type of the newChild node while appending the child node; or the parent node is created from a different document than the one which created the child node while appending the child node; or the parent node is read-only or if the previous parent of the node being inserted is read-only while appending the child node; or while sets the mapping to be used by the marshalling Framework; or while marshalling Object as XML.

Action

Verify the content of the mapping file.

CTGDKJ007E Error while transforming DOM to string:

Exception message

Explanation

There are several possible reasons for this Exception: while obtain the new instance of the TransformerFactory if the implementation is not available or cannot be instantiated; or while creating the new Transformer object; or while setting the output property if the property is not supported, and is not qualified with a namespace; or while transforming if an unrecoverable error occurs during the transformation.

Action

Contact IBM support.

CTGDKJ008E Could not load mapping file: *Exception message*

Explanation

This Exception could occur if the mapping file is invalid or if an Error occur while reading the mapping file.

Action

Check the mapping file and try again.

CTGDKJ009E Could not create Document Builder: *Exception message*

Explanation

An Exception occurred while creating the DocumentBuilder which satisfies the configuration requested.

Action

Check the configuration parameters and try again.

CTGDKJ010E Error on object marshalling: *exception message***Explanation**

There are several possible reasons for this Exception: while creating the DOMELEMENT, if an illegal character is in the specified name; or while setting the mapping file to be used by the marshalling Framework; or while marshalling Object as XML.

Action

Verify the syntax of the name of the root element.

**CTGDKJ011E Exception while transforming DOM to String:
*exception message*****Explanation**

There are several possible reasons for this Exception: the Function Component may have been unable to obtain the new instance of the TransformerFactory because the implementation was not available or could not be instantiated; or the Function Component may have been unable to create the new Transformer object; or the Function Component may have been unable to set the output property because the property was not supported, or was not qualified with a namespace; or the Function Component may have encountered an unrecoverable error during a transformation.

Action

Examine the exception message. Contact IBM support.

CTGDKJ012E Invalid return type specified: *return type*.**Explanation**

The return type does not match the supported return types.

Action

Provide a proper return type.

CTGDKJ101E Castor mapping file not specified.**Explanation**

The 'mappingFile' Function Component parameter is not set.

Action

Specify the mappingFile parameter.

CTGDKJ102E Invalid value for '*parameter name*': *parameter value*.**Explanation**

The return type value is incorrect.

Action

Set a proper value to the return type parameter.

CTGDKJ103E Empty attribute specification: *attributes*. **Explanation**

The received attribute is empty.

Action

Provide a valid value in the Attribute Specification.

CTGDKJ104E XPath not specified for attribute: *attribute name*. **Explanation**

The received attribute value is not correct.

Action

In the Attribute Specification provide a valid value.

CTGDKJ105E Could not load mapping file: *exception message* **Explanation**

An error occurred while trying to load mapping file. The file is invalid.

Action

Provide a valid mapping file and try again.

CTGDKJ106E Could not create Unmarshaller: *exception message* **Explanation**

An error occurred while trying to create a new Unmarshaller object. A possible reason for the error is when an invalid mapping is used for creating the Unmarshaller object.

Action

Try with valid mapping for creating the Unmarshaller object.

CTGDKJ107E Unable to create DOM Document from XML String: *exception message* **Explanation**

An error occurred while trying to create Document from XML String. There are several possible reasons: - while creating a new DocumentBuilder if a DocumentBuilder cannot be created which satisfies the configuration requested. -

while parsing the Document with the given InputSource if an Input/Output error occurs or if a parse error occurs.

Action

If the exception is during the parse of the xmlString, correct the XML element given as String object and try again.

CTGDKJ108E No input data was passed to the Function Component. The Function Component was passed the following expected type: *input type*.

Explanation

No data is provided to the Function Component.

Action

Try with input data matching the expected type.

CTGDKJ109E Special type '*special type attribute*' with attribute:*attribute name* is not supported.

Explanation

The specified special type of attribute in the Attribute Specification section of the Function Component is not supported.

Action

Change the type of the attribute in the Attribute Specification section of the Function Component and try again.

CTGDKJ110E Unable to select attribute from XML at path: *attribute XPath* Exception occurred: *Exception message*

Explanation

An error occurred while trying to select a nodelist with the given prefix.

Action

Specify a valid XPath variable of the attribute in the Attribute Specification section of the Function Component and try again.

CTGDKJ111E Error on unmarshalling: *exception message*

Explanation

There are several possible reasons for this error: if an error occurred during the unmarshalling process; or if there is a validation error; or while creating the DOMELEMENT if there is an invalid character; while appending the child node if the parent node is of a type that does not allow children of the type of the newChild node; or if the parent node is created from a different document than the one which created the child node while appending the child node; or the parent node is read-only or if the previous parent of the node being inserted is read-only while appending the child node.

Action

Verify that no invalid characters are used or contact IBM support.

CTGDKJ112E Could not select XML elements: *Exception message*

Explanation

An error occurred while trying to select a nodelist with the given prefix.

Action

The used prefix is '*'. Contact IBM support.

CTGDKJ113E Invalid input data passed. The Function Component was passed the following expected type: *input type*. Exception occurred: *Exception message*.

Explanation

Invalid data is provided to the Function Component.

Action

Try with input data matching the expected type.

CTGDJA001E The situation.reasoningScope attribute has not been defined.

Explanation

The user has not mapped a value for attribute situation.reasoningScope.

Action

Map value for the attribute situation.reasoningScope.

CTGDJA002E The value of attribute situation.categoryName is not defined.

Explanation

The user has not mapped a value for attribute situation.categoryName.

Action

Map value for the attribute situation.categoryName.

CTGDJA003E The value of attribute RepeatCount is invalid.

Explanation

The user has mapped an invalid value for attribute RepeatCount in output map.

Action

Map a numerical value for attribute RepeatCount.

CTGDJA004E The value of attribute ElapsedTime is undefined.**Explanation**

The user has not mapped a value for attribute ElapsedTime in output map.

Action

Map a numerical value for attribute ElapsedTime.

CTGDJA005E The value of attribute ElapsedTime is invalid.**Explanation**

The user has mapped an invalid value for attribute ElapsedTime in output map.

Action

Map a numerical value for attribute ElapsedTime.

CTGDJA006E The value of attribute Severity is invalid.**Explanation**

The user has mapped a non-numerical value for attribute Severity in the output map.

Action

Map a numerical value between 0 and 70 for attribute Severity.

CTGDJA007E The value of attribute Priority is invalid.**Explanation**

The user has mapped a non-numerical value for attribute Priority in the output map.

Action

Map a numerical value between 0 and 100 for attribute Priority.

CTGDJA008E The value of attribute SequenceNumber is invalid.**Explanation**

The user has mapped a non-numerical value for attribute SequenceNumber in the output map.

Action

Map a numerical value for attribute SequenceNumber.

CTGDJA009E The value of attribute situation.categoryName is invalid: *Value of attribute*

Explanation

The user has mapped an invalid value for attribute situation.categoryName in the output map.

Action

Refer to the documentation for defined values for attribute situation.categoryName.

CTGDJA010E The argument being passed to perform method is invalid.

Explanation

The user has mapped an invalid value as an argument for the perform method .

Action

An argument of type Entry must be passed to the perform method.

CTGDJA011E A null value cannot be passed as an argument to the perform method.

Explanation

The user has mapped an invalid value as an argument for the perform method.

Action

An argument of type Entry must be passed to the perform method.

CTGDJA012E Both of the attributes 'event' and 'eventXml' have invalid or undefined values.

Explanation

The user has mapped an invalid value or has not mapped any value.

Action

Either a valid object of type "org.eclipse.hyades.logging.events.cbe.CommonBaseEvent" must be set to the "event" attribute or a valid XML String representation of a CBE object must be set to the "eventXml" attribute.

CTGDJA013E The 'eventXml' attribute does not contain a valid XML as a CBE object representation. Reason: *Exception Message*

Explanation

The user has mapped an invalid XML String.

Action

A valid XML String must be set to the "eventXml" attribute.

CTGDJA014E Only one of the attributes 'event', 'eventXml' must be set.

Explanation

The user has mapped both attributes ("event" and "eventXml") at the same time.

Action

A Single attribute is expected to be mapped (either "event" or "eventXml").

CTGDJA015E Could not retrieve a CBE object from the XML specified in 'eventXml' attribute.

Explanation

The user has mapped an invalid XML String.

Action

A valid XML String must be set to the "eventXml" attribute.

CTGDKL101E Error parsing XML. An invalid XML representation of a CBE object. Exception occurred:

ExceptionMSG

Explanation

The input XML does not comply with the CBE specification.

Action

Correct the input XML so it be valid against the CBE schema.

CTGDKL103E Error generating a CBE object from the specified attributes.

Explanation

Some of the required attributes are missing or incorrect.

Action

Refer to the documentation to check the required attributes.

CTGDKL106E Unable to validate the CBE object in the 'event' attribute. Exception occurred: *ExceptionMSG*

Explanation

The user has mapped an invalid CBE object.

Action

Map a valid CBE object.

CTGDKL107E The CBEParse writer is not initialized.

Explanation

The CBEParse cannot write due to writer initialization failure.

Action

Check the configuration of the component which is using the CBEParse.

CTGDIH201E Parameter '*param name*' was initialized with value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH202E Parameter '*param name*' is not provided.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH203E Unsupported mode: '*mode*' for selected artifact type: '*type name*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH204E An exception occurred while trying to close the database connection: *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH205E No Entry provided.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH206E Incompatible classification: expected - '*expected class name*' , found - '*actual class name*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH207E Unable to create '*instance*' instance from an input Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH208I Search Query for '*instance*' : '*searchQuery*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH209E Actual CI already exists for GUID - '*guid*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH210E Config Item already exists for GUID - '*guid*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH211E Relation already exists: '*relation*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH212E CI Relation already exists: '*ciRelation*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH213E Could not get the classification for the selected class type '*classType*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ551E Close IdML Function Component accepts only a IBM Security Directory Integrator Entry as input. **Explanation**

At the beginning of the Function Component's execution cycle the input data passed was not a IBM Security Directory Integrator Entry.

Action

Close IdML Function Component expects only a IBM Security Directory Integrator Entry as input. Check the AL logic and try again.

CTGDJZ552E The book '*book name*' is already closed or has never been created.

Explanation

Close IdML Function Component always attempts to close its configured book. If its is executed repeatedly in the Flow of the AssemblyLine for the same book name, an error will occur.

Action

Check the AL logic and try again.

CTGDJZ553I Close IdML Function Component will work with book: '*book name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ554I The name of the currently used book '*book name*' has been overridden to '*new name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ555I Close IdML Function Component closed book '*book name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ556E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the Close IdML Function Component and must be provided.

Action

Provide a value for this parameter.

CTGDIX001E The 'commandLine' parameter must be set to use the Command Line Connector.

Explanation

The required parameter `commandLine` was not specified in the Command Line Connector.

Action

Specify the `commandLine` parameter in the Connector.

CTGDIX002E Unable to run a command. The 'commandLine' parameter must be set to use the Command Line Connector.

Explanation

The required parameter `commandLine` was not specified in the Command Line Connector.

Action

Specify the `commandLine` parameter in the Connector.

CTGDIZ701I Running WSDL2Java...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ702I WSDL2Java finished running.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ703I Compiling java files...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ704I Creating JAR file...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ705I Purging java files...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ706I Purging class files...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ707I Deleting JAR file...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ708I Deleting '*file name*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ709I Creating directory '*directory path*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ710E Could not generate Java source files from the specified WSDL. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIZ711E Could not compile generated Java source files. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIZ712E Could not generate JAR file from the compiled Java class files. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIZ713I Command part at index *index*: '*command part*'.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ714I Compile argument at index *index*: '*argument*'.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ715I JAR argument at index *index*: '*argument*'.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJW001I The column separator is set to '*separator*'.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJW002I Parser will use provide column names: '*column names*'.
Explanation

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJW003I Parser will use first input line for column names.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJW004I No column names provide. Will use first output entry for column names: '*column names*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJW005I A long line was encountered at line number '*line number*'. The line is '*number of bytes*' bytes and the line contents are '*line*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ701I The Class Type *param name* has value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ702I Use a DIS system for the needed meta-data: '*use dis*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ703I The parameter *param name* was initialized with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ704E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the Data Cleanser Function Component and must be provided.

Action

Provide a value for this parameter.

CTGDJZ705E The Data Cleaser Function Component accepts only a IBM Security Directory Integrator Entry as input.

Explanation

At the beginning of the Function Component's execution cycle the input data passed was not a IBM Security Directory Integrator Entry.

Action

The Data Cleaser Function Component expects only a IBM Security Directory Integrator Entry as input. Check the AL logic and try again.

CTGDIZ901E Delta key attribute not defined.

Explanation

In order for the Delta mechanism to be able to uniquely identify each entry, a unique attribute must be specified to use as the Delta key.

Action

Verify the Delta configuration.

CTGDIZ902E The perform method of the Function Component was not passed an object of type com.ibm.di.entry.Entry. This object is not a valid parameter to pass to the perform method.

Explanation

A parameter of type different from com.ibm.di.entry.Entry was passed to the perform method.

Action

Verify that the parameter being manually passed to the perform method of a Function Component (for example from a Script Component) is an object of type com.ibm.di.entry.Entry.

CTGDIZ903E DELTA: Duplicate delta key: *key value*.

Explanation

The sequence id of the entry with the specified key is not consistent with the sequence id for the Delta Table from the Delta Systable.

Action

Verify the Delta Store is not corrupted and if the problem persists contact IBM support.

CTGDIZ904I DELTA: new entry, key = *key value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ905I DELTA: modified entry, key = *key value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ906I DELTA: No changes, key = *key value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ907I DELTA: skip next unchanged entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ908I DELTA: Iterating through deleted entries.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ909I DELTA: get next deleted entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ910I DELTA: Remove deleted entry, key = *key value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ911W DELTA: The Key Attribute '*attribute name*' contains more than one value. *Number of values values were found*.

Explanation

A key Attribute should contain only one value.

Action

Make sure the key Attribute(s) contain only one value.

CTGDIZ912I DELTA: Entry without value for key attribute = *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ913W Delete table *table name*?

Explanation

The delete operation will delete the delta table and commit the change. The operation is permanent and there is no possible rollback of this transaction.

Action

Confirm if the delta table is to be deleted and proceed with the operation.

CTGDIZ914I Table *table name* deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ915I Using Derby Delta: *tableName=table name, database=database URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ916I Delta component using unique key *key name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN401I Initialization in progress...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN402E An exception occurred while creating the Message Queue: *exception*

Explanation

An internal Domino server error may have occurred.

Action

See the error message for more information.

CTGDKN403E An exception occurred while opening the Message Queue: *exception*

Explanation

An internal Domino server error may have occurred.

Action

Check the exception message for more information.

CTGDKN404E An exception occurred: *exception*

Explanation

An unexpected exception has occurred.

Action

Check the exception message for more information.

CTGDKN405I Terminating...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN406I Terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN407E The Password Store is not ready. No password synchronization will be performed on this agent run.

Explanation

The Password Store is not available at the moment and no password changes can be sent.

Action

Verify the Password Store is running and try again.

CTGDKN408I Agent search returned no documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN409I Agent search returned *number of documents* documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN410E An unexpected Lotus Notes exception occurred.

Explanation

An unexpected exception has occurred.

Action

Check the error message for more information.

CTGDKN411E An unexpected exception occurred.

Explanation

An unexpected exception has occurred.

Action

Checkout the error message for more information.

CTGDKN412I Processing admin request with UNID: 'UNID'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN413I Unable to obtain parent document for admin log with UNID: 'UNID'. The password change will not be stored.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN414I Missing or hashed password in admin request with UNID 'UNID'. Skipping this admin request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN415I Missing FullName in admin request. Skipping this request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN416I The password of user '*user name*' is successfully stored.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN417I The password of user '*user name*' could not be stored.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN418E Unable to mark admin request '*UNID*' as processed.

Explanation

An error has occurred and the admin request could not be processed on this cycle.

Action

Check the NotesException following this error message.

CTGDKN419I Will assume the objects [*object name*;] and [*object name*] are equal.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN420E Unable to retrieve password document from helper database.

Explanation

An error has occurred while retrieving a document.

Action

Check the auxiliary message of the exception for more details.

CTGDKN421E The field '*field ID*' is missing from a document in the '*database name*' database.

Explanation

See message.

Action

Check if the secret key is imported in the Server ID file.

CTGDKN422I Could not save success indicator for Notes client.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN423I Will reject all changes to the Person document for user '*user name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN424E An error has occurred while retrieving the Person document.

Explanation

See the error message.

Action

Check the auxiliary message of the exception for more details.

CTGDKN425E Could not read data from the Person document.

Explanation

An error has occurred while reading a document.

Action

Check the auxiliary message of the exception for more details.

CTGDKN426E Could not remove custom fields in the Person document.

Explanation

An error has occurred while removing document fields.

Action

Check the auxiliary message of the exception for more details.

CTGDKN427E Cannot synchronize password. User identifier field '*field ID*' is empty.

Explanation

See message.

Action

No help provided.

CTGDKN428I User identifier is NULL. Will not synchronize password.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN429I Searching for UNID with filter: '*filter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN430I Missing UNID. Password will not be synchronized.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN431I Will use the Distinguished Name for password synchronization.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN432I Will prefix Distinguished Name with: '*prefix name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN433I Found UNID: '*UNID*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN434I Synchronizing User ID: '*user name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN435I Domino Plug-in/Proxy authentication successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN436I Domino Plug-in/Proxy authentication failed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN437E Could not connect to localhost on port *port number*.

Explanation

The Domino plug-in was unable to connect to the Java Proxy. The Java Proxy may not be running.

Action

Ensure the Java Proxy is running and try again.

CTGDKN438E The file '*file name*' could not be found.

Explanation

The specified configuration file must be placed in the Domino Data directory.

Action

Ensure the configuration file is available.

CTGDKN439E The file '*file name*' could not be read.

Explanation

The file is probably read-protected.

Action

Ensure the user that runs the Domino Server has enough privileges to read the configuration file.

CTGDJE002E The Notes Thread not alive. Domino Change Detection Connector cannot execute the needed command against the Domino Server without an active Notes Thread.

Explanation

See message.

Action

Contact IBM support.

CTGDJE003E Fatal Error while executing command against Domino Server: *exception*

Explanation

See message.

Action

Review the message returned from the Domino Server to see how to respond.

CTGDJE004I Domino Change Detection Connector is restarting.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE005I Checkpoint/restart is only supported in 'After read' and 'End of cycle' mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE006E No documents in the list of UnIDs, or the list is null.

Explanation

The method `getCurrentDocumentUnID` failed trying to get the UnID of the current document from the document info returned by the native layer.

Action

Review the exception to find further details on the error.

CTGDJE007E No documents in the list of UnIDs, or the list is null.

Explanation

The method `getCurrentDocumentNoteID` failed trying to get the NoteID of the current document from the document info returned by the native layer.

Action

Contact IBM support.

CTGDJE008E No documents in the list of UnIDs, or the list is null.

Explanation

The method `getCurrentDocumentState` failed trying to get the state (normal or deleted) of the current document from the document info returned by the native layer. This is an internal error.

Action

Contact IBM support.

CTGDJE009E Connector already initialized. You must terminate it before initializing again.

Explanation

An attempt was made to initialize the Domino Change Detection Connector after it was already initialized.

Action

Verify that the Connector is terminated before attempting to initialize the Connector again.

CTGDJE010E Connector was unable to initialize local Notes session to Domino Server. Exception encountered: *exception*

Explanation

The Domino Change Detection Connector could not create a local Notes session to the Domino Server.

Action

Verify that the Connector parameters are configured correctly and that the Domino Server is running. Also, review the exception in the message for further information on why the error occurred.

CTGDJE011I Enabling SSL flag since 'iioPSSL' was not set to true or false.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE012E NotesException encountered trying to create a session with the Domino Server: Class Name='class name', Exception=exception

Explanation

The Domino Change Detection Connector encountered an exception while trying to create a session with the Domino Server and was unable to continue.

Action

Verify that the Domino Server being queried is still running and that the connection information in the Domino Change Detection Connector has been configured properly.

CTGDJE013I Successfully connected to Domino Server: Name='server name', Version='version number', Platform='operating system'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE014E Domino Change Detection Connector unable to open database 'database name' on server 'server name'.

Explanation

The Domino Change Detection Connector was unable to connect to the specified database on the Domino Server.

Action

Verify that the correct database name was specified for the Domino Change Detection Connector and that the connection information in the Domino Change Detection Connector has been configured properly.

CTGDJE015E Domino Change Detection Connector unable to open database 'database name' on server 'server name'.

Explanation

The Domino Change Detection Connector was unable to connect to the specified database on the Domino Server.

Action

Verify that the correct database name was specified for the Domino Change Detection Connector and that the connection information in the Domino Change Detection Connector has been configured properly.

CTGDJE016E Could not initialize the Domino Change Detection Connector. Exception occurred: *exception*

Explanation

Failed to initialize the Domino Change Detection Connector.

Action

See exception in message for information on how to respond.

CTGDJE017W Domino Change Detection Connector could not terminate the local Notes session. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJE018W Domino Change Detection Connector could not close the IIOP objects. Exception occurred: *id=id exception=exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJE020E The 'dominoServerIP' parameter must be set to use the Domino Change Detection Connector.

Explanation

The required parameter dominoServerIP was not specified in the Domino Change Detection Connector.

Action

Specify the dominoServerIP parameter in the Connector.

CTGDJE021E The 'userName' parameter must be set to use the Domino Change Detection Connector.

Explanation

The required parameter userName was not specified in the Domino Change Detection Connector.

Action

Specify the userName parameter in the Connector.

CTGDJE022E The 'database' parameter must be set to use the Domino Change Detection Connector.

Explanation

The required parameter database was not specified in the Domino Change Detection Connector.

Action

Specify the database parameter in the Connector.

CTGDJE024E The 'deliveryMode' parameter was set to an invalid value: '*parameter value*'.

Explanation

The required parameter deliveryMode was specified in the Domino Change Detection Connector but the value was not valid

Action

Specify a valid value for the deliveryMode parameter in the Connector.

CTGDJE025E The 'systemStoreKey' parameter must be set to use the Domino Change Detection Connector.

Explanation

The required parameter systemStoreKey was not specified in the Domino Change Detection Connector.

Action

Specify the systemStoreKey parameter in the Connector.

CTGDJE026W The 'sleepInterval' parameter set to an invalid value '*parameter value*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid sleepInterval parameter in the Connector if the default value is not wanted.

CTGDJE027W The 'timeout' parameter set to an invalid value '*parameter value*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid timeout parameter in the Connector if the default value is not wanted.

CTGDJE028E Could not read synchronization state from System Store. Exception occurred: *exception*

Explanation

The method selectEntries failed trying to read the start synchronization state.

Action

Review the exception to find further details on the error.

CTGDJE029E Could not retrieve state from persistent store. Exception occurred: *exception*

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDJE030E The System Store key not found and 'Start At' parameter not specified.

Explanation

See message.

Action

Specify a valid 'Start At' parameter in the Connector.

CTGDJE031I Start at start of data. Will perform full synchronization.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE032I Start at end of data. Will listen for new changes only.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE033I Start at specific date. Will use start date: *date*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE034E Invalid Start At value: *date*.**Explanation**

See message.

Action

Specify a valid 'Start At' parameter in the Connector.

CTGDJE035E The System Store Entry does not contain the 'SYNC_TIME' attribute.**Explanation**

Either the System Store database is corrupted or an internal error occurred.

Action

Make sure the System Store database is not corrupted, before contacting IBM support.

CTGDJE036E Invalid value of the '*PROP_SYNC_TIME*' System Store Entry attribute: *attrValue*.**Explanation**

An internal error has occurred.

Action

Contact IBM support.

CTGDJE037E The System Store Entry attribute 'SYNC_TIME' is of unknown type: *class name*.

Explanation

An internal error has occurred.

Action

Contact IBM support.

CTGDJE038I Start date for synchronization: *date*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE039I Verify reported UnIDs are processed on previous runs.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE040I Timeout waiting for next changed entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE041E UnID list is null.

Explanation

Connector tries to retrieve the next valid document from the list of changed document UnIDs, the list is null. This is an internal error.

Action

Contact IBM support.

**CTGDJE042E Could not retrieve document with UnID
'unID'.****Explanation**

Domino Change Detection Connector could not retrieve document with specific UnID.

Action

Check database permissions.

CTGDJE043I Check database permissions.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJE044I If the document is already deleted, it will be
reported on the next poll.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJE045E Could not read document's last modification
date. Exception occurred: id=id: exception=exception****Explanation**

Failed to verify whether the document passed has not been processed on previous Connector's runs.

Action

Review the exception to find further details on the error.

CTGDJE046E Invalid end date value: *time stamp***Explanation**

The 'UnID' parameter read from the Property Store has an invalid value.

Action

Make sure the Property Store is not corrupted, before contacting IBM support.

CTGDJE047E Error on closing the store: *exception*
Explanation

Failed to delete all stored document UnIDs from the System Store.

Action

Inspect the error message for more detailed information on the error.

CTGDJE048E Could not clear Property Store table:.
Exception occurred: *exception***Explanation**

Failed to delete all stored document UnIDs from the System Store.

Action

Review the exception to find further details on the error.

CTGDJE049I Stores the synchronization state in the System Store. Start date is '*date*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE050I Check docs is set to '*UnIDs*' UnID.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE051E Could not store the synchronization state in the System Store. Exception occurred: *exception*
Explanation

Failed to store the synchronization state in the System Store.

Action

Review the exception to find further details on the error.

**CTGDJE052E Could not terminate the IIOP session.
Exception occurred: id=*ID*, exception=*exception***

Explanation

Failed to terminate the IIOP Notes sessions.

Action

Review the exception to find further details on the error.

**CTGDJE053E Could not terminate the local Notes session.
Exception occurred: *exception***

Explanation

Failed to terminate the local Notes sessions.

Action

Review the exception to find further details on the error.

**CTGDJE054E Error on stopping internal thread. Exception
occurred: *exception***

Explanation

The method terminate failed trying to stop the internal thread.

Action

Review the exception to find further details on the error.

**CTGDJE055E Exception while closing the System Store
table: *exception***

Explanation

Failed to close the connection to the System Store.

Action

Review the exception to find further details on the error.

**CTGDJE056E Could not retrieve created date for the
document '*document ID*'. Exception occurred: id=*ID*,
exception=*exception***

Explanation

Failed to set the creation date attribute.

Action

Review the exception to find further details on the error.

CTGDJE057I Will assign a value of NULL to attribute '\$\$DateCreated'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE058E Could not retrieve last modified date for document '*document ID*'. Exception occurred: id=*ID*, exception=*exception*

Explanation

Failed to set the modification date attribute.

Action

Review the exception to find further details on the error.

CTGDJE059I Will assign a value of NULL to attribute '\$\$DateModified'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE060I The item '*item name*' is of type ATTACHMENT and will not be added to the Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE061I Added a new attribute to the entry: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE062I The item type is *item type*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE063E Could not retrieve item values. Exception occurred: *id=ID, exception=exception*

Explanation

The Notes API could not recognize the item value.

Action

Contact IBM support.

CTGDJE064I Value(s) for attribute '*attribute name*' will be skipped.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE065I The data is: *value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJE066E Could not convert Notes date to Java date.
Exception occurred: id=*ID*, exception=*exception***

Explanation

Connector failed to convert Domino dates to Java dates.

Action

Review the exception to find further details on the error.

**CTGDJE067I Date value for attribute '*attribute name*'
will be skipped.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJE068E Could not determine change type for document
with UNID '*document ID*'. Exception occurred: id=*ID*,
exception=*exception***

Explanation

Connector cannot determine the type of the added document.

Action

Review the exception to find further details on the error.

**CTGDJE069I Will assign change type 'unknown' to document
'*document ID*'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJE070E Native call to `getModifiedNotes` method
returned NULL.**

Explanation

Connector failed to retrieve the UNIDs of all changed Domino documents.

Action

Contact IBM support.

CTGDJE071E Could not parse end date value: *date*.**Explanation**

An internal error has occurred.

Action

Contact IBM support.

CTGDJE072E Invalid string date format passed: *date string*.**Explanation**

An internal error has occurred.

Action

Contact IBM support.

CTGDJE073E Exception occurred while retrieving document with UnID '*unID*': id=*ID*, exception=*exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDJE074I Local Client Session successfully created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE075E Connector unable to create Local Client Session. Exception encountered: *exception detail message string***Explanation**

The Domino Change Detection Connector could not create a Local Client session to the Domino Server.

Action

Verify that the Connector parameters are configured correctly and that the Domino Server is running. Also, review the exception in the message for further information on why the error occurred.

CTGDJE076I IIOP Session successfully created. The specified IOR string is used. SSL is turned on.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE077E Connector unable to create IIOP Session with the configured IOR string. SSL is turned on. Exception encountered: *exception detail message string*

Explanation

The Domino Change Detection Connector could not create a IIOP Session to the Domino Server.

Action

Verify that the Connector parameters are configured correctly and that the Domino Server is running. Also, review the exception in the message for further information on why the error occurred.

CTGDJE078I IIOP Session successfully created. SSL is turned on.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE079E Connector unable to create IIOP Session with SSL turned on. Exception encountered: *exception detail message string*

Explanation

The Domino Change Detection Connector could not create a IIOP Session to the Domino Server.

Action

Verify that the Connector parameters are configured correctly and that the Domino Server is running. Also, review the exception in the message for further information on why the error occurred.

CTGDJE080I IIOP Session successfully created. SSL is turned off.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE081E Connector unable to create IIOP Session with the configured IOR string. SSL is turned off. Exception encountered: *exception detail message string*

Explanation

The Domino Change Detection Connector could not create a IIOP Session to the Domino Server.

Action

Verify that the Connector parameters are configured correctly and that the Domino Server is running. Also, review the exception in the message for further information on why the error occurred.

CTGDJE082I IIOP Session successfully created. SSL is turned off.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE083E Connector unable to create IIOP Session. SSL is turned off. Exception encountered: *exception detail message string*

Explanation

The Domino Change Detection Connector could not create a IIOP Session to the Domino Server.

Action

Verify that the Connector parameters are configured correctly and that the Domino Server is running. Also, review the exception in the message for further information on why the error occurred.

CTGDJE084W The '**systemStoreKey**' parameter was not specified in the Domino Change Detection Connector. The Connector will not persist state.

Explanation

The parameter `systemStoreKey` was not specified in the Domino Change Detection Connector.

Action

Specify the `systemStoreKey` parameter in the Connector to enable state persistence.

CTGDJE085W The Document item *name of document item* of type *type of document item* was not handled.

Explanation

The Notes API failed to process this document item's values.

Action

Contact IBM support.

CTGDJE086I Notes API exception ID: *ID of Notes API exception* Notes API exception text: *text of Notes API exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE087E The following exception occurred during Connector's initialization: *exception*

Explanation

Needed jar file, that is `Notes.jar` or `NCSO.jar` is not added to the classpath of IBM Security Directory Integrator.

Action

Add the needed jar file to the classpath of IBM Security Directory Integrator.

CTGDJE088E The following exception occurred during Connector's termination: *exception*

Explanation

Needed jar file, that is Notes.jar or NCSO.jar is not added to the classpath of IBM Security Directory Integrator.

Action

Add the needed jar file to the classpath of IBM Security Directory Integrator.

CTGDJE089E Failed to convert the port parameter value to a numeric type: *parameter value*.

Explanation

The specified value for the parameter does not have the appropriate format.

Action

Specify value with appropriate format for the httpPort parameter.

CTGDJE090I The Delivery Mode parameter is removed since IBM Security Directory Integrator 6.1.1. Refer to the IBM Security Directory Integrator documentation for more information.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJE091I Sorting changed documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE092W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used.

Explanation

See message.

Action

Specify the iterator state key if you want the state of the changelog connector to be saved.

CTGDKC001E Connector Notes Thread not alive. Cannot perform.

Explanation

The user tries to execute operation after the Connector has been terminated.

Action

Check the business logic of the solution, so that the Connector is not used after it has been terminated.

CTGDKC002E Failed to execute the command. NotesException occurred: *exception*

Explanation

The Notes Run time might be not initialized or error has occurred during operation execution.

Action

Check that Security Directory Integrator and the external systems are configured correctly.

CTGDKC003E Fatal error while executing the command. Exception occurred: *exception*.

Explanation

This error occurs in result of class linkage, thread or virtual machine error.

Action

Review the exception to find further details on the error.

CTGDKC004E Connector already initialized. You must terminate it before initializing again.

Explanation

The user tries to initialize the Connector, for example through script, that has been already initialized.

Action

Check the values of the configuration parameters and the business logic of your solution.

CTGDKC005W Exception occurred while terminating:
exception

Explanation

The user may have loaded a Connector without initializing it. For example through the getConnector method.

Action

Check the values of the configuration parameters and the business logic of the solution.

CTGDKC009I Will use full-text search in Iterator and Lookup modes.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC010I Will use regular database search in Iterator and Lookup modes.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKC012I Successfully connected to Domino Server:
Name='server name', Version='version number',
Platform='operating system'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC013E Unable to open 'Name and Address Book' database: *database name*.

Explanation

The configuration parameter, pointing to the server where the database is or the database name may be mistyped or the user may have not rights to access the database.

Action

Verify the database exists and is available as well as check the other configuration parameters of the Connector.

CTGDKC014I Successfully opened 'Name and Address Book' database *database name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC015I The Database *database name* is full-text indexed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC016I The database *database name* is not full-text indexed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC017E Unable to open Admin database: *database name*.

Explanation

The user may have not rights to access the database or the configuration parameter, pointing to the server where the database is or the database name may be mistyped.

Action

Check the configuration of the Connector as well as that the user have rights to access the database.

CTGDKC018I Successfully opened the Administration Requests Database: *database name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC019E Unable to select entries. The View 'People' was not found.

Explanation

If the database is local, both the public and personal views and folders are returned. If the database is on server, only public views and folders are returned.

Action

Check that the view you look up is present and is not forbidden to be returned. Contact IBM support if the problem still exists.

CTGDKC020E Could not filter documents. NotesException occurred: ID=*ID*, Error Text=*error text*

Explanation

Domino server allows to restrict the operations a user can perform. If the full-text filter is mistyped, no documents will be returned.

Action

Check configuration of the Connector and security settings of the Domino server. Contact IBM support if the problem still exists.

CTGDKC021I View search returned NULL.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC022I View search returned *number of documents* documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKC023E Could not perform database search.
NotesException occurred: ID=*ID*, Error Text=*error text***

Explanation

Domino server allows to restrict the operations a user can perform. The user might have not rights to search the database.

Action

Check the security settings of the Domino server. Contact IBM support if the problem still exists.

CTGDKC024I Database search returned NULL.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC025I Database search returned *number of documents* documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKC026E Error retrieving next user Document.
NotesException occurred: ID=*ID*, Error Text=*error text***

Explanation

If one creates more than one object to represent the same Domino element, recycling one recycles all. Results are undefined if one attempts to use a recycled object.

Action

Check the business logic of the solution and contact IBM support if the problem still exists.

CTGDKC027E Unable to find the entry. The View 'People' was not found.

Explanation

Domino server allows to restrict the operations a user can perform. The user might have not proper rights.

Action

Check the security settings and contact IBM support if the problem still exists.

CTGDKC028I Full Text Search view for: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC029I Full Text Search returns *number of documents* documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC030I Database search with formula: *formula*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC031I Database search returned NULL in the findEntry method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC032I Database search returned *number of documents* documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC033E Given Document is NULL. Cannot build Entry.

Explanation

Null is returned if the document collection that results from database search contains no documents.

Action

Check the configuration of the Connector.

CTGDKC034I Document vector of items is NULL.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC035I Building entry with all items: *items*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC036I Item '*item name*' is of type ATTACHMENT will not be added to Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC037I New Attribute: *attribute name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC038I item type: *item type*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC039I Item values: *item values*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC040E Unable to modify the entry. The document not found or multiple documents found.**Explanation**

Internal error has occurred.

Action

Contact IBM support.

CTGDKC041E Unable to modify the entry. The user FullName not found. Cannot set user's access type.**Explanation**

The user FullName has no value or the value is numeric or date-time.

Action

Contact IBM support.

CTGDKC042E Entry Attribute '*attribute name*' is required when creating a mail database using a custom mail template.

Explanation

The MailFile attribute is mandatory to be present in the entry.

Action

Ensure that the entry has MailFile attribute with proper value.

CTGDKC043E Unable to add entry. Cannot build search criteria to find user document after registration. User document not updated.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC044E Unable to add the entry. Cannot update user document after registration. User document not found or multiple documents found.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC045E Unable to add the entry. Cannot create person document. The required Attribute '*attribute name*' is missing or empty.

Explanation

The LastName attribute is mandatory to be present.

Action

Ensure that the LastName attribute is present in the entry and has proper value.

CTGDKC046E Unable to add the entry. Cannot create new user document.

Explanation

Domino server allows to restrict the rights of a user.

Action

Check that the security settings are proper and contact IBM support if the problem still exists.

CTGDKC047E Unable to delete the entry. The document not found or multiple documents were found.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC048E Unable to delete the entry. The user FullName not found. Cannot delete user.

Explanation

The item FullName has no value or the value is numeric or date-time.

Action

Contact IBM support.

**CTGDKC049I Will find person document using formula:
formula.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC050I Updating attribute in document: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC051E Could not hash the http password. Exception occurred: *exception*

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC052I Updating password value in document: *password*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC053I Updating value in document: *attribute value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC054I Updating values in document: *attribute values*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC055E Cannot update the document. The document cannot be saved.

Explanation

Someone else might be editing the document at the moment.

Action

Check the business logic of the document and contact IBM support if the problem still exists.

CTGDKC056I FullName criteria element value changed from '*FullName*' to '*FullName*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC057I FullName Attribute changed from '*FullName*' to '*FullName*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC058W Could not recycle Domino object. Exception occurred: *exception*

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC059E NotesException occurred while performing Domino Action: ID=*ID*, Error Text=*error text*.

Explanation

Required attribute, needed for the operation being executed, is missing.

Action

Ensure all the required attributes are available in the entry and have proper values.

CTGDKC060E NotesException occurred while trying to reset and extract the data: ID=*ID*, Error Text=*error text*.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC061E Cannot perform Domino Action: *error message*.

Explanation

Domino server allows to restrict the actions a user can do.

Action

Check that the security settings have proper values and contact IBM support if the problem still exists.

CTGDKC062E Cannot perform Domino Action. NotesException occurred: ID=*ID*, Error Text=*error text*.

Explanation

Domino server allows to restrict the actions a user can do.

Action

Check that the security settings have proper values and contact IBM support if the problem still exists.

CTGDKC063E Unable to clear attributes. NotesException occurred: ID=*ID*, Error Text=*error text*.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC064E Cannot perform Domino Action: *error message*.

Explanation

Review the message for explanation why the operation cannot be performed.

Action

Contact IBM support.

CTGDKC065E Unable to execute Domino Action. NotesException occurred: ID=*ID*, Error Text=*error text*.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC066E The `isDenyGroupMember` method was passed NULL for the Deny Group Document parameter.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC067E The `isDenyGroupMember` method was passed NULL for the User Name parameter.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC068E Deny Access Group '*group name*' does not exist.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKC069E Cannot instantiate UserAccess. The Connector's Notes session is NULL.

Explanation

The Connector did not succeed to create session to Domino server.

Action

Check that the needed configuration for creating session is set up and contact IBM support, if the problem still exists.

CTGDKC070E Cannot instantiate UserAccess. The Connector's database is NULL.

Explanation

Domino allows to restrict the actions a user can perform. Or the database may not be present on the specified server.

Action

Check the security settings and the configuration of the Connector.

CTGDKC071E Unable to enable the user. Could not find view
'view name'.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC072E Unable to enable the user. Could not find view
'view name'.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC073E Unable to enable the user. NotesException
occurred: ID=ID, Error Text=error text.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC074E Unable to disable user. Could not find view
'view name'.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC075E Unable to disable user. Could not find view
'view name'.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC076E Unable to disable user. Deny Access Group 'group name' does not exists.

Explanation

The specified Deny Access Group does not exist.

Action

Specify an existing Deny Access Group.

CTGDKC077E Unable to disable user. Deny Access Group 'group name' does not exists.

Explanation

The specified Deny Access Group does not exist.

Action

Specify an existing Deny Access Group.

CTGDKC078E Unable to disable user. NotesException occurred: ID=*ID*, Error Text=*error text*.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check the security settings and contact IBM support if the problem still exists.

CTGDKC079E Cannot instantiate UserDeletion. The Connector's Notes session is NULL.

Explanation

The Connector has not been initialized.

Action

Make sure the Connector is initialized.

CTGDKC080E Cannot instantiate UserDeletion. Admin database is NULL.

Explanation

The Connector has not been initialized.

Action

Make sure the Connector is initialized.

CTGDKC081E Cannot instantiate UserDeletion. The Connector's database is NULL.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check the security settings and the configuration of the Connector and contact IBM support if the problem still exists.

CTGDKC082E The UserDeletion::sendAdminRequestDeleteUser method could not create admin request document.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC083E Could not create admin request document.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC084E Cannot instantiate UserRegistration. The Connector's Notes session is NULL.

Explanation

The Connector has not created a session.

Action

Check that the required configuration of Security Directory Integrator and all the external systems are performed and contact IBM support if the problem still exists.

CTGDKC085W The UserRegistration::extractAndStoreData method could not parse 'REG_Expiration' value (*attribute value*). Will use default value of NULL.

Explanation

The value of the REG_Expiration attribute is not a valid date object.

Action

Make sure the attribute has a valid date object.

CTGDKC086E The UserRegistration::perform method could not create Registration object.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC087E Could not create Registration object.

Explanation

Domino server allows to restrict the actions a user can perform.

Action

Check that the security settings are correct and contact IBM support if the problem still exists.

CTGDKC088E Failed to convert the port parameter value to a numeric type: *parameter value*.

Explanation

The specified value for the parameter does not have the appropriate format.

Action

Specify value with appropriate format for the httpPort parameter.

CTGDKC089E NotesException encountered while trying to create a session with the Domino Server: Class Name=''*class name*', Exception=*exception*

Explanation

The Domino Users Connector encountered an exception while trying to create a session with the Domino Server and was unable to continue.

Action

Verify that the Domino Server being queried is still running and that the connection information in the Domino Users Connector has been configured properly.

CTGDKC090I IIOP Session successfully created. The specified IOR string is used. SSL is turned on.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC091I IIOP Session successfully created. SSL is turned on.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC092I IIOP Session successfully created. The specified IOR string is used. SSL is turned off.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC093I IIOP Session successfully created. SSL is turned off.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC094I Using specified 'IOR' in the connection information for opening the session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC095I Session to Domino Server is created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC096I Opening Session to Domino Server: Session Type='''Session Type''', Hostname='''Hostname''', User ID='''User ID''', Requested IIOP/SSL='''Boolean'''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC097E Unable to create local Notes thread because the lotus.domino.NotesThread class was not found in the classpath of the program. Exception occurred: *exception*

Explanation

The Domino Users Connector encountered an exception while trying to create a local notes thread. The lotus.domino.NotesThread class is needed to create the thread and it was not found in the classpath.

Action

Verify the classpath of the program and ensure the Notes.jar file is in the classpath.

CTGDKC098I Domino Users Connector's local Notes thread started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC099W Domino Users Connector could not terminate the local Notes thread. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDKC100I Domino Users Connector's local Notes thread terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC101I Missing '*attr name set type*' value

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC102I Invalid '*attr name set type*' value

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC103I Missing '*attr name deny group*' value

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC104I Group does not exist: *group name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC105I Missing user's FullName value

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC106I Invalid Delete Mail File value

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC107E Group does not exist: *group name*

Explanation

The Domino group that the user should be added to does not exist.

Action

Verify that the group name is correct and exists.

CTGDKC108E Invalid Delete Mail File value

Explanation

See message

Action

Verify the delete mail file value.

CTGDKC109I Required Attribute '*attr name*' is missing.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC110I Invalid value ('*id*') set to Attribute '*type*'. Check Connector's documentation.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC111I User Registration should not perform according to the '*attribute name*' Attribute.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKC112E Could not register user '*last name*'.

Explanation

Registration of the new user has failed.

Action

Check for errors reported during registration.

CTGDIH251E An exception occurred while trying to close the database connection: *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH252E Parameter '*param name*' is not provided.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH253E Parameter '*param name*' was initialized with value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH254E No Entry provided.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH255E Primary key not found while deleting an deployed asset!

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH256I deleteRow(...); Query: '*query*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH257E Deployed Asset with the given description already exists!: 'dpaObject'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH258I saveClassInstance(..); saved instance: 'instance'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH259E Foreign Key to parent class is null or missing. 'instanceDesc'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH260E Multiple parent instance found: keys - ['pkList'] for 'instanceDesc'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH261E Parent instance not found for: 'instanceDesc'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH262E Missing or unsupported data type: '*dataType*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH263E Missing child named '*childName*' under '*nodeName*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH264E Missing Class definition for : '*className*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH265E Primary key not specified for '*classDef*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH266E Parent class reference not found for : '*classDesc*' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH267E Parent class instance not found for : 'classDesc'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH268E Parent is null for : 'classDesc'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH269E Required property is missing: 'propName'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH270E Required reference is missing: 'refName'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH271E Multiple reference found: 'refName'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH272I getNextEntry(...) return: 'entry'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH273E Unable to create a class instance for the input Entry 'entry'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH274I addEntry(...); class instance: 'classInst'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH275E Incompatible asset class found while adding a new asset 'asset'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH276I addEntry(...); saved class instance: 'classInst'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH277I removeEntry(...); class instance: 'classInst' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH278E Missing asset class name in the input entry **'entry'**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH279I createSelectQuery(...); Query: 'query' **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM101E Failed to read DSML because input stream was not found. The input or output modes of the DSML Parser may not be valid.

Explanation

See message.

Action

Check the input and output modes of the DSML Parser.

CTGDIM102W Writing out entry but the entry is missing the DN attribute '*attribute value*'.

Explanation

See message.

Action

Verify that all entries have the DN attribute set.

CTGDIM103I Reading entry where parent node is '*node name*' and the current node is '*node name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM104I *indent* DOCUMENT node type.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM105I *indent* Node Name: *node name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM106I *indent* Node Value: *node value*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM107I *indent* Node type is not recognized.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN001E The 'url' parameter must be set to use the DSML v2 SOAP Connector.

Explanation

The required parameter url was not specified in the DSML v2 SOAP Connector.

Action

Specify the url parameter in the Connector.

CTGDIN002I Connector will use SOAP binding.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN003E Unable to initialize DSML v2 SOAP Connector because an unsupported protocol '*protocol name*' was specified.

Explanation

The specified protocol is not correct.

Action

Set the appropriate protocol. This is set in the URL specified in the URL parameter.

CTGDIN004E The putEntry method was called without the required '\$dn' Attribute in Entry.

Explanation

The mandatory \$dn attribute is not specified.

Action

Set the \$dn attribute in the Entry.

CTGDIN005I The putEntry method called with '\$dn' attribute set to '*attribute value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN006I Selecting entries with search base of ''DN'' and filter of ''filter''.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN007I Searching for entry where ''naming DN'' equals ''DN''.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN008I Searching for entry using filter ''filter''.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN009I No entries found while searching for entry in DSML v2 SOAP Connector.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0010I Single entry found while searching for entry in DSML v2 SOAP Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0011I Multiple entries found while searching for entry in DSML v2 SOAP Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0012E The modify entry operation failed because the operation was invoked without an update entry being specified.

Explanation

No update entry applied for modify entry operation because no update entry was specified.

Action

Set the update entry.

CTGDIN0013E The modify entry operation failed because it was a delta modify and no '\$dn' attribute was provided in either the conn entry or the link criteria.

Explanation

See message.

Action

Set the \$dn attribute in conn entry or link criteria.

CTGDIN0014E The modify entry operation failed because no distinguished name was found in existing entry.

Explanation

See message.

Action

Provide required distinguished name in the Entry.

CTGDIN0015I The modify entry for the modify operation is ''DN''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0016I The modify operation will rename entry ''old DN'' to ''DN''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0017E The deleteEntry method was called with no '\$dn' attribute or link-criteria.

Explanation

No specified \$dn attribute or link-criteria.

Action

Set \$dn attribute or link-criteria.

CTGDIN0018I The deleteEntry method was called with '\$dn' attribute equal to ''DN''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0019I No DSML response returned from server.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0020I No message body returned from server.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0021I No response returned from DSML server.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0022E Received a error DSML response Entry. Entry attribute information: dsml.operation attribute:*attribute value*, dsml.errorType attribute:*attribute value*, dsml.message attribute:*attribute value*.

Explanation

errorResponse accepted.

Action

No action is required.

CTGDIN0023I Received a search DSML response Entry. Entry attribute information: dsml.operation attribute:*attribute value*, dsml.resultcode attribute:*attribute value*, resultDescr:*attribute value*, dsml.error attribute:*attribute value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIN0024E Received a search DSML response Entry. Entry attribute information: dsml.operation attribute=*attribute value*, dsml.resultcode attribute:*attribute value*, dsml.resultdescr attribute:*attribute value*, dsml.error attribute:*attribute value*.

Explanation

See message.

Action

No action is required.

CTGDIN025I Connector will not use SOAP binding.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM001E Required parameter is missing: '*parameter*'.

Explanation

The specified required parameter is not set.

Action

Set the specified parameter.

CTGDIM002I The Parser is running in server mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM003I The Parser output indentation is disabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM004I Soap envelope enabled in the Parser.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM005E Failed to read DSML because input stream was not found. The input or output modes of the DSMLv2 Parser may not be valid.

Explanation

See message.

Action

Check the input and output modes of the DSMLv2 Parser.

CTGDIM006I Initializing DSML Input Document.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM007E The DSML document being parsed has no root node.

Explanation

See message.

Action

Verify that the DSML document being passed to the Parser has a root node.

CTGDIM008I Reading batchRequest.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM009I Reading batchResponse.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM010E Failed to write DSML because output stream was not found. The input or output modes of the DSMLv2 Parser may not be valid.

Explanation

See message.

Action

Check the input and output modes of the DSMLv2 Parser.

CTGDIM011I Initializing Output Document.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM012I Parser configured to resume on error.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM013I Parser will perform parallel processing.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM014I Parser configured so that responses will be unordered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM015E Message type not supported while reading an Entry: *DSML operation*.

Explanation

The message that must be parsed is not a supported type.

Action

Check documentation of supported types of messages, provide requests that has only this types.

CTGDIM016E Error while transforming DOM to string: *exception*

Explanation

An unrecoverable error occurred during the course of transforming DOM to string.

Action

Check the syntax of message in the request.

CTGDIM017W An error occurred while flushing the SOAP message: *exception*

Explanation

See message

Action

Check configuration of the server that should receive the message.

CTGDIM018I Base64 decoding attribute: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM019I Attribute *attribute anem* is specified as binary attribute but the value received is not Base64 encoded. A value of NULL will be assigned.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIM020E The required attribute 'principal' was not set for the authorization request.

Explanation

The mandatory required principal attribute is not set for the authorization request.

Action

Set the principal attribute.

CTGDIM021E The required attribute 'DN' was not set for the search request.

Explanation

The mandatory DN attribute is not set for the search request.

Action

Set the DN attribute.

CTGDIM022W Error on base64 decoding: *entry*.

Explanation

This error occurs when all binary attribute values of the Entry are decoded on base64.

Action

No action is required.

CTGDIM023E The required attribute 'DN' was not set for the modify request.

Explanation

The mandatory DN attribute is not set for the modify request.

Action

Set the DN attribute.

CTGDIM024E The required attribute 'modification' was not set for modify request.

Explanation

The mandatory modification attribute is not set for modify request.

Action

Set the modification attribute.

CTGDIM025E The required attribute 'DN' was not set for the add request.

Explanation

The mandatory DN attribute is not set for the add request.

Action

Set the DN attribute.

**CTGDIM026E Attribute not set for the add request:
*attribute name.***

Explanation

The dsml attribute must be provided when creating and writing an add request

Action

Set the correct dsml attributes.

CTGDIM027E The required attribute 'DN' was not set for the delete request.

Explanation

The mandatory DN attribute is not set for the delete request.

Action

Set the DN attribute.

CTGDIM028E The required attribute 'DN' was not set for the modifyDN request.

Explanation

The mandatory DN attribute is not set for the modifyDN request.

Action

Set the DN attribute.

CTGDIM029E The required attribute 'newRDN' was not set for the modifyDN request.

Explanation

The mandatory newRDN attribute is not set for modifyDN request.

Action

Set the newRDN attribute.

CTGDIM030E The required attribute 'DN' was not set for the compare request.

Explanation

The mandatory DN attribute is not set for the compare request.

Action

Set the DN attribute.

CTGDIM031E Assertion is not set for the compare request.

Explanation

See message.

Action

Set the correct dsml attributes.

CTGDIM032E The required attribute 'abandonID' not set for the abandon request.

Explanation

The Mandatory abandonID attribute is not set for the abandon request.

Action

Set the abandonID attribute.

CTGDIM033E The required attribute 'requestName' was not set for the extended request.

Explanation

The mandatory requestName attribute is not set for the extended request.

Action

Set the requestName attribute.

CTGDIM034E The required attribute 'requestValue' was not set for the extended request.

Explanation

The mandatory requestValue attribute is not set for the extended request.

Action

Set the requestValue attribute.

CTGDIM035E The searchResultEntry was not set while creating the search request.

Explanation

See message.

Action

Set the searchResultEntry in the attribute in the Entry.

CTGDIM036E The searchResultEntry was not set while creating the search response.

Explanation

See message.

Action

Set searchResultEntry in the attribute in the Entry while writing search response.

CTGDIM037E The require attribute 'errorType' not set for the error response.

Explanation

The mandatory errorType attribute is not set for the error response.

Action

Set error type attribute.

CTGDIM038E Unable to write the Entry. The required attribute 'dsml.operation' was missing from the Entry.

Explanation

See message.

Action

Set the specified attribute.

CTGDIO001I Exiting initialization early because Connector already initialized with a java.net.Socket object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO002I Connector will use SOAP binding.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO003I Using provided java.net.Socket object for DSML client session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO004I No DSML request available from client.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIO005W Exception while authenticating to HTTP Parser:
*exception***

Explanation

See message.

Action

No action is required.

CTGDIO006W No message body available from client.

Explanation

Request from the client has no message body. Request cannot be processed.

Action

Check the client request structure and body.

CTGDIO007W Failed to initialize the DSML v2 SOAP Server Connector because the DSML Parser could not be initialized. Exception encountered: *exception*

Explanation

See message.

Action

No action is required.

CTGDIO008E The 'dsmlPort' parameter must be set to use the DSML v2 SOAP Server Connector.

Explanation

The required parameter dsmlPort was not specified in the DSML v2 SOAP Server Connector.

Action

Specify the dsmlPort parameter in the Connector.

CTGDIO009I Listening for DSML SSL connections on port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO0010I Listening for DSML connections on port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO0011I DSML v2 SOAP Server Connector closed client connection.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO0012I Terminate server request received.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIO0013I Creating dummy connection using IP Address
'IP Address' and port 'port number'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIO0014W Encountered an IOException on unblocking the
DSML v2 SOAP Server Connector's server socket: *exception***

Explanation

See message.

Action

No action required.

**CTGDIO0015I DSML v2 SOAP Server Connector is already
terminating. Not sending termination request.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO0016I Sending termination request to the DSML v2 SOAP Server Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO0017E Server Socket is not open, cannot accept client requests.

Explanation

DSMLv2 SOAP Server Connector cannot listen on a specified port and cannot accept client connections.

Action

Check parameters that specified the port of the Server Socket, check that this port is not used yet.

CTGDIO0018I Connector terminated by external request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO0019W Authentication failed. Client could not authenticate more than 3 times. Exiting...

Explanation

See message.

Action

No action is required.

CTGDIO0020I The user name is set to '*user name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIO021I Connector will not use SOAP binding.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK201W The Connector has overridden the Server Location parameter: '*new value*'.**Explanation**

The connector will use the new value specified in the Advanced Properties section.

Action

Verify that the Advanced Properties section does not contain a ServerLocation property.

CTGDJK20wW The connector has overridden the Server Port parameter: '*new value*'.**Explanation**

The connector will use the new value specified in the Advanced Properties section.

Action

Verify that the Advanced Properties section does not contain a ServerPort property.

CTGDJK103I Initialization successful.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK104I Waiting *number of seconds* second(s) for an event to occur.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK105I Getting an event from the cache.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK106I Waiting for an event to occur...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK107I Sending event: *raw message text*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK208E Error sending event. Error code: '*error code*'

Explanation

An error was encountered while sending an event to the remote server.

Action

Check that the remote server is reachable.

CTGDJK109I Termination successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK110I Received event: '*event raw text*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK111I The Event contains *number of entries* entry(s). Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK212E Error parsing event message: '*event raw text*'. Explanation

The underlying framework was unable to parse the received message.

Action

Check the configuration settings of the remote server, as well as the connector's configuration.

CTGDJK213E Error processing mapping file: *exception*. Explanation

See the message for more details.

Action

Check whether the schema file name is specified correctly and that the file exists.

CTGDIA001E The perform method of the Function Component was not passed an object of type *com.ibm.di.entry.Entry*. This object is not a valid parameter to pass to perform method.

Explanation

A parameter of type different from *com.ibm.di.entry.Entry* was passes to the perform method.

Action

Verify that the parameter being manually passed to the perform method of Function Component (for example from a Script Component) is an object of type *com.ibm.di.entry.Entry*.

CTGDIA002E Error occurred while converting the Data Objects to XML: *exception*

Explanation

The specified error occurred while converting the structure of Data Objects to an XML document.

Action

Make sure the data objects are consistent with the XML Schema file.

CTGDIA003E Required Function Component parameter '*parameter name*' is not set.

Explanation

The specified required Function Component parameter is not set.

Action

Set the specified Function Component parameter.

CTGDIA004E Invalid prefix to namespace URI mapping on line '*line number*'.

Explanation

The format of the prefix to namespace URI mapping is invalid on the specified line.

Action

Check the namespaceMap parameter of the Function Component.

CTGDIA005E An error occurred while processing the XML Schema file '*file name*': *exception*

Explanation

The specified error occurred while processing the XML Schema file.

Action

Verify the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIA006E There is no feature representing the XML element or attribute with name '*attribute name*'.

Explanation

The EClass object has no feature representing the XML element or attribute with the specified name.

Action

Check the names of the Entry Attributes to conform to the XML Schema name.

CTGDIA007E There are siblings from the same namespace with case-insensitive equality in names: '*feature name*'.

Explanation

The element with the specified name has a sibling with a case-insensitive equal name and the elements are from the same namespace.

Action

Change the name of the siblings so there is no case-insensitive equality.

CTGDIA008E There are siblings from different namespaces with case-insensitive equality in names, and the names are not namespace prefixed: '*feature name*'.

Explanation

The element with the specified name has a sibling with case-insensitive equal name, from a different namespace. The names are not namespace prefixed.

Action

Change the name of the siblings or should use the useNamespace parameter so the names are prefixed.

CTGDIA009E The '*feature name*' XML element or attribute is invalid according to the XML Schema.

Explanation

The specified name is an invalid XML element or attribute according to the XML Schema.

Action

Check the names of the XML elements and attributes in the names of the Entry Attributes to conform with the XML Schema.

CTGDIA010E The Entry Attribute '*attribute name*' specifies an XML element or attribute with ancestor '*feature name*' that has a sibling with the same name.

Explanation

The specified Entry Attribute refers to an XML element or attribute with ancestor that has a sibling with the same name.

Action

Do not specify an XML element or attributes with an ancestor that has a sibling with the same name. Remove the specified Entry Attribute from the mapping or

ensure that the XML element or attribute has no ancestor with a sibling with the same name.

**CTGDIA011E The XML Schema does not define a root element.
Explanation**

See message.

Action

Verify the XML Schema defines a root element and if it does not, the XML Schema should be changed to define a root element.

CTGDIA012I The XML Schema has been successfully parsed and an Ecore model has been created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA013I The Entry Attributes have been successfully applied to the data structure.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA014I The parameter '*parameter name*' initialized with a value of '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA015E An error occurred while processing the XML Schema file '*file name*': '*diagnostic message*'.

Explanation

The error occurred while processing the XML Schema file.

Action

Verify the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIA016E An error occurred while processing the XML Schema file '*file name*'.

Explanation

The error occurred while processing the XML Schema file.

Action

Verify the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIA017E An error occurred while processing the XML Schema file '*file name*': *exception*

Explanation

The specified error occurred while processing the XML Schema file.

Action

Verify the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIA018I The XML that results from conversion from the DOM Element to XML is: *xml data*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIA019E Invalid value encountered in attribute '*attribute name*' '*attribute value*'.

Explanation

The Function Component encountered an invalid value for an Enumeration data type in the Attribute Map.

Action

Verify the value set for the specified attribute is valid according to the xml schema being used by the Function Component.

CTGDIB001E The perform method of the Function Component was not passed an object of type com.ibm.di.entry.Entry. This object is not a valid parameter to pass to perform method.

Explanation

A parameter of type different from com.ibm.di.entry.Entry was passes to the perform method.

Action

Verify that the parameter being manually passed to the perform method of Function Component (for example from a Script Component) is an object of type com.ibm.di.entry.Entry.

CTGDIB002E The Entry Attribute '*attribute name*' is not present in the Entry.

Explanation

The expected Entry Attribute is not present in the Entry.

Action

Verify the specified Entry Attribute is properly mapped to the connection Entry.

CTGDIB003E Error occurred while processing the XML document: *exception*

Explanation

The specified error occurred while processing the XML document. This error normally occurs when the XML document is not well formed or is not valid according to the XML Schema.

Action

Verify the XML document passed to the Function Component is well formed and valid according to the XML Schema.

CTGDIB004E The required Function Component parameter '*parameter name*' is not set.

Explanation

The specified required Function Component parameter is not set.

Action

Set the specified Function Component parameter.

CTGDIB005E Invalid prefix to namespace URI mapping on line '*line number*'.

Explanation

The format of the prefix to namespace URI mapping is invalid on the specified line.

Action

Check the namespaceMap parameter of the Function Component.

CTGDIB006E An error occurred while processing the XML Schema file '*file name*': *exception*

Explanation

The specified error occurred while processing the XML Schema file.

Action

Verify the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIB007E There are siblings from the same namespace with case-insensitive equality in names: '*feature name*'.

Explanation

The element with the specified name has a sibling with case-insensitively equal name and the elements are from the same namespace.

Action

Change the name of the siblings so there is no case-insensitive equality.

CTGDIB008E There are siblings from different namespaces with case-insensitive equality in names, and the names are not namespace prefixed: '*feature name*'.

Explanation

The element with the specified name has a sibling with case-insensitive equal name, from a different namespace. The names are not namespace prefixed.

Action

Change the name of the siblings or should use the useNamespace parameter so the names are prefixed.

CTGDIB009I The parameter '*parameter name*' initialized with a value of '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIB010I The XML parsing has been completed. Data Objects have been successfully created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIB011I The Entry Attributes have been successfully created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIB012I The XML Schema has been successfully parsed and an Ecore model has been created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIB013I The Ecore model has been successfully checked for conformity.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIB014E An error occurred while processing the XML Schema file '*file name*': '*diagnostic message*'.

Explanation

The specified error occurred while processing the XML Schema file.

Action

Verify the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIB015E An error occurred while processing the XML Schema file '*file name*'.

Explanation

The specified error occurred while processing the XML Schema file.

Action

Verify the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIB016E An error occurred while processing the XML Schema file '*file name*': '*diagnostic message*'.

Explanation

The specified error occurred while processing the XML Schema file.

Action

Verify the if the XML Schema file is well-formed and valid according to the XML Schema specification.

CTGDIB017E The Entry Attribute '*attribute name*' is not present in the Entry.

Explanation

The expected Entry Attribute is not present in the IBM Security Directory Integrator Entry.

Action

Verify the specified Entry Attribute is properly mapped to the connection Entry.

CTGDIB018I The XML resulting from the conversion from DOM Element is: *xml data*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT001E The 'filePath' parameter must be set to use the File Connector.

Explanation

The required parameter filePath was not specified in the File Connector.

Action

Specify the filePath parameter in the Connector.

CTGDIT002I File Connector waiting for data. On attempt '*attempt count*' and will timeout after attempt '*maximum number of attempts*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT003E The 'filePath' parameter must be set to use the File Connector to a open file for reading.

Explanation

The required parameter filePath was not specified in the File Connector. Must be specified to open a file for reading.

Action

Specify the filePath parameter in the Connector.

CTGDIT004E The 'filePath' parameter must be set to use the File Connector to a open file for writing.

Explanation

The required parameter filePath was not specified in the File Connector. The parameter must be specified to open a file for writing.

Action

Specify the filePath parameter in the Connector.

CTGDIT008E File Connector timed out while waiting for lock on file.

Explanation

The File Connector must be able to lock the file it is going to read from or write to.

Action

Verify that the program has permissions to read from or write to the file. Also, verify the file is not currently being used or locked by another program.

CTGDIT010I Open input: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT011I Open output: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT051E The starting directory path is not specified.

Explanation

The 'Directory Path' parameter in the configuration of the Connector is not set.

Action

Set the 'Directory Path' parameter in the configuration of the Connector.

CTGDIT052E The depth parameter can not be negative.

Explanation

The 'Depth' parameter is a negative number.

Action

Either leave the 'Depth' parameter blank or provide a non-negative value.

CTGDIT053E The glob pattern '*glob pattern*' is invalid.

Explanation

The given filter is not a correct glob pattern.

Action

Check the documentation of the Connector and modify the filter so that it matches the glob syntax.

CTGDIT054I No permission to read '*directory*' directory.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT055I '*file*' does not exist.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT056I Full Path '*full path*' criteria is used. Connector will skip Lookup and use the specified file or directory directly.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT057I Read only file '*file*' is deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT058E File '*file*' is read-only.

Explanation

The specified file is Read-Only and cannot be deleted without the 'Force Delete' option.

Action

Enable the 'Force Delete' option in the configuration of the Connector.

CTGDIT059I Non-empty directory '*directory*' is deleted.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIT060E Directory '*directory*' is not empty.**Explanation**

The specified directory is not empty and cannot be deleted without the 'Force Delete' option.

Action

Enable the 'Force Delete' option in the configuration of the Connector.

CTGDIT061E Deleting '*file*' failed.**Explanation**

The 'Force Delete' operation failed.

Action

This operation relies on file system specific capabilities.

CTGDIT062E '*file*' is not a directory.**Explanation**

The provided 'Directory Path' is not a real directory.

Action

Provide a correct starting directory path.

CTGDIT063E The name of the file or directory is not specified. At least the '*fullPath*' or '*name*' attribute must be provided in the Output Map.**Explanation**

The file cannot be named with the provided information.

Action

Provide the '*fullPath*' or '*name*' attribute in the Output Map.

CTGDIT064E '*file*' already exists.

Explanation

The specified file or directory already exists on the file system.

Action

Provide information for a non-existent file or directory.

CTGDIT065E Directory '*directory*' could not be created.

Explanation

A problem occurred during the directory creation.

Action

This operation relies on file system specific capabilities.

CTGDIT066E File '*file*' could not be created.

Explanation

A problem occurred during the file creation.

Action

This operation relies on file system specific capabilities.

CTGDIT067E '*file*' could not be made Read-Only.

Explanation

A problem occurred when setting the Read-Only flag.

Action

This operation relies on file system specific capabilities.

CTGDIT068E Dates must use format: *date format*

Explanation

A Date attribute in the Link Criteria is not formatted correctly.

Action

Provide a value in accordance with the specified format.

CTGDIT069E Copying '*from file*' to '*to file*' failed.

Explanation

The copy operation has failed.

Action

This operation relies on file system specific capabilities.

CTGDIT070E Moving '*from file*' to '*to file*' failed.

Explanation

The move operation has failed.

Action

This operation relies on file system specific capabilities.

CTGDIT071E Boolean attributes expect values true or false.

Explanation

A Boolean attribute in the Link Criteria has an incorrect value.

Action

Provide a correct value for the Boolean attribute.

CTGDJZ801I The parameter *param name* was initialized with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ802E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the File Transfer Function Component and must be provided.

Action

Provide a value for this parameter.

CTGDJZ803I File Transfer Function Component will work FTP file transfer mode set to: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ804I File Transfer Function Component will work 'Convert source file to character set of target system' option set to: 'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ805I File Transfer Function Component will work 'Enable SSL for AS400 connection' option set to: 'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ806I File Transfer Function Component will use 'value' for AS400 connections.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ807I The parameter *param name* is not specified. Default connection protocol 'value' will be used.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ808I The value of Source parameter *param name* is set with the value: 'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ809I The value of Target parameter *param name* is set with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ810I The direction of the file transfer is: '*value*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ811E Unable to determine the direction of the file transfer.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ812I File Transfer Function Component is establishing connection to the host: '*value*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ813I File Transfer Function Component has successfully established a connection to the host: 'value

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ814E File Transfer Function Component could not establish a connection to the host: 'value

Explanation

A connection to the target machine is not possible because the connection parameters provided are not valid, or because of problems with the network.

Action

Verify that the connection parameters are valid and that the network connection to the target is active and then try again the connection.

CTGDJZ815E File Transfer Function Component could not establish a connection to the target machine.

Explanation

A connection to the target machine is not possible because the connection parameters provided are not valid, missing connection parameters or because of problems with the network.

Action

Verify that the connection parameters are valid and that the network connection to the target is active and then try again the connection.

CTGDJZ816E Parameter 'param name' is not provided.

Explanation

The specified parameter is needed to establish the FTP connection.

Action

Provide a value for this parameter.

CTGDJZ817E File Transfer Function Component accepts only a IBM Security Directory Integrator Entry as input.

Explanation

At the beginning of the Function Component's execution cycle the input data passed was not a IBM Security Directory Integrator Entry.

Action

File Transfer Function Component expects only a IBM Security Directory Integrator Entry as input. Check the AL logic and try again.

CTGDJZ818I The value of configuration parameter '*param*' set in configuration GUI has been overridden to '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ819E An invalid connection type has been specified. The valid values for the 'connectionType' parameter are: 'RSH', 'SSH', 'REXEC', 'AS400', 'WIN' and 'FTP'.

Explanation

The value for the 'connectionType' parameter should be one of the following: "RSH", "SSH", "REXEC", "AS400", "WIN", "FTP".

Action

Verify that the 'connectionType' parameter has been set to an appropriate value. The valid values for this parameter are: "RSH", "SSH", "REXEC", "AS400", "WIN", "FTP".

CTGDJZ820E Not all parameters have been provided. Ensure you have provided a hostname and username. For an REXEC, FTP and Windows connection you will also need to provide a password. For an SSH connection you have the option of providing a password OR a keystore (with associated passphrase if applicable).

Explanation

Not all required properties have been configured for the Function Component.

Action

Ensure you have provided a hostname and username. For an REXEC, FTP and Windows connection you will also need to provide a password. For an SSH connection you have the option of providing a password OR a keystore (with associated passphrase if applicable).

CTGDJZ821E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the File Transfer Function Component and must be provided.

Action

Provide a value for this parameter.

CTGDJZ822E Unable to delete temporary file '*param name*'.

Explanation

The specified file might be in use.

Action

Please delete the file manually.

CTGDJZ823E Target file path '*param name*' is same as Source file path, unable to transfer file.

Explanation

Source and Target file paths should not be same.

Action

Please specify a different Target file path.

CTGDJZ824E Source file path '*param name*' not found.

Explanation

Source file path should be existing.

Action

Please specify a different Source file path.

CTGDJZ825E Target file '*param name*' might be in use or read-only or target path does not exist.

Explanation

Target file should not be in use or read-only, also the target path should exist.

Action

Please specify a different Target file path.

CTGDJZ826E File Transfer Function Component could not establish a connection to the target machine using given parameters in Configuration Editor. File Transfer Function Component will continue, if any attribute mapping provided in runtime.

Explanation

This exception occurs because there might be invalid connection parameters provided in Configuration Editor either in Source or Target section.

Action

Verify that the connection parameters are valid and that the network connection to the target is active and then try again the connection.

CTGDJZ827E Specified target directory '*param name*' does not exist.

Explanation

Target directory path should exist on the target machine.

Action

Please specify a different Target directory or select 'Create Directory' check-box in configuration panel.

CTGDJZ828E Unable to create specified target directory '*param name*'

Action

Please check you have proper access to create specified target directory.

CTGDJY101I Parser set padding character to '*character*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIP001I Connector terminating: '*Connector name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIP002W Exception encountered while closing socket connection to ftp server: '*error*'

Explanation

An exception was encountered while trying to close the socket connection to ftp server. The exception was caught and the program will continue running.

Action

No action is required.

CTGDIP003I Opening connection to FTP Server: '*hostname*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIP004I Logging onto FTP server with user ID '*user ID*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIP005I Using FTP operation '*operation*' at server location '*location*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIP006E The '*ftpHost*' parameter must be set to use the FTP Client Connector.

Explanation

The required parameter ftpHost was not specified in the FTP Client Connector.

Action

Specify the ftpHost parameter in the Connector.

CTGDKK101E The 'configFile' parameter must be set to use the GLA Connector.

Explanation

The required parameter configFile is not set in the GLA Connector.

Action

Specify the path to the adapter configuration file in the configFile parameter.

CTGDKK102E The adapter configuration file is not valid: *exception message*.

Explanation

The given configuration file is not valid. See the exception message for more information.

Action

Correct the adapter configuration file and try again.

CTGDKK103I The adapter configuration file is validated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK104I The adapter configuration file is started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK105E The execution of the adapter configuration file failed: *Exception message*

Explanation

An Exception occurred during the execution of the adapter configuration file. See the Exception message for more information.

Action

See the Exception message for more information.

CTGDKK106E There is no registered GLAConnector matching the specified in the TDIOutputter 'tdi_correlation_id' parameter: *Correlation ID*.

Explanation

The Hashtable of the TDIOutputter does not contain a Connector registered to the specified 'tdi_correlation_id'.

Action

Specify a correct value in the TDIOutputter 'tdi_correlation_id' parameter.

CTGDKK107E There are more than one configured TDIOutputters in the adapter configuration file.

Explanation

The GLAConnector allows only one TDIOutputter to be configured in the adapter configuration file.

Action

Put only one TDIOutputter in the adapter configuration file.

CTGDKK108E An exception occurred while converting the XML file to Document object: *exception message*

Explanation

There are several possible reasons for this exception. A DocumentBuilder may not have been able to be created which satisfied the configuration requested. An IO error occurred. Or, a parse error occurred.

Action

See the Exception message for more information.

CTGDKK109E The given adapter configuration file does not have a configured TDIOutputter.

Explanation

The GLAConnector needs a TDIOutputter to be configured in the adapter configuration file in order to receive the CBE objects.

Action

Set a TDIOutputter in the adapter configuration file and try again. Refer to the GLAConnector documentation about how to configure the TDIOutputter.

CTGDJP201I Finding entries with URL set to *URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP202E Unable to send request to HTTP Server because an invalid protocol *protocol* was specified in the URL.

Explanation

See message.

Action

Verify the URL specified contains a valid protocol for the HTTP Client Connector. Valid values for the protocol are http and https.

CTGDJP203I Connected to *URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP204I Constructing filtered entry for Parser *Parser name* to generate http.body contents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP205I Setting attribute *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP206E Exception occurred while writing HTTP body to file: *error*

Explanation

Review the exception message for more details. This is an internal error.

Action

Contact IBM support.

CTGDJP207I Using persistent connection for *url*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP208I Connecting through *proxy* to *host*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP209I Failed to connect through *proxy* to *host* with the response, *response*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP210I Unable to parse the proxy host *proxy*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP401I HTTP Parser will use the input reader.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP402I HTTP Parser will read a line from the input stream using character set '*character set*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP403I HTTP Parser starting to reading line.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP404I HTTP Parser read in character '*integer value*' which has an ascii character value of '*character*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP405I HTTP Parser will read an entry using the character set '*character set*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP406I HTTP Parser read in the following line:
''line''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP407I HTTP Parser will write entry with client mode of ''boolean''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP408E Unable to write entry because no URL was provided for the client mode in the HTTP Parser.

Explanation

See message.

Action

Ensure the URL for the client mode is set in the HTTP Parser.

CTGDJP409I HTTP Parser entry begin writtent redirect to ''redirect info''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP410I HTTP Parser entry being written has status set to ''status''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP411I HTTP Parser entry being written has header set to '*header*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP412I Unsafe output conversion.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP413I HTTP Parser reading HTTP body: Body length=*length*, Input stream=*stream information*, Reader=*reader information*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP414I Only a Reader available. This might cause problems when reading a multi-byte character set.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP415E No input stream/reader available.**Explanation**

The method readBody is trying to read the body but the object reader is null.

Action

No action is required.

CTGDJP416I HTTP Parser successfully read the HTTP body.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP417I 'http.Transfer-Encoding' parameter: *parameter value*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP418I Disable charset conversion since Reader object used to read data.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP419I Content type charset: *character set*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP420I Chunk size line: *size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP421I Chunk size is: *size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJP422I Authentication information from the Entry:
`http.remote_user=username, http.remote_pass=password`.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP423I Trying to decode the URL: *URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP424I Skipping token: *token name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP425I Parsing HTTP URL to retrieve the credentials. Pure HTTP URL has been stripped off of its prefix and suffix, but still contains credential information: *pure HTTP URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP426I Authentication information: *username:username, password:password*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP427I Authorization result: *authorization string*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP428I Chunk part is: *buffer length=length, size=size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP429I HTTP Parser found no content type and will default it to *content type*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP430I HTTP body for the HTTP Parser: *HTTP body*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP431I Parsed HTTP header: *HTTP header*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP301I Exiting initialization early because Connector already initialized with a `java.net.Socket` object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP302I Using provided `java.net.Socket` object for HTTP client session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP303E Unable to load authenticator Connector *Connector name*. Exception occurred: *exception*

Explanation

Authenticator Connector used in the HTTP Server Connector cannot be initialized.

Action

Check the configuration and parameters of the chosen Authenticator Connector.

CTGDJP304I Listening for HTTP SSL connections on port: *port number*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP305I Listening for HTTP connections on port: *port number*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP306E Server Socket is not open, cannot accept client requests.

Explanation

HTTPServerConnector cannot listen on a specified port and can not accept client connections.

Action

Check parameters that specified the port of the Server Socket, and if this port is not used yet.

CTGDJP307I Connector terminated by external request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP309I Terminate server request received.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP310I Creating dummy connection using IP Address ''IP Address'' and port ''port number''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP311W IOException on unblocking Connector server socket: *exception*.

Explanation

IOException is thrown while terminateServer method is executed. However, the Connector may have terminated.

Action

No action is required.

CTGDJP312I Server is already terminating.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP313I Sending termination request to server Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP314I Client connection closed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJP315E Unable to get the next Entry. A
SocketException occurred: *exception*.****Explanation**

See message.

Action

Check the connection between the HTTP Server Connector and the client.

CTGDJP316E Connection closed by client.**Explanation**

See message.

Action

No action is required.

CTGDJP317I Reject Client Authentication.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJP318I Constructing filtered entry for Parser *Parser
name* to generate http.body contents.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP319I Setting attribute *attribute name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP320I Authenticate user: *user name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP321E Unable to authenticate Connector. Exception occurred: *exception*

Explanation

The credentials do not exist in the system where the Authentication Connector is searching.

Action

Check that the credentials exist in the system where the Authentication Connector is searching.

CTGDJP322E Authentication failed. Client could not authenticate 3 times. Exiting ...

Explanation

The credentials do not exist in the system where the Authentication Connector is searching.

Action

Verify the credentials exist in the system where the Authentication Connector is searching.

CTGDJP323I Authentication successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP324E Username or Password not provided. Client could not authenticate 3 times. Exiting ...

Explanation

See message.

Action

Provide a username and password.

CTGDJP325I Username: *username*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP326E No HTTP request available from client.

Explanation

See message.

Action

Check the client HTTP request.

CTGDJP327E Authentication exception: *exception*

Explanation

The credentials do not exist in the system where the Authentication Connector is searching.

Action

Verify the credentials exist in the system where the Authentication Connector is searching.

CTGDJP328I SSL exception occurred. The only action to be taken is to ignore this exception.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP329I NoSuchElement exception occurred. The only action to be taken is to ignore this exception.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG001I Usage: IDILoader java-class [params]

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG002E The IDILoader cannot locate installation directory.

Explanation

The IDILoader could not load in the IDILoader.properties resource. This is an internal error.

Action

Contact IBM support.

CTGDKG003I Jars Directory: *directory*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG004I addFiles: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG005I The directory path specified does not exist:
path.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG006I The file is not a jar or zip file: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG007I No files found in the path: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG008I Adding files to the jar files list: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG009I addPackages: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG010I The directory path specified does not exist:
path.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG011I No files found in the path: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG012I Adding files to the packages list: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG019I cacheJarContents: *path*. Exception occurred:
exception

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG020I Load initial class: *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG021I Get main method: *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG022I Invoke main method: *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG023E Error while starting main class.

Explanation

Launching the entry point class of the IBM Security Directory Integrator product failed.

Action

Examine the error. Verify the IBM Security Directory Integrator installation is not corrupted. If the problem persists contact IBM support.

CTGDKG024I findResource: *resource name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG029I URL: *URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG030I The resource *resource name* was not found by the IDILoader. Try the parent loader.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG031I Searching for the library *library name* in directory *directory*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG032I The library *library name* was found in the file *file*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG037I Looking for *tdi.xml* or *idi.inf* in *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG038I Found *file name* in *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKG039I An exception occurred while reading *path*:
exception

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ651E Attribute *attribute* does not accept value
'*value*'.

Explanation

The specified value is not supported by that parameter. For instance the '\$operation' attribute of this Connector accepts the following string values: 'create', 'modify', 'delete' (case insensitive). If something else is passed into the attribute this error will occur.

Action

Provide valid values for the Connector's parameters. Consult the documentation for the supported ones.

CTGDJZ652E The IdML book is opened in REFRESH mode and
supports only CREATE operations.

Explanation

The IdML book this Connector is working with has been opened in Refresh mode, meaning only 'create' operations may be used for it.

Action

Set the operation to 'create' from the '\$operation' attribute or as a delta operation (i.e. the operation set to delta tagged entry will override the operation attribute of the Connector). Alternatively, change the book mode to Delta (from the Open IdML Function Component).

CTGDJZ653E No class type specified in the configuration of
the IdML Ci and Relationship Connector.

Explanation

In order to discover the schema of this Connector, the class type parameter must be provided. Otherwise the Component does not know which attributes to display.

Action

Set the required Class Type parameter from IdML Ci and Relationship Connector's configuration panel.

CTGDJZ654I IdML Ci and Relationship Connector will work with book: *book name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ655I The parameter *param name* was initialized with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ656I The name of the currently used book '*book name*' has been overridden to '*new name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ657I Use an IT registry for the needed meta-data: '*use it registry*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ658I The book '*book name*' does not exist or is already closed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ659E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the IdML Ci and Relationship Connector and must be provided.

Action

Provide a value for this parameter.

CTGDJZ751E Error parsing XML. An invalid input IdML XML is passed to the parser.

Explanation

The input XML does not comply with the IdML XML schema.

Action

Correct the input XML so it is valid against the IdML XML schema.

CTGDJZ752I Reading entry where parent node is '*node name*' and the current node is '*node name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ754I *indent* Node Name: *node name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ755I *indent* Node Value: *node value*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR001W The 'pageSize' parameter set to an invalid value '*parameter value*'. Will not use paging.

Explanation

See message.

Action

Specify a valid pageSize parameter in the Connector if paging needs to be enabled.

CTGDJR002W The 'pageSize' parameter set to a negative value '*parameter value*'. Will not use paging.

Explanation

See message.

Action

Specify a valid pageSize parameter in the Connector if paging needs to be enabled.

CTGDJR003E Unable to initialize Connector because a connection to the directory server could not be established or the search at base DN *DN* was not valid.

Explanation

See message.

Action

Verify the directory server is running and that the ldapSearchBase parameter is set to a valid value.

CTGDJR004W Cannot set starting change number to '*change number*'.

Explanation

The change number specified in the nsChangenum parameter could not be used to set the starting change number.

Action

Verify the nsChangenum parameter is set to a valid change number.

CTGDJR005I Starting with change number set to ''change number'' and the 'iteratorStateKey' was set to ''state value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR006I Block for notifications ...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR007W Thread interrupted: *exception*

Explanation

An InterruptedException is encountered when executing the method 'blockForNotifications'.

Action

No action is required.

CTGDJR008I Timeout waiting for next changed entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR009I LDAP search query set to ''filter''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR010I Getting the next changelog entry: *CN*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR011I Got next changelog entry: *CN*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR012I Entry not found in Changelog: *CN*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJR013I Skipping and trying next changelog entry:
change number.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR014E Unable to get next search result.

PartialResultException occurred: *exception*

Explanation

The method getNextSearchResult fails trying to get the next search result.

Action

No action is required.

CTGDJR015I Get next page: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR016E The entry does not contain a valid changelog entry (changes attribute missing) for operation: *operation type*.

Explanation

See message.

Action

Put a valid 'changes' attribute in the entry.

CTGDJR017E LDIF Parser could not parse 'changes' attribute from the entry.

Explanation

See message.

Action

Put a valid 'changes' attribute in the entry.

CTGDJR018I The attributes does not contain 'lastchangenumber' attribute.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR019E Could not retrieve the last change number.

Explanation

Attributes do not contain 'lastchangenumber' attribute.

Action

No action is required.

CTGDJR020E Could not store the change number value in the System Store. Exception occurred: *exception*

Explanation

The method storeChangenumberForNextSynch fails trying to set a property in the System Store.

Action

Check the System Store.

CTGDJR021I The current change number value is: *change number*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR022I A NamingExceptionEvent occurred: *event*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR023I A notification event was received: *event*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJR024E Restart info does not contain 'changeNumber' attribute.

Explanation

See message.

Action

No action is required.

CTGDJR025W Exception occurred while terminating the Connector: *exception*

Explanation

See message.

Action

No action is required.

CTGDJR026W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used.

Explanation

See message.

Action

Specify the iterator state key if you want the state of the changelog connector to be saved.

CTGDJZ401E An Exception occurred when using the Naming and Reconciliation Service API.

Explanation

The Component was not able to use the IT registry Naming and Reconciliation Service. Check the provided Exception for details.

Action

For more information please refer to the logs of the Naming and Reconciliation Service API.

CTGDJZ402E An Exception occurred during a database operation when using Naming and Reconciliation Service API.

Explanation

The Component was not able to use the IT registry database. Check the provided Exception for details.

Action

For more information please refer to the logs of Naming and Reconciliation Service API.

CTGDJZ403I The parameter *param name* was initialized with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ404I Init IT registry Function Component will work with book: '*book name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ405I Init IT registry Function Component will work with Refresh set to: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ406I The Common Data Model version of the registered MSS will be '*cdm version*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ407E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the Init IT registry Function Component and must be provided.

Action

Provide a value for this parameter.

CTGDJZ408I Use an IT registry system for the needed meta-data: 'use it registry'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ409E Init IT registry Function Component accepts only a IBM Security Directory Integrator Entry as input.

Explanation

At the beginning of the Function Component's execution cycle the input data passed was not a IBM Security Directory Integrator Entry.

Action

Init IT registry Function Component expects only a IBM Security Directory Integrator Entry as input. Check the AL logic and try again.

CTGDJZ410E The Common Data Model version specified '*param name*' is not a valid Common Data Model version.

Explanation

The Common Data Model version should be in a format of three dot-separated numbers.

Action

Please specify value of Common Data Model version in a format of three dot-separated numbers.

CTGDJZ411I The MSS's *param name* has value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ412E Either MSS Name or Manufacturer Name, Hostname and Product Name are not set in output map of FC.

Explanation

Either MSS Name or Manufacturer Name, Hostname and Product Name are mandatory for an MSS registration.

Action

Please provide the listed information in the FC's Output Map.

CTGDJZ413E The Common Data Model version is not set in configuration panel of FC.

Explanation

Common Data Model version is mandatory for an MSS registration.

Action

Please provide a valid Common Data Model version in the FC's Configuration panel.

CTGDJZ414I The name of the currently used book '*book name*' has been overridden to '*new name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ415E JDBC parameter '*param name*' is not set in Configuration panel of FC and can not be read from the IT registry's properties file.

Explanation

This JDBC parameter is mandatory for an MSS registration.

Action

Please provide this parameter either in Configuration panel or in IT registry's properties file.

CTGDJZ416I Init IT registry Function Component has already opened book '*book name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ417E The book '*book name*' is opened and currently used.

Explanation

The book with the provided book name is currently in use by another Init IT registry Function Component. It will have to release it before this Component can use it.

Action

Check if there is another running AssemblyLine with IT registry Components. If the problem persists either provide another book name for your IT registry Components or restart the SDI server.

CTGDIZ401I There was no SOAP response header.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ402E Parameter '*wsdlUrl*' is empty.

Explanation

See message.

Action

Specify a valid '*wsdlUrl*' parameter in the FC.

CTGDIZ403I Parameter '*wsdlUrl*': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ404E Parameter '*soapOperation*' is empty.

Explanation

See message.

Action

Specify a valid '*soapOperation*' parameter in the Function Component.

CTGDIZ405I Parameter 'soapOperation': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ406I Parameter 'providerUrl': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ407I Parameter 'returnXMLType': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ408E Invalid value for 'returnXMLType': *parameter value*.

Explanation

See message.

Action

Specify a valid 'returnXMLType' parameter in the Function Component.

CTGDIZ409I Parameter 'inputType': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ410E Invalid value for 'inputType': *parameter value*.
Explanation

See message.

Action

Specify a valid 'inputType' parameter in the Function Component.

CTGDIZ411I SOAP request Attribute: *mInputAttr*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ412I SOAP response Attribute: *attribute*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ413E Entry Attribute '*attribute*' is missing.
Explanation

See message.

Action

Check the attributes in the entry.

CTGDIZ414I About to call web service at *provider URL* using:
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ415I SOAP Action: *SOAP action*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ416I SOAP request: *SOAP request.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ417I Called successfully web service at *provider URL.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ418I SOAP response: *SOAP response.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ419I SOAP response header: *SOAP response header.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ420I SOAP response body: *SOAP response body.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ421I Web service is one way: *boolean*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ422E The SOAP request message is not initialized.

Explanation

The Function Component has not received a SOAP request message. It should receive the message either as XML DOM Element or as XML String Java object.

Action

Check the AssemblyLine logic and try again.

CTGDIZ423E Invalid object recieved: *object*.

Explanation

The Function Component has not received a SOAP request message. It must receive the message either as XML DOM Element or as XML String Java object.

Action

Check the AssemblyLine logic and try again.

CTGDIR301I Password not specified. Will use empty string value for password.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR302E Required parameter is missing: *parameter name*.

Explanation

See message.

Action

The specified parameter of the ITIM Agent Connector should be checked.

CTGDIR303I The selectEntries method will perform Agent search with filter: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR304I The selectEntries method's search returned at least one Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR305I No Entries returned by search in the selectEntries method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR306I The getNextEntry method has no more Entries to return.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIR307E The putEntry method could not add new Entry.
Exception occurred: *exception***

Explanation

Could not create the new JNDI Entry.

Action

Check the DN attribute \$dn in the entry.

CTGDIR308E Unable to add Entry. The naming attribute \$dn was not specified in Entry.

Explanation

The DN attribute \$dn is null.

Action

Check the DN attribute \$dn in the entry.

CTGDIR309E Unable to modify the Entry because the Entry to modify was not found.

Explanation

See message.

Action

Check the Search Criteria.

CTGDIR310E The modEntry was unable to modify the Entry because the aOldEntry parameter passed in was null.

Explanation

The parameter aOldEntry of the method modEntry is null.

Action

Check the old entry parameter and verify that value is not null.

CTGDIR311I No distinguished name was given to the modEntry method. Will use the existing one.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR312E Unable to modify entry. The entry is missing the naming attribute.

Explanation

No distinguished name attribute existing in the old Entry.

Action

Check the entry attribute \$dn.

CTGDIR313I Rename entry from *old DN* to *DN*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR314I Ignoring attribute *attribute ID*. It is empty and does not exist in the current Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR315I No modification items for entry: *DN*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR316E The entry will not be modified. There are no modification items.

Explanation

The modification items count is zero.

Action

Check the contents of the entry.

CTGDIR317E Unable to modify entry. Exception occurred while building ModificationItems object: *exception*

Explanation

An exception was encountered when the method modEntry tried to modify the Entry.

Action

Analyse the exception.

CTGDIR318E Deletion of multiple entries not yet supported by the deleteEntry method.

Explanation

The method deleteEntry is called with no entry.

Action

Invoke the method deleteEntry with a valid entry.

CTGDIR319E The deleteEntry method was called with no \$dn attribute in the Entry.

Explanation

There is no DN attribute in the entry.

Action

Check the DN attribute \$dn in the entry.

CTGDIR320I Searching for Entry with \$dn equal to *DN*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR321I Search for *DN* did not return any entries.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR322I The findEntry method found the Entry: *entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR323I The findEntry method could not add found entry: *entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR324I NULL entry returned by findEntry method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR325E Could not find a JNDI Entry with the given search criteria: *exception*

Explanation

An PartialResultException is encountered when trying to find the entry.

Action

Check the search criteria.

CTGDIR326E Could not find a JNDI Entry with the given search criteria: *exception*

Explanation

An NameNotFoundException is encountered when trying to find the entry.

Action

Check the search criteria.

CTGDIR327I The findEntry method search using the filter *filter* on the base DN *DN*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR328I Search for Entries using the filter *filter* did not return any entries.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR329I The findEntry method found the Entry: *entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR330I The findEntry method could not add found entry: *entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR331I NULL entry returned by findEntry method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR332E Could not find a JNDI Entry with the given search criteria: *exception*

Explanation

An PartialResultException is encountered when trying to find the entry.

Action

Check the search criteria.

CTGDIR333E Could not find a JNDI Entry with the given search criteria: *exception*

Explanation

An NameNotFoundException is encountered when trying to find the entry.

Action

Check the search criteria.

CTGDIR334I addDNFromCriteria: Vector instance.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR335I addDNFromCriteria: SearchCriteria instance.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR336I The addDNFromCriteria method was passed an SearchCriteria.rscSearch instance object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR337E Cannot mix \$dn matching with other attributes in a search.

Explanation

The method addDnFromCriteria encountered a SearchCriteria object equals to \$dn.

Action

Check the values in the object criteria.

CTGDIR338I The addDNFromCriteria method will add DN value to list: *search filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR339E Unknown object type in search filter: *class name: search filter*.

Explanation

The object in search filter must be an instance of Vector or SearchCriteria.

Action

Ensure the search filter specified is an instance of Vector or SearchCriteria.

CTGDIR340W Exception occurred while trying to terminate: *exception*

Explanation

An NamingException is encountered when trying to terminate the Connector.

Action

No action is required.

CTGDJZ451E Attribute *attribute* does not accept value '*value*'.

Explanation

The specified value is not valid for this attribute. 1)If the attribute is '\$operation', the following string values are valid: 'create', 'modify', 'delete' (case insensitive). If anything else is passed into the attribute an exception will occur. 2)If the attribute is 'dateFilter', it accepts a valid date in past.

Action

Provide valid values for the Connector's parameters. Consult the documentation for those that are supported.

CTGDJZ452E An IT registry book opened in REFRESH mode supports only CREATE operations.

Explanation

The IT registry Book this Connector is working with has been opened in Refresh mode, meaning only 'create' operations may be used for it.

Action

Set the operation to 'create' from the '\$operation' attribute or as a delta operation (for example, the operation set to delta tagged entry will override the operation attribute of the Connector). Alternatively, change the book mode to Delta (from the Init IT registry Function Component).

CTGDJZ453E No class type specified in the configuration of the IT registry Ci and Relationship Connector.

Explanation

In order to discover the schema of this Connector, the class type parameter must be provided. Otherwise the Component does not know which attributes to display.

Action

Set the required Class Type parameter from IT registry Ci and Relationship Connector's configuration panel.

CTGDJZ454I IT registry Ci and Relationship Connector will work with book: *book name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ455I The parameter *param name* was initialized with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ456I The name of the currently used book '*book name*' has been overridden to '*new name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ457I Use an IT registry system for the needed meta-data: '*use it registry*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ458I The book '*book name*' does not exist or is already closed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ459E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the IT registry Ci and Relationship Connector and must be provided.

Action

Provide a value for this parameter.

CTGDJZ460E Relationship '*relationship name*' cannot be updated.

Explanation

The specified relationship cannot be updated by the IT registry Ci and Relationship Connector and must be removed

Action

Remove this relationship or change the \$operation.

CTGDJZ461E Lookup Criteria '*criterion*' is not supported.

Explanation

The specified criteria is inappropriate for IT registry Ci and Relationship Connector.

Action

Change the criterion to 'equals' or uncheck 'Match Any'

CTGDJZ462E Filter Criteria '*criterion*' is not valid

Explanation

The criteria mentioned is not in proper format for the IT registry Ci and Relationship Connector.

Action

The attributes should be mention in format as specified below: (for example, cdm:Model=T61p,cdm:Manufacturer=IBM).

CTGDJZ463E An exception occurred while trying to close the database connection: *exception message*

Explanation

A database access error may had occurred. See the exception message for details.

Action

No action required.

CTGDJZ464E Configuration Item '*ci name*' cannot be updated.

Explanation

The IT registry contains only identifying attributes for each Configuration Item. And since they cannot be updated, no update operation is supported by the Connector.

Action

Change the \$operation of the IT registry Ci and Relationship Connector, or remove it from the AssemblyLine.

CTGDJZ465E Incorrect GUID value passed to attribute '*guid attr*'.

Explanation

The GUID attributes of the IT registry Ci and Relationship Connector require values from type 'com.ibm.di.fc.itregistry.ConfigurationItemId'. Such objects are

created by both this Connector and the Init IT registry FC.

Action

Change the value of the specified attribute.

CTGDJZ466I All IT registry items will be queried.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ468E Relationship '*relationship name*' cannot be fetched as 'isDeleted' is set.

Explanation

Relationships cannot be fetched by the IT registry Ci and Relationship Connector and must be removed for such configuration.

Action

Change the artifact type or uncheck isDeleted.

CTGDJJ001E The 'method' parameter must be set to use the Java Class FC.

Explanation

The required parameter method was not specified in the Java Class FC.

Action

Specify the method parameter in the Function Component.

CTGDJJ002E The 'javaClass' parameter must be set to use the Java Class FC.

Explanation

The required parameter javaClass was not specified in the Java Class FC.

Action

Specify the javaClass parameter in the Function Component.

CTGDJJ003E Unable to locate the method '*method name*' in class '*class name*'.

Explanation

The configured method in the Java Class FC could not be found.

Action

Verify that the configured Java Class and method exist and are valid. The operator should ensure the class can be found in the class path of the IBM Security Directory Integrator server.

CTGDJJ004E Unable to locate the method '*method name*' in class '*class name*'.

Explanation

The configured method in the Java Class FC could not be found.

Action

Verify that the configured Java Class and method exist and are valid. The operator should ensure the class can be found in the class path of the IBM Security Directory Integrator server.

CTGDJJ005E Function Component could not perform the configured method because it expected an Entry object but encountered an object of another type.

Explanation

The Java Class Function Component expected to perform a method using an Entry object but encountered an object of a different type.

Action

Verify that the data being passed to the Java Class Function Component are valid entries.

CTGDJJ006E Function Component failed to convert the object '*object type*' to a Date object. Exception occurred: *exception*

Explanation

See message.

Action

Verify that the data being passed to the Java Class Function Component is of valid Java object types. Review exception to find further details on the error.

CTGDJJ007E Function Component could not convert the object '*object type*' with the name '*object name*' to class '*class name*' because the class type was not recognized.

Explanation

See message.

Action

Verify that the data being passed to the Java Class FC is of valid Java object types.
Review the Reference Guide for more information.

CTGDIJ001E No default JDBC driver. The 'jdbcDriver' parameter must be set.

Explanation

The required parameter jdbcDriver is not set.

Action

Set the jdbcDriver parameter.

CTGDIJ002W An exception occurred while trying to disable autocommit mode in the database. The database does not allow autocommits to be disabled. Autocommit will always occur on the database itself.

Explanation

See message.

Action

No action is required. Any value configured for the parameter 'jdbcDriver' will not be used and autocommit will always occur on the database itself.

CTGDIJ003I Successfully built an entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ004W Unable to set the commit mode specified in the 'jdbcCommit' parameter with a value of '*commit mode*'.

Explanation

The Database does not support autocommit or autocommit mode cannot be enabled.

Action

No action is required.

CTGDIJ005W Unable to obtain schema information from the database. The following exception was encountered: *error*.

Explanation

Metadata cannot be obtained due to incorrect parameter or database error.

Action

Provide correct table name and schema name.

CTGDIJ006I Executing query to catch the metadata: *meta query*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ007I JDBC provider parameter being parsed with the following value: '*parameter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ008W JDBC provider parameter was encountered with no colon separator in line and will be skipped: '*parameter*'.

Explanation

Extra parameters cannot be extracted.

Action

Check current Database documentation and provide correct parameters separated with colon.

CTGDIJ009I JDBC provider parameter successfully parsed. The parameter name is '*parameter*' and the value is '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ010I Executing a ALTER SESSION SQL statement: *SQL statement.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ011I Executing a SELECT SQL statement to retrieve entries: *SQL statement.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ012E Cannot execute SQL Statement: *SQL statement.***Explanation**

Error occurred while executing the specified SQL statement.

Action

Specify correct SQL Statement.

CTGDIJ013I JDBC/ODBC Source Columns.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ014I Committing the SELECT statement issued.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ015I Entries has been selected.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ016I No more entries to retrieve from SQL search results.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ017I Preparing and executing the query SQL statement to find an entry: *SQL statement.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ018W Prepared SQL statement to find entry failed: *exception***Explanation**

After prepared SQL statement has been executed and error occurs due to an incorrect SQL statement or database error.

Action

Specify correct SQL Statement.

CTGDIJ019I Executing query SQL statement to find entry: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ020W No attributes found in the entry to modify.

Explanation

Entry which should be modified has no attributes.

Action

Provide some attributes in the entry.

CTGDIJ021E No attributes specified to modify.

Explanation

There are no specified attributes to modify.

Action

Set some attributes for modification.

CTGDIJ022I Set update attribute in prepared SQL statement: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ023W The prepared SQL statement to modify the entry will not be used. Exception occurred: *exception*

Explanation

An error occurred while prepared SQL statement was being prepared or executed.

Action

Verify the prepared SQL statement is correct.

**CTGDIJ024I Executing update SQL statement modify an entry:
SQL statement.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIJ025I Update SQL statement to modify an entry returned
'return value'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIJ026W The prepared SQL statement to add an entry will
not be used. Exception occurred: exception**

Explanation

An error occurred while the prepared SQL statement was being prepared or executed.

Action

Verify the prepared SQL statement is correct.

**CTGDIJ027I Executing update SQL statement to add an entry:
SQL statement.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIJ028I Update SQL statement to add an entry returned
'return value'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ029I Executing update SQL statement to delete an entry: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ030I Update SQL statement to delete an entry returned '*return value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ031W Exception caught in getNextSQLSelectEntry method while building an Entry: *exception*

Explanation

An error occurred while building the Entry.

Action

Verify the database is working correctly.

CTGDIJ032E No metadata available for the specified table: '*table name*'.

Explanation

No metadata available for specified table.

Action

Check whether the specified table name is valid or not in the jdbcTable parameter of the Connector.

CTGDIJ033E The jdbc table name was not specified.

Explanation

No table name was specified and it is required.

Action

Specify an appropriate table name. The `jdbcTable` parameter can be used to specify the table name.

CTGDIJ034E Null ResultSet is received when retrieving metadata of the table.

Explanation

No result returned from current request. The `ResultSet` object is null.

Action

Provide correct data for the `tablename` and `schema`.

CTGDIJ035I ResultSet object was received successful when retrieving metadata of the table. Message: *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ036I Metadata was received successful. The metadata contained *number of elements* elements.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ037E The table or view specified (*tablename*) was not found, or not accessible.

Explanation

The metadata received from the server was an empty list.

Action

Specify appropriate table name or schema name.

CTGDIJ038W Cannot build where clause (Advanced Link Mode).

Explanation

See message.

Action

No action is required.

CTGDIJ039E Cannot build where clause because the link criterai list is empty.**Explanation**

The where clause cannot be built. The link criteria is empty.

Action

Set link criteria.

CTGDIJ040E Cannot build where clause because an unknown criteria type was specified.**Explanation**

The where clause cannot be built. The link criteria specified is not valid.

Action

Set the link criteria correctly.

CTGDIJ041E Cannot build where clause (substring match).**Explanation**

The where clause cannot be built. The link criteria is not correct.

Action

Set link criteria correctly.

CTGDIJ042E Cannot build where clause (initial string match).**Explanation**

The where clause cannot be built. The link criteria is not correct.

Action

Set link criteria correctly.

CTGDIJ043E Cannot build where clause (final string match).**Explanation**

The where clause cannot be built. The link criteria is not correct.

Action

Set the link criteria correctly.

CTGDIJ044I Prepared SQL statement: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ045I Preparing to set prepared SQL statement value using attribute name '*attribute name*' and attribute value '*attribute value*'. The index is set at '*index*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ046E No MetaData description for attribute being set in the prepared SQL statement: '*attribute name*'.

Explanation

See message.

Action

Set the description for attributes.

CTGDIJ047I Set prepared SQL statement value for attribute to null at index apos;'*index*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ048I Java Class name of attribute value: '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ049I Type of attribute value: '*attribute type*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ050I Set 'LONGVARCHAR' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ051I Set 'VARCHAR' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ052I Set 'CHAR' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ053I 'CHAR' value found but has a different size from the column. The column size is '*column size*' and the value length is '*value length*'. The Connector will attempt to pad or trim the value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ054I Unable to pad or trim 'CHAR' value. The column size is '*column size*' and the value length is '*value length*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ055I Successfully padded or trimmed the 'CHAR' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ056I Set 'OTHER' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ057I Set 'INTEGER/TINYINT/SMALLINT' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ058W Exception caught while parsing Integer from 'INTEGER/TINYINT/SMALLINT' value: *exception*

Explanation

The value being parsed is not an Integer.

Action

No action is required.

CTGDIJ059I Set 'DECIMAL/BIGINT/NUMERIC' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ060W Exception caught while parsing Double from 'DECIMAL/BIGINT/NUMERIC' value: '*exception*'.

Explanation

The value being parsed is not numeric.

Action

No action is required.

CTGDIJ061I Set 'FLOAT' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ062I Set 'REAL/DOUBLE' value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ063I Set 'BIT' value: ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ064I Set 'DATE/TIME/TIMESTAMP' value: ''class name'', ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ065I Set 'java.sql.Timestamp' value: ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ066I Set 'java.sql.Date' value: ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ067I Set 'java.sql.Time' value: ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ068I Set 'java.util.Date' value: ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ069I Converting 'java.util.Date' to 'java.sql.Timestamp': ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ070I Creating a timestamp value using the current time in the format specified in the 'jdbcDateFormat' parameter with the 'SimpleDateFormat' class: ''date format''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ071W Exception encountered using the 'SimpleDateFormat' class to create timestamp value: *exception*

Explanation

The program encountered an exception while trying to create a timestamp value using the current time in the format specified in the jdbcDateFormat parameter SimpleDateFormat class.

Action

No action required. The program will find another method to create the timestamp.

CTGDIJ072I Creating a timestamp value using the current time with the 'DateFormat' class: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ073I Creating a timestamp value using the current time in the format 'yyyy.MM.dd hh:mm' with the 'SimpleDateFormat' class.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ074I Set timestamp value from 'SimpleDateFormat' class: '*date*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ075I Convert and set the timestamp value to a long value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ076I Set 'BLOB': *value*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ077I Set 'CLOB': *value***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ078I Set value for an unhandled type '*type*' as a string on column '*column name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ079W SQL warning encountered from prepared SQL statement: *SQL statement*.**Explanation**

See message.

Action

No action is required.

CTGDIJ080I Attempting to build an entry.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ081I Retrieving attribute value based on the column name '*column name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ082I Retrieved attribute of type 'CHAR/VARCHAR':
'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ083I Retrieved attribute of type 'OTHER': 'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ084I Retrieved attribute of type 'LONGVARBINARY'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ085I Retrieved attribute of type 'LONGVARCHAR'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ086I Retrieved attribute of type 'DECIMAL/INTEGER':
'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ087W When building Entry 'null' value has been received for INT: *value*.

Explanation

The value being parsed is not an Integer.

Action

No action is required.

CTGDIJ088I Retrieved attribute of type 'NUMERIC': '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ089W 'null' value has been received for NUMERIC while building Entry: *value*.

Explanation

The value being parsed is not numeric.

Action

No action is required.

CTGDIJ090I Retrieved attribute of type 'REAL/FLOAT/DOUBLE': '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ091W 'null' value has been received for REAL/FLOAT/DOUBLE while building Entry: *value*.

Explanation

The value being parsed is not real number.

Action

No action is required.

CTGDIJ092I Retrieved attribute of type 'DATE': '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ093W Retrieved attribute of type 'DATE': 'null'.

Explanation

Value that is provided is not Date.

Action

No action is required.

CTGDIJ094I Retrieved attribute of type 'TIME': '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ095W Retrieved attribute of type 'TIME': 'null'.

Explanation

The attribute retrieved is of type Time.

Action

No action is required.

CTGDIJ096I Retrieved attribute of type 'TIMESTAMP': '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ097W Retrieved attribute of type 'TIMESTAMP': 'null'.

Explanation

Value that is provided is not Timestamp.

Action

No action is required.

CTGDIJ098I Retrieved attribute of type 'VARBINARY': *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ099I Retrieved attribute value of type 'VARBINARY': 'null'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ100I Retrieved attribute value of type 'OBJECT': '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ101I Set value of attribute '*attribute name*': '*attribute value*'. The class type of the attribute is '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ102I Set value of attribute '*attribute name*': '*attribute value*'. The class type of the attribute is '*basic*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ103I Set value of attribute '*attribute name*': '*null*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ104W Exception encountered using the '*DateFormat*' class to create a timestamp value: *exception*

Explanation

The program encountered an exception while trying to create a timestamp value using the current time with the *DateFormat* class.

Action

No action required. The program will find another method to create the timestamp.

CTGDIJ105W Exception encountered using the 'SimpleDateFormat' class to create a timestamp value:
;exception

Explanation

The program encountered an exception while trying create a timestamp value using the current time in the format 'yyyy.MM.dd hh:mm' with the SimpleDateFormat class.

Action

No action required. The program will find another method to create the timestamp.

CTGDIJ106W Unable to set 'DATE/TIME/TIMESTAMP' value: '*class name*', '*value*'. Exception encountered trying to convert the timestamp value to a long: *exception*

Explanation

The program encountered an exception while trying create a timestamp value using the current time in the format 'yyyy.MM.dd hh:mm' with the SimpleDateFormat class.

Action

The program will continue without setting the timestamp value in the prepared SQL statement. You might need to check the timestamp value to ensure it is valid.

CTGDIJ107I 'CHAR' value found but has a different size from the column. The column size is '*column size*' and the value length is '*value length*'. The Connector will not pad or trim the value since the padding is disabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIJ108E The database '*Schema*' name is not provided.

Explanation

The Schema name is required for establishing connection with the database.

Action

Please provide the schema name to establish connection with the database.

CTGDIJ109E Unable to connect to the database (*exception message*). Verify that all the database connection parameters are correctly specified.

Explanation

Unable to connect to database. One reason could be that DB User name and password may be required for establishing connection with the database. The JDBC URL and driver specified should be valid.

Action

Try connecting to database after providing the correct database connection properties.

CTGDIJ110E The database user 'Password' is not provided.

Explanation

The DB User Password is required for establishing connection with the database.

Action

Please provide the user password to establish connection with the database.

CTGDIJ111E An error occurred while trying to create sql statement.

Explanation

An error occurred while trying to create sql statement.

Action

Check the sql parameters provided and try again.

CTGDIJ112E An exception occurred while trying to close the database connection: *exception message*

Explanation

A database access error may have occurred. See the exception message for details.

Action

No action required.

CTGDIJ113E An exception occurred while trying to clear warnings from connection object: *exception message*

Explanation

A database access error may have occurred. See the exception message for details.

Action

No action required.

CTGDIJ114E Unable to set 'BIT' value using attribute name: '*attribute name*' and attribute value '*attribute value*'.

Explanation

The attribute value provided could not be parsed.

Action

Provide correct value.

CTGDIJ115E Incorrect number of parameters in prepared SQL statement: *sql statement*

Explanation

There must be exactly one expression immediately following each question mark in a custom prepared SQL statement.

Action

Provide a correct prepared SQL statement.

CTGDIJ116W Unable to get MetaData for PreparedStatement: *exception*

Explanation

The call PreparedStatement.getParameterMetaData() failed with the given Exception. All parameters will be set with the PreparedStatement setObject(int, Object) method.

Action

Make sure that all parameters provided to the PreparedStatement can be automatically converted with the standard mapping from Java Object types to SQL types.

CTGDII001I The getNextEntry method received message of type *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII002I Topic factory obtained from script.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII003I Topic obtained from script.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII004I JMS Topic Session Established.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII005I Queue factory obtained from script.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII006I queueSession and sendSession are created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII007I readQueue initialized from script.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII008I sendQueue initialized from script.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII009I readQueue created: *queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII010I sendQueue created: *queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII011I JMS Queue Session Established.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII012I queueConnection created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII013I Get topic connection factory from System Queue.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII014I Get queue connection factory from System Queue.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII015I JMS load driver: *driver class name*.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII016I Map all JMS headers to/from attributes.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII017I Map specific JMS headers to/from attributes.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII018I No specific mapping of JMS headers to/from attributes.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII019I Map all JMS properties to/from attributes.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII020I Map specific JMS properties to/from attributes.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII021I Using backwards compatible mapping of all JMS properties to Entry properties.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII022I Topic listener started.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII023I Queue listener started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII024I Lookup filter: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII025I Lookup will remove JMS messages found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII026I No entries in QueueReceiver. Attempts to retrieve entries: *number of attempts*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII027I Lookup will not remove JMS messages found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII028I No entries in QueueBrowser: Attempts to retrieve entries: *number of attempts*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII029I Lookup mode not supported for Topic Connections.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII030I Received a message of type *message type*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII031I MQ format: '*MQ format*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII032I Perform backward compatible property mapping of all properties.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII033I Map all properties.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII034I Not set JMS property *property name*. The JMS property is either a JMS Header or does not start with 'jms.'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII035I Getting JMS header: *JMS header*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII036I No attribute for JMS header: *JMS header*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII037I Setting JMS header: *JMS header*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII038I Setting JMS reply to *value*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII039I No message to acknowledge.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII040I Using the configured Parser for this JMS Connector to generate a JMS text message.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII041I While generating JMS text message - using the value of the following Entry attribute for the contents of the JMS text message:**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII042I While generating JMS bytes message - using the serialized Entry object as the contents of this JMS bytes message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII043I While generating JMS object message - using the Entry object as the contents of this JMS object message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII044I Parsing a JMS text message with the following contents:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII045I Using the configured Parser for this JMS Connector to parse this JMS text message into an Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII046I While parsing JMS text message - there is no configured Parser for this JMS Connector; storing the raw text data in the 'message' Entry attribute.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII047I Deserializing JMS bytes message into Entry.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII048I Storing the raw bytes data of the JMS bytes message in the 'message' Entry attribute as a byte array.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII049I Successfully extracted Entry object from JMS bytes message.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII050I Map certain properties.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII051E No default JMS driver. The 'jms.driver' parameter must be set to use the JMS Connector.**Explanation**

See message.

Action

Set the `jms.driver` parameter.

CTGDII052E Unknown JMS Header: *JMS header.***Explanation**

See message.

Action

No action is required.

CTGDII053W Error while closing topic connection: *exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDII054W Error while closing queue connection: *exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDII055W Unable to deserialize bytes message: *exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDII056I Interrupted while waiting for messages. Closing connection to server.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN601E *parameter name JMS IBMMQ Driver parameter must be provided.*

Explanation

See message.

Action

Verify that the parameters for IBMMQ are correct and that the IBMMQ Driver is properly initialized.

CTGDKN602E *Bad broker parameter for IBMMQ. Expecting host:port. Exception occurred: exception*

Explanation

See message.

Action

Check used parameters for correct format and verify that the IBMMQ Driver is properly initialized.

CTGDKN603E *parameter name JMS IBM MQe Driver parameter must be provided*

Explanation

See message.

Action

Specify value for jms.mqe.driver parameter

CTGDKN604E *MQe does not support JMS Topics.*

Explanation

MQe only supports JMS Queues (the Point-to-Point mechanism in terms of the JMS specification), and not JMS Topics (the Publish/Subscribe mechanism in terms of the JMS specification).

Action

Only JMS Queues can be used with MQe. If JMS Topics are needed, a different JMS provider must be used.

CTGDKN605E *Either the 'js.jsfile' or 'js.jsscript' parameter must be set to use the JMS Script Driver.*

Explanation

See message.

Action

Specify the js.jsfile or js.jsscript parameter in the JMS Script Driver.

CTGDKN606E Unable to read custom script from file: *file name*.

Explanation

See message.

Action

Contact IBM support.

CTGDKN607E Unable to initialize ScriptEngine:

Explanation

See message.

Action

Contact IBM support.

CTGDKN608E Script error:

Explanation

An error occurred while executing the JMS initialization script.

Action

Check the JMS initialization script of the JMS Connector.

CTGDKN609E Exception occurred in Script Driver initialization: *exception*.

Explanation

The JMS initialization script has thrown an exception.

Action

Check the Script Driver initialization parameters and contact IBM support.

CTGDKN610E The JMS Driver is missing the required property 'property name'.

Explanation

See the error message.

Action

Check the JMS Driver configuration section and correct the problem.

CTGDKN611E Invalid numeric value for property ' *property name*': *property value*'.

Explanation

The specified property must contain a numerical value.

Action

Correct the value of the specified property.

CTGDKN612E The MQe JMS Driver could not open a port to receive notifications.

Explanation

See the error message.

Action

Check the exception message for more details.

CTGDKN613E Exception caught: *exception*

Explanation

An unexpected exception has been thrown.

Action

Check the exception message for more details.

CTGDKN614I Notification server terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN615I Received notification operation opcode: '*operation code*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN616I Connection accepted from *hostname: port number*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN617I Message transfer was triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN618E Invalid notification operation code:
'*operation code*'.**

Explanation

The client has sent a operation code that is not recognized by the notification listener.

Action

No help provided.

CTGDKN619I Message transfer was not triggered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN620E *parameter name* JMS WebsphereESB Driver
parameter must be provided.**

Explanation

See message.

Action

Verify that the parameters for WebsphereESB are correct and that the WebsphereESB Driver is properly initialized.

**CTGDKN621E Bad broker parameter for WebsphereESB.
Expecting host:port:sib_endpoint. Exception occurred:
*exception***

Explanation

See message.

Action

Check used parameters for correct format and verify that the WebsphereESB Driver is properly initialized.

CTGDKN201E Invalid values for the properties: '*property name*' and '*property name*'. Only one of the properties can have a value of true.

Explanation

Only one of the specified properties can be set to true at the same time.

Action

Set only one of the properties to be true, or set both to be false.

CTGDKN202E An unexpected exception has been thrown.

Explanation

See the error message.

Action

Check the exception for more details.

CTGDKN203I The remote JMS Provider could not be contacted at the moment: '*exception*'. The password change will be rejected.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN204I The password for user '*user name*' could not be stored as changed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN205I The password for user '*user name*' was successfully stored as added.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN206I The password for user '*user name*' could not be stored as added.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN207I The password for user '*user name*' was successfully stored as deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN208I The password for user '*user name*' could not be stored as deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN209I Loading JMS Driver: '*driver name*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN210I Could not configure JMS but the exception will be ignored: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN211I The linked exception is: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN212I Connecting to the JMS Provider...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN213I JMS connection started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN214I An exception occurred while sending password update message. The exception will be ignored.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN215E The required property '*property name*' is missing from the configuration file.

Explanation

See the error message.

Action

Check the configuration file for that property.

CTGDKN216I Exit requested.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN217I JMS connection closed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN218I The password for user '*user name*' was successfully stored as changed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN219I Successfully set port range 1414-1700.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN220I Unable to set port range, error: *error*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK001E The 'mode' parameter must be set to use the JMX Connector.

Explanation

The required parameter mode was not specified in the JMX Connector.

Action

Specify the mode parameter in the Connector.

CTGDJK002E Invalid 'mode' parameter set in the the JMX Connector: '*parameter value*'.

Explanation

The required parameter mode was specified in the JMX Connector but was set to an invalid value.

Action

Specify a proper value for the mode parameter in the Connector.

CTGDJK003E The 'mBeanTypes' parameter must be set to use the JMX Connector.

Explanation

The required parameter mBeanTypes was not specified in the JMX Connector.

Action

Specify the mBeanTypes parameter in the Connector. If you need to receive notifications from all MBeans, check the allMBeans parameter.

CTGDJK004E The 'url' parameter must be set to use the JMX Connector.

Explanation

The required parameter url was not specified in the JMX Connector.

Action

Specify the url parameter in the Connector.

CTGDJK005E The MBean name '*MBean name*' provided does not match any of the registered MBeans.

Explanation

An InstanceNotFoundException was encountered when the method addListener was trying to add NotificationListener. The NotificationListener handles the notifications emitted by the registered MBean.

Action

No action is required.

CTGDJK006E A communication problem occurred when talking to the MBean server. Exception occurred: *exception*

Explanation

An IOException was encountered when the method addListener was trying to add NotificationListener. The NotificationListener will handle the notifications emitted by the registered MBean.

Action

Check the network connection.

CTGDJK007E The MBean name '*object name*' provided does not match any of the registered MBeans.

Explanation

An InstanceNotFoundException was encountered when the method isNotificationBroadcaster was verifying the ObjectName name, an MBean, was registered in the MBean server.

Action

No action is required.

CTGDJK008E A communication problem occurred when talking to the MBean server. Exception occurred: *exception*

Explanation

An IOException was encountered when the method isNotificationBroadcaster was verifying the ObjectName name, an MBean, was registered in the MBean server.

Action

Check the network connection.

CTGDJK009E The MBean name '*object name*' provided does not match any of the registered MBeans.

Explanation

An InstanceNotFoundException was encountered when method removeListeners was trying to remove a listener from a registered MBean.

Action

No action is required.

CTGDJK010E A communication problem occurred when talking to the MBean server. Exception occurred: *exception*

Explanation

An IOException was encountered when method removeListeners was trying to removes a listener from a registered MBean.

Action

Check the network connection.

CTGDJK011E The listener object name '*object name*' is not registered in the MBean.

Explanation

An ListenerNotFoundException was encountered when method removeListeners was trying to remove a listener from a registered MBean.

Action

No action is required.

CTGDJK012I The listener object name '*object name*' has been successfully removed from a registered MBean.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJK013I Notification received: Type:*type object*, Sequence number:*SequenceNumber*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL001I Using LDAP SSL connection. Ensure that TCP port number is changed accordingly.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL002I Parsing next JNDI Provider Parameter: '*JNDI Provicer Parameter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL003E Bad JNDI Provider Parameter encountered: '*JNDI Provicer Parameter*'.

Explanation

The specified parameter is not properly set.

Action

Set the parameter in proper way.

CTGDIL004I Searching for entries from base DN '*DN*' using search filter '*filter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL005I There are more entries that can be processed in the search results.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL006I No entries returned in the search results.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL007W The throw limit was exceeded, when method selectEntries performed the search in the named context.

Explanation

This happened due to a user or system specified limit. Examples of such limits include client and server configuration limits such as size, time, number of hops, etc.

Action

Increase or remove the limit set.

CTGDIL008W The naming exception is encountered when the method selectEntries performed the search in the named context: *exception*

Explanation

The nature of the failure is described by the name of the subclass.

Action

No action is required.

CTGDIL009I No entries returned in the search results.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL010I No more entries to retrieve, so no entries returned in search results.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL011I Performing a directory search.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL012I Search filter for directory search is set to '*filter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL013E Cannot add entry because the naming parameter *parameter name* was not found in the entry.

Explanation

The specified parameter not presented.

Action

Set the parameter.

CTGDIL014W The modify entry operation failed because no distinguished name was found in existing entry.

Explanation

See message.

Action

Provide required distinguished name in the Entry.

CTGDIL015I Renaming entry from '*old DN*' to '*new DN*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL016I No distinguished name given, using existing one.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL017E The deleteEntry method was called with no *naming parameter* attribute.

Explanation

The deleteEntry method is called with no nameParameter attribute.

Action

Ensure the naming parameter is set before calling the deleteEntry method.

CTGDIL018I Searching for an entry where '*naming parameter*' equals '*DN*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL019I Searching for entry using filter '*filter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL020I No entries found while searching for entry in JNDI Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL021I Single entry found while searching for entry in JNDI Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL022I No entries found while searching for entry in JNDI Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL023I Multiple entries found while searching for entry in JNDI Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL024I JNDI Connector successfully added attribute value to attribute in entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL025W Modification of entry failed. Attribute already exists with given value. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDIL026W Modification of entry failed. An exception was encountered when the method `addAttributeValue` tried to add a given value to an attribute: *exception*

Explanation

See message.

Action

No action is required.

CTGDIL027I Retrieving next schema entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL028I The class definition for object class '*object class name*' is *class definition*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL029W An exception was encountered when retrieving a context containing the schema objects of the named object's class definitions. The name of the object whose object class definition is to be retrieved: *search DN*. The exception is: *exception*

Explanation

See message.

Action

No action is required.

CTGDIL030W A naming exception was encountered when retrieving the named object in the method `getAttributeSyntax`. The name of the object to look up is: *attribute name*. The exception is: *error*

Explanation

See message.

Action

No action is required.

CTGDIL031I Successfully replaced a given attribute value from an entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL032I Successfully removed a given attribute value from an entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL033I Successfully remove an attribute from an entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIL034W Modification of entry failed. An exception was encountered while replacing a given attribute with a certain value: *exception*

Explanation

See message.

Action

No action is required.

CTGDIL035W Modification of entry failed. An exception was encountered while removing a given attribute value from an entry: *exception*

Explanation

See message.

Action

No action is required.

CTGDIL036W Modification of entry failed. An exception was encountered while removing a given attribute from an entry: *exception*

Explanation

See message.

Action

No action is required.

CTGDIL037W Modifitation of entry failed. An attribute already exists with given value. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDJQ001I Using LDAP SSL connection. Ensure TCP port number is changed accordingly.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ002I Username specified, using Simple authentication.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ003I Using Anonymous bind.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ004I No username specified, using Anonymous bind.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ005I Next extra parameter: *parameter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ006I Parsed a JNDI extra parameter with no colon separator in the line: *parameter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ007I JNDI Provider Parameter: *parameter name=parameter name, parameter value=value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ008I Setting binary attributes to: *attribute value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ009I No binary attributes specified using default: *attribute names*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ010E Cannot perform VirtualListView search without sort attribute specified.

Explanation

The ldapVLVPageSize and dapSortAttribute attributes are dependant. If the user specifies ldapVLVPageSize to perform VirtualListView search, the ldapSortAttribute must be specified also.

Action

Specify a valid sort attribute value.

CTGDJQ011I Using Virtual List View. The sort attribute is *attribute name* and page size is *page size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ012I Requesting Sort Control for attribute *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ013I Dumping LDAP return attributes...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ014I Attribute: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ015I Using 'Paged Search' control: The page size is set to *page size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ016W The LDAP server did not confirm that it supports 'Paged Search' control.

Explanation

See message.

Action

No action is required. The Paged Search control may be ignored by the LDAP server.

CTGDJQ017I The selectEntries method will search the LDAP server for entries using the search base *DN* and the search filter '*search filter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ019I Entries were returned from the search.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ020I No entries returned from the search

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ021I The selectEntries method will return a NULL value for the entries.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ022I The selectEntries method will return no entries.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ023I A PartialResultException occurred and will be ignored.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ024I Request the next page using Virtual List View Control at offset *index*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ025W PartialResultException occurred while retrieving the next entry from the LDAP server. LDAP server does not support paged results.

Explanation

See message.

Action

Check LDAP server documentation to see if it supports paged results or set the attribute ldapPageSize to 0.

CTGDJQ026E The putEntry method failed because no distinguished name (\$dn attribute) was specified in entry.

Explanation

See message.

Action

Add the \$dn attribute to the Entry.

CTGDJQ027E Unable to modify the entry. A delta modify occurred and no distinguished name (\$dn attribute) was provided in the conn entry or the link criteria.

Explanation

See message.

Action

Add the \$dn attribute to the Entry.

CTGDJQ028I No distinguished name (\$dn attribute) was given. The existing distinguished name will be used to modify the entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ029E Unable to modify the entry. No distinguished name (\$dn attribute) was given and no existing entry was found.

Explanation

See message.

Action

Add the \$dn attribute to the Entry.

CTGDJQ030I Renaming entry from ''old DN'' to ''new DN''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ031I Initial rename of entry was unsuccessful. A manual move of entry will be attempted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ032I Initial rename of entry was unsuccessful. A manual move of entry will not be attempted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ033I The modify operation on attribute *attribute name* will be ignored. The attribute value would have been removed if the attribute was present in the current entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ034E Unable to modify the entry. The attribute *attribute name* at index *index* was specified to be modified but had an attribute value with an undefined operation code.

Explanation

See message.

Action

Ensure the attribute values of the modify work entry contains a valid operation code.

CTGDJQ035I The attribute *attribute name* will not be modified. The operation code for attribute value '*attribute value*' was unchanged.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ036I The entry *DN* will not be modified because there were no modification operations specified on the entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ038E LDAP Connector was unable to modify the entry. An exception occurred while creating a ModificationItem object that is used to modify the entry: *exception*

Explanation

See message.

Action

Check all attributes and attribute values specified to be modified in the Entry. See the exception for more information on the error.

CTGDJQ039I Dumping LDAP Connector Modification List...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ040I Modification item: *modification item*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ041I Finished dumping LDAP Connector Modification List.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ042I Attribute already exists with given value: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ043E The deleteEntry method was called with no '\$dn' attribute or link-criteria.

Explanation

See message.

Action

Verify the required \$dn is an attribute in the Entry or presence of link criteria.

CTGDJQ044I Searching for \$dn = DN.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ045I Object found for DN.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ046E Unable to find the Entry. The findEntry method encountered a PartialResultException: *exception***Explanation**

The error indicates the result being returned are partial, and that the operation cannot be completed.

Action

No action is required.

CTGDJQ047I LDAP Connector will look for Entry using the filter *filter* on the base DN *DN*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ048E Unable to find the Entry. The findEntry method encountered a PartialResultException: *exception***Explanation**

The error indicates the result being returned are partial, and that the operation cannot be completed.

Action

No action is required.

CTGDJQ049E Unable to find the Entry. The findEntry method encountered a NameNotFoundException: *exception*

Explanation

The error indicates the named component cannot be resolved because it is not bound.

Action

No action is required.

CTGDJQ050E Unable to convert the entry to a set of attributes. The AD unicode password is not a multi-value field (ref AutoMapADPassword).

Explanation

See message.

Action

Check the AD unicode password.

CTGDJQ051I The Attribute 'userPassword' was encoded and auto-mapped to 'unicodePwd'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ052I Ignoring unchanged attribute:*attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ053I Removing empty string value for attribute *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ055I Removing empty attribute: *attribute ID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ056E Unable to move the Entry. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ057E The moveEntry method removed the Entry '*DN*' but failed to add it again during rename.

Explanation

See message.

Action

Verify the LDAP server is still active and attempt to modify the entry again.

CTGDJQ058I Successfully moved entry '*DN*' to '*DN*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ059I Doing a compare of DN *DN* using filter *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ060I Comparison is true using filter *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ061I Comparison is false using filter *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ062I The modification was successful. The attribute value was added.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ063E Attribute already exists with given value: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ064E The modification failed. An exception occurred while trying to add an attribute value: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ065I The modification was successful. The attribute value was replaced.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ066E Attribute already exists with given value:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ067E The modification failed. An exception occurred while trying to replace an attribute value: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ068I The modification was successful. The attribute value was removed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ069E The modification failed. An exception occurred while trying to remove an attribute value: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ070I The modification was successful. All attribute values were removed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ071E The modification failed. An exception occurred while trying to remove all the attribute values: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ072I The page result size: *result size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ073I The page result size is unknown.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ074E Virtual List View Sort did not complete successfully. The return code returned was *return code*.

Explanation

See message.

Action

No action is required.

CTGDJQ075I Virtual List View List Size: *size*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ076I Virtual List View Target Offset: *offset*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ077I Target Offset: *offset*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ078I Virtual List View changed result set size from *size* to *size*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ079I Virtual List View Context ID is NULL.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ080I Getting the next Schema class.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ081I The object class *object class* attributes: *attributes*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ082W Unable to query server information: *error message*.**Explanation**

The LDAP Server does not support querying server information.

Action

No action is required.

CTGDJQ083I The LDAP server does not tell us about it's supported controls.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ085I The LDAP server does not tell us about it's supported extensions.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ086I Dumping LDAP Server Information...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ087W Unable to get server information.

Explanation

The LDAP Server does not support querying server information.

Action

No action is required.

CTGDJQ088I Supported Controls of LDAP Server:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ089I Control *control name: boolean.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ090I Naming Contexts (use in your search base parameter).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ091I No info on the naming contexts.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ092I Naming context at *indexindex: naming context*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ093I Finished dumping LDAP Server Information.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ094I The feature object passed to the addDNFromCriteria method is an instance of class Vector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ095I The feature object passed to the addDNFromCriteria method is an instance of class SearchCriteria.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ096I The feature object passed to the addDNFromCriteria method is an instance of class SearchCriteria.rscSearch.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ097E Cannot mix \$dn matching with other attributes in a search.

Explanation

See message.

Action

No action is required.

CTGDJQ098I Add DN value: ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ099E Unknown object type in search filter: *class name: object.*

Explanation

The type of the object in the filter is not supported.

Action

Use one of the supported types.

CTGDJQ100E LDAP Connector is unable to rebind to the LDAP server.

Explanation

All attempts to reauthenticate using the currently open connection but underlying reconnect function failed.

Action

Check the connection to the server.

CTGDJQ101E Failed to query the schema on the search DN DN. Exception occurred: *exception*

Explanation

An NameNotFoundException is encountered.

Action

Review the exception to find further details on the error.

CTGDJQ102E Failed to get the attribute syntax on the search DN DN. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ103E The VirtualListViewControl class cannot be loaded.

Explanation

An appropriate JAR library (which contains the VirtualListViewControl class) needs to be provided.

Action

Contact IBM support.

CTGDJQ104E The VirtualListViewControl class does not provide the required interface.

Explanation

A required method was not found in the currently loaded VirtualListViewControl class. Possibly a wrong version of this class was provided.

Action

Contact IBM support.

CTGDJQ105E The VirtualListViewResponseControl class cannot be loaded.

Explanation

An appropriate JAR library (which contains the VirtualListViewResponseControl class) needs to be provided.

Action

Contact IBM support.

CTGDJQ106E The VirtualListViewResponseControl class does not provide the required interface.

Explanation

A required method was not found in the currently loaded VirtualListViewResponseControl class. Possibly a wrong version of this class was provided.

Action

Contact IBM support.

CTGDJQ107W The selectEntries method was unable to perform the search. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ108W The compare method was unable to perform the search. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ109W Error while quering schema. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ110W Cannot close the connection to the LDAP Server. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDJQ111W Unable to find the Entry. The findEntry method encountered a NameNotFoundException: *exception*

Explanation

The error indicates the named component cannot be resolved because it is not bound.

Action

No action is required.

CTGDJQ112W The LDAP "ldapUrl" name is not provided.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ113W The Distinguished Name *url* cannot be parsed as a URL.

Explanation

The LDAP server returned a Distinguished Name marked as a URL, but it cannot be parsed as a URL.

Action

No action is required.

CTGDKN101I Adding LDAP entry for person with distinguished name '*distinguished name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN102I Successfully added LDAP entry for person with name '*person name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN103E Failed to add LDAP entry for person with distinguished name '*distinguished name*'. An exception occurred: *exception*

Explanation

The LDAP add operation failed. See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operating normally.

CTGDKN104E An exception occurred during password encryption: *exception*

Explanation

A password could not be encrypted.

Action

Verify that the configuration of the LDAP Password Store is correct.

CTGDKN105E An exception occurred during password decryption: *exception*

Explanation

A password could not be decrypted.

Action

Verify that the configuration of the LDAP Password Store is correct.

CTGDKN106E Failed to initialize encryption: *exception*

Explanation

The cryptography module of the LDAP Password Store could not be initialized.

Action

Verify that the configuration of the LDAP Password Store is correct.

CTGDKN107E Missing required property: *property name*.

Explanation

A required property could not be found in the configuration.

Action

Verify that the configuration of the LDAP Password Store is correct.

CTGDKN108E Failed to connect to the LDAP server. An exception occurred: *exception*

Explanation

Could not establish connection to the LDAP server. See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN109I Adding password values for user with distinguished name '*distinguished name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN110E Could not add password values, because the user name is empty.

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDKN111E Unable to add password values for user '*user name*' because the password store could not connect to the LDAP Server. An exception occurred: *exception*

Explanation

Could not establish connection to the LDAP server. See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN112I There is no LDAP entry for user '*user name*'. Will create one.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN113E Could not add password values for user '*user name*': *exception*

Explanation

An error occurred while adding password values for the user. See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct.

CTGDKN114I Deleting password values for user with distinguished name '*distinguished name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN115E Could not delete password values, because the user name is empty.

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDKN116E Could not delete password values for user 'user name'. Failed to obtain the original list of passwords for the user from the LDAP server: exception

Explanation

When the LDAP Password Store is about to delete password values for a user, it first obtains the existing password values from the LDAP server. This task has failed. See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN117E Could not delete password values for user 'user name': exception

Explanation

See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN118E Could not delete password values for user 'user name': exception

Explanation

See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN119I Checking if the LDAP server is accessible.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN120I Modifying password values for user with distinguished name 'distinguished name'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN121E Could not modify password values because the user name is empty.

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDKN122I Empty list of passwords found while modifying password values. Will remove the password attribute.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN123I There is no LDAP entry for user '*user name*'. Will create one.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN124E Could not modify password values for user '*user name*': exception

Explanation

See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN125I The password values to modify are *count*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN126I There is no LDAP entry for user 'user name'. Will create one.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN127E Could not modify password values for user 'user name': exception

Explanation

See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN128I No password attribute was found while trying to remove the password attribute for user 'user name'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN129E Failed to remove password attribute for user 'user name': exception

Explanation

See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN130I Verifying LDAP suffix.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN131E Suffix '*LDAP suffix*' does not exist in the LDAP server: *exception*

Explanation

The configured LDAP suffix is incorrect.

Action

Verify that the configuration of the LDAP Password Store is correct.

CTGDKN132E An exception occurred while verifying the LDAP suffix: *exception*

Explanation

Unexpected LDAP error is encountered while verifying that the configured LDAP suffix is correct. See the error message for details.

Action

Verify that the LDAP server is operational.

CTGDKN133W Password values will not be stored in the Password Store, because the user identifier is empty.

Explanation

This is an internal error.

Action

Inspect the error logs.

CTGDKN136W Additional information about a user will not be written to the Password Store because the user identifier is empty.

Explanation

This is an internal error.

Action

Inspect the error logs.

CTGDKN137I There is no LDAP entry for user '*user name*'. Will create one.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN138E Could not set additional information for user '*user name*': exception

Explanation

See the error message for details.

Action

Verify that the configuration of the LDAP Password Store is correct. Verify that the LDAP server is operational.

CTGDKN139I Setting additional information '*extra info*' for user with distinguished name '*distinguished name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ301I Terminate server request received while accepting connections.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ302I Creating dummy connection using IP Address '*IP Address*' and port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ303I LDAP Server Connector is already terminating. Not sending termination request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ304I Sending termination request to LDAP Server Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ305E No server Connector available or this Connector is no longer accepting connections.

Explanation

The Connector terminated and is no longer accepting connections

Action

No action is required.

CTGDJQ306I Connector already initialized with a java.net.Socket object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ307I Using provide java.net.Socket object for LDAP client session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ308I Listening for LDAP SSL connections on port: *port*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ309I Listening for LDAP connections on port: *port*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ310E Server Socket is not open, cannot accept client requests.

Explanation

LDAPServerConnector cannot listen on a specified port and cannot accept client connections.

Action

Check the parameters used to specify the port of the Server Socket. Verify the port is not already in use.

CTGDJQ311I Connector terminated by external request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ312E LDAP Server Connector was unable to get the next message because there is no client session.

Explanation

See message.

Action

Use the getNextClient method to get next client session.

CTGDJQ313E Failed to get the next message. An IOException occurred while reading the next request: *exception*

Explanation

See message.

Action

Verify the connection between server and client.

CTGDJQ314E LDAP Server Connector unable to get the next entry. The LDAPMessage object returned a NULL Request object.

Explanation

See message.

Action

No action is required.

CTGDJQ315I Starting packet dump...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ316I Finished packet dump.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ317I Start of packet dump of search result...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ318I Finished packet dump of search result.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ319I Start of packet dump of response...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ320I Finished packet dump of response.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ321I LDAP Server Connector closed the connection.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ322E Unable to get the boolean value from the byte buffer. The byte buffer contained more than one byte.

Explanation

See message.

Action

No action is required.

CTGDJQ323E The byte comparison failed. Expected the byte value *hex value* but found byte value *hex value*.

Explanation

See message.

Action

No action is required.

CTGDJQ324I Starting packet dump....

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ325I Finished packet dump.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ326E Unknown bind type was specified. Only simple and SASL binds are currently supported.

Explanation

See message.

Action

Specify a simple or SASL bind on the bind request.

CTGDJQ327E Unable to convert the entry into a control. An unknown control type was found in the entry: *control type*.

Explanation

The entry could not be converted to a control because an unknown control type was found in the entry. Only the paged search control is supported.

Action

Specify the paged search control in the entry.

CTGDJQ328E Unable to parse input message. The input message did not begin with a BER sequence: *character*.

Explanation

See message.

Action

No action is required.

CTGDJQ329E Unable to parse input message. The input message contained an unknown operation: *operation ID*.

Explanation

See message.

Action

No action is required.

CTGDJQ330E An unknown control type was encountered while parsing the input message: *control type*. Control will not be added to the entry.

Explanation

See message.

Action

No action is required.

CTGDJQ331I Adding control *object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ332E Unable to add control. Object was not of type LDAPControl: *object*.

Explanation

See message.

Action

No action is required.

CTGDJQ333I Message ID of LDAPMessage object: *message ID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ334I Dumping request entry...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ335E Unable to parse search filter. The search filter contained an unknown filter code: *filter code*.

Explanation

See message.

Action

No action is required.

CTGDJQ336I Hexadecimal value: *hexadecimal value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ337I Decimal value: *decimal value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ338I Hexadecimal value: *hexadecimal value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJQ339I Decimal value: *decimal value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII501E Skipping undefined flow specified

Explanation

A Flow id has been specified in the global.flows property that is not defined.

Action

Check the Error log for more information and adjust the configuration accordingly.

CTGDII502E Error starting migration for Flow

Explanation

An error occurred trying to start the Flow.

Action

Check the Error log for more information.

CTGDII503E Error starting synchronization for Flow
Explanation

An error occurred trying to start the Flow.

Action

Check the Error log for more information.

CTGDII504I Check that the source.changeDetectionType property is set to Sun, AD, SDS or Delta
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII505E Cannot handle delete of entry - lastKnownParent not found.
Explanation

@

Action

@

CTGDII506E Error parsing the DN attribute returned by the Active Directory Change Detection Connector
Explanation

The \$dn attribute returned by the Active Directory Change Detection Connector was invalid. This is most likely caused by an invalid response by the AD system.

Action

@

CTGDII507I migrating container entries using search filter
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII508E No \$dn attribute found in entry - skipping**Explanation**

@

Action

@

CTGDII509E Error parsing container DN**Explanation**

@

Action

@

CTGDII510W Type of entry not set - defaulting to 'person'**Explanation**

@

Action

@

CTGDII511E Parser not found**Explanation**

@

Action

@

CTGDII512I No RDN attribute found in entry read**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII513I migrating group entries using search filter**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII514I migrating person entries using search filter**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII515I Resetting change detection state for Flow**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII516I Mirroring hierarchy**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII517I Flattening hierarchy**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII518I Starting migration**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII519I containers to migrate**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII520I containers to skip

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII521I Property not set

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII522I You must specify where person entries are to be flattened under.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII523I You must specify where group entries are to be flattened under.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII524E Error re-parsing container DN

Explanation

@

Action

@

CTGDII525I Creating suffix in target

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII526W LDAPSync can not be simulated. Please change the simulate property

Explanation

@

Action

@

**CTGDII527W Please set the following property:
simulate=false**

Explanation

@

Action

@

CTGDII528W or use the commandline option: -0 actual

Explanation

@

Action

@

CTGDII529E Error dropping delta snapshot table

Explanation

@

Action

@

CTGDII530W Unable to delete delta store table

Explanation

@

Action

@

CTGDII531E Properties in error - cannot configure Connector

Explanation

@

Action

@

CTGDII532E Connector not found

Explanation

@

Action

@

CTGDII533I Initializing Connector

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII534I Include entries from the following container
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII535E Error initializing Connector
Explanation

@

Action

@

CTGDII536E Error during operation
Explanation

@

Action

@

CTGDII537I Searching with Connector
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII538I success
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII539E Error selecting entries with Connector**Explanation**

@

Action

@

CTGDII540E Error reading change entry with Connector**Explanation**

@

Action

@

CTGDII541E Check properties - unable to set up**Explanation**

@

Action

@

CTGDII542I Confirming container exists**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII543E Container not found

Explanation

@

Action

@

CTGDII544I Checking for property

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII545I Property not defined

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII546E Map file is missing

Explanation

@

Action

@

CTGDII547I Testing configuration and connections

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII548I Testing configuration and connection for Flow
Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII549I !SUCCESS! All connections worked correctly!
Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII550E !FAILURE! You must correct the problems listed
above****Explanation**

@

Action

@

**CTGDII551E error reading group.map file
Explanation**

@

Action

@

CTGDII552E error reading person.map file

Explanation

@

Action

@

CTGDII553E Error creating missing members file

Explanation

@

Action

@

CTGDII554E Error during initial parsing of source dn

Explanation

@

Action

@

CTGDII555I changelog number

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII556I failed

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII557E Error parsing source dn after target lookup**Explanation**

@

Action

@

CTGDII558I detected rename!**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII559I SIMULATED RUN - NO DATA WILL BE MODIFIED**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII560I Property is not set**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII561I Count for progress display**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII562E Error parsing source dn to handle moddn**Explanation**

@

Action

@

CTGDII563E Error parsing source dn for moddn/modrdn**Explanation**

@

Action

@

CTGDII564I Multiple entries were found in the target.**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII565W Duplicate entry**Explanation**

@

Action

@

CTGDII566W More entries exist**Explanation**

@

Action

@

CTGDII567W Unable to identify type of entry**Explanation**

@

Action

@

CTGDII568W Cannot find RDN attribute**Explanation**

@

Action

@

CTGDII569I Processing**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII570I current count

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII571I Skipping member because multiple entries were found in the target:

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII572I Skipping member because no entry was found in the target:

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII573W The following members were not added from source group

Explanation

@

Action

@

CTGDII574I cannot find these members of the Group
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII575W Skipping entry because member attribute is empty.

Explanation

@

Action

@

CTGDII626I No RDN value attribute found in entry read
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII669I accumulating membership
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII670W Unable to find member entry in source ldap
Explanation

@

Action

@

CTGDII671E Error reading next entry from source
Explanation

@

Action

@

CTGDII672E The property 'global.flows' is incorrect
Explanation

@

Action

@

CTGDII673E Error parsing source dn
Explanation

@

Action

@

CTGDII674I reading data
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII675I performing search

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII676E Error during initialization

Explanation

@

Action

@

CTGDII677W Unable to find entry in target system - unable to delete. Type:

Explanation

@

Action

@

CTGDII678E Source Endpoint form is missing

Explanation

@

Action

@

CTGDII679E Target Flow form is missing

Explanation

@

Action

@

CTGDII680E ** Form is missing
Explanation

@

Action

@

CTGDII681I Source Endpoint
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII682I Flow Settings
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII683I Endpoint
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII684E property not specified

Explanation

@

Action

@

CTGDII685I 0k

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII686E Not found or inaccessible!

Explanation

@

Action

@

CTGDII687I Mapping Files

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII688I Behavior

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII689I not set**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII690I Simulation Only - no data will be changed in the target**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII691I Simulation Only - no data has been changed in the target**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII692I Summary for Flow
Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII693I Total
Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII694I Add
Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDII695I Mod
Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII696I Unchanged**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII697I Skip**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII698E Error**Explanation**

@

Action

@

CTGDII699E Errors**Explanation**

@

Action

@

CTGDII700I Warnings

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII701I One or more group members were not migrated.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII702E These are listed in the GroupMembersMissing.log file located in the log folder

Explanation

@

Action

@

CTGDII703E To troubleshoot errors and warnings, check the log file

Explanation

@

Action

@

CTGDII704I Successful

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII705I Skipping**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII706I sourceUserObjectClass and/or sourceGroupObjectClass is undefined.**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII707E Error deleting old log**Explanation**

@

Action

@

CTGDII708E Error renaming old log**Explanation**

@

Action

@

CTGDII709E Error renaming previous log

Explanation

@

Action

@

CTGDII710E Error renaming latest log

Explanation

@

Action

@

CTGDII711E Error writing to log

Explanation

@

Action

@

CTGDII712E Property is missing or blank

Explanation

@

Action

@

CTGDII713I Property is invalid

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII714I Make sure that the search base is visible in the source system, for example from an LDAP browser.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII715I Also ensure that the credentials defined for the Source connection are authorized to see entries in this container.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII716I Invalid search filter specified

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII717I Make sure that the properties source.userObjectClass and source.groupObjectClass are correct.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII718I Also, make sure the client certificate for this server has been imported to the SDI keystore.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII719I Username and/or password properties are incorrect.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII720I Username and/or SearchBase properties are incorrect.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII721I Note: make sure the Changelog feature is enabled for the source directory server.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII722I Make sure that the user name specified references a Person entry that exists in the directory.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII723I Also that containers have been migrated before Person or Group entries.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII724I Make sure that the target suffix references a node that exists in the target.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII725I Start dumping**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII726I End dumping**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII727E Error retrieving property**Explanation**

@

Action

@

CTGDII728I flowKey is undefined**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII729E Error parsing dn to translate it**Explanation**

@

Action

@

CTGDII730E Error parsing newSuperior**Explanation**

@

Action

@

CTGDII731E Error parsing targetDn**Explanation**

@

Action

@

CTGDII732I Connector parameters**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII733E Error parsing source searchBase**Explanation**

@

Action

@

CTGDII734E Error opening file

Explanation

@

Action

@

**CTGDII735W Any entries that were not written to the target
can be found here**

Explanation

@

Action

@

CTGDII736I Source entry not written to target

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII737E Error initializing join connector

Explanation

@

Action

@

CTGDII738E Error joining data

Explanation

@

Action

@

CTGDII739E Error parsing

Explanation

@

Action

@

CTGDII740E Internal error

Explanation

@

Action

@

CTGDII751I Warning

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII752E Error creating log file

Explanation

@

Action

@

CTGDII753I Unable to create file

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII754E Error parsing rules**Explanation**

@

Action

@

CTGDII755I property name invalid**Explanation**

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII756E Multiple matches found by join**Explanation**

@

Action

@

CTGDII757E No match found by join**Explanation**

@

Action

@

CTGDII761E Error calling post-write AL**Explanation**

@

Action

@

CTGDII762E Error loading CI

Explanation

@

Action

@

CTGDII763E AssemblyLine name not specified

Explanation

@

Action

@

CTGDII769I Response AL in failed state

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII770I Response AL failed

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII771E Response AL not specified or not found
Explanation

@

Action

@

CTGDII772I Response AL initialization failed
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII773I Unknown condition type
Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII774E Rule-response error
Explanation

@

Action

@

CTGDII775E Writeback could not find entry with dn
Explanation

@

Action

@

CTGDII777E Endpoint is not an Active Directory Domain Controller

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII779E Error opening response log file

Explanation

@

Action

@

CTGDII780I Ensure that nothing is blocking your access to the system, for example a firewall.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII781I Ensure that the system is running and ensure the communication port is open.

Explanation

@

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDII782E Changelog is not enabled for the directory server

Explanation

@

Action

@

CTGDII785E SSL has been specified for this directory (ldaps://), but may not be enabled for the LDAP server itself

Explanation

@

Action

@

CTGDII786E SSL has not been specified for this server (ldap://), but may be required by the LDAP server.

Explanation

@

Action

@

CTGDJX001E Unable to process entry read because a line read in was not in the key:value pair format: '*line*'.

Explanation

See message.

Action

Ensure that the lines sent to the LDIF Parser are in the key:value pair format.

CTGDJX002I LDIF Parser encountered attribute '*attribute name*' which has a language tag. The Parser ignores language tag attributes.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJX003E Unknown LDIF changetype in: *value*.

Explanation

See message.

Action

No action is required.

CTGDJX004E Exception while encoding the string '*string*': *exception*

Explanation

See message.

Action

No action is required.

CTGDJX005I LDIF file to be tested: *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJX006E File not found: *file name*.

Explanation

See message.

Action

No action is required.

CTGDJX007I Entry: *entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJX008E Error reading line from file: *file name*.

Explanation

See message.

Action

No action is required.

CTGDJY001I The parameter 'attributeName' set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK301E The 'com.ibm.di.log.interface' parameter must be set to use the Log Connector.

Explanation

The required parameter com.ibm.di.log.interface was not specified in the Log Connector.

Action

Use a Logger with the com.ibm.di.log.interface parameter in the Connector.

CTGDKN301I Initializing the Password Store class...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN302I Initializing method received the object:
'object name'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN303I Checking Password Store for user 'user name'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN304I ...with passwords: 'password values'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN305I Storing password modifications for user:
'userName' with passwords: 'password values', timestamp:
'timestamp' and 'customData'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN306I Storing password additions for user: 'user
name' with passwords: 'password values', timestamp:
'timestamp' and 'customData'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN307I Storing password deletions for user: 'user name' with passwords: 'password values', timestamp: 'timestamp' and 'customData'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN308I Terminating the Password Store class.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN309I Storing additional information for user: 'user name' with extra data: 'additional information about the user'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV001E NotesException encountered while trying to retrieve the next entry from the Domino Server: 'exception ID', 'exception message'

Explanation

The Lotus Notes Connector encountered an exception while trying to retrieve the next entry from the Domino Server and was unable to continue.

Action

Verify that the Domino Server being queried is still running and that the information being retrieved is still present.

CTGDIV002I Opening Session to Domino Server: Session Type=''*Session Type*'',, Hostname=''*Hostname*'', User ID=''*User ID*'', Requested IIOP/SSL=''*Boolean*''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV003I Using specified 'IOR' in the connection information for opening the session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV004E NotesException encountered trying to create a session with the Domino Server: Class Name=''*class name*'', Exception=*exception*

Explanation

The Lotus Notes Connector encountered an exception while trying to create a session with the Domino Server and was unable to continue.

Action

Verify that the Domino Server being queried is still running and that the connection information in the Lotus Notes Connector has been configured properly.

CTGDIV005I Success establishing a Notes Session: Name=''*server name*'', Version=''*version number*'', Platform=''*operating system*''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIV006E Lotus Notes Connector unable to open database
'*database name*' on server '*server name*'.**

Explanation

The Lotus Notes Connector was unable to connect to the specified database on the Domino Server.

Action

Verify that the correct database name was specified for the Domino Server and that the connection information in the Lotus Notes Connector has been configured properly.

CTGDIV007I The Database connected to is full-text indexed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV008I The Database connected to not is full-text indexed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV009I The Connector will use full-text search on the database.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV010I The Connector will not use full-text search on the database.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV011E The specified search view '*search view*' was not found in the database. The Lotus Notes Connector is unable to select entries without a valid database search view.

Explanation

The Lotus Notes Connector was unable to find the specified search view in the database of the Domino Server.

Action

Verify that the correct search view was specified for the Domino Server. The `notesSearchView` parameter of the Lotus Notes Connector should be checked.

CTGDIV012I Database select statement: '*select statement*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV013E Unable to retrieve entries from Domino Server. NotesException encountered: *exception*

Explanation

The Lotus Notes Connector encountered an exception while trying to perform a search to retrieve a set entries from the Domino Server.

Action

Verify that the correct select statement was specified for the Domino Server. The `notesSelection` parameter of the Lotus Notes Connector should be checked.

CTGDIV014I No results returned from database search.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV015I Database search returned *number of documents* documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV016E The Lotus Notes Connector failed to create a new document on the Domino Server.

Explanation

The Lotus Notes Connector encountered an exception while trying to create a new document on the Domino Server.

Action

Verify that the document being added does not already exist on the Domino Server and that the Domino Server is still running.

CTGDIV017I Lotus Notes Connector building entry from retrieved document: *document attributes*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV018I Lotus Notes Connector's local Notes thread started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV019I Lotus Notes Connector's local Notes thread terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV020E Unable to create local Notes thread because the lotus.domino.NotesThread class was not found in the classpath of the program. Exception occurred: *exception*

Explanation

The Lotus Notes Connector encountered an exception while trying to create a local notes thread. The lotus.domino.NotesThread class is needed to create the thread and it was not found in the classpath.

Action

Verify the classpath of the program and ensure the Notes.jar file is in the classpath.

CTGDIV021E Lotus Notes Connector was unable to modify the entry because the entry was not found on the Domino Server.

Explanation

See message.

Action

Verify the document being modified exists on the Domino Server.

CTGDIV022E Lotus Notes Connector was unable to delete the entry because the entry was not found on the Domino Server.

Explanation

See message.

Action

Verify the document being deleted exists on the Domino Server and that the correct document is being chosen for deletion.

CTGDIV023I Adding attribute to entry: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV024I Attribute value added was null.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV025I Attribute value added was '*attribute value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV026I Attempting to build an entry in the Lotus Notes Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV027I Successfully built an entry in the Lotus Notes Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV028I Database search view is set to *search view*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV029I FTSearch filter on search view: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV030I FTSearch return code was *return code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV031W Reverting to basic search because FTSearch on database view failed: *filter*. NotesException occurred: Error=*error*, Error Text=*error text*

Explanation

See message.

Action

No action is required.

CTGDIV032I FTSearch filter on database: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV033I Formula Search filter on database: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV034I No documents found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV035I Found *number of documents* documents.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV036I Get document with Notes ID '*Notes ID*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV037I Document with Notes ID '*Notes ID*' not found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV038W Unable to get document with Notes ID: *Notes ID*. NotesException occurred: Error=*error*, Error Text=*error text*

Explanation

See message.

Action

Review the exception to determine the next course of action to take.

CTGDIV039I Will update *number of attributes* attributes in document.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV040E Lotus Notes Connector was unable to save the document it was trying to modify.

Explanation

See message.

Action

Verify you have the permissions to modify the document on Domino Server and that the Domino Server is still running.

**CTGDIV041E Lotus Notes Connector was unable to save the document it was trying to modify. Exception occurred:
*exception***

Explanation

See message.

Action

Review the exception encountered. The exception should provide more information on why the failure occurred.

CTGDIV042I Attribute '*attribute name*' will be updated with value '*attribute value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV043I Attribute '*attribute name*' will be updated with value '*attribute value*' which is of class type '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV044W Lotus Notes Connector could not terminate the local Notes thread. Exception occurred: *exception*

Explanation

See message.

Action

No action is required.

CTGDIV045I IIOP Session with specified IOR string is created. SSL is on.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV046I IIOP Session with specified IOR string is created. SSL is off.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV047I IIOP Session is created. SSL is on.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV048I IIOP Session is created. SSL is off.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV049I Session to Domino Server is created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV050I The specified port: '*port*' is bigger than 65535. The default port 80 will be used.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV051I No port is specified. The default port 80 will be used.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIV052E The specified match operation for the UNID or NoteID in the Link Criteria is not correct.

Explanation

The allowed match operation when using UNID or NoteID is only exact matching. The user has specified another one.

Action

Specify "equals" match operation. The case does not have effect.

CTGDIV053E Document with the specified UNID/NoteID was not found.

Explanation

Document with the specified UNID/NoteID was not found.

Action

No action required.

CTGDIV054E Connector already initialized. You must terminate it before initializing again.

Explanation

The user tries to initialize the Connector, for example through script, that has been already initialized.

Action

Check the values of the configuration parameters and the business logic of your solution.

CTGDIV055W Error occurred while executing the command ''SET_CURRENT''. Exception thrown: *exception*

Explanation

See message.

Action

Look at the exception message and try to fix the problem.

CTGDIV056W Exception occurred while terminating: *exception*

Explanation

The user may have loaded a Connector without initializing it. For example, through the `getConnector` method.

Action

Check the values of the configuration parameters and the business logic of the solution.

CTGDIV057E The Notes thread is not alive. Lotus Notes Connector cannot execute the required command against the Domino Server without an active Notes Thread.

Explanation

See message.

Action

Try to initialize the NotesThread first, that is, using the initNotesThread method.

CTGDIV058E Fatal Error while executing command against Domino Server: *exception*

Explanation

See message.

Action

Review the message returned from the Domino Server to see how to respond.

CTGDIV059I Did not find view *view name* in database *database name*: Database.getView returned NULL.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN001E Required Connector parameter 'mailServer' is not set.

Explanation

The specified Connector parameter mailServer is required, but not set.

Action

Set the Connector parameter mailServer.

CTGDJN002E Required Connector parameter 'mailUser' is not set.

Explanation

The specified Connector parameter mailUser is required, but not set.

Action

Set the Connector parameter mailUser.

CTGDJN003E Required Connector parameter 'mailFolder' is not set.

Explanation

The specified Connector parameter mailFolder is required for Addonly mode, but not set.

Action

Set the Connector parameter mailFolder.

CTGDJN004E The 'pollInterval' parameter set to an invalid value '*parameter value*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid pollInterval parameter in the Connector if the default value is not wanted.

CTGDJN005E The 'pollInterval' parameter set to an invalid value '*parameter value*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid pollInterval parameter in the Connector if the default value is not wanted.

CTGDJN006E The port specified as part of the 'mailServer' parameter must be a numeric value. Exception encountered while try to parse out port: *parameter value*

Explanation

See message.

Action

Specify a valid mailServer parameter in the Connector and ensure the port portion specified is numeric.

CTGDJN007I Opened mail folder '*folder name*' in read and write mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN008E Unable to initialize Mailbox Connector. The mail folder '*folder name*' does not exist on the mail server.

Explanation

See message.

Action

Set the Connector parameter mailFolder to a folder that exists on the mail server being connected to.

CTGDJN009I Initializing SSL settings.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN010I Disconnecting from mail server but exception was encountered while closing the mailbox: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN011W Mail message at index '*index number*' could have been deleted from the mail server and could not be retrieved. Error encountered while creating an Entry from a javax.mail.Message object: *exception*

Explanation

See message.

Action

Verify that the mail message was deleted.

CTGDJN012E The findEntry method could not process request because it was passed a search criteria one or more attributes it does not support.

Explanation

See message.

Action

Verify that the attributes for the search criteria are supported attributes. Use the following Supported attributes list : mail.messageid, mail.from, mail.to, mail.cc, mail.subject, and mail.messageid.

CTGDJN013E Unable to delete entry because more than one entry found to potentially remove.

Explanation

See message.

Action

Verify that the search criteria sent to the deleteEntry method will result in only a single Entry being returned to delete.

CTGDJN014E Unable to delete entry because the specified entry to delete could not be found.

Explanation

See message.

Action

Verify that the search criteria sent to the deleteEntry method will result in only a single Entry being returned to delete.

CTGDJN015E Unable to delete entry because the specified entry does not have the required property 'mail.message'.

Explanation

See message.

Action

Verify that entry being deleted has the mail.message property.

CTGDJN016I Folder does not support the expunge method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN017W Mail message at index '*index number*' could have been deleted from the mail server and could not be deleted. Error encountered while creating an Entry from a javax.mail.Message object: *exception*

Explanation

See message.

Action

Verify that the mail message was deleted.

CTGDJN018E POP3 protocol does not support appending of messages.

Explanation

The Mailbox Connector cannot be used in Addonly mode for POP3 server.

Action

Use the Connector in Addonly mode with another protocol(for example, IMAP).

CTGDJN019I Mail Folder is automatically set to '*INBOX*' for POP3 protocol.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN020E Mail Folder '*folder name*' does not exist on the mail server and parameter 'createFolder' is set to false.

Explanation

The supplied mail folder does not exist on the mail server and the parameter for auto-creation 'createFolder' is set to false.

Action

Supply an existing mail folder or set the 'createFolder' parameter to true.

CTGDJN021I The mail folder '*folder name*' did not exist on mail server and was automatically created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN022I The mail folder '*folder name*' was searched for messages, but none were found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN022E The Mailbox Connector cannot find mail matching the specified Link Criteria.

Explanation

The Connector did not find a message corresponding to the Link criteria. The Connector tried to add the message, but adding a message is not available in 'Update mode'.

Action

Verify that the looked-up mail message exists on the store.

CTGDJN023E No Entry is supplied in the output map for 'update' or 'add' operation.

Explanation

The input Entry object supplied for 'update' or 'add' operation is null.

Action

Verify that an Entry is supplied correctly.

CTGDJN024E Message in Attribute '*message*' is not in appropriate format.

Explanation

The supplied object is of type different from 'javax.mail.Message' 'javax.mail.Message[]'.

Action

Verify that the supplied object is of the appropriate type.

CTGDJN025E An Error occurred when appending the message to the specified folder: '*Exception*'.

Explanation

An internal error occurred while executing the javax.mail.Folder.appendMessage() method.

Action

No response needed.

CTGDJN026I The supplied messages were successfully added to the folder: '*folder name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN027E Unable to update entry, because the specified entry to update could not be found.

Explanation

See message.

Action

Verify that the search criteria sent to the modEntry method will result in only a single Entry being returned to update.

CTGDJN028E Unable to update entry, because the specified entry to update does not contain the message.

Explanation

See message.

Action

Verify that the 'mail.message' Attribute is mapped correctly.

CTGDJN029I Searching folder: '*folder name*' for subfolders.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN030I No subfolders were found in folder: '*folder name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN031I The folder: '*folder name*' does not exist on the store.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN032I The folder: '*folder name*' cannot be opened.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN033I Serching folders in namespaces: '*folder name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN034E The folder: '*folder name*' cannot be created successfully.

Explanation

The javax.mail.Folder.create() method failed, when attempting to create the specified folder.

Action

Verify that a folder can be created at the specified location and that the user has the necessary permissions.

CTGDJN035E The value for flag: '*flag name*' was not updated due to the following error: '*Exception*'.

Explanation

A MessagingException was thrown when trying to update a message flag. A reason might be that the store does not support this type of flag.

Action

Verify that the store supports this type of flag.

CTGDJN036I POP3 Messages do not support 'Flags.Flag.RECENT', therefore the Flag is not updated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJN037E Unable to initialize Mailbox Connector. The Mailbox Connector supports only the 'INBOX' folder when the POP3 protocol is chosen.

Explanation

The POP3 protocol supports only 'INBOX' folder on the server side, therefore when the Connector is in POP3 mode, you cannot specify another mail folder.

Action

Set the Connector parameter mailProtocol to 'IMAP' or supply 'INBOX' as the value for the mailFolder parameter.

CTGDIQ201I The 'watermark' parameter is set to *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIQ202E Queue with name *name* does not exist.

Explanation

Queue with given name does not exist.

Action

Specify a valid queue name.

CTGDIQ001E The Memory Stream Connector cannot add the entry because it has no Parser to write to.

Explanation

The Memory Stream Connector failed to add an entry because it had no Parser to write to.

Action

Verify that the Memory Stream Connector has a Parser configured to write to.

CTGDIQ101E Required Connector parameter 'queueName' is not set.

Explanation

The specified Connector parameter queueName is required, but not set.

Action

Set the Connector parameter queueName.

CTGDIQ102E Required Connector parameter 'jdbcTable' is not set.

Explanation

The specified Connector parameter jdbcTable is required, but not set.

Action

Set the Connector parameter jdbcTable.

CTGDIQ103E Unable to get next entry because a non-entry object was received from queue: '*object info*'.

Explanation

The Memory Queue Connector could not get the next entry because the entry in the queue was not a valid Entry object.

Action

Verify the entries in the Memory Queue Connector's queue are valid Entry objects.

CTGDIQ104E Queue with name *name* does not exist.**Explanation**

Queue with given name does not exist.

Action

Specify a valid queue name.

CTGDIC001I Delete selected items?**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC002E Cannot load a Connector with configuration type: *class*.**Explanation**

An internal error has occurred.

Action

Contact IBM support.

CTGDIC003W Delete table *table name*?**Explanation**

The delete operation will delete the delta table and commit the change. The operation is permanent and there is no possible rollback of this transaction.

Action

Confirm if the delta table is to be deleted and proceed with the operation.

CTGDIC004I Table *table name* deleted.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC005I Server says it supports the Paged Search control.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC006W Unable to determine whether the LDAP Server supports paged searches. Verify the LDAP Server supports paged searches.

Explanation

The Server did not give any response around the ability to support paged searches. Paged searches may or may not be supported.

Action

Verify whether the LDAP server supports Paged Search control before using Paged Search.

CTGDIC007W Unable to perform paged search. This LDAP server does not support paged search.

Explanation

The LDAP Server does not support paged search.

Action

Paged search cannot be used.

CTGDIC008W Unable to lookup changelog information. The LDAP server does not provide server information.

Explanation

The LDAP Server does not provide server information, therefore it is not possible to query the server for the changelog base.

Action

Use another method to find the changelog base.

CTGDIC009W Unable to lookup changelog information. The Context attribute 'firstchangenumber' does not exist on the LDAP Server.

Explanation

The Context attribute "firstchangenumber" does not exist on the LDAP Server.

Action

Check the LDAP Server configuration.

**CTGDIC010I The First Change number is set to *first number*.
The Last Change number is set to *last number*.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIC011W Unable to retrieve Changelog base name. The
'changelog' attribute does not exist in the LDAP server
info entry.**

Explanation

The "changelog" attribute of this LDAP server does not exist.

Action

Use another method to find the Changelog base name.

CTGDIC012I LDAP Server changelog base name: '*changelog*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC013W Delete table *table name*?

Explanation

The delete operation will delete the named table and commit the change. The operation is permanent and there is no possible rollback of this transaction.

Action

Confirm if the table is to be deleted and proceed with the operation.

**CTGDIC014W Unable to query schema until the Connector is
configured.**

Explanation

The Connector has not been configured. The schema cannot be queried.

Action

Configure the Connector before querying the schema.

CTGDIC015W Unable to lookup change number information. The LDAP server does not provide server information.

Explanation

The LDAP Server does not provide server information, therefore it is not possible to lookup the first/last change number.

Action

Use another method to find the first/last change number.

CTGDIC016E Enter the WSDL URL first.

Explanation

In order to retrieve the services from a WSDL file, the location to such should be specified.

Action

Enter a valid WSDL file location in the WSDL URL field.

CTGDIC017E No services were found in the specified WSDL file.

Explanation

The WSDL file specified in the WSDL URL parameter contains no services.

Action

Check the WSDL file. If it does not contain any services then it is an invalid WSDL file.

CTGDIC018E Enter a service name first.

Explanation

Each endpoint/operation is associated with a service. In order to see all endpoints/operations you must enter a service first.

Action

Enter a service name first. You can use the service button to discover all services in the WSDL file.

CTGDIC019E No endpoints were found in the specified WSDL file.

Explanation

The WSDL file specified in the WSDL URL parameter contains no endpoints.

Action

Check that the WSDL file is a valid one.

CTGDIC020E No operations were found in the specified WSDL file.**Explanation**

The WSDL file specified in the WSDL URL parameter contains no operations.

Action

Check that the WSDL file is a valid one.

CTGDIC022E The attribute '*attribute name*' is already mapped.**Explanation**

The specified attribute is already mapped and cannot be mapped a second time.

Action

Select an alternate attribute to map in the attribute map.

CTGDIC023E Exception encountered while creating component of type '*component type*': '*error message*'.**Explanation**

See message.

Action

Review the error message and exception to find further details on the error.

CTGDIC024W Unable to update component. The referenced component no longer exists: *file name*.**Explanation**

The component could not be updated because it no longer exists.

Action

Review the exception to find further details on the warning.

CTGDIC025E Exception encountered while updating an external component.**Explanation**

The component could not be updated because an error was encountered.

Action

Review the exception to find further details on the error.

CTGDIC026E The remote Config *Config file* cannot be found on server *server name*.

Explanation

The configuration instance specified in the Config parameter of AssemblyLine Function Component could not be found on the remote server.

Action

The operator should check if the specified config parameter exists on the remote server.

CTGDIC027E Connection to server *server name* cannot be obtained.

Explanation

The remote server instance specified in the AssemblyLine Function component's server parameter may not be currently active.

Action

The operator should make sure that the specified server instance [hostname:port] combination is active on the remote server and then try to establish a connection again.

CTGDIC028E No server configured.

Explanation

The Server configuration parameter is required for the query configuration operation to work.

Action

The Operator should enter a valid remote IBM Security Directory Integrator server information [hostname:port] in the AssemblyLine function component's server parameter fields and then perform the query configuration operation.

CTGDIC029I The application will not function properly without the IBM Security Directory Integrator install directory. Specify the IBM Security Directory Integrator install directory.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC030E Installation directory specified is not valid. A local IBM Security Directory Integrator installation is required for the application to run.

Explanation

See message.

Action

Specify a valid local IBM Security Directory Integrator installation directory so the application can run properly.

CTGDIC031E Exception encountered while loading the Config file: '*file name*'.

Explanation

The application was unable to load the specified Config file.

Action

Review the exception to find further details on the error.

CTGDIC032W Exception encountered while loading the Config file: '*file name*'.

Explanation

The application was unable to load the specified Config file.

Action

Review the exception to find further details on the error.

CTGDIC033E Unable to load Config file. Cannot determine folder for referenced Config file: '*file name*'.

Explanation

The application was unable to load the specified Config file because the folder where the Config file is located could not be found.

Action

Check the file system where the Config file should be located and ensure it exists.

CTGDIC034E Unable to save file because an exception was encountered.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIC035E Unable to load BaseEditor because there is no quick-edit object.

Explanation

An internal error has occurred.

Action

Contact IBM support.

CTGDIC036E Exception occurred while downloading properties.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIC037I Update completed successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC038E Exception occurred while upload properties.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIC039I The connector did not return any schema information. Do you want to open the connection and read one entry?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC040I Do you want to clear the current schema before updating?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC041I Do you want to clear the current schema before updating?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC043I The Component returned an empty entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC044I No schema information returned. Would you like to read an entry?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC045I Solution directory updated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC046E The folder already exists: '*folder name*'.

Explanation

A folder with that name already exists.

Action

Choose a unique name and try again.

CTGDIC047E Attribute already assigned to attribute '*attribute name*'.

Explanation

This attribute name has already been used for another attribute.

Action

Use another attribute name that is not already used.

CTGDIC048E Error: '*error message*'

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIC049E Exception encountered while opening the configuration file: '*error message*'

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIC050E Unable to open the configuration file. An exception occurred: 'error message'

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIC051I Solution directory created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC052I Unable to build configuration file. An exception occurred: 'error message'

Explanation

See message.

Action

Review the attached Exception to find further details on the error.

CTGDIC053I Unable to create folder 'name'. An exception occurred: 'error message'

Explanation

See message.

Action

Review the attached exception to find further details on the error.

CTGDIC054E Target folder 'folder name' is not a folder.

Explanation

The name specified is not a folder. The problem occurred while trying to build a configuration file.

Action

Check the configuration file.

CTGDIC055E Unable to remove object from configuration file. An exception occurred: '*error message*'

Explanation

The problem occurred while trying to remove an object from the configuration file.

Action

Check the configuration file.

CTGDIC056E Cannot determine folder for object '*object name*'.

Explanation

While trying to build the configuration file, the object mentioned was not recognized and could not be placed in any folder.

Action

Check the object and the configuration file.

CTGDIC057W Cannot find cached configuration for file '*file name*'.

Explanation

While trying to build the configuration file, the named object did not have a cached copy.

Action

Check the object and the configuration file. The named object was probably deleted. Add the object back to the configuration as needed.

CTGDIC058W Using cached version of file '*file name*'.

Explanation

While trying to build the configuration file, the file containing the named object was not found and a cached copy was used instead.

Action

The named object was probably deleted. Add the object back to the configuration as needed.

CTGDIC059E An unsupported action was encountered. You can only open configuration files that exist in your workspace.

Explanation

Only IBM Security Directory Integrator configuration files that exist in your workspace can be opened. Using File/Open to open files outside the workspace is not supported.

Action

Use the File/Import command to import the files into your workspace project.

CTGDIC060E Cannot create the specified directory: '*directory name*'.

Explanation

The named directory could not be created.

Action

Verify that the file name is correct. Verify that the file system permissions allow the file to be written.

CTGDIC061E The specified solution directory '*name*' is a file.

Explanation

The solution directory is a file.

Action

Remove existing file, rename the file, or use another name for the solution directory.

CTGDIC062E Created the file '*file name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC063I Do you want to stop the local server running on '*server address*'?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC064I The server is being started...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC065I This will clear the current object(s) and restore the value to the inherited one.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC066I When the Skip Lookup option is selected, no 'Before/After Lookup' and 'On Multiple Entries' hooks are invoked. Also, no add is done in Update mode if an entry is not found to match the criteria.

Explanation

Make sure that your solution takes into account these restrictions.

Action

No response needed.

CTGDIC067I The Schema item '*schema name*' already exists.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC068I The file has been changed on the file system. Do you want to reload the editor?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC069I Referenced component no longer exists: '*file name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC070I Unknown class encountered. Unable to reattach to the class '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC071I The parent is not a container.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC072I Th Server Mode Connector '*Connector name*' appears after another Server Mode Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC073I The Connector '*Connector name*' references unknown property '*property name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC074I The Connector '*Connector name*' references unknown string '*string value*' which is not defined in the schema.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC075I The attribute map '*attribute map name*' references undefined/unavailable work attribute '*attribute name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC076I Local development server launched ...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC077I Process exit code: '*exit code*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC078I The Connector '*Connector name*' references the object '*object name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC079I You have not updated the solution directory and not doing so may affect your connection to this server. Do you want to update the solution properties before saving?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC080I Resource already exists. Do you wish to overwrite? Overwrite: '*File name*' Last modified: '*Last modified*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC081I Cannot find a form to display for object class *Object Class*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC082I The file .rs.xml cannot be imported, please export the project and then import that file.

Explanation

The file .rs.xml in every project is special, and cannot be directly imported into another project. Instead, the whole project should be exported, and the resulting file can be imported.

Action

Export the project in question, then import the exported file.

CTGDIC083I A restart of the IBM Security Directory Integrator server is required to activate changes made to the system store of a running IBM Security Directory Integrator server.

Explanation

The IBM Security Directory Integrator server cannot change its system store configuration while running. A restart of the server is required to active changes.

Action

Stop the server and then start it again.

CTGDIC084I IBM Security Directory Integrator Version: 7.2 This plug-in is provided by IBM Corp. Your use of this plug-in is governed by the license that was agreed to when the plug-in was installed as part of a feature installation. Licensed Materials - Property of IBM Corp. Copyright IBM Corp. and other(s), 2002, 2013. All Rights Reserved.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC085I Do you want to restore the file from the runtime configuration of the project?

Explanation

The Configuration Editor maintains a copy of each project file in a runtime configuration. When you save a component to disk it is also copied to the runtime configuration.

Action

Answer yes to recreate the file with the copy from the runtime configuration.

CTGDIC086W A Property can only be exposed once.

Explanation

This message is displayed when an attempt is made to expose a property more than once.

Action

No action is required.

CTGDIC087W An item with that name already exists.

Explanation

Items must have unique names.

Action

Choose another name.

CTGDIC088W Error while renaming to '*new name*'.

Explanation

The component could not be renamed because an error was encountered.

Action

Consider the attached error message, and choose another name.

CTGDIC089W You must configure sandbox settings before running the AssemblyLine in Record or Playback mode.

Explanation

The AssemblyLine must have a database name specified in order to record or playback an AssemblyLine.

Action

Use the Sandbox Settings and configure a database name.

CTGDIC090W This Attribute Map item contains an expression. If it is changed, it must be changed to javascript code.

Explanation

This Attribute Map item is of the deprecated type expression. There is no editor to change an expression. Using the javascript editor on this item will cause it to be changed to type javascript.

Action

Answer OK to go ahead with the change.

CTGDIC091W The proxy AssemblyLine was successfully updated.

Explanation

The proxy AssemblyLine was updated with the changes from the simulation settings of the current AssemblyLine.

Action

CTGDIC092E The ikeyman.exe file not found. Searched in folders *path1* and *path2*.

Explanation

The IBM Key Management could not be started, because the executable could not be found.

Action

Verify the ikeyman.exe file exists.

CTGDIC093E No // found in '*url*'. Hostname cannot be determined.

Explanation

The URL prefix is parsed to determine the hostname and port. There should be a // in front of the hostname.

Action

Enter a correct URL prefix.

CTGDIC094I Delete selected items? There will be no undo.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC095W Component '*name*' automatically moved to the DataFlow section.

Explanation

The named component had the wrong mode for being in the Feed section, and was automatically moved to the DataFlow section.

Action

If necessary, change the mode and move the Connector to the Feed section.

CTGDIC096W The AssemblyLine is still running on the server. Do you want to stop it?

Explanation

When you close a run window you have the option of leaving the assemblyline running or stop it. You can also stop or reopen the assemblyline from the Servers view.

Action

Choose yes or no as appropriate.

CTGDIC097W Could not locate *name* while resolving dependencies.

Explanation

When you import a configuration file, all the resources that are needed are also imported into the project. This message indicates that one such resource could not be found, it may have been deleted from the configuration file.

Action

Verify that this does not cause a problem.

CTGDIC098I Connection to *DataBase* Successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC099W Connection to *DataBase* Failed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC100I The branch '*Branch name*' has no preceding IF/ELSEIF component.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC101I The case '*Case name*' is not inside a Switch component.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC102I The attribute map for '*Connector name*' is empty (auto-mapping is either off in the AssemblyLine or the connector is not part of an AssemblyLine).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC103I Do you want to replace the reference to '*Property name*' with the value '*Value name*'?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC104I The system store configuration has no value for parameter: {0}

Explanation

The configuration for the system store is incomplete. Open the system store configuration screen and fill in the missing parameter.

Action

CTGDIC105E The specified namespace is already defined

Explanation

There can only be one definition for a namespace.

Action

Either delete the existing definition for the namespace, or choose another name for the namespace.

CTGDIC106I *Run option on Server name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC107W **An Operation with that name already exists.**

Explanation

There can only be one operation with a given name.

Action

Choose another name.

CTGDIC108E **The system encountered an internal error while trying to validate a product license. Message: *message*.**

Explanation

An internal error is preventing validation of the product license.

Action

Contact IBM support.

CTGDIC109E **The system cannot find an enrolled product license.**

Explanation

An enrolled product license could not be found.

Action

In order to use Security Directory Integrator, you need to ensure that a valid license is enrolled. If you experience any problems with licensing, you should contact your IBM representative or authorized dealer for assistance.

CTGDIC110E **The evaluation period has expired.**

Explanation

The evaluation period for this copy of Security Directory Integrator has now expired.

Action

This copy of Security Directory Integrator is licensed for use for a limited period only. This copy of Security Directory Integrator has now exceeded the licensed period and will no longer execute. You can purchase a full license for unlimited use of the product by contacting your IBM representative or authorized dealer.

CTGDIC111W There are *number of days* days left in the evaluation period.

Explanation

The evaluation period for this copy of Security Directory Integrator has the specified number of days to run until expiry.

Action

This copy of Security Directory Integrator is licensed for use for a limited period only. This copy of Security Directory Integrator will continue to execute for the specified number of days, but will then expire and not execute in the future. You can purchase a full license for unlimited use of the product by contacting your IBM representative or authorized dealer.

CTGDIC112E The evaluation period is invalid.

Explanation

The evaluation period for this copy of Security Directory Integrator is invalid.

Action

This copy of Security Directory Integrator is licensed for use for a limited period only. This copy of Security Directory Integrator appears to have more than the maximum allowed number of days (90) remaining in the evaluation period.

CTGDIC113E No help page found for topic '*topic*'.

Explanation

There was an error while trying to display the help for the selected topic.

Action

Search the Security Directory Integrator documentation on the IBM website for help on the selected topic.

CTGDIC114E Parameter '*parameter name*' is required.

Explanation

The named parameter must be given a value.

Action

Specify a value for the parameter.

CTGDIC115E There are *number* missing values.

Explanation

Several parameters have not been given a value.

Action

Specify a value for all parameters that require a value.

CTGDIC116W AssemblyLine terminated - showing last 10 log messages (use view log file to view entire log)

Explanation

The AssemblyLine was terminated and logging of messages is suspended until the log has been drained. Only the last ten lines are shown but you can use the View log button to view all log lines from the AssemblyLine.

Action

Specify a value for all parameters that require a value.

CTGDIC117W Software Update is disabled in this product.

Explanation

Software update is not supported in this product. To use this product with other Eclipse plugins you should install Security Directory Integrator in a separate Eclipse installation.

Action

Install this product in a different Eclipse installation for use with other plugins.

CTGDIC118E An error occurred while retrieving the CDM version.

Explanation

The used CDM meta-data source is not available. Depending on the used source either the idmlcert.jar is missing, or the CDM meta-data of the IT registry has been corrupted.

Action

Try changing the meta-data source to the alternative (either the JAR file or an IT registry system). If the problem persists, verify the location of the JAR file (/jars/3rdparty/IBM/cdm/idmlcert.jar) and the integrity of the meta-data in the remote IT registry system.

CTGDIC119E Failed to connect to the IT registry database (parameters: *it_registry_credentials*). The thrown exception is: *exception*.

Explanation

A connection could not be established with the IT registry database.

Action

Verify that the IT registry is running and the used credentials are correct.

CTGDIC120I Successfully connected to the IT registry database (parameters: *it_registry_credentials*).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDI3244I Successfully connected to the database (parameters: *credentials*).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDI3245I Failed to connect to the database (parameters: *credentials*). The thrown exception is: *exception*.

Explanation

A connection could not be established with the database.

Action

Verify that the database is running and the used credentials are correct.

CTGDIC121I No types were found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC122I Common Data Model version is 'cdm'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC123E AssemblyLine failed: *string*

Explanation

The assemblyline failed while running or stepping through it.

Action

Check the log in the console view for more information about the error.

**CTGDIC124I AssemblyLine Completed- *number* record(s) read-
number record(s) written- *number* error(s)*string***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC126I *number* record(s) record(s) found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC127I No MSS were found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC128I The Component has reached the end of the data source.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC129I Input value:- *string*Output value: *string*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIC130I AssemblyLine Completed- *number* record(s) read-
number record(s) added- - *number* record(s) modified- *number*
record(s) unchanged- - *number* error(s)*string***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIC131I An error occurred while initializing component
[*name*].**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC132I An error occurred in component [*name*].

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC133I An error occurred while executing AssemblyLine Hook *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC134I Illegal character '*character*' in name.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC135E Parameter '*parameter name*' must be a number.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC136E Parameter '*parameter name*' cannot be less than *value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC137E Parameter '*parameter name*' cannot be greater than *value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC138E Value for 'label' must be a list of increasing numbers.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC139E There are not that many days in the month.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC140W For some combinations of Day and Month this Scheduler will not run.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC141W Some months this Scheduler will not run.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC142E Can not find a suitable protocol.**Explanation**

A suitable protocol could not be found to connect to target computer with the given configuration parameters.

Action

In order to get the list of suitable protocol(s) please provide sufficient and correct configuration parameters.

CTGDIC143W Some files could not be refactored. Check Error log for details.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC144W Unable to locate the connection form for this component. This is mostly likely because a jar or zip file is missing. Make these library files available to SDI by copying them anywhere under the 'jars' subfolder of the SDI installation directory. Or if you want to leave these files in place and point to them instead, then add their file/folder paths to the 'com.ibm.di.loader.userjars' property. You must restart SDI for changes made to take affect.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIC145W The port for your *name* SDI Server is already in use at *address* in the Solution Directory *directory name*.

Explanation

The Solution Directory, which is used by the connected SDI Server, does not match the Solution Directory in the Default Server Document.

Action

Ensure that every SDI Server uses a unique API port. This allows you to run several SDI Servers with different Solution Directories. You can access all the SDI Servers using unique API port.

CTGDKE001I Use a named ExternalProperties object for this call.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE002I Listing property store *property store name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE003E No Config driver for: *URL*.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE004E Missing password for Encrypted file.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE005I Inside the getNamespace method: name=*object*, namespace contains the key=*boolean*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE006I Registering namespace: '*object*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE007I Unregister namespace: '*object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE008I Add namespace pending unload list: '*object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKE009I The namespace is not in global namespace:
object.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE010I Inside the garbageCollect method...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE011I Reviewing namespace *named URL* for garbage collection.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE012I Removing namespace: *named URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE013I Inside `canRemoveNamespace` method: *object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE014I The `canRemoveNamespace` method check includes: *object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE015I The `canRemoveNamespace` method determined the '*named URL*' is referenced by '*object*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE016E Not a namespace reference: *name*
Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE017E Undefined namespace reference: *string*.
Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE018E Undefined namespace reference: *namespace in object*.
Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE019E Package has no Info/packageid node.
Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE020I Registered package '*package name*'.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKE021I Inside the removeNamespace method: *name=object*,
namespace contains the *key=boolean*.**
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE022E No available property stores to read key ''key''.

Explanation

The property store from which the user tried to get a value is not defined.

Action

Define a property store with suitable name that contains the needed key(s).

CTGDKE023I The getProperty method will search using key key.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE024I Checking to see if property is in the property store: *property store name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE025I Found the property in the property store: *property store name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE026I The property was not found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE027E No available property stores to write key 'key'.

Explanation

The user has tried to write to a property store that does not exist.

Action

Define a property store with suitable name.

CTGDKE028E No default store to accept: key.

Explanation

The user has not specified default property store.

Action

Define default property store to be used instead of the store with the specified name or property store with such name.

CTGDKE029I The Property Store cache is disabled. The cache timeout is set to *number of seconds* seconds.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE030I The Property Store cache is enabled. The cache timeout is set to *number of seconds* seconds.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE031I Caching all properties from data source.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE032I *Cached number of properties properties.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE033I *Returning cached entry for key key.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE034I *Removing expired cache entry for key=key*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE035I *Adding cache entry for key key.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE036E *Property key 'key' is not unique.*

Explanation

The key, of which the user tried to read the value, is not unique.

Action

Ensure the records in a property store have not repeating keys.

CTGDKE037E Property store '*property store name*' is configured as read-only.

Explanation

The store to which the user writes is configured as read only.

Action

Configure the property store so that it is not read only.

CTGDKE038E No 'key' attribute specified.

Explanation

The entry does not have the "key" attribute.

Action

Define the "key" attribute in the entry.

CTGDKE039E Error occurred when creating IBM Security Directory Integrator Property store. Property store: *property store name* Exception: *exception*

Explanation

Error occurred during the initialization of Properties Connector.

Action

Check the configuration.

CTGDKE040E Property store '*store name*' is not available to read key '*key*'.

Explanation

The named property store from which the user tried to get a value, is not available.

Action

Verify that the property store with the given name exists and is properly configured.

CTGDKE041W Property store '*store name*' does not contain key '*key*'.

Explanation

The named property store from which the user tried to get a value, did not contain the given key.

Action

Verify that the property store with the given name contains the key.

CTGDKE042E Problem parsing component definition file

'path name'.

Explanation

The file indicated by the given path could not be parsed, and the corresponding component will not be available.

Action

Verify the syntax of the file indicated.

CTGDKE043E An error occurred while encrypting data.

Explanation

See error trace.

Action

Check the configuration and try again.

CTGDKM201I Parsing to get options provided by user.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM202I Starting the Administration and Monitoring Console back up operations to location: *location*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM203I Starting the Administration and Monitoring Console restore operations from location: *location*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM204I Parsing to get options provided by user.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM205I The database table being backedup is: *table name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM206E SQL Exception while trying to read Database tables**Explanation**

The tool encountered an SQL exception while trying to read the database to be migrated.

Action

Check that database properties specified in amc.properties are accurate and try again.

CTGDKM207E An Exception was encountered while trying to connect to customer database. Unable to back the database.**Explanation**

The tool encountered an exception while trying to back up the database.

Action

Check error logs and try again.

CTGDKM208E An exception occurred while trying to write to an xml file for the database table *table name*.**Explanation**

The tool encountered an exception while trying to write to an xml file for a specific table in the database.

Action

Check error logs.

CTGDKM209E An exception occurred while trying to read column data from tables to create xml files.

Explanation

The tool encountered an SQL exception while trying to read from table column from database.

Action

Check error logs.

CTGDKM210I Column Name:*column name*. Column Value:*column value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM211I Generated SQL statements for rest of the tables.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM212I Back up location is: *location*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM213I SQL exception thrown while executing the following SQL statement: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM214I Adding the autogenerated ids from master tables to rest of xml files.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM215I Updating xml of table: *statement* with new ID.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM216I Writing to xml files: .

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM217I Inspecting xml files for new constraints added.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM218E The global id, host, or port is null.

Explanation

The data for the TDI_SERVER_MASTER saved in xml file TABLE_TDI_SERVER_MASTER is corrupted.

Action

Check error messages to determine cause or repeat the backup operation.

CTGDKM219E The data violates unique constraint requirement of table TDI_SERVER_MASTER. The data cannot be migrated.

Explanation

The unique constraint defined in table TDI_SERVER_MASTER on columns -GLOBAL_ID,HOST,PORT has been violated. The data cannot be migrated.

Action

Modify existing data in TDI_SERVER_MASTER to satisfy unique constraint requirement.

CTGDKM220I Generating Autogenerated IDs for the following table: *table name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM221I Old ID value is: *ID value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM222I Column added to insert: *column name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM223I SQL statement in master tables:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM224I Generated ID: *ID*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM225E Error cannot generate key for table: *table name*.**Explanation**

The tool was not able to obtain the autogenerated key for table.

Action

Check error logs.

CTGDKM226E An error was encountered while connecting to the database for generating IDs for master tables.**Explanation**

The tool was not able to connect to Security Directory Integrator 7.2 database.

Action

Check database connection properties and try again.

CTGDKM227I SQL insert statements for the rest of the tables:**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM228I Reading list of files from directory...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM229I Renaming table *table name* to *table name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM230I Adding columns for Security Directory Integrator 7.2 changes.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM231I Number of columns to be added: *number of columns*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM232I Column data added to xml. Column name:*column name*. Column value:*column value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM233I Initializing DB Connection properties...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM234E An error was encountered while trying to read amc.properties file.**Explanation**

An error was encountered while trying to read the amc.properties file.

Action

Check that the location specified for the amc.properties file is accurate and try again.

CTGDKM235E An error was encountered while trying to write to file.**Explanation**

An error was encountered while trying to write to file.

Action

Check logs and try again.

CTGDKM236E An error was encountered while trying to add data to database.**Explanation**

An error was encountered while trying to add data to database.

Action

Check logs and try again.

CTGDKM237I Updating XML files with constraints added in new release.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM238E The global id, host or port is null.**Explanation**

The global id, host or port is null.

Action

The data has been corrupted. Try again.

CTGDKM239E The data violates unique constraint requirement. The data cannot be migrated.**Explanation**

The data violates unique constraint requirement. The data cannot be migrated.

Action

The data has been corrupted. Try again.

CTGDKM240E An error has occurred while parsing the xml holding AMC DB data.**Explanation**

An error has occurred while parsing the xml holding AMC DB data.

Action

Check the logs and try again.

CTGDKM241E An error has occurred while reading Administration and Monitoring Console data transferred to xml files.**Explanation**

An error has occurred while reading Administration and Monitoring Console data transferred to xml files.

Action

The saved data has been corrupted. Try again.

CTGDKM242I Autogenerating ids for : *table name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM243E An error has occurred while autogenerating key.**Explanation**

An error has occurred while autogenerating key.

Action

Check error logs and try again.

CTGDKM244E An error has occurred while removing columns to update saved data.

Explanation

An error has occurred while removing columns to update saved data.

Action

Check error logs and try again.

CTGDKM245E An error has occurred while adding columns to update saved data.

Explanation

An error has occurred while adding columns to update saved data.

Action

Check error logs and try again.

CTGDKM246E An error has occurred while renaming table to update saved data.

Explanation

An error has occurred while renaming table to update saved data.

Action

Check error logs and try again.

CTGDKM247E An error has occurred while creating sql insert statements.

Explanation

An error has occurred while creating sql insert statements.

Action

Check error logs and try again.

CTGDKM248E An error has occurred while updating xml files with newly generated ids.

Explanation

An error has occurred while updating xml files with newly generated ids.

Action

Check error logs and try again.

CTGDKM249I Updating the XML for table: *table name* with new ID.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM301I Starting file migration...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM302I Parsing options...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM303E The *operator switch* option occurred more than once.

Explanation

The `tdmigamc` command was invoked with the same parameter passed more than once. Options can be passed only once. For example, the user may have passed the `'-b'` option twice, which is not allowed.

Action

Pass each option only once.

CTGDKM304E No value specified for *option name* option.

Explanation

The `tdmigamc` command was invoked by passing an option whose value had not been specified. The value is also required.

Action

Check the `tdimigamc` command usage, and invoke the `tdisrvctl` command again with the correct option and associated value.

CTGDKM305E Incorrect command usage.

Explanation

The `tdimigamc` command was invoked by passing unsupported command line options, or unexpected end of argument list was encountered or there was an incorrect usage of the command line options.

Action

Check the `tdimigamc` command usage and try invoking the `tdisrvctl` command with valid arguments.

CTGDKM306E Unknown option *operator switch* encountered.

Explanation

The `tdimigamc` command was invoked with an unknown option.

Action

See the `tdimigamc` command usage and invoke the command with the allowed options only.

CTGDKM307E The *operator switch* option was not specified. This is a mandatory option.

Explanation

The `tdimigamc` command was invoked without specifying the `-op` option.

Action

See the `tdimigamc` command usage and invoke the command with the correct and mandatory options specified.

CTGDKM308I Options Parsed: *options*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM309E An error *error* occurred while reading the XML properties file.

Explanation

There was an error while loading the XML properties file.

Action

Refer to the logs for additional information. Verify that the migamc.jar file is in the classpath.

CTGDKM310E Unable to migrate the file *file name*. The file does not exist or cannot be read.

Explanation

The migration failed because the file to migrate does not exist or could not be read.

Action

Verify that the specified file to migrate exists and can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM311E Unable to migrate the file *file name*. The file specified is not a file.

Explanation

The migration failed because the file specified for migration was not a file.

Action

Verify that the specified file to migrate exists and is a file that can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM312E Unable to migrate the file *file name*. The file specified cannot be written to.

Explanation

The migration failed because the file could not be written to.

Action

Verify that the specified file to migrate exists and can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM313E Unable to migrate the file *file name*. The file name of the backup file must not be the same name as the file name.

Explanation

The migration failed because the file to migrate and the file to backup are the same.

Action

Specify a different file names for the file to migrate and the backup file.

CTGDKM314E Unable to migrate the file *file name*. The file name of the backup file must not be the same name as the new file.

Explanation

The migration failed because the new file name and the file to backup are the same.

Action

Specify a different file names for the file to backup and the new file.

CTGDKM315E Unable to perform the migration. Unable to backup the file *file name* to *file name*.

Explanation

The migration failed because the file to migrate could not be backed up.

Action

Verify that the specified file to migrate exists and a can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM316I Adding the new properties...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM317I Completed adding the new properties.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM318I Started modifying the old properties with new values and commenting the old properties....

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM319I Completed modifying the old properties with new values and commenting the old properties.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM320I Starting commenting the old properties....

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM321I The number of old properties to be commented are *number of properties*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM322I There are no old properties to be removed for release *release version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM323I There are no new properties added for release *release version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM324I Updating the properties....

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM325I Migration completed with exit code *exit code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM326I The file *file name* is successfully deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM327I Failed to delete file *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM328I Initializing migration, loading the *xml prop file* properties file .

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM329I There are no properties in the new release which need to be updated in the older release.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM101W The command did not complete successfully. See previous messages or error logs for details.

Explanation

One or more errors occurred during the execution of the command.

Action

Check the previous messages displayed by the tdimigam command, or look at the error logs for more details.

CTGDKM102E Unknown value passed for '-op' option.

Explanation

An illegal operation parameter was passed.

Action

Check the tdimigam command usage for allowed options.

CTGDKM103E Incorrect command usage.

Explanation

The tdimigam command was invoked by passing unsupported command line options, or unexpected end of argument list was encountered or there was an incorrect usage of the command line options.

Action

Check the `tdmigam` command usage and try invoking the `tdisrvctl` command with valid arguments.

CTGDKM104E No value specified for *option name* option.

Explanation

The `tdmigam` command was invoked by passing an option whose value had not been specified. The value is also required.

Action

Check the `tdmigam` command usage, and invoke the `tdisrvctl` command again with the correct option and associated value.

CTGDKM105I The usage for the command is: `tdmigam -f propfile [-b backfile] [-n newfile] [-v] [-?]` where: `-f propfile` The name of the file to migrate `-b backfile` Back up the original file with the specified name `-n newfile` Name to give the file that is migrated `-v` Enable verbose mode `-?` Prints this usage statement

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM106I Return Code: *return code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM107I Parsing options...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM108I Options Parsed: *options*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM109E The *operator switch* option occurred more than once.**Explanation**

The `tdimigam` command was invoked with the same parameter passed more than once. Options can be passed only once. For example, the user may have passed the `'-b'` option twice, which is not allowed.

Action

Pass each option only once.

CTGDKM110E Unknown option *operator switch* encountered.**Explanation**

The `tdimigam` command was invoked with an unknown option.

Action

See the `tdimigam` command usage and invoke the command with the allowed options only.

CTGDKM111W Already reached the end of argument list.**Explanation**

While parsing the arguments, the `tdimigam` utility encountered an unexpected end of arguments.

Action

Check the command usage and try again.

CTGDKM112E The *operator switch* option was not specified. This is a mandatory option.**Explanation**

The `tdimigam` command was invoked without specifying the `-op` option.

Action

See the `tdimigam` command usage and invoke the command with the correct and mandatory options specified.

CTGDKM113I Starting file migration...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM114E Unable to perform the migration. Unable to backup the file *file name* to *file name*.

Explanation

The migration failed because the file to migrate could not be backed up.

Action

Verify that the specified file to migrate exists and can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM115E Unable to migrate the file *file name*. The file does not exist or cannot be read.

Explanation

The migration failed because the file to migrate does not exist or could not be read.

Action

Verify that the specified file to migrate exists and can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM116E Unable to migrate the file *file name*. The file specified is not a file.

Explanation

The migration failed because the file specified for migration was not a file.

Action

Verify that the specified file to migrate exists and is a file that can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM117E Unable to migrate the file *file name*. The file specified cannot be written to.

Explanation

The migration failed because the file could not be written to.

Action

Verify that the specified file to migrate exists and can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM118E Unable to migrate the file *file name*. The file name of the backup file must not be the same name as the file name.

Explanation

The migration failed because the file to migrate and the file to back up are the same.

Action

Specify a different file names for the file to migrate and the backup file.

CTGDKM119E Unable to migrate the file *file name*. The file name of the backup file must not be the same name as the new file.

Explanation

The migration failed because the new file name and the file to back up are the same.

Action

Specify a different file names for the file to backup and the new file.

CTGDKM120E Error deleting file: *file name*.

Explanation

The specified file could not be deleted.

Action

Check the file permissions.

CTGDKM001W The command did not complete successfully. See previous messages or error logs for details.

Explanation

One or more errors occurred during the execution of the command.

Action

Check the previous messages displayed by the `tdimiggb1` command, or look at the error logs for more details.

CTGDKM002E Unknown value passed for '-op' option.

Explanation

An illegal operation parameter was passed.

Action

Check the tdimigbl command usage for allowed options.

CTGDKM003E Incorrect command usage.

Explanation

The tdimigbl command was invoked by passing unsupported command line options, or unexpected end of argument list was encountered or there was an incorrect usage of the command line options.

Action

Check the tdimigbl command usage and try invoking the tdisrvctl command with valid arguments.

CTGDKM004E No value specified for *option name* option.

Explanation

The tdimigbl command was invoked by passing an option whose value had not been specified. The value is also required.

Action

Check the tdimigbl command usage, and invoke the tdisrvctl command again with the correct option and associated value.

CTGDKM005I The usage for the command is: tdimigbl -f propfile [-b backfile] [-n newfile] [-v] [-?] where: -f propfile The name of the file to migrate -b backfile Backup the original file with the specified name -n newfile Name to give the file that is migrated -s dir Specifies the working directory where the solution directory is located. -v Enable verbose mode -? Prints this usage statement

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM006I Return Code: *return code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM007I Parsing options...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM008I Options Parsed: *options*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM009E The *operator switch* option occurred more than once.

Explanation

The `tdimigbl` command was invoked with the same parameter passed more than once. Options can be passed only once. For example, the user may have passed the `'-b'` option twice, which is not allowed.

Action

Pass each option only once.

CTGDKM010E Unknown option *operator switch* encountered.

Explanation

The `tdimigbl` command was invoked with an unknown option.

Action

See the `tdimigbl` command usage and invoke the command with the allowed options only.

CTGDKM011W Already reached the end of argument list.

Explanation

While parsing the arguments, the `tdimigbl` utility encountered an unexpected end of arguments.

Action

Check the command usage and try again.

CTGDKM012E The *operator switch* option was not specified. This is a mandatory option.

Explanation

The `tdimigbl` command was invoked without specifying the `-op` option.

Action

See the `tdimigbl` command usage and invoke the command with the correct and mandatory options specified.

CTGDKM013I Starting file migration...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM014E Unable to perform the migration. Unable to backup the file *file name* to *file name*.

Explanation

The migration failed because the file to migrate could not be backed up.

Action

Verify that the specified file to migrate exists and can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM015E Unable to migrate the file *file name*. The file does not exist or cannot be read.

Explanation

The migration failed because the file to migrate does not exist or could not be read.

Action

Verify that the specified file to migrate exists and can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM016E Unable to migrate the file *file name*. The file specified is not a file.

Explanation

The migration failed because the file specified for migration was not a file.

Action

Verify that the specified file to migrate exists and is a file that can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM017E Unable to migrate the file *file name*. The file specified cannot be written to.

Explanation

The migration failed because the file could not be written to.

Action

Verify that the specified file to migrate exists and a can be read and written to. Also, verify you have read permissions on the backup file location.

CTGDKM018E Unable to migrate the file *file name*. The file name of the backup file must not be the same name as the file name.

Explanation

The migration failed because the file to migrate and the file to backup are the same.

Action

Specify a different file names for the file to migrate and the backup file.

CTGDKM019I Performing migration deletion operations...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM020I Performing migration addition operations...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM021I Performing migration Derby operations...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM022I Performing migration modification operations...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKM023E Unable to migrate the file *file name*. The file name of the backup file must not be the same name as the new file.

Explanation

The migration failed because the new file name and the file to backup are the same.

Action

Specify a different file names for the file to backup and the new file.

CTGDKM024E An error has occurred while reading the stash file: *exception*

Explanation

The specified error has occurred while reading the stash file.

Action

See the exception for more information.

CTGDKM025E No password has been found in the Server stash file.

Explanation

The Server stash file must contain the password of the Server keystore (and optionally the password of the key).

Action

Provide a password in the stash file.

CTGDIS001E The version number of the Connector is undefined.

Explanation

The getVersion method of the Connector did not return a version number. A version number can only be displayed for a user defined Connector if the getVersion method of the Connector is defined and returns a java.lang.String object.

Action

If the Connector is not a user defined Connector that has been added to the IBM Security Directory Integrator jars directory, contact IBM Support. Otherwise, verify the user defined Connector has properly implemented the getVersion method.

CTGDIS002E Error on printing component version numbers.

Explanation

There was an error while displaying the version information of all the installed components using the ibmdisrv -v flag.

Action

See the ibmdi.log to view the specific exception.

CTGDIS003I * Start dumping Entry**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS004I * Finished dumping Entry**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS005I * Start dumping Object *******Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS006I * Finished dumping Object *******Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS007I Dump of SYSTEM.PROPERTIES.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS008I Loading system templates.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS009E Error while setting log file: '*file name*'.**Explanation**

There was an error setting the specified log file for the output logs using the -l flag of ibmdisrv.

Action

Verify you have the required security permission to reassign the standard output stream. You can check this through the Security Manager permissions.

CTGDIS010E No configuration file specified.

Explanation

There was no configuration file specified for the ibmdisrv command.

Action

Confirm if you want to proceed with the delete operation. Choose Cancel if you do not want the network server to be deleted from the configuration list.

CTGDIS011E Error loading configuration file *file name*.

Explanation

The configuration file specified using the -c commandline option for the ibmdisrv could not be loaded. Either the configuration file does not exist or the path to configuration file might be wrong.

Action

Verify that the specified file exists, and that the specified path is correct.

CTGDIS012E Error while setting properties.

Explanation

There was an error while setting the system properties.

Action

Verify a security manager exists and its checkPermission method allows setting the specified properties.

CTGDIS014E Error while initializing manager.

Explanation

Could not initialize the administration and the monitoring console. The administration and monitoring console might already be started.

Action

Verify the administration and monitoring console is already started.

CTGDIS015E Error while auto starting AssemblyLines.

Explanation

Error while auto-starting the AssemblyLine(s) specified by the -r flag of ibmdisrv.

Action

The specified AssemblyLine might not exist in the configuration file. Specify an Assembly Line that exists in the currently selected configuration file.

CTGDIS016E Error while auto starting EventHandlers.

Explanation

Error while auto-starting the EventHandler(s) specified by the -t flag of ibmdisrv.

Action

The specified EventHandler might not exist in the configuration file. Specify an EventHandler that exists in the currently selected configuration file.

CTGDIS017E Error while starting EventHandler *EventHandler name*.

Explanation

Error while auto-starting the EventHandler(s) specified by the -t flag of ibmdisrv.

Action

The specified EventHandler might not exist in the configuration file. Specify an AssemblyLine that exists in the currently selected configuration file.

CTGDIS018E Cannot declare the error object.

Explanation

Error while declaring the Script engine error object for the AssemblyLine component.

Action

Check the logs for the exception thrown by the Bean Scripting framework.

CTGDIS019E The EventHandler *EventHandler name* has no associated Java class.

Explanation

There is no corresponding Java class for the specified EventHandler.

Action

Verify the jar file for the specified EventHandler exists under TDI_HOME/jars/eventhandlers directory.

CTGDIS020E Cannot debug old style EventHandlers.

Explanation

The old style EventHandlers cannot be debugged.

Action

The old style EventHandlers cannot be debugged. The old style EventHandlers are deprecated and should not be used. You should use a new style EventHandler instead.

CTGDIS021E No Config path configured.

Explanation

There is no configuration path specified for the reloading the configuration file.

Action

Make sure that the configuration path is set and then try to reload the configuration.

CTGDIS022E Error while loading configuration.

Explanation

The Connector configuration could not be loaded.

Action

Check the Connector is a valid meta-merge config object.

CTGDIS023E Error while getting AttributeMap for *attribute map*.

Explanation

Could not retrieve the attribute map for the named Connector. The attribute map may not be defined.

Action

Verify the attribute map is defined for the named Connector.

CTGDIS024E Error while getting Config for AssemblyLine *AssemblyLine name*.

Explanation

Could not retrieve the configuration for the specified AssemblyLine.

Action

Verify the configuration for the AssemblyLine exists.

CTGDIS025E Exception while loading configuration: *file name*.

Explanation

The Connector configuration could not be loaded.

Action

Check the logs for the specific exception. Contact IBM support for resolution of the specific exception.

CTGDIS026E SkipTo: Unknown Connector *Connector name*.

Explanation

The specified Connector is an unknown Connector type and cannot be loaded. Only Connectors of known types can be loaded. Either you have mentioned a Connector of unknown type or you trying to inherit from a Connector of unknown type.

Action

Specify a Connector which is supported by IBM Security Directory Integrator. For getting a list of all the known or supported Connectors use the `ibmdisrv -v` option. This will list the supported Connectors and their classes. Use this list to the specify a Connector inside the AssemblyLine or in the inheritance of a Connector.

CTGDIS027E Could not auto-start the EventHandler(s).

Explanation

The `ibmdisrv` command line parameter `'-D'` prevented start of EventHandler/Listener tasks.

Action

If you want the EventHandlers to auto-start make sure that the `-D` commandline option is not used while starting `ibmdisrv`.

CTGDIS028I Starting AssemblyLine *AssemblyLine name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS029I Starting AssemblyLine *AssemblyLine name* for debug.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS030I AssemblyLine *AssemblyLine name* started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS031I AssemblyLine *AssemblyLine name* started for debugging.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS032I Starting EventHandler: *EventHandler name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS033I EventHandler *EventHandler name* has started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS034I Wait for completion of AssemblyLine:
AssemblyLine name.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS035I Wait for completion of EventHandler:

EventHandler name.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS036I Exit after auto-run requested.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS037I Server terminates because only main thread is left.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS038I System termination requested by external process.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS039I Waiting for the completion of the currently executing task.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS040I Loading configuration from stdin.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS041I Loading configuration from *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS042W Possible deadlock detected, allowing one more thread to start.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS043I Enabled hook script for *hook name* is empty.

Explanation

The specified hook is enabled but is empty.

Action

You can disable the specific hook if it is empty and not needed.

CTGDIS044I Initializing Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS045I Connector is iterator, call selectEntries.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS046I Initialization finished.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS047W Entry not found.**Explanation**

Could not find the entry object specified by the link criteria.

Action

No entry object matching the link criteria was found. Consider changing the link criteria.

CTGDIS048E Multiple entries found and no 'On Multiple Entries' Hook defined.**Explanation**

The link criteria has returned multiple entries on lookup. But there are no multiple hooks defined to handle the multiple entries. The On Multiple Entries hooks must be defined to let IBM Security Directory Integrator know how to handle multiple entries returned by the link criteria.

Action

You must define the On Multiple Entries hooks and enable it.

CTGDIS049I Entry not found, calling ADD.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS050I Entry found, calling MODIFY.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS051W Task is not allowed to modify entries.

Explanation

You are trying to modify an entry object, but there are no modify attributes specified in the attribute map. This operation will be skipped.

Action

Specify a valid attribute in the attribute map for modification.

CTGDIS052I (Modify) Attribute *attribute name* removed. It is part of the attribute map (mod) but not present in the conn entry (ref. Null Value Behavior).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS053I (Modify) Attribute *attribute name* included in modify operation.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS054E Connector is not configured to add Entries.

Explanation

You are trying to add an entry object with a Connector which is not configured to run in either the add or modify mode.

Action

To perform add operations configure the Connector in the addonly mode or the update mode and then run the AssemblyLine.

CTGDIS055I Loading user jars from *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS056I Trigger *trigger name* was not handled, call default handler.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS057I Hook *hook name* not enabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS058I Connector *Connector name* inherits from *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS059I Virtual Connector provided.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS060W No Connector provided for runtime Connector.**Explanation**

You are trying to use a virtual Connector but no runtime Connector is specified.

Action

Specify a runtime Connector.

CTGDIS061I Reuse Connector *Connector name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS062I Cannot load Connector *Connector name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS063I Using advanced link criteria (script).**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS064I Loading Attribute Map.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS065I Load Hooks .

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS066W No link criteria configured.

Explanation

The Connector is configured in either the update/lookup or the delete mode, but no link criteria is configured. It is required that the link criteria be configured for a Connector configured to run in update/lookup or delete mode.

Action

Configure the link criteria by using the simple link criteria or the advanced link criteria.

CTGDIS067E Unable to find configuration for AssemblyLine *AssemblyLine name.*

Explanation

For the specified AssemblyLine there is no corresponding configuration file specified using the -c commandline option of ibmdisrv.

Action

You should specify the configuration file which includes the specified AssemblyLine. Use the ibmdisrv's -c commandline option to specify the configuration file.

CTGDIS068E Unknown object class passed as parameter to AssemblyLine: *AssemblyLine name.*

Explanation

An unknown object is passed as a parameter to the AssemblyLine.

Action

Make sure only supported parameters are passed to an AssemblyLine.

CTGDIS069I Loading Connectors.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS070I Finished loading Connectors.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS071I Entering TaskCallBlock.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS072I Succeeded entering TaskCallBlock.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS073I Initializing Connectors.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS074I Finished initializing Connectors.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS075I Trying to exit TaskCallBlock.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS076I Succeeded exiting TaskCallBlock.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS077I Failed with error: *error*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS078I AssemblyLine *AssemblyLine name* failed with error: *error*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS079I AssemblyLine *AssemblyLine name* terminated successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS080I Terminated successfully (*number of errors errors*).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS081I AssemblyLine component *component name* disabled by configuration.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS082I Load: *component name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS083I While loading Connector *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS084I Initialization of *component name* failed: error.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS085I Initializing Component *component name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS086I No iterator in AssemblyLine, will run single pass only.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS087I Iterating.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS088I Finished iterating.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS089I Current statistics: Interval=*interval*, Maximum Errors=*max errors*, Maximum Read=*max read*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS090I Task specified maximum number of errors encountered: *max errors*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS091I Ending AssemblyLine after reaching maximum number of entries to read: *max errors*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS092I Using runtime provided entry as working entry (first pass only).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS093I Switching to iterator *iterator name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS094I Skip input entry.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS095I Ignore entry.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS096I Restarting entry from iterator (potential loop).**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS097I Skip to *message*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS098I Abort AssemblyLine requested: *message*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS099I *number of entries* **entries processed ...****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS100I **Printing the Connector statistics.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS101I **Finished printing the Connector statistics.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS103I **No statistics.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS104I **Total: *total*.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS105I Set parameter *parameter name* to *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS106I Wrote parameter *parameter name* to *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS108E Bad number for *component name* parameter: *parameter name*.

Explanation

The parameter should be a number, but a non-numeric value was specified.

Action

Specify a number as value for the specified parameter.

CTGDIS109I Declare Connector bean as *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS110I No script for *hook name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS111I The Prolog before initialization of Connectors.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS112I The Prolog after initialization of Connectors.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS113I The Epilog

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS114I The Shutdown hook

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS115I Starting scripting hook of type *operation*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS116I Scripting hook of type *operation* finished.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS117I Execute script for *component hook*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS118I Script execution failed.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS119I The script *wasscript name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS120I Include from Script Library disabled by configuration.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS121I Expecting String for AttributeMap, got *value*. **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS122I Printing attribute map: *attribute name attribute name*. **Explanation**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS123I Returned object class *class name*. **Explanation**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS124I Copying file "*source file*" to file "*destination file*". **Explanation**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS126I Return *return value*. **Explanation**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS127I Null Behavior for *value: value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS128E Cannot find AssemblyLine *AssemblyLine name*.

Explanation

The specified AssemblyLine could not be found in the list of configuration files mentioned while starting up the ibmdisrv.

Action

Specify an AssemblyLine which exists in the currently loaded configuration(s).

CTGDIS129I No config entry for Component *component name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS131I Delta Sequence now at *sequence ID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS140E Unable to decrypt the file. Either no password was specified or the password specified is not correct.

Explanation

The specified configuration has been encrypted using the old style password encryption. The password used for encryption must be specified to decrypt it correctly. Either no password was specified or the password specified is not correct.

Action

To decrypt a file correctly a valid encryption password must be specified.

CTGDIS141I Load properties from *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS142I Error while loading *file name*, exception is *message* .

Explanation

Could not load the named global.properties/solution.properties file. The file does not exist, is not readable, or contains a syntax error.

Action

Check the exception message for more information about the problem, and correct the problem.

CTGDIS143E No criteria can be built from input (no link criteria specified).

Explanation

The specified input criteria has not been specified or is incorrect. A valid criteria must be specified for successful lookup of the entry object.

Action

Specify a valid criteria which returns at least one entry object.

CTGDIS144E No such AssemblyLine: *AssemblyLine name*.

Explanation

The AssemblyLine must exist in the currently loaded configuration file for operations to be performed. The specified AssemblyLine does not exist in the configuration file.

Action

Specify a valid and existing AssemblyLine's name while starting the AssemblyLine using the ibmdisrv -r flag or while using main.startAL() method calls.

CTGDIS145E TCB: Missing required parameter *parameter name*.

Explanation

A required parameter for the TCB is missing.

Action

Specify the TCB parameter to correct the error.

CTGDIS147E TCB:Wrong accumulator object type *object type*.
Explanation

The valid values for the accumulator object types are Collection, AssemblyLineListener, ConnectorInterface, ParserInterface and AssemblyLineComponent.

Action

Specify an object of one of the above types in the TCBs accumulateEntry() method call.

CTGDIS148I Setting Connector parameters.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS149I Finished setting Connector parameters.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS150I Changing parameters for *component name*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS151I Setting parameter *key*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS152I Building TCB entry.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS153I Finished building TCB entry.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS156E Input Attribute *attribute name* is required, but not present.**Explanation**

The specified input attribute is required but is not present in the entry object.

Action

The input attribute must be mapped into the entry object.

CTGDIS157E Output Attribute *attribute name* is required, but not present.**Explanation**

The specified Output attribute is required but is not present in the entry object.

Action

The Output attribute must be mapped into the entry object.

CTGDIS158I Registering Script Beans.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS159E This Connector has no configured Parser.

Explanation

There is no Parser configured in the Connector's config tab. This Connector needs a Parser.

Action

Configure a valid Parser from the available Parser list in the Connector's config tab.

CTGDIS160E Connector does not support getNextEntry.

Explanation

The Connector does not support the iterator mode. Calling getNextEntry() on this Connector object is not supported.

Action

Check the supported mode of the Connectors. If the Connector does not support the iterator mode then you cannot call the getNextEntry() method.

CTGDIS161E Connector does not support modEntry.

Explanation

The Connector does not support the update mode. Calling modEntry() on this Connector object is not supported.

Action

Check the supported mode of the Connectors. If the Connector does not support the update mode then you cannot call the modEntry method.

CTGDIS162E Connector does not support deleteEntry.

Explanation

The Connector does not support the delete mode. Calling deleteEntry() on this Connector object is not supported.

Action

Check the supported mode of the Connectors. If the Connector does not support the delete mode then you cannot call the deleteEntry method.

CTGDIS163E Connector does not support findEntry.

Explanation

The Connector does not support the lookup mode. Calling findEntry() on this Connector object is not supported.

Action

Check the supported mode of the Connectors. If the Connector does not support the lookup mode then you cannot call the findEntry() method.

CTGDIS164E Connector does not support putEntry.

Explanation

The Connector does not support the addonly mode. Calling putEntry() on this Connector object is not supported.

Action

Check the supported mode of the Connectors. If the Connector does not support the addonly mode then you cannot call the putEntry method.

CTGDIS165E Connector does not support queryReply.

Explanation

The Connector does not support the CallReply mode. Calling queryReply method on this Connector object is not supported.

Action

Check the supported mode of the Connectors. If the Connector does not support the call/reply mode then you cannot call the queryReply method.

CTGDIS167E Connector does not support queryTables.

Explanation

The queryTables method of a Connector is used to discover "tables" for a connection. The Connector may implement this in which case a Vector of strings is returned. For a database Connector this would typically be a list of table/view names the user can access with the current set of parameters. For other Connectors this might translate to different concepts. For this specific Connector there is no queryTables method implemented.

Action

The Connector does not support the queryTable().

CTGDIS168E Pipe with name *pipe name* already exists.

Explanation

The pipe (memory queue pipe) already exists. You cannot create two pipes with the same name.

Action

Specify an unique name for the memory queue pipe.

CTGDIS169E No value specified.**Explanation**

The queue name is a required parameter.

Action

Specify a valid and unique queue name.

CTGDIS170E The memory queue pipe is full.**Explanation**

The memory queue pipe is full and no entries can be added to it.

Action

Flush out entries from the queue or stop the push() operation till the memory queue becomes empty.

CTGDIS171E Error calculating threshold.**Explanation**

The memory buffer queue calculates the threshold or the water mark dynamically by taking the size of the first page written. There was an error while serializing the page which is needed to calculate the threshold.

Action

Create a new queue and try the operation again.

CTGDIS172E Error while initializing system store for paging support.**Explanation**

The memory queue uses the underlying system store to persist the entry objects. If the system store is configured to use the Derby server in networked mode, make sure that the Derby network server is started. Similarly if the DB2, MS SQL Server or Oracle server is used as the system store, make sure a database instance is booted in these servers.

Action

Make sure the underlying system store database server is started and an instance of database booted in.

CTGDIS173E The MemBufferQ Callback could not be found.**Explanation**

Callback not found.

Action

Callback not found.

CTGDIS174I Config Instance *Config name* exited with status *return code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS175I Non delta-entry provided in update mode with use-delta on.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS176I Delta-entry provided in normal update mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS179E Error while saving the task parameters.

Explanation

There was an error saving the task parameters back into the user defined repository.

Action

See the ibmdi.log to view the specific exception.

CTGDIS180E Error while restoring the task parameters.

Explanation

There was an error restoring the task parameters from the user defined repository.

Action

See the ibmdi.log to view the specific exception.

CTGDIS181E Error while evaluating Hook '*Hook name*' in the Component '*Component name*' (*Internal Hook name*).

Explanation

There was an error while evaluating the named Hook.

Action

See the ibmdi.log to view the specific Exception.

CTGDIS182E Error while registering the JSSE Provider *provider name*.

Explanation

There was an error evaluating the single attribute map.

Action

See the ibmdi.log to view the specific exception.

CTGDIS183E Error while mapping attribute '*attribute name*' in the *MapName* Attribute Map of Component '*component name*' (*internal name*).

Explanation

There was an error mapping the attribute.

Action

See the ibmdi.log to view the specific exception.

CTGDIS184E This AssemblyLine was invoked with operation '*operation*', which does not match any of the defined operations for this AssemblyLine.

Explanation

The AssemblyLine was called with an unknown operation.

Action

Change the operation name to a valid operation or define a new operation in the AssemblyLine configuration.

**CTGDIS185I Cannot load pooled Connector: *Connector name*.
Pool not found.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS186I Could not get Connector from pool: *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS187I Loaded *Connector name*, *Connector version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS188E An error has occurred while starting the Derby network server: *exception*

Explanation

The specified error has occurred while starting the Derby network server.

Action

Verify the global properties related to the Derby network server, such as com.ibm.di.store.port, are properly configured.

**CTGDIS189E Cannot find AssemblyLine with name
'AssemblyLine name'.**

Explanation

The specified AssemblyLine was not found.

Action

Verify the AssemblyLine's name is correct and the AssemblyLine exists.

CTGDIS191E TaskCallBlock (TCB) does not name an AssemblyLine.

Explanation

The TaskCallBlock parameter of RS.startAL method does not name an AssemblyLine.

Action

Provide a TaskCallBlock parameter that names an AssemblyLine.

CTGDIS192E An error has occurred while terminating Connector Pool: *exception*

Explanation

The specified error has occurred while terminating the Connector pool.

Action

See the exception for more information.

CTGDIS193E An error has occurred on Connector Pool initialization: *exception*

Explanation

The specified error has occurred while initializing the Connector pool.

Action

See the exception for more information.

CTGDIS194E Could not create Connector Pool for Connector '*Connector name*'. Exception occurred: *exception*

Explanation

The specified error has occurred while creating a Connector pool for the specified Connector.

Action

See the exception for more information.

CTGDIS195E An error has occurred while executing server hook file '*file name*': *exception*

Explanation

The specified error has occurred while executing a server hook file.

Action

See the exception for more information.

CTGDIS196E Config or group name is not specified.

Explanation

See message.

Action

Specify both a config and a group names.

CTGDIS197E Config instance with name '*Config name*' is already running.

Explanation

See message. You cannot start the same Configuration more than once.

Action

No action is required.

CTGDIS198E getServer(): an error has occurred while trying to obtain the RS context: *exception*

Explanation

See message.

Action

See the exception for more information.

CTGDIS199E Error has occurred while initializing the server Hooks: *exception*

Explanation

The specified error has occurred while initializing the server hooks.

Action

See the exception for more information.

CTGDIS200E An error has occurred while reading the stash file: *exception*

Explanation

The specified error has occurred while reading the stash file.

Action

See the exception for more information.

CTGDIS201E No password has been found in the Server stash file.

Explanation

The Server stash file must contain the password of the Server keystore (and optionally the password of the key).

Action

Provide a password in the stash file.

CTGDIS202E Could not set up the Server keystore password info. Exception occurred: *exception*

Explanation

See message.

Action

See the exception for more information.

CTGDIS203E Unable to find EventHandler configuration for the name: *EventHandler name*.

Explanation

The EventHandler cannot operate without configuration.

Action

Define an EventHandler with proper name.

CTGDIS204E AutoStart Folder: an exception occurred while finding/loading autostart element with name '*name*': *exception*

Explanation

The autostart element cannot be launched without configuration.

Action

Verify an AssemblyLine/EventHandler with the specified name exists.

CTGDIS205E AutoStart Folder: Do not know how to start component: *name*.

Explanation

The component with the specified name is not from autostart type (ex. AssemblyLine/EventHandler).

Action

Check that the component with the specified name is from autostart type (ex. AssemblyLine/EventHandler).

CTGDIS206W An error has occurred on Remote Server API initialization: *exception***Explanation**

See Message.

Action

See the exception message for more information.

CTGDIS207W The Remote Server API engine is not started.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS208W An error has occurred on Remote JMX initialization: *exception*.**Explanation**

See Message.

Action

See the exception message for more information.

CTGDIS209W The Remote JMX Server Connector is not started.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS210W An error has occurred on Server API initialization: *exception*.**Explanation**

See Message.

Action

See the exception message for more information.

CTGDIS211W Server API engine is not started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS212W The '*property name*' external property is already specified and will be overwritten.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS213W No external file is specified in [-f] parameter.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS214W There is no such property store '*property store name*' in '*Config ID*' configuration.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS215W An error has occurred while processing command line parameter [-f].

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS216W An error has occurred while decrypting protected property: *exception*

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS217W An error has occurred while encrypting protected property '*property name*' in file '*file name*': *exception*.

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS218W An error has occurred while rewriting the properties file: *exception*

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS219W An error has occurred while calling server hook '*hook name*': *exception*

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS220W An error has occurred while unregistering the server with the Server API: *exception*

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS221W An error has occurred while registering the server with the Server API: *exception***Explanation**

See Message.

Action

See the exception message for more information.

CTGDIS222W Server security has not been initialized.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS223W Server PKI encryption and secure remote Server API communication cannot be used.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS224I No autoloading directory is configured (com.ibm.di.server.autoload).**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS225I The specified path is not a directory: *directory*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS226I Looking for *.xml files in directory: *directory*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS227I Autoloading Config file: *file name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS228I Unregister server: *server name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS229I Register server: *server name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS230I JVM ShutDown Hook has been added: '*hook*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS231I Server is running in secure mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS232I Server is running in standard mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS233I Server instance for the following configuration is starting: *Config name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS234I IDI Server is entering daemon mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS235I An error has occurred while sending server shutdown event: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS236I The stash file has been successfully read.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS237I The key password is not present in the stash file. The keystore password will be used.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS238I Server security has been successfully initialized.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS239I '*file*' was created from '*source*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS240I Copying SERVERAPI files from '*directory*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS241I All threads have been stopped.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS242I User: *object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS243I Loaded EventHandler *class name: version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS244E Bad run mode value: *run mode*.

Explanation

The run mode value provided by the TCB block is invalid.

Action

Specify valid running mode.

CTGDIS245E Unable to interpret '*parameter*' as a run AssemblyLine parameter.

Explanation

The specified value is not valid run AssemblyLine parameter.

Action

Specify valid optional parameter

CTGDIS246W Unknown object class passed as parameter to start AssemblyLine: *class name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS247E Connector not defined: '*Connector name*'

Explanation

In order to add a Connector in Iterator mode to the AssemblyLine at runtime, the Connector must exist in the AssemblyLine configuration.

Action

Verify that a Connector with the specified name exists in the configuration.

CTGDIS248E Not an EntryFeed mode Connector: *Connector name:Connector mode*.

Explanation

The specified Connector is not in Iterator or Server mode.

Action

Set the specified Connector in Iterator or Server mode.

CTGDIS249E Unknown Connector name: *Connector name*.

Explanation

Cannot find a Connector with the specified name.

Action

Specify correct fully qualified name of Connector.

CTGDIS250W Problem when declaring *name*, possibly illegal name.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS251I Completed iterator ''*iterator name*'' is not initialized.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS253E Server Connector *Connector name* could not be terminated. Exception occurred: *exception*.

Explanation

Problem occurred while shutting down the AssemblyLine - a Connector in Server mode could not be properly terminated.

Action

See the exception message for more information.

CTGDIS254I Adding reply channel for Connector: *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS255I AssemblyLine *AssemblyLine name* is started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS256I AssemblyLine *AssemblyLine name* is started, recording to: *sandbox identifier*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS257I AssemblyLine *AssemblyLine name* is started, playing back from: *sandbox identifier*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS258I AssemblyLine *AssemblyLine name* is started in manual mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS263E Only callable when AssemblyLine was started in Cycle mode.

Explanation

executeTerminateAL method should be called only when the AssemblyLine was started in cycle mode.

Action

Start the AssemblyLine in cycle mode

CTGDIS264E This AssemblyLine was not started in 'Cycle' mode.

Explanation

The executeCycle method should not be called when the AssemblyLine was not started in cycle mode.

Action

Ensure the executeCycle method is being called when the AssemblyLine is started in cycle mode.

CTGDIS265E Cannot execute beyond end-of-iteration.

Explanation

The executeCycle method cannot execute anything beyond the end of the iteration.

Action

Ensure the executeCycle method is being called before the AssemblyLine has finished iterating.

CTGDIS266E Error in *AssemblyLine* step. Exception occurred: *exception*

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS269I Skipping to response section.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS271I Restarting entry from *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS272I Retrying operation in *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS273I Ignoring entry in *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS274I Skipping entry from *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS275I Inside exitBranch method: current component=*component name*; branch=*branch name*; data flow=*boolean*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS276I exitBranch: exitFlow

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS277I Exit AssemblyLine requested.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS278E Cannot locate branch *branch name* in the context of component *component name*.

Explanation

Cannot find a branch with the specified name in the specified component.

Action

Verify a branch with the specified name exists in the specified component.

CTGDIS279E Cannot locate loop *loop name* in the context of component *component name*.

Explanation

Cannot find a loop with the specified name in the specified component.

Action

Verify a loop with the specified name exists in the specified component.

CTGDIS280I Switch to next iterator.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS281E Error caused by: *exception*.

Explanation

The AssemblyLine is terminating with an error caused by a script.

Action

See the exception message for more information.

CTGDIS283E EventHandlers are no longer a feature of 6.0. Remove them for your solution.

Explanation

See message.

Action

Remove all Eventhandlers.

CTGDIS284I Draining Connector: *Connector name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS285I Connector drained: *Connector name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS286I Waiting for AssemblyLine pool to terminate.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS287I [Performance]: *performance record.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS288I Draining the Connector. The entry mode is set to
boolean.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS290I Property '*property name*' is undefined, using:
*property name***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS291E Invalid thread mode value: *thread mode*
(*integer-integer*).**

Explanation

The specified thread mode for the AssemblyLine Pool is invalid.

Action

The thread mode for the AssemblyLine Pool should be set to a value that falls between the specified values.

**CTGDIS292I AssemblyLine pool: initialize: preload=*preloaded*
AssemblyLine, max concurrent=*integer*.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS293I AssemblyLine pool: Connector pool timeout:
timeout.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS294I AssemblyLine pool: Connector pooling is
disabled.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS295I AssemblyLine pool: Save runtime Connectors: AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS296I AssemblyLine pool: null function not pooled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS297I AssemblyLine pool: null Connector not pooled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS298I AssemblyLine pool: Connector type *class name* is excluded.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS299I AssemblyLine pool: adding to pool: name=*component name*; type=*class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS300I AssemblyLine pool: reuse PooledConnectorSet object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS301I AssemblyLine pool: garbageCollectPool: pool timeout disabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS302I AssemblyLine pool: Connector pool size = *size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS303I AssemblyLine pool: removing PooledConnectorSet object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS304I AssemblyLine pool: getAssemblyline: wait for release.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS305I AssemblyLine pool: preparing AssemblyLine: AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS306I AssemblyLine pool: Adding pooled runtime Connector: Connector name.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS307I AssemblyLine pool: AssemblyLine worker thread: worker name: active=boolean.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS308E AssemblyLine pool termination is pending.

Explanation

The error occurs when trying to execute event while termination of the AssemblyLine Pool is pending.

Action

See message.

CTGDIS309I executeEvent: *hash code*, **event:** *event*,
threadMode: *thread mode*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS310I AssemblyLine worker thread: *thread name* is started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS311I -- add runtime Connector: *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS312I -- add runtime Connector config: *Config name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS313I exitBranch: skipping to: *AssemblyLine component*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS314I -- executeCycle: *work entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS315I AssemblyLine worker thread: *thread name* is stopped.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS316I AssemblyLine pool: ConnectorPool: close Connector: *Connector name; class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS317I AssemblyLine pool: ConnectorPool: close function: *Connector name; class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS318I AssemblyLine pool: PoolTimer:
garbageCollectPool.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS319E Connector Library name is NULL.

Explanation

The error occurs when the constructor of the ConnectorPool is called with null Connector Library Name.

Action

Configure Pool definition

**CTGDIS320E Connector Pool Definition Config is NULL for
Connector: *Connector name*.**

Explanation

The error occurs when the constructor of the ConnectorPool is called with null Pool Definition Config.

Action

Contact IBM support.

**CTGDIS321E Connector Pool is not enabled for Connector:
Connector name.**

Explanation

The configuration of the Connector does not enable Connector Pool usage.

Action

Configure Connector Pool for the Connector.

**CTGDIS322E Connector Pool Log is NULL for Connector:
Connector name.**

Explanation

The error occurs when the constructor of the ConnectorPool is called with null Connector Pool Log.

Action

Contact IBM support.

CTGDIS323E Invalid max pool size for Connector *Connector name: pool size.*

Explanation

The error occurs when the maximum Connector Pool size is less or equal to 0.

Action

Set the maximum Connector pool size to a value greater than 0.

CTGDIS324W Minimum Connector pool size exceeds the maximum size: *pool size; Connector name.*

Explanation

This occurs when the minimum Connector Pool size exceeds the maximum Connector Pool size.

Action

Set the minimum Connector pool size to a value less than or equal to the maximum Connector pool size.

CTGDIS325W Minimum Connector pool size is set to the maximum value: *pool size; Connector name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS326W Invalid initialize attempts number: *number of attempts; Connector name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS327W Initialize attempts set to: *number of attempts; Connector name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS328W Invalid initialize sleep interval: *time interval*; *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS329W Initialize sleep interval set to: *time interval*; *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS330E Error on preparing Connector Pool instance for *Connector Connector name*. Exception occurred: *exception*

Explanation

This error occurs during creation of the initial Connector instances.

Action

See the exception message for more information.

CTGDIS331I Pool shrinker thread started for: *Connector name*; purge interval: *time interval*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS332I *Connector name* **Connector Pool** is initialized.
Prepared instances: *pool size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS333E **Error terminating Connector:** *exception*

Explanation

This error occurs while terminating a Connector instance.

Action

See the exception message for more information.

CTGDIS334I *Connector name* **Connector Pool** is terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS335E **Connector Pool is not initialized:** *Connector name*.

Explanation

This error occurs when there is an attempt to use a Connector Pool that is not initialized.

Action

Contact IBM support.

CTGDIS336E **Connector Pool reached its maximum size:**
Connector name.

Explanation

This error occurs when there is an attempt to add a new Connector to the pool, but the pool size has reached its maximum limit.

Action

Check the configuration of the Connector Pool and the setting of exhaustedPoolBehavior Connector's parameter.

CTGDIS337I Connector added to pool: *Connector name*; **new pool size:** *pool size*; **free Connectors:** *integer*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS338I InterruptedException while waiting for free Connector: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS339I Connector taken from pool: *Connector name*; **pool size:** *pool size*; **free Connectors:** *integer*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS340I Connector added to pool on request: *Connector name*; **pool size:** *pool size*; **free Connectors:** *integer*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS341I Connector returned to pool: *Connector name*; **pool size:** *pool size*; **free Connectors:** *integer*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS342I Connector returned to pool after pool termination: *Connector name*; pool size: *pool size*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS343E Error initializing Connector on attempt *attempt number*: *exception*

Explanation

This error occurs when attempting to initialize Connector.

Action

See the exception message for more information.

CTGDIS344I InterruptedException on Connector initialize attempt: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS345E Could not initialize pooled Connector *Connector Name* after *number of attempts* attempts.

Explanation

This error occurs when initialization of the Connector failed.

Action

Ensure the pooled Connector is configured appropriately.

CTGDIS346I New pooled Connector created: *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS347I Connector pool purge: *Connector name; old size/free: pool size/integer; new size/free: pool size/integer.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS348E Null configuration for attribute map.

Explanation

This error occurs when the attribute map configuration passed to the loadMap method is null.

Action

Contact IBM support.

CTGDIS349E Null configuration for Hooks.

Explanation

This error occurs when the hook configuration passed to the loadEventManager method is null.

Action

Contact IBM support.

CTGDIS350I Hook *hook name* [*counter*].

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS351I Map Attribute *attribute name* [*counter*].

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS352I Use null Behavior for *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS353I Script is: *script_mapping*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS354E The key store password is NULL or empty.

Explanation

This error occurs when the key store password passed to the createStashFile method is null or an empty string.

Action

Specify valid key store password

CTGDIS355E Stash file already read.

Explanation

This error occurs when trying to read the stash file more than once.

Action

Check the configuration and if the problem persists contact IBM support.

CTGDIS356E Stash file *file name* not found in solution folder.

Explanation

This error occurs when trying to read the stash file but the specified file is not present in the solution directory.

Action

The stash file should be created.

CTGDIS357E Input Stream is NULL.**Explanation**

This error occurs when the input stream passed to the readArray method is null.

Action

Contact IBM support.

CTGDIS358E The key password or keystore password failed a size validation check. Unable to read in the key password or the keystore password from the stash file.**Explanation**

The correct size of the key password or keystore password was determined before reading their values from the stash file. The size of one of the values read in did not match the specified size and failed the validation check.

Action

Verify that the stash file is valid and has not been corrupted. Verify the stash file has not been changed by a user or process while the application was running.

CTGDIS359E Output Stream is NULL.**Explanation**

This error occurs when the output stream passed to the writeArray method is null.

Action

Contact IBM support.

CTGDIS360E Byte array is NULL.**Explanation**

This error occurs when the byte array passed to the writeArray method is null.

Action

Contact IBM support.

CTGDIS361E Encrypted password data too long: *length*.**Explanation**

This error occurs when the byte array passed to the writeArray is longer than 255 characters.

Action

Contact IBM support.

CTGDIS362I Stash file *file name* has been created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS363E Could not create stash file. Exception occurred: *exception*

Explanation

See message.

Action

See the exception message for more information.

CTGDIS364I Usage: createstash keyStorePassword [keyPassword [securityProviderClass]]

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS365E Expecting CRLF after javascript expression start.

Explanation

The parameter substitution for javascript expressions uses Here Document syntax to delimit the javascript code snippet. The end of the terminator string of the Here Document must be marked by CRLF.

Action

Specify the external property correctly.

CTGDIS366E Cannot find javascript terminator line: *string*.

Explanation

The parameter substitution for javascript expressions uses Here Document syntax to delimit the javascript code snippet. The end of the code snippet must be marked

by the terminator string(on its own line), which is specified at the beginning of the Here Document.

Action

Verify the syntax of the parameter substitution.

CTGDIS367E Bad index specification (missing end bracket)

in: *name*

Explanation

The parameter must be in the following format: object.name_or_attribute[index]

Action

Specify the parameter correctly.

CTGDIS368E Unable to index the class *class name*.

Explanation

IBM Security Directory Integrator parameter substitution mechanism does not support indexing of objects of the specified type.

Action

Verify that the syntax is correct.

CTGDIS369E No MetamergeConfig (mc) or Config object provided.

Explanation

The method requires access to a MetamergeConfig object either explicitly through the "mc" parameter or by way of the "config" parameter.

Action

Contact IBM support.

CTGDIS370I Error decrypting password. Exception occurred:
exception

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS371I Table *table name* does not exist. Will try to create.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS372I Table *table name* has been successfully created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS373I Database shutdown not performed (non-embedded database).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS374I Database shutdown ignored for: *database name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS375I Database *database name* retained.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS376I Shutting down database: *database name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS377I Renamed table IDI_SYSPROPS to IDI_PS_DEFAULT.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS378I Error in migratetable.syspros. Exception occurred: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS379I Exception occurred while migrating delta tables: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS380I Migrating Delta Tables.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS381I Error in renaming table. The table does not exist. Exception occurred: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS382I Finished Migrating Delta Tables.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS383E Cannot get local namespace for: *namespace*

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDIS384I Finished including all scripts from the script library where auto-include is true in the *Config name* Config.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS385I -- Include script: *script*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS386I Including all scripts from the script library where auto-include is true in the *Config name* config.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS387E No such script: *script* (included by *context name*)

Explanation

The script is not found in the configuration.

Action

Ensure the script exists in the configuration.

CTGDIS388I Dump of JSEngine global variables

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS389E '*function*' is not a function

Explanation

The script element with the specified name is not a function.

Action

Ensure the script element with the specified name is a function.

CTGDIS390E Function *function name* not found.

Explanation

The function with the specified name is not defined. A script must define the function before the function can be called.

Action

Ensure the function is defined before it is called.

CTGDIS391E No functions defined.

Explanation

No function definitions are loaded by the ScriptEngine.

Action

Ensure functions are defined before used.

CTGDIS392E The system.deleteFile(...) tried to delete a directory and failed. Supplied file path: *file path*

Explanation

The system.deleteFile(...) can only delete normal files.

Action

Set an appropriate file path to point to a normal file.

CTGDIS393I Throwing this exception to tell the AssemblyLine to skip the current Entry. If used in an EventHandler, this exception tells the EventHandler to skip the remaining actions.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS394I Created file *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS395I Do not overwrite existing file *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS396I Do not copy directory *directory*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS397E Cannot create directory: *directory*.

Explanation

Copying directory failed because the destination directory cannot be created.

Action

See message

CTGDIS398I Created directory: *directory*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS399I Unable to send mail.Exception occurred:
*messaging_exception***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS400E Bad number in com.ibm.di.server.rotatelog:
'parameter value'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS401I declareUserFunctions: *key as class name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS402E No 'class' parameter in EventHandler configuration.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS403I Function '*Config name*' in '*thread name*' will be *state*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS404I Connector '*Config name*' in '*thread name*' will be *state*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS405E Deprecated Connector:
com.ibm.di.connector.ConsumerProducer.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS406E The loadConnector method cannot find 'connectorType' or 'class' parameter in configuration.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS407E Cannot get configuration for Connector: *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS408E The loadParser method cannot find 'class' parameter in configuration.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS409E Cannot get configuration for Parser: *Parser name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS410I Creating sandbox store: *identifier*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS411W Error on firing eventProcessed method on EventHandler Listener: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS412W Exception in dispatchEvent: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS413I Terminate Signal: skip all actions and terminate Handler.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS414E Action not found. SkipToException occurred: *exception*

Explanation

SkipToException is used to instruct an EventHandler to skip to a named action. The action must exist in the EventHandler configuration.

Action

Ensure the action exists in the EventHandler configuration.

CTGDIS415I SkipToException *exception* found at index *index*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS416I SkipToException occurred: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS417I Ignore Entry: continue with next action.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS418I Restart Entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS419I Skip Entry: skip rest of actions.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS420I Action did not match criteria.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS421I Action: *Switchboard Action* not matched.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS422I Execute Action.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS423I Unable to dispatch the event because the *component type* is not initialized and is NULL.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS424W Error on firing eventCaptured method on EventHandler Listener: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS425I Finished dumping EventHandler properties.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS426I key: *key*, *property*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS427I Dumping EventHandler properties.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS428I Finished including Script Library.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS429I Including Script Library.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS430W Cannot load script engine. Exception occurred:
exception

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS431W Error creating logger in *parameter name*.
Exception occurred: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS432I Normal Termination.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS433I Terminated with errors.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS434W Debugger: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS435I EventHandler Terminating.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS436I ExitHook: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS437I Interceptor.stop: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS438I *thread name* will record all events.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS439I Parser output stream class: *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS440I Null value for Parser output stream.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS441I Parser input stream class: *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS442I Call Parser for: *Parser mode*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS443I Applying Parser: output stream *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS444I Applying Parser: input stream *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS445I Applying Parser: *Parser name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS446E No EventHandler specified for this action.

Explanation

No EventHandler specified for execution.

Action

Set the EventHandler for execution.

CTGDIS447E No AssemblyLine specified for this action.

Explanation

No AssemblyLine specified for execution.

Action

Set the AssemblyLine for execution.

CTGDIS448I The executeAction will execute action *action*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS449I Execute actions in Condition *condition*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS450I Switchboard Action: Execute error handlers.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS451W Switchboard Action: No error handlers.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS452E Key not found: *key*.

Explanation

Object with the specified key does not exist in the B-Tree. This is an internal error.

Action

Contact IBM support.

CTGDIS453E Bad node index *index*.

Explanation

The B-Tree node does not have a child node with the specified index. This is an internal error.

Action

Contact IBM support.

CTGDIS454E Expected a DBNode object but the following object was encountered: *node name*.

Explanation

IBM Security Directory Integrator represents B-Tree nodes as objects of type DBNode. This exception is an internal error.

Action

Contact IBM support.

CTGDIS455E Duplicate key: *key*.

Explanation

A node with this key already exists. This is an internal error.

Action

Contact IBM support.

CTGDIS456W Failed to write entry to the B-Tree database.

Explanation

The B-Tree logic failed. This is an internal error.

Action

Contact IBM support.

CTGDIS457E Undefined type of interface.

Explanation

Each IBM Security Directory Integrator Java Object, which wraps a COM object, must derive from com.ibm.di.automation.IUnknown or com.ibm.di.automation.IDispatch.

Action

Contact IBM support.

CTGDIS458E Cannot convert to VARIANT.

Explanation

Do not know how to convert this type of Object to VARIANT.

Action

Contact IBM support.

CTGDIS459E IDispatch object expected.

Explanation

The requested operation requires a derivative of com.ibm.di.automation.IDispatch.

Action

Contact IBM support.

CTGDIS480E EntryFilter has no script engine instance to execute scripts.

Explanation

This is an internal error.

Action

Contact IBM support

CTGDIS481E 'fmatch' function did not return a boolean value.

Explanation

The scripted condition for an EventHandler action can optionally define a 'fmatch' function. This function must return a java.lang.Boolean value. (This implies that the return value must not be null.)

Action

Verify the configuration of the EventHandler.

CTGDIS482E No such method ''method name''.

Explanation

The operand for a simple condition of an EventHandler action must have a corresponding binary predicate in the EntryFilterExpression class.

Action

Check the settings of the EventHandlers

CTGDIS483E Function has not been initialized.

Explanation

The initialize method of the function component has not been executed since its creation or since its last termination.

Action

Ensure the function component is initialized before being used.

CTGDIS484I Connector *class name: version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS485I Parser *class name: version number*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS486I Do not initialize a (runtime provided) Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS487I Skipping *number of entries* entries for iterator: *Connector name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS488E Non delta entry received in Delta mode.

Explanation

Configuration requires strict Delta mode - only delta entries (added, modified or deleted) are being accepted.

Action

Verify the configuration and if the problem persists contact IBM support.

CTGDIS489I Ignoring non-delta entry in Delta mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS490I Generated new-style delta entry from delta.old property.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS491I Original delta entry

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS492I New delta entry

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS493I Delta Operation: *operation*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS494I Entry found, calling delete method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS495I handleException , *operation*, *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS496E Automatic Reconnect.

Explanation

This exception is part of the automatic reconnect logic flow and should always be internally handled.

Action

Check the Connector' settings. If the problem persists, contact IBM support.

CTGDIS497W Cannot find the java class for *component*. The jar file may be corrupted, or a file may have been deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS498I Using provided parameter.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS503E No values to add.

Explanation

This exception is part of the logic flow. It is used to instruct the AssemblyLine to skip the current Connector and continue with the next Connector in the AssemblyLine. This exception should always be internally handled.

Action

Check if the configuration is correct. If the problem persists, contact IBM support.

CTGDIS504I *Result of attribute mapping*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS505I The 'conn' object

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS506I The 'work' object

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS507I The 'current' object

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS508E Invalid component type specified for JLOGAppender: '*component type*'. The only valid values are 'AL' and 'EH'.

Explanation

See message.

Action

See message

CTGDIS509E No component type assigned to MOBJ appender.

Explanation

See message.

Action

See message

CTGDIS510I Activate the jlog options...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS511I Component type has not been specified.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS512I JLogHandler: component name has not been specified.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS513I JLogHandler: log pattern has not been specified.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS514W Could not generate log file name. Exception occurred: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS515W Exception occurred while saving
jlog.properties: *exception***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS516E No component type assigned to JLOG appender.

Explanation

JLOG incorporates the component type in the file system path to the log file.

Action

Check the configuration of the JLOG appender.

CTGDIS517E Unsupported appender: *appender*

Explanation

The specified type of appender is not supported by the IBM Security Directory Integrator logging framework. The supported appenders are : IDIFileRoller, Console, File, Syslog, NTEventLog, DailyRollingFile and SystemLog.

Action

Verify the appender is supported by IBM Security Directory Integrator.

**CTGDIS518W Cannot create appender: *appender* Exception
occurred: *exception***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS519W Error initializing custom appender: *appender*
Exception occurred: *exception***

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS520W *appender*: Parameter value for parameter ('value') must be a positive integer.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS521W *appender*: Parameter value for parameter ('value') must be a known hostname.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS522W *appender*: No method to set Parameter value for parameter ('value')

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIS523W Parser will use default encoding.
UnsupportedEncodingException occurred while setting the
character set: *exception***

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS524I Closing Parser on input stream.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS525I Closing Parser on output stream.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS526W Closing Parser: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS527W EntryList::AddEntry: PerfEntry null.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS528W Entry Already Exists. Entry Not added *entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS529I *****

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS530I Current instance name: *instance name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS531I Not all required system store properties have been defined. The memory queue initialization will be done using system store default values.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS532E Bad signature in input stream.

Explanation

Readers of class com.ibm.di.security.EncryptedReader expect the input stream to start with a predefined character sequence (signature).

Action

Verify the input stream is encrypted and is not corrupted.

CTGDIS533E Invalid encrypted signature in input stream.

Explanation

All streams, encoded by com.ibm.di.security.EncryptedWriter are laid out in the following format: [signature][encrypted data]. Where [encrypted data] after decryption looks like this: [signature][payload data]. Where [payload data] is the actual data which was passed to the EncryptedWriter for encryption. Readers of class com.ibm.di.security.EncryptedReader expect the encrypted part of the input stream after decryption to start with the predefined signature.

Action

Verify the input stream is encrypted and is not corrupted.

CTGDIS534E Exception occurred while reading line:
exception

Explanation

See message.

Action

Contact IBM support.

CTGDIS535E Unable to decrypt the string because it was not in the proper format. The required string format is 'length of encrypted data/space_character/encrypted data'.

Explanation

See message.

Action

Verify the string being decrypted is in the proper format.

CTGDIS536E Conditional script did not do 'ret.value=true|false'.

Explanation

Conditional script of a branch component must set the 'value' attribute of the 'ret' object to either 'true' or 'false'.

Action

Verify the configuration of the branch component.

CTGDIS537E Invalid return value: *value (class name)*.

Explanation

Conditional script of a branch component must return a java.lang.Boolean value.

Action

Verify the configuration of the branch component.

CTGDIS538E NULL attribute name in condition number + index '*index*'.

Explanation

Each condition in a branch component must specify a valid attribute name.

Action

Verify the configuration of the branch component.

CTGDIS541I branch-end: setNextConnector: *branch component*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS542I loop-end: setNextConnector: *component*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS543E Cannot set next Connector.
Explanation

See message.

Action

Check whether Connector with such name exists and contact IBM support.

CTGDIS544E Parsing error on line *line_number*. Last line was: *line*. Error is *error*.
Explanation

Problem found while parsing the built-in configuration from the .inf files. This is an internal error.

Action

Contact IBM support.

CTGDIS545E Parsing error at *URL* on line *line_number*. Last line was: *line*. Error is *error*.
Explanation

Problem found while parsing the built-in configuration from the .inf files. This is an internal error.

Action

Contact IBM support.

CTGDIS546E Unexpected line: *line*.**Explanation**

Problem found while parsing the built-in configuration from the .inf files. This is an internal error.

Action

Contact IBM support.

CTGDIS547I Do not initialize a (runtime provided) function**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS548E Function returned non-Entry/Attribute object in AssemblyLine and no default attribute name defined: *class name=object*.**Explanation**

See message.

Action

Check the configuration and if the problem persists contact IBM support.

CTGDIS549I Initialize loop component: *loop type*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS550E No work Entry Attribute name specified for the Attribute Loop.**Explanation**

Loop Components support three types of loops: Conditional Loop, Connector Loop and Attribute Value Loop. The name of this work Entry Attribute is required because an Attribute Value Loop must iterate on the values of a multi-valued Attribute from the work Entry. This error indicates the name of the work Entry Attribute was not provided.

Action

Type in the name of the work Entry Attribute in the "Work Attribute Name:" text box.

CTGDIS551E No loop Entry Attribute name specified for attribute loop

Explanation

Loop Components support three types of loops: Conditional Loop, Connector Loop and Attribute Value Loop. Attribute Value Loop iterates over the values of a specified Attribute from the work Entry. Each value is passed into the loop in a new work Entry attribute - the loop Entry Attribute. This error indicates the name of the loop Entry Attribute was not provided.

Action

Specify valid name for Loop Attribute Name parameter.

CTGDIS552I checkConnectorInit: *work entry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS553I Begining of setConnectorParams method

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS554I -- setting Connector parameter: *name=parameter name, value=parameter value*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS555E Reply Channel: Target component is null.

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDIS556I SWITCH *component name*: '*expression*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS557I CASE: *component name*'*expression*' == '*expression*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS564I The delta SQL1 is: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS565E Invalid DeltaStore identifier: *ID*.

Explanation

The DeltaStore identifier must not be empty and must not consist of whitespaces only.

Action

Specify valid name for deltaDB(Delta Store) parameter

CTGDIS566E Update sequence for key: *key*, update count != 1 (count = *count*).

Explanation

Inconsistency is observed while updating the database: updating info for a single key should affect a single row. This is an internal error.

Action

Contact IBM support.

CTGDIS567E Update entry for key: *key*, update count != 1 (count = *count*)

Explanation

Inconsistency is observed while updating the database: updating info for a single key should affect a single row. This is an internal error.

Action

Contact IBM support.

CTGDIS568E Insert entry for key: *key*, update count != 1 (count = *count*).

Explanation

Inconsistency is observed while inserting into the database: update count should be 1. This is an internal error.

Action

Contact IBM support.

CTGDIS569E Duplicate delta key: *key*.

Explanation

The sequence id of the entry with the specified key is not consistent with the sequence id for the Delta Table from the Delta Systable.

Action

Verify the Delta Store is not corrupted and if the problem persists contact IBM support.

CTGDIS570E Delete entry for key: *key*, update count != 1 (count = *count*).

Explanation

Inconsistency is observed while inserting into the database: update count should be 1. This is an internal error.

Action

Contact IBM support.

CTGDIS571E The getNextDeletedEntry method was called without prior selectDeletedEntries method call.**Explanation**

The deleted entries should be selected before they can be iterated.

Action

Contact IBM support.

CTGDIS572E Incompatible version in *table name*.**Explanation**

The table version is newer than supported.

Action

Contact IBM support.

CTGDIS573E Must specify table.**Explanation**

A PropertyStore must be associated with a table.

Action

Check the PropertyStore configuration. If the problem persists contact IBM support.

CTGDIS574E Cannot put NULL value for key: *key*.**Explanation**

The value of a property in a PropertyStore cannot be null.

Action

Contact IBM support.

CTGDIS582E *name: exception***Explanation**

An error occurred while registering the parent IBM Security Directory Integrator Server instance with the ScriptEngine of the Trigger.

Action

Contact IBM support.

CTGDIS583W Initializing script engine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS584I Cannot load log-appender: *error*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS585I Including all scripts from the Script Library marked for auto-include.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS586I Finished including all scripts from the Script Library marked for auto-include.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS587E XML document has no root.

Explanation

The CSServersInfo.xml document is not well formed because it has no root element.

Action

Provide valid xml document

CTGDIS588E Expected child item at index *index*.**Explanation**

Child node of the root element not found in CSServersInfo.xml. This is an internal error.

Action

Contact IBM support.

CTGDIS589I Connect to *server name: port***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS590E Process stopped by debugger.**Explanation**

See message.

Action

Contact IBM support.

CTGDIS591E Call to *name* but no more calls recorded in table *table*.**Explanation**

For the Sandbox record feature all operations are serialized into a store. Later replay is done based on the information in the store. Operations are recreated one by one while iterating over the store. The error indicates that replay is requested after the store is depleted. This is an internal error.

Action

Contact IBM support.

CTGDIS592E Call to *name* but next recorded method was: *method*.**Explanation**

For the Sandbox record feature all operations are serialized into a store. Later replay is done based on the information in the store. Operations are recreated one by one while iterating over the store. The error indicates that the name of the operation, for which replay is requested, does not match the name of the operation in the current position of the store. This is an internal error.

Action

Contact IBM support.

CTGDIS593E Internal IDI proxy object exception: *exception*
Explanation

An error occurred while replaying/recording an operation.

Action

Contact IBM support.

CTGDIS594I Recording Connector calls to table *table name* in database *database name*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS595I Reading Connector calls from table *table name* in database *database name*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS596E The nibble was unable to parse a hexadecimal digit: '*symbol*'.
Explanation

The symbol is an invalid hexadecimal digit.

Action

Check that the parameters have valid names and contact IBM support.

CTGDIS597E Error in releasing License: *exception*
Explanation

An error occurs while releasing the license when the application is shutting down

Action

Check the license on the License Manager Server.

CTGDIS598E No Valid License was found. Server exiting...**Explanation**

No license could be obtained for the current product instance. The product will not operate without license.

Action

Check the license on the License Manager Server.

CTGDIS599E Not enough capacity was found. Server exiting...**Explanation**

License could not be obtained for the current product instance because all registered licenses are already in use. The product will not operate without license.

Action

Check the license on the License Manager Server.

CTGDIS600E Cannot contact IBM Tivoli License Manager Server. Server exiting...**Explanation**

License could not be obtained for the current product instance because a connection to the License Manager Server could not be established. The product will not operate without license.

Action

Check the connection to the License Manager Server.

CTGDIS601E An internal error occurred while using the IBM Tivoli License Manager Toolkit. Contact IBM support.**Explanation**

The IBM Tivoli License Manager Toolkit encountered an internal error. License could not be obtained for the current product instance. The product will not operate without license.

Action

Contact IBM support.

CTGDIS602E Invalid parameter exception occurred while using the IBM Tivoli License Manager Toolkit. The server is exiting...

Explanation

License request failed due to an invalid parameter.

Action

Check the parameters of the license. Check the license on the License Manager Server. If the problem persists contact IBM support.

CTGDIS603E Error in retrieving License : *exception*.

Explanation

License could not be obtained for the current product from the License Manager Server.

Action

See the exception message for more information. Check the parameters of the license and connection to the License Manager Server.

CTGDIS604I ***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS605I Usage: ibmdisrv [OPTION]... Allowable options are: **-c <file ...>** Configuration files. Loading multiple files requires the **-d** option. **-d** Run in daemon mode **-d close** Run in daemon mode, and close standard output and standard error when ready to accept commands **-e** Start the Server in secure mode. **-f <extProp1=file1,extProp2=file2 ...>** External property files. **-g** Create solution directory files and exit. **-i** Ignore global properties file and read from solution properties file. **-j <file>** Read AssemblyLine regression info from the named file. **-k** Ignore the work Entry when reading or writing regression info. **-l <file ...>** Redirect Console output to specified log file. **-n <encoding>** Encoding to be used when writing configuration files. **-p** Dump java properties on startup. **-q <mode>** mode=1 Run in record mode, mode=2 Run in playback mode, mode=4 Run in simulate mode **-r <a1 ...>** List of AssemblyLine names to start. To start AssemblyLine a and b, use the command **-r a b**. **-s <dir>** Specifies the working directory where the solution is located. Must be first option. **-v** Show version information and exit. This is logged only in the logfile. **-w** Wait for each AssemblyLine to complete before starting the next. **-D** Disable startup of auto-started AssemblyLines. **-J <file>** Write AssemblyLine regression info to the named file. **-M** Make no modifications on the external systems. (a.k.a. Simulation Mode) **-P <password>** Password if configuration file is encrypted. **-R** Disable Remote API, ignoring the setting in global.properties. **-T** Enable Performance logging **-W** Never terminate the server **-X** Start Derby Network Server and exit **-Y** Stop Derby Network Server and exit **-?** This message **-0** to **-9** for user-defined parameters

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS626I Copying etc files from '*directory*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS627I IBM Security Directory Integrator Shutdown.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS628E Error in COMProxy.dll: *description*.**Explanation**

See message.

Action

Examine the error description for further detail.

CTGDIS629I Entry found in BTree database: *object*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS630I Dumping BTree database at offset *offset...***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS631I Btree database is empty at this offset. Total bytes used: *number of bytes*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS632I Btree database size: *number of bytes.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS633I Total number of bytes used: *number of bytes.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS634I Btree class name: *class name.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS635I Btree object string: *object string.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS636I Btree database statistics for file *file name.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS637I Records in database: *number of records.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS638I Size of records: *record size.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS639I Size of smallest database record: *record size.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS640I Size of largest database record: *record size.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS641I Number of empty blocks: *number of blocks.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS642I Empty blocks size: *number of bytes.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS643I Size of smallest empty block: *number of bytes.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS644I Size of largest empty block: *number of bytes.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS645I *indentation white space* Dumping database structure. Start of a node at offset: *node offset.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS646I *Indentation white space*Left node: *node.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS647I Indentation white spaceLeaf key: leaf key.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS648I Database header: [Version=*version number*, Root node=*node*, Properties=*properties*, Database last modified=*time stamp*]

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS649E Cannot compare at level 1 without a key attribute.

Explanation

At level 1 entries are compared based only on a specified key attribute. This error indicates that the name of the key attribute is missing.

Action

Contact IBM support.

CTGDIS650E Key attributes at level 1 are both null.

Explanation

At level 1 entries are compared based only on a specified key attribute. This error indicates that the key attribute is null in both the compared entries.

Action

Contact IBM support.

CTGDIS651I Dumping EventHandler event properties.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS652I key: *key*, *property*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS653I Finished dumping EventHandler event properties.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS654I GSM07_05: parseEntry: '*entry*'**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS655I Mapping the substring *string* to the character *char*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS656I Mapped the string *string* to value *string*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS657E FileRollerAppender: Cannot delete file: *next* **Explanation**

See message.

Action

Check the problem file.

CTGDIS658E Cannot rename file: *file name.* **Explanation**

See message.

Action

Check the problem file.

CTGDIS659W Exception occurred while using EncryptedReader: *exception* **Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDIS660W Exception occurred while using EncryptedWriter: *exception* **Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDIS661I [FTPClient] Connect to *hostname:port.* **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS662W Exception occurred while parsing the PASV command reply: *exception*

Explanation

See message.

Action

No action is required.

CTGDIS663E Unable to retrieve the file. The file *file name* is a directory.

Explanation

See message.

Action

Verify the file specified for retrieval is not a directory.

CTGDIS664E *file name* does not exist or is a directory.

Explanation

See message.

Action

Verify the specified file exists and is not a directory.

CTGDIS665I [FTPClient] Reading directory listing.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS666I [FTPClient] Directory: *directory name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS667E The connect object is null in the run method.

Explanation

A member field is not properly initialized. This is an internal error.

Action

Contact IBM support.

CTGDIS668I System store not initialized...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS669I [ScriptEngine] RegEx library: *library name* library.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS670I [ScriptEngine] Engine last modified date: *date*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS671E Hierarchical search criteria not supported for SQL.

Explanation

A specified search criteria object is not supported. The only supported types of criteria objects for a SQL filter are com.ibm.di.server.SearchCriteria and com.ibm.di.server.SearchCriteria.rscSearch.

Action

Verify the configuration.

CTGDIS672E Hierarchical search criteria not supported for SimpleFilter.

Explanation

A specified search criteria object is not supported. The only supported type of criteria objects for a simple filter is com.ibm.di.server.SearchCriteria.rscSearch.

Action

Verify the configuration.

CTGDIS673E Hierarchical search criteria not supported for Notes.

Explanation

A specified search criteria object is not supported. The only supported type of criteria objects for a Notes filter is com.ibm.di.server.SearchCriteria.rscSearch.

Action

Verify the configuration.

CTGDIS674I Main Step: *MAIN_STEPS[mainStep]*, Connector Index: *connectorIndex*, Iterator: *iteratorIndex*, Cycle: *cycleCounter*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS675I Licensed Materials - Property of IBM (c) Copyright IBM Corp. 2003, 2003,2006 All Rights Reserved. US Government Users Restricted Rights - Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS676E Branch component with no preceding IF/SWITCH component: *component name*.

Explanation

See message.

Action

Check the configuration.

CTGDIS677E CASE branch without preceding SWITCH or CASE component: *component name*.

Explanation

See message.

Action

Check the configuration.

CTGDIS678E ELSE branch without preceding IF/ELSEIF component: *component name*.

Explanation

See message.

Action

Check the configuration.

CTGDIS679E ELSEIF branch without preceding IF/ELSEIF component: *component name*.

Explanation

See message.

Action

Check the configuration.

CTGDIS680E The System Queue was not able to obtain a JMS Driver with name '*driver name*'.

Explanation

The System Queue was not able to obtain a JMS Driver with the specified name.

Action

Verify the JMS Driver name is correct and if the JMS Driver class is accessible by the Java Virtual Machine.

CTGDIS681E The System Queue was not able ot obtain a Queue Connection Factory.

Explanation

The System Queue was not able to obtain a Queue Connection Factory.

Action

Verify the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS682E An error occurred while getting a Queue Connection Factory: *exception*

Explanation

The specified error has occurred while getting a Queue Connection Factory.

Action

Verify the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS683E The System Queue was not able ot obtain a queue with name '*queue name*'

Explanation

The System Queue was not able to obtain a queue with the specified name.

Action

Verify the queue name is correct and the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS684E An error has occurred while getting a queue with name '*queue name*': *exception*

Explanation

The specified error has occurred while obtaining a queue with the specified name.

Action

Verify the queue name is correct and the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS685E An error has occurred while receiving a message from the queue with name '*queue name*': *exception*

Explanation

The specified error has occurred while receiving a message from the queue with the specified name.

Action

Verify the queue name is correct and the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS686E The object received from queue with name '*queue name*' is not a com.ibm.di.entry.Entry object.

Explanation

The object received from the specified queue is not a com.ibm.di.entry.Entry object.

Action

Verify the queue name is correct.

CTGDIS687E The message received from queue with name '*queue name*' is not a Text Message (javax.jms.TextMessage).

Explanation

The message received from the specified queue is not a Text Message (javax.jms.TextMessage).

Action

Verify the queue name is correct.

CTGDIS688E The message received from queue with name '*queue name*' is not a Bytes Message (javax.jms.BytesMessage).

Explanation

The message received from the specified queue is not a Bytes Message (javax.jms.BytesMessage).

Action

Verify the queue name is correct.

CTGDIS689E The message received from queue with name '*queue name*' is not an Object Message (javax.jms.ObjectMessage).

Explanation

The message received from the specified queue is not an Object Message (javax.jms.ObjectMessage).

Action

Verify the queue name is correct.

CTGDIS690E An error has occurred while sending a message to the queue with name *'queue name'*: *exception*

Explanation

The specified error has occurred while sending a message to the queue with the specified name.

Action

Verify the queue name is correct and the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS691E An error has occurred while creating receiver for the queue with name *'queue name'*: *exception*

Explanation

The specified error has occurred while creating a receiver for the queue with the specified name.

Action

Verify the queue name is correct and the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS692E An error has occurred while creating sender for the queue with name *'queue name'*: *exception*

Explanation

The specified error has occurred while creating a sender for the queue with the specified name.

Action

Verify the queue name is correct and the JMS Driver is properly initialized. The JMS Driver initialization properties are set in global.properties or solution.properties files.

CTGDIS693E Cannot initialize Default System Queue : *exception*

Explanation

The specified error has occurred while creating a Default System Queue object.

Action

Verify the parameters are correct and if the JMS Driver is properly initialized.

CTGDIS694E Default System Queue is not initialized.**Explanation**

The specified error occurred while using Default System Queue object.

Action

Verify the parameters are correct and if the JMS Driver is properly initialized.

CTGDIS695E Cannot initialize MQe System Queue.**Explanation**

The specified error occurred while creating MQe System Queue object.

Action

Verify the parameters for MQe System Queue are correct and if the JMS Driver is properly initialized.

CTGDIS696E MQe System Queue is not initialized.**Explanation**

The specified error occurred while using MQe System Queue object.

Action

Verify the parameters for MQe System Queue are correct and if the JMS Driver is properly initialized.

CTGDIS697E The System Queue has not been started. The IBM Security Directory Integrator server has been configured to not start the System Queue.**Explanation**

The specified error occurred while using System Queue engine.

Action

Verify the System Queue is turned on.

**CTGDIS698W Default System Queue is not initialized.
Required property 'systemqueue.jmsdriver.name' is not set.****Explanation**

The specified property systemqueue.jmsdriver.name is required, but not set.

Action

Set the property systemqueue.jmsdriver.name.

CTGDIS699W MQe System Queue is not initialized. Required property '*parameter value*' is not set.

Explanation

The specified property is required, but not set.

Action

Set the specified property.

CTGDIS705E ERROR : *error*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIS706I XML document has no children: *tag name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS707I XML document has *number of children* children.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS708I XML Child node has no children (skipped).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS709I XML Child node has no children (skipped).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS710I The node does not exist. Creating a new one.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS711I XML Child node has no children (skipped).**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS712E Failed to delete node. Exception occurred:

exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIS714W SAX Parse Warning: line:*line number*, ID:*ID*.**Explanation**

See message.

Action

No action is required.

CTGDIS715I Usage: com.ibm.di.util.ConvertEncoding srcFile destFile srcEncoding [destEncoding]. Where destEncoding is optional; if not specified the default encoding is used.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS718E The number of source files does not match the number of destination files.

Explanation

The ConvertEncoding tool converts text files between two specified encodings. The tool accepts two lists of files - source files and destination files. The n-th file from the source list will be converted to the n-th file from the destination list. The error indicates that the two lists differ in size.

Action

Verify the command-line arguments for the ConvertEncoding tool.

CTGDIS719E Error constructing RacfCredential object: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIS720I Credential: *password*, Version: *version*, Change Time: *timestamp*, Language: *language*, Expired: *date*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS721I No Connector list in task.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS724I Test program to test PKCS7 SignedData methods.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS725I Usage: IDIpkcs7Crypto

```
[-receivecertKeystore=receiverCertificateKeystoreFileName]  
[-receivecertKeystorePW=receiverCertificateKeystorePassword]  
[-receivecertAlias=receiverCertificateAlias]  
[-receivecertPW=receiverCertificatePassword] [-  
signercertKeystore=signerCertificateKeystoreFileName]  
[-signercertKeystorePW=signerCertificateKeystorePassword]  
[-signercertAlias=signerCertificateAlias]  
[-envelope=pkcs7EnvelopeFileName]
```

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS726E Unknown parameter *parameter name*.

Explanation

The IDIpkcs7Crypto tool does not know how to interpret the specified parameter.

Action

Verify the command-line arguments for the IDIpkcs7Crypto tool.

CTGDIS727I Password Envelope specified: *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS728I Recipient certificate keystore specified: *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS729I Recipient Certificate Keystore Password specified: *keystore password*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS730I Recipient Certificate Alias specified: *\tralias*
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS731I Recipient Certificate password specified: *\tpassword*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS732I Signer Certificate Alias specified: *\talias*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS733I Password Value obtained: *password*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS734I Password Object Contents: *object*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS735E Exception getting ContentInfo from bytes.

Detail: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDIS736I Obtaining EnvelopedData content from ContentInfo...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS737E Error in packaged information. Expecting EnvelopedData.

Explanation

The data is not enveloped for protection by encryption.

Action

Specify envelope file that contains valid PKCS7 package to be decrypted.

CTGDIS738E Error in packaged information. Expecting SignedData.

Explanation

See message.

Action

No action is required.

CTGDIS739E No KeyStore certificate returned because alias specified may be invalid. Alias: *alias* KeyStore File.

Explanation

See message.

Action

Verify that the alias specified was correct.

CTGDIS740E Error encountered while obtaining KeyStore certificate. Alias specified may be invalid. Alias: *alias* KeyStore File. Detail: *exception*

Explanation

See message.

Action

Verify that the alias specified was correct.

CTGDIS741E Error decoding password payload while obtaining sequence for DerInputStream Detail: *exception*

Explanation

I/O error occurred while reading the enveloped data from the envelope file.

Action

Try again later and contact IBM support if the problem occurs again.

CTGDIS742E Error searching Recipient keystore certificates Detail: *exception*

Explanation

The keystore has not been initialized (loaded).

Action

Contact IBM support.

CTGDIS743E Exception decrypting envelopedData. Detail: *exception*

Explanation

Cannot get the key or cannot decrypt the enveloped data.

Action

Check the configuration data.

CTGDIS744E Error opening signer certificate file: *file name* Detail: *exception*

Explanation

The certificate provided in inStream must be DER-encoded and may be supplied in binary or printable (Base64) encoding. If the certificate is provided in Base64 encoding, it must be bounded at the beginning by -----BEGIN CERTIFICATE-----, and must be bounded at the end by -----END CERTIFICATE-----.

Action

Ensure the file that contains the data for the certificate contains all the needed information and the data is properly encoded.

CTGDIS745E Exception decrypting envelopedData obtaining aliases from KeyStore object: *exception*

Explanation

The keystore is not initialized.

Action

Check that the specified keystore password is correct, the java.security file is consistent and the run-time service provider is consistent.

CTGDIS746E Exception decrypting envelopedData obtaining key from KeyStore object: *exception*

Explanation

The algorithm used for recovering the key cannot be found.

Action

Check that the java.security file is consistent as well as the run-time service provider.

CTGDIS747E Exception decrypting envelopedData obtaining key from KeyStore object: *exception*

Explanation

The key cannot be recovered. The password might be wrong.

Action

Ensure the keystore password is correct and contact IBM support if the problem still exists.

CTGDIS748E SignedData does not have certificate: *type*.**Explanation**

The specified keystore does not have certificate with such alias.

Action

Specify a different keystore or certificate alias.

CTGDIS749E SignedData not verified with public key from certificate: *type*.**Explanation**

The signatures on signed data are not valid for the specified certificate.

Action

If possible, specify a different keystore and/or certificate alias.

CTGDIS750E Exception occurred while verifying SignedData: *exception***Explanation**

An I/O error occurred.

Action

Check the configuration data.

CTGDIS751E Exception occurred while verifying SignedData: *exception***Explanation**

The signatures on signed data are not valid for the specified certificate.

Action

If possible, specify other keystore and/or certificate alias.

CTGDIS752E Exception occurred while verifying SignedData: *exception***Explanation**

The key cannot be recovered.

Action

Check the service provider is consistent.

**CTGDIS753E Key file not found for load: *path*.
Explanation**

The keystore is not found at the specified location.

Action

Specify valid path to the keystore.

**CTGDIS754E Error processing key file during load: *path*
Verify keystore password is correctly specified. Detail:
*exception*****Explanation**

I/O or format problem with the keystore data.

Action

Verify the data in the keystore are in the proper format.

**CTGDIS755E Error processing key file while obtainin
KeyStore instance: Provider: *provider name* Type: *store type*
Detail: *exception*****Explanation**

The requested keystore type is not available for the provider.

Action

Contact IBM support.

**CTGDIS756E The algorithm used to check the integrity of
the keystore cannot be found. Detail: *exception*****Explanation**

The requested algorithm is not available in the environment.

Action

Check the configuration data in java.security file and that the run-time service provider is consistent.

CTGDIS757E Keystore could not be loaded because the provider '*provider name*' was not found. Encountered an exception: *exception*

Explanation

See message.

Action

Check the provider specification in the java.security file. See the exception message for more information.

CTGDIS758E Certificates in the keystore could not be loaded. Exception occurred: *exception*

Explanation

There is a certificate in the keystore that cannot be loaded.

Action

See the message for more information.

CTGDIS761E The substitution method failed. A circular reference was found a parameter: '*parameter object.parameter name*'.

Explanation

See message.

Action

Ensure the parameter does not cause a circular reference.

CTGDIS766I Parameter { Pattern: *pattern* Object: *object* Name: *name* Qualifier: *name qualifier* Index: *index* MF Params: *params*}

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS769I Next Parameter: *parameter name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS770I -- *object*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS771I *id: error*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS772I --> *string*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS773I *name: exception***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS774E The version number of the Parser is undefined.**Explanation**

The getVersion method of the Parser did not return a version number. A version number can only be displayed for a user defined Parser if the getVersion method of the Parser is defined and returns a java.lang.String object.

Action

If the Parser is not a user defined Parser that has been added to the IBM Security Directory Integrator jars directory, contact IBM Support. Otherwise, verify the user defined Parser has properly implemented the getVersion method.

CTGDIS775E The version number of the Function Component is undefined.

Explanation

The getVersion method of the Function Component did not return a version number. A version number can only be displayed for a user defined Function Component if the getVersion method of the Function Component is defined and returns a java.lang.String object.

Action

If the Function Component is not a user defined Function Component that has been added to the IBM Security Directory Integrator jars directory, contact IBM Support. Otherwise, verify the user defined Function Component has properly implemented the getVersion method.

CTGDIS776E The version number of the EventHandler is undefined.

Explanation

The getVersion method of the EventHandler did not return a version number. A version number can only be displayed for a user defined EventHandler if the getVersion method of the EventHandler is defined and returns a java.lang.String object.

Action

If the EventHandler is not a user defined EventHandler that has been added to the IBM Security Directory Integrator jars directory, contact IBM Support. Otherwise, verify the user defined EventHandler has properly implemented the getVersion method.

CTGDIS777I Exception occurred in debugConnect method: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS778I The following SQL statement is to be executed:
sql statement.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS779E The following error occurred during method invocation, performed by Connector: *error message.*

Explanation

An internal error has occurred.

Action

Contact IBM support.

CTGDIS780I The result from method invocation, performed by Connector is: *error message.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS781I Dumping the Performance Entry: *entry.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS782I Dumping performance entry: *additional information: entry*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS783I Dumping performance entry: *additional information: entry*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS784I Method parameters: *method parameters.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS785I ---

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS786I *entry*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS787W The AssemblyLine could not be set up.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS788I Throwing this exception to tell the AssemblyLine to skip the current Connector and continue with the next Connector in the AssemblyLine. If used in an EventHandler, this exception tells the EventHandler to skip to the next action.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS789I Throwing this exception to tell the AssemblyLine to restart. The AssemblyLine will continue at the first non-Iterator Connector in the AssemblyLine, using the current work object. If used in an EventHandler, this exception tells the EventHandler to skip to the first action.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS790I Throwing this exception to tell the AssemblyLine to retry this Connector. The AssemblyLine will perform the operation of the current Connector again, using the current work object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS791I *property name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS792I *property value*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS793E Connector class is missing on the following line of the reconnect rules configuration file: *line*

Explanation

Connector class must be specified for each rule in the reconnect rules file. Eventually the class name can be empty, but the corresponding delimiters must appear.

Action

Verify that the syntax of the problem line of the reconnect rules file is correct.

CTGDIS794E Connector name is missing on the following line of the reconnect rules configuration file: *line*

Explanation

Connector name must be specified for each rule in the reconnect rules file. Eventually the connector name can be empty, but the corresponding delimiters must appear.

Action

Verify that the syntax of the problem line of the reconnect rules file is correct.

CTGDIS795E Exception class is missing in the reconnect rules file on the following line: *line*

Explanation

Exception class must be specified for each rule in the reconnect rules file. Eventually the class name can be empty, but the corresponding delimiters must appear.

Action

Verify that the syntax of the problem line of the reconnect rules file is correct.

CTGDIS796E Action is missing in the reconnect rules file on the following line: *line*

Explanation

Action must be specified for each rule in the reconnect rules file.

Action

Verify that the syntax of the problem line of the reconnect rules file is correct.

CTGDIS797E Error while loading reconnect rules

Explanation

There was a problem while loading the reconnect rules - either the rules which are built into the connector jar files, or the rules from the user defined file.

Action

If the problem is in the file with user defined rules, verify that the used syntax is correct. If the problem is not in the file with user defined rules, contact IBM support.

CTGDIS798I Reconnect rule: connector class = *connectorClass*, connector name = *connectorName*, exception class = *exceptionClass*, regular expression = *exceptionMessageRegExp*, action = *action*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS800I User-defined reconnect rules:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS801I Getting reconnect choice for: connector class = *connectorClass*, connector name = *connectorName*, error = *error*. Selected rule: connector class = *rule.connectorClass*, connector name = *rule.connectorName*, exception class = *rule.exceptionClass*, regular expression = *rule.exceptionMessageRegExp*, action = *rule.getAction()*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS802I Getting reconnect choice for connector class = *connectorClass*, connector name = *connectorName*, error = *error*. No matching rule found. Using default action - *defaultAction*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS803E Invalid action encountered in the reconnect rules file on the following line: *line*

Explanation

Action must be 'error', 'ignore' or 'reconnect'.

Action

Verify that the syntax of the problem line of the reconnect rules file is correct.

CTGDIS805E Problems were encountered while parsing the file with user-defined reconnect rules. The rules with errors were not loaded. Total count of rules with errors: *error count*.

Explanation

While parsing the file with user-defined reconnect rules, an error message for each problem rule was logged. The current message only alerts that there were errors.

Action

Verify that the syntax of the user-defined rules is correct - check the logged error messages for each particular problem rule.

CTGDIS806E User-defined rule with error has been encountered: *exception error message*.

Explanation

See message.

Action

Verify that the syntax of the user-defined rules is correct.

CTGDIS807E Queue with the name *name* does not exist.

Explanation

See message.

Action

Specify queue that exists in memory.

CTGDIS808E Problem encountered while running AssemblyLine Pool

Explanation

See message.

Action

Examine the Server log to see what is the concrete problem.

CTGDIS809E handleException - cannot handle exception , *operation*

Explanation

An exception occurred during the operation of the AssemblyLineComponent. No hooks are available, so the exception is left unhandled.

Action

Verify that the configuration is correct.

CTGDIS810E handleException - cannot handle exception , *operation*

Explanation

An exception occurred during the operation of the AssemblyLineComponent. The reconnect mechanism (for Connectors only) could not handle the exception. The

configured error hooks did not handle the exception, so the exception is left unhandled.

Action

Verify that the configuration is correct.

CTGDIS811E Cannot insert new Entry in Delta Table, the original Exception was *sqlException*

Explanation

An Exception occurred while inserting an Entry into the Delta Table. This could be caused by some database problem, lack of permission, or maybe because more than one AssemblyLine used the same Delta Table.

Action

Consider the original Exception, and try to correct the problem. If more than one AssemblyLine use the same Delta Table at one time, the solution should be rewritten.

CTGDIS812E Cannot create table. The SQL statements on which the error occurred are: *sql statements*. The Exception is: *exception*

Explanation

The SQL statements, used to create table did not execute correctly. It might be due to the configuration of IBM Security Directory Integrator or some Connector or due to internal error.

Action

Check the configuration and contact IBM support if the problem still exists.

CTGDIS813W The AssemblyLine could not be set up due to problem with the Script Engine.

Explanation

The reference to the Script Engine is null.

Action

Contact IBM support.

CTGDIS814E An exception occurred while starting an AssemblyLine: *exception*

Explanation

The AssemblyLine cannot be started. It might be due to error in constructing the Task Call Block or in the process of starting the AssemblyLine.

Action

Check the configuration and contact IBM support if the problem still exists.

CTGDIS818I Next Parameter Expanded: *parameter value*. **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS819E Error occurred in starting Event Handler: ***exception*.**

Explanation

Error occurred during starting Event Handler on debug port. The port might be already busy or the Event Handler might not be defined.

Action

Check that such Event Handler is defined and the port on which it should run is not already used by another program.

CTGDIS820E Error occurred in initializing server' security **when the server runs in secure mode: *exception*.**

Explanation

The specified error has occurred while reading the stash file.

Action

See the message for more information.

CTGDIS821I *version information* **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS822E Error occurred getting version information: ***exception*.**

Explanation

I/O error occurred.

Action

Try again later and contact IBM support if the problem still exists.

CTGDIS823I The command is: *command*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS824I Sending password...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS825I Read 1 line: *line*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS826I Line included in the reply: *line*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS827I Class name: *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS828I Superclass / Interface

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS829E Exception occurred while creating the database file: *exception*

Explanation

Error while creating database file.

Action

Check the configuration.

CTGDIS830I *formatting message*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS831I Next database element: *database element*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS832W Database element information: *element information*.

Explanation

The B-Tree logic failed. This is an internal error.

Action

Contact IBM support.

CTGDIS833I Executing empty system store method. All contents of table associated with queue will be deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS834E SAX Parse error message: *message*

Explanation

Review the error message for more information.

Action

Contact IBM support.

CTGDIS835I The memory buffer store thread is alive and an interrupt request was sent to it.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS836I The memory buffer load thread is alive and an interrupt request was sent to it.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS837E Exception occurred while trying to evaluate script expression: *exception*.

Explanation

See the exception message for more information.

Action

Verify that the script expression is correct.

CTGDIS840W The size of the AssemblyLine Pool has been reset to 1 because debugging is enabled.

Explanation

While debugging, the size of the AssemblyLine Pool cannot be greater than 1.

Action

Disable debug mode if the solution needs a larger AssemblyLine Pool size.

CTGDIS841W AssemblyLine pool: The maximum number of concurrent instances has been reset to the number of prepared instances, *number of prepared instances*, because the configured value, *maximum number of concurrent instances*, is less than the number of prepared instances.

Explanation

The Config has a value for maximum concurrent instances that is less than the number of prepared instances. The value for maximum concurrent instances has been reset.

Action

Set the maximum concurrent instances to a value that is greater than or equal to the number of prepared instances.

CTGDIS845E No config object provided, cannot evaluate *expression*.

Explanation

To evaluate this expression, you need to provide a config object.

Action

Add a config object to the map provided to the substitute method.

CTGDIS846E Cannot evaluate *expression*, no AssemblyLine Component found.

Explanation

The AssemblyLine Component that this expression refers to, could not be located.

Action

Make sure the config object is part of an AssemblyLine containing the named AssemblyLine Component.

CTGDIS847W Could not recognize value *value* for Global Property *property*, default value will be used.

Explanation

The value for the named property was not one that could be recognized and used. As a consequence, the default value will be used instead.

Action

Verify the spelling for the value of the named property.

CTGDIS848E FIPS Mode failed to initialize. Exception: *exception*

Explanation

An Exception occurred during FIPS initialization. Check the Exception message for more details.

Action

Review the Exception message; verify that all FIPS recommendations are met.

CTGDIS849I FIPS Mode successfully initialized.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS850E An Error occurred while trying to remove the IBMJCEFIPS security provider from the providers list.

Exception: *exception*

Explanation

The IBMJCEFIPS provider should be set before the IBMJCE provider. That is why it is first removed and later installed in the correct place in the security providers list.

Action

View the Exception message for more information.

CTGDIS851E An Error occurred while trying to install the security providers. Exception: *exception*

Explanation

The security providers should be installed in specific order to run IBM Security Directory Integrator in FIPS Compliant Mode.

Action

View the Exception message for more information.

CTGDIS852E An Error occurred while trying to install the IBMJCEFIPS security provider in the correct place in the security providers list.

Explanation

The IBMJCEFIPS provider should be set before the IBMJCE provider in the security providers list.

Action

View the Exception message for more information.

CTGDIS853E An Error occurred while trying to set the default JSSE socket factories, the IBM Security Directory Integrator security provider System property and the FIPS enabling property in IBMJSSE2 provider. Exception: *exception*

Explanation

This could be due to some Security permissions. The properties are not set because the JVM Security Manager did not allowed it.

Action

View the Exception message for more information.

CTGDIS854E The '*property name*' property is read-only and its value could not be changed.

Explanation

User tries to set a property which is internal and its value cannot be changed.

Action

Change the property name to value which is not a read-only property.

CTGDIS855I A property with the name *property name* does not exist.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS859E A required parameter is missing: *parameter name*
Explanation

The parameter with the specified name was not found within the supplied parameters.

Action

Provide the required parameter.

CTGDIS860E Unexpected token: *parameter name* If the token is intended to be a parameter value, provide a parameter name for it. If the token is intended to be a parameter name, prefix it with <->.

Explanation

The command line uses an incorrect syntax.

Action

Verify that the command line is correct.

CTGDIS861I Usage: -genseckey -alias <key alias> -keyalg <key algorithm> -keysize <key size> -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> [-keypass <key password>] [-keygenproviderclass <security provider for key generation>] -delete -alias <key alias> -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> -importkey -srcalias <key alias in the source keystore> -srckeystore <source keystore file> -srcstorepass <source keystore password> -srcstoretype <type of the source keystore> [-srckeypass <password for the key in the source keystore>] -destalias <key alias in the destination keystore> -destkeystore <destination keystore file> -deststorepass <destination keystore password> -deststoretype <destination keystore type> [-destkeypass <password for the key in the destination keystore>] -list -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> -printseckey -alias <key alias> -keystore <keystore file> -storepass <keystore password> -storetype <keystore type> [-keypass <key password>]

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS862E The tool could not determine the operation you would like to execute. Verify that your syntax is correct. Currently supported operations are : *parameter name*, *parameter name* and *parameter name*. Call the tool without parameters to see the usage manual.

Explanation

The provided parameters are either not correctly spelled or are insufficient.

Action

Verify that the command line syntax is correct.

CTGDIS863E Cannot read keystore file *file name: exception*

Explanation

See the exception message.

Action

See the exception message. Check if the keystore file exists. Check if the keystore password is correct.

CTGDIS864E Key generation failed for algorithm '*algorithm name*' and key size *number: exception*

Explanation

See the exception message.

Action

See the exception message. Check if the key size and the key algorithm name are valid.

CTGDIS865I Key algorithm: *algorithm name* Key size: *number*
Raw key: *raw binary data*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS866E No secret key has been found under alias '*alias*' in keystore '*alias*'.

Explanation

See the exception message.

Action

See the exception message. Check if the key password is correct.

CTGDIS867I *alias* : private key entry

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS868I *alias* : trusted certificate entry

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS869I *alias* : secret key entry

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS870E No entry exists under alias '*alias*' in keystore '*file name*'

Explanation

The entry cannot be deleted because it does not exist.

Action

Verify that the alias is correct.

CTGDIS871E Operation failed with error: *exceptions*
Explanation

See the message of the exception.

Action

See the message of the exception.

CTGDIS872E The keystore does not contain a private key entry under alias '*key alias*'. Transformation '*transformation name*' requires a public/private key pair.

Explanation

The keystore entry under the specified alias is either missing or is not a private key entry.

Action

Provide an RSA key pair under the specified alias.

CTGDIS873E The key pair under alias '*key alias*' is for algorithm '*algorithm name*'. RSA keys are required for transformation '*transformation name*'.

Explanation

The key pair under the specified alias is not suited for the specified transformation.

Action

Provide an RSA key pair under the specified alias.

CTGDIS874E The keystore does not contain a secret key under alias '*key alias*'. Transformation '*transformation name*' requires a secret key.

Explanation

The keystore entry under the specified alias is either missing or is not a secret key entry.

Action

Provide a secret key under the specified alias.

CTGDIS875E The required system property '*property name*' has not been set.

Explanation

The specified property is mandatory. Provide an appropriate value for it in `global.properties/solution.properties`.

Action

Verify that the property is set.

CTGDIS876E Cannot load keystore file '*file name*' of type '*keystore format*': exception

Explanation

See the exception message.

Action

See the exception message. Verify that the keystore password is correct. Verify that the keystore file is of the specified type.

CTGDIS877E Cannot write keystore file '*file name*' of type '*keystore format*': exception

Explanation

See the exception message. The keystore could not be written to the file system.

Action

See the exception message. Verify that the keystore file is writable.

CTGDIS878E No entry exists under alias '*alias*' in the source keystore '*file name*'

Explanation

Cannot find the entry to be imported under the specified alias in the source keystore file.

Action

Verify that the alias is correct.

CTGDIS879E The provided password for the entry under alias '*alias*' is incorrect: '*exception*'

Explanation

The tool cannot read the entry because the provided password is incorrect.

Action

Verify that the password for the entry is correct.

CTGDIS880I Started Derby in Network mode on host '*host name*' and port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS881E Not able to start Derby server in Network mode. An exception occurred while starting Derby server in Network mode: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS882E Derby server Host name is not specified, hence starting Derby server on localhost.

Explanation

The host name is not provided by the user, hence the System falls back on the default value namely localhost.

Action

Verify that the global.properties/solution.properties file for the following property: com.ibm.di.store.jdbc.host. Ensure the property is not commented out in the file.

CTGDIS883E Derby server port number is not specified, hence starting Derby server on default port 1527.

Explanation

The port number is not provided by the user. The IBM Security Directory Integrator will use 1527 as the default port value.

Action

Verify that the global.properties/solution.properties file for the following property: com.ibm.di.store.jdbc.port. Ensure the property is not commented out in the file.

CTGDIS884I AssemblyLine *AssemblyLine* name is started in simulate mode.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS885E The 'key' or 'value' the desired entry is null.

Explanation

User wants to add a null value either for 'key' or 'value' in the MapEntry.

Action

Make sure both value are not null and try again.

CTGDIS886E Line *line number* is incorrectly formatted in the properties file: *line information*.

Explanation

Lines in properties files should be in the format 'propertyName=propertyValue'

Action

Correct the line indicated in the properties file.

CTGDIS888E The values in the result entry should be of type com.ibm.di.entry.Entry. The value found is: *Java Object*.

Explanation

During the simulation process the Proxy AssemblyLine contains a non-Entry value in its conn attribute. All values which are set to the conn attribute during the execution of the Proxy AssemblyLine must be of type com.ibm.di.entry.Entry.

Action

Correct the logic in the Proxy AssemblyLine and try again.

CTGDIS889E Checkpoint/Restart is no longer supported. Edit the configuration file so that it does not depend on the Checkpoint/Restart functionality.

Explanation

Checkpoint/Restart is no longer supported. As a result, the AssemblyLine was aborted.

Action

Use the Config Editor to look at the AssemblyLine, and then save the config file. Checkpoint/Restart related settings are automatically removed from the configuration when it is saved. Verify that the solution does not need Checkpoint/Restart.

CTGDIS890E The system store 'username' is null.

Explanation

The system store username is not provided.

Action

Check the property 'com.ibm.di.store.jdbc.user' in the global.properties OR solution.properties.

CTGDIS891E The system store 'jdbcdriver' is null.

Explanation

The system store jdbcdriver is not provided.

Action

Check the property 'com.ibm.di.store.jdbc.driver' in the global.properties OR solution.properties.

CTGDIS892E Error calling method '*Method Name*'. Expected '*Java Object*' object for parameter '*Parameter Name*'.

Explanation

An object from an inappropriate type was provided.

Action

Check the JavaDoc documentation for more information about the method.

CTGDIS893E The entry already contains an Attribute object with the name: '*Attribute Name*'.

Explanation

The entry object maps its attributes to unique names, therefore the 'appendChild' method can not append a child if its local name is already registered in the Entry object.

Action

Make sure that the name of the Attribute is not already registered in the Entry. If it is then use the 'setAttribute(name,object)' method to explicitly replace the existing Attribute.

CTGDIS895E Invalid Property name passed to the constructor.

Explanation

The creation of a Property with an empty name or a null name is forbidden.

Action

Make sure that you provide a valid name for the new Property object.

CTGDIS896I Using configuration id '*name*' for a configuration instance loaded from file '*file name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS897I The memory queue *queue name* is being deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS898E The memory queue was unable to store data to the system store.

Explanation

An error was encountered while trying to store data to the system store.

Action

Make sure the database properties are valid and try again.

CTGDIS899E Memory queue was unable to connect to the system store.

Explanation

An error was encountered while trying to connect to the system store.

Action

Make sure the database properties are valid and try again.

CTGDIS900E Memory queue was unable to empty the system store table.

Explanation

An error was encountered while trying to empty the table associated with the memory queue.

Action

Make sure the database properties are valid and try again.

CTGDIS901E Memory queue was unable to create an instance of the system store connector.

Explanation

An error was encountered while trying to create an instance of the system store connector.

Action

Make sure the database properties are valid and try again.

CTGDIS902E Memory queue was unable to read data from the system store.

Explanation

An error was encountered while trying to read data from the system store.

Action

Make sure the database properties are valid and try again.

CTGDIS903E The value specified for parameter Timeout is invalid.

Explanation

The value specified for Timeout is invalid.

Action

Specify an integer value for timeout.

CTGDIS904E The value specified for parameter Watermark is invalid.

Explanation

The value specified for parameter Watermark is invalid.

Action

Specify an integer value for Watermark.

CTGDIS905E The value specified for parameter Page size is invalid.

Explanation

The value specified for parameter Page size is invalid.

Action

Specify an integer value for Page size.

CTGDIS906E The value specified for parameter Percentage memory to use is invalid.

Explanation

The value specified for parameter Percentage memory to use is invalid.

Action

Specify an integer value for Percentage memory use.

CTGDIS907E The value specified for parameter Percentage memory to use is invalid.

Explanation

The value specified for parameter Percentage memory to use is invalid.

Action

Specify a value between 0 and 100 for Percentage memory to use.

CTGDIS908E The HAttribute object cannot have for a child itself or a HAttribute object which is a parent of it.

Explanation

The provided HAttribute object is either the same or one of the parents of the current HAttribute object.

Action

Check the passed child object and try again.

CTGDIS909E Error deleting file: *file name*

Explanation

The specified file could not be deleted.

Action

Check the file permissions.

CTGDIS910E Error creating directory: *directory name*

Explanation

The specified directory could not be created.

Action

Check the file permissions.

CTGDIS911E Error renaming file: *file name***Explanation**

The specified file could not be renamed.

Action

Check the file permissions.

CTGDIS912E Invalid JavaString extension call: *function name***Explanation**

The provided function name is not supported. The recognized names are 'slice' and 'search'.

Action

Check your internal logic and try again.

CTGDIS913E ALComponent returns bad value for branchType: *AssemblyLine Component*.**Explanation**

The branch type is neither IF/ELSE nor LOOP branch.

Action

Check the configuration and if the problem persists contact IBM support.

CTGDIS914E Unable to add object to the end of the queue.**Explanation**

An error occurred while adding object to the queue.

Action

Check the configuration and if the problem persists contact IBM support.

CTGDIS915I config**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS916I DebugServer : Error sending config : *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS917I ERROR

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS918I switch

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS919E Unable to process the command because the required Config ID was not specified.

Explanation

The Config ID was missing in the command sent to the server.

Action

If the problem persists contact IBM support.

CTGDIS920E Unable to process the command. A Config name must be specified.

Explanation

The Config name was missing in the command sent to the server.

Action

If the problem persists contact IBM support.

CTGDIS921E Sub command required**Explanation**

The sub command was missing in the command sent to the server.

Action

If the problem persists contact IBM support.

CTGDIS922E Must post configuration file to load.**Explanation**

The configuration file was not posted to the server, therefore it cannot be saved.

Action

If the problem persists contact IBM support.

CTGDIS923E Unknown command was encountered: *command*.**Explanation**

The command sent to the server is unknown. This may indicate a protocol failure.

Action

If the problem persists contact IBM support.

CTGDIS924E Configuration file not found: *file name*.**Explanation**

The configuration file was not found.

Action

Verify that the configuration file exists. If the problem persists contact IBM support.

CTGDIS925E Unknown property store name: *property store name*.**Explanation**

The named property store was not found.

Action

Verify that the property store exists with the correct name. If the problem persists contact IBM support.

CTGDIS926E Expected 'Entry' root tag got '*tag*'.**Explanation**

The XML that was sent to the server had the wrong root tag, it should have been an Entry tag.

Action

If the problem persists contact IBM support.

CTGDIS927I Calling the startAssemblyLine method...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS928E Entry does not contain a valid changelog entry (changes attribute missing) for operation: *type*.**Explanation**

The changes attribute 'newrdn' is missing in the entry.

Action

Check the attributes in the entry.

CTGDIS929E Unable to parse changes attribute.**Explanation**

The LDIF Parser could not read the entry.

Action

Check the entry.

CTGDIS930W Error creating directory: *directory name*.**Explanation**

The specified directory could not be created.

Action

Check the file permissions.

CTGDIS931W Error creating directory: *directory name*.**Explanation**

The specified directory could not be created.

Action

Check the file permissions.

CTGDIS932W Cannot delete file: *file name*.

Explanation

See message.

Action

Check the problem file.

CTGDIS933W Cannot rename file: *file name*.

Explanation

See message.

Action

Check the problem file.

CTGDIS934W Cannot rename file: *file name*.

Explanation

See message.

Action

Check the problem file.

CTGDIS935W An Exception occurred while trying to close the debugger connection. Exception: *exception*.

Explanation

Before the debugger is close a message is logged. The Exception is due to an error while the message is being printed. The debugger connection is not closed. See the Exception message for more details.

Action

Examine the Exception and try again.

CTGDIS936W An Exception occurred while declaring the ''work'' script object. Exception: *exception*.

Explanation

The "work" object might not be available in the script of "On Failure" AssemblyLine hook.

Action

Examine the Exception and try again.

CTGDIS937W An Exception occurred while executing the 'On Failure' AssemblyLine hook. Exception: *exception*.

Explanation

The script of "On Failure" AssemblyLine hook throw an Exception.

Action

Examine the Exception and try again.

CTGDIS938W An Exception occurred while building the Link Criteria from the work Entry object. Exception: *exception*.

Explanation

The Link Criteria was not build successfully. It could be due to insufficient data in the AssemblyLine or error in the Link Criteria rules.

Action

Examine the Exception and try again.

CTGDIS939W Cannot declare the name of the AssemblyLine Pool instance as a bean in the Javascript engine. Exception: *exception*.

Explanation

The AssemblyLine Pool instance will not be available for access through script.

Action

Examine the Exception and try again.

CTGDIS940E The AssemblyLine is already being debugged.

Explanation

Cannot attach a debugger to the AssemblyLine, because it is already has a debugger. Only one debugger is allowed per AssemblyLine.

Action

Detach the current debugger of the AssemblyLine. Then attach the new one.

CTGDIS941E Cannot connect to the debugger on host *ip address or host name* and port *TCP port number*.

Explanation

The AssemblyLine will not use the debugger, because a connection cannot established.

Action

Verify that the debugger is running.

CTGDIS942E The argument is not recognized as a document:
object document.

Explanation

The argument should be a StreamSource, String, Reader, InputStream or File.

Action

Verify the type of the argument.

CTGDIS943W The component '*name*' is erroneously placed in the Feed Folder. It will be temporarily moved to the Data Flow Folder.

Explanation

In earlier versions, it was possible to place components in the Feed Folder, even when they were not a Connector in Iterator or Server mode. This is conceptually wrong, and deprecated. To make the AssemblyLine run, the component is temporarily moved to the Data Flow Folder.

Action

Use the Config Editor to look at the AssemblyLine. This will automatically move the Component into the Data Flow section. Verify that the Component has the correct position, and save the AssemblyLine.

CTGDIS944E The provided Property object ("*property name*") is not owned by this Attribute object.

Explanation

The Property belongs to a different Attribute than the one which removeAttributeNode was called on.

Action

Make sure the Property object is removed only from its owner Attribute object.

CTGDIS946E Cannot set debug mode for component '*component name*'. There is no such component in AssemblyLine '*AssemblyLine name*'.

Explanation

The specified component name is invalid.

Action

Verify that the component name is consistent with the AssemblyLine configuration.

CTGDIS947E Cannot retrieve debug mode for component '*component name*'. There is no such component in AssemblyLine '*AssemblyLine name*'.

Explanation

The specified component name is invalid.

Action

Verify that the component name is consistent with the AssemblyLine configuration.

CTGDIS948E Cannot set debug mode for component '*component name*'. There is no such component in AssemblyLine '*AssemblyLine name*'.

Explanation

The specified component name is invalid.

Action

Verify that the component name is consistent with the AssemblyLine configuration.

CTGDIS949E Cannot retrieve debug mode for component '*component name*'. There is no such component in AssemblyLine '*AssemblyLine name*'.

Explanation

The specified component name is invalid.

Action

Verify that the component name is consistent with the AssemblyLine configuration.

**CTGDIS950I Delta Statistics: Sequence ID: *sequence number*
Number of Entries: *number of entries* Number of old Entries:
*number old entries***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS951E While getting delta statistics: *error*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS952I Calls: *number of calls*, Errors: *number of errors* **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS953I Calls: *number of calls* **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS954E Error loading configuration files *file names*. Specifying multiple files requires the -d option. **Explanation**

The configuration files specified using the -c commandline option for the ibmdisrv could not be loaded. When specifying multiple files, the -d option must also be used.

Action

Use the -d command line option when specifying multiple files. If only one file was specified, verify that the specified file exists.

CTGDIS955E Error while registering cryptographic provider '*provider name*'. **Explanation**

The default cryptographic provider could not be loaded.

Action

Verify that the provider name is correct. Verify that the jar of the provider is on the classpath. See the Server log to view the specific exception.

CTGDIS956E Cannot use SSL on data channel if SSL on the command channel is not enabled.

Explanation

When the FTP client uses SSL there are two options: to use SSL on the command channel only, or to use it on both the command and data channels. SSL enablement on the data channel alone is not allowed, because of security issues.

Action

Verify that SSL is used on the command channel. If SSL is not needed, neither SSL option may be used.

CTGDIS957E The system encountered an internal error while trying to validate a product license. Message: *message*.

Explanation

An internal error is preventing validation of the product license.

Action

Contact IBM support.

CTGDIS958E The system cannot find an enrolled product license.

Explanation

An enrolled product license could not be found.

Action

In order to use Security Directory Integrator, you need to ensure that a valid license is enrolled. If you experience any problems with licensing, you should contact your IBM representative or authorized dealer for assistance.

CTGDIS959E The evaluation period has expired.

Explanation

The evaluation period for this copy of Security Directory Integrator has now expired.

Action

This copy of Security Directory Integrator is licensed for use for a limited period only. This copy of Security Directory Integrator has now exceeded the licensed period and will no longer execute. You can purchase a full license for unlimited use of the product by contacting your IBM representative or authorized dealer.

CTGDIS960W There are *number of days* days left in the evaluation period.

Explanation

The evaluation period for this copy of Security Directory Integrator has the specified number of days to run until expiry.

Action

This copy of Security Directory Integrator is licensed for use for a limited period only. This copy of Security Directory Integrator will continue to execute for the specified number of days, but will then expire and not execute in the future. You can purchase a full license for unlimited use of the product by contacting your IBM representative or authorized dealer.

CTGDIS961E The evaluation period is invalid.

Explanation

The evaluation period for this copy of Security Directory Integrator is invalid.

Action

This copy of Security Directory Integrator is licensed for use for a limited period only. This copy of Security Directory Integrator appears to have more than the maximum allowed number of days (90) remaining in the evaluation period.

CTGDIS962W Running the AssemblyLine in Simulation mode

Explanation

The AssemblyLine runs in Simulation mode. Most operations will only be simulated.

Action

This can be changed in the Specify Run Options panel in the Config Editor.

CTGDIS963W AssemblyLine *name* cannot be started, because the Config Instance is shutting down.

Explanation

While the Config Instance is shutting down, new AssemblyLines cannot be started.

Action

No action is required.

CTGDIS964I Shutting down the AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS965W AssemblyLine *name* could not be stopped.

Explanation

The AssemblyLine could not be stopped; is there code in the AssemblyLine catching all Exceptions?

Action

If there is code in the AssemblyLine to catch Exceptions, consider rewriting the code to allow the AssemblyLine to be shut down gracefully.

CTGDIS966E The keystore file '*file name*' had the following problem: *error message*

Explanation

There was a problem using the named keystore file.

Action

See the included error message for further details.

CTGDIS967I AssemblyLine started by *thread name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS968E No Failover Connector Name provided

Explanation

Connection failover was specified, but no Failover Connector Name was provided

Action

Specify a Failover Connector Name, or do not use Connection failover.

CTGDIS969E Changelog Entry does not contain a changetype Attribute. The Entry is: *entry*.

Explanation

The changetype attribute is missing in the entry. This attribute is mandatory.

Action

Check the attributes in the entry.

CTGDIS1880W Transactions are not supported by the database.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1881W The specified row locking is not supported by the database.**Explanation**

The database does not support the selected transaction isolation level.

Action

Select another row locking option.

CTGDIS1882E Error while loading script *name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1884E Cannot compute the next date**Explanation**

The month/day combination in the schedule is not valid.

Action

Change the schedule to use valid dates.

CTGDIS1885E No AssemblyLine specified.**Explanation**

No AssemblyLine has been specified for the Scheduler to run.

Action

Specify an AssemblyLine for the Scheduler.

CTGDIS1886I Scheduler started by *thread name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1887I Finished.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1888E No config instance name specified.

Explanation

A remote server was specified, but no config instance name.

Action

Specify a config instance name.

**CTGDIS1889E Problem while starting the AssemblyLine:
*exception***

Explanation

The AssemblyLine could not be started.

Action

Examine the exception to determine the cause of the problem.

**CTGDIS1890E The AssemblyLine did not run long enough,
terminating.**

Explanation

The AssemblyLine did not run as long as specified in the Min-secs parameter.

Action

Determine the cause of the problem.

CTGDIS1891E Cannot find config instance *id*.

Explanation

The named config instance could not be found.

Action

Determine the cause of the problem.

**CTGDIS1892E Problem while starting the Failure
AssemblyLine: *exception***

Explanation

The Failure AssemblyLine could not be started.

Action

Examine the exception to determine the cause of the problem.

**CTGDIS1893W Cannot locate file *file name* referenced by
component.**

Explanation

The named file could not be found.

Action

Create the file.

**CTGDIS1894E Schedule: Incorrect number of fields in
string.**

Explanation

A Schedule must be exactly 6 fields separated by space.

Action

Make sure the schedule consists of 6 fields separated by space.

CTGDIS1895E Schedule field value too large: *value*.

Explanation

The fields in a schedule must be comma separated integers in the following ranges:
Month 0-11, day in month 1-31, day in week 1-7, hour 0-23, minute and second
0-59.

Action

Correct the value that is too large.

CTGDIS1896E No AssemblyLine specified.**Explanation**

No AssemblyLine name has been specified in a Sequence.

Action

Specify an AssemblyLine name.

CTGDIS1897I Sequence *name* started.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1898I Sequence started by *thread name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1899I Rule with priority '*priority*' and name '*name*' requires: *attr names* (+ add, - remove).**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1900I Rule with priority '*priority*' and name '*name*' is satisfied.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1901I Rule with priority '*priority*' requires: *attr names* (+ add, - remove).

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1902I Rule with priority '*priority*' is satisfied.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1903E Class type is not provided.

Explanation

No class type provided in the UI of the Component.

Action

Provide the class type in the UI of the Component.

CTGDIS1904E The IT registry meta data is not supported for Naming Rule validation.

Explanation

The IT registry meta data does not provide support for Naming Rules and cannot be used for validation.

Action

Change the configuration of the Component to rely on CDM meta data.

CTGDIS1905E Unable to find configuration for Sequence *name*.

Explanation

The named Sequence cannot be found.

Action

Verify that the configuration file contains the named Sequence.

CTGDIS1906E An error has occurred while decrypting protected property: *exception*

Explanation

See Message.

Action

See the exception message for more information.

CTGDIS1907I Compute changes is not supported for hierarchical entries.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1908E Cannot read regression info: *exception*

Explanation

This AssemblyLine was supposed to read regression info from a specified file, but were unable to open the file. Read the attached exception for more information.

Action

Make sure the file name is correct, and that the file has the proper permissions.

CTGDIS1909E Cannot write regression info: *exception*

Explanation

This AssemblyLine was supposed to write regression info to a specified file, but were unable to do so. Read the attached exception for more information.

Action

Make sure the file name is correct, and that the file has the proper permissions.

CTGDIS1910W The regression file does not contain information about this AssemblyLine

Explanation

This AssemblyLine was supposed to read regression info from a file and make a comparison, but the file does not contain information from this AssemblyLine.

Action

Make sure the file name is correct, and that the file contains information from the correct AssemblyLine.

CTGDIS1911W Premature end of regression file at cycle number.

Explanation

This AssemblyLine reads regression info from a file and compares to that. There is not enough information in the file, maybe the previous run stopped prematurely.

Action

The AssemblyLine behaves different than before, this could indicate a regression problem.

CTGDIS1912W Not the same information in Entry name at component, cycle number. Old info: *oldinfo*, new info: *newinfo*.

Explanation

This AssemblyLine was supposed to read regression info from a file and compare to that. A difference was found.

Action

The AssemblyLine behaves different than before. This could indicate a regression problem.

CTGDIS1913W This run of the AssemblyLine stopped earlier than the previous run, only *number* cycles completed.

Explanation

This AssemblyLine reads regression info from a file and compares to that. When the AssemblyLine stopped, there was still data in the regression file.

Action

The AssemblyLine behaves different than before, this could indicate a regression problem.

CTGDIS1914I Not initializing a re-used Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1915I Derby Network Server started.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1916W Only able to start or stop Derby Network Server.**Explanation**

This command is only able to start or stop a Derby Network Server.

Action

Verify the `com.ibm.di.store.jdbc.driver` property.

CTGDIS1917I Derby Network Server stopped.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1918W Unable to stop Derby Network Server.**Explanation**

The network server could not be stopped, it may not be running.

Action

Look at the Exception to determine the cause of the problem.

CTGDIS1919E No path was found in the SCIM request.**Explanation**

The HTTP request path was empty.

Action

Use a correct SCIM request path.

CTGDIS1920E XML is not supported.**Explanation**

This SCIM server does not support XML.

Action

Use JSON.

CTGDIS1921E Cannot change *endPoint*.**Explanation**

The SCIM request tried to change fixed information.

Action

Fixed information can only be changed in the server configuration files.

CTGDIS1922E Unknown schema *schema*.**Explanation**

The SCIM request tried to read an unknown schema.

Action

Only the Users and Groups schemas exist.

CTGDIS1923E Unknown endpoint *endPoint*.**Explanation**

The SCIM endpoint was unknown.

Action

Use a correct SCIM endpoint.

CTGDIS1924E The *name* attribute was not specified.**Explanation**

The SCIM request to create a new resource must contain the specified attribute. This attribute is used to create the LDAP Distinguished Name.

Action

Add the attribute with the specified name to the request, providing a unique value.

CTGDIS1925E A resource with that *name* attribute already exists.**Explanation**

The request tried to create a new resource, using the identifier for a user or group that already exists. This identifier was provided in the attribute with the specified name.

Action

Specify a unique identifier for each user and group.

CTGDIS1926E Could not find the new resource after adding it.

Explanation

The new resource could not be found.

Action

Contact the SCIM administrator.

CTGDIS1927E Unable to find ID: *ID*.

Explanation

The SCIM ID in the request could not be found.

Action

Specify an existing SCIM ID.

CTGDIS1928E The ID was not specified.

Explanation

The request needs a valid ID.

Action

Specify an existing ID.

CTGDIS1929E The file *fileName* was not found.

Explanation

This is an internal server error.

Action

Contact the SCIM administrator.

CTGDIS1930E Cannot connect to the LDAP server.

Explanation

The SCIM server is unable to connect to the backend LDAP server.

Action

Contact the SCIM administrator.

CTGDIS1931E The request did not have a body.

Explanation

The SCIM request requires a body containing information.

Action

Provide a body.

CTGDIS1932E The information in the request body could not be parsed: *exception*

Explanation

The information in the request body could not be parsed by the JSON parser. The exception provides information that may help in understanding the error.

Action

Provide a body in correct JSON format.

CTGDIS1933E An error occurred while parsing JSON in the file *file name*.

Explanation

The information in the specified mapping file could not be parsed by the JSON parser.

Action

Contact the SCIM administrator.

CTGDIS1934I No resource was found using the filter: *filterString*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1935W No resource was found using the search base *base*.

Explanation

The specified search base did not contain any information, probably because no users or groups were created yet.

Action

No action is required.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1936E No CreatedN mapping was found in the mapping file.

Explanation

The mapping file must contain exactly one attribute with a CreateDN mapping, which is used to create an LDAP Distinguished Name. The default is `userName` for users and `displayName` for groups.

Action

Contact the SCIM administrator, to correct the `UserMapping.json` or `GroupMapping.json` file.

CTGDIS1937E Unable to parse filter at column *number*.

Explanation

The provided filter could not be parsed. The column number indicates approximately where the error occurred.

Action

Correct the search filter.

CTGDIS1938I Unknown attribute: *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1939I Additional text after end of expression: *text*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1940I An operator was expected.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1941I Unsupported operator: *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1942I A closing parenthesis was expected, but found: *token*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1943I The value is missing for operator: *operator*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1944I A string value was expected, but found: *token*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1945I Unknown Unicode character expression: *token*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1946I Unexpected end of string value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1947I *attribute name* cannot have the value *value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1948I Unsupported operator *operator* for *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1949W Cannot parse URL: *url*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1950W Cannot read truststore *filename*. The following error occurred: *exception*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1951W Cannot create SSLContext. The following error occurred: *exception*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1952W Cannot connect to host *host* on port *number*. The following error occurred: *exception*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1953I The connection is already trusted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1954W The following socket exception occurred: *exception*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1955W Did not receive any certificate.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1956W Unable to add certificate to truststore. The following error occurred: *exception*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIS1957I Added certificate with subject: *subject*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE101E Constructed with non-TreeMap object: *data*.

Explanation

See message.

Action

No action is required.

CTGDKE102E *Component name* Cannot setup inheritance: *parameter*.

Explanation

See message.

Action

No action is required.

CTGDKE103E Cannot inherit from itself: *component name*?

Explanation

This message occurs when a component is defined to inherit from itself, or the component from which it inherits is changed with the 'Inherit from' button.

Action

Change the configuration so that no components inherit from themselves.

CTGDKE104E *component name*: This object has no MetamergeConfig object.

Explanation

See message.

Action

No action is required.

CTGDKE105E *component name* cannot inherit from self.

Explanation

See message.

Action

No action is required.

CTGDKE106I this class is no longer in use: ConnectorSchemaConfigImpl.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE107E Unknown property line: *string*.

Explanation

See message.

Action

No action is required.

CTGDKE108E No filename specified for *component name*.

Explanation

See message.

Action

No action is required.

CTGDKE109I EXTPROP: getParameter: *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE110I EXTPROP: setValue: *name* = *value*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE111E No metamerger Config in this or parents object for: *object*.

Explanation

See message.

Action

No action is required.

CTGDKE112E Loading configuration in server secure mode combined with password is not allowed

Explanation

See message.

Action

No action is required.

CTGDKE113I Convert old style CFG file.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE114I Using new style CFG file.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE115E FileConfig Data is NULL.

Explanation

See message.

Action

No action is required.

CTGDKE116I Ignoring create of forms folder.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE117I Move folder from *name* to *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE118I convertNames: fixHooks for AssemblyLine

AssemblyLine name. **Exception occurred: *exception***

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE119I convertNames: fixHooks for Connectors.
Exception occurred: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE120I fixIncludes: *ignore*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE122I L00KUP: *name, class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE123I Cache hit for: *name, class name@hash code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE124E Not a context/treemap: *name*.

Explanation

See message.

Action

No action is required.

CTGDKE125I Add baseconfig cache: *name, class name@obj.hashCode()*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE126I Add object cache: *name, class name@ hash code.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE127E Cannot save to: *class name.*

Explanation

See message.

Action

No action is required.

CTGDKE128E Creating a folder is not supported by this config driver.

Explanation

This is the base config driver. It does not support creating folders.

Action

Consider using a config driver which supports creating folders.

CTGDKE129E Bind not supported by this Config driver.

Explanation

See message.

Action

No action is required.

CTGDKE130E Rename not supported by this Config driver.

Explanation

See message. This method rename in MetamergeConfigImpl class is intended to be overridden by descendants of MetamergeConfigImpl class.

Action

No action is required.

CTGDKE131I AssemblyLine *name* found in *folder name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE132E *name* is not an AssemblyLineConfig.

Explanation

See message. The user tries to perform an operation for an Assembly Line that does not exist.

Action

Specify the name of existing Assembly Line.

CTGDKE133I ConnectorConfig *name* found in *folder name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE134E *name* is not a ConnectorConfig.

Explanation

See message.

Action

No action is required.

CTGDKE135I ParserConfig *name* found in *folder name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE136E *name* is not a Parser.

Explanation

See message.

Action

No action is required.

CTGDKE137I EventHandlerConfig *name* found in *folder name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE138E *name* is not an EventHandler

Explanation

See message.

Action

No action is required.

CTGDKE139I Script *name* found in *folder name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE140E *name* is not a Script.

Explanation

See message.

Action

No action is required.

CTGDKE141I Function *name* found in *folder name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE142E *name* is not a Function object.

Explanation

See message.

Action

No action is required.

CTGDKE143E *name* is not a NamespaceConfig.

Explanation

See message.

Action

No action is required.

CTGDKE144E Cannot recursively create folders.

Explanation

See message.

Action

No action is required.

CTGDKE145E Single name component required.

Explanation

See message.

Action

No action is required.

CTGDKE146I CREATE FOLDER: *foldr name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE147E Invalid behavior on exhausted pool value passed: *integer*.

Explanation

See message.

Action

No action is required.

CTGDKE148I Found existing attribute for '*attribute name*.' while migrating 5.2 call parameters.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE149E No name for CallParam

Explanation

See message.

Action

No action is required.

CTGDKE150I AssemblyLineFactory: build *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE151I AssemblyLineFactory: end build

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE152E Cannot parse: *class name*.**Explanation**

See message.

Action

No action is required.

CTGDKE153E Cannot serialize: *class name*.**Explanation**

See message.

Action

No action is required.

CTGDKE154E Cannot serialize *class name*.**Explanation**

See message.

Action

No action is required.

CTGDKE155I XML ConnectorFactory: migrating version 1.0 config to 1.1 (schema configuration).**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE156E Cannot serialize *class name*..**Explanation**

See message.

Action

No action is required.

CTGDKE157I parse: *tag name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE158I EventHandler: *Config name, actionCount=integer.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE159E ACTION_MAP_TAG with no ACTION_MAP_NAME_TAG child element.

Explanation

See message.

Action

No action is required.

CTGDKE160I Created EventHandlerActionConfig: *name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE161I build: *Config name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE162E No XML factory defined for tag: *tag*

Explanation

See message.

Action

No action is required.

CTGDKE163I getImpl: tag=*tag*, class=*class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE164E No configuration implementation defined for tag: *tag*.

Explanation

See message.

Action

No action is required.

CTGDKE165I Dumping Config...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE166I >> Config parameter: *parameter name*: *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE167I HookFactory parse: *tag name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE168I HookFactory getItem: *tag name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE169I H00K: name=*name*, enabled=*string*, debug=*debug*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE167E 'Hook' encountered without a name.

Explanation

See message.

Action

No action is required.

CTGDKE168E No loop type tag in config.

Explanation

See message. Loop type tag is created when a loop component is added.

Action

No action is required.

CTGDKE169E Multiple nodes: *node name*; *node name*.

Explanation

Internal error occurred when working with the Library.

Action

Contact IBM support.

CTGDKE170E Only one Config item allowed: *Config object*
Explanation

See message.

Action

No action is required.

CTGDKE171I External lookup in: *base*; for *name*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE172I Setting base: *base name*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE173I MetamergeConfigFS Commit Changes.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE174I - Commit Changes: Process dirty list.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE175I - Commit Changes: next dirty: *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE176I - Commit Changes: Update modified flags.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE177E No such file: *file name*.

Explanation

See message.

Action

No action is required.

CTGDKE178I Create new File: *path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE179E Cannot load client encrypted file in server secure mode.

Explanation

See message.

Action

No action is required.

CTGDKE180E Missing password for Encrypted file.

Explanation

See message.

Action

No action is required.

CTGDKE181I Read current File (encrypted).**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE182I Read current File.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE183I Read input stream.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE184I Read byte array.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE185I Read URL.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE186I Path is a RemoteConfigURL.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE187E Unknown PROVIDER_URL: *path*.**Explanation**

See message.

Action

No action is required.

CTGDKE188E Config file is not PKI encrypted (not allowed in server secure mode).**Explanation**

See message.

Action

No action is required.

CTGDKE189I *name* >> found cached object.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE190E Single name component required.**Explanation**

See message.

Action

No action is required.

CTGDKE191E Cannot recursively create folders.**Explanation**

See message.

Action

No action is required.

CTGDKE192E Move not supported.**Explanation**

See message.

Action

No action is required.

CTGDKE193E Internal error: The XML element not found for rename operation.**Explanation**

See message.

Action

No action is required.

CTGDKE194E Cannot remove standard object.**Explanation**

See message.

Action

No action is required.

CTGDKE195E Cannot remove top level element.**Explanation**

See message.

Action

No action is required.

CTGDKE196I InternalBind: *object name, size --> object.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE197E No XML Factory for object: *name*, class: *class name*.

Explanation

See message.

Action

No action is required.

CTGDKE198I transformObject: Name=*name*, class=*class name*, tag=*tag*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE199I MetamergeXML Commit Changes.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE200E Saving configuration in server secure mode combined with password is not allowed.

Explanation

See message.

Action

No action is required.

CTGDKE202I - Commit Changes: Process dirty list.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE203I - Commit Changes: next dirty: *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE204I - Commit Changes: Update modified flags.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE205W Restoring *file name* as *file name*.

Explanation

See message.

Action

No action is required.

CTGDKE206E Cannot save because no output was specified.

Explanation

See message.

Action

No action is required.

CTGDKE207E Unknown output object class: *class name*.

Explanation

See message.

Action

No action is required.

CTGDKE208I SchemaFactory parse method: *tag name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE209I SchemaFactory migrateSchemaItem method: *tag name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE210I SchemaFactory getItem method: *tag name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE211E Cannot rename standard folder.

Explanation

Standard folders cannot be renamed.

Action

No action is required.

CTGDKE212E Could not obtain remote Session: Session object is null.

Explanation

The remote session must be defined and set before it can be used

Action

Define the remote session parameters

CTGDKE213E The XML document *filename* does not have a root tag of *tag name*.

Explanation

The XML configuration file does not have the MetamergeConfig root tag.

Action

Valid IBM Security Directory Integrator XML configurations must have the MetamergeConfig root tag. Ensure that the XML configuration that you have selected has the MetamergeConfig root tag.

CTGDKE214E The XML document *filename* is newer than version *version number*.

Explanation

The version of the configuration file is not supported in the current version of the IBM Security Directory Integrator Configuration Editor.

Action

Use the latest version of the IBM Security Directory Integrator Configuration Editor tool to load this version of the configuration file.

CTGDKE215W The XML document *filename* is old. Version *version number* expected, version *version number* found. The configuration will be upgraded in memory and used.

Explanation

The version of the configuration file used is older than the expected version.

Action

The older version of the configuration is updated in memory. You need to save the older version as a new different file using the Save as functionality to incorporate the changes made.

CTGDKE216I The old version of the file saved as *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE217E *compound name* could not be found at *context*.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE218E *compound name* could not be found.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE219E Parent from which AssemblyLine Component inherits is not present.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKE220E *name* is already used as operation name.

Explanation

This error occurred because the user tried to name an operation on the Connector level and an operation with that name already exists.

Action

Specify different name for the operation.

CTGDKE220I Inheriting from *name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKE221W The component name is invalid: *name*. An exception occurred: *exception*

Explanation

Component name cannot be parsed.

Action

Examine the exception and check the configuration.

CTGDKE222W Component *component name* has been renamed to *component name*. This has been corrected in your Config file.

Explanation

The name has been changed as the message indicated.

Action

Nothing needs to be done, the next time the config file is saved from the Config Editor, the new name will be written.

CTGDKE223W The old Component name *component name* has been resolved to *component name*.

Explanation

The component name has been resolved to its new name as the message indicated.

Action

No action is required.

CTGDKE224W The evaluation of parameter *parameter name* in *config item* using expression '*expression*' did not return any value.

Explanation

The named parameter did not evaluate to any value.

Action

If the expression uses a property, verify that the property store is well defined and contains the given key. If the expression uses javascript, check the javascript code.

CTGDKE225E The evaluation of parameter *parameter name* in *config item* using expression '*expression*' caused an error.

Explanation

Evaluating the named parameter caused an error.

Action

Inspect the logged error and the expression. Verify that the expression is well formed. If the expression uses a property, verify that you have access to the property store. If the expression uses javascript, check the javascript code.

CTGDKE226E Cannot read the config file *file path*.

Explanation

The config file either does not exist or is empty.

Action

Verify that the config file exists at the specified location and is not empty.

CTGDKE227E Translation file *file path* not found.

Explanation

The translation file was not found.

Action

Verify that the translation file exists inside a jar file in the jars folder.

CTGDKE228E Cannot find the Java class, which the reconnect rule refers to. The error is: *exception*

Explanation

The 'exceptionClass' parameter of the reconnect rule references a Java class, which is not available.

Action

Verify that the exception class is on the classpath.

CTGDKE229E '*action name*' is not valid for a value of the 'action' parameter of the reconnect rule. Must be either 'error' or 'reconnect'.

Explanation

The configuration of the reconnect rule is incorrect.

Action

Verify that the configuration is correct.

CTGDKE230E Cannot find configuration for component '*component name*' inside the configuration of AssemblyLine '*AssemblyLine name*'.

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDKE231E The provided path : '*path*' does not contain a configuration object.

Explanation

The provided path is not valid

Action

Check the path of the configuration and make sure it is correct.

CTGDKE232E The provided path : '*path*' does not contain configuration a object.

Explanation

The provided path is not valid

Action

Check the path of the configuration and make sure it is correct.

CTGDKE233E The provided path : '*path*' does not contain a configuration object.

Explanation

The provided path is not valid

Action

Check the path of the configuration and make sure it is correct.

CTGDKE234W *Exception message*

Explanation

We log a Security Directory Integrator exception message which has its own explanation.

Action

Examine the Exception message.

CTGDKE235E *name* is not an Attribute Map.

Explanation

The named Attribute Map could not be found.

Action

Specify the name of an existing Attribute Map.

CTGDKN501E Could not load configuration file '*file name*'.

Explanation

The specified file either does not exist or could not be read.

Action

Verify that the the file exists and that you have the required permissions to access the file.

CTGDKN502E Invalid mode: 'mode'.

Explanation

The specified mode is not recognized.

Action

See the printed usage information and choose from the available modes.

CTGDKN503E Invalid type: 'type'.

Explanation

The specified type is not recognized.

Action

See the printed usage information and choose from the available types.

CTGDKN504I Property 'property name' is NULL or empty.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN505E Client QueueManager root folder property 'property name' not specified in the configuration file.

Explanation

The configuration property is missing.

Action

Check the configuration file.

CTGDKN506I Client MQe configuration successfully completed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN507E Client MQe configuration failed.

Explanation

See the error message.

Action

Check the exception for more details.

CTGDKN508I Certificate renewal for entity '*entity name*' completed successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN509E Client MQe certificate renewal failed.

Explanation

See the error message.

Action

See the exception for more details.

CTGDKN510E Server QueueManager root folder property '*property name*' was not specified in the configuration file.

Explanation

The configuration property is missing.

Action

Check the configuration file.

CTGDKN511I Server MQe configuration successfully completed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN512E Server MQe configuration failed.**Explanation**

See the error message.

Action

Check the exception for more details

CTGDKN513I Queue operation successfully completed.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN514E The queue operation failed.**Explanation**

See message.

Action

Check the exception for more details.

CTGDKN515I Will create Connection for: '*adapter*'**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN516I A Connection definition with that name is already registered.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN517E Invalid numeric value for property ' *property name* ': *property value* '.

Explanation

The specified property must contain a numerical value.

Action

Correct the value of the specified property.

CTGDKN518I Building connection admin message...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN519I MQeConfig <configuration file> <mode: *mode1* | *mode2* | *mode3* | *mode4*> <type: *type1* | *type2* | *type3* | *type4*> [queuename [targetQMname [QM_ip_or_hostname comm_port]]]

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN520I Building admin message to create remote queue: '*queue*' ; on QM: *apos*;QM'; adapter: *apos*;adapter'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN521E Listener section not specified in QueueManager config.

Explanation

The MQe .ini file must contain a 'Listener' section.

Action

Check the MQe .ini file for errors.

CTGDKN522I Building admin message to create a listener.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN523I Press Enter to send test message...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN524I Message sent.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN525E Could not send test message.

Explanation

See the error message.

Action

Check the exception for additional details.

CTGDKN526I QueueManager terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN527E An unexpected exception occurred.

Explanation

See the error message.

Action

See the exception for more details.

CTGDKN528I Press Enter to receive test message...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN529I Test Failed. Could not receive MQe message. Queue is empty.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN530I Test failed: message received but not of expected type 'TextMessage'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN531I Test failed: message received but text does not match - expected 'msg', received 'msgTxt'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN532I Test MQe message successfully received.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN533E Could not receive test message.**Explanation**

See message.

Action

Check the exception for additional details.

CTGDKN534I Built an admin message to delete a queue.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN535I Queue deleted successfully.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN536I Sending an admin message to QM/queue: *onQMgr/AdminQName*; using QM: *QMgrName*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN537I Waiting for a response to the admin message...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN538E No response message received.**Explanation**

See message.

Action

No help provided.

CTGDKN539I Action failed: '*error message*'**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN540I Error information: '*error message*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN541I Problematic field: '*field name*' '*field value*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN542E The QueueManager is already running.**Explanation**

A reinitialization was attempted.

Action

Only one initialization of the MQe Queue Manager is possible.

CTGDKN543I QueueManager config fields:**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN544E Failed to add the QM Alias name: '*alias*'**Explanation**

An error has occurred while adding the alias for a Queue Manager.

Action

No help provided.

CTGDKN545I Listener port is '*port number*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN546I Listener port was not specified. Using the default value of '*port number*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN547E Unable to create destination directory:
'*directory name*'****Explanation**

The application could not create the directory.

Action

Check whether you have sufficient privileges.

CTGDKN548I MQe QueueManager .ini file was not specified.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN549I MQe QueueManager Queues folder was not specified.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN550E The file '*file name*' is not a valid MQe configuration file, or does not exist.

Explanation

A required file could not be found.

Action

Check the mqeconfig.props configuration file for incorrect values.

CTGDKN551W Unable to delete the directory: '*directory name*'.

Explanation

The specified directory could not be deleted.

Action

Verify that you have sufficient permissions to access the directory and that the directory exists.

CTGDKN552I Admin request was successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM003I KeyStore certificate password is NULL or empty. Will use keystore password to get private key.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM004I The parameter 'storageNotification' was not specified so no notification servers will be set.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM005E Unable to notify Storage notification server '*server URL*' because the format is not valid. The expected format is '<host>:<port>'.

Explanation

See message.

Action

Verify the storage notification servers in the storageNotification parameter are formatted correctly.

CTGDJM006E Unable to notify Storage notification server '*server URL*' because the port '*server URL*' in the URL is not valid.

Explanation

See message.

Action

Verify that the storage notification servers in the storageNotification parameter are formatted correctly and have valid port numbers.

CTGDJM007E Could not notify the Storage Component at *notification server*. Exception occurred: *exception*

Explanation

Could not connect to Storage Component. The port is not open.

Action

Verify that the storage notification server in the storageNotification parameter are formatted correctly and have valid port numbers.

CTGDJM008W JMS Password Store Connector will start in 'offline' mode: - messages already transferred to the local MQe QueueManager will be retrieved; - if in the meantime the JMS Storage Component is started, any new messages will be transferred and delivered by the Connector.

Explanation

See message.

Action

No action is required.

CTGDJM009I The Storage Component at *notification server* is successfully notified for the Connector startup.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM010E Error closing the notification connection to the Storage Component: *exception*

Explanation

An I/O error occurs when closing the socket.

Action

No action is required.

CTGDJM014I The getNextEntry method received message of type: *class name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM015E Exception while closing queue connection:
exception

Explanation

If the JMS provider fails to stop message delivery and close the connection due to an internal error.

Action

No action is required.

CTGDJM016E Invalid message type. Received message type of class *class name* but expected class type was TextMessage.

Explanation

The Connector expected TextMessage, but received other message type.

Action

Check messages types on the server

CTGDJM017I 'UpdateType' field retrieved from message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM018I 'UserId' field retrieved from message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM019I 'PasswordCount' field retrieved from message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJM020E Incorrect password update message format.
Exception occurred: *exception***

Explanation

See message.

Action

Check messages format on the server.

CTGDJM021I 'Passwords' value retrieved from message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM022I Attribute 'Passwords' created with no values.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJM023E Could not parse password update message.

Exception occurred: *exception*

Explanation

See message.

Action

Check messages format on the server.

CTGDJM024E Message contains invalid update type: *type*.

Explanation

See message.

Action

No action is required.

CTGDJM025E Unable to use both PKCS7 and the encryption from releases prior to IBM Security Directory Integrator 6.1.1 at the same time.

Explanation

Invalid values for: 'usePkcs7' and 'decryptMessages' parameters. Both are set to TRUE. Only one of them can be chosen at the same time. Either PKCS7 or the encryption from releases prior to IBM Security Directory Integrator can be used but not both at the same time.

Action

See the configuration of the JMS PasswordStore Connector and set only one of these parameters to true. The setting match the ones set at the Store.

CTGDJZ501E Open IdML Function Component accepts only a IBM Security Directory Integrator Entry as input.

Explanation

At the beginning of the Function Component's execution cycle the input data passed was not a IBM Security Directory Integrator Entry.

Action

Open IdML Function Component expects only a IBM Security Directory Integrator Entry as input. Check the AL logic and try again.

CTGDJZ502E The book '*book name*' is currently in use. Release it, before attempting to use it again.

Explanation

The book with the provided book name is currently in use by another Open IdML Function Component. It will have to release it before this Component can use it.

Action

Check if there is another running AssemblyLine with IdML Components. If the problem persists either provide another book name for your IdML Components or restart the SDI server.

CTGDJZ503E Not all CDM attributes needed for registering an MSS are provided.

Explanation

The attributes required for creating an MSS as specified by the naming policy are not provided.

Action

For creating a MSS the user needs to pass either the 'cdm:MSSName' attribute or both 'cdm:Hostname', 'cdm:ManufacturerName' and 'cdm:ProductName'.

CTGDJZ504E Both a target and a source must be provided, in order to create a relationship.

Explanation

An IdML Relationship connects two IdML Configuration Items, which can perform role of either a target or a source of the Relationship. Therefore, the ids of two CIs must be mapped to these attributes of the Relationship.

Action

Pass correct CI id values for both the 'source' and 'target' attributes.

CTGDJZ505E The IBM DL Certification Tool assessed that book '*book name*' is not a valid IdML document (file name: '*file name*').

Explanation

The Open IdML FC can be configured to validate the generated IdML. If it fails the validation the user is notified with this message.

Action

Verify that the logic of the associated AssemblyLine is correct.

CTGDJZ506E A valid CDM version and MSS's Application Code and Hostname are mandatory for the MSS creation.

Explanation

The CDM version, MSS's Application Code and Hostname must be specified by the user.

Action

Provide the listed information in the FC's configuration panel, or its Output Map (for Application Code and Hostname).

CTGDJZ507E Class '*class name*' cannot be found.

Explanation

The specified class name cannot be found in the CDM meta-data, so its attributes cannot be listed.

Action

Check if the class name is entered correctly.

CTGDJZ508I Open IdML Function Component has already opened book '*book name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ509I The parameter *param name* was initialized with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ510I Open IdML Function Component will work with book: '*book name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ511I The name of the currently used book '*book name*' has been overridden to '*new name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ512I Use an IT registry for the needed meta-data: '*use it registry*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ513I Open IdML Function Component will create a *idml mode* IdML.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ514I The generated IdML will be validated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ515I The MSS''s *param name* has value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ516I The MSS''s *param name* has been overridden to value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ517I The Common Data Model version of the generated IdML will be '*cdm version*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ518I Open IdML Function Component opened book '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ519E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the Open IdML Function Component and must be provided.

Action

Provide a value for this parameter.

CTGDJU101E Unable to read the entry because the '*defaultAttribute*' '*attribute value*' value was not set in the Entry object.

Explanation

See message.

Action

Specify a valid *defaultAttribute* parameter in the FC and ensure that each Entry object that is parsed contains that attribute.

CTGDJU102E Unable to read the entry because the Entry object is of an unknown type: '*object type*'. Specify an object of type 'String', 'File', 'InputStream', or 'Reader'.

Explanation

See message.

Action

Ensure that each Entry object that is parsed is of type String, File, InputStream, or Reader.

CTGDIR101I The properties file '*file name*' does not exist and will be ignored.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR102E Unable to modify entry because no key value was provided.

Explanation

The modify entry operation in the Properties Connector failed because no key value was specified.

Action

Specify a key value in the configuration of the Properties Connector.

CTGDIR103W The properties file '*file name*' for *property store name* was not found, and will be created if anything is written to it.

Explanation

The named file was not found. The Create flag was set in the configuration for this Properties Connector, so the file will be created if needed.

Action

If the Create flag was erroneously set, the non-existing file may indicate a problem. Verify that the Properties Connector does not need the file to exist, and if necessary, uncheck the Create flag in the configuration.

CTGDIR104E The Certificate '*certificate name*' for property file *file name* was not found.

Explanation

The named Certificate was not found in the server keystore, or could not be used to create a Crypto Object. Therefore properties in this file cannot be decrypted.

Action

Verify that the named Certificate exists in the keystore.

CTGDKN001I Proxy stop requested.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN002E Encountered an unknown hostname or IP address.

Explanation

Unexpected internal error has occurred that may be due to the current network configuration settings of the Java Proxy.

Action

Check the Java Proxy configuration and try again.

CTGDKN003E Proxy stop request failed! The server is probably already stopped.

Explanation

This error might be thrown if the proxy's maximum opened connections limit is reached by the time the proxy is requested to stop.

Action

Try to stop the proxy using the 'stopProxy' console utility.

CTGDKN004I Waiting for '*number of threads*' threads to die.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN005I Interrupted while waiting for the other threads to die.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN006E Unable to start the Java Proxy because the Java property '*property name*' was not specified.

Explanation

The specified property was missing and is required.

Action

Verify that the configuration is correct. and try again.

CTGDKN007E Unable to start the Java Proxy. The path to the Java Proxy configuration file is not valid.

Explanation

The path to the Java Proxy configuration file is either missing or not existing.

Action

Verify that the configuration is correct.

CTGDKN008E Unable to start the Java Proxy. The proxy configuration file property was not specified.

Explanation

The 'proxyConfigFile' property does not contain a value

Action

Verify that the configuration is correct.

CTGDKN009E Unable to start the Java Proxy. The server socket could not be created.

Explanation

This indicates an issue in the environment. The specified port is already taken and is in use by another application.

Action

Check the message of the corresponding exception for further details. Verify that the port number is in use and specify an alternate port.

CTGDKN010I The authentication folder is: '*directory name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN011I Plug-in/Proxy authentication successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN012I Plug-in/Proxy authentication failed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN013E An unexpected Input/Output Exception occurred.

Explanation

An unexpected exception has occurred.

Action

Check the exception message for more information.

CTGDKN014I The Java Proxy is shutting down...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN015E An unexpected exception occurred.

Explanation

See the error message.

Action

Check the exception message for more information.

CTGDKN016E Unable to start the Java Proxy. The configuration property 'syncClass' is missing.

Explanation

The syncClass property is missing. The syncClass property is required and is used to specify the Password Store class.

Action

Check the configuration file and ensure the syncClass property is specified.

CTGDKN017E Unable to start the Java Proxy. The Password Store class could not be instantiated.

Explanation

The Password Store class could not be instantiated. This could happen if the specified class name is invalid.

Action

Check the message of the auxiliary exception for more details.

CTGDKN018I Invalid value for '*property name*' property, falling back to the default port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN019I Sending Proxy Stop request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN020E Could not connect to '*hostname*' : '*port number*'.

Explanation

The connection with the Java Proxy failed.

Action

Either the Proxy has already been stopped or the connection limit has been reached. Verify the Java Proxy is running.

CTGDKN021I The Java Proxy does not recognize the byte-order mark.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN022W The Proxy Stop request was rejected by the Java Proxy.**Explanation**

The proxy did not acknowledge the request.

Action

Check log file of the Java Proxy.

CTGDKN023I The Proxy stop request was sent successfully. The Proxy will react in less than *number of seconds* seconds.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN024I Usage of the StopProxy program:**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN025I stopProxy <full path to the configuration file of the Password Synchronizer>**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN026I Received operational code: '*operational code*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN027I Invalid operational code: 'operational code'. Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN028I Rejecting operation. Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN029I Invalid data received. The data might contain null characters. The operation for 'operation name' will be rejected.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN030E Invalid protocol data. Expected 0x00, received: *byte*.

Explanation

The client plug-in is using a protocol which is not recognized by the Java Proxy.

Action

Make sure that the versions of both the client plug-in and the Java Proxy are the same.

CTGDKN031I Reading BOM. Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN032I Encoding not found. Using default encoding ('character set').

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN033I Found encoding 'character set'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN034I Sending positive response to the client plug-in.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN035I Insufficient input data.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN037E A password file was not created successfully.

Explanation

The proxy sent a notification that it failed to create a password file. The authentication process could not continue.

Action

Ensure the authentication folder has the right file system permissions.

**CTGDKN040I Both password files were successfully read.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN041I Sending proxy password.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN044E The authentication process failed. The proxy did not respond as expected.
Explanation**

An unknown error occurred on the proxy side during the authentication process.

Action

Ensure the proxy is operating normally. Inspect the proxy log for errors.

**CTGDKN045I The password sent by the proxy is valid.
Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKN046E Authentication failed. The password sent by the proxy is not the same as the one that the client generated at the beginning of the authentication process.
Explanation**

See the error message.

Action

Verify the proxy is operating normally. Inspect the proxy log for errors.

CTGDKN047E The authentication failed: *exception*
Explanation

See the error message.

Action

Inspect the error logs.

CTGDKN049E The password file '*file name*' is missing.
Explanation

The client could not find a password file.

Action

Verify that the proxy is operating normally. Inspect the proxy error log.

CTGDKN050E The password file '*file name*' is of unexpected format.
Explanation**Explanation**

The client does not recognize the format of the password file.

Action

Verify that the proxy is operating normally. Inspect the proxy error log.

CTGDKN051E Authentication failed because a password file could not be created: *exception*
Explanation**Explanation**

See the error message for details.

Action

Make sure the authentication folder has the right file system permissions.

CTGDKN052W Could not delete proxy password file '*file name*'.
Explanation**Explanation**

The proxy password file should be deleted after the client reads the proxy password.

Action

Ensure the authentication folder has the right file system permissions. Verify the specified password file is not left in the authentication folder after the authentication process completes.

CTGDKN053I Proxy password file deleted successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN054E The client did not respond as expected.

Explanation

This is an error in the authentication process. An error might have occurred on the client side.

Action

Inspect the proxy log for errors.

CTGDKN055E The password received from the client does not match the password generated by the proxy in the beginning of the authentication process.

Explanation

See error message.

Action

Inspect the proxy log for errors.

CTGDKN056I Received correct password from client.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN057I Sending password to client.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN059W Could not delete client password file '*file name*'.

Explanation

The client password file should be deleted after the proxy reads the client password.

Action

Ensure the authentication folder has the right file system permissions. Verify the specified password file is not left in the authentication folder after the authentication process completes.

CTGDKN060I Client password file deleted successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN061E The client did not respond as expected.

Explanation

This is an error in the authentication process. An error might have occurred on the client side.

Action

Inspect the proxy log for errors.

CTGDKN062E The client rejected the password sent by the proxy.

Explanation

This is an error in the authentication process.

Action

Inspect the log for errors.

CTGDKN063I The client accepted the password sent by the proxy.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN064E The authentication failed. An exception occurred: *exception*

Explanation

See the error message.

Action

Inspect the error logs.

CTGDKN067E The client password file '*file name*' is missing.

Explanation

The proxy could not find the client password file.

Action

Verify that the client is operating normally. Inspect the client error log.

CTGDKN068E The authentication failed. The proxy does not recognize the format of the client password file.

Explanation

See the error message.

Action

Verify that the client is operating normally. Inspect the client error log.

CTGDKN069E Cannot install IBMJCE provider. An exception occurred: *exception*

Explanation

This is an internal error. The installation may be corrupted.

Action

Verify that the installation is not corrupted.

CTGDKN070E Could not obtain cipher '*cipher name*' implementation from provider '*provider name*': exception

Explanation

This is an internal error. Probably the installation is corrupted.

Action

Verify that the installation is not corrupted.

CTGDKN071E Key store file '*file name*' does not exist.

Explanation

The specified key store file could not be found.

Action

Verify that the key store file exists.

CTGDKN072E Failed to open key store file '*file name*': exception

Explanation

See the error message.

Action

Verify that the key store password is correct, the key store file is accessible and is not corrupted.

CTGDKN073E Could not find certificate with alias '*certificate alias*' in key store file '*file name*'.

Explanation

A certificate with the specified alias does not exist in the key store.

Action

Verify that the certificate exists.

CTGDKN074E Failed to retrieve certificate with alias '*certificate alias*' from key store file '*file name*': exception

Explanation

See the error message. The key store password is not correct or the key store is corrupt.

Action

Verify that the certificate exists and the key store password is correct.

CTGDKN075E Failed to retrieve private key with alias 'private key alias' from key store file 'file name': exception

Explanation

See the error message. The key store password is not correct, the key password is not correct or the key store is corrupt.

Action

Verify that the private key exists, the key store password is correct and the private key password is correct.

CTGDKN076E Failed to retrieve public key with alias 'alias name' from key store file 'file name': exception

Explanation

See the error message. The key store password is not correct or the key store is corrupt.

Action

Verify that the public key exists and the key store password is correct.

CTGDKN077E An exception occurred during the encryption operation: exception

Explanation

See the error message.

Action

Verify that the configuration is correct.

CTGDKN078E An exception occurred during the decryption operation: exception

Explanation

See the error message.

Action

Verify that the configuration is correct.

CTGDKN079I Usage: java com.ibm.di.plugin.idipwsync.EncodePW <password>

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKN080E An unexpected error occurred.

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDKN081E Incorrect class specified in the syncClass property.

Explanation

The specified class does not implement the proper interface.

Action

Check the value of the syncClass property in the pwsync.props file.

CTGDKN082I Invalid value for '*property name*' property, falling back to the default retry attempts '*retry attempt*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK001E Missing required parameter: *parameter name*.

Explanation

A required parameter is not specified in the configuration.

Action

Specify the required parameter.

CTGDKK002E Parameter *parameter name* must be a number greater than *number*.

Explanation

The value of the parameter is not appropriate.

Action

Specify a proper value for the parameter in the configuration.

CTGDKK003E Parameter *parameter name* must be a number greater than or equal to *number*.

Explanation

The value of the parameter is not appropriate.

Action

Specify a proper value for the parameter in the configuration.

CTGDKK004E Parameter *parameter name* must be a number less than or equal to *number*.

Explanation

The value of the parameter is not appropriate.

Action

Specify a proper value for the parameter in the configuration.

CTGDKK005E Parameter *parameter name* must be a number.

Explanation

The provided value for the parameter is not a number.

Action

Specify a number value for the parameter.

CTGDKK006E Cannot create connection to Agent Controller.

Explanation

Cannot create connection to the remote host on which the Agent Controller runs.

Action

Verify that the host of the Agent Controller is accessible.

CTGDKK007I Waiting *number of milliseconds* milliseconds for monitoring client...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK008I Monitoring client has arrived.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK009E No monitoring client has arrived.**Explanation**

No monitoring client has arrived within the predefined time window.

Action

Make sure a client starts to monitor the Logging Agent, registered by the Connector, before the configured timeout expires.

CTGDKK010I Waiting for monitoring client...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK011I Monitoring client has arrived.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK012I Started monitoring remote agent.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK013I Remote Logging Agent is dead.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK014I Data from dead agent depleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK015I Logging Agent Life Monitoring thread interrupted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK016I Connection to remote AgentController disrupted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK017E Error while processing incoming data from the Logging Agent: *exception*

Explanation

Could not read a Common Base Event out of the incoming data buffer.

Action

Analyze the exception for more information. Check if the remote Logging Agent is functioning properly.

CTGDKK018E Error while processing incoming data from the Logging Agent: *exception*

Explanation

Could not read a Common Base Event out of the incoming character data.

Action

Analyze the exception for more information. Check if the remote Logging Agent is functioning properly.

CTGDKK019W Received invalid data from the remote Logging Agent.

Explanation

The incoming data does not conform to the expected format.

Action

Check if the remote Agent Controller is functioning properly and is compatible with the RAC Connector.

CTGDKK020I Data Processor waiting for data...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKK021E Cannot parse the ConnectionTimeout parameter.

Explanation

An illegal value for the ConnectionTimeout parameter has been passed.

Action

The ConnectionTimeout value must be a positive number.

CTGDJG001I Connector will restart with restored change token: '*change token*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJG002I Removing processed rows before '*change token*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJG003I Removed *number of rows* processed rows.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJG004I Connector will wait for '*seconds*' seconds. First wait was at '*number of seconds*' seconds and last wait was at '*number of seconds*' seconds.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJG005I RDBMS Changelog Connector restarting with changeToken *change token*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJG006I RDBMS Changelog Connector restarting at point *restart point*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJG007E The 'Start at' parameter is set to an invalid value '*parameter value*'.\n The parameter must be greater than 0 and less than *Integer*.

Explanation

The specified value for the "Start at" parameter is not valid. It should point to a valid numeric value for a record position to start the iteration at.

Action

Check the value of the parameter and try again.

CTGDJG008E The 'Start at' parameter is set to an invalid value '*parameter value*'.\n The parameter must be greater than 0 and less than *Integer*.

Explanation

The specified value for the "Start at" parameter is not valid. It should point to a valid numeric value for a record position to start the iteration at.

Action

Check the value of the parameter and try again.

CTGDJG009E The 'Start at' parameter is set to an invalid value '*parameter value*'.\n The parameter must be greater than 0 and less than *Integer*.

Explanation

The specified value for the "Start at" parameter is not valid. It should point to a valid numeric value for a record position to start the iteration at.

Action

Check the value of the parameter and try again.

CTGDJC001E The Function Component could not establish a connection to the host.

Explanation

A connection to the target machine is not possible because the hostname specified is not a valid hostname, or because of problems with the network.

Action

Verify that the specified hostname is valid and that the network connection to the target is active and then retry the connection.

CTGDJJC002E The remote pathname specified could not be found.

Explanation

The specified remote file or directory does not exist or cannot be accessed.

Action

Verify that the path you specified exists and that it is accessible by remote operations with the proper ACLs.

CTGDJJC003E An error occurred when reading from the local file

Explanation

The Function Component could not successfully read the specified file from the local filesystem.

Action

Verify that the local file specified exists and is readable.

CTGDJJC004E Pathname cannot be removed.

Explanation

The Function Component could not remove the specified file or directory.

Action

Use the recursive flag on rmdir() to recursively remove directories, or use the force flag for files.

CTGDJJC005E An error occurred when accessing the remote filesystem.

Explanation

The Function Component encountered an error when accessing the remote filesystem.

Action

Ensure that that the remote machine is available and can be remotely accessed.

CTGDJJC006E A unique service name cannot be found on the target machine.

Explanation

An attempt was made to execute a command on a target machine, but a uniquely-named Windows service could not be created on the remote machine.

Action

All current service names are in use. Stop any unneeded services named trisvc# on the target machine.

CTGDJJC007E The native Windows service binary cannot be read.

Explanation

The Function Component cannot find the native Windows binary, TRIsvc.exe, anywhere in the classpath.

Action

The trisvc.exe binary file, which is normally located in RemoteAccess.jar file packaged with the Function Component, cannot be located. Verify that the TRIsvc.exe file is in the JAR file.

CTGDJJC008E RSH could not bind to any local privileged port.

Explanation

An rsh operation was attempted but failed because rsh could not bind to a privileged port.

Action

Ensure that the local machine has administrative privileges to open restricted ports.

CTGDJJC009E Could not find the remote user RemoteUser.

Explanation

The specified remote username could not be found.

Action

Verify that the specified username exists on the target machine.

CTGDJJC010E The specified username is not authorized to run shutdown.

Explanation

This exception is thrown when shutdown is attempted from a non-privileged account.

Action

To execute a command that shuts down the target machine, the username you have supplied must have the appropriate privileges.

CTGDJJC011E An error occurred when executing the remote command.

Explanation

The remote command returned a non 0 return code, indicating a failure. This could be a permissions, syntax or path problem.

Action

Verify the remote command is in the current path, the user has permissions to execute the command, and that the command syntax is correct.

CTGDJJC012E Unable to execute the command remotely since the Remote Command Line Function Component has not been initialized.

Explanation

An attempt to invoke the Function Component's perform() has occurred before the Function Component has been initialized. Therefore, the Function Component is not able to execute the remote command.

Action

Call the initialize method of the Function Component before attempting to call the perform method.

CTGDJJC013E The Function Component can no longer be used as it has been terminated.

Explanation

The Function Component has been terminated. It cannot be used further once the terminate method has been called.

Action

Call the initialize method of the Function Component to prepare it for use. Do not call the terminate method until use of the Function Component is no longer required.

CTGDJJC014E No command has been specified to execute. Provide a command on the IBM Security Directory Integrator GUI or as an attribute called 'command.line' in the provided Entry object.

Explanation

The Function Component must be configured with a command that is to be executed remotely. The command should be provided on the IBM Security Directory Integrator GUI or as an entry attribute called 'command.line'.

Action

Specify a command on the IBM Security Directory Integrator GUI or as an attribute called 'command.line' in the provided Entry object.

CTGDJJC015E Not all parameters have been provided. Ensure you have provided a hostname and username. For an REXEC or Windows connection you will also need to provide a password. For an SSH connection you have the option of providing a password OR a keystore (with associated passphrase if applicable).

Explanation

Not all required properties have been configured for the Function Component.

Action

Ensure you have provided a hostname and username. For an REXEC or Windows connection you will also need to provide a password. For an SSH connection you have the option of providing a password OR a keystore (with associated passphrase if applicable).

CTGDJJC016E The target machine's remote service could not be started.

Explanation

The Function Component could not start the native Windows service binary file (trissvc.exe) on the remote machine.

Action

Ensure that the trissvc.exe binary file has been copied to the target machine.

CTGDJJC017E The following internal RXA error message was generated: {0}

Explanation

An error message was generated by the RXA toolkit when attempting to perform the requested operation.

Action

Respond appropriately to the generated RXA message.

CTGDJJC018E An Entry object is expected.

Explanation

The object supplied to the perform method of the Remote Command Line Function Component should be of type Entry.

Action

Ensure that the object provided to the perform method is a IBM Security Directory Integrator Entry object.

CTGDJJC019E An error occurred when reading the remote file.

Explanation

The Function Component could not successfully read the specified file from the target filesystem.

Action

Verify that the file named on the target exists and is readable.

CTGDJJC020E The execution of the requested command has timed out.

Explanation

The timeout duration that you have configured expired before the remote command could be completed.

Action

Re-attempt the operation. If you do not want the remote command to have a time limit then set the timeout configuration field to 0, which will give the operation unlimited time to complete.

CTGDJJC021E The specified standard input file does not exist.

Explanation

The path to the standard input file that has been configured for the Remote Command Line Function Component is not correct.

Action

Check the path to the standard input file on the local machine.

CTGDJJC022E An invalid connection type has been specified. The valid values for the 'connectionType' parameter are: 'ANY', 'RSH', 'SSH', 'REXEC' and 'WIN'.

Explanation

The value for the 'connectionType' parameter should be one of the following: "ANY", "RSH", "SSH", "REXEC", "WIN".

Action

Verify that the 'connectionType' parameter has been set to an appropriate value. The valid values for this parameter are: "ANY", "RSH", "SSH", "REXEC", "WIN".

CTGDJJC023E Could not establish a connection to the target machine with the authorization credentials that were provided.

Explanation

See message.

Action

Verify that the login name and password are valid for the target machine. Retry the connection.

CTGDJJC024I An attribute called 'command.line' has been provided in the Input Entry. The value entered for 'command' provided on the configuration screen, '*value*', will be disregarded.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC025I Using the remote configuration option '*option*' = '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC026I About to remotely execute the command: '*command*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC027I The command has been executed remotely.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC028I No connection exists.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC029I Starting Initalization of Function Component, 'class name'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC030I Finished initalization of Function Component, 'class name'. Initialized with value of: 'boolean'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC031I Initalizing the Function Component parameters.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC032I Initalizing the Function Component option 'name' = 'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC033I Finding a suitable protocol to create a connection.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC034I Protocol chosen '*protocol name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC035I A connection could not be established using the provided parameters. Check the values and try again.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC036I Initializing Function Component parameters done.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC037E A connection to the remote machine does not exist so the specified command cannot be executed.

Explanation

See message.

Action

Verify the provided configuration parameters and initialize the Function Component again before re-attempting to perform the remote execution.

CTGDJJC038I Creating a connection using the '*protocol name*' protocol to host '*host name*' for user '*user name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC039I Beginning the '*session name*' session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC040I Session started successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC041I A suitable protocol could not be found. No connection has been made.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC042I Creating a connection using the RSH protocol with the provided username on the specified host.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC043I Creating a connection using the SSH protocol with the provided username, keystore and passphrase on the specified host.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC044I The file '*file name*' could not be found.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC045I You have selected to use 'any' protocol, but no password has been provided. Therefore, only SSH or RSH connections will be attempted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC046I You have selected to use 'any' protocol, but no password or SSH keystore details have been provided. Therefore, only an RSH connection will be attempted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC047I The standard input destination directory on the target machine has been set to '*directory name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC048I The specified standard input will be used.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC049I Standard input has been appended to the specified command. The complete command that will be executed on the remote machine is: '*command*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC050I The standard input file '*file name*' has been successfully transferred to the destination directory '*directory name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC051I Removing the temporary directory: '*directory name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC052I The value provided for the input Entry attribute, '*attribute value*', is not of the correct type. Therefore, this entry attribute will be disregarded. The value provided should be of type java.lang.String.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC053I A port number has been provided when attempting to create a Windows connection. It is not possible to specify a port number for this type of connection. Therefore, the supplied port will be disregarded.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC054I Internal RXA Debug Message from RXA method *method name*: '*message*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC055I Internal RXA Info Message from RXA method
method name: 'message'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC056I Internal RXA Warning Message from RXA method
method name: 'message'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC057E Internal RXA Error Message from RXA method
method name: 'message'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJJC058I Creating the directory: '*directory name*' on the target computer.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH301E AL Overview Report v.1.5

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH302E Expand A11

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH303E Hide A11

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH304E Resources

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH305E Script

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH306E Configuration

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH307E Output Attribute Map

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH308E Input Attribute Map

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH309E Link Criteria

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH310E Reconnect Settings

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH311E Delta Settings

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH312E Parser

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH313E Hooks

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH314E Entry Feed Container

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH315E Data Flow Container

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH316E Proxy Settings

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH317E Settings

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH318E Enabled

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH319E Mode

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH320E Type

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH321E Match Any
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH322E Operations
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKH001E Exception occurred while trying to read property file: *exception*.

Explanation

Review the exception message for more information. This is an internal error.

Action

Contact IBM support.

CTGDJZ601E Rolling IdML Function Component accepts only a IBM Security Directory Integrator Entry as input.
Explanation

At the beginning of the Function Component's execution cycle the input data passed was not a IBM Security Directory Integrator Entry.

Action

Rolling IdML Function Component expects only a IBM Security Directory Integrator Entry as input. Check the AL logic and try again.

CTGDJZ602E Rolling IdML Function Component can be used only for IdML books stored as files (in-memory books are not allowed).

Explanation

This Function Component is used to roll the generated IdML file when a certain condition is met. Therefore, it is not applicable for in-memory IdML books.

Action

Either remove (disable) the Rolling IdML Function Component causing the problem, or change the type of the used IdML book to one stored as file (from the Open IdML Function Component).

CTGDJZ603I The book '*book name*' does not exist or is already closed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ604I The parameter *param name* was initialized with the value: '*value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ605I Rolling IdML Function Component will work with book: '*book name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ606I The name of the currently used book '*book name*' has been overridden to '*new name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ607E Parameter '*param name*' is not provided.

Explanation

The specified parameter is needed by the Rolling IdML Function Component and must be provided.

Action

Provide a value for this parameter.

CTGDIK101E The SAP ABAP AS BOR Connector has failed to create an instance of the IBM Security Directory Integrator Function Component named '*Function Component name*'. This failure may have been caused by incorrect installation of the Function Component or incorrect Function Component name.

Explanation

The SAP ABAP AS BOR Connector internally creates and uses an instance of the named Function Component to enable communication to the SAP ABAP AS system. The Connector was unable to create an instance of this Function Component.

Action

To correct this problem, ensure that the named Function Component has been correctly installed. Ensure the jar file containing the Function Component implementation is located in the jars/functions. Check that the SAP Java Connector has been correctly deployed.

CTGDIK102E An error has been detected while initializing the Function Component named '*Function Component name*'.

Explanation

The SAP ABAP AS BOR Connector internally creates and uses an instance of the named Function Component to enable communication to the SAP ABAP AS system. Before using the function component, the Connector needs to call the initialize method of the Function Component. The Connector initializes the Function Component with the configuration parameter information defined for the Connector.

Action

Ensure that the configuration information defined for the Connector is correct. Check that the SAP Java Connector has been correctly deployed.

CTGDIK103E An XSL transformation has failed. Ensure that a valid XML value has been supplied for the 'sapXml' attribute. The source XSL file name is '*file name*'.

Explanation

The XSL transformation defined in the named file has returned an empty XML result document.

Action

If the transform has been applied to an XML request document, check that the XML request value is correct.

CTGDIK105E The XSL files for the Connector's putEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.

Explanation

The putEntry method is called by the AssemblyLine when a Connector has been deployed in AddOnly mode. The SAP User Connector requires XSL stylesheets to process RFC requests and responses executed against the target SAP system. In this case, the Connector was unable to read the required XSL stylesheets that it uses when deployed in AddOnly mode.

Action

Ensure the XSL stylesheet files associated with Add Mode StyleSheets configuration parameter are correct. Try specifying the fully qualified path name of the XSL stylesheets. Ensure the XSL stylesheets have read permissions set.

CTGDIK106E The XSL files for the Connectors' modEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.

Explanation

The modEntry method is called by the AssemblyLine when a Connector has been deployed in Update mode. The SAP User Connector requires XSL stylesheets to process RFC requests and responses executed against the target SAP system. In this case, the Connector was unable to read the required XSL stylesheets that it uses when deployed in Update mode.

Action

Ensure the XSL stylesheet files associated with Update Mode StyleSheets configuration parameter are correct. Try specifying the fully qualified path name of the XSL stylesheets. Ensure the XSL stylesheets have read permissions set.

CTGDIK107E The XSL files for the Connectors' deleteEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.

Explanation

The deleteEntry method is called by the AssemblyLine when a Connector has been deployed in Delete mode. The SAP User Connector requires XSL stylesheets to process RFC requests and responses executed against the target SAP system. In this case, the Connector was unable to read the required XSL stylesheets that it uses when deployed in Delete mode.

Action

Ensure the XSL stylesheet files associated with Delete Mode StyleSheets configuration parameter are correct. Try specifying the fully qualified path name of the XSL stylesheets. Ensure the XSL stylesheets have read permissions set.

CTGDIK108E The configured XSL file named '*file name*' does not exist.

Explanation

The Connector has attempted to read the named XSL stylesheet file. This file does not exist in the specified location on the file system.

Action

Ensure the XSL stylesheet file name is correct and exists. XSL stylesheet file names are specified using Connector parameters and differ based on the Connector mode.

CTGDIK109E The configured XSL file named '*file name*' is not a valid file. A possible cause of this error might be that the configured name is actually a directory.

Explanation

The Connector has attempted to read the named XSL stylesheet file. This file does not exist in the specified location on the file system or is not a valid file.

Action

Ensure the XSL stylesheet file name is correct and exists. XSL stylesheet file names are specified using Connector parameters and differ based on the Connector mode.

CTGDIK110E The configured XSL file named '*file name*' is not readable.

Explanation

The Connector has attempted to read the named XSL stylesheet file. This file is not readable.

Action

Ensure the file has read permissions set.

CTGDIK111E The configuration parameter named '*parameter name*' is missing

Explanation

The named Connector configuration parameter is missing.

Action

The configured Connector mode requires additional configuration of this parameter. Ensure these values have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode. See the the IBM Security Directory Integrator Users Guide for specific details.

CTGDIK112E The Attribute named '*file name*' is not present, or does not have a value in the Entry supplied. This attribute must be present in the Connector entry.

Explanation

The named Connector configuration parameter is missing.

Action

Supply a value for the Connector configuration parameter. Refer to the IBM Security Directory Integrator Users Guide for details.

CTGDIK113W No search criteria have been defined for the Connectors' findEntry method. This method will return null to indicate no objects found.

Explanation

Link criteria are typically needed for Connectors in Update, Delete, and Lookup mode. The Link Criteria is used to obtain the current details of a given object instance in the target system.

Action

If the Connector is not behaving as expected, try specifying the Link Criteria. See the IBM Security Directory Integrator Users Guide for details.

CTGDIK114W An XSL transform was performed before calling an SAP RFC. The result of the XSL transform was an empty document. An empty transform result typically occurs when mandatory XPath or Parameters are missing. The RFC call will not be performed.

Explanation

See message.

Action

If the Connector is not behaving as expected, ensure the Connector entry contains the necessary attributes with associated XML values.

CTGDIK115W The XSL transform defined in file '*file name*' resulted in an empty XML document. An empty transform result typically occurs when mandatory XPath or Parameters are missing. The RFC call was not performed.

Explanation

See message.

Action

If the Connector is not behaving as expected, ensure the Connector entry contains the necessary attributes with associated XML values.

CTGDIK116W Some application level errors and warnings have been detected while creating the ABAP AS user. The operation may be incomplete.

Explanation

The Connector has received a response from the SAP system which indicates that some request data or application state might be incorrect. This status is typically indicated in the RFC parameter named RETURN.

Action

Ensure the target SAP system and target application are functioning correctly. Ensure the request data values mapped onto the Connector are valid with respect to SAP business logic.

CTGDIK117W Some application level errors and warnings have been detected while deleting the ABAP AS user. The operation may be incomplete.

Explanation

The Connector has received a response from the SAP system which indicates that some request data or application state might be incorrect. This status is typically indicated in the RFC parameter named RETURN.

Action

Ensure the target SAP system and target application are functioning correctly. Ensure the request data values mapped onto the Connector are valid with respect to SAP business logic.

CTGDIK118W Some application level errors and warnings have been detected while updating the ABAP AS user. The operation may be incomplete.

Explanation

The Connector has received a response from the SAP system which indicates that some request data or application state might be incorrect. This status is typically indicated in the RFC parameter named RETURN.

Action

Ensure the target SAP system and target application are functioning correctly. Ensure the request data values mapped onto the Connector are valid with respect to SAP business logic.

CTGDIK119E The Connector detected an exception during initialization. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK120E The Connector detected an exception while performing a schema query. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK121E The Connector detected an exception while adding an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK122E The Connector detected an exception while deleting an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK123E The Connector detected an exception while modifying an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK124E The Connector detected an exception while attempting to find an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK125E The Connector detected an exception while selecting entries in preparation for iterator mode processing. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK126E The Connector detected an exception while iterating through the known entries. The number of entries successfully processed before the exception was *number of entries*. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK127E No XSL style sheet files have been configured for the Connector running in '*Connector mode*' mode. This mode requires XSL style sheets to be defined. See the IBM Security Directory Integrator Users Guide for specific details.

Explanation

See message.

Action

Correct the Connector configuration parameters related to XSL stylesheet specifications.

CTGDIK128E Delete mode requires the attribute named '*sapXml*' to present if no Link Criteria have been defined.

Explanation

When deleting an object instance from the target system, the Connector performs a lookup of the object attributes. Link Criteria are needed to find the given object instance.

Action

Specify the Link Criteria for the Connector.

CTGDIK129I Adding message to error list: '*message*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK130I Adding message to warning list: '*message*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK131I Extracting the return data from element named '*tag name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIK132I Creating AbapErrorInfo object:
message='message', error number='error number', error
flag='error flag'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIK133I The XML element to return is a table style
element: 'boolean'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK134I The result of pre RFC XSL call is: 'string'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK135I The result of RFC call is: 'string'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK136I Executing function for XSL file:: 'file'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK137I The findEntry method is returning the initialized entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK138I The findEntry method is returning null.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK301I Started JCo IDoc Server and listening for requests.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK302E Unable to initialize the Connector. Exception occurred: *exception*

Explanation

See message.

Action

See the exception message for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK303E The '*parameter name*' parameter must be set to use the SAP IDocs Connector.

Explanation

A value is required for this RFC Connection parameter for either the RFC Server or RFC Client connection.

Action

Specify the required parameter in the Connector.

CTGDIK304I Optional RFC Connection parameter '*parameter name*' set with the value '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK305I Connector configuration parameter '*parameter name*' set with the value '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK306I Checking if TID Manager for TID '*TID*' is available for processing.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK307E No TID Manager found for TID '*TID*'.

Explanation

The Connector IDoc Inbound queue has a key of the given transaction identifier but has not had a TID Manager object created.

Action

An internal error occurred. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK308I TID Manager for TID ''TID'' is available for processing.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK309W Provided poll time value is 0 or less. Single request will be processed only.

Explanation

The Connector will operate in standard Iterator mode. Only one IDoc request will be processed by the Connector. After all the IDocs have been place in the AssemblyLine as IBM Security Directory Integrator entries, the Connector will return null to exit Iterator mode.

Action

Check that this was an intentional action. If not the poll time must be greater then zero.

CTGDIK310I Polling for next the IDoc request in getNextEntry method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK311E Exception generated while polling.

Explanation

Unexpected error has occurred in Thread.sleep(pollTime).

Action

Restart the AssemblyLine of the Connector.

CTGDIK312E Null Entry found in the Entry list of the TID Manager for TID ''TID''.

Explanation

Unexpected error has occurred. Null entries should not be possible in a TID Manager.

Action

An internal error occurred. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK313W No TID provided with this RFM call. Manually removing the TID Manager to complete the TID Management cycle.

Explanation

An RFM request has been processed by the Connector, where no transaction identifier was provided.

Action

No response required. RFM Entry will be place on AL the same as is done for IDoc entries.

CTGDIK314I No Parser Attached to the Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK315I Finished processing TID Manager for TID ''TID'' . TID ready for confirmation.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK316E The getNextEntry method returned null in Iterator mode with a valid poll time.

Explanation

The modified Iterator mode to act as a Server has failed. Exception has been thrown to prevent standard Iterator mode taking place.

Action

An internal error occurred. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK317W Entry contains no XML attributes to parse.**Explanation**

An XML Parser has been attached but there are no XML valued attributes available.

Action

An internal error occurred. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK318I Attempting to parse XML content with attached Parser.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK319W The attached Parser returned a null Entry.**Explanation**

A Parser has been attached but no entry with parsed attributes was produced.

Action

Check that an XML Parser was used, and that the parser was configured correctly.

CTGDIK320E Unable to parse the XML. Exception occurred:
*exception***Explanation**

See message.

Action

See the exception message for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

**CTGDIK321W Exception occurred while generating schema:
*exception***

Explanation

See message.

Action

See the exception message for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK322E Unable to start the JCo IDoc Server.

Explanation

The Connector was not able to start the internal JCo IDoc Server.

Action

The problem may be caused by invalid Config parameters. Verify the Config parameters of the Connector are set properly. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

**CTGDIK323I Polling for next IDoc request in getNextClient
method.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIK324I The onCheckTID method was called for TID
'TID'. . TID Management already in progress for this TID.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIK325I The onCheckTID method was called for TID
'TID'. TID Management beginning now for this TID. Next
handleRequest method call will begin the inbound processing.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK326I TID Manager for TID ''TID'' is not yet confirmed. Current status is ''status''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK327I TID Manager for TID ''TID'' is now confirmed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK328I The handleRequest method was invoked. Current TID value is ''TID'' . Incoming IDoc list request contains ''number of IDocs'' IDocs.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK329E Unable to convert IDoc request into a IBM Security Directory Integrator entry. The writeIDocToTDIEntry method returned null IDoc Entry.

Explanation

The functionality in the Connector that converts a JCoIDoc.Document object to a IBM Security Directory Integrator Entry object has failed.

Action

The problem may be an issue with the JCo middleware. Verify the JCo middleware is installed properly with all dependent libraries. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK330E No value provided for current transaction identifier. This list of IDocs will not be processed.

Explanation

The Connector received a handleRequest method callback without a prior onCheckTID method call.

Action

The problem may be an issue with the JCo middleware. Verify the JCo middleware is installed properly with all dependent libraries. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK331E Current TID ''TID'' already has a TID Manager and is being processed. Ignoring this request.

Explanation

The Connector received a second handleRequest method callback for a particular transaction identifier.

Action

The problem may be an issue with the JCo middleware. Verify the JCo middleware is installed properly with all dependent libraries. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK332E No IDoc Entries available. Ignoring request for TID ''TID''.

Explanation

The Connector received a handleRequest method callback for a particular transaction identifier but no IDocs were contained in that request.

Action

The problem may be an issue with the JCo middleware. Verify the JCo middleware is installed properly with all dependent libraries. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK333I Created TID Manager for TID ''TID'' with ''number of IDoc entries'' IDoc entries for processing.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK334E Unable to convert IDoc request into a IBM Security Directory Integrator entry. The Connector received a null JCoIDoc.Document object.

Explanation

The Connector encountered a null IDoc object.

Action

The problem may be an issue with the JCo middleware. Verify the JCo middleware is installed properly with all dependent libraries. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK335I The handleRequest method was invoked. Current TID value is '*TID value*'. Incoming RFM request is '*RFM name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK336W No TID received with this RFM request. Defaulting for TID Management processing.

Explanation

The Connector has received a request that contains a SAP client Remote Function Call. No transaction identifier has been provided with the request so the Connector will use a dummy value for the purposes of TID Management.

Action

No response required.

CTGDIK337I RFM as XML: ['*TID*'].

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK338E Unable to convert RFM request into a IBM Security Directory Integrator entry. No RFMs provided in request.

Explanation

The Connector has received a request that should contain a SAP client Remote Function Call, but the Connector was not able to produce a IBM Security Directory Integrator Entry for the RFM.

Action

The problem may be an issue with the JCo middleware. Verify the JCo middleware is installed properly with all dependent libraries. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK339E Unable to convert RFM request into a IBM Security Directory Integrator entry. The JCO.Function object received was null.

Explanation

The Connector has received a request that contained a null JCO.Function object. This should not happen a may indicate a problem in the JCo middleware or the Connector configuration.

Action

The problem may be an issue with the JCo middleware. Verify the JCo middleware is installed properly with all dependent libraries. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK340I Storing RFM request as XML file '*file name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK341E Failed to read RFM request XML file '*file name*' into IBM Security Directory Integrator Entry. No contents found in file.

Explanation

The Connector stores RFM as a file that contains their XML form as part of RFM processing. This message indicates that no XML content was available from the file.

Action

An internal error occurred. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK342E Failed to process RFM XML file. Exception occurred: *exception*

Explanation

The Connector stores RFM as a file that contains their XML form as part of RFM processing. This message indicates an exception occurred while handling the file.

Action

See the exception message for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK343E An exception occurred. Exception trapped from JCo Server with Program ID of '*Program ID*': *exception*

Explanation

The Connector uses an exception listener to trap internal JCo exceptions. The exception message indicates the type of exception trapped.

Action

See the exception message from the JCo Server in the message for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK344E An error was encountered. An error message was trapped from JCo Server with Program ID of '*Program ID*': *error message*.

Explanation

The Connector uses an error message listener to trap internal JCo error messages when an error is encountered.

Action

See the error message from the JCo Server in the message for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK345I State Change occurred for JCo Server with Program ID of '*Program ID*'. Previous State: '*old state*'. New State: '*new state*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK346I Trace message trapped from JCo Server. Trace Level: ''trace level'' Trace Message: ''trace message''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK347W File was not able to be deleted: ''file name''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK348I Import parameter: ''value''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK349I The import parameter is a structure.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK350I The import parameter is a table.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK351I The import parameter is a simple field.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK352I No Input Fields required for this RFM.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK353I RFM export Paramters:-----**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK354I The export parameter is a structure.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK355I The export parameter is a simple field.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK356I No Export Fields returned for this RFM.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK357I RFM table Paramters:-----**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK358I Rows found for table: '*table name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK359I No rows found for table: '*table name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK360I Field '*field name*' has string value '*value*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK362I Field '*field name*' has raw value '*value*'. **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK364I A bad field value passed. **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK365I Input is a Record. Record fields are as follows: **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK366I Record field: '*value*'. **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK367I Input is a table. Table records are as follows: **Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK368I Input is a structure. Structure records are as follows:

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK201E Must call the initialize method first!

Explanation

An attempt to use an uninitialized Function Component has been detected. This error may occur if the initialize method has not been successfully called before calling other Function Component methods. This may also occur if a Function Component method has been called after calling terminate.

Action

Correct the calling code so that initialize method has been successfully called before calling other Function Component methods.

CTGDIK202E Entry Attribute '*attribute name*' missing value.

Explanation

A mandatory attribute is missing or is missing a value.

Action

Correct the AssemblyLine mapping or client code so that the named attribute has a value.

CTGDIK203E Entry Attribute '*attribute name*' missing value or value does not match expected type. Expected type: '*document type*'.

Explanation

A mandatory attribute is missing or is missing a value of the correct type.

Action

Correct the AssemblyLine mapping or client code so that the named attribute has a value and its type is as expected. See Users Guide for details.

CTGDIK204E Entry attribute '*attribute name*' must be one of 'xmlDomDocument', 'xmlString', or 'multiValuedAttributes'.

Explanation

See message.

Action

Correct the AssemblyLine mapping or client code.

CTGDIK205E Entry object expected.

Explanation

The object type passed the Function Components perform method was not a IBM Security Directory Integrator Entry.

Action

Correct the client code.

CTGDIK206E Must call initialize() first.

Explanation

An attempt has been made to use an uninitialized Function Component.

Action

Correct the client code. Ensure the initialize method is called before using the Function Component. Ensure the Function Component is not use after calling its terminate method.

CTGDIK207E Function cannot be reused once terminate() has been called.

Explanation

An attempt has been made to use the Function Component after its terminate method has been called.

Action

Correct the client code. Ensure the initialize method is called before using the Function Component. Ensure the Function Component is not use after calling its terminate method.

CTGDIK208E '*class name*' != '*class name*'.

Explanation

The classname does not match the expected classname.

Action

Correct the AssemblyLine attribute mapping or client code.

CTGDIK209E Mandatory RFC parameter named '*field name*' has not been supplied.

Explanation

RFC modules in SAP often define mandatory import and table parameters. The parameters must be present when calling the RFC.

Action

For the RFC being called, use transaction SE37 in the target SAP system to determine the mandatory RFC parameters. Correct the AssemblyLine attribute mapping or client code.

CTGDIK210E Length of supplied value for field '*field name*' exceeds maximum length '*field length*'.

Explanation

The length of the value supplied for the named RFC parameters or table parameter field exceeds the maximum length defined by the RFC in the target SAP system.

Action

For the RFC being called, use transaction SE37 in the target SAP system to determine the length of the given RFC parameter or table parameter field. Correct the AssemblyLine attribute mapping or client code.

CTGDIK211E '*class name*' does not equal '*class name*'.

Explanation

The classname does not match the expected classname.

Action

Correct the AssemblyLine attribute mapping or client code.

CTGDIK212E Mandatory RFC parameter named '*field name*' has not been supplied.

Explanation

RFC modules in SAP often define mandatory import and table parameters. The parameters must be present when calling the RFC.

Action

For the RFC being called, use transaction SE37 in the target SAP system to determine the mandatory RFC parameters. Correct the AssemblyLine attribute mapping or client code.

CTGDIK213E No such function named '*function name*'.

Explanation

The entry attributes and values represent an RFC request for an RFC module that does not exist in the target SAP system, or has not been released.

Action

Ensure the RFC exists on the target SAP system. Ensure the RFC name is correctly specified in the entry.

CTGDIK214E The remove method is not implemented.

Explanation

See message.

Action

See the Users Guide.

CTGDIK215E The Function Component detected an exception while attempting to disconnect. The message is:

***'exception'*.**

Explanation

See message.

Action

Ensure the network between the Function Component and SAP is available.

CTGDIK216E Connection pool '*pool name*' already exists. The message is: '*exception*'.

Explanation

See message.

Action

Restart the AssemblyLine.

CTGDIK217E No more connections available in '*pool name*'. The message is: '*exception*'.

Explanation

See message.

Action

Restart the AssemblyLine.

CTGDIK218E Unable to establish a connection using '*pool name*'. The message is: '*exception*'.

Explanation

See message.

Action

Ensure the network is available. Ensure the target SAP system is available.

CTGDIK219E Unable to execute RFC '*function name*'. The message is: '*exception*'.

Explanation

See message.

Action

Ensure the RFC on the target SAP system is functioning correctly.

CTGDIK220E Communication error with SAP ABAP Application Server. The message is: '*exception*'.

Explanation

See message.

Action

Ensure the network is available. Ensure the target SAP system is available.

CTGDIK221W Trouble invoking '*function name*'. The function has been retried *apos;number of retries*' times.

Explanation

See message.

Action

Ensure the network is available. Ensure the target SAP system is available.

CTGDIK222E Trouble invoking '*function name*'. The function has been retried *apos;number of retries*' times. The message is: '*exception*'.

Explanation

See message.

Action

Ensure the network is available. Ensure the target SAP system is available.

CTGDIK223E Unable to create DOM parser. The message is: *'exception'*.

Explanation

See message.

Action

Ensure IBM Security Directory Integrator has been correctly installed.

CTGDIK224E Unable to parse DOM parser. The message is: *'exception'*.

Explanation

See message.

Action

Ensure IBM Security Directory Integrator has been correctly installed.

CTGDIK225E Unable to read DOM parser. The message is: *'exception'*.

Explanation

See message.

Action

Ensure Security Directory Integrator has been correctly installed.

CTGDIK226E Failed to prepare parameters for RFC. The message is: *'exception'*.

Explanation

See message.

Action

Ensure the AssemblyLine attribute mapping or client code has correctly initialized the entry for the Function Component.

CTGDIK227I Executing function for XSL file:: *'file'*. Multiple elements with name *'element name'* are present in the structure type. Using the element in first position following the preorder traversal.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK228I D0M: Connecting to SAP ABAP Application Server...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK229I D0M: Connecting to SAP ABAP Application Server...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK230I D0M: Getting the dynamic proxy.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK231I D0M: Getting the importer.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK232I D0M: Populating the request with data values.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK233I D0M: Executing RFC: ''function name''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK234I D0M: Exporting RFC results.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK235I D0M: Disconnecting...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK236I XSchema: Connecting to the SAP system.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK237I XSchema: Getting the dynamic proxy.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK238I XSchema: Creating the importer.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK239I XSchema: Populating the request with data values.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK240I XSchema: Disconnecting...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK241I XSchema: Getting the importer.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK242I Entry: Connecting to SAP system...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK243I Entry: Getting the dynamic proxy.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK244I Entry: Disconnecting...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK245I The input entry is: '*entry*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK246I Obtaining RFC request from DOM Document.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK247I Invoking RFC from DOM Document.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK248I Obtaining RFC request from XML string.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK249I Invoking RFC from XML string.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK250I Invoking RFC using MVA parameter.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIK251I Using JCo config option '*option name*':
'*option value*'.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK252I The supplied options are not supported or were incomplete. Usage: java -cp (SAP_JCO_HOME)/sapjaco.jar;(TDI_HOME)/jars/functions/SapR3RfcFC.jar -Djava.library.path=(SAP_JCO_HOME)com.ibm.di.fc.sapr3rfc.RfcXmlInvoker-f [input XML file] -o [output XML file] -p [JCO Connection properties file] -f The name of the file containing the input RFC request as XML. -o The name of the file to be produced containing RFC response as XML. -p The JCO Connection properties file.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK253I Input entry value: '*entry value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK001E The SAP ABAP Application Server User Registry Connector failed to create an instance of the Security Directory Integrator Function Component '*Function Component Name*'. This failure may have been caused by incorrect installation of the Function Component or an incorrect Function Component name.

Explanation

The SAP ABAP Application Server User Registry Connector internally creates and uses an instance of the named Function Component to enable communication to the SAP ABAP AS system. The Connector was unable to create an instance of this Function Component.

Action

To correct this problem, ensure that the named Function Component has been correctly installed. Ensure the jar file containing the Function Component implementation is located in the jars/functions. Check that the SAP Java Connector has been correctly deployed.

CTGDIK002E An error has been detected while initializing the Function Component '*Function Component name*'.

Explanation

The SAP ABAP Application Server User Registry Connector internally creates and uses an instance of the named Function Component to enable communication to the SAP ABAP AS system. Before using the Function Component, the Connector needs to call the initialize method of the Function Component. The Connector initializes the Function Component with the configuration parameter information defined for the Connector.

Action

Ensure that the configuration information defined for the Connector is correct. Check that the SAP Java Connector has been correctly deployed.

CTGDIK003E An XSL transformation has failed. Ensure that a valid XML value has been supplied for the 'sapUserXml' attribute. The source XSL file name is '*file name*'.

Explanation

The XSL transformation defined in the named file has returned an empty XML result document.

Action

If the transform has been applied to an XML request document, check that the XML request value is correct.

CTGDIK005E The XSL files for the Connectors' putEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.

Explanation

The putEntry method is called by the AssemblyLine when a Connector has been deployed in AddOnly mode. The SAP User Connector requires XSL stylesheets to process RFC requests responses executed against the target SAP system. In this case, the Connector was unable to read the required XSL stylesheets that it uses when deployed in AddOnly mode.

Action

Ensure the XSL stylesheet files associated with Add Mode StyleSheets configuration parameter are correct. Try specifying the fully qualified path name of the XSL stylesheets. Ensure the XSL stylesheets have read permissions set.

CTGDIK006E The XSL files for the Connectors' modEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.

Explanation

The modEntry method is called by the AssemblyLine when a Connector has been deployed in Update mode. The SAP User Connector requires XSL stylesheets to process RFC requests responses executed against the target SAP system. In this case, the Connector was unable to read the required XSL stylesheets that it uses when deployed in Update mode.

Action

Ensure the XSL stylesheet files associated with Update Mode StyleSheets configuration parameter are correct. Try specifying the fully qualified path name of the XSL stylesheets. Ensure the XSL stylesheets have read permissions set.

CTGDIK007E The XSL files for the Connectors' deleteEntry method have not been configured. Ensure these files have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode.

Explanation

The deleteEntry method is called by the AssemblyLine when a Connector has been deployed in Delete mode. The SAP User Connector requires XSL stylesheets to process RFC requests responses executed against the target SAP system. In this case, the Connector was unable to read the required XSL stylesheets that it uses when deployed in Delete mode.

Action

Ensure the XSL stylesheet files associated with Delete Mode StyleSheets configuration parameter are correct. Try specifying the fully qualified path name of the XSL stylesheets. Ensure the XSL stylesheets have read permissions set.

CTGDIK008E The configured XSL file named '*file name*' does not exist.

Explanation

The Connector has attempted to read the named XSL stylesheet file. This file does not exist in the specified location on the file system.

Action

Ensure the XSL stylesheet file name is correct and exists. XSL stylesheet file names are specified using Connector parameters and differ based on the Connector mode.

CTGDIK009E The configured XSL file named '*file name*' is not a valid file. A possible cause of this error might be that the configured name is actually a directory.

Explanation

The Connector has attempted to read the named XSL stylesheet file. This file does not exist in the specified location on the file system or is not a valid file.

Action

Ensure the XSL stylesheet file name is correct and exists. XSL stylesheet file names are specified using Connector parameters and differ based on the Connector mode.

CTGDIK010E The configured XSL file named '*file name*' is not readable.

Explanation

The Connector has attempted to read the named XSL stylesheet file. This file is not readable.

Action

Ensure the file has read permissions set.

CTGDIK011E The configuration parameter named '*file name*' is missing. The configured Connector mode requires additional configuration of this parameter. Ensure these values have been configured. If this error continues, try removing and adding the Connector to the AssemblyLine in the correct mode. See the IBM Security Directory Integrator Users Guide for specific details.

Explanation

The named Connector configuration parameter is missing.

Action

Supply a value for the Connector configuration parameter. Refer to the IBM Security Directory Integrator Users Guide for details.

CTGDIK012E The Attribute named '*attribute name*' is not present, or does not have a value, in the Entry supplied. This attribute must be present in the Connector entry.

Explanation

See message.

Action

Modify the Connector attribute mappings or client code. See the IBM Security Directory Integrator Users Guide for details regarding supported Connector attributes and values.

CTGDIK013W No search criteria have been defined for the Connectors'' findEntry method. This method will return null to indicate no objects found.

Explanation

Link criteria are typically needed for Connectors in Update, Delete, and Lookup mode. The Link Criteria is used to obtain the current details of a given object instance in the target system.

Action

If the Connector is not behaving as expected, try specifying the Link Criteria. See the IBM Security Directory Integrator Users Guide for details.

CTGDIK014W An XSL transform was performed before calling an SAP RFC. The result of the XSL transform was an empty document. An empty transform result typically occurs when mandatory XPath or Parameters are missing; for example, sapUserName. The RFC call will not be performed.

Explanation

See message.

Action

If the Connector is not behaving as expected, ensure the Connector entry contains the necessary attributes with associated XML values.

CTGDIK015W The XSL transform defined in file '*file name*' resulted in an empty XML document. An empty transform result typically occurs when mandatory XPath or Parameters are missing, e.g. sapUserName. The RFC call was not performed.

Explanation

See message.

Action

If the Connector is not behaving as expected, ensure the Connector entry contains the necessary attributes with associated XML values.

CTGDIK016W Some application level errors and warnings have been detected while creating the SAP ABAP AS user. The operation may be incomplete.

Explanation

The Connector has received a response from the SAP system which indicates that some request data or application state might be incorrect. This status is typically indicated in the RFC parameter named RETURN.

Action

Ensure the target SAP system and target application are functioning correctly.
Ensure the request data values mapped onto the Connector are valid with respect to SAP business logic.

CTGDIK017W Some application level errors and warnings have been detected while deleting the SAP ABAP AS user. The operation may be incomplete.

Explanation

The Connector has received a response from the SAP system which indicates that some request data or application state might be incorrect. This status is typically indicated in the RFC parameter named RETURN.

Action

Ensure the target SAP system and target application are functioning correctly.
Ensure the request data values mapped onto the Connector are valid with respect to SAP business logic.

CTGDIK018W Some application level errors and warnings have been detected while updating the SAP ABAP AS user. The operation may be incomplete.

Explanation

The Connector has received a response from the SAP system which indicates that some request data or application state might be incorrect. This status is typically indicated in the RFC parameter named RETURN.

Action

Ensure the target SAP system and target application are functioning correctly.
Ensure the request data values mapped onto the Connector are valid with respect to SAP business logic.

CTGDIK019E The Connector detected an exception during initialization. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK020E The Connector detected an exception while performing a schema query. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK021E The Connector detected an exception while adding an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK022E The Connector detected an exception while deleting an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK023E The Connector detected an exception while modifying an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK024E The Connector detected an exception while attempting to find an entry. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK025E The Connector detected an exception while selecting entries in preparation for iterator mode processing. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK026E The Connector detected an exception while iterating through the known entries. The number of entries successfully processed before the exception was *number of entries*. The message is: '*exception*'.

Explanation

See message.

Action

See exception stack trace. Check for earlier errors or warnings in the log.

CTGDIK027E No XSL style sheet files have been configured for the Connector running in '*Connector mode*' mode. This mode requires XSL style sheets to be defined. See the IBM Security Directory Integrator Users Guide for specific details.

Explanation

See message.

Action

Correct the Connector configuration parameters related to XSL stylesheet specifications.

CTGDIK028I The `findEntry` method is returning null.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK029I The findEntry method is returning the initialized entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK030I The findEntry method is returning null.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK031I Adding message to error list: '*message*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK032I Adding message to warning list: '*message*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK033I Extracting the return data from element named '*tag name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIK034I Creating AbapErrorInfo object:
message='message', error number='error number', error
flag='error flag'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIK035I The XML element to return is a table style
element: 'boolean'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK036I The result of pre RFC XSL call is: 'string'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK037I The result of RFC call is: 'string'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK038I Executing function for XSL file: 'file'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR001W Unable to load script libraries. The Script Connector has no associated MetamergeConfig object.

Explanation

The current configuration for this Connector is not an instance of BaseConfiguration object.

Action

No action is required.

CTGDIR002E Operation 'selectEntries' failed in Script Connector: '*error message*'.

Explanation

The method 'selectEntries' returns an exit code error.

Action

Check the method 'selectEntries' in the Script Connector.

CTGDIR003E Operation 'getNextEntry' failed in Script Connector: '*error message*'.

Explanation

The method 'getNextEntry' returns an exit code error.

Action

Check the method 'getNextEntry' in the Script Connector.

CTGDIR004E Operation 'modEntry' failed in Script Connector: '*error message*'.

Explanation

The method 'modEntry' returns an exit code error.

Action

Check the method 'modEntry' in the Script Connector.

CTGDIR005E Operation 'deleteEntry' failed in Script Connector: '*error message*'.

Explanation

The method 'deleteEntry' returns an exit code error.

Action

Check the method 'deleteEntry' in the Script Connector.

CTGDIR006E Operation 'findEntry' failed in Script Connector: '*error message*'.

Explanation

The method 'findEntry' returns an exit code error.

Action

Check the method 'findEntry' in the Script Connector.

CTGDIR007E Operation 'putEntry' failed in Script Connector: '*error message*'.

Explanation

The method 'putEntry' returns an exit code error.

Action

Check the method 'putEntry' in the Script Connector.

CTGDIR008E Operation 'queryReply' failed in Script Connector: '*error message*'.

Explanation

The method 'queryReply' returns an exit code error.

Action

Check the method 'queryReply' in the Script Connector.

CTGDIR009E Operation 'querySchema' failed in Script Connector: '*error message*'.

Explanation

The method 'querySchema' returns an exit code error.

Action

Check the method 'querySchema' in the Script Connector.

CTGDIR010I Script Connector configured to execute script:
script

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIR011I The Script Connector will keep its global state.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJT101E The Scripted FC failed because the getUI method returned an unknown GUI object type: '*object type*'.

Explanation

The function getUI returned GUI object not instance of Component.

Action

Check the function 'getUI(fc)' of the ScriptedFC.

CTGDJT001I Declaring the user functions.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJT002I Declaring my configuration.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJT003I Declaring the input and output streams.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJT004I Executing the following script: '*script*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJT005E Required Connector parameter '*script*' is not set.

Explanation

The specified Connector parameter *script* is required, but not set.

Action

Set the Connector parameter *script*.

CTGDJT006W Unable to load script libraries. The Script Connector has no associated MetamergeConfig object.

Explanation

See message.

Action

Verify script libraries can be accessed and loaded.

CTGDJT007E Script Parser encountered error while reading entry: '*error*'

Explanation

See message.

Action

Check the script. There is an error in the script, because exitcode status is not OK.

CTGDJT008E Script Parser encountered error while writing entry: '*error*'

Explanation

There is an error in the script, because exitcode status is not OK.

Action

Check the script.

CTGDJT009E Script Parser encountered error while querying schema: *'error'*

Explanation

There is an error in the script, because exitcode status is not OK.

Action

Check the script.

CTGDIF001E The perform method of the Function Component was not passed an object of type com.ibm.di.entry.Entry. This object is not a valid parameter to pass to perform method.

Explanation

A parameter of type different from com.ibm.di.entry.Entry was passes to the perform method.

Action

Verify that the parameter being manually passed to the perform method of Function Component (for example from a Script Component) is an object of type com.ibm.di.entry.Entry.

CTGDIF002E The Entry Attribute *'attribute name'* is not present in the Entry.

Explanation

The required Entry Attribute is not present in the IBM Security Directory Integrator Entry.

Action

Verfiy the specified Entry Attribute is properly mapped to the connection Entry.

CTGDIF003E The required Function Component parameter *'parameter name'* is not set.

Explanation

The specified required Function Component parameter is not set.

Action

Set the specified Function Component parameter.

CTGDIF004E The following Function Component parameter was not set or its corresponding Entry Attribute was not mapped: '*parameter name*'.

Explanation

See message.

Action

Set the specified Function Component parameter or make sure the corresponding Entry Attribute is mapped.

CTGDIF005I The parameter *parameter name* was initialized with the value: '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD001E Unable to read custom script from file: *property*.

Explanation

See message.

Action

Check access to the custom script file.

CTGDKD002E Invalid value specified for 'api.remote.naming.port': '*parameter value*'.

Explanation

The naming port must be a number, in the range 1..65535.

Action

Check the property 'api.remote.naming.port' in the global.properties file, and assign it a proper value.

CTGDKD003I Will use default value for 'api.remote.naming.port': '*port*'.

Explanation

The naming port is not defined in the global.properties file, and a default value is used.

Action

Check the property 'api.remote.naming.port' in the global.properties file, and assign it a proper value.

CTGDKD004E Could not create RMI custom socket factories. Exception occurred: *exception*

Explanation

Review the exception to find further details on the error.

Action

Check the SSL properties in the global.properties file.

CTGDKD005E Could not get localhost IP address.

Explanation

No IP address for the host could be found.

Action

Review the exception to find further details on the error.

CTGDKD006E Server API not initialized.

Explanation

Review the previous exception to find further details on the error.

Action

No action is required.

CTGDKD007I Secure RMI socket factories created successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD008I Remote Session Factory object bound to name 'SessionFactory'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD009E Could not create SessionFactory. Exception occurred: *exception*

Explanation

Could not initialize the Server API for remote access. Could not create an instance of the factory that is used to access the Server API.

Action

Review the exception to find further details on the error.

CTGDKD010E Could not bind RemoteSessionFactory.

Explanation

See message.

Action

Check the remote session factory name.

CTGDKD011E Unable to get TombstonesConfig. Exception occurred: *exception*

Explanation

Review the exception to find further details on the error.

Action

Check the configuration file.

CTGDKD012I RMI Registry started on port: *port number*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD013I Successfully connected to RMI Registry: *existing registry*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD019E Could not create RMI Registry:**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD020E Server cryptography is already initialized.**Explanation**

This is an internal error.

Action

Contact IBM support.

CTGDKD021E LDAP Authentication initialization error.**Explanation**

Exception caught on initialization of the LDAP Authenticator.

Action

No action is required.

**CTGDKD022E LDAP Authentication initialization error:
*exception*****Explanation**

Exception caught on initialization of the LDAP Authenticator.

Action

Review the exception to find further details on the error.

**CTGDKD023I Remote API Engine successfully initialized. SSL
and Client Authentication are enabled.****Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD024I Remote API successfully started on port:*port*, bound to:'SessionFactory'. SSL and Client Authentication are enabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD025E Unable to initialize ScriptEngine:

Explanation

The APIAuthenticator constructor could not initialize ScriptEngine.

Action

Review the exception to find further details on the error.

CTGDKD026E Custom authentication is disabled.

Explanation

See message.

Action

Verify the property 'api.custom.authentication' in the global.properties file.

CTGDKD027E Script error:

Explanation

Review the exception to find further details on the error.

Action

Check the custom script provided.

CTGDKD028I Authentication failed for user: *username*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKD029E Missing configuration property:
api.config.folder.**

Explanation

See message.

Action

Check the property 'api.config.folder' in the global.properties file.

**CTGDKD030E Unable to get canonical path of the
'api.config.folder' property value: *path*. Exception
occurred: *exception*.**

Explanation

An IOException was encountered while getting canonical path.

Action

Check the property api.config.folder in the global.properties file and ensure the file path is correct.

**CTGDKD031E Invalid value specified for
'api.config.lock.timeout': '*paramater value*'. Exception
occurred: *exception***

Explanation

An NumberFormatException was encountered while parsing string to int.

Action

Check the property 'api.config.lock.timeout' in the global.properties file.

**CTGDKD032I Will use default value for
'api.config.lock.timeout': *value*.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD034E Invalid folder path: '*path*'.

Explanation

The path is a file.

Action

Check the property 'api.config.folder' in the global.properties file.

CTGDKD035E Invalid folder path: ''path''

Explanation

The path is a file.

Action

Check the property 'api.config.folder' in the global.properties file.

CTGDKD036E Configuration ''path'' is already checked out.

Explanation

See message.

Action

Check in the configuration first.

CTGDKD037E Configuration ''path'' is password protected.

Explanation

An PasswordException is encountered while loading configuration.

Action

Provide password for the configuration.

CTGDKD038E Error while loading configuration ''path''.

Explanation

An Exception is encountered while loading configuration.

Action

Review the exception to find further details on the error.

CTGDKD039E Configuration ''path'' is already checked out.

Explanation

See message.

Action

Check in the configuration first.

CTGDKD041E Configuration ''path'' is not checked out.

Explanation

The reason for exception might be timeout expired.

Action

Check the configuration first.

CTGDKD042E Configuration '*path*' is not checked out.**Explanation**

The reason for exception might be timeout expired.

Action

Check out the configuration first.

CTGDKD043E Configuration file '*path*' already exists.**Explanation**

See message.

Action

Give other name of configuration or confirm overwriting.

CTGDKD044E Configuration '*path*' is already checked out.**Explanation**

See message.

Action

Check in the configuration first.

CTGDKD045E Could not load configuration '*path*'.**Explanation**

An Exception is encountered while loading configuration.

Action

Review the exception to find further details on the error.

**CTGDKD046E recurseDirs: Invalid folder path:
'*directory*'.****Explanation**

The path must be a valid directory.

Action

Check the folder path.

CTGDKD047E Internal error: NULL user ID in configuration registry for '*path*'.

Explanation

See message.

Action

Check the name of the configuration.

CTGDKD048I The Config '*file path*' was locked by the user '*user ID*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD049I The Config '*file path*' lock was released.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD050I The Config '*file path*' lock time was reset.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD051E Unable to save the Config because the configuration path '*file path*' could not be set.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD052E Unable to save the Config '*file path*'.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD053E Unable to save the Config '*file path*' because the Config is not committable.

Explanation

See message.

Action

No action is required.

CTGDKD054I Stopped Config instance '*file path*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD055E Unable to stop Config instance '*file path*'. The Config instance was not found.

Explanation

See message.

Action

No action is required.

CTGDKD056I Reloaded Config instance '*file path*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD057E Unable to reload Config instance '*file path*'. An exception was encountered: *exception*
Explanation

See message.

Action

No action is required.

CTGDKD058E Unable to reload Config instance '*file path*'. The Config instance was not found.
Explanation

See message.

Action

No action is required.

CTGDKD059E Automatic unlock thread of the configuration registry was interrupted. An exception was encountered: *exception*
Explanation

See message.

Action

No action is required.

CTGDKD060E Automatic unlock thread of the configuration registry encountered a fatal exception: *exception*
Explanation

See message.

Action

No action is required.

CTGDKD061E Automatic unlock thread of the configuration registry could not stop Config instance '*Config instance ID*'. An exception was encountered: *exception*
Explanation

See message.

Action

No action is required.

CTGDKD062I The Config instance '*Config instance ID*' was automatically unlocked.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD063E Absolute path provided : *path* expecting relative.

Explanation

See message.

Action

No action is required.

CTGDKD065E Path provided : *path* is not allowed.

Explanation

See message.

Action

Provide a relative path.

CTGDKD066E Config Instance is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD067E Config Instance is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD068E AssemblyLine is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD069E Config Instance for AssemblyLine
'*AssemblyLine*' not registered.**

Explanation

See message.

Action

No action is required.

CTGDKD070E AssemblyLine is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD071E On AL terminate: Config Instance for
AssemblyLine '*AssemblyLine*' not registered.**

Explanation

See message.

Action

No action is required.

CTGDKD072E EventHandler is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD073E Config Instance for EventHandler
'*EventHandler*' not registered.**

Explanation

See message.

Action

No action is required.

CTGDKD074E EventHandler is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD075E On EventHandler terminate: Config Instance for EventHandler '*EventHandler*' not registered.

Explanation

See message.

Action

No action is required.

CTGDKD076E Trigger is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD077E Config Instance for Trigger '*trigger name*' not registered.

Explanation

See message.

Action

No action is required.

CTGDKD078E Trigger is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD079E On EH terminate: Config Instance for Trigger '*trigger name*' not registered.

Explanation

See message.

Action

No action is required.

CTGDKD080E Listener object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD081E Error on handleEvent method: *exception***Explanation**

See message.

Action

No action is required.

CTGDKD082E Error on handleEvent method: *exception***Explanation**

See message.

Action

No action is required.

CTGDKD083E Event type is NULL.**Explanation**

Internal error has occurred.

Action

Contact IBM support.

CTGDKD084I Not authorized to perform this operation.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD085E Username is null. Authentication failed.

Explanation

See message.

Action

Provide a valid username.

CTGDKD086E Password is null. Authentication failed.

Explanation

See message.

Action

Provide a valid password.

CTGDKD087I Performing search for full DN for '*username*' with filter: *filter*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD088I Using LDAP SSL connection.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD089E Authentication failed for '*username*'. Exception occurred: *exception*

Explanation

See message.

Action

Provide a valid username and password.

CTGDKD090I LDAP Authentication succeeded for '*username*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD091I LDAP Authentication module closed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD092I Using Simple authentication for search context.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD093I Using Anonymous authentication for search context.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD094I Using LDAP SSL connection.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD095I Trying to create search context ...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD096I Search context created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD097E Error while creating search context: *exception*

Explanation

There are some possible reasons: the settings in the configuration file as well as the LDAP server could not be running.

Action

Check the settings in the configuration file and whether the LDAP server is running.

CTGDKD098E More than one search result found.

Authentication failed for `'username'`.

Explanation

See message.

Action

Provide unique username.

CTGDKD099E Full DN not found. Authentication failed for

`'username'`.

Explanation

See message.

Action

Provide valid username.

CTGDKD100E Missing property ''property''.

Explanation

The LDAP Host name is not set.

Action

Check the settings in the configuration file.

CTGDKD101E Missing property ''property''.

Explanation

See message.

Action

Ensure the port and other settings are correct.

CTGDKD102E Unable to create search context.

Explanation

See message.

Action

Check the settings in the configuration file.

**CTGDKD103E AuthenticationException: Unable to parse
ErrorCode : *error code***

Explanation

See message.

Action

No action is required.

CTGDKD104I User not authenticated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD105I Configuration already exists.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD106I Configuration is not checked out.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD107E Server API JMX Agent already initialized.**Explanation**

Internal error has occurred.

Action

Contact IBM support.

CTGDKD108I Server API JMX Agent successfully initialized.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD109E Could not initialize Server API JMX Agent.**Explanation**

Internal error has occurred.

Action

Contact IBM support.

**CTGDKD110E Server API JMX Agent is not initialized.
Cannot initialize JMX Remoting.****Explanation**

Most probably the Server API JMX layer is not turned on.

Action

Check the settings in global.properties/solution.properties file related to JMX.

CTGDKD111I JMX Remote Server Connector started at: *URL*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD112E Could not initialize Server API JMX Remoting.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKD113E Server API JMX Agent not initialized.

Explanation

See message.

Action

No action is required.

CTGDKD114I JMX MBean registered: *object name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD115E Server API JMX Agent not initialized.

Explanation

See message.

Action

No action is required.

CTGDKD116I JMX MBean unregistered: *object name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD117E Server API JMX Agent not initialized.**Explanation**

Internal error has occurred.

Action

Contact IBM support.

CTGDKD118E Server API JMX Agent not initialized.**Explanation**

See message.

Action

No action is required.

CTGDKD119E Could not initialize/register Notification service. Exception occurred: *exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD120E JMX Server API Listener already initialized.**Explanation**

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD121E Local Session is NULL.**Explanation**

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD122I JMX Server API Listener successfully registered.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD123I DIEvent received: *event*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD124E Unrecognized event type: *event type*. Event skipped.

Explanation

See message.

Action

No action is required.

CTGDKD125E Could not register AssemblyLine MBean.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD126E JMX Notification service could not handle event for AssemblyLine start: *exception*

Explanation

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD127E Could not register Config Instance MBean.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD128E Could not register TDIProperties MBean.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD129E Could not register TDIProperties MBean.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD130E JMX Notification service could not handle event for ConfigInstance start. Exception occurred:

exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD131E Could not register EventHandler MBean.

Explanation

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD132E JMX Notification service could not handle event for EventHandler start: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD133E Could not unregister AssemblyLine MBean:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD134E JMX Notification service could not handle event for AssemblyLine stop. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD135E Could not unregister EventHandler MBean.
Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD136E JMX Notification service could not handle event for EventHandler stop. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD137E Could not unregister Config Instance MBean.
Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD138E Could not unregister TDIProperties MBean:
*exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD139E Could not unregister TDIProperties MBean.
Explanation**

See message.

Action

Review the exception to find further details on the error.

**CTGDKD140E JMX Notification service could not handle
event for Config Instance stop. Exception occurred:
*exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD141E JMX Notification service could not handle
event for Config Instance file updated. Exception occurred:
*exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD142E JMX Notification service could not handle
Server stop event. Exception occurred: *exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD143E JMX Notification service could not handle custom notification event: *exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD144E Could not create AssemblyLine JMX Object Name.**Explanation**

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD145E Could not unregister AssemblyLineHandler MBean. Exception occurred: *exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD146E Could not create AssemblyLineHandler JMX Object Name.**Explanation**

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD147E Listener object is NULL.**Explanation**

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD148E Listener object is NULL.

Explanation

Internal error has occurred.

Action

Contact IBM Security Directory Integrator support.

CTGDKD149I JMX MBean call from remote user: ''userId''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD150E Error retrieving JMX remote user ID: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD151E Could not register AssemblyLineHandler MBean.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD152E Exception on JMX assemblyLineCycleDone():

exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD153E Exception on JMX assemblyLineFinished():

exception

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD154E Exception on JMX messageLogged method:
*exception*****Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD155E Exception on JMX eventCaptured(): *exception*
Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD156E Exception on JMX eventProcessed method:
*exception*****Explanation**

See message.

Action

Review the exception to find further details on the error.

**CTGDKD157E Exception on JMX eventHandlerTerminated
method: *exception*****Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD158E Exception on JMX messageLogged(): *exception*
Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD159E Could not create ConfigInstance JMX Object Name.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD160E Could not create EventHandler JMX Object Name.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD161E Listener object is NULL.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKD162E Listener object is NULL.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDKD163E JMX Notification Service already initialized.

Explanation

See message.

Action

No action is required.

CTGDKD164E JMX Notification service is not started (initialized).

Explanation

See message.

Action

No action is required.

CTGDKD165E Could not create JMX Notifier Object Name.

Explanation

See message.

Action

No action is required.

CTGDKD166E Could not create TDIProperties JMX Object Name.

Explanation

See message.

Action

No action is required.

CTGDKD167E AssemblyLine object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD168E Raw AssemblyLine object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD169E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD170E Could not execute AssemblyLine cycle.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD171E Could not execute AssemblyLine cycle.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD172E Could not execute AssemblyLine cycle.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD173E Could not close AssemblyLine.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD174E Raw AssemblyLine object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD175E Config Instance object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD176E Session object is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD177E Error while obtaining SystemLog for
AssemblyLine: *AssemblyLine name.AssemblyLine hash code.***

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD178E Could not get AssemblyLine configuration.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD179E Raw Config Instance is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD180E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD181E Raw Config Instance is not running.

Explanation

See message.

Action

No action is required.

**CTGDKD182E User ''User ID'' cannot set configuration for:
Config ID.**

Explanation

See message.

Action

No action is required.

CTGDKD183E Not a supported call.

Explanation

See message.

Action

No action is required.

CTGDKD184E Not a supported call.

Explanation

See message.

Action

No action is required.

CTGDKD185E Could not obtain External Properties.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD186E Could not obtain External Properties.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD187E Could not obtain External Properties Keys.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD188E Not a supported call.

Explanation

See message.

Action

No action is required.

CTGDKD189E Not a supported call.

Explanation

See message.

Action

No action is required.

CTGDKD190E Not a supported call.

Explanation

See message.

Action

No action is required.

CTGDKD191E Could not retrieve AssemblyLines names.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD192E Could not obtain AssemblyLine input schema.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD193E Could not obtain AssemblyLine output schema.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD194E Could not retrieve EventHandlers names.

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD195E Not authorized to execute AssemblyLine:
AssemblyLine.**

Explanation

See message.

Action

No action is required.

CTGDKD196E Could not start AssemblyLine *AssemblyLine*.

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD197E Not authorized to execute AssemblyLine:
AssemblyLine.**

Explanation

See message.

Action

No action is required.

CTGDKD198E Could not start AssemblyLine *AssemblyLine*.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD199E Not authorized to execute AssemblyLine:
AssemblyLine.

Explanation

See message.

Action

No action is required.

CTGDKD200E Could not start AssemblyLine *AssemblyLine.*

Explanation

See message.

Action

No action is required.

CTGDKD201E Not authorized to execute AssemblyLine:
AssemblyLine.

Explanation

See message.

Action

No action is required.

CTGDKD202E Could not start AssemblyLine *AssemblyLine.*

Explanation

See message.

Action

No action is required.

CTGDKD203E Not authorized to execute EventHandler:
EventHandler.

Explanation

See message.

Action

No action is required.

CTGDKD204E Could not start EventHandler.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD205E Could not reload Config Instance.

Explanation

See message.

Action

No action is required.

CTGDKD206E Connector Pool does not exist: *Connector Pool name*.

Explanation

See message.

Action

No action is required.

CTGDKD207E Connector Pool does not exist: *Connector Pool name*.

Explanation

See message.

Action

No action is required.

CTGDKD208E Connector Pool does not exist: *Connector Pool name*.

Explanation

See message.

Action

No action is required.

CTGDKD209E Connector Pool does not exist: *Connector Pool name.*

Explanation

See message.

Action

No action is required.

CTGDKD210E Unable to obtain config object.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD211E Could not retrieve AssemblyLines Folder.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD212E AssemblyLines Folder object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD213E getAssemblyLineCfg: Could not retrieve configuration for AssemblyLine '*AssemblyLine name*'.

Explanation

See message.

Action

No action is required.

CTGDKD214E getAssemblyLineCfg: AssemblyLine '*AssemblyLine name*'. Configuration object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD215E Could not retrieve EventHandlers Folder.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD216E EventHandlers Folder object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD217E Error updating configuration lock time:

exception

Explanation

See message.

Action

No action is required.

CTGDKD218E Raw Switchboard object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD219E Config Instance object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD220E Session object is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD221E Error while obtaining SystemLog for
EventHandler: *Switchboard name.Switchboard hashcode.***

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD222E Raw Trigger object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD223E Config Instance object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD224E Session object is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD225E Error while obtaining SystemLog for
EventHandler: *trigger name.trigger hashcode.***

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD226E Internal error: invalid EventHandler type:
EventHandler type.

Explanation

See message.

Action

No action is required.

CTGDKD227E Internal error: invalid EventHandler type:
EventHandler type.

Explanation

See message.

Action

No action is required.

CTGDKD228E Internal error: invalid EventHandler type:
EventHandler type.

Explanation

See message.

Action

No action is required.

CTGDKD229E Could not retrieve Connectors names.

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD230E Could not retrieve '*Connector Name*'
description. Exception occurred: *exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD231E Could not retrieve ''Connector name'' version info. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD232E Could not retrieve Connector's names.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD233E Could not retrieve description for Connector ''Connector name''.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD234E Could not retrieve class name for Connector ''Connector name''.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD235E Could not retrieve EventHandler's names.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD236E Could not retrieve '*EventHandler name*' description. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD237E Could not retrieve '*EventHandler name*' enabled status. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD238E Could not retrieve '*EventHandler name*' version info. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD239E Could not retrieve EventHandlers names.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD240E Could not retrieve description for EventHandler apos;'*EventHandler name*'.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD241E Could not retrieve enabled status for EventHandler '*EventHandler name*'.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD242E Could not retrieve class name for EventHandler '*EventHandler name*'.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD243E Could not retrieve Parsers names.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD244E Could not retrieve '*Parser name*' description. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD245E Could not retrieve '*Parser name*' version info. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD246E Could not retrieve Parsers names.

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD247E Could not retrieve description for Parser
'Parser name'.**

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD248E Could not retrieve class name for Parser
'Parser name'.**

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD249E Could not retrieve Function Components names.

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD250E Could not retrieve 'Parser name'
description. Exception occurred: *exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD251E Could not retrieve '*Parser name*' version info. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD252E Could not retrieve Function Components names.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD253E Could not retrieve description for Function Component '*Function Component name*'.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD254E Could not retrieve class name for Function Component '*Function Component name*'.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD255E Component class '*class name*' not found.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD256E Access error on loading '*class name*' class.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD257E Could not instantiate class '*class name*'.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD258E Could not retrieve version info for class '*class name*'.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD259E Could not retrieve password parameter names for class '*class name*'.**Explanation**

See message.

Action

Review the exception to find further details on the error.

**CTGDKD260E Authentication failed for user: *username*.
Exception occurred: *exception*****Explanation**

See message.

Action

Provide a valid username and password.

CTGDKD261E Config ID is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD262E Could not start Config Instance.

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD263E Not supported Server API call:
createNewConfigInstance.**

Explanation

See message.

Action

No action is required.

**CTGDKD264E Not supported Server API call:
createNewConfigInstance.**

Explanation

See message.

Action

No action is required.

**CTGDKD265E InternalError: Unknown EventHandler type:
class name.**

Explanation

See message.

Action

No action is required.

CTGDKD266E User with ID: *user ID* not authorized.

Explanation

See message.

Action

No action is required.

CTGDKD267E Could not get default System Queue.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD268E Could not getMessage. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD269E Could not putMessage. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD270E Could not getTextMessage. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD271E Could not putTextMessage. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD272E Could not getBytesMessage. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD273E Could not putBytesMessage. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD274E Could not getEntry. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD275E Could not putEntry. Exception occurred:
exception

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD276E Local TDIProperties is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD277E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD278E AssemblyLine object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD279E Raw AssemblyLine Handler object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD280E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD281E Local AssemblyLine is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD282E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD283E Remote Listener object is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD284E RemoteException on assemblyLineCycleDone
method: *exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD285E RemoteException on assemblyLineFinished
method: *exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD286E RemoteException on messageLogged method:
*exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD287E Listener object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD288E Listener object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD289E Local Config Instance is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD290E Session object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD291E MetamergeConfig.instantiateAllObjects method failed:**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD292E Remote Listener object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD293E RemoteException on handleEvent method.**Explanation**

See message.

Action

No action is required.

CTGDKD294E Listener object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD295E Listener object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD296E Local EventHandler is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD297E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD298E Remote Listener object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD299E RemoteException on eventCaptured method.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD300E RemoteException on eventProcessed method.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD301E RemoteException on eventHandlerTerminated method.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD303E Listener object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD304E Listener object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD305E Local Security Registry object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD306E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD307E Local Server Info object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD308E Session object is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD309E SSL client authentication is disabled.**Explanation**

When connecting to a remote IBM Security Directory Integrator Server over SSL, either SSL Client authentication or LDAP/Custom Authentication must be used. Connections using the createSession() API will not succeed because the server has SSL client authentication disabled.

Action

Verify the authentication mechanism configured for the server and enable it in the client before attempting to create another session with the server. Try using the createSession(username,password) API which uses LDAP/Custom Authentication. Refer to the Security related chapters in the IBM Security Directory Integrator Installation and Administrator Guide for more information.

CTGDKD310E Unable to get userId.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD311I Remote session created for user: *user ID*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD312E Error in host authentication.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD313E Host not allowed.**Explanation**

S See message.

Action

No action is required.

CTGDKD314I Remote session created with local Identity.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD315I Remote session created for user: *username***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD316E Authentication failed for user: *username*.**Exception occurred: *exemption*****Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD317E Local System Log is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD318E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD319E Local TDIProperties is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD320E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD321E Local TombstoneManager is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD322E Session object is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD323E No Socket is associated with the current thread.

Explanation

Socket is null.

Action

No action is required.

**CTGDKD324E Unable to create socket. Exception occurred:
*exception*****Explanation**

An IOException is encountered.

Action

Review the exception to find further details on the error.

CTGDKD325E Required property is missing: *key*.**Explanation**

See message.

Action

No action is required.

CTGDKD326E Invalid type for property '*key*': *class name*.**Explanation**

The property must be an instanceof String.

Action

No action is required.

**CTGDKD328E No SSL socket is associated with the current
thread.****Explanation**

Socket is null.

Action

No action is required.

CTGDKD329E SSL socket session is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD330E SSL session certificate chain is empty.

Explanation

See message.

Action

No action is required.

CTGDKD331E Required property is missing: *key*.

Explanation

See message.

Action

No action is required.

CTGDKD332E Invalid type for property '*key*': *class name*.

Explanation

See message.

Action

No action is required.

CTGDKD335E Input file '*file name*' does not exist.

Explanation

See message.

Action

No action is required.

CTGDKD336E Server cryptography is not initialized.

Explanation

This is an internal error.

Action

Contact IBM support.

CTGDKD337E Illegal value '*mode*' for mode parameter.

Explanation

The mode must be 'encrypt' or 'decrypt'.

Action

No action is required.

CTGDKD346E Registry already initialized.

Explanation

See message.

Action

No action is required.

CTGDKD347E Registry file name is NULL.

Explanation

See message.

Action

Provide a valid registry file name.

CTGDKD348E Registry file '*file name*' does not exists.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD349I Reading security registry ...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD350I Decrypting security registry ...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD351E Error while decrypting registry file.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD352E Registry file not found.**Explanation**

A FileNotFoundException is encountered.

Action

Provide a valid registry file.

CTGDKD353E Error while reading registry file.**Explanation**

An IOException is encountered.

Action

Review the exception to find further details on the error.

CTGDKD354I Security registry successfully read.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKD355E Invalid tag at line *line number*: *line*.
Expected '[USER]'.****Explanation**

See message.

Action

Provide a valid registry file.

CTGDKD356E No user ID specified.**Explanation**

See message.

Action

Provide a valid registry file.

CTGDKD357E Invalid tag at line *line number*: *line*.
Expected '[ID]:'.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD358E Empty user ID specified at line *line number*.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD359E Invalid User definition. User ID '*user ID*'
at line *line number* has already been defined in the registry
file.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD360E User definition not closed at end of file.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD361E Invalid tag at line *line number*: *line*.
Expected '[ROLE]:' or '[ENDUSER]'.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD362E Empty ROLE specified at line *line number*.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD363E Invalid ROLE specified at line *line number*:
role name.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD364E User definition not closed at end of file.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD365E Invalid tag at line *line number*: *line*.
Expected '[CONFIG]:' or '[ROLE]:' or '[ENDUSER]'.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD366E Empty CONFIG specified at line *line number*.

Explanation

See message.

Action

Provide a valid registry file.

CTGDKD367E User definition not closed at end of file.

Explanation

See message.

Action

Provide a valid registry file.

**CTGDKD368E Empty AL specified at line *line number*.
Explanation**

See message.

Action

Provide a valid registry file.

**CTGDKD369E Empty EH specified at line *line number*.
Explanation**

See message.

Action

Provide a valid registry file.

**CTGDKD370E Invalid tag at line *line number*: *line*.
Expected '[AL]:' or '[EH]:' or '[CONFIG]:' or '[ROLE]:' or
'[ENDUSER]'.****Explanation**

See message.

Action

Provide a valid registry file.

**CTGDKD371E Role is NULL.
Explanation**

See message.

Action

Provide a valid registry file.

**CTGDKD372E Invalid role: *aRole*
Explanation**

The role must be 'admin', 'read' or 'execute'.

Action

Provide a valid registry file.

CTGDKD373E Log Listener is NULL.

Explanation

See message.

Action

No action is required.

**CTGDKD374E Exception caught on messageLogged method:
*exception***

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD375E The `getSystemLogAppender` method called with a
NULL log; will return NULL.**

Explanation

See message.

Action

No action is required.

**CTGDKD376E `getComponentLog`: `LogFileName` parameter is NULL
or empty.**

Explanation

See message.

Action

No action is required.

CTGDKD377E Error while reading '*file name*' log file.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD378E `LogFileName` parameter is NULL or empty.

Explanation

See message.

Action

No action is required.

CTGDKD379E getComponentLogLastChunk: Error while reading '*file name*' log file.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD380E Component name parameter is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD381E Component name parameter is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD382E Min date parameter is NULL.

Explanation

See message.

Action

No action is required.

CTGDKD383E Internal error: deleteAllOldCompLogs: Invalid componenet type: *component type*.

Explanation

See message.

Action

No action is required.

CTGDKD384E Internal error: deleteAllOldCompLogs: Invalid component type: *component type*.

Explanation

See message.

Action

No action is required.

CTGDKD385E Invalid component type specified for SystemLogAppender: '*component type*'. The only valid values are 'AL' and 'EH'.

Explanation

See message.

Action

No action is required.

CTGDKD386E No component type assigned to SystemLog Appender.

Explanation

See message.

Action

No action is required.

CTGDKD387E SystemLogAppender: component type has not been specified.

Explanation

See message.

Action

No action is required.

CTGDKD388E SystemLogAppender: component name has not been specified.

Explanation

See message.

Action

No action is required.

CTGDKD389E SystemLogAppender: log pattern has not been specified.

Explanation

See message.

Action

No action is required.

CTGDKD390E SystemLogAppender: could not generate log file name. Exception occurred: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD391E No component type assigned to SystemLog Appender.

Explanation

See message.

Action

No action is required.

CTGDKD392I TombstoneAutoCleaner started. Will delete Tombstones older than *number of days* days.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD393I TombstoneAutoCleaner: initial run performed. Deleted: *number of tombstones* tombstones.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKD394I TombstoneAutoCleaner: scheduled run performed.
Deleted: *number of tombstones* tombstones.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD395E TombstoneAutoCleaner: thread interrupted.

Explanation

An InterruptedException is encountered.

Action

No action is required.

CTGDKD396E TombstoneAutoCleaner error: *exception*

Explanation

See message.

Action

Review the exception to find further details on the error.

**CTGDKD397I TombstoneAutoCleaner: time to next run:
timestamp.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKD398I TombstoneAutoCleaner: next run is scheduled for
timestamp.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD399E Could not initialize Tombstone Manager database connection.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD400E Could not initialize Tombstone Manager Listener.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD401E Error in checking for tombstone records table.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD402I ''table name'' CREATE: SQL statement.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD403E Error in creating tombstone table.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD404E Error in getting tombstone record by GUID.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD405E Error in deleting tombstone record by GUID.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD406E Error in constructing tombstone from database record.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD407E Error on retrieving tombstone records:**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD408E Error in retrieving last record to keep:**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD409E Error in deleting tombstone records:**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD410E Error in object deserialization:**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD411I Tombstones record count: *count*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD412E Error in count Tombstone records:**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD413E Insert operation of tombstone record in database failed.**Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDKD414E Tombstone Manager Listener already initialized.**Explanation**

See message.

Action

No action is required.

CTGDKD415E Local Session is NULL.**Explanation**

See message.

Action

No action is required.

CTGDKD416E Tombstone Manager Server API Listener successfully registered.**Explanation**

See message.

Action

No action is required.

CTGDKD417I Tombstone created for event: *event*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD418I Current record count: *number of records*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD419I Initiating record deletion to max records: *integer*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD420I Finished record deletion.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD421E Tombstone statistics serialization error.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD422E Object serialization failed.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD423E Unable to get AssemblyLineConfig for AssemblyLine: *event ID*.

Explanation

See message.

Action

No action is required.

CTGDKD424E Unable to get TombstonesConfig for EventHandler: *event ID*.

Explanation

See message.

Action

No action is required.

CTGDKD425I initRecordCounters: recordsTrigger: *boolean*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD426I *initRecordCounters: recordsMax: integer.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD427I *initRecordCounters: recordsCount: integer.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD428I **Records count monitoring is turned on.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD429I **Records count monitoring is disabled.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD430I *line number: inputLine*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD431E The IBM Security Directory Integrator property store *property store name* does not exist.

Explanation

See message.

Action

Pass an existing IBM Security Directory Integrator Property store name.

CTGDKD432I Remote API Engine successfully initialized. SSL is enabled and Client Authentication is disabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD433I Remote API successfully started on port:*port*, bound to:'SessionFactory'. SSL is enabled and Client Authentication is disabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD434I Remote API Engine successfully initialized. SSL and Client Authentication are disabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD435I Remote API successfully started on port:*port*, bound to:'SessionFactory'. SSL and Client Authentication are disabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD436E The desired custom class can not be found.**Explanation**

See message.

Action

Pass a valid class name.

CTGDKD437E The desired custom method can not be found.**Explanation**

See message.

Action

Pass a valid method name.

CTGDKD438E Exception occurred in the invoked custom method.**Explanation**

See message.

Action

No action is required.

CTGDKD439E Method does not have access to the definition of the specified custom class.**Explanation**

See message.

Action

No action is required.

CTGDKD440E This method does not support invocations of methods with null value parameters.**Explanation**

See message.

Action

Use the other invokeCustom method.

CTGDKD441E The custom method invocation is not turned on.

Explanation

See message.

Action

Turn on custom method invocation from global.properties file. Change api.custom.method.invoke.on property to true.

CTGDKD442E No classes are allowed for custom invocation.

Explanation

See message.

Action

Allow invocation of custom classes from global.properties file. Change api.custom.method.invoke.allowed.classes property.

CTGDKD443E The desired class is not allowed for invocation: *class name*.

Explanation

See message.

Action

Allow invocation of the class from global.properties file. Change api.custom.method.invoke.allowed.classes property.

CTGDKD444I Allowed classes for custom invocation: *class names*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD445I Custom method invocation is set to *boolean value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD446I Usage: `-input <input file> -output <output file> -mode <operation mode|operation mode|operation mode|operation mode> -keystore <keystore file> -storepass <keystore password> -alias <encryption key alias> [-keypass <key password>] [-transformation <encryption transformation>] [-storetype <keystore type>] [-cryptoproviderclass <security provider used for encryption>]`

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD447E The provided file is not an encrypted IBM Security Directory Integrator Config file.

Explanation

The IBM Security Directory Integrator Config file signature is either missing or corrupted.

Action

Ensure the provided file is a valid encrypted IBM Security Directory Integrator config file.

CTGDKD458E Error on retrieving tombstone records:

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKD459W The Solution Name '*Solution Name*' of the configuration '*file name*' is not a valid file name. The configuration instance id and Solution Name will be changed to: '*Solution Name*'.

Explanation

When a configuration has a defined Solution Name, the name used as the configuration instance id by the IBM Security Directory Integrator Server. The configuration id is used to store certain artifacts, such as system logs, on the file system of the IBM Security Directory Integrator Server. The Solution Name in the configuration file was not valid file name. The IBM Security Directory Integrator

Server has modified the Solution Name internally so that it can be used as a configuration id.

Action

Provide a valid Solution Name in the configuration file.

CTGDKD461I The Configuration Registry parsed file '*file name*' and found Solution Name '*name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD462E Solution Name '*Solution Name*' is already in use by configuration '*file name*'.

Explanation

No two configurations are allowed to have the same Solution Name within the same IBM Security Directory Integrator Server.

Action

Ensure that no two configurations have the same Solution Names.

CTGDKD463W The IBM Security Directory Integrator Server detected the Solution Name '*Solution Name*' from a client in the token '*token name*'.

Explanation

The Server encountered a client utility that prefixes the Solution Names with the path of the configuration folder.

Action

No response is necessary.

CTGDKD464E Solution Name '*name*' of configuration '*file name*' coincides with the name of file '*file name*'.

Explanation

For security reasons, Solution Names are not allowed to coincide with names of existing files.

Action

Ensure the Solution Name of the configuration is not the same as the path of an existing file.

CTGDKD465W Password protected configuration detected in file '*file name*'. The configuration will be only be accessible through its file name.

Explanation

The Server API is unable to extract Solution Names for password protected configurations present in the configuration codebase folder.

Action

No response is necessary.

CTGDKD466I Unable to parse the file '*file name*'. The file will processed as a valid configuration file and added it to the list of configurations.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD467W Password protected configuration detected '*name*'. The Solution Name will be ignored and may already be used by another configuration.

Explanation

The Server API is unable to extract Solution Names for password protected configurations present in the configuration folder. The Solution Name will be ignored and may already be used by another configuration.

Action

Verify no configurations loaded on the server have the same Solution Name.

CTGDKD468E Invalid value specified for '*api.config.load.timeout*': '*paramater value*'. Server API will use the default value of this property.

Explanation

A NumberFormatException was encountered while converting the parameter from a String to an Integer.

Action

Ensure the `api.config.load.timeout` property in the `global.properties` is valid.

CTGDKD469W The configuration could not be loaded in the time specified in 'api.config.load.timeout': property.

Explanation

Server API is unable to load configuration in the timeout interval specified in 'api.config.load.timeout': property.

Action

No response is necessary.

CTGDKD470E Error while broadcasting audit notification. The event type was not specified in the event.

Explanation

The event could not be sent because it has no specified type.

Action

Set type of the event before attempting to send the event.

CTGDKD471E A password was not specified or was invalid for the encrypted file.

Explanation

See message.

Action

Provide a valid password.

CTGDKD472E The specified Run Name '*name*' cannot be used as a configuration instance id because it contains one or more of the following symbols: \ / : * ? ' < > |.

Explanation

Each Run Name is used as a configuration instance id. Configuration instance ids are used as file names to store certain instance-related entities such as system logs. That is why a Run Name must be a valid file name.

Action

Specify a run name that does not contain slashes or colons.

CTGDKD473I User '*user name*' cannot be successfully looked up in the directory context. No group search was performed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD474E The required attribute '*attribute name*' is not specified.

Explanation

The attribute is required in order to search for the groups of the LDAP user, but the attribute is not set to a value.

Action

Specify an appropriate value for this attribute in `global.properties` or `solution.properties` or turn off the LDAP group support.

CTGDKD475E No search base was specified for the group search option. Assign a value to the property '*property name*'.

Explanation

The attribute is required in order to search for the groups of the LDAP user, but the attribute is not set to a value.

Action

Specify a valid base for the group searches.

CTGDKD476I The attempt at direct binding for the LDAP group '*group name*' has failed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKD477I The value for '*api.remote.naming.port*': '*port*' is in the reserved range of port numbers.

Explanation

The naming port has a value between 1 and 1023. Port numbers in that range are reserved for special purposes.

Action

Check the property '`api.remote.naming.port`' in the `global.properties/` `solution.properties` file, and assign it a proper value.

CTGDKD478E User Registry could not parse CONFIG identifier '*name*'. Exception occurred: *exception*

Explanation

The User Registry could not derive a configuration instance id from the specified CONFIG identifier.

Action

Verify that the CONFIG identifier is either an absolute file name or is acceptable for a configuration instance run name.

CTGDKD479E The file cannot be deleted, because it is currently checked out.

Explanation

Someone holds a lock over the file (possibly editing it at the moment). The file cannot be deleted until the lock is released.

Action

Verify that the file is not checked out.

CTGDKD480E Cannot delete file '*file name*'.

Explanation

A file system error occurred while deleting the file. Possibly the file does not exist.

Action

Verify that the file exists. Verify the file system permissions of the IBM Security Directory Integrator Server process over the file.

CTGDKD481E Error occurred while reading the configuration: *exception*

Explanation

A problem was encountered while reading the configuration in order to obtain its Solution Name. Possibly the configuration syntax is incorrect.

Action

Verify that the configuration is valid.

CTGDKD482E No SSL socket is associated with the current thread.

Explanation

SSL socket is null.

Action

No action is required.

CTGDKD483E SSL socket session is NULL.**Explanation**

A problem was encountered while retrieving SSL socket session.

Action

Check the connection settings.

CTGDKD484E SSL session certificate chain is empty.**Explanation**

No certificates were found for this SSL session.

Action

Check the connection settings.

CTGDKD486E Required property is missing: *property key***Explanation**

There is no value for the provided key in the property map.

Action

No action is required.

CTGDKD489E Unable to create socket: *exception***Explanation**

See the error message.

Action

Check host name and port number and if the problem persists contact IBM support.

CTGDKD492E No socket is associated with the current thread.**Explanation**

Socket is null.

Action

No action is required.

CTGDKD493E Unrecognized Callback.

Explanation

See error trace.

Action

No action is required.

CTGDKD494E One of the listeners for AssemblyLine events threw an exception: '*exception*'.

Explanation

See the message of the exception.

Action

No action is required.

CTGDKD495E One of the listeners for AssemblyLine events threw an unexpected exception: '*exception*'. Will unregister that listener.

Explanation

Unexpected error occurred while notifying one of the AssemblyLine listeners. Probably the process of a remote listener was terminated. See the message of the exception.

Action

No action is required.

CTGDKD496W One of the listeners for logged messages threw an unexpected exception: '*exception*'. Will unregister that listener.

Explanation

Unexpected error occurred while notifying one of the log listeners. Probably the process of a remote listener was terminated. See the message of the exception.

Action

No action is required.

CTGDKD497E Listener object is NULL.

Explanation

A listener object is required.

Action

Make sure a non-null listener is passed to the API.

CTGDKD498E Listener object is NULL.**Explanation**

A listener object is required.

Action

Make sure a non-null listener is passed to the API.

CTGDKD499E Cannot unregister the specified listener because it has not been registered.**Explanation**

Listener objects are associated with the Server API handle. You cannot unregister a listener that was registered in another handle.

Action

Use the same Server API handle to unregister the listener that you used to register it in the first place.

CTGDKD500E Listener object is NULL.**Explanation**

A listener object is required.

Action

Make sure a non-null listener is passed to the API.

CTGDKD501E Cannot unregister the specified listener because it has not been registered.**Explanation**

Listener objects are associated with the Server API handle. You cannot unregister a listener that was registered in another handle.

Action

Use the same Server API handle to unregister the listener that you used to register it in the first place.

CTGDKD502E Listener object is NULL.**Explanation**

A listener object is required.

Action

Make sure a non-null listener is passed to the API.

CTGDKD503E Cannot unregister the specified listener because it has not been registered.

Explanation

Listener objects are associated with the Server API handle. You cannot unregister a listener that was registered in another handle.

Action

Use the same Server API handle to unregister the listener that you used to register it in the first place.

CTGDKD504E Listener object is NULL.

Explanation

A listener object is required.

Action

Make sure a non-null listener is passed to the API.

CTGDKD505E Cannot unregister the specified listener because it has not been registered.

Explanation

Listener objects are associated with the Server API handle. You cannot unregister a listener that was registered in another handle.

Action

Use the same Server API handle to unregister the listener that you used to register it in the first place.

CTGDKD506E A communication error occurred while sending a log message to remote listener: *exception*

Explanation

Could not send message to remote log listener. It is possible that the remote listener has died or there are network problems.

Action

Review the exception to find further details on the error.

CTGDKD507E Out of Server Ports

Explanation

The range of server ports specified by the property `api.remote.server.ports` was exhausted.

Action

Increase the range of ports.

**CTGDKD508I Remote API successfully started on port:*port*
IP:*ip*, bound to:'SessionFactory'. SSL and Client
Authentication are enabled.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKD509I Remote API successfully started on port:*port*
IP:*ip*, bound to:'SessionFactory'. SSL is enabled and Client
Authentication is disabled.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDKD510I Remote API successfully started on port:*port*
IP:*ip*, bound to:'SessionFactory'. SSL and Client
Authentication are disabled.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJU001I Simple Parser read in an entry: '*entry*
value'.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJU002I Simple Parser wrote out a string: '*entry value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJU003E Unable to process entry read because a line read in was not in the key:value pair format: '*line*'

Explanation

See message.

Action

Ensure the lines sent to the Simple Parser are in the key:value pair format.

CTGDJP501I Parsing XML response from the server.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP502I Configuration parameters: *params*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP503I New MxConnIterator instance created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP504I New MxConnAddOnly instance created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP505I New MxConnLookup instance created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP506I New MxConnUpdate instance created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP507I New MxConnDelete instance created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP508I Selecting entries.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP509I Creating entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP510I Performing search.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP511I Updating entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP512I Deleting entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP513I Receiving HTTP response message.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP514I XML character validation enabled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP515I Sending HTTP message: *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP516I XML message after validation: *message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP517I Can not close file stream.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP518I Can not load properties from file: *file*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP519I Configuration parameters from file on classpath: *params*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP520I Loading properties from file: *file*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP521I Configuration parameters from file in solution folder: *params*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP522I Configuration parameters from file specified as system property: *params*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP523I Clearing configuration parameters.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP524I Select MB0**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP525I Schema cache has been cleared.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP526E Unsupported Link criteria operator.**Explanation**

The operator used for matching is not supported by the Connector.

Action

Change Link criteria operators.

**CTGDJP527E The following unique keys are not specified:
*keys.*****Explanation**

All unique keys must be specified when adding, updating or deleting an entry.

Action

Specify all unique keys.

CTGDJP528E The HTTP server did not returned "HTTP OK".**Explanation**

The HTTP server returned a response code other than 200.

Action

Check configuration parameters.

CTGDJP529E Sending message timed out.**Explanation**

See message.

Action

Change value of Timeout parameter.

CTGDJP530E Can not send HTTP request.**Explanation**

An I/O operation has been interrupted or failed.

Action

Check network or server availability.

CTGDJP531E Invalid value for Timeout parameter.**Explanation**

Timeout parameter have to be greater or equal to zero.

Action

Change the value of the Timeout parameter.

CTGDJP532E List of target URLs is empty.**Explanation**

See message.

Action

Check Base URLs parameter.

CTGDJP533E Parameter not defined: *param*.**Explanation**

Parameter's value is either empty or contains only whitespace characters.

Action

Specify parameter's value.

CTGDJP534W Unable to send HTTP request.**Explanation**

Could not send HTTP message to any of the target URLs.

Action

Check Base URLs parameter.

CTGDJP535E Not supported encoding: *encoding*.**Explanation**

See message.

Action

No action is required.

CTGDJP536W Can not read the HTTP error message.**Explanation**

Can not obtain detailed error message about failed HTTP request.

Action

No action is required.

CTGDJP537E Can not load XML template.**Explanation**

See message.

Action

No action is required.

CTGDJP538E Can not parse received XML.**Explanation**

See message.

Action

No action is required.

CTGDJP539E Parameter not defined: *param*.**Explanation**

The value of this parameter is either empty or contains only whitespace characters.

Action

Specify parameter's value.

**CTGDJP540W Can not read file: *file*. Exception occurred:
*exception*****Explanation**

See message.

Action

Verify the file exists and has the right permission.

CTGDJP541W Can not load resource: *resource*. Exception occurred: *exception*

Explanation

See message.

Action

Verify the resource exists.

CTGDJP542E Schema does not contain MBO: *mbo*.

Explanation

See message.

Action

Check MBO name.

CTGDJP543E Can not obtain schema for object structure: *mos*.

Explanation

See message.

Action

Regenerate XSD files for object structure.

CTGDJP544E Illegal schema element: *name*.

Explanation

Entry or Link Criteria contains another MBO.

Action

No action is required.

CTGDJP545E Illegal schema element for Link criteria: *name*.

Explanation

Link criteria name is defined as XML attribute. Only XML elements are allowed.

Action

Check Link criteria.

CTGDJP546E Element not found: *name*.

Explanation

The specified element can not be found in the schema.

Action

No action is required.

CTGDJP547E No configuration is specified.**Explanation**

The configuration of the Connector has not been initialized.

Action

Specify all configuration parameters in the Connector.

CTGDJP548E Unsupported Link criteria type.**Explanation**

See message.

Action

Change the type of the used Link criteria.

CTGDJP549E Invalid value for Page size parameter.**Explanation**

Page size parameter has to be greater than zero.

Action

Change Page size parameter's value.

CTGDJP550E The '*name*' attribute exceeds the maximum allowed size: *size*.**Explanation**

Length of attribute or link criteria value exceeds the maximum allowed size for this type of field.

Action

Review and change entry or link criteria.

CTGDJP551E The value is not a valid boolean: *value*.**Explanation**

The value can not be converted to a valid boolean.

Action

Check value.

CTGDJP552E The string does not contain a boolean: *value*.

Explanation

The string can not be parsed as a boolean.

Action

Check string.

CTGDJP553E The value is not a valid date: *value*.

Explanation

The value can not be converted to a valid date.

Action

Check value.

CTGDJP554E The string does not contain a parsable date: *value*.

Explanation

The string can not be parsed as a date.

Action

Check string.

CTGDJP555E The value is not a valid double: *value*.

Explanation

The value can not be converted to a valid double.

Action

Check value.

CTGDJP556E The string does not contain a parsable double: *value*.

Explanation

The string can not be parsed as a double.

Action

Check string.

CTGDJP557E The value is not a valid integer: *value*.

Explanation

The value can not be converted to a valid integer.

Action

Check value.

CTGDJP558E The string does not contain a parsable integer: *value*.

Explanation

The string can not be parsed as an integer.

Action

Check string.

CTGDJP559E The value is not a valid long: *value*.

Explanation

The value can not be converted to a valid long.

Action

Check value.

CTGDJP560E The string does not contain a parsable long: *value*.

Explanation

The string can not be parsed as a long.

Action

Check string.

CTGDJP561I Can not find a Maximo exception.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP562I The unique attribute: *attributeName* has a value of '*originalValue*'. It cannot be changed to *userValue*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP563E Unique attribute '*attribute*' is not provided.

Explanation

No attribute with this name is provided in the entry.

Action

Assign a value to the attribute (empty string is also supported).

CTGDJP564I Target URL: *url*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ001I Simple XML Parser will request validating Parser.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ002I Simple XML Parser will request namespace aware Parser.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ003I Simple XML Parser will not indent output.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ004I Simple XML Parser turned off Deferred DOM.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ005I Simple XML Parser could not turned off Deferred DOM.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ006E Failed to read XML because input stream was not found. The input or output modes of the Simple XML Parser may not be valid.**Explanation**

See message.

Action

Check the input and output modes of the Simple XML Parser.

CTGDJZ007E Failed to write XML because output stream was not found. The input or output modes of the Simple XML Parser may not be valid.**Explanation**

See message.

Action

Check the input and output modes of the Simple XML Parser.

CTGDJZ008I Initializing XML Input Document.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ009I Initializing XML Output Document.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ010I The XML document has no children. The top level tag name in the document is '*tag name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ011I The XML document has '*number of children*' children.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ012E Simple XML Parser failed to initialize because XML document read in has no document root.**Explanation**

The Simple XML Parser can only parse XML documents that have a document root.

Action

Verify that the XML document being read has a document root.

CTGDJZ013E Expected child item at index '*index number*'.**Explanation**

The node for this index is null.

Action

Check the content of XML file.

CTGDJZ014I The XML Child node has no children so its being skipped.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ015W SAX Parse Warning: line:*line number*, uri:*uri*, message:*message*.

Explanation

See message.

Action

No action is required.

CTGDJH001E Connector could not return entry because an unknown class type was encountered: '*object type*'

Explanation

The SNMP Connector was trying to return an entry but the class type was unknown.

Action

No action is required.

CTGDJH002I Connector listening for SNMP traps only.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH003E The 'snmpOID' parameter must be set to use the SNMP Connector.

Explanation

The required parameter snmpOID was not specified in the SNMP Connector.

Action

Specify the snmpOID parameter in the Connector.

CTGDJH004I Getting the next SNMP entry. Comparing response OID ''OID'' of the entry with configured walkOID parameter ''OID''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH005E Connector could not get next SNMP entry because a bad PDU was received from the SNMP Server. Error occurred: *exception*

Explanation

The SNMP Connector was trying to retrieve the next entry for the SNMP server but failed because a bad PDU was received.

Action

Verify that the SNMP Server the Connector is receiving data from is still running.

CTGDJH006I Ignoring unsupported link criteria name: ''link criteria''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH007I Search criteria for entry search: OID=''OID'' version=''version'' host=''hostname'' port=''port number''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH008E Connector could not add entry because set request to SNMP Server failed. Error occurred: *error message*

Explanation

The SNMP Connector was trying to add an entry to the SNMP server but failed because the set request failed.

Action

Verify that the SNMP Server the Connector trying to add the entry to is still running and that the entry being added is valid. Also, review the message from SNMP Server for additional detail on why the error occurred.

CTGDJH009I Will send request to get entry with OID ''OID''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH010E Connector could not get next SNMP entry because a bad PDU was received from the SNMP Server. Error occurred: *exception*

Explanation

The SNMP Connector was trying to retrieve the next entry for the SNMP server but failed because a bad PDU was received.

Action

Verify that the SNMP Server the Connector is receiving data from is still running.

CTGDJH011I Empty queue, waiting for data for '*number of seconds*' seconds.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH012I Empty queue, waiting for data with no timeout value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH013I Trap received: *trap*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH101I Initializing with the provided `java.net.DatagramPacket` object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH102E The 'udp.port' parameter must be set to use the SNMP Server Connector.

Explanation

The required parameter `udp.port` was not specified in the SNMP Server Connector.

Action

Specify the `udp.port` parameter in the Connector.

CTGDJH103E Invalid 'udp.port' parameter set in the the SNMP Server Connector: '*parameter value*'.

Explanation

The required parameter `udp.port` was specified in the JMX Connector but was set to an invalid value.

Action

Specify a valid value for the `udp.port` parameter in the Connector.

CTGDJH104I Waiting for SNMP packets on UDP port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH105I Connector terminated by external request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH106I Connector terminating by external request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH107I Receiving Connection from '*hostname*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH108I Receiving Connection from '*hostname*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH109I Ignoring add request for community '*community name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH110I Response PDU on add entry request i '*PDU*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH111I The SNMP error code '*error code*' has an illegal value. The error code value will be changed to 5.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH112I Terminate server request received.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH113I Creating dummy connection using IP Address '*IP Address*' and port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH114W Encountered an IOException on unblocking the SNMP Server Connector's server socket: *exception*

Explanation

See message.

Action

No action required.

CTGDJH115I SNMP Server Connector is already terminating. Not sending termination request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH116I Sending termination request to SNMP Server Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJH117W Unable to add one or more attributes to the entry. Exception occurred: *exception*

Explanation

See message.

Action

No action required.

CTGDJV001E Failed to read XML because input stream was not found. The input or output modes of the SOAP Parser may not be valid.

Explanation

See message.

Action

Check the input and output modes of the SOAP Parser.

CTGDJV002E XML document has no <SOAP-ENV:Body> element.**Explanation**

The SOAP message is not valid.

Action

Check the input SOAP message for node <SOAP-ENV:Body>.

CTGDJV003E <SOAP-ENV:Body> tag has no elements.**Explanation**

The SOAP message is not valid.

Action

The SOAP tag <SOAP-ENV:Body> must have at least an element.

CTGDJV004I The method parseXML returns: *node name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJV005I SOAP Call: *node name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJV006I The element *node name* has no value.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJV007I The element *node name* has no value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJV008I *prefix* DOCUMENT node type.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJV009I *prefix* Node Name: *node name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJV010I *prefix* Node Value: *node value*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJV011I *prefix* Node type is not recognized.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKL001E Unable to process the batch message because an unknown type was encountered: *class name*.

Explanation

The batch message contains an object that is neither request, nor response.

Action

Edit the batch message so that it contains only requests or responses.

CTGDKL002W The Base64 decoding has not finished successfully for the entry with the following attributes: *entry attributes*.

Explanation

An exception occurred while decoding attributes

Action

Check that the binaryAttributes parameter of the Parser is set correctly.

CTGDKL003E Unable to process the request because an unknown request type was received: *class name*.

Explanation

The request type is unknown to the Parser or the object is not a request at all.

Action

Edit the batch message so that it contains only valid requests.

CTGDKL004E Unknown response type: *class name*.

Explanation

The response type is unknown to the Parser or the object is not a response at all.

Action

Edit the batch message so that it contains only valid responses.

CTGDKL005E Unable to complete the *operation name* request. The *operation name* request must contain exactly one <ps> element.

Explanation

The modify, lookup or delete request does not specify ps.

Action

Edit the request in order to be compliant with the SPML v2 specification.

CTGDKL006E Unable to process the entry. The entry is missing required Attribute: *attribute name*.

Explanation

The IBM Security Directory Integrator Entry does not contain an Attribute that is required.

Action

Add the missing Attribute to the IBM Security Directory Integrator Entry.

CTGDKL007E Unknown operation type: *SPML v2 operation*.

Explanation

The SPML v2 operation type is neither request, nor response.

Action

Edit the IBM Security Directory Integrator Entry so that it represents a valid operation.

CTGDKL008E Unable to process the request because an unknown request was received: *SPML v2 request*.

Explanation

The request is unknown to the Parser or is not valid SPML v2 request.

Action

Edit the IBM Security Directory Integrator Entry so that it represents a valid request.

CTGDKL009E Unknown response : *SPML v2 response*.

Explanation

The response is unknown to the Parser or is not valid SPML v2 response.

Action

Edit the IBM Security Directory Integrator Entry so that it represents a valid response.

CTGDKL010W An error occurred while flushing the batch message: *exception*

Explanation

Refer to the exception message for more information.

Action

Check the configuration of the Parser.

CTGDKL011I Base64 decoding attribute: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKL012I Base64 decoding attribute: *attribute name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKL013E Unable to complete the *operation name* request. The *operation name* request must contain a <psoid ID> attribute.

Explanation

The modify, lookup, or delete request does not specify 'psoid ID' attribute correctly.

Action

Edit the request in order to be compliant with the SPML v2 specification. Note that 'psoid ID' declaration is case sensitive.

CTGDID001E Required Connector parameter 'connectionType' is not set.

Explanation

The specified Connector parameter connectionType is required, but not set.

Action

Set the Connector parameter connectionType.

CTGDID002E Required Connector parameter 'url' is not set.

Explanation

The Connector parameter url is required, but not set.

Action

Set the Connector parameter url.

CTGDID003E The 'connectionType' parameter is set to an invalid value '*parameter value*'.

Explanation

See message.

Action

Should specify a valid connectionType parameter in the Connector.

CTGDID004I Server Notification Event received: '*event name*'

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDID005E Unable to add entry. Entry missing required attribute '*event.type*'.

Explanation

The specified Connector attribute *event.type* is not provided in the work Entry.

Action

Verify the attributes in the work Entry. The attribute *event.type* must not have null values.

CTGDID006E Unable to add entry. Entry missing required attribute '*event.id*'.

Explanation

The specified Connector attribute *event.id* is not provided in the work Entry.

Action

Verify the attributes in the work Entry. The attribute *event.id* must not have null values.

CTGDJO001I The '*deliveryMode*' parameter is set to *delivery mode*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO002E Unable to initialize Connector because a connection to the directory server could not be established or the search at base DN *DN* was not valid.

Explanation

See message.

Action

Verify the directory server is running and that the `ldapSearchBase` parameter is set to a valid value.

CTGDJO003W Cannot set starting change number to '*change number*'.

Explanation

The change number specified in the `nsChangenum` parameter could not be used to set the starting change number.

Action

Verify that the `nsChangenum` parameter is set to a valid change number.

CTGDJO004I Starting with change number set to '*change number*' and the '*iteratorStateKey*' was set to '*state value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO005I Connector has timed out and is waiting for next changed entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO006I LDAP search query set to '*filter*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO007I Attempting to find entry with attribute changenumber equal to '*change number*' using the LDAP base DN of '*DN*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO008I Found entry with attribute changenumber equal to '*change number*' using the LDAP base DN of '*DN*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO009I Unable to find entry with attribute change number equal to '*change number*' using the LDAP base DN of '*DN*'. Skipping to try the next entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO010I Will continue but caught a PartialResultException while getting the next search result: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO011E Entry does not contain a valid changelog entry (changes attribute missing) for operation: *type*.

Explanation

The changes attribute 'newrdn' is missing in the entry.

Action

Check the attributes in the entry.

CTGDJO012E Unable to parse changes attribute.

Explanation

The LDIF Parser could not read the entry.

Action

Check the entry.

CTGDJO014E Could not retrieve last change number.

Explanation

The method `getLastChangeNumber` could not retrieve the last change number. The value must be a number.

Action

Check the attribute 'lastchangenumber' in the entry.

CTGDJO015E Could not store the change number value in System Store: *exception*

Explanation

See message.

Action

Check the system store.

CTGDJO016I Current change number value is: *change number*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO017I A namingException is thrown: *xxception*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO018I notificationReceived: *event*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO019E An exception is encountered when executing the method 'callEventFunction': *exception*

Explanation

See message.

Action

Analyse the exception.

CTGDJO020I Block for notifications ...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJO021W Thread interrupted: *exception*

Explanation

An InterruptedException is encountered when executing the method 'blockForNotifications'.

Action

No action is required.

CTGDJO022E Restart info does not contain 'changeNumber' attribute.

Explanation

See message.

Action

Check the attribute 'changeNumber' in the entry.

CTGDJO023W Exception occurred while terminating the Connector: *exception*

Explanation

See message.

Action

No action is required.

CTGDJO024W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used.

Explanation

See message.

Action

Specify the iterator state key if you want the state of the changelog connector to be saved.

CTGDIH001E Required Connector parameter '*parameter name*' is not set.

Explanation

The specified Connector parameter is required, but not set.

Action

Set the Connector parameter.

CTGDIH002E The 'connectionType' parameter is set to an invalid value '*parameter value*'.

Explanation

See message.

Action

Specify a valid connectionType parameter in the Connector.

CTGDIH101E The System Store Connector cannot initialize because the create table statement is missing.

Explanation

The System Store Connector cannot initialize because it cannot determine the proper "create table" statement for the database it is configured to use.

Action

Check the createTable parameter and make sure the proper "create table" statement is specified.

CTGDIH102W Unable to set the commit mode in the System Store Connector to '*commit mode*'. Continuing, but a valid value should be set for the 'pesCommit' parameter.

Explanation

See message.

Action

Verify that the pesCommit parameter in the System Store Connector is set to a valid value. See the IBM Security Directory Integrator Reference Guide for information on valid parameter values for the System Store Connector.

CTGDIH103W An exception was encountered while terminating the System Store Connector: *exception*

Explanation

See message.

Action

No action is required.

CTGDIH104I Entry found without a value for the key attribute '*attribute name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH105E Required Connector parameter 'keyAttribute' is not set.

Explanation

The specified Connector parameter keyAttribute is required, but not set.

Action

Set the Connector parameter keyAttribute.

CTGDIH106E Unable to add the entry because a null Entry object was passed into the putEntry method.

Explanation

See message.

Action

Verify that the entries being passed into the putEntry method are valid and are not null.

CTGDIH107E Unable to add entry because DML Operations are not allowed on the table '*table name*'

Explanation

An attempt was made to add an entry on a table where DML Operations are not allowed. DML Operations are not allowed on the following tables: Delta, CPR, Property store or the Systable.

Action

Verify that the table the entry is added to is not one of the following types of tables: Delta, CPR, Property store or the Systable. The dbTableName parameter is where the table name is configured in the System Store Connector.

CTGDIH108E Unable to modify entry because DML Operations are not allowed on the table '*table name*'.

Explanation

An attempt was made to modify an entry on a table where DML Operations are not allowed. DML Operations are not allowed on the following tables: Delta, CPR, Property store or the Systable.

Action

Verify that the table the entry is being modified in is not one of the following types of tables: Delta, CPR, Property store or the Systable. The dbTableName parameter is where the table name is configured in the System Store Connector.

CTGDIH109E Unable to delete entry because DML Operations are not allowed on the table '*table name*'.

Explanation

An attempt was made to delete an entry on a table where DML Operations are not allowed. DML Operations are not allowed on the following tables: Delta, CPR, Property store or the Systable.

Action

Verify that the table the entry is being delete from is not one of the following types of tables: Delta, CPR, Property store or the Systable. The dbTableName parameter is where the table name is configured in the System Store Connector.

CTGDIH110E Unable to modify the entry because a null Entry object was passed into the modEntry method.

Explanation

See message.

Action

Verify that the entries being passed into the modEntry method are valid and are not null.

CTGDIH111E The entry cannot be added because the keyAttribute attribute '*attribute name*' in the entry has a value of NULL.

Explanation

Attempted to add an entry that did not have the required keyAttribute attribute.

Action

Verify the entries being passed to the System Store Connector have the keyAttribute attribute set and that the System Store Connector is configured with the correct keyAttribute parameter.

CTGDIH112E The entry cannot be modified because the keyAttribute attribute '*attribute name*' in the entry has a value of NULL.

Explanation

Attempted to modify an entry that did not have the required keyAttribute attribute.

Action

Verify the entries being passed to the System Store Connector have the keyAttribute attribute set and that the System Store Connector is configured with the correct keyAttribute parameter.

CTGDIH113E Unable to modify the entry because of a search key mismatch. The search criteria supplied was '*attribute name*' and the keyAttribute configured in the Connector is '*attribute name*'.

Explanation

Tried to search for an entry with a search criteria that did not match the configured keyAttribute of the System Store Connector.

Action

Verify the search criteria is scoped to match on the same keyAttribute parameter that is configured in the System Store Connector.

CTGDIH114I Preparing and executing the query SQL statement to find an entry: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH115W Prepared SQL statement to find entry failed: *exception*

Explanation

See message.

Action

No action is required.

CTGDIH116W The prepared SQL statement to delete an entry will not be used. Exception encountered: *exception*

Explanation

See message.

Action

No action is required.

CTGDIH117E The selectEntries method failed. Cannot execute SQL Statement: *SQL statement*.

Explanation

Error occurred while executing the specified SQL statement.

Action

Specify correct SQL Statement.

CTGDIH118I No more entries to retrieve from SQL search results.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH119E Cannot build where clause (Advanced Link Mode).**Explanation**

See message.

Action

No action is required.

CTGDIH120I Attempting to build an entry in the System Store Connector.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH121I Saving Meta Data. Saving column '*column name*' of column type '*column type*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH122I Retrieving attribute value based on the column name '*column name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH123I Retrieved attribute of type 'CHAR/VARCHAR':
'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH124I Retrieved attribute of type 'LONGVARBINARY'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH125I Retrieved attribute of type 'DECIMAL/INTEGER':
'value'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH126I Retrieved NULL value for INT: *'value'*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH127I Retrieved attribute value of type 'OBJECT':
'class name'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH128I Set value of attribute '*attribute name*' to '*attribute value*'. The class type of the attribute is '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH129I Set value of attribute '*attribute name*' to '*attribute value*'. The class type of the attribute is 'basic'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH130I Set value of attribute '*attribute name*' to 'null'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH131I Successfully built an entry in the System Store Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH132I Preparing to set prepared SQL statement value with attribute name '*attribute name*' and attribute value '*attribute value*'. The index is set to '*index*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH133E No Meta Data description for attribute being set in the prepared SQL statement: '*attribute name*'.

Explanation

The user tried to get the type of a column that does not exist.

Action

Specify an attribute name that matches a column name in the Meta Data.

CTGDIH134W Set prepared SQL statement value for attribute to null: index='*index*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH135W Java Class name of attribute value: '*class name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH136I Type of attribute value: '*attribute value type*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH137I Set 'LONGVARCHAR' value: ''value''.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH138I Set 'VARCHAR' value: ''value''.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH139I Set 'OTHER' value: ''value''.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH140I Set 'INTEGER/TINYINT/SMALLINT' value: ''value''.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH141W Exception caught while parsing Integer from 'INTEGER/TINYINT/SMALLINT' value: ''exception''**Explanation**

The value being parsed is not an Integer.

Action

No action is required.

CTGDIH142I Set value for an unhandled type ''type'' as a string on column ''column name''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH143W SQL warning encountered from prepared SQL statement: *warning message*

Explanation

See message.

Action

No action is required.

CTGDIH144I findEntry method will use SQL statment: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH145I deleteEntry method will use SQL statment: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH146I The delete operation returned *return code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH147I selectEntries method will use SQL statment: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH148I No entries from selectEntries method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH149I Prepared statement: *SQL statement*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIH150E The table name is not specified.

Explanation

The field "Table Name" in the Connector configuration is empty.

Action

Provide the table name.

CTGDIH151E Error: *error message* occured while creating the table *Table Name*.

Explanation

The error occured while creating the table in the system store DB.

Action

Take the necessary action as per the exception.

CTGDIH152E The table name does not begin with a letter.

Explanation

The "Table Name" must start with a letter.

Action

Provide a table name starting with a letter.

CTGDIH153E The table name is not alphanumeric.

Explanation

The "Table Name" must only contain letters, digits or underscore.

Action

Provide a valid table name.

CTGDIH154W An exception occurred while trying to close the database connection: *exception message*

Explanation

A database access error may have occurred. See the exception message for details.

Action

No action required.

CTGDIH155W The following sql exception has occurred while using PreparedStatement *exception message*

Explanation

A database access error may have occurred. See the exception message for details.

Action

No action required.

CTGDIK401E Invalid ENTRY type: *Entry Type*.

Explanation

The Connector was configured to use an Entry Type that is not supported.

Action

Reconfigure the Connector to use a valid Entry Type.

CTGDIK402E Missing ENTRY type. Entry type is null.

Explanation

The Connector was configured to use no Entry Type.

Action

Set the Entry Type in the Connector.

CTGDIK403E Invalid TAM configuration file: *file name*.

Explanation

The Connector was configured to use an invalid TAM Configuration File.

Action

Reconfigure the Connector to use a valid TAM Configuration File.

CTGDIK404E Could not log on to TAM.

Explanation

The Connector was configured to use invalid TAM credentials.

Action

Ensure the TAM ID and TAM Password configuration parameters of the Connector are set to valid values.

CTGDIK405E Could not query TAM Domains.

Explanation

The Connector was unable to query TAM for a list of valid Domains.

Action

Ensure you have configured the TAM JRTE correctly, and that all Configuration parameters are correct. If the problem persists, contact IBM support.

CTGDIK406E Could not shutdown TAM *object name*.

Explanation

The Connector was unable to shutdown TAM.

Action

Ensure you have configured the TAM JRTE correctly, and that all Configuration parameters are correct. Ensure your TAM Server is operational and available. If the problem persists, contact IBM support.

CTGDIK407E Could not retrieve entries for: *object name*.

Explanation

The Connector was unable to retrieve entries for the target object.

Action

Ensure the Connector to is configured to use the correct Entry Type. If the problem persists, contact IBM support.

CTGDIK408E Could not retrieve next entry for: *object name*.

Explanation

The Connector was unable to retrieve the next entry for the target object.

Action

Ensure the Connector to is configured to use the correct Entry Type. If the problem persists, contact IBM support.

CTGDIK409E Could not find entries for: *object name*.

Explanation

The Connector was unable to find entries for the target object.

Action

Ensure the Connector to is configured to use the correct Entry Type. If the problem persists, contact IBM support.

CTGDIK410E There was an error while creating: *object name*.

Explanation

The Connector was unable to create an entry of the configured Entry Type.

Action

Check the HashMap object returned from the TAMConnectorException.getFailed method for more details on the error. Ensure the Connector is configured to use the correct Entry Type. If the problem persists, contact IBM support.

CTGDIK411E There was an error while updating: *entry name*.

Explanation

The Connector was unable to modify an entry of the configured Entry Type.

Action

Check the HashMap object returned from the TAMConnectorException.getFailed method for more details on the error. Ensure the Connector is configured to use the correct Entry Type. If the problem persists, contact IBM support.

CTGDIK412E Could not delete entry for: *entry name*.

Explanation

The Connector was unable to delete an entry of the configured Entry Type.

Action

Ensure the Connector is configured to use the correct Entry Type. If the problem persists, contact IBM support.

CTGDIK413E Unable to interface with the TAM server. The following invalid message was retrieved by TAM while processing an exception thrown by TAM: *invalid message*.

Explanation

The Connector has tapped a TAM exception while interfacing with TAM. The message type attached to the exception message is invalid message.

Action

See the logs for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK414E Unable to interface with the TAM server. The following error message was retrieved by TAM while processing an exception thrown by TAM: *error message*.

Explanation

The Connector has tapped a TAM exception while interfacing with TAM. The message type attached to the exception message is error message.

Action

Ensure the Connector to is configured correctly, and that the TAM Server is operational. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK415E Unable to interface with the TAM server. While retrieving the cause of an exception thrown by TAM, an internal exception has occurred.

Explanation

The Connector has trapped an underlying Java Exception while attempting to find the cause for a previous TAM exception.

Action

Check the logs for details. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK416E Unable to complete the operation. The attribute *attribute name* was missing.

Explanation

The Connector was attempting an operation for a specific Entry Type and was missing an attribute.

Action

Make sure that the required attribute for the respective Entry Type is available. If the problem persists, contact IBM support.

CTGDIK417E Connector search failed. An unsupported search criteria was specified.

Explanation

The Connector was attempting to search/find with unsupported search criteria.

Action

Verify the search criteria for the respective Entry Type is valid.

CTGDIK418E Deleting policy failed. User name is not specified.

Explanation

The Connector was attempting to delete a Policy without a valid User Name.

Action

Make sure that the User Name is valid for the Policy being deleted. If the problem persists, contact IBM support.

CTGDIK419E Invalid Resource Type: *resource type*.

Explanation

The Connector was attempting an operation with an invalid resource type.

Action

Ensure the resource type is valid for the Entry Type. If the problem persists, contact IBM support.

CTGDIK420E Admin Group *group name* is reserved and cannot be deleted.

Explanation

The Connector was attempting to delete a Group that is reserved.

Action

Unreserve the Group before attempting to delete it.

CTGDIK421E Admin User *user name* is reserved and cannot be deleted.

Explanation

The Connector was attempting to delete a User that is reserved.

Action

Unreserve the User before attempting to delete it.

CTGDIK422E Error while loading the group *group name*.**Explanation**

The Connector could not load the Group specified.

Action

Confirm the Group exists in TAM. If the problem persists, contact IBM support.

CTGDIK423E No Credentials Exist for User: *user name*.**Explanation**

The Connector could not find credentials for the User specified.

Action

Confirm the User credentials exist in TAM.

CTGDIK424E Operation Code *operation code* not supported.**Explanation**

The Connector does not support the operation code specified.

Action

Change to a supported operation code.

CTGDIK425I Shutting down connection to TAM.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK426I Initializing PAdmin for application: *TAM program ID*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK427I Creating a TAM Context: *context name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK428I Retrieving data for entries with the entry type
entry type and the attribute value attribute value.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK429I The groups for the user: *group names.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK430I Importing User: *user name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK431I Adding User: *user name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK432I The groups to add: *group names*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK433I The groups to delete: *group names*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK434I Removing User: *user name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK435I The users to add: *user names*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK436I The users to delete: *user names*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK437I Removing members from Group: *group name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK438I Adding members to Group: *group name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK439I Removing Group: *group name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK440I Removing User: *user name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK441I Creating Policy for User: *user name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK442I Removing Policy for User: *user name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK443I Creating Domain: *domain name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK444I Removing Domain: *domain name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK445I Creating SS0 Credential: *credential name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK446I Deleteing SS0 Credential: *credential name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK447I Refer to Users Guide, or initialize the Connector first.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIK448E No valid value found for the following Connector Configuration Parameter: *Config Param Name*.

Explanation

The Connector was configured with a Configuration Parameter that either had no value, or the value specified was invalid.

Action

Reconfigure the Connector to use valid values for all required Configuration Parameters.

CTGDIK449E Unable to interface with the TAM server. The following invalid context message was retrieved by TAM while processing an exception thrown by TAM: *invalid context message*.

Explanation

The Connector has tapped a TAM exception while interfacing with TAM. The message type attached to the exception message is invalid context.

Action

See the logs for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDIK450E Unable to interface with the TAM server. The following unknown message type was retrieved by TAM while processing an exception thrown by TAM: *unknown message*.

Explanation

The Connector has tapped a TAM exception while interfacing with TAM. The message type attached to the exception message is unknown.

Action

See the logs for additional information on how to respond. Attempt to restart the AssemblyLine containing this Connector. If the problem persists, contact IBM support.

CTGDJI001I Listening for TCP SSL connections on port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI002I Listening for TCP connections on port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI003E The '*tcpHost*' parameter must be set to use the TCP Connector in client mode.

Explanation

The required parameter *tcpHost* was not specified in the TCP Connector. The parameter is required in client mode.

Action

Specify the *tcpHost* parameter in the Connector.

CTGDJI004I Connecting to TCP host '*hostname*' over SSL on port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI005I Connecting to TCP host '*hostname*' on port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI006I Waiting for incoming connection on port '*port number*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI007I Incoming connection established from '*IP Address*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI008E The '*tcpPort*' parameter must be set to use the TCP Connector in client mode.

Explanation

The required parameter *tcpPort* was not specified in the TCP Connector. The parameter is required in client mode.

Action

Specify the *tcpPort* parameter in the Connector.

CTGDJI009I Interrupted while waiting for incoming connection. Closing the server socket.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI101E The 'tcp.port' parameter must be set to use the TCP Server Connector.

Explanation

The required parameter tcp.port was not specified in the TCP Server Connector.

Action

Specify the tcp.port parameter in the Connector.

CTGDJI102I Exiting initialization early because Connector already initialized with a java.net.Socket object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI103I Using the provided java.net.Socket object for TCP client session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI104I Listening for TCP SSL connections on port '*port number*'. The backlog connections allowed is set to '*number of connections*' connections and client authentication is set to '*boolean*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI105I Listening for TCP connections on port '*port number*'. The backlog connections allowed is set to '*number of connections*' connections.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI106I Connector terminated by external request.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI107I Connector terminating by external request.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI108I Incoming connection established from '*IP Address*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI109I Terminate server request received.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI110I Creating dummy connection using IP Address '*IP Address*' and port '*port number*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI111W Encountered an IOException on unblocking the TCP Server Connector's server socket: *exception*

Explanation

See message.

Action

No action required.

CTGDJI112I TCP Server Connector is already terminating. Not sending termination request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJI113I Sending termination request to TCP Server Connector.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW001E Select a Solution View to delete.

Explanation

No Solution View was selected for deletion.

Action

Select at least one Solution View and click Delete.

CTGDIW002W Delete Solution View *Solution View name?*

Explanation

Confirm the deletion of Solution View. This cause all Solution View related information to be deleted.

Action

Choose OK to delete the Solution View, or CANCEL to abort.

CTGDIW003E Unable to delete Solution View *Solution View name*. This might happen if Action Manager rules are configured for this Solution View. See error logs for more details.

Explanation

The delete of Solution View failed. This might have occurred because the specified Solution View might not exist or might have been deleted by another user. Also, if Action Manager rules are configured for this Solution View, then Solution View cannot be deleted. Some other internal error could also have occurred. See the error logs for the details.

Action

If Action Manager rules are configured for this Solution View, then the Solution View cannot be deleted. In such a case, go to the Action Manager configuration screen and delete all the Action Manager rules for this Solution View and then delete the Solution View from the Manage Solution View panel.

CTGDIW004E Select a Solution View to manage.

Explanation

No Solution View was selected for Manage ACL operation.

Action

Select at least one Solution View and click Manage ACL.

CTGDIW005E Select a Solution View to modify.

Explanation

No Solution View was selected for Modify operation.

Action

Select at least one Solution View and click Modify.

CTGDIW006E The session with remote server for the Solution View could not be established.

Explanation

A session could not be established with the remote IBM Security Directory Integrator server associated with this Solution View. Editing a Solution View is not possible unless the remote IBM Security Directory Integrator server is running, and the associated Config instance is also loaded on the remote server.

Action

Check the remote server associated with this Solution View. Ensure the the remote API engine is running on the remote server. Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

CTGDIW007E The Config instance associated with the Solution View is not loaded on the server.

Explanation

Editing a Solution View is not possible unless the remote IBM Security Directory Integrator server is Running, and the associated Config instance is also loaded on the remote server. In this case, the server session was established, but the associated Solution View was not loaded on it.

Action

Check the remote server associated with this Solution View. Ensure that the required Config instance is loaded on the remote server.

CTGDIW008E The Solution View *Solution View name* already exists.

Explanation

A Solution View with the same name already exists in the Administration and Monitoring Console. Duplicate Solution View names are not allowed.

Action

Specify a unique Solution View name.

CTGDIW009E It is mandatory to select a Config instance.

Explanation

You must select at least one Config instance in order to create a Solution View.

Action

Select a Config instance. If no Config instance is visible, then select a running IBM Security Directory Integrator server which has Config instances loaded, or load the remote IBM Security Directory Integrator server with the required Config instance before proceeding with Solution View creation.

CTGDIW010E It is mandatory to select at least one AssemblyLine.

Explanation

You must select at least one AssemblyLine in order to create a Solution View.

Action

Select at least one AssemblyLine and proceed. If no AssemblyLines are visible, then select a Config instance which has AssemblyLines or load an appropriate Config instance before proceeding with Solution View creation.

CTGDIW011E Select a Health AssemblyLine or check the None checkbox.

Explanation

It is required to select one Health AssemblyLine or explicitly state that no health AssemblyLine for this Solution View. If neither is done, then the user cannot continue with Solution View creation.

Action

Select a Health AssemblyLine or check the None checkbox.

CTGDIW012I The Solution View *Solution View name* has been successfully created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW013E The Solution View could not be created. Check the logs for errors.

Explanation

Unable to create the Solution View in the Administration and Monitoring Console database. An internal error might have occurred, or an associated data element might have been deleted from the database.

Action

See the error logs. Also try creating the Solution View again.

CTGDIW014E The Config instance associated with the Solution View *Solution View name* is not loaded on the server.

Explanation

The user selected a Solution View whose associated Config instance is not loaded on the server. Managing property store of a Solution View is not possible unless the associated Config instance is loaded on the IBM Security Directory Integrator server.

Action

Load the associated Config instance on the remote server and try again.

CTGDIW015I The current Solution View has been set to:
Solution View name.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW016E Select a Config instance to reload.

Explanation

It is mandatory to select a running Config instance and click Reload. The user did not select any Config instance.

Action

Select a loaded Config instance and click Reload.

CTGDIW017I Config Instance *Config instance ID* successfully reloaded.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW018E Error occurred while reloading Config instance *Config instance ID*.

Explanation

Unable to reload the Config instance on the remote IBM Security Directory Integrator Server. This might have occurred because the remote IBM Security Directory Integrator server might no longer be running, or the remote Config instance might have been unloaded. Check the error logs for more information.

Action

Check the error logs for more information, or try again.

CTGDIW019E The Config *Config path* is not loaded on the server. Only loaded Configs can be reloaded.

Explanation

Unable to reload the Config instance on the remote IBM Security Directory Integrator Server. This occurred because the selected Config is not loaded on the remote server. Only loaded Configs can be reloaded.

Action

Select a loaded Config and click on Reload. Alternatively, select a Config that is not loaded, and click on Load.

CTGDIW020E Select a Config to load.

Explanation

It is mandatory to select a Config that is not loaded and click Load. The user did not select any Configs.

Action

Select a Config that is not loaded and click Load.

CTGDIW021E Select a Config instance to unload.

Explanation

It is mandatory to select a loaded Config instance and click Unload. The user did not select any Configs.

Action

Select a loaded Config instance and click Unload.

CTGDIW022E Error occurred while trying to unload the Config instance *Config instance ID*.

Explanation

An error occurred while trying to unload the Config instance on the remote server. This might have occurred because the Administration and Monitoring Console was unable to contact the remote server or the Config instance might not be loaded on the remote server. See the error logs for more details.

Action

See the error logs for more details, or try again.

CTGDIW023E The Config *Config instance ID* is not loaded on the server. Only a loaded Config can be unloaded.

Explanation

The user tried to unload a Config that is not loaded on server. Only loaded Configs can be unloaded.

Action

See the error logs for more details, or try again by selecting a loaded Config.

CTGDIW024E Error occurred while trying to load the Config *Config path* .

Explanation

An error occurred while trying to load the Config on the remote server. This might have occurred because the Administration and Monitoring Console was unable to contact the remote server or the Config path might have changed. It can also occur if the specified Config is password protected, and no password was specified in the Config Password field, or an incorrect password was specified in the Config Password field. It might also occur if the selected file is not a valid IBM Security Directory Integrator Config file. See the error logs for more details.

Action

Ensure that the remote Config is valid and that the path is correct. Also ensure that for password protected Configs, the correct password is supplied in the Config Password field. See the error logs for more details, or try again.

CTGDIW025E The Config *Config instance ID* is already loaded on the server.

Explanation

Cannot load an already loaded Config. Only Configs that are not loaded can be loaded.

Action

Select a Config that is not loaded to perform the Load operation.

CTGDIW026E Select a group.

Explanation

A group must be selected to assign a role. If no groups exist in the list, then create groups first and then assign roles.

Action

Select an existing group, or create new ones before assigning roles.

CTGDIW027E Select a role.

Explanation

A group must be assigned a role.

Action

Select a role.

CTGDIW028E Unable to set role for group *group name*

Explanation

Unable to set the role for the user requested group. This might have occurred because the associated Config instance might have been deleted or renamed, or the group might have been deleted or renamed, or an internal error occurred. See the error logs for more details.

Action

See the error logs, or try again.

CTGDIW029I The role for group *group name* has been successfully updated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW030E Select a user.

Explanation

A user must be selected to assign a role. If no user exist in the list, then create users first and then assign roles.

Action

Select an existing user, or create new ones before assigning roles.

CTGDIW031E Select a role.

Explanation

A user must be assigned a role.

Action

Select a role.

CTGDIW032E Unable to set role for user *user name*

Explanation

Unable to set the role for the requested user. This might have occurred because the associated Config instance might have been deleted or renamed, or the user might have been deleted or renamed, or an internal error occurred. See the error logs for more details.

Action

See the error logs, or try again.

CTGDIW033I The role for user *user name* has been successfully updated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW034E Select a Health AssemblyLine or check the None checkbox.

Explanation

It is required to select one Health AssemblyLine or explicitly specify no health AssemblyLine for this Solution View. The user cannot continue with Solution View modify until a health AssemblyLine is selected, or no health AssemblyLine is specified.

Action

Select a Health AssemblyLine or check the None checkbox.

CTGDIW035I The Solution View has been successfully updated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW036E The Solution View could not be updated. Check the logs for errors.

Explanation

An error occurred while updating the Solution View details in database. This might have occurred because another user modified or deleted the Solution View.

Action

Check the error logs or try editing the Solution View again.

CTGDIW037E It is mandatory to select at least one AssemblyLine.

Explanation

A Solution View must have at least one AssemblyLine.

Action

Select at least one AssemblyLine and proceed. If no AssemblyLines are visible, then select a Config instance which has AssemblyLines or load an appropriate Config instance before proceeding with Solution View editing.

CTGDIW038E Select members to remove access.

Explanation

The user did not select any members whose access to the particular Solution View must be removed. It is mandatory to select at least one member and click Remove.

Action

Select at least one member and click Remove.

CTGDIW039E Unable to remove members. See error logs for details.

Explanation

An internal error occurred because of which the access of the selected members could not be removed. This might have occurred because the selected Solution View might have been deleted or the database might have been in an inconsistent state.

Action

See error logs or try again.

CTGDIW040E Select a server to delete.

Explanation

The error occurred because the user clicked the Delete without selecting a server from the list. The user needs to specify which server to delete.

Action

Select a IBM Security Directory Integrator server from the list and click Delete.

CTGDIW041W Deleting a server will also delete all Solution Views and other information associated with this server. Do you really want to delete the server *server name* ?

Explanation

Deleting a server results in deletion of all Solution Views associated with this server from the Administration and Monitoring Console. Any information associated with those Solution Views will also be deleted to maintain database referential consistency. The deletion of the server information is permanent.

Action

If you want to delete the server, click OK, otherwise click Cancel.

CTGDIW042E Unable to delete server *server name*. Check the logs for errors.

Explanation

An internal error occurred because of which the server could not be deleted. This might have occurred because another process might have modified or already deleted the server. Check the error logs for details.

Action

Check the error logs or try again.

CTGDIW043E Update failed for property *property name*.

Explanation

An internal error occurred and the specified property value could not be updated. This might have occurred because another process might have modified or already deleted the property. Check the error logs for details.

Action

Check the error logs or try again.

CTGDIW044E Unable to add property *property name*.

Explanation

An internal error occurred because of which the specified property could not be added. Check the error logs for details.

Action

Check the error logs or try again.

CTGDIW045E Select a property to delete.

Explanation

The user did not select any property and hit delete. It is mandatory to select a property before clicking Delete.

Action

Select a property from the list and click Delete.

CTGDIW046W Delete property *property name*?

Explanation

Confirmation from user about whether he really wishes to delete the specified property.

Action

If you want to delete the property, click OK, otherwise click Cancel.

CTGDIW047E Select a property to modify.

Explanation

The user clicked Modify without selecting a property. Select a property before clicking Modify.

Action

Select a property from the list and click Modify.

CTGDIW048E Select a property to modify.

Explanation

The user did not select any property and hit Modify. It is mandatory to select a property before clicking Modify.

Action

Select a property from the list and click Modify.

CTGDIW049E Select a property to delete.

Explanation

The user clicked Delete without selecting a property. Select a property before clicking Delete.

Action

Select a property from the list and click Delete.

CTGDIW050W Delete property *property name*?

Explanation

Confirm that you want to delete the specified property.

Action

If you want to delete the property, click OK, otherwise click Cancel.

CTGDIW051E Select a property to modify.

Explanation

The user did not select any property and click Modify. It is mandatory to select a property before clicking Modify.

Action

Select a property from the list and click Modify.

CTGDIW052E Select a property to delete.

Explanation

The user clicked Delete without selecting a property. Select a property before clicking Delete.

Action

Select a property from the list and click Delete.

CTGDIW053W Delete property *property name*?

Explanation

Confirm that you want to delete the specified property.

Action

If you want to delete the property, click OK, otherwise click Cancel.

CTGDIW054E Select a property to modify.

Explanation

The user clicked Modify without selecting a property. Select a property before clicking Modify.

Action

Select a property from the list and click Modify.

CTGDIW055E Select a property to delete.

Explanation

The user clicked Delete without selecting a property. Select a property before clicking Delete.

Action

Select a property from the list and click Delete.

CTGDIW056W Delete property *property name*?

Explanation

Confirm that you want to delete the specified property.

Action

If you want to delete the property, click OK, otherwise click Cancel.

CTGDIW057E Select a property to modify.

Explanation

The user clicked Modify without selecting a property. Select a property before clicking Modify.

Action

Select a property from the list and click Modify.

CTGDIW058E Select a property to delete.

Explanation

The user clicked Delete without selecting a property. Select a property before clicking Delete.

Action

Select a property from the list and click Delete.

CTGDIW059W Delete property *property name*?

Explanation

Confirm you want to delete the specified property.

Action

If you want to delete the property, click OK, otherwise click Cancel.

CTGDIW060E The current password for user *user name* is incorrectly entered.

Explanation

The user supplied incorrect value of the current password. The current password must be supplied correctly to change the password.

Action

Specify the current user password.

CTGDIW061E The new passwords do not match.

Explanation

To change the password, the new password and confirm password values should be the same. This is to ensure that the user is sure of what the new password is.

Action

Specify the same password in the New Password and Confirm Password fields.

CTGDIW062E Unable to change password.

Explanation

An internal error occurred which prevented the change of password. See the error logs for more information.

Action

See the error logs or try again.

CTGDIW063E Unable to change password. User *user name* not found.

Explanation

An internal error occurred which prevented the change of the password. Most likely, this user was deleted and hence the password could not be changed.

Action

See the error logs or try again.

CTGDIW064I Password for user *user name* changed successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW065E Group already exists: *group name*

Explanation

The user entered the name of a group that already exists. Duplicate groups are not allowed.

Action

Enter a unique group name and try again.

CTGDIW066E Illegal character encountered in group name.

Explanation

The user entered an illegal character (for example, single quotes) in the group name.

Action

Enter a unique group name without any illegal characters.

CTGDIW067E Unable to add group. Check the logs for errors.

Explanation

An internal error prevented the creation of the specified group. Check the error logs for more details.

Action

Check the error logs or try again.

CTGDIW068E No users selected.**Explanation**

No users were selected to be added to this group as members. At least one user has to be selected.

Action

Select at least one user to become a member, or click Cancel.

CTGDIW069E Group *group name* does not exist.**Explanation**

Members could not be added to the group because the group does not exist any more. Another user might have deleted this group. Check the logs for more details.

Action

Check the error logs or try again.

CTGDIW070E Select a group to modify.**Explanation**

The user clicked Modify without selecting a group. Select a group before clicking Modify.

Action

Select a group from the list and click Modify.

CTGDIW071E Select a group to delete.**Explanation**

The user clicked Delete without selecting a group. Select a group before clicking Delete.

Action

Select a group from the list and click Delete.

CTGDIW072W Delete group *group name*?**Explanation**

Confirm the deletion of group. This cause all group related information to be deleted.

Action

Choose OK to delete the group, or CANCEL to abort.

CTGDIW073E Group *group name* does not exist.**Explanation**

The group does not exist any more. Another user might have deleted this group. Check the logs for more details.

Action

Check the error logs or try again.

CTGDIW074E Group *group name* does not exist.**Explanation**

The group could not be updated because it no longer exists. Another user might have deleted this group. Check the error logs for details.

Action

Check the error logs or try again.

CTGDIW075E No members selected.**Explanation**

No members were selected to be deleted from this group. At least one user has to be selected.

Action

Select at least one user for deleting.

CTGDIW076W Remove selected members from group?**Explanation**

Confirm the user wants to remove the selected members from the group.

Action

If you want to remove the members, click OK, otherwise click Cancel.

CTGDIW077E Group *group name* does not exist.**Explanation**

The group does not exist any more. Another user might have deleted this group. Check the logs for more details.

Action

Check the error logs or try again.

CTGDIW078E Passwords do not match.

Explanation

To add a new user, the new password and confirm password values should be the same. This is to ensure that the user is sure of what the new password is.

Action

Specify the exact same password in the New Password and Confirm Password fields.

CTGDIW079E User already exists: *user name*

Explanation

You entered the name of a user that already exists. Duplicate users are not allowed.

Action

Enter a unique user name and try again.

CTGDIW080E Illegal character encountered in user name.

Explanation

You entered an illegal character (for example single quotes) in the user name.

Action

Enter a unique user name without any illegal characters.

CTGDIW081E Unable to add user. Check the logs for errors.

Explanation

An internal error prevented the creation of the specified user. Check the error logs for more details.

Action

Check the error logs or try again.

CTGDIW082E Select a user to modify.

Explanation

The user clicked Modify without selecting a user. Select a user before clicking Modify.

Action

Select a user from the list and click Modify.

CTGDIW083E Select a user to delete.

Explanation

The user clicked Delete without selecting a user. Select a user before clicking Delete.

Action

Select a user from the list and click Delete.

CTGDIW084W Delete user *user name*?

Explanation

Confirm the deletion of user. This cause all user related information to be deleted.

Action

Choose OK to delete the user, or CANCEL to abort.

CTGDIW085E User *user name* does not exist.

Explanation

The user does not exist any more. Another operator might have deleted this user. Check the logs for more details.

Action

Check the error logs or try again.

CTGDIW086E Passwords do not match.

Explanation

For a user, the new password and confirm password values should be the same. This is to ensure that the user is sure of what the new password is.

Action

Specify the exact same password in the New Password and Confirm Password fields.

CTGDIW087E User *user name* does not exist.

Explanation

The user does not exist any more. Another operator might have deleted this user. Check the logs for more details.

Action

Check the error logs or try again.

CTGDIW088E Unable to modify user. Check the logs for errors.

Explanation

An internal error occurred which prevented the user from being updated. Check the logs for error.

Action

Check the error logs or try again.

CTGDIW089E SSL Key store file is not specified.

Explanation

The user specified SSL key store related properties without specifying the key store file.

Action

Either delete the SSL key store properties(such as password,etc) or specify the key store file name.

CTGDIW090E SSL Trust store file is not specified.

Explanation

The user specified SSL trust store related properties, without specifying the trust store file.

Action

Either delete the SSL trust store properties(such as password,etc) or specify the trust store file name.

CTGDIW091E Unable to add the server. The IBM Security Directory Integrator Server ID *Server ID* duplicates the Server ID already assigned to another server having the same hostname and port number.

Explanation

The attributes Hostname, Server ID and Port should be unique for each IBM Security Directory Integrator server entry. A new IBM Security Directory Integrator Server cannot be added if this constraint is violated.

Action

Change the Server ID of the server that need to be added or delete the existing entry in the Administration and Monitoring Console and try again. The Server ID can be changed by editing the global.properties or solution.properties and by setting the com.ibm.di.server.id property.

CTGDIW092E Unable to establish connection with the server.

Explanation

Unable to establish connection with the server. This might be because the server is down, or the Remote Server API engine is not running on the remote server or the connection settings to the server are incorrect.

Action

Verify the server is running, and the Remote Server API engine is also running. Also confirm if the hostname, port and authentication details are correct.

CTGDIW093I Connection successfully established.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW094E Select a server to shutdown.

Explanation

The error occurred because the user clicked the Shutdown without selecting a server from the list. The user needs to specify which server to shutdown.

Action

Select a IBM Security Directory Integrator server from the list and click Shutdown.

CTGDIW095W If this server is shut down, then all users connected or working with this server will get disconnected. Also, any AssemblyLines or Config instances on this server will be shut down. Do you really want to shutdown the server *server name*?

Explanation

Shutting down a IBM Security Directory Integrator server results in the unloading of all Config instances and AssemblyLines running on this server.

Action

If you want to shut down the server, click OK, otherwise click Cancel.

CTGDIW096E Unable to shutdown server *server name*.

Explanation

An error occurred and the server could not be shutdown. Either the session could not be established, or there was a server API failure. Check the logs for errors.

Action

Check the logs for errors, or try again.

CTGDIW097E The Config instance associated with the Solution View *Solution View name* is not loaded on the server.

Explanation

The user selected a Solution View whose associated Config instance is not loaded on the server. Generating a Solution View report is not possible unless the associated Config instance is loaded on the IBM Security Directory Integrator server.

Action

Load the associated Config instance on the remote server and try again.

CTGDIW098E Select an AssemblyLine to start.

Explanation

The user clicked on Start AssemblyLine without selecting any AssemblyLine. It is mandatory to specify which AssemblyLine to start.

Action

Select an AssemblyLine and click Start AL.

CTGDIW099E The AssemblyLine *AssemblyLine name* is already running.

Explanation

The user chose to start an AssemblyLine that is already running.

Action

Select a stopped AssemblyLine and clicked Start AL.

CTGDIW100E The AssemblyLine *AssemblyLine name* could not be started. Check the logs for errors.

Explanation

Due to an internal error, or remote IBM Security Directory Integrator server error, the starting of the specified AssemblyLine failed.

Action

Check the error logs or try again.

CTGDIW101E Select an AssemblyLine to stop.

Explanation

The user clicked on Stop AssemblyLine without selecting any AssemblyLine. It is mandatory to specify which AssemblyLine to stop.

Action

Select a running AssemblyLine and click Stop AL.

CTGDIW102E The AssemblyLine *AssemblyLine name* is already stopped.

Explanation

The user chose to stop an AssemblyLine that is already stopped.

Action

Select a running AssemblyLine and click Stop AL.

CTGDIW103W Stop AssemblyLine *AssemblyLine name*?

Explanation

Confirm stopping of the AssemblyLine.

Action

If you want to stop the selected AssemblyLine click Ok otherwise click Cancel.

CTGDIW104E The AssemblyLine *AssemblyLine name* could not be stopped. Check the logs for errors.

Explanation

Due to an internal error the specified AssemblyLine could not be stopped on the remote IBM Security Directory Integrator server.

Action

Check the error logs or try again.

CTGDIW105E Select an AssemblyLine to view component information.

Explanation

The user clicked View Components without selecting a AssemblyLine. Select a AssemblyLine before clicking View Components.

Action

Select an AssemblyLine and click View Components.

CTGDIW106E Unable to obtain Connector information for AssemblyLine *AssemblyLine name*.

Explanation

Unable to obtain handle to AssemblyLine object. See error logs for details.

Action

Check the Config containing this AssemblyLine is loaded on the server, and try again.

CTGDIW107E Select a property to modify.

Explanation

The user did not select any property and click Modify. It is mandatory to select a property before clicking Modify.

Action

Select a property from the list and click Modify.

CTGDIW108E Select a property to delete.

Explanation

The user clicked Delete without selecting a property. Select a property before clicking Delete.

Action

Select a property from the list and click Delete.

CTGDIW109W Delete property *property name*?

Explanation

Confirmation the user wants to delete the specified property.

Action

If you want to delete the property, click OK, otherwise click Cancel.

CTGDIW110E Select a Solution View to view its server information.

Explanation

No Solution View was selected for Server Information task.

Action

Select at least one Solution View and click IBM Security Directory Integrator Server Information menu option.

CTGDIW111E The session with remote server for the Solution View could not be established.

Explanation

A session could not be established with the remote IBM Security Directory Integrator server associated with this Solution View. Cannot view Server information if the server is not running.

Action

Check the remote server associated with this Solution View. Ensure the the remote API engine is running on the remote server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

CTGDIW112I Server shutdown successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW113E Could not shutdown server.

Explanation

The server could not be shutdown. See the error logs for more details.

Action

Check the error logs or try again.

CTGDIW114E Select a Solution View to view its details.

Explanation

No Solution View was selected for viewing its monitor details.

Action

Select at least one Solution View and click Solution View Details menu option.

CTGDIW115W The Config instance associated with the Solution View *Solution View name* is not loaded on the server.

Explanation

The currently selected Solution View is not loaded on the server. This is not an error, but implies that any AssemblyLine associated with this Solution View would also not be running on the server. This might also be because the Administration and Monitoring Console was not able to establish a connection with the remote

IBM Security Directory Integrator Server (because the server is unreachable, or the remote server API engine is not reachable).

Action

This is just for operator information, and does not in any way indicate any error, or unusual condition. You need not take any action, unless you determine the Solution View should have been in a running condition. In that case, the you may choose to load the Config first, or check the logs for errors, or check the Action Manager for any error runs, or view the tombstones for last run statistics, or verify the IBM Security Directory Integrator server itself is running and the remote Server API engine is also running.

CTGDIW116E Select an AssemblyLine to view Tombstones.

Explanation

The user clicked View Tombstones without selecting any AssemblyLine.

Action

Select an AssemblyLine and click View Tombstones.

CTGDIW117E Could not obtain an instance of Tombstone Manager. It might not be running on the remote server.

Explanation

The Administration and Monitoring Console was unable to obtain a connection to the Tombstone Manager on the remote server.

Action

Verify the tombstone manager is configured to be running. Check the error logs for the exact error. Start the tombstone manager on the remote IBM Security Directory Integrator server and try again.

CTGDIW118E Select a log file to view.

Explanation

The user clicked on View without selecting a log file.

Action

Select a log file to view.

CTGDIW119E Unable to connect to IBM Security Directory Integrator server associated with Solution View *Solution View name*. Cannot clean up logs for this Solution View.

Explanation

The Administration and Monitoring Console was unable to connect to the server associated with the Solution View. Logs cannot be deleted for Solution View if the server is not running.

Action

Ensure that the remote IBM Security Directory Integrator server is up and running, with the Remote Server API engine on. Also check the settings of the server in the Administration and Monitoring Console to ensure that all information required to make a connection by the Administration and Monitoring Console is correctly made available.

CTGDIW120E There were errors while cleaning up logs for Solution view *Solution View name*.

Explanation

An errors occurred while firing cleanup logs on IBM Security Directory Integrator server. Check the error logs for more details.

Action

View the error logs for more details, or try again.

CTGDIW121I Cleanup logs for Solution View *Solution View name* completed successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW122E An error occurred while saving your preferences.

Explanation

An errors occurred while saving your preferences. See the error logs for details.

Action

View the error logs for more details, or try again.

CTGDIW123I Your preferences have been successfully saved.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW124E Unable to create a rule in database. See error logs for details.

Explanation

Unable to create an entry in the Administration and Monitoring Console database for this rule. See the error logs for more information.

Action

View the error logs for more details, or try again.

CTGDIW125E Unable to create/update rule in database. See error logs for details.

Explanation

Unable to update the rule and trigger information in the Administration and Monitoring Console database. See the error logs for more information.

Action

View the error logs for more details, or try again.

CTGDIW126E No Property name specified for trigger.

Explanation

The property name is mandatory for the On Property trigger. The current Solution View has no properties chosen, and therefore the Property Name field is empty.

Action

Modify the Solution View to contain at least one property so that the On Property trigger can be specified. Otherwise, choose a different trigger.

CTGDIW127E No Rule selected for delete.

Explanation

The user did not select any rule and click Delete. It is mandatory to select a rule before clicking Delete.

Action

Select a rule from the table to delete.

CTGDIW128W Deleting a rule will delete all information associated with this rule, including the run history of this rule from database. Do you really want to delete the *rule name* rule?

Explanation

Confirm the deletion of the selected Action Manager Rule. The user may choose to Disable rather than Delete the rule.

Action

If you want to delete the rule, click OK, otherwise click Cancel. If the operator wants to keep the Rule in database, but not run the rule, Disable the rule, instead of Deleting the rule.

CTGDIW129E Unable to delete the rule from database. Ensure that some other rule is not associated with this rule. Also, check the error logs.

Explanation

Unable to delete the rule from the Administration and Monitoring Console database. This might happen because another rule depends on this rule (when an action is configured to execute, or enable/disable this rule). See the error logs for more information.

Action

View the error logs for more details, or try again. Ensure that there is no other rule, that executes or enables/disables this rule in one of its actions. If that is the case, then delete that action or rule before deleting the current rule.

CTGDIW130E It is mandatory to select at least one Action.

Explanation

The user clicked OK without selecting any action.

Action

Select an action on the page, and click OK, otherwise click CANCEL.

CTGDIW131E For the Copy property action, the source and destination properties are the same: *property name*. Select different property names.

Explanation

For the Copy Property Action, the user chose the same property names for Copy From and Copy To. These must be different properties.

Action

Select different properties in Copy property value action, or clear the action.

CTGDIW132E One or more actions could not be stored. See the logs for errors.

Explanation

One or more actions could not be stored in database. See the error logs for details, and the list of actions in the previous page, to see the actions which were stored.

Action

See the error logs, or try again.

CTGDIW133E Select an Action to move.

Explanation

The user chose to change the execution order of an action, without selecting any actions from the list.

Action

Select an action and then choose to move it up or down the order.

CTGDIW134E Unable to move the chosen action. See logs for more information.

Explanation

An error occurred while performing the move operation. See the error logs for details.

Action

See the error logs, or try again.

CTGDIW135E Select an Action to delete.

Explanation

The user chose to delete an action, without selecting any actions from the list.

Action

Select an action and then choose to delete it.

CTGDIW136E Unable to delete the chosen action. See logs for more information.

Explanation

An error occurred while performing the delete operation. See the error logs for details.

Action

See the error logs, or try again.

CTGDIW137W Delete action *action name*?

Explanation

Confirm deletion of the selected Action.

Action

If you want to delete the action, click OK, otherwise click Cancel.

CTGDIW138E Either an event type or an event source must be specified.

Explanation

For the received event trigger, one of the two - event type or event source - must be specified. The user did not specify either.

Action

Specify either the event type or the event source. Otherwise select a different trigger condition. See the `com.ibm.di.api.remote.Session.addListener()` API for more details.

CTGDIW139E Value for the property has not been specified in trigger.

Explanation

For the On property trigger, the value field is mandatory. The user did not specify this value.

Action

Specify the property value. Otherwise select a different trigger condition.

CTGDIW140E Attribute name or value not specified.

Explanation

For the query AssemblyLine result trigger, the Attribute name and Value fields are mandatory. The user did not specify the attribute name or the attribute value.

Action

Specify the attribute name and the value. Otherwise select a different trigger condition.

CTGDIW141E Illegal interval value specified. Value must be greater than zero.

Explanation

For the Time since last execution trigger, the interval value must be greater than zero. The user entered an illegal value, or did not modify the value.

Action

Specify a valid interval value.

CTGDIW142E Insufficient rights to perform Solution View management for the selected Solution View.

Explanation

The user chose to perform a Solution View modification with insufficient rights for the chosen Solution View. The user must have Config admin privilege to perform

this operation, or must be the console administrator.

Action

Select an authorized Solution View, or login using a user id with appropriate authority. Alternatively, login as Console Administrator and then try again.

CTGDIW143E Insufficient rights to perform Config administration (load/unload/reload) task for the selected Config instance *Config instance*.

Explanation

The user chose to perform a Config load, unload or reload without having Config admin privilege to any associated Solution View. Only when a user has Config admin privilege to a particular Solution View which is associated with the chosen Config instance, can the user perform the load, unload or reload operation for that Config instance. Otherwise, the user must be the console administrator.

Action

Select an authorized Config instance, or login using a user id with appropriate authority. Alternatively, login as Console Administrator and then try again.

CTGDIW144E Insufficient rights to view details for Solution View *Solution View name*.

Explanation

The user chose to view the details of a Solution View without having any rights associated with the Solution View. The user must have some rights associated (whether reader, execute, admin or Config_admin) for the chosen Solution View. Otherwise, the user must be the console administrator.

Action

Select an authorized Solution View, or login using a user id with appropriate authority. Alternatively, login as Console Administrator and then try again.

CTGDIW145E Insufficient rights to view server information for Solution View *Solution View name*.

Explanation

The user chose to view the server information of a Solution View without having any rights associated with the Solution View. The user must have some rights associated (whether reader, execute, admin or Config_admin) for the chosen Solution View. Otherwise, the user must be the console administrator.

Action

Select an authorized Solution View, or login using a user id with appropriate authority. Alternatively, login as Console Administrator and then try again.

CTGDIW146I The Administration and Monitoring Console has been set up for LDAP Authentication. User and Group addition (or modification) is not supported via the Administration and Monitoring Console for external LDAP servers.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW147E Illegal value specified for Action Manager Log Rotate rate (days). Minimum is 1 day.

Explanation

The Action Manager Log rotate rate is used to delete logs older than the specified number of days. This value must be a positive integer greater than or equal to 1.

Action

Enter a valid value satisfying the above criteria for Action Manager Log Rotate rate (in days).

CTGDIW148E Select an Action to modify.

Explanation

The user chose to modify an action, without selecting any actions from the list.

Action

Select an action and then choose to modify it.

CTGDIW149E The action could not be updated. See the logs for errors.

Explanation

The action information could not be updated in database. See the error logs for details, and the list of actions in previous page, to see the ones which successfully got stored.

Action

See the error logs, or try again.

CTGDIW150E No Rule selected for modify.

Explanation

The user did not select any rule and clicked Modify. It is mandatory to specify which rule to modify.

Action

Select a rule from the table to modify.

CTGDIW151E The Action Manager Rule status could not be updated. See the logs for errors.

Explanation

The Action Manager Rule status could not be updated in database. See the error logs for details.

Action

See the error logs, or try again.

CTGDIW153I Instance of AMConfigManager class created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW154I In createConfigViewMethod(). Parameters received: Solution View Name: *Solution view name* Solution View Desc: *description* Server ID: *server ID* Exposed AssemblyLines: *list of AssemblyLines* Is Health AssemblyLine specified: *boolean* Selected Health AssemblyLine: *Health AssemblyLine name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW155E Unable to insert into CONFIG_VIEW_MASTER table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW156E Unable to obtain CV_ID (primary key) value for Solution view *Solution view name*

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW157E Unable to insert into CONFIG_VIEW_AL_DETAILS table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW158E Unable to insert into CONFIG_VIEW_HEALTH_AL_DETAILS table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW159I In updateConfigView() method. Parameters received: Solution View ID: *Solution view ID* Exposed AssemblyLines: *list of AssemblyLines* Is Health AssemblyLine specified: *boolean* Selected Health AssemblyLine: *Health AssemblyLine name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW160I Deleting AssemblyLine details.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW161I Deleting IBM Security Directory Integrator Properties.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW162I Deleting Health AssemblyLine details.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW163I Insert into CONFIG_VIEW_AL_DETAILS table the exposed AssemblyLines.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW164E Unable to insert into CONFIG_VIEW_HEALTH_AL_DETAILS table in database.**Explanation**

See message. The Administration and Monitoring Console encountered an internal database error while updating a Solution View.

Action

See the accompanying exception for more details. Try again.

**CTGDIW165E Unable to insert into
CONFIG_VIEW_HEALTH_AL_DETAILS table in database.**

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while updating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW166I Instance of AMCTDIServerManager class created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIW167E Unable to delete server from TDI_SERVER_MASTER
table from database.**

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while attempting to delete a IBM Security Directory Integrator server entry from database.

Action

See the accompanying exception for more details. Try again.

**CTGDIW168W Unable to set the amc.session.timeout value.
Value obtained from amc.properties file: *session timeout
value.***

Explanation

The Administration and Monitoring Console encountered an error while setting the Administration and Monitoring Console session timeout value. This may have happened because the session timeout was not specified correctly.

Action

Check the amc.properties file for the value of amc.session.timeout variable.

CTGDIW169W Unable to set the monitor.refresh.rate value. Value obtained from amc.properties file: *monitor refresh rate*.

Explanation

The Administration and Monitoring Console encountered an error while setting the Administration and Monitoring Console monitor.refresh.rate. This may have happened because the refresh rate was not specified correctly.

Action

Check the amc.properties file for the value of monitor.refresh.rate variable.

CTGDIW170W Unable to determine the monitor.startup value. Value obtained from amc.properties file: *boolean*.

Explanation

The Administration and Monitoring Console encountered an error while setting the Administration and Monitoring Console monitor.startup value. This may have happened because the boolean value was not specified correctly.

Action

Check the amc.properties file for the value of monitor.startup variable. It must be a boolean indicating whether monior page will be startup page or not.

CTGDIW171E An error occurred while attempting to read the amc.properties file.

Explanation

See message.

Action

Check the location of amc.properties file. See the accompanying exception trace. Ensure that the file is not corrupted / truncated.

CTGDIW172E An error occurred while attempting to read the amc.properties file.

Explanation

See message.

Action

Check the location of amc.properties file. See the accompanying exception trace. Ensure that the file is not corrupted / truncated.

CTGDIW173E An error occurred while attempting to read the amc.properties file.

Explanation

See message.

Action

Check the location of amc.properties file. See the accompanying exception trace. Ensure that the file is not corrupted / truncated.

CTGDIW174E An error occurred while attempting to read the amc.properties file.

Explanation

See message.

Action

Check the location of amc.properties file. See the accompanying exception trace. Ensure that the file is not corrupted / truncated.

CTGDIW175E An error occurred while attempting to write to the amc.properties file.

Explanation

See message.

Action

Check that the amc.properties file is not locked by another application. See the accompanying exception trace.

**CTGDIW176E Unable to clear logs for AssemblyLine
*AssemblyLine name in Config Config.***

Explanation

The Administration and Monitoring Console was unable to clean log files associated with the above mentioned AssemblyLine and Config.

Action

See the accompanying exception trace. Also check the remote Config logs. Try again.

**CTGDIW177E Unable to clear logs for AssemblyLine
*AssemblyLine name in Config Config.***

Explanation

The Administration and Monitoring Console was unable to clean log files associated with the above mentioned AssemblyLine and Config.

Action

See the accompanying exception trace. Also check the remote Config logs. Try again.

CTGDIW178E Unable to get system log for Solution view: *Solution View ID*

Explanation

The Administration and Monitoring Console was unable to obtain a handle to the System Log from the remote server API for the above mentioned Solution view. For this reason, the Cleanup log functionality was not completed.

Action

See the accompanying exception trace. Also check the remote Config logs. Try again.

CTGDIW179W Unable to get status of Action Manger Rules for Solution view id: *Solution View ID*

Explanation

Due to some internal error, the Administration and Monitoring Console was unable to get rule status information from the AM_RUN_HISTORY table in database.

Action

See the accompanying exception trace. Try again.

CTGDIW180E Unable to update AM_RULES_MASTER while trying to update status.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to update Action Manager rule status information in the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW181E Unable to update AM_RULES_MASTER while trying to update status.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to update Action Manager rule status information in the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW182E Unable to add Action Manager rule into database. Rule Name: *Rule Name* Rule Description: *Description* Solution View ID: *Solution View ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to add Action Manager rule information in the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW183E Unable to obtain the AM_ID (primary key) for the recently added rule.

Explanation

Most probably, due to an internal database error the Administration and Monitoring Console was unable to obtain the ID for the recently added Action Manager rule.

Action

See the accompanying exception trace. Try again.

CTGDIW184E Unable to add Action Manager rule into database. Rule Name: *Rule Name* Rule Description: *Description* Solution View ID: *Solution View ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to add Action Manager rule information in the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW185E Unable to read Action Manager rule from AM_RULES_MASTER table for rule: *Rule Name*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to read Action Manager rule information from the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW186E No rows were updated in AM_RULES_MASTER while trying to update trigger type.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to update the Action Manager trigger type information in the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW187E No rows were updated in AM_RULES_MASTER while trying to update trigger type.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to update the Action Manager trigger type information in the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW188E Unable to read Action Manager rule from AM_RULES_MASTER table for rule: *Rule ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to read Action Manager rule information from the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW189E No rows were updated in AM_RULES_MASTER while trying to update Rule name: *Rule Name* Rule Description: *Description* Trigger type: *Trigger type*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to update the Action Manager information in the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW190E Unable to insert data into trigger configuration tables.

Explanation

Due to an internal error, the Administration and Monitoring Console was unable to insert information into Action Manager Trigger tables.

Action

See the accompanying exception trace. Try again.

CTGDIW191E Unable to store rule or trigger information.

Explanation

Due to an internal error, the Administration and Monitoring Console was unable to store rule or trigger into Action Manager related tables.

Action

See the accompanying exception trace. Try again.

CTGDIW192E Unable to store rule or trigger information.

Some error occurred. The parameters passed to code were:

Rule ID: *Rule ID* **Rule Name:** *Rule Name* **Rule Description:**

Description **Trigger Type:** *Trigger Type* **Parameter 1:***value*

Parameter 2:*value* **Parameter 3:** *value* **Parameter 4:** *value*

Explanation

Due to an internal error, the Administration and Monitoring Console was unable to store rule or trigger into Action Manager related tables.

Action

See the accompanying exception trace. Try again.

CTGDIW193E Unable to Delete rule: *Rule ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to delete Action Manager rule information from the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW194E Some error occurred while attempting to delete rule: *Rule ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to delete Action Manager rule information from the AM_RULES_MASTER table.

Action

See the accompanying exception trace. Try again.

CTGDIW195E Unable to store Action information. Some error occurred. The parameters passed to code were: Rule ID: *Rule ID* Action Type: *Action Type* Parameter 1:*value* Parameter 2:*value* Parameter 3: *value* Parameter 4: *value*

Explanation

Due to an internal error, the Administration and Monitoring Console was unable to store action information in database.

Action

See the accompanying exception trace. Try again.

CTGDIW196E Unable to read action information for rule: *Rule ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to read action information for the specified rule.

Action

See the accompanying exception trace. Try again.

CTGDIW197E Unable to modify execution order of specified action.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to modify the execution order of the specified action.

Action

See the accompanying exception trace. Try again.

CTGDIW198E Unable to modify execution order of specified action. The parameters passed were: Rule ID: *Rule ID* Direction: *Direction* Action ID: *Action ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to modify the execution order of the specified action.

Action

See the accompanying exception trace. Try again.

CTGDIW199E Unable to delete the specified action. The parameters passed were: Rule ID: *Rule ID* Action ID: *Action ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to delete the specified action.

Action

See the accompanying exception trace. Try again.

CTGDIW200E Unable to insert row into AM_UPDATE_DETAILS table.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to make an entry in the AM_UPDATE_DETAILS table. This table is used by Action Manager to monitor real-time updates to rules.

Action

See the accompanying exception trace. Try again.

CTGDIW201E Unable to obtain action details for Rule: *Rule ID* and Action: *Action ID*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to obtain action details for the specified Rule and Action.

Action

See the accompanying exception trace. Try again.

CTGDIW202E Unable to obtain rule details for rule: *Rule ID*

Explanation

Due to an internal error, the Administration and Monitoring Console was unable to obtain rule details.

Action

See the accompanying exception trace. Try again.

CTGDIW203E Error while obtaining Solution View Status.

Explanation

Due to an internal error, the Administration and Monitoring Console was unable to obtain the status of Solution View.

Action

See the accompanying exception trace. Try again.

CTGDIW204E Error while obtaining status of AssemblyLines.

Explanation

Due to a IBM Security Directory Integrator server API error, the Administration and Monitoring Console was unable to determine the AssemblyLine details. This may occur if the log4j jar file, or some other jars are not present in the the Administration and Monitoring Console classpath or incompatible libraries are present in the Administration and Monitoring Console (or Remote IBM Security Directory Integrator server).

Action

See the accompanying exception trace. Also check the version of the remote IBM Security Directory Integrator server. Ensure that correct library files (jars) are present in the Administration and Monitoring Console and remote IBM Security Directory Integrator server's classpath.

CTGDIW205E Unable to store user preferences for user: *user name*

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to store the user's preferences.

Action

See the accompanying exception trace. Try again.

CTGDIW206E Unable to get Action Manager Details for Solution View: *Solution View ID*

Explanation

Due to an internal error, the Administration and Monitoring Console was unable to query the AM_LOGS, AM_RULES_MASTER for the Action Manager rules associated with this Solution View.

Action

See the accompanying exception trace. Try again.

CTGDIW207E Unable to delete data from AM_LOGS table.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to delete data from AM_LOGS table.

Action

See the accompanying exception trace.

CTGDIW208W Unable to convert the monitor.refresh.rate value to integer.

Explanation

The Administration and Monitoring Console encountered an error while reading the Administration and Monitoring Console monitor.refresh.rate. This may have happened because the refresh rate was not specified correctly.

Action

Check the amc.properties file for the value of monitor.refresh.rate variable.

CTGDIW209E Could not obtain an instance of Tombstone Manager for Solution View:*Solution View name*. It might not be running on the remote server.

Explanation

The Administration and Monitoring Console was unable to obtain a connection to the Tombstone Manager on the remote server.

Action

Verify the tombstone manager is configured to be running. Check the error logs for the exact error. Start the tombstone manager on the remote IBM Security Directory Integrator server and try again.

CTGDIW210E No log files found for AssemblyLine:

AssemblyLine name and Config: Config

Explanation

The Administration and Monitoring Console was unable to find any log files associated with the specified AssemblyLine.

Action

Verify that a logger is attached to the specified AssemblyLine and that there are log files present. Try again.

CTGDIW211E No log files found for AssemblyLine:

AssemblyLine name and Config: Config

Explanation

The Administration and Monitoring Console was unable to find any log files associated with the specified AssemblyLine.

Action

Verify that a logger is attached to the specified AssemblyLine and that there are log files present. See the accompanying exception. Try again.

CTGDIW212E Unable to display contents of Log File: *Log file name of AssemblyLine: AssemblyLine name in Config: Config*

Explanation

The Administration and Monitoring Console was unable to find any log files associated with the specified AssemblyLine.

Action

Verify that a logger is attached to the specified AssemblyLine and that there are log files present. See the accompanying exception. Try again.

CTGDIW213E Unable to retrieve tombstones for

AssemblyLine: *AssemblyLine in Config: Config*

Explanation

The Administration and Monitoring Console was unable to obtain Tombstones for the specified AssemblyLine due to some internal error.

Action

Check if the tombstone manager is running. See the accompanying exception. Try again.

CTGDIW214W Unable to find group: *group name*

Explanation

While loading the Modify Group screen, the Administration and Monitoring Console was unable to find the specified group details in database. It may have been modified or deleted already.

Action

Check the logs, and try again.

CTGDIW215W Error closing database statement.

Explanation

The Administration and Monitoring Console encountered an error while attempting to close a database statement. This may have occurred because of an underlying JDBC or Database error.

Action

See the exception logs for details.

CTGDIW216W Error closing database ResultSet.

Explanation

The Administration and Monitoring Console encountered an error while attempting to close a database ResultSet. This may have occurred because of an underlying JDBC or Database error.

Action

See the exception logs for details.

CTGDIW217W Error closing database connection.

Explanation

The Administration and Monitoring Console encountered an error while attempting to close a database connection. This may have occurred because of an underlying JDBC or Database error.

Action

See the exception logs for details.

CTGDIW218W Message with programmer's Key: *key string* not found.

Explanation

The Administration and Monitoring Console was unable to find a message for the specified key in its properties file.

Action

No user action needed.

CTGDIW219W Some error occurred while evaluating the user's role. User: *User Name* Solution View ID: *Solution View ID*

Explanation

The Administration and Monitoring Console was unable to determine the role of the user because of some internal error.

Action

See the accompanying logs.

CTGDIW220W Some error occurred while evaluating the user's role. User: *User Name*

Explanation

The Administration and Monitoring Console was unable to determine the role of the user because of some internal error.

Action

See the accompanying logs.

CTGDIW221W Unable to obtain authorized Config instances. User: *User ID*

Explanation

The Administration and Monitoring Console was unable to determine the authorized configs for the user.

Action

See the accompanying logs.

CTGDIW222I An instance of DBConnectionFactory class created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW223W Illegal value specified for Action Manager Log Rotate rate (days). Unable to convert to integer. Current value specified for am.logrotate: *value*

Explanation

The Action Manager Log rotate rate is used to delete logs older than the specified number of days. This value must be a positive integer greater than or equal to 1. On error, the default is set to 10 days.

Action

Enter a valid value satisfying the above criteria for Action Manager Log Rotate rate (in days).

CTGDIW224I The Administration and Monitoring Console database: *database details*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW225I Derby network server already running.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW226I Unable to ping Derby network server. Attempting to start.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW227W Table does not exist: *table name*

Explanation

A required table was not found in the database by the Administration and Monitoring Console. The Administration and Monitoring Console will attempt to create the database. This usually happens when the Administration and

Monitoring Console database is created for the first time, or the database settings have been changed in amc.properties.

Action

No user response needed, unless the table creation is unexpected. In that case, check if the database settings in amc.properties are correct. If in doubt, mention the complete path of the database in amc.properties.

CTGDIW228W Table created: *table name*

Explanation

A required table was not found in the database by the Administration and Monitoring Console. The Administration and Monitoring Console will attempt to create the database. This usually happens when the Administration and Monitoring Console database is created for the first time, or the database settings have been changed in amc.properties.

Action

No user response needed, unless the table creation is unexpected. In that case, check if the database settings in amc.properties are correct. If in doubt, mention the complete path of the database in amc.properties.

CTGDIW229I The Administration and Monitoring Console Database has been shutdown.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW230W An error occurred while attempting the Administration and Monitoring Console DB shutdown.

Explanation

Some error occurred while attempting to shutdown the Administration and Monitoring Console database.

Action

Check the accompanying exception trace for more information.

CTGDIW231I LDAP user filter: *search filter string*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW232I LDAP user tree base DN: *base DN*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW233E An error occurred while attempting to obtain all LDAP users for the Administration and Monitoring Console.

Explanation

An error occurred while attempting to obtain all LDAP users.

Action

Check the LDAP settings in amc.properties file. Also see the accompanying exception.

CTGDIW234I LDAP user filter: *search filter string*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW235I LDAP user tree base DN: *base DN*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW236W More than one result obtained for username:
user name

Explanation

While attempting to determine valid the Administration and Monitoring Console user (in LDAP), the Administration and Monitoring Console obtained more than one user satisfying the search criteria. Only one user must be obtained.

Action

Check the LDAP settings in amc.properties file. Also see the accompanying exception.

CTGDIW237E Valid user not found (in LDAP): *user name*

Explanation

The Administration and Monitoring Console was unable to obtain the specified user in LDAP.

Action

Check the LDAP settings in amc.properties file. Also see the accompanying exception.

CTGDIW238E Unable to bind to LDAP server with user: *user name*

Explanation

The Administration and Monitoring Console was unable to bind to the specified LDAP server with the passed username and password.

Action

Check the username and password on the LDAP server. Check the LDAP settings in amc.properties file. Also see the accompanying exception.

CTGDIW239I LDAP group filter: *search filter string*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW240I LDAP group tree base DN: *base DN*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW241E An error occurred while attempting to obtain all LDAP groups for the Administration and Monitoring Console.

Explanation

An error occurred while attempting to obtain all LDAP groups.

Action

Check the LDAP settings in amc.properties file. Also see the accompanying exception.

CTGDIW242I Obtaining members of group *Group DN*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW243E An error occurred while attempting to obtain all members of LDAP group: *Group DN*

Explanation

An error occurred while attempting to obtain all members of the specified LDAP group.

Action

Check the LDAP settings in amc.properties file. Also see the accompanying exception.

CTGDIW244E LDAPHostname attribute not specified in amc.properties.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW245W No value specified for LDAPBindID variable in amc.properties file. Attempting to bind as anonymous user.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW246E An error occurred while creating LDAP search context.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file. See accompanying exception.

CTGDIW247E LDAPHostname attribute value not specified in amc.properties or is invalid. Value: *Attribute value*

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW248E LDAPPort attribute value not specified in amc.properties or is invalid. Value: *Attribute value*

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW249E LDAPAdminUid attribute value not specified in amc.properties or is invalid. Value: *Attribute value*

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW250E LDAPAdminPwd attribute value not specified in amc.properties or is invalid.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW251E LDAPServerType attribute value not specified in amc.properties or is invalid.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW252E LDAPBindID attribute value not specified in amc.properties or is invalid.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW253E LDAPBindPassword attribute value not specified in amc.properties or is invalid.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW254E LDAPSuffix attribute value not specified in amc.properties or is invalid.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW255E LdapUserPrefix attribute value not specified in amc.properties or is invalid.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW256E LDAPUserSuffix attribute value not specified in amc.properties or is invalid.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW257W LDAPsslEnabled attribute value not specified in amc.properties or is invalid. Setting SSL to false.

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW258W Unable to obtain membership for user:*user* DN

Explanation

See message.

Action

Check the LDAP settings in amc.properties file.

CTGDIW259I Instance of TDISessionFactory class created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW260W The api.Config.folder property is not set on the remote server.

Explanation

The api.Config.folder attribute which points to the directory containing configs exposed for remote use is not set on the IBM Security Directory Integrator server. Because of that, the Administration and Monitoring Console will not be able to get the list of stopped configs on the remote server.

Action

Set the api.Config.folder property on the remote IBM Security Directory Integrator server's global.properties file if you want the Administration and Monitoring Console to also list the stopped configs.

CTGDIW261I Trying to establish connection to: Server: *hostname* Port: *port*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW262I Attempting to use Custom Authentication with username: *username*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW263I Unable to establish connection to: Server: *hostname* Port: *port*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW264W Console administrator *username* login failed.

Explanation

Console administrator login failed because of incorrect password.

Action

Specify the correct password.

CTGDIW265W User *username* login failed.**Explanation**

Login failed because of incorrect username or password.

Action

Specify the correct password.

CTGDIW266E An error occurred while loading Navigation XML file.**Explanation**

The console files seem to be corrupted.

Action

Check the XML files in IBMAppConfig folder for corruption. Contact IBM Support.

CTGDIW267W Unable to set the `amc.session.timeout` value. Value obtained from `amc.properties` file: *session timeout value*. Web server's default value will be applicable.**Explanation**

The Administration and Monitoring Console encountered an error while setting the Administration and Monitoring Console session timeout value. This may have happened because the session timeout was not specified correctly. It must be an integer

Action

Check the `amc.properties` file for the value of `amc.session.timeout` variable.

CTGDIW268E An error occurred while trying to read the Console Admin Password file.**Explanation**

The Administration and Monitoring Console encountered an error while trying to read the Console Administrator's password file.

Action

Check the `console_passwd` file or replace it with the original, uncorrupted file.

CTGDIW269I Obtaining handle to `amc.properties` file.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW270E Unable to initialize LDAP properties. Switching to the Administration and Monitoring Console database based authentication.

Explanation

The Administration and Monitoring Console encountered an error while trying to initialize LDAP properties, and therefore has switched to normal the Administration and Monitoring Console database based authentication.

Action

Check the LDAP properties and error logs for LDAP related issues. Restart the Administration and Monitoring Console after modifying amc.properties.

CTGDIW271I LDAP properties initialized. The Administration and Monitoring Console authentication source is set to LDAP.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW272E An error occurred while attempting to read the amc.properties file.

Explanation

See message.

Action

Check the location of amc.properties file. See the accompanying exception trace. Ensure that the file is not corrupted / truncated. The Administration and Monitoring Console will not be able to run unless this issue is resolved.

CTGDIW273E Unable to initialize DBConnectionFactory.

Explanation

The Administration and Monitoring Console was unable to initialize the Administration and Monitoring Console Database.

Action

Check the JDBC properties of amc.properties file. See the accompanying exception trace. Ensure that the file is not corrupted / truncated. The Administration and Monitoring Console will not be able to run unless this issue is resolved.

CTGDIW274I Administration and Monitoring Console initialization complete.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW275I Administration and Monitoring Console Shutdown.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW276I Calling CSA render with URL: *URL*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW277E Select a server to modify.

Explanation

The error occurred because the user clicked the Modify button without selecting a server from the list. The user needs to specify which server to modify.

Action

Select a IBM Security Directory Integrator server from the list and click Modify.

CTGDIW278E Incompatible version of remote IBM Security Directory Integrator server. Remote server version: *version number*

Explanation

The error occurred because the user attempted to work with a remote IBM Security Directory Integrator server which is incompatible with the Administration and Monitoring Console.

Action

Connect to a compatible IBM Security Directory Integrator server version. Check the error logs.

CTGDIW279W The remote IBM Security Directory Integrator server is of version *version number*. Some of the features of the Administration and Monitoring Console will not be available or will not work correctly with this server version.

Explanation

The Administration and Monitoring Console displayed an incompatible server version warning.

Action

It is recommended to use the same version of IBM Security Directory Integrator server as the version of the Administration and Monitoring Console.

CTGDIW280I Thread created for cleanup of Action Manager related logs.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW281E AssemblyLine required to create or update the Start AssemblyLine Action.

Explanation

The user did not select any AssemblyLines. It is mandatory to select an AssemblyLine.

Action

Enter an AssemblyLine.

CTGDIW282E AssemblyLine is required to create or update the Stop AssemblyLine Action.

Explanation

The user did not select any AssemblyLines. It is mandatory to select an AssemblyLine.

Action

Enter an AssemblyLine.

CTGDIW283E Notify event actions could not be stored. See the logs for errors.

Explanation

Notify event action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW284E Enable/Disable rule action could not be stored. See the logs for errors.

Explanation

Enable/Disable rule action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW285E Start AssemblyLine action could not be stored. See the logs for errors.

Explanation

Start AssemblyLine action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW286E Stop AssemblyLine action could not be stored. See the logs for errors.

Explanation

Stop AssemblyLine action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

**CTGDIW287E Modify Property action could not be stored.
See the logs for errors.**

Explanation

Modify Property action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW288E Write Log action could not be stored. See the logs for errors.

Explanation

Write Log action could not be stored in database. See the error logs for details, and the list of actions in the previous page, to see the actions which were stored.

Action

See the error logs, or try again.

CTGDIW289E Execute rule action could not be stored. See the logs for errors.

Explanation

Execute rule action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW290E Copy property value action could not be stored. See the logs for errors.

Explanation

Copy property value action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW291E The Notify event action could not be updated. See the logs for errors.

Explanation

The Notify event action information could not be updated in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW292E The Enable/Disable Rule action could not be updated. See the logs for errors.

Explanation

The Enable/Disable Rule action information could not be updated in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW293E The Start AssemblyLine action could not be updated. See the logs for errors.

Explanation

The Start AssemblyLine action information could not be updated in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW294E The Stop AssemblyLine action could not be updated. See the logs for errors.

Explanation

The Stop AssemblyLine action information could not be updated in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW295E The Modify Property action could not be updated. See the logs for errors.

Explanation

The Modify Property action information could not be updated in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW296E The Write Log action could not be updated. See the Administration and Monitoring Console logs for errors.

Explanation

The Write Log action information could not be updated in the Administration and Monitoring Console database. To see the list of actions which were successfully stored go to the previous the Administration and Monitoring Console panel. See the Administration and Monitoring Console logs for more information on the error.

Action

See the error logs, or try again.

CTGDIW297E The Execute Rule action could not be updated. See the logs for errors.

Explanation

The Execute Rule action information could not be updated in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW298E The Copy property Value action could not be updated. See the logs for errors.

Explanation

The Copy property value action information could not be updated in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW299E Select a Tombstone entry from the table to view Tombstone details.

Explanation

The user clicked View Details without selecting any tombstone entry from the table.

Action

Select a Tombstone entry from the table to view details.

CTGDIW300E Unable to determine Action Manager Status.

Explanation

The Administration and Monitoring Console was unable to determine Action Manager status. There was some database error while retrieving the Action Manager status.

Action

See the Administration and Monitoring Console logs for error details and try again.

CTGDIW301E Click on Clear menu option to clear Action Manager Triggered Status.

Explanation

Click on Clear menu option to clear Action Manager Triggered Status and set it to Action Manager not triggered state.

Action

Click on Clear menu option to clear Action Manager Triggered Status.

CTGDIW302E Unable to obtain input parameters for AssemblyLine *AssemblyLine name*.

Explanation

Unable to obtain handle to AssemblyLine object. This may happen if the Config instance associated with the AssemblyLine is not loaded on the server.

Action

See the Administration and Monitoring Console logs for error details. Check the Config containing this AssemblyLine is loaded on the server, and try again.

CTGDIW303I There are no input parameters needed for the chosen AssemblyLine Operation.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW304E The AssemblyLine *AssemblyLine* name could not be started. Check the logs for errors.

Explanation

Due to an internal error, or remote IBM Security Directory Integrator server error, the starting of the specified AssemblyLine failed. This might also happen if the AssemblyLine was already started by some other process.

Action

Check the error logs or try again.

CTGDIW305E The specified Entry string in AssemblyLine Input parameter panel is incorrectly constructed: *string*

Explanation

An Entry string in the AssemblyLine operation input parameters has to be of the format: Entry[attr1:value1;attr2:value2;attr3:value3]. Use a semicolon to separate attribute-value pairs and use a colon to separate an attribute from its value.

Example: Entry[ldapserver:myserver.com]

Entry[ldapserver:myserver.com;ldapport:389]

Entry[ldapserver:myserver.com;ldapserver:anotherserver.com;ldapport:389] (This is an example of a multi valued attribute). The Administration and Monitoring Console encountered an entry string that could not be parsed as per the above format.

Action

Enter the Entry string in the required format.

CTGDIW306E An error occurred while attempting to parse the string: *string*.

Explanation

An Entry string in the AssemblyLine operation input parameters has to be of the format: Entry[attr1:value1;attr2:value2;attr3:value3]. Use a semicolon to separate attribute-value pairs and use a colon to separate an attribute from its value.

Example: Entry[ldapserver:myserver.com]

Entry[ldapserver:myserver.com;ldapport:389]

Entry[ldapserver:myserver.com;ldapserver:anotherserver.com;ldapport:389] (This is an example of a multi valued attribute). The Administration and Monitoring Console encountered an entry string that could not be parsed as per the above format.

Action

Enter the Entry string in the required format and try again.

CTGDIW307E An error occurred while attempting to parse the string: *string*.

Explanation

An Entry string in the AssemblyLine operation input parameters has to be of the format: Entry[attr1:value1;attr2:value2;attr3:value3]. Use a semicolon to separate attribute-value pairs and use a colon to separate an attribute from its value.

Example: Entry[ldapserver:myserver.com]

Entry[ldapserver:myserver.com;ldapport:389]

Entry[ldapserver:myserver.com;ldapserver:anotherserver.com;ldapport:389] (This is an example of a multi valued attribute). The Administration and Monitoring Console encountered an entry string that could not be parsed as per the above format.

Action

Enter the Entry string in the required format and try again.

CTGDIW308E Unable to obtain input parameters for AssemblyLine *AssemblyLine name*.

Explanation

Unable to obtain handle to AssemblyLine object. This may happen if the Config instance associated with the AssemblyLine is not loaded on the server. See error logs for details.

Action

Check the Config containing this AssemblyLine is loaded on the server, and try again.

CTGDIW309E AssemblyLine required to create or update Start AssemblyLine Action.

Explanation

The user did not mention any AssemblyLines. AssemblyLine Operations cannot be discovered or configured without specifying an AssemblyLine to work with.

Action

Enter an AssemblyLine.

CTGDIW310E The session with the chosen remote server could not be established.

Explanation

A session could not be established with the remote IBM Security Directory Integrator server. Discovering AssemblyLine operations is not possible until the specified IBM Security Directory Integrator server is running, and the Config instance is loaded on that server.

Action

Ensure the the remote API engine is running on the remote server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

CTGDIW311E The Config *Config* is not loaded on the server. The Config needs to be loaded for the Administration and Monitoring Console to discover the AssemblyLine operations. Do you want to Load the Config?

Explanation

The chosen Config is not loaded on the server. Discovering AssemblyLine operations is not possible until the specified Config instance is loaded on the server.

Action

Click OK if you want the specified Config to be loaded, or Cancel to return to the previous screen.

CTGDIW312E Error occurred while trying to start the Config *Config path*.

Explanation

An error occurred while trying to start the Config on the remote server. This might have occurred because the Administration and Monitoring Console was unable to contact the remote server or the Config path might have changed. It can also occur if the specified Config is password protected, and no password was specified in the Config Password field, or an incorrect password was specified in the Config Password field. It might also occur if the selected file is not a valid IBM Security Directory Integrator Config file. See the error logs for more details.

Action

Ensure that the remote Config is valid and that the path is correct. Also ensure that for password protected Configs, the correct password is supplied in the Config Password field. See the error logs for more details, or try again.

CTGDIW313E The AssemblyLine *AssemblyLine name* is not present in the specified Config. Available AssemblyLines: *AssemblyLine list* .

Explanation

The specified AssemblyLine does not exist.

Action

Specify a valid AssemblyLine name.

**CTGDIW314E No operations exposed in AssemblyLine
AssemblyLine name.**

Explanation

The specified AssemblyLine does not expose any AssemblyLine operations.

Action

Specify an AssemblyLine that contains operations.

CTGDIW315E Select an operation from the list.

Explanation

The user must select an operation from the list to proceed.

Action

Select one of the available operations or press Cancel to return to the previous screen.

**CTGDIW316I There are no input parameters needed for the
chosen AssemblyLine Operation.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIW317E An error occurred while attempting to parse the
string: *string*.**

Explanation

An Entry string in the AssemblyLine operation input parameters has to be of the format: Entry[attr1:value1;attr2:value2;attr3:value3]. Use a semicolon to separate attribute-value pairs and use a colon to separate an attribute from its value.
Example: Entry[ldapserver:myserver.com]
Entry[ldapserver:myserver.com;ldapport:389]
Entry[ldapserver:myserver.com;ldapserver:anotherserver.com;ldapport:389] (This is an example of a multi valued attribute). The Administration and Monitoring Console encountered an entry string that could not be parsed as per the above format.

Action

Enter the Entry string in the required format and try again.

CTGDIW318E An error occurred while attempting to parse the string: *string*.

Explanation

An Entry string in the AssemblyLine operation input parameters has to be of the format: Entry[attr1:value1;attr2:value2;attr3:value3]. Use a semicolon to separate attribute-value pairs and use a colon to separate an attribute from its value.

Example: Entry[ldapserver:myserver.com]

Entry[ldapserver:myserver.com;ldapport:389]

Entry[ldapserver:myserver.com;ldapserver:anotherserver.com;ldapport:389] (This is an example of a multi valued attribute). The Administration and Monitoring Console encountered an entry string that could not be parsed as per the above format.

Action

Enter the Entry string in the required format and try again.

CTGDIW319E A Config is required to create or update Start AssemblyLine Action.

Explanation

The user did not enter any Configs. It is mandatory for Start AssemblyLine Action to select a Config.

Action

Enter a Config.

CTGDIW320E A Config is required to create or update Stop AssemblyLine Action.

Explanation

The user did not enter any Configs. It is mandatory to select a Config for Stop AssemblyLine Action.

Action

Enter a Config.

CTGDIW321E Select an AssemblyLine to view Logs.

Explanation

The user clicked View Logs without selecting any AssemblyLine.

Action

Select an AssemblyLine and click View Logs.

CTGDIW322E The On property trigger is not supported for Solution Views on IBM Security Directory Integrator 6.0 servers. Select a different trigger.

Explanation

IBM Security Directory Integrator Properties were introduced in IBM Security Directory Integrator 6.1. Therefore, triggers on property values are not supported for Solution Views created for remote IBM Security Directory Integrator 6.0 servers.

Action

Select a different trigger, or use a Solution View created on IBM Security Directory Integrator 6.1 server or above.

CTGDIW323E The Copy IBM Security Directory Integrator Property value Action is not supported for Solution Views on IBM Security Directory Integrator 6.0 servers.

Explanation

IBM Security Directory Integrator Properties were introduced in IBM Security Directory Integrator 6.1. Therefore, actions on properties are not supported for Solution Views created for IBM Security Directory Integrator 6.0 servers.

Action

Select a different action, or use a Solution View created on IBM Security Directory Integrator 6.1 server or above.

CTGDIW324E The Modify IBM Security Directory Integrator Property Action is not supported for Solution Views on IBM Security Directory Integrator 6.0 servers.

Explanation

IBM Security Directory Integrator Properties were introduced in IBM Security Directory Integrator 6.1. Therefore, actions on properties are not supported for Solution Views created for IBM Security Directory Integrator 6.0 servers.

Action

Select a different action, or use a Solution View created on IBM Security Directory Integrator 6.1 server or above.

CTGDIW325E The Notify event Action is not supported for IBM Security Directory Integrator 6.0 Solution Views.

Explanation

The sendEventNotification API for sending events remotely to a IBM Security Directory Integrator Server was introduced in IBM Security Directory Integrator 6.1. Notify event action is therefore not supported for Solution Views on IBM Security Directory Integrator 6.0 servers.

Action

Select a different action, or use a Solution View created on IBM Security Directory Integrator 6.1 server or above.

CTGDIW326E The IBM Security Directory Integrator server corresponding to the selected Solution View is not running. It is mandatory for the remote IBM Security Directory Integrator server to be running for adding rules.

Explanation

Creation of rules in the Administration and Monitoring Console requires that the version of the IBM Security Directory Integrator server be known. The Administration and Monitoring Console can determine the server version only for running IBM Security Directory Integrator servers. For this reason, it is mandatory that the remote IBM Security Directory Integrator server be running for creating/editing rules for the Solution View. Depending on the server version, certain features are enabled or disabled in the Administration and Monitoring Console.

Action

Verify that the remote IBM Security Directory Integrator server corresponding to the Solution View is running.

CTGDIW327E The IBM Security Directory Integrator server corresponding to the selected Solution View is not running. It is mandatory for the remote IBM Security Directory Integrator server to be running for editing rules.

Explanation

Editing of rules in the Administration and Monitoring Console requires that the version of the IBM Security Directory Integrator server be known. The Administration and Monitoring Console can determine the server version only for running IBM Security Directory Integrator servers. For this reason, it is mandatory that the remote IBM Security Directory Integrator server be running for creating/editing rules for the Solution View. Depending on the server version, certain features are enabled or disabled in the Administration and Monitoring Console.

Action

Verify that the remote IBM Security Directory Integrator server corresponding to the Solution View is running.

CTGDIW328E The IBM Security Directory Integrator server corresponding to the selected Solution View is a IBM Security Directory Integrator 6.0 server. IBM Security Directory Integrator Properties feature is not available in IBM Security Directory Integrator 6.0 Solution Views.

Explanation

IBM Security Directory Integrator Properties were introduced in IBM Security Directory Integrator 6.1. For this reason, the Administration and Monitoring Console does not support properties feature.

Action

Select a Solution View that corresponds to a IBM Security Directory Integrator 6.1 or later server version.

CTGDIW329E Unable to obtain the SERVER_ID (primary key) for the recently added server.

Explanation

Most probably, due to an internal database error the Administration and Monitoring Console was unable to obtain the ID for the recently added Server.

Action

See the accompanying exception trace. Try again.

CTGDIW330E Unable to insert row into AM_SERVER_UPDATE_DETAILS table.

Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to make an entry in the AM_SERVER_UPDATE_DETAILS table. This table is used by Action Manager to monitor real-time updates to servers registered with the Administration and Monitoring Console.

Action

See the accompanying exception trace. Try again.

CTGDIW331E Could not obtain an instance of Tombstone Manager. It might not be running on the remote server.

Explanation

The Administration and Monitoring Console was unable to obtain a connection to the Tombstone Manager on the remote server.

Action

Verify the tombstone manager is configured to be running. Check the error logs for the exact error. Start the tombstone manager on the remote IBM Security Directory Integrator server and try again.

CTGDIW332E No AssemblyLines found in Config. Atleast one AssemblyLine must be present to create a Solution View.

Explanation

There are no AssemblyLines in the specified Config. Atleast one AssemblyLine must be present in the Config for creating a new Solution View.

Action

Choose a Config that has at least one AssemblyLine and try again.

CTGDIW333E Unable to read the AssemblyLine information from Config.

Explanation

The Administration and Monitoring Console was unable to read the AssemblyLine information from the Config. This may have occurred because of some internal error in IBM Security Directory Integrator.

Action

Check the Administration and Monitoring Console logs and try again.

CTGDIW334E Unable to get published Solution details from Config.

Explanation

The Administration and Monitoring Console was unable to read the published Solution information from the Config. This may have occurred because of some internal error in IBM Security Directory Integrator, or if the Config was corrupted, or if the solution was not published correctly.

Action

Check the Solution details of the Config in Config Editor. Also check the Administration and Monitoring Console logs and try again.

CTGDIW335I Simple create of Solution View *Solution View name* successful.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW336E The Solution View could not be created. Check the logs for errors.

Explanation

The Administration and Monitoring Console was unable to quick create the Solution View in the Administration and Monitoring Console database. If Simple Create from a solution was chosen, then one of the following may have occurred: 1) The solution details could not be read by the Administration and Monitoring Console. 2) The AssemblyLines exposed in Solution, do not exist in Config. Alternatively, an internal error may have occurred in the Administration and Monitoring Console due to which the Administration and Monitoring Console was unable to read the Config details or a database error may have occurred.

Action

See the Administration and Monitoring Console logs for more details. Also try creating the Solution View again.

CTGDIW337I Detected remote IBM Security Directory Integrator Server version *version number*. Skipping Select Properties step.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW338I Creating Solution View *Solution View name* from Published Solution. Config Instance ID: *Config ID*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW339E Unable to determine AssemblyLines in Config.

Explanation

The Administration and Monitoring Console was unable to determine the AssemblyLines in the Config. This may occur if the Config is corrupted, or if there are no AssemblyLines in the Config.

Action

See the Administration and Monitoring Console logs for more details. Check the Config file in CE. Also try creating the Solution View again.

CTGDIW340E No AssemblyLines found in solution. Cannot create Solution View from solution.

Explanation

There are no AssemblyLines exposed in the solution. A Solution View cannot be created unless there is at least one AssemblyLine in the solution.

Action

Modify the solution in Config Editor to expose at least one AssemblyLine and try again. Alternatively try creating the Solution View manually.

CTGDIW341E None of the AssemblyLines exposed in the solution exist in Config. Cannot create Solution View from solution.

Explanation

None of the AssemblyLines exposed in the solution actually exist in the Config. This could occur if the AssemblyLines in Config were removed or modified after creating the solution in Config Editor. The Administration and Monitoring Console cannot create a Solution View with AssemblyLines that are not actually found in the Config.

Action

Modify the solution in Config Editor to expose at least one valid AssemblyLine and try again. Alternatively try creating the Solution View manually.

CTGDIW342E Unable to insert into CONFIG_VIEW_MASTER table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW343E Unable to obtain CV_ID (primary key) value for Solution View *Solution View name*

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW344E Unable to insert into CONFIG_VIEW_AL_DETAILS table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW345E Unable to obtain handle to IBM Security Directory Integrator Properties objects.

Explanation

See message. The Administration and Monitoring Console encountered an internal IBM Security Directory Integrator Properties related error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW346E Unable to insert into CONFIG_VIEW_HEALTH_AL_DETAILS table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW347E Unable to determine AssemblyLines in Config.

Explanation

The Administration and Monitoring Console was unable to determine the AssemblyLines in the Config. This may occur if the Config is corrupted, or if there are no AssemblyLines in the Config.

Action

See the Administration and Monitoring Console logs for more details. Check the Config file in CE. Also try creating the Solution View again.

CTGDIW348E Unable to insert into CONFIG_VIEW_MASTER table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW349E Unable to obtain CV_ID (primary key) value for Solution View *Solution View name*

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW350E Unable to insert into CONFIG_VIEW_AL_DETAILS table in database.

Explanation

See message. The Administration and Monitoring Console encountered an internal database error while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW351E Unable to get a handle to IBM Security Directory Integrator Properties object.

Explanation

See message. The Administration and Monitoring Console encountered an internal error related to IBM Security Directory Integrator Properties while creating a Solution View.

Action

See the accompanying exception for more details. Try again.

CTGDIW352E Unable to establish connection to the remote IBM Security Directory Integrator Server. Viewing of AssemblyLine tombstones, AssemblyLine Logs and Manage Properties functionality will not be available.

Explanation

The Administration and Monitoring Console was unable to connect to the remote IBM Security Directory Integrator Server associated with the Solution View. View AssemblyLine Tombstones, View AssemblyLine Logs and Manage Properties functionality will not be available.

Action

Check the remote server associated with this Solution View. Ensure the the remote API engine is running on the remote server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

CTGDIW353W Solution is disabled in Config *config* instance.

Explanation

The chosen Config has its solution disabled. The Administration and Monitoring Console cannot create a Solution View based on a disabled solution.

Action

If a Solution View is required to be created using a published solution, then specify a config that has a solution that has not been disabled. Alternatively, from the Config Editor, enabled the solution checkbox for the Config.

CTGDIW354E Rule with name *Rule Name* already exists for this Solution View.

Explanation

A rule with the same name already exists for this Solution View. Duplicate rule names are not allowed for the same Solution View.

Action

Specify a unique rule name.

CTGDIW355E Polling Interval not specified.

Explanation

For the Query AssemblyLine result trigger, the Polling Interval is mandatory. The user did not specify the Polling Interval.

Action

Specify the Polling Interval.

CTGDIW356W Select the log file(s) to delete.

Explanation

Select the log file(s) which are to be deleted. The user has not selected a single log file.

Action

Delete the log file by selecting the check boxes opposite the log file names that are to be deleted.

CTGDIW357W Delete the selected logs?

Explanation

All the log files which are selected will be deleted on clicking on the "Ok" button.

Action

The confirmation dialog with a warning message is displayed since deletion of logs is an irreversible action. The log files are permanently deleted from the file system. All the selected log files for the configuration will be deleted from the servers system_logs directory if the "OK" button is clicked. However if the user wants to cancel the action, the user can click on the "Cancel" button.

CTGDIW358E Error occurred while deleting the log files.

Explanation

An error has occurred while deleting the log files for the AssemblyLine.

Action

An error has occurred while deleting the log files. For determining the actual reason for this error refer the IBM Security Directory Integrator server's log file.

CTGDIW359E Error *error message* occurred while deleting the log files.

Explanation

An error has occurred while deleting the log files for the AssemblyLine. The reason for the error is mentioned in the IBM Security Directory Integrator server's log file.

Action

An error has occurred while deleting the log files. The log message gives the reason for the error.

CTGDIW360W All the selected log files were not deleted.

Explanation

Due to some error, all the selected log files were not deleted.

Action

Due to some error, all the selected log files were not deleted. For details on which log files were not deleted refer the server log file.

CTGDIW361W The log files which were not deleted are : *log file names*

Explanation

Due to some error, all the selected log files were not deleted.

Action

Due to some error, all the selected log files were not deleted.

CTGDIW362W Delete log is not supported for IBM Security Directory Integrator Server version *version number*

Explanation

The delete log feature and API was added in IBM Security Directory Integrator 7.0 release. It is not supported by earlier IBM Security Directory Integrator server versions.

Action

The delete log functionality makes a call to an API which is present with only IBM Security Directory Integrator 7.0 server. Hence the functionality is not available for the earlier IBM Security Directory Integrator server versions.

CTGDIW363W A session could not be established with the remote IBM Security Directory Integrator server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

Explanation

A new IBM Security Directory Integrator server cannot be added because the Administration and Monitoring Console was unable to establish connection with the server. This might be because the server is down, or the Remote Server API engine is not running on the remote server or the connection settings to the server are incorrect.

Action

Ensure the the remote API engine is running on the remote server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

CTGDIW364W A session could not be established with the remote IBM Security Directory Integrator server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

Explanation

The Server ID cannot be changed because the Administration and Monitoring Console was unable to establish connection with the server. The inability to establish a connection could be caused by any of these three conditions: The server could be down. The Remote Server API engine may not be running on the remote

server. The connection settings to the server may be incorrect.

Action

Ensure the the remote API engine is running on the remote server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

CTGDIW365W Decimal digits cannot be entered in the field *filed name.*

Explanation

A user cannot enter decimal values in the specified field.

Action

The user should enter only whole numbers,that is integers in the specified field.

CTGDIW366W Do you want to change the ServerID of *server* *name* from *Old Server ID* to *server id*?

Explanation

Associating the Server ID of a IBM Security Directory Integrator Server with a different instance could invalidate the Solution Views and rules for this server.

Action

If you want to change the Server ID, click OK, otherwise click Cancel.

CTGDIW367E Unable to change the ServerID. A IBM Security Directory Integrator Server entry with the same Server ID, Hostname and Port has been already added. Check the logs for errors.

Explanation

The attributes Hostname, Server ID and Port should be unique for each IBM Security Directory Integrator server entry. A new IBM Security Directory Integrator Server cannot be added if this constraint is violated.

Action

Change the Server ID of the server that need to be added or delete the existing entry in the Administration and Monitoring Console and try again. The Server ID can be changed by editing the global.properties or solution.properties and by setting the com.ibm.di.server.id property.

CTGDIW368E Incorrect config password. Could not load the Config *Config path* .

Explanation

An incorrect password is specified for the password protected config.

Action

Ensure that for password protected Configs, the correct password is supplied in the Config Password field. Specify the correct password and try again.

CTGDIW369E The Administration and Monitoring Console is unable to obtain ISC role information.

Explanation

The Administration and Monitoring Console is unable to obtain role information because of an internal error.

Action

See the accompanying exception for more details.

CTGDIW370E The AssemblyLine *AssemblyLine* name is already running.

Explanation

The user chose to start an AssemblyLine in a simulate mode that is already running.

Action

Select a stopped AssemblyLine and click Start AssemblyLine in simulate mode.

CTGDIW371E The AssemblyLine *AssemblyLine* name could not be started. Check the logs for errors.

Explanation

Due to an internal error, or remote IBM Security Directory Integrator server error, the starting of the specified AssemblyLine failed.

Action

Check the error logs or try again.

CTGDIW372E Select an AssemblyLine to start.

Explanation

The user clicked on Start AssemblyLine in simulate mode without selecting any AssemblyLine. It is mandatory to specify which AssemblyLine to start.

Action

Select an AssemblyLine and click Start AssemblyLine in simulate mode.

CTGDIW373E The AssemblyLine *AssemblyLine name* is already running.

Explanation

The user chose to start an AssemblyLine that is already running.

Action

Select a stopped AssemblyLine and click Start AL

CTGDIW374E The AssemblyLine *AssemblyLine name* could not be started. Check the logs for errors.

Explanation

Due to an internal error, or remote IBM Security Directory Integrator server error, the starting of the specified AssemblyLine failed.

Action

Check the error logs or try again.

CTGDIW375E Select an AssemblyLine to start.

Explanation

The user clicked on Start AssemblyLine without selecting any AssemblyLine. It is mandatory to specify which AssemblyLine to start.

Action

Select an AssemblyLine and click Start AL.

CTGDIW376E The AssemblyLine *AssemblyLine name* is already running.

Explanation

The user chose to start an AssemblyLine in a simulate mode that is already running.

Action

Select a stopped AssemblyLine and click Start AssemblyLine in simulate mode.

CTGDIW377E The AssemblyLine *AssemblyLine name* could not be started. Check the logs for errors.

Explanation

Due to an internal error, or remote IBM Security Directory Integrator server error, the starting of the specified AssemblyLine failed.

Action

Check the error logs or try again.

CTGDIW378E Select an AssemblyLine to start.

Explanation

The user clicked on Start AssemblyLine in simulate mode without selecting any AssemblyLine. It is mandatory to specify which AssemblyLine to start.

Action

Select an AssemblyLine and click Start AssemblyLine in simulate mode.

CTGDIW379E An error has occurred while reading the stash file: *exception* .

Explanation

The specified error has occurred while reading the stash file.

Action

See the exception for more information.

CTGDIW380E No password has been found in the Administration and Monitoring Console stash file.

Explanation

The Administration and Monitoring Console stash file must contain the password of the Administration and Monitoring Console keystore (and optionally the password of the key).

Action

Provide a password in the stash file.

CTGDIW381I The key password is not present in the stash file. The keystore password will be used.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW382E Unable to recover the key from the keystore *keystore*. Exception occurred: *exception*

Explanation

The Administration and Monitoring Console was not able to retrieve the entry from the keystore.

Action

Ensure that the keystore is valid and is not corrupted.

CTGDIW383E The keystore *keystore* has no entry for the alias *alias*.**Explanation**

The keystore does not have an entry corresponding to the alias provided.

Action

Ensure that the keystore is correct and is not corrupted.

CTGDIW384E The key store password is NULL or empty.**Explanation**

This error occurs when the key store password passed to the createStashFile method is null or an empty string.

Action

Specify valid key store password

CTGDIW385E Stash file already read.**Explanation**

This error occurs when trying to read the stash file more than once.

Action

Check the configuration and if the problem persists contact IBM support.

CTGDIW386E Stash file *file name* not found.**Explanation**

This error occurs when trying to read the stash file but the specified file is not present in the Administration and Monitoring Console web application.

Action

The Administration and Monitoring Console war file needs to be bundled with a new stash file and deployed.

CTGDIW387E Input Stream is NULL.**Explanation**

This error occurs when the input stream passed to the readArray method is null.

Action

Contact IBM support.

CTGDIW388E The key password or keystore password failed a size validation check. Unable to read in the key password or the keystore password from the stash file.

Explanation

The correct size of the key password or keystore password was determined before reading their values from the stash file. The size of one of the values read in did not match the specified size and failed the validation check.

Action

Verify that the stash file is valid and has not been corrupted. Verify the stash file has not been changed by a user or process while the application was running.

CTGDIW389E Output Stream is NULL.

Explanation

This error occurs when the output stream passed to the writeArray method is null.

Action

Contact IBM support.

CTGDIW390E Byte array is NULL.

Explanation

This error occurs when the byte array passed to the writeArray method is null.

Action

Contact IBM support.

CTGDIW391E Encrypted password data too long: *length*.

Explanation

This error occurs when the byte array passed to the writeArray is longer than 255 characters.

Action

Contact IBM support.

CTGDIW392E No Provider specified for the stash file.

Explanation

Specify the provider to be used by the stash file.

Action

Refer the usage of the stash file command.

CTGDIW393I Stash file *file name* has been created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW394I Could not create stash file. Exception occurred: *exception*

Explanation

See message.

Action

See the exception message for more information.

CTGDIW395I Usage: StashFile keyStorePassword [keyPassword [securityProviderClass]]

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW396E The Administration and Monitoring Console failed to initialize the encrypt/decrypt keystore.

Explanation

The keystore used for encryption/decryption was not initialized correctly because of the exception.

Action

See the exception message for more information.

CTGDIW397E Select a property to modify.

Explanation

The user clicked Modify without selecting a property. Select a property before clicking Modify.

Action

Select a property from the list and click Modify.

CTGDIW398E Select a property to delete.

Explanation

The user did not select a property and press delete. You must select a property before clicking Delete.

Action

Select a property from the list and click Delete.

CTGDIW399E Delete property *property name*?

Explanation

Confirm you want to delete the specified property.

Action

If you want to delete the property, click OK, otherwise, click Cancel.

CTGDIW400E Config is not specified for the config load trigger.

Explanation

The config load trigger type requires a config.

Action

Specify config in trigger.

CTGDIW401E Config is not specified for the Config unload trigger.

Explanation

The config unload trigger type requires a config.

Action

Specify config in trigger.

CTGDIW402E Decimal digits cannot be entered in the *Interval* field.

Explanation

A user cannot enter decimal values in the specified field.

Action

The user should enter only whole numbers, that is integers in the specified field.

CTGDIW403E Illegal interval value specified. Value must be greater than zero.

Explanation

For the Timer trigger, the interval value must be greater than zero. The user entered an illegal value, or did not modify the value.

Action

Specify a valid interval value.

CTGDIW404E Failed to retrieve trigger details. Refer to the logs for additional information.

Explanation

An error occurred while retrieving the action manager trigger details. Please check the logs for additional information.

Action

Check if Action Manager is running. Check logs for additional information.

CTGDIW405E Failed to retrieve trigger thread details. Refer to the logs for additional information

Explanation

An error occurred while retrieving the Action Manager trigger thread details. Please check the logs for additional information.

Action

Check if Action Manager is running. Check logs for additional information.

CTGDIW406E Not able to establish session with the action manager.

Explanation

An error occurred while establishing session with Action Manager. Please check the logs for additional information.

Action

Check if Action Manager is running. Check logs for additional information.

CTGDIW407E Failed to retrieve the Acton Manager boot time. Refer to the logs for additional information.

Explanation

Refer to the logs for additional information.

Action

Check if Action Manager is running. Check the logs for additional information.

CTGDIW408E The selected Solution View is marked for auto update. Ensure that auto update is disabled to modify the Solution View.

Explanation

Editing a Solution View is not possible if the Solution View is marked for auto update.

Action

Disable Auto Update for the Solution View by selecting "Disable Auto Update" from the context menu.

CTGDIW409I The selected Solution View has been refreshed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW410E The selected Solution View could not be refreshed. Check the logs for errors.

Explanation

The Administration and Monitoring Console was unable to refresh the Solution View in the Administration and Monitoring Console database. One of the following may have occurred: 1) The solution details could not be read by the Administration and Monitoring Console. 2) The AssemblyLines exposed in the Solution do not exist in the Config. 3) Alternatively, an internal error may have occurred in the Administration and Monitoring Console. The internal error may have rendered the Administration and Monitoring Console unable to read the Config details, or a database error may have occurred

Action

See the the Administration and Monitoring Console logs for more details. Also try refreshing the Solution View again.

CTGDIW411E The trigger value for the local Action Manager variable has not been specified.

Explanation

For the On local variable trigger, the value field is mandatory. The user did not specify this value.

Action

Specify the trigger value for the Action Manager local variable.

CTGDIW412E Modify local variable action could not be stored. See the logs for errors.

Explanation

Modify local variable action could not be stored in database. To see which actions were stored successfully, go to the previous Administration and Monitoring Console window. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW413E The Modify local variable action could not be updated. See the logs for errors.

Explanation

The Modify local variable action information could not be updated in the database. To see which actions were stored successfully, go to the previous Administration and Monitoring Console window. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW414E Name or value for the local variable has not been specified in trigger.

Explanation

For the local variable, the name and initial value field is mandatory. The user did not specify these values.

Action

Specify the name and the initial value for the local variable.

CTGDIW415E The local variable name already exists.

Explanation

Local variable names must be unique. The name specified by the user already exists.

Action

Specify a different name for the local variable or remove the existing one.

CTGDIW416E Select a local variable to delete.

Explanation

No local variable was selected for deletion.

Action

Select a local variable and click Delete.

CTGDIW417E Select a local variable to modify.

Explanation

No local variable was selected for editing.

Action

Select a local variable and click Modify.

CTGDIW418I Rule *rule Name* executed successfully. The following actions were executed: *actions list*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW419E Rule *rule Name* execution failed. Refer to the logs for additional information.

Explanation

Some action may not have executed successfully. Refer to the logs for more information.

Action

Some action may not have executed successfully. Refer to the logs for more information.

CTGDIW420E The Administration and Monitoring Console was unable to obtain running config instances for the local IBM Security Directory Integrator Server.

Explanation

The Administration and Monitoring Console was unable to obtain running config instances for the local IBM Security Directory Integrator server. Ensure that at least one config instance is running on the local IBM Security Directory Integrator server.

Action

See the Administration and Monitoring Console logs for more details.

CTGDIW421I Solution View *Solution View name* created successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW422E A unknown error has occurred. See error logs for more details.

Explanation

The Administration and Monitoring Console was unable to create a Solution View or to redirect control to the Simple Create window. One of the following may have occurred: 1) Config instances are not loaded on the local IBM Security Directory Integrator server. 2) The AssemblyLines exposed in Solution, do not exist in Config. 3) A Solution View with a similar name already exists. 4) Alternatively, an internal error may have occurred in the Administration and Monitoring Console. The internal error may have rendered the Administration and Monitoring Console unable to read the Config details, or a database error may have occurred.

Action

See the error logs, or try again.

CTGDIW423E An exception occurred while verifying the Action Manager status. Refer to the logs for additional information.

Explanation

Check if the action manager RMI service is started on the host and port mentioned in the amc.properties. For additional information refer to the logs.

Action

Refer to the logs for additional information.

CTGDIW424I No thread statistics data were retrieved from Action Manager. This could occur because there are no rules configured in Action Manager.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW425I None of the Action Manager rules was triggered in the time interval *time interval*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW426W The Action Manager RMI Host is not set in the amc.properties file. As a result the default host *hostname* will be used.

Explanation

The am.api.host property is not set in the amc.properties file. The Administration and Monitoring Console is using the default host that is localhost.

Action

Set the am.api.host property in the amc.properties file.

CTGDIW427W The Action Manager RMI Port is not set in the amc.properties file. As a result the default port *port number* will be used.

Explanation

The am.api.port property is not set in the amc.properties file. The Administration and Monitoring Console is using the default port.

Action

Set the am.api.port property in the amc.properties file.

CTGDIW428W Not able to establish a connection with the Action Manager. Action Manager Session is null.

Explanation

The Action Manager might not be running. Or the host and port specified in the amc.properties file may be incorrect.

Action

Verify if the action manager is running on the same host and port as specified in the amc.properties file.

CTGDIW429E An exception occurred while triggering the rule *rule name*. Refer to the logs for additional information.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW430E An exception occurred while initializing the AMStatus Bean. Refer to the logs for additional information.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW431E The RMI object *remote object name* is not bound to the RMI Registry.

Explanation

The RMI remote object name is not the same.

Action

Verify whether the name of the remote object which is bound to the registry is the same as the one mentioned in exception.

CTGDIW432E The RMI registry is not reachable on host: *host* and port: *port*. The error message is *error*

Explanation

The RMI registry might be started on a different host and port. Therefore, the Administration and Monitoring Console is not able to connect to the Action Manager RMI Registry.

Action

Verify that the Action Manager RMI Registry is started on the correct host and port as expected by the Administration and Monitoring Console.

CTGDIW433E The RMI URL is malformed: *url*.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW434I The rollback action for the rule *rule name* has completed successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW435I The rollback action for the rule *rule name* failed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW436E The rollback action for the rule *rule name* failed. Refer to the logs for additional information.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW437E A config file is required to start a config using the run name.

Explanation

Selecting a config file is mandatory.

Action

Select a config file.

CTGDIW438E Error occurred while trying to load the config *Config path*.

Explanation

An error occurred while trying to load the config on the remote server. This might have occurred because the Administration and Monitoring Console was unable to

contact the remote server or because the config path might have changed. An error might also occur if the selected file is not a valid IBM Security Directory Integrator config file or if a config is already started using the run name that has been specified. See the error logs for more details.

Action

Ensure that the remote config is valid and that the path is correct. Also try using a different config run name. See the error logs for more details.

CTGDIW439E Incorrect or no config password. Could not load the property stores associated with config *Config path*

Explanation

No password or an incorrect password is specified for the password protected config.

Action

Ensure that for password protected configs, the correct password is supplied in the Config Password field. Specify the correct password and try again.

CTGDIW440E Error occurred while trying to load the config *Config path* to display the property stores associated with it..

Explanation

An error occurred while trying to load the config on the remote server. This might have occurred because the Administration and Monitoring Console was unable to contact the remote server or because the config path might have changed. An error might also occur if the selected file is not a valid IBM Security Directory Integrator config file. See the error logs for more details.

Action

Ensure that the remote config is valid and that the path is correct. See the error logs for more details.

CTGDIW441E Insufficient rights to perform config load task. for the selected Config instance *Config instance*.

Explanation

The user chose to perform a config load without having config admin privilege to any associated Solution View. Only when a user has config admin privilege to a particular Solution View which is associated with the chosen config instance, can the user perform the load operation for that config instance. Otherwise, the user must be the console administrator.

Action

Select an authorized config instance, or login using a user id with appropriate authority. Alternatively, login as Console Administrator and then try again.

CTGDIW442E Action of type 'Send email' could not be stored. See the logs for errors.

Explanation

Send email action could not be stored in database. To see which actions were stored successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW443E Action of type 'Send email' could not be updated. See the logs for errors.

Explanation

The Send email action could not be updated in database. To see which actions were updated successfully, go to the previous panel of the Administration and Monitoring Console. See the Administration and Monitoring Console logs for error details.

Action

See the error logs, or try again.

CTGDIW444E The recipient email address is invalid.

Explanation

The recipient email address is invalid.

Action

Provide a valid email address for the recipient.

CTGDIW445W Do you want to delete the tombstones for the AssemblyLine *AssemblyLine name* ?

Explanation

A confirmation is requested from the user if the selected tombstones are to be deleted.

Action

If the tombstones are to be deleted click OK. If you do not want to delete the tombstones click Cancel.

CTGDIW446E Unable to load the amc.properties file.

Explanation

See message.

Action

See the Administration and Monitoring Console logs for error details.

CTGDIW447E The Administration and Monitoring Console is unable to delete AssemblyLines associated with the Solution View.

Explanation

The Administration and Monitoring Console is unable to delete AssemblyLines associated with the Solution View.

Action

See the Administration and Monitoring Console logs for error details.

CTGDIW448W Do you want to delete the tombstones with GUID *GUID*?

Explanation

A confirmation is requested from the user whether the selected tombstone is to be deleted.

Action

If the tombstone is to be deleted click OK and if not click Cancel.

CTGDIW449E An error occurred while deleting the tombstones: *error*. Refer to the exception stack trace for more details.

Explanation

There was an error while deleting the tombstone(s).

Action

There was an error while deleting the tombstone(s). Refer to the exception stack trace in logs for more details.

CTGDIW450I The properties file *file name* loaded successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW451I Administration and Monitoring Console database type property set to *database type*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW452I The Administration and Monitoring Console is connected to database *database name* on host *host name* using port *port number*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW453I The jdbc driver *driver name* is loaded successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW454I The conf directory path: *directory path*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW455I Loading schema file *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW456W The property `amc.db.type` is not set and hence setting the database type to *file name*.

Explanation

The property `amc.db.type` is not set, hence defaulting to the default database type.

Action

Ensure the `amc.db.type` property is set to a valid value.

CTGDIW457W The properties file *file name* does not exist.

Explanation

The property `amc.db.type` is not set and will be set to the default database type.

Action

Ensure the `amc.db.type` property is set to a valid value.

CTGDIW458I The database handler class *class name* is used for parsing the XML file and constructing the SQL queries.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW459E No handler found for database *database type* in the properties file *file name*.

Explanation

The database type specified in the `amc.db.type` property in the `amc.properties` is not supported by the Administration and Monitoring Console.

Action

The valid database types supported by the Administration and Monitoring Console are Derby, DB2, Oracle and MS SQL Server.

CTGDIW460I DBUtils initialized successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW461I The handler class *class name* is initialized successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW462E The handler class *class name* cannot be found.

Explanation

The handler class cannot be loaded because it was not found in the classpath.

Action

The handler class cannot be found in the classpath, hence it cannot be loaded. Ensure that the handler class is present in the classpath.

CTGDIW463E The handler class *class name* cannot be accessed.

Explanation

See message.

Action

The handler class cannot be accessed because of some security issues. Refer to the logs for additional information.

CTGDIW464E The handler class *class name* cannot be initialized.

Explanation

See message.

Action

The handler class cannot be initialized. Refer to the logs for additional information.

CTGDIW465E An error occurred while parsing the XML file: *error message*.

Explanation

See message.

Action

Refer to the logs for additional information.

CTGDIW466E The XML file *file name* cannot be found.

Explanation

See message.

Action

Refer to the logs for additional information.

CTGDIW467I The SQL Query executed successfully: *SQL query*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW468W The SQL query execution failed: *SQL query*.

Explanation

See message.

Action

Refer to the logs for additional information.

CTGDIW469I SQL query *SQL query* not executed as the database object already exists.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW470E An rrror occurred while initializing the Administration and Monitoring Console database.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW471E An error occurred while inserting the default local server. Refer to the stack trace for more details.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW472E An exception was encountered while processing the XML data.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW473E None of the tombstones have been deleted from the selected delete criteria.

Explanation

No tombstones were deleted matching the specified delete criteria.

Action

Verify whether the tombstone manager is running or verify that the delete criteria specified is valid.

CTGDIW474I Number of tombstones deleted successfully : *number of tombstones.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW475I The Administration and Monitoring Console database XML file path is *file path*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW476I Successfully loaded the jdbc driver *class name*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW477I The property *amc.db.type* is not set in the *amc.properties* file. Defaulting to Derby Database type.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW478I The database type is set to *type name*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW478E Unable to update the database with the values specified in the checkboxes.
Explanation

Due to an internal database error, the Administration and Monitoring Console was unable to update the values of checkboxes in the database.

Action

See the accompanying exception trace for more information and try again.

CTGDIW479W No log files found for AssemblyLine:
AssemblyLine name* and Config: *Config name
Explanation

The Administration and Monitoring Console was unable to find any log files associated with the specified AssemblyLine.

Action

Verify that a logger is attached to the specified AssemblyLine and that there are log files present. See the accompanying exception and try again.

CTGDIW480W Select the log file(s) to delete.

Explanation

Select the log file(s) which are to be deleted. The user has not selected a single log file.

Action

Delete the log file by selecting the check boxes opposite the names of the log files that are to be deleted.

CTGDIW481W Unable to delete the following log files: *file names*.

Explanation

An error occurred and some of the selected log files were not deleted.

Action

An error occurred and some of the selected log files were not deleted.

CTGDIW482E An error occurred while deleting the log files.

Explanation

An error has occurred while deleting the log files for the AssemblyLine.

Action

An error occurred while deleting the log files. Refer the log file of the IBM Security Directory Integrator server for more information.

CTGDIW483E An error occurred while deleting the log files: *error message*.

Explanation

An error occurred while deleting the log files for the AssemblyLine. The reason for the error is mentioned in the IBM Security Directory Integrator server log file.

Action

An error has occurred while deleting the log files. Refer the error message more information.

CTGDIW484W Delete the selected logs?

Explanation

All the log files which are selected will be deleted on clicking the "Delete" button.

Action

The confirmation window displaying a warning message is displayed because deleting logs is an irreversible action. The log files are permanently deleted from the file system. All the selected log files for the configuration will be deleted from the servers system_logs directory if you click "OK" button. Click "Cancel" button to cancel the action.

CTGDIW485W An error occurred while displaying the log files.

Explanation

An error occurred while displaying the log files.

Action

Refer to the exception stack trace in logs for more details and try again.

CTGDIW486W An error occurred while displaying the log files.

Explanation

An error occurred while displaying the log files.

Action

Refer to the exception stack trace in logs for more details and try again.

CTGDIW487E Unable to establish connection to the remote IBM Security Directory Integrator Server. Log management functionality is not available for the selected Solution View.

Explanation

The Administration and Monitoring Console was unable to connect to the remote IBM Security Directory Integrator Server associated with the Solution View. Log management functionality is not available for the selected Solution View.

Action

Check the remote server associated with this Solution View. Ensure that the remote API engine is running on the remote server. The Administration and Monitoring Console must be able to connect and establish a session with the remote IBM Security Directory Integrator server before it can continue with the current task.

CTGDIW488I This Solution View belongs to a server prior to IBM Security Directory Integrator version 7.0. The user cannot see the log file listing. All log files satisfying the deletion criteria will be deleted when you click delete.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW489W A username and password or keystore and keystore password must be specified in order to log into the remote computer.

Explanation

The user credentials in the form of username and password or keystore and keystore password are required for logging in to the target computer.

Action

Provide the username and password or keystore and keystore password for enabling communication with the target computer.

CTGDIW490W The selected action *action name* is not supported.

Explanation

The selected action is not supported by the Administration and Monitoring Console.

Action

The selected action is not supported by the Administration and Monitoring Console.

CTGDIW491E The Solution View could not be created. Check the logs for errors.

Explanation

The Solution View could not be created. Check the logs for errors.

Action

See the Administration and Monitoring Console logs for more details.

CTGDIW492W The Parent User Task manager object is null and cannot display the panels.

Explanation

The parent utm object is required in order to display the panels. The object is null the panels cannot be displayed.

Action

See the Administration and Monitoring Console logs for more details.

CTGDIW493E The sender email address is invalid.

Explanation

The sender email address is invalid.

Action

Provide a valid email address for the sender.

CTGDIW494I No healthAL details for Solution View: *Solution View name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW495E An error while rolling back database transaction : *error*

Explanation

Check logs for additional information.

Action

Check logs for additional information.

CTGDIW496E The command length exceeds the database column width.

Explanation

The database column length for saving the command is 800 characters. If the command length exceeds 800 characters the Administration and Monitoring Console will not be able to save the command in the database.

Action

Modify the command such that the length of the command is less than 800 characters.

CTGDIW497I The AssemblyLine *Solution View name* has no tombstones to be deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW498E An error *error* occurred while initializing the Administration and Monitoring Console security.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW499E An error *error* occurred while connecting to Action Manager.

Explanation

Verify if Action Manager is running on the port specified in amc.properties file.

Action

Verify if Action Manager is running on the port specified in amc.properties file.

CTGDIW500E An error *error* occurred while writing the SQL file.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW501I Inside the tokenizeSQLCommands method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW502I The total number of sql queries generated is *number of sql queries*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW503I The handler property name for getting the handler class is *property name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW504I Loaded the *file name* file.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW505W The configuration file *file name* does not exist.

Explanation

Administration and Monitoring Console is not able to load the XML file containing the database schema.

Action

Refer to the logs for additional information.

CTGDIW506E An error occurred while reading the configuration XML file *file name*.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW507E An error occurred while closing the input stream.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW508I Inside the `parseXML(InputStream, String)` method of `DBUtils`.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW509I Started parsing the XML file.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW510I Completed parsing the XML file.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW511I Inside the parseXML() method of DBUtils.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW512I Reading the XML file *file name* into the input stream.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW513I Parsing the XML file *file name* using the Handler *Handler name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW514E Error closing the input stream.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW515E An error *error* occurred while connecting to Action Manager.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW516I Unencrypted string is null or empty

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW517I Encrypted string was null or empty.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW518E An error occurred while decrypting property: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW519E An error occurred while initializing of String encryption decryption utility: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW520E An error occurred while encrypting property: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW521E An error occurred while retrieving the information of *Solution View name* solution view: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW522E An error occurred while retrieving the Server information: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW523E An error occurred while creating the Solution View *solution view name*: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW524E An error occurred while rolling back the database transaction: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW525E An error occurred while retrieving the latest Solution View ID: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW526E An error occurred while adding the Solution View details in database: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW527E An error occurred while adding the Solution View properties in database: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW528E An error occurred while adding the Health AssemblyLine details: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW529E An error occurred while committing changes to the database: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW530E An error occurred while creating a solution view from a published solution: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW531E An error occurred while deleting AssemblyLine
details: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW532E An error occurred while adding AssemblyLine
details: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW533E An error occurred while updating Solution View
properties: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW534E An error occurred while retrieving Solution
Views for user *user id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW535W Invalid integer Solution View ID: *Solution
View id.*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW536E An error occurred while deleting Solution View: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW537E An error occurred while executing the SQL query *SQL query: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW538E An error occurred while retrieving the ACL information: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW539E An error occurred while retrieving user information for Solution View *solution view id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW540E An error occurred while retrieving groups with no access to Solution View *solution view id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW541E An error occurred while storing user *user name* with role *role* for Solution View *solution view id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW542E An error occurred while deleting user groups: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW543E An error occurred while retrieving ACL information for Solution View *Solution view id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW544E An error occurred while retrieving the Solution View properties: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW545E An error occurred while retrieving the Health AssemblyLine details for Solution View id *solution view id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW546E An error occurred while retrieving the Local Action Manager Variables for Solution View id *solution view id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW547E An error occurred while disabling auto update for Solution View id *solution view id: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW548E An error occurred while adding the local variable *variable name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW549E An error occurred while updating the local variable *variable name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW550E An error occurred while deleting the local variable *variable name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW551E An error occurred while verifying if the local variable *variable name* exists: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW552E An error occurred while refreshing the Solution View: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW553E An error occurred while deleting the AssemblyLines for Solution View id *solution view id*: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW554E An error occurred while deleting the properties for Solution View id *solution view id*: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW555E An error occurred while retrieving properties for property store *Property Store name*: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW556E An error occurred while refreshing published solution: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW557E An error occurred while initializing the ManageTDISrvBean: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW558E An error *error* occurred while verifying the Local Server.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW559E An error occurred while initializing ViewMonitorBean: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW560E An error occurred while initializing the QuickCreateBean: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW561E An error occurred while getting the start time for AssemblyLine *AssemblyLine name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW562E An error occurred while retrieving the AssemblyLine details: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW563E An error occurred while retrieving the Config for AssemblyLine *AssemblyLine name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW564E An error occurred while initializing the *class name class: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW565E An error occurred while stopping the AssemblyLine *AssemblyLine name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW566E An error occurred while starting the
AssemblyLine *AssemblyLine name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW567E An error occurred while starting the
AssemblyLine *AssemblyLine name in simulate mode: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW568E An error occurred while retrieving the
AssemblyLine details: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW569E An error occurred while retrieving properties:
error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW570E An error occurred while populating the
AssemblyLine table for AssemblyLine *AssemblyLine name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW571E An error occurred while populating the Health AssemblyLine table for Health AssemblyLine *Health AssemblyLine name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW572E An error occurred while retrieving the AssemblyLines for the Solution View *Solution view name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW573E An error occurred while preparing the Properties panel: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW574E An error occurred while refreshing the Properties panel: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW575E An error occurred while retrieving the last stop time for the AssemblyLine *AssemblyLine name: error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW576E An error occurred while obtaining the
AssemblyLine name AssemblyLine statistics: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW577E An error occurred while getting the
AssemblyLine status: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW578E An error occurred while getting the preferred
Solution Views: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW579E An error occurred while getting the Solution
Views for user name user: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW580E An error occurred while getting the IBM
Security Directory Integrator port: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW581E An error occurred while deleting the
AM_LOGS_HISTORY for Solution View ID *Solution View id: error*
Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW582E An error occurred while getting the Solution
View ID for *Solution View Solution View: error*
Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW583E An error *error* occurred while closing the
Statement object.
Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW584E An error occurred while stopping a Config
Instance: *error*
Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW585I An error occurred while executing the SQL query
SQL query: error
Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW586E An error occurred while creating the table
table name: error

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW587E An error *error* occurred while getting the
connector.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW588E An error occurred while getting the
parserConfig for Connector: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW589E An error occurred while getting the Connector
name: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW590E An error occurred while getting the Connector
mode: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW591E An error occurred while getting the parser type associated with Connector: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW592E The Connector Config instance is null.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW593E An error occurred while getting the connector status and will assume its enabled: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW594E An error occurred while getting the connector information on inheritance: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW595E An error *error* occurred while getting the connector information.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW596I Completed processing the Administration and Monitoring Console XML document.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW597I Processing the Primary Key instruction.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW598I Processing the Foreign Key instruction.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW599I Processing the Unique Key instruction.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW600I Constructing the CREATE TABLE SQL query for *table name* table.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW601I Processing the column tag for table for *table name* table.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW602I Processing the autoincrement instruction.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW603I Processing the constraint *constraint type* for *column* column.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW604I The primary key name is *primary key name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW605I The foreign key name is *key name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIW606I Detected remote server version: *server version*.
Disabling tombstone button and Manage properties button.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIW607E An error occurred while getting the meta merge config: *error*

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

**CTGDIW608I No action to be performed for the command
command name.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDIW609E An error occurred while deleting the rule with
Rule ID *rule id*: *error***

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

**CTGDIW610W An error occurred while deleting the file *file
name*:**

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW611E The string *path* is not a valid URL. Malformed Url exception occurred while converting the string to URL.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW612E An error occurred while closing the output stream.

Explanation

Refer to the logs for additional information.

Action

Refer to the logs for additional information.

CTGDIW613E The selected tombstone entry does not exist.

Explanation

The tombstone entry no longer exists in the database. It may have been removed by another application.

Action

Refresh the panel. Check any error logs.

CTGDIW614E A thread in waiting/sleeping/paused state is interrupted by another thread.

Explanation

The tombstone entry no longer exists in the database. It may have been removed by another application.

Action

Refresh the panel. Check any error logs.

CTGDIW615E An error occurred while getting the server id for IBM Security Directory Integrator server on host *host* and port *port*: *error*

Explanation

The tombstone entry no longer exists in the database. It may have been removed by another application.

Action

Refresh the panel. Check any error logs.

CTGDIW616E Conversion of string *string* to number type failed

Explanation

The tombstone entry no longer exists in the database. It may have been removed by another application.

Action

Refresh the panel. Check any error logs.

CTGDIW617E An error occurred while deleting the tombstones.

Explanation

There was a remote API error while deleting the tombstone(s).

Action

Ensure that the remote server is running and try again.

CTGDIW618W Any changes to JDBC or SSL properties will need require a manual restart of the Administration and Monitoring Console. Apply changes to console properties?

Explanation

Confirm updation of console properties.

Action

If you want to save the changes to console properties, click OK, otherwise click Cancel.

CTGDIW619E An error occurred while reading properties using Server API.

Explanation

There was a remote API error while reading properties.

Action

Ensure that the remote server is running and try again.

CTGDIW620E An error occurred while accessing AssemblyLine information using Server API.

Explanation

There was a remote API error.

Action

Ensure that the remote server is running and try again.

CTGDIW621E An error occurred while accessing Config information using Server API.**Explanation**

There was a remote API error.

Action

Ensure that the remote server is running and try again.

CTGDIW622E An error occurred while closing file stream.**Explanation**

An error occurred while closing file stream.

Action

Check error message and try again.

CTGDIW623E An error occurred while rolling back database transaction : *error***Explanation**

Check logs for additional information.

Action

Check logs for additional information.

CTGDIW624E An error while rolling back database transaction : *error***Explanation**

Check logs for additional information.

Action

Check logs for additional information.

CTGDIW625E Select an Action Manager log to delete.**Explanation**

No Action Manager logs were selected for deletion.

Action

Select an Action Manager log for deletion.

CTGDIW626E The End Date is earlier than the Start Date.

Explanation

See the error message.

Action

Select the End Date to be after the Start Date.

CTGDIW627E Unable to find group: *string*.

Explanation

An error occurred while retrieving the specified group, used for setting user privileges.

Action

Check logs for additional information, more specifically SQLExceptions. A problem may have occurred with the database used to store group information.

CTGDIW628I SDI servers earlier than 7.1 version does not support graceful shutdown.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB001W The command did not complete successfully. See previous messages or error logs for details.

Explanation

One or more errors occurred during the execution of the command.

Action

Check the previous messages displayed by the `tdisrvctl` command, or look at the error logs for more details.

CTGDJB002E Unknown value passed for '-op' option.

Explanation

An illegal operation parameter was passed.

Action

Check the `tdisrvctl` command usage for allowed options.

CTGDJB003E The server *hostname* does not support Tombstones. Tombstone support is not available in pre-6.1 servers.

Explanation

The `tdisrvctl` command tried obtaining Tombstones from a pre-6.1 server. Tombstone support has been introduced from v6.1 onward.

Action

Connect to a version 6.1 or later server for viewing Tombstones.

CTGDJB004E Incorrect command usage.

Explanation

The `tdisrvctl` command was invoked by passing unsupported command line options, or unexpected end of argument list was encountered or there was an incorrect usage of the command line options.

Action

Check the `tdisrvctl` command usage and try invoking the `tdisrvctl` command with valid arguments.

CTGDJB005E Unable to get Tombstone manager.

Explanation

The `tdisrvctl` command was unable to connect to the Tombstone manager in the remote server. Probable reason being that the Tombstone feature was incorrectly configured on the server.

Action

Check the remote server API and Tombstone manager settings on the remote server and try executing the `tdisrvctl` command again.

CTGDJB006E Only a single Config can be specified.

Explanation

The `tdisrvctl` command was invoked by passing multiple Configs as a parameter to an option which allows only a single Config to be specified.

Action

Invoke the `tdisrvctl` command by passing only a single Config at a time.

CTGDJB007E No value specified for *option name* option.

Explanation

The `tdisrvctl` command was invoked by passing an option whose value had not been specified. The value is also required.

Action

Check the `tdisrvctl` command usage, and invoke the `tdisrvctl` command again with the correct option and associated value.

CTGDJB008E Only a single AssemblyLine can be specified.

Explanation

The `tdisrvctl` command was invoked by passing multiple `AssemblyLines` as a parameter to an option which allows only a single `AssemblyLine` to be specified.

Action

Invoke the `tdisrvctl` command by passing only a single `AssemblyLine` at a time. Check the `tdisrvctl` command usage.

CTGDJB010E The value for the age option has to be an integer greater than zero (days).

Explanation

The `tdisrvctl` command was invoked by passing a non-integer or a negative value for the `age` (in days) option.

Action

Invoke the `tdisrvctl` command by passing a valid integer (greater than 0) for the specified option of `Tombstone`.

CTGDJB011E Conflicting Tombstone option passed. Use keyword 'all' or specify a set of Tombstone attributes.

Explanation

The `tdisrvctl` command with `Tombstone` option was invoked with contradictory options. Cannot ask for 'all' attributes and 'specific' attributes together.

Action

Either specify the specific `Tombstone` attributes that should be displayed, or ask to be shown all attributes. Not both. See `tdisrvctl` command usage.

CTGDJB012E The 'all' keyword should be the last argument passed.

Explanation

The `tdisrvctl` command with `Tombstone` option was invoked with incorrect options. The 'all' keyword has to be the last argument passed.

Action

See the `tdisrvctl` command usage.

CTGDJB014E The *option switch* option is mandatory.

Explanation

The tdisrvctl command was invoked with a mandatory option not specified.

Action

See the tdisrvctl command usage.

CTGDJB015E Could not locate Config *Config name*.

Explanation

Unable to locate the Config specified by user.

Action

Check whether the Config name specified is correct and exists on the remote machine.

CTGDJB016I Connected to server *hostname and port*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB017I Config started: *Config name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB018I Config already running: *Config name*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB019E Could not start Config: *Config name*

Explanation

Unable to start Config. An internal error occurred because the remote IBM Security Directory Integrator server was not properly setup or the configuration was incorrect. This may also occur because the configuration file was password protected, and the user did not specify a password in the `tdisrvctl` command. Also, if the Config path is incorrect or not fully qualified, `tdisrvctl` will not be able to locate the Config.

Action

See the `tdisrvctl` command error logs for help. Verify the configuration on remote server is properly set up. Additionally, verify the Config file is password protected. If so, then specify the password in the `tdisrvctl` start option using the `-e` switch. Also, ensure that the fully qualified path of the Config file is mentioned exactly as it appears on the remote machine.

CTGDJB020I AssemblyLine running: *AssemblyLine name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB021I AssemblyLine started: *AssemblyLine name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB022E AssemblyLine *AssemblyLine name* not found.

Explanation

Unable to find user specified AssemblyLine. The Assembly Name passed may be incorrect or misspelled.

Action

Check whether the AssemblyLine specified exists in the configuration on the remote server.

**CTGDJB023E Could not start AssemblyLines on the server
*hostname and port.***

Explanation

Some exceptions occurred while starting the AssemblyLines.

Action

Check whether the Configurations and AssemblyLines are correctly set up on the remote server. Also check the tdisrvctl error logs for more information on the errors.

CTGDJB028E The Config *Config name* is not loaded.

Explanation

The user specified stopping of components of a configuration which is already not loaded on the server.

Action

Check whether the Configuration name is correct. Also check the tdisrvctl error logs for more information on the errors.

CTGDJB029I Config stopped: *Config name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB030E Could not stop Config: *Config name.*

Explanation

Some exceptions occurred while stopping the configuration.

Action

Check the tdisrvctl error logs for more information on the errors.

CTGDJB031I AssemblyLine stopped: *AssemblyLine name.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB032E Could not stop AssemblyLine: *AssemblyLine name*.

Explanation

Some exceptions occurred while stopping the AssemblyLine.

Action

Check the tdisrvctl error logs for more information on the errors.

CTGDJB033E AssemblyLine already stopped: *AssemblyLine name*.

Explanation

The user specified AssemblyLine is already not running.

Action

Check the tdisrvctl error logs for more information on the errors.

CTGDJB034E Error occurred while stopping AssemblyLines.

Explanation

Some exceptions occurred while stopping the AssemblyLines.

Action

Check the tdisrvctl error logs for more information on the errors.

CTGDJB039E Cannot connect to server *hostname and port*.

Explanation

Unable to connect to server. This error might occur for one or more of the following reasons: If the server is not running, or the machine on which the server is running is not accessible, or the remote server API engine over RMI is not running, or if remote server API accepts only SSL connections, and the SSL parameters / certificates in the trust and key stores may be incorrect.

Action

Check the tdisrvctl error logs for more information on the reason for connection errors. Try connecting again.

CTGDJB040I The server *hostname and port* **has been shutdown.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB041I Config *Config name* reloaded.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB042E Config *Config name* is not running.

Explanation

The user tried reloading a Config that is not running / loaded. Only already loaded Configs can be reloaded. If the Config is not loaded, then start the Config instead of trying to reload it.

Action

Give the `tdisrvctl -op start` command instead of reload command, or check the name of the Config.

CTGDJB043E One or more Configs could not be reloaded on the server *hostname and port*. Check the previous messages or error logs for details.

Explanation

There were some errors encountered while reloading Configs. One or more Configs failed to reload.

Action

Check the `tdisrvctl` command error logs for details on the errors.

CTGDJB044I All the specified Configs have been successfully reloaded on the server *hostname and port*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB045E The *operator switch* option occurred more than once.

Explanation

The `tdisrvctl` command was invoked with the same parameter passed more than once. Options can be passed only once. For example, the user may have passed the '-h' option twice, which is not allowed.

Action

Pass each option only once.

CTGDJB046E Unknown option *operator switch* encountered. Explanation

The tdisrvctl command was invoked with an unknown option.

Action

See the tdisrvctl command usage and invoke the command with the allowed options only.

CTGDJB047E The *operator switch* option was not specified. This is a mandatory option.

Explanation

The tdisrvctl command was invoked without specifying the -op option.

Action

See the tdisrvctl command usage and invoke the command with the correct and mandatory options specified.

CTGDJB048E It is mandatory to specify Config. 'all' keyword is not allowed with -c option.

Explanation

Instead of passing the Config name, the user asked for ALL Configs. This is not allowed. User must specify the configuration name.

Action

Specify the explicit Config name when invoking the tdisrvctl command. See tdisrvctl command usage.

CTGDJB049I Usage: tdisrvctl [general_options] -op operation [operation_specific_options] general_options: -h host remote server IP address or hostname(default is localhost) -K keystore name of the SSL key database file -p port port number(default is 1099) -P key_pwd key file password -s dir Specifies the working directory where the solution directory is located. -T truststore name of the SSL trust store database file -u userID username(for custom authentication) -v run in verbose mode -w user_pwd user password(for custom authentication) -W trust_pwd trust file password -? display command usage operation: event send custom notification event prop manage Config properties queryop query an AssemblyLine for operations reload reload running Configs report generate Config report or list Configs on remote server shutdown shut down the server srvinfo view IBM Security Directory Integrator server information status view status of Configs or AssemblyLines start start specific Config or AssemblyLines stop stop specific Config or AssemblyLine tombstone view Tombstone entries for specific Config or AssemblyLine deletetombstone delete a tombstone entry debug debug components in a running AssemblyLine To get help for a specific operation: tdisrvctl -op operation -?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB050I The usage for reload operation is: tdisrvctl [general_options] -op reload -c config_list where: -c config_list comma separated list of Configs to reload

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB051I The usage for shutdown operation is: `tdisrvctl [general_options] -op shutdown [-o return_code] [-f]` where: `-o return_code` shutdown server with specified return code `-f` force a controlled shutdown and exit all AssemblyLines

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB052I The usage for srvinfo operation is: `tdisrvctl [general_options] -op srvinfo`

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB053I The usage for status operation is: `tdisrvctl [general_options] -op status [-c config_list | all] [-r AL_list | all] [-listen]` where: `-c config_list` comma separated list of Configs or keyword 'all' `-r AL_list` comma separated list of ALs or keyword 'all' `-listen` start receiving the logs of a running Config or AssemblyLine
Example: To see the status of all loaded Configs and ALs `tdisrvctl [general_options] -op status` To see the status of all running ALs `tdisrvctl [general_options] -op status -r all` To see the status of all components of a particular loaded Config `tdisrvctl [general_options] -op status -c Config.xml -r all` Note: - The keyword 'all' indicates all Configs or AssemblyLines. - The `-listen` option requires exactly one Config or AssemblyLine to be specified.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB054I The usage for the start operation is: `tdisrvctl [general_options] -op start -c config [-e password] [-r AL_list | all] [-s] [-r AL_list -alop opname [{attr1:value1;attr2:value2;attrN:valueN}] | -f filename] [-m config_run_name -o storeName1=value1, storeName2=value2, storeNameN=valueN] [-t] [-listen] [-sync]` where: `-c` config name of config to start `-e password` password of the config file if it is password protected `-r AL_list` comma separated list of AssemblyLines to start or keyword 'all' `-s` simulate mode run AssemblyLine in simulate mode `-alop opname` AssemblyLine operation with required attributes and their values `-f filename` filename to specify the operations `-m config_run_name` run name of config `-o property file list` comma separated list of property store names and values `-t` start a temporary Config `-listen` receive the logs of the specified Config or AssemblyLine `-sync` execute AssemblyLine synchronously Note: - The `-c` option is mandatory. - The keyword 'all' indicates all AssemblyLines. - The `-t` option expects the Config specified in the `-c` option to be located on the client machine. - The `-listen` option requires exactly one Config or AssemblyLine to be specified. - The `-listen` option executes an AssemblyLine synchronously. There is no need to combine it with the `-sync` option. - The `-sync` option requires exactly one AssemblyLine to be specified.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB055I The usage for stop operation is: `tdisrvctl [general_options] -op stop -c config [-r AL_list | all] [-f]` where: `-c config` name of Config `-r AL_list` comma separated list of ALs to stop or keyword 'all' `-f` force a controlled shutdown of AssemblyLines Note: - The `-c` option is mandatory. - The keyword 'all' indicates all AssemblyLines.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB056I The usage for tombstone operation is: `tdisrvctl [general_options] -op tombstone -c config [-r AL_name] [-age n] [[attribute_list] | all]` where: `-age n` display tombstone record for the last 'n' days (default is 1 day) `-c config` name of Config `-r AL_name` name of Asembly Line `all` show all Tombstone attributes `attribute_list`: `-ct` component type `-cn` component name `-cfg` configuration name `-guid` Tombstone entry's guid `-et` event type `-ex` exit code `-stime` component's start time `-ctime` Tombstone create time `-desc` error description `-um` user message `-stat` statistics (valid for ALs only) Example: To see the last 2 days Tombstone entries (all attributes) for Config C1.xml `tdisrvctl [general_options] -op tombstone -c C1.xml -age 2 all` Note: - The `-c` option is mandatory. - Only one of the `-r` or `-t` option is allowed. Not both.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB057E The Config *Config name* is not loaded on the server *hostname and port*.

Explanation

A Config that is not loaded on the server was specified for the 'report' option. Reports can only be generated if the specified Config is loaded on the server.

Action

Check that the Config name specified is correct and that the Config is loaded on the server. Use the `tdisrvctl 'status'` option to obtain a list of the currently loaded Configs on the server. Alternatively, load the Config on the server and then fire the `tdisrvctl` command with the 'report' option.

CTGDJB058I The Config folder on server *hostname and port* is empty.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB059I The usage for report operation is: `tdisrvctl [general_options] -op report [-c config | -l]` where: `-c` config name of the Config whose report is to be generated `-l` list the Configs in the remote server's Config folder Note: - The specified Config must be already loaded on the remote server. - Only one of the `-c` or `-l` option is allowed. Not both.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB060E The server *hostname* does not support 'config' folder. The 'config' folder support is not available in pre-6.1 servers.

Explanation

The `tdisrvctl` command tried obtaining Config listing from a pre-6.1 server. 'config' folder support has been introduced from v6.1 onwards.

Action

Connect to a v6.1 or later server for obtaining listing of Configs in the 'config' folder.

CTGDJB061I The usage for event operation is: `tdisrvctl [general_options] -op event -e event_name [-s source] [-d data]` where: `-e event_name` name of the event to send `-s source` the name of the source invoking the event (default `tdisrvctl`) `-d data` the data (message) to be passed to an event listener (default is null) Note: - All events sent from `tdisrvctl` (`-e` option) are automatically prefixed by the string "user". Example: To send an event "user.process.X.completed" from "admin" `tdisrvctl -h hostname -op event -e "process.X.completed" -s admin -d "Admin triggered event"`.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB062I The event *event name* successfully sent.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB063I The usage for prop operation is: `tdisrvctl [general_options] -op prop -c config [-l] | [[-o store] [[-g key | all] | [-s key=value [-e]] | [-d key]]]` where:
-c config name of the Config to use -l list all the configured property stores -o name of the property store to use -g key get the value of the specified key (or keyword 'all' implying get all keys) -s key=value set the key to the specified value -e encrypt the value when putting in the store (can be used with -s option only) -d key delete the specified key from the store Note: - The -c option is mandatory. The specified Config should be a loaded Config on the remote server. - The -l, -g, -s, and -d options are mutually exclusive, and cannot be used together. - The -e option can be used with only the -s option. - The -o option is mandatory when using the -d option. Examples: To list all property stores for Config C1.xml `tdisrvctl -op prop -c C1.xml -l` To get all properties for Config C1.xml `tdisrvctl -op prop -c C1.xml -g all` To get all properties for Config C1.xml from store MyStore `tdisrvctl -op prop -c C1.xml -o MyStore -g all` To set a property MY_PROP to value MY_VALUE for Config C1.xml in store MyStore and mark it as protected `tdisrvctl -op prop -c C1.xml -o MyStore -s "MY_PROP=MY_VALUE" -e`

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB064E Only one of the options -l, -g, -s, and -d can be specified. They cannot occur together.

Explanation

The tdisrvctl command was invoked with options that are not allowed together. For example, the -l option is used for specifying the list of property stores, and hence cannot be used along with the -o option.

Action

See the usage of the tdisrvctl "prop" option and invoke the command with the appropriate arguments passed.

CTGDJB065E The property store (-o option) is not specified.

Explanation

The tdisrvctl command prop option was invoked without specifying the property store (-o option).

Action

See the usage of the tdisrvctl "prop" option and invoke the command with the appropriate arguments passed.

CTGDJB066E Property store *property store name* does not exist.

Explanation

The tdisrvctl command prop option was invoked with a property store name that does not exist (or was misspelled).

Action

Fire the tdisrvctl command with prop option and -l switch to see the list of available property stores.

CTGDJB067I The property key *property key* does not exist.

Explanation

The tdisrvctl command prop option was invoked with a property key name that does not exist (or was misspelled).

Action

Check the property key name, or view all the available properties by using the -g option with the "all" keyword.

CTGDJB068E The server *hostname* does not support remote client event notification. This feature is not available in pre-6.1 servers.

Explanation

The `tdisrvctl` command was used to send an event notification to a pre-6.1 server. User event notification support has been introduced from v6.1 onwards.

Action

Connect to a v6.1 or later server for sending remote client event notifications.

CTGDJB069E The server *hostname* does not support common APIs for IBM Security Directory Integrator Property management. This feature is not available in pre-6.1 servers.

Explanation

The `tdisrvctl` command was used for property store management of a pre-6.1 server. Common APIs for IBM Security Directory Integrator property store management were introduced from version 6.1 onwards.

Action

Connect to a version 6.1 or later server for remote IBM Security Directory Integrator property store management.

CTGDJB070I The property *key name* has been set and committed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB071I The property *key name* successfully deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB072I The usage for query operation is: `tdisrvctl [general_options] -op queryop -c config -r AL_name` where: `-c` config name of a loaded configuration `-r AL_name` valid AssemblyLine in the specified configuration

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB073I Return Code: *return code*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB074I Determining whether Tombstone is supported.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB075I Server version: *version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB076I Start Date:*date*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB077I End Date :*date*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB078I Config ID :*Config ID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB079I Number of Tombstones found: *number of tombstones*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB080I Determining whether remote client event notification is supported.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB081I Server version: *version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB082I Determining whether IBM Security Directory Integrator Properties is supported.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB083I Server version: *version*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB084I In displayPropertyStoreList method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB085I In displayPropertyValues method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB086I In setTDIPropertyValue method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB087I In deleteTDIProperty method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB088I The server is: *server name*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB089E Config instance not started. Exception occurred: *exception***Explanation**

See message.

Action

Review the exception to find further details on the error.

CTGDJB090I In viewServerInformation method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB091I In sendEventNotification method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB092I In viewStatus method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB093I In startComponents method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB094I In stopComponents method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB095I In viewAllALStatus method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB096I Number of running Configs:*number of Configs.***Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB098I Number of running Configs:*number of Configs.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB099I Attempting to connect to IBM Security Directory Integrator server: *hostname: port.*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB100I Using custom authentication. Username:
username.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB102I In shutdownServer method. Return code
return_code passed to method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB103I Determining whether Config folder feature is supported.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB104I Server version: *version*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB105I In reloadConfigs method.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB106W Duplicate argument: '*token*'. Argument is ignored.**Explanation**

The user passed duplicate arguments while calling the command. The command has discarded the extraneous ones.

Action

Refer the help for command, and pass appropriate command line parameters while invoking the command.

CTGDJB107I Parsing general options.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB108I General Options: *options*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB109E Unable to determine server version. Cannot continue.

Explanation

The tdisrvctl utility was unable to determine the IBM Security Directory Integrator server version. It needs to know this to detect whether Tombstone Manager is present or not.

Action

Check the remote IBM Security Directory Integrator server version that you are connecting to using tdisrvctl. The tombstone support has been introduced in the IBM Security Directory Integrator 6.0 version of the product.

CTGDJB110E Unable to obtain Tombstones.

Explanation

Some exception occurred while trying to obtain tombstones. This could be because of some error in connecting to the remote IBM Security Directory Integrator server, or because of some other error while communicating with the IBM Security Directory Integrator server.

Action

Check the error logs for other error messages, or try again.

CTGDJB111E Invalid age: *age value*.

Explanation

The tdisrvctl command was invoked by passing a non-integer or a negative value for the age (in days) option.

Action

Invoke the tdisrvctl command by passing a valid integer (greater than 0) for the specified option of Tombstone.

CTGDJB112E Error while processing shutdown return code.

Explanation

There was an error in converting the shutdown code into an integer value.

Action

Ensure that the passed shutdown code is an integer value.

CTGDJB113E Unable to determine server version. Cannot continue.

Explanation

The tdisrvctl utility was unable to determine the server version, so as to detect if event notification APIs are supported in this particular server release or not.

Action

Connect to a v6.1 or later server for sending remote client event notifications.

CTGDJB114E Error while trying to obtain list of property stores for Config: *Config name*.

Explanation

The tdisrvctl utility encountered an internal error while trying to obtain the list of configured property stores from the remote IBM Security Directory Integrator server. This may have occurred because the property store list in the remote server has got corrupted, or maybe an incompatible version of the remote IBM Security Directory Integrator server is being used.

Action

Check if the property stores list can be correctly seen in the ibmditk. Also, check the Problem Determination Guide for problems related to the property store. Ensure that the version of tdisrvctl and the version of the remote IBM Security Directory Integrator server match. The property store feature has been introduced in version 6.1 of IBM Security Directory Integrator.

CTGDJB115E Error while trying to obtain list of property stores for Config: *Config name*.

Explanation

The tdisrvctl utility encountered an internal error while trying to obtain the list of configured property stores from the remote IBM Security Directory Integrator server. This may have occurred because the property store list in the remote server has got corrupted, or maybe an incompatible version of the remote IBM Security Directory Integrator server is being used.

Action

Check if the property stores list can be correctly seen in the ibmditk. Also, check the Problem Determination Guide for problems related to the property store. Ensure that the version of tdisrvctl and the version of the remote IBM Security Directory Integrator server match. The property store feature has been introduced in version 6.1 of IBM Security Directory Integrator.

CTGDJB116E Error while trying to obtain property for Config:*Config name*.

Explanation

The tdisrvctl utility encountered an internal error while trying to obtain the properties of a particular store from the remote IBM Security Directory Integrator

server. This may have occurred because the property store list in the remote server has got corrupted, or maybe an incompatible version of the remote IBM Security Directory Integrator server is being used.

Action

Check if the property values can be correctly seen in the `ibmditk`. Also, check the Problem Determination Guide for problems related to the property store. Ensure that the version of `tdisrvctl` and the version of the remote IBM Security Directory Integrator server match. The property store feature has been introduced in version 6.1 of IBM Security Directory Integrator. Also have a look at the output messages of the `tdisrvctl` command.

CTGDJB117E Error while trying to set property for Config:*Config name*.

Explanation

The `tdisrvctl` utility encountered an internal error while trying to set a property in a particular store in the remote IBM Security Directory Integrator server. This may have occurred because the property store in the remote server has got corrupted, or maybe an incompatible version of the remote IBM Security Directory Integrator server is being used.

Action

Check if the property values can be correctly set in the `ibmditk`. Also, check the Problem Determination Guide for problems related to the property store. Ensure that the version of `tdisrvctl` and the version of the remote IBM Security Directory Integrator server match. The property store feature has been introduced in version 6.1 of IBM Security Directory Integrator. Also have a look at the output messages of the `tdisrvctl` command. Try again.

CTGDJB118E Error while trying to delete property '*key name*' for Config:*Config name*

Explanation

The `tdisrvctl` utility encountered an internal error while trying to delete a property in a particular store in the remote IBM Security Directory Integrator server. This may have occurred because the property store in the remote server has got corrupted, or maybe an incompatible version of the remote IBM Security Directory Integrator server is being used. This would also happen in-case the particular property store is READ-ONLY.

Action

Check if the property values can be correctly set in the `ibmditk`. Also, check the Problem Determination Guide for problems related to the property store. Ensure that the version of `tdisrvctl` and the version of the remote IBM Security Directory Integrator server match. The property store feature has been introduced in version 6.1 of IBM Security Directory Integrator. Also have a look at the output messages of the `tdisrvctl` command. Ensure that the particular property store is not READ-ONLY. Try again.

CTGDJB119E The KEY=VALUE format should have been specified for *property key and value*

Explanation

The tdisrvctl command was invoked incorrectly.

Action

See the command usage and try again. Very double quotes are used to group arguments that have spaces.

CTGDJB120E Unable to retrieve server information.

Explanation

The tdisrvctl utility encountered an internal error while trying to obtain the remote IBM Security Directory Integrator server host details.

Action

Ensure that the remote IBM Security Directory Integrator server is of version 6.0 or above. Also ensure that there are no connection errors while connecting to IBM Security Directory Integrator server, and the IBM Security Directory Integrator server has its remote server API engine is turned on.

CTGDJB121E Error while sending custom event notification: event name=*event name*, event source=*event source*, event data=*event data*.

Explanation

The tdisrvctl utility encountered an error while trying to send a custom notification event.

Action

Have a look at the log trace, or the server logs to find out the problem. Ability to send custom notification was added in IBM Security Directory Integrator version 6.1. Ensure that you are using a compatible version of IBM Security Directory Integrator server. Try sending the event again.

CTGDJB122E Unable to get the Config info or stop the Config.

Explanation

The tdisrvctl utility was unable to obtain handle to the remote Config to stop.

Action

Check the exception, or previous messages. Also have a look at the server logs. Try again.

CTGDJB123E Unable to get details for AssemblyLines.

Explanation

The tdisrvctl utility was unable to get details for AssemblyLines. This may happen because the IBM Security Directory Integrator server version does not match the tdisrvctl utility version, or some other internal server error occurred. The AssemblyLine or the Config could also be corrupted.

Action

Check the exception trace, or the command output. Also check the server logs. Try again.

CTGDJB125E Unable to get list of all running Configs.

Explanation

The tdisrvctl utility encountered an error while trying to obtain the list of all running configs. This may happen because the IBM Security Directory Integrator server version does not match the tdisrvctl utility version, or some other internal server error occurred.

Action

Ensure that the tdisrvctl and remote IBM Security Directory Integrator server versions match. Also look into the exception trace and the server logs. Try again.

CTGDJB126E Unable to get list of all Configs.

Explanation

An internal error occurred while trying to obtain the list of all configs. This occurred because of m_Session.listAllConfigurations() method threw an error.

Action

Ensure that the tdisrvctl and remote IBM Security Directory Integrator server versions match. Also look into the exception trace and the server logs. Try again.

CTGDJB127E Error while getting assembly line details.

Explanation

The tdisrvctl utility was unable to get details for AssemblyLines. This may happen because the IBM Security Directory Integrator server version does not match the tdisrvctl utility version, or some other internal server error occurred. The AssemblyLine or the Config could also be corrupted.

Action

Check the exception trace, or the command output. Also check the server logs. Try again.

CTGDJB128E Error while getting Connector library details.

Explanation

The tdisrvctl utility was unable to get details for Connector Library. This may happen because the IBM Security Directory Integrator server version does not match the tdisrvctl utility version, or some other internal server error occurred. The Config could also be corrupted.

Action

Check the exception trace, or the command output. Also check the server logs. Try again.

CTGDJB129E Error while getting Parser library details.

Explanation

The tdisrvctl utility was unable to get details for Parser Library. This may happen because the IBM Security Directory Integrator server version does not match the tdisrvctl utility version, or some other internal server error occurred. The Config could also be corrupted.

Action

Check the exception trace, or the command output. Also check the server logs. Try again.

CTGDJB130E Error while getting script library details.

Explanation

The tdisrvctl utility was unable to get details for Script Library. This may happen because the IBM Security Directory Integrator server version does not match the tdisrvctl utility version, or some other internal server error occurred. The Config could also be corrupted.

Action

Check the exception trace, or the command output. Also check the server logs. Try again.

CTGDJB131E Error while getting function library details.

Explanation

The tdisrvctl utility was unable to get details for Function Library. This may happen because the IBM Security Directory Integrator server version does not match the tdisrvctl utility version, or some other internal server error occurred. The Config could also be corrupted.

Action

Check the exception trace, or the command output. Also check the server logs. Try again.

CTGDJB132E Unable to determine server version. Cannot continue.

Explanation

The tdisrvctl utility was unable to determine the server version, so as to detect if config folder feature is supported in this particular server release or not.

Action

Connect to a v6.1 or later server for viewing configs in the config folder.

CTGDJB133E Unable to get list of all Configs.

Explanation

An internal error occurred while trying to obtain the list of all configs. This occurred because of Session.listAllConfigurations() method threw an error.

Action

Ensure that the tdisrvctl and remote IBM Security Directory Integrator server versions match. Also look into the exception trace and the server logs. Try again.

CTGDJB134E Error while retrieving list of loaded Configs.

Explanation

An internal error occurred while trying to obtain the list of all loaded configs on the remote IBM Security Directory Integrator server. This occurred because Session.getConfigInstances() method threw an error.

Action

Ensure that the tdisrvctl and remote IBM Security Directory Integrator server versions match. Also look into the exception trace and server logs. Try again.

CTGDJB135W Already reached the end of argument list.

Explanation

While parsing the arguments, the tdisrvctl utility encountered an unexpected end of arguments.

Action

Check the command usage and try again.

CTGDJB136I Argument at index *index*: *value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB137I Configuration: *configuration name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB138E AssemblyLine *AssemblyLine name* not found.

Explanation

Unable to find user specified AssemblyLine. The Assembly Name passed may be incorrect or misspelled.

Action

Check whether the AssemblyLine specified exists in the configuration on the remote server.

CTGDJB139I No operations exposed by the AssemblyLine.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB140E The Config *Config name* is not loaded.

Explanation

The Config specified for the 'queryop' option is not loaded on the server.

Action

Verify the Config name is correct.

CTGDJB141E The server *hostname* does not support deletion of tombstones. Delete tombstone support is not available in pre-7.0 servers.

Explanation

The tdisrvctl command tried deleting tombstones from a pre-7.0 server. Deletion of tombstones has been introduced from v7.0 onward.

Action

Connect to a version 7.0 or later server for deleting tombstones.

CTGDJB142I The usage for the tombstone deletion operation is: `tdisrvctl [general_options] -op deletetombstone -guid 'GUID # '` where: `-guid 'GUID # '` is the unique identifier for the tombstone to be deleted. Note: - GUID for a tombstone can be obtained by viewing a tombstone

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB143I Tombstone with guid *GUID* successfully deleted.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB144I Temp configs cannot be run with password specified.

Explanation

The `tdisrvctl` command was invoked by specifying the `-t` (temp config) option in a combination with the `-e` (password) option, but temp configs cannot be started with a password.

Action

Remove either the `-t` or `-e` option in order to successfully run the command.

CTGDJB145E It is mandatory to specify an AssemblyLine name. '*keyword*' keyword is not allowed.

Explanation

Instead of passing the AssemblyLine name, the user asked for ALL AssemblyLines. This is not allowed. User must specify the AssemblyLine name.

Action

Specify the explicit AssemblyLine name when invoking the `tdisrvctl` command. See `tdisrvctl` command usage.

CTGDJB146E Option '*option*' is not allowed for operation '*option*'.

Explanation

The user specified an option which is not supported for the specified operation.

Action

See tdisrvctl command usage.

CTGDJB147I Listening for AssemblyLine messages...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB148I Listening for Config messages...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB149I In debugComponents method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB150E The AssemblyLine *AL name* is not running.

Explanation

The user specified debugging of components of an AssemblyLine that is not running on the server.

Action

Check whether the AssemblyLine name is correct. Also check the tdisrvctl error logs for more information on the errors.

CTGDJB151E Could not set debug mode to *component name* component.

Explanation

The user specified a component that does not exist in the specified AssemblyLine.

Action

Check whether the component name is correct. Also check the tdisrvctl error logs for more information on the errors.

CTGDJB152I The usage for the debug operation is: `tdisrvctl [general_options] -op debug -c config -r assembly_line [-alc al_component] -on/off` where: `-c config` config instance ID `-r assembly_line` name of the AssemblyLine `-alc al_component` name of the AssemblyLine component `-on` flag to enable debug mode `-off` flag to disable debug mode Note: - The `-c` and `-r` options are mandatory and require exactly one Config/AssemblyLine to be specified. - If `-alc` option is not specified all components in the specified AssemblyLine will be affected. Examples: To view the Debug mode value of the components in the AssemblyLines of a specified Config `tdisrvctl -op report -c config` To enable the debug mode for all components in the running AssemblyLine `al2` `tdisrvctl -op debug -c config_name -r al2 -on` To disable the debug mode for specified components in the running AssemblyLine `al3` `tdisrvctl -op debug -c config_name -r al3 -alc fread,httpServer,myconn -off`

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB153I AssemblyLine *AssemblyLine name* completed successfully. Statistics: *AssemblyLine statistics*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB154I AssemblyLine *AssemblyLine name* failed with exception: *exception* Statistics: *AssemblyLine statistics*
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB155I Last AssemblyLine Entry: *Entry object*
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJB156W Could not retrieve last AssemblyLine Entry: *exception*

Explanation

The last Entry of the executed AssemblyLine cannot be retrieved from the Server. Probably it contains Attribute values which do not implement the java.io.Serializable interface.

Action

Check the configuration of the AssemblyLine.

CTGDKI001I The 'java.naming.factory.initial' is set to 'com.ibm.dsm12.jndi.DSML2InitialContextFactory'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIU001E Invalid day of the month, '*day*', was entered for the schedule time. Only 1-31 are valid days of the month.

Explanation

Specified a day of the month that was not valid for the schedule time in the Timer Connector. Valid days of the month that can be specified are 1-31.

Action

Specify a day of the month that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU002E Invalid day of month, '*day*', was entered for the schedule time in February. Only 1-29 are valid days of the month in February.

Explanation

Specified a day of the month that was not valid for the schedule time in February in the Timer Connector. Valid days of the month that can be specified are 1-29 for February.

Action

Specify a day of the month in February that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU003E Invalid day of month, '*day*', was entered for the schedule time in month '*month*'. Only 1-30 are valid days of the months in April, June, September, or November.

Explanation

Specified a day of the month that was not valid for the schedule time in the Timer Connector. Valid days of the month that can be specified are 1-30 for April, June, September, or November.

Action

Specify a day of the month that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU004E Invalid day of the month, '*day*', was entered for the schedule time. Only 1-31 are valid days of the month.

Explanation

Specified a day of the month that was not valid for the schedule time in the Timer Connector. Valid days of the month that can be specified are 1-31.

Action

Specify a day of the month that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU005E Invalid month, '*month*', was entered for the schedule time. Only 0-11 are valid months.

Explanation

Specified a month that was not valid for the schedule time in the Timer Connector. Valid months that can be specified are 0-11.

Action

Specify a month that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU006E Invalid day of week, '*day of week*', was entered for the schedule time. Only 1-7 are valid days of the week.

Explanation

Specified a day of week that was not valid for the schedule time in the Timer Connector. Valid day of week that can be specified are 1-7.

Action

Specify a day of week that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU007E Invalid hour, '*hour*', was entered for the schedule time. Only 0-23 are valid hours.

Explanation

Specified a hour that was not valid for the schedule time in the Timer Connector. Valid hour that can be specified are 0-23.

Action

Specify a hour amount that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU008E Invalid minute, '*minute*', was entered for the schedule time. Only 0-59 are valid minutes.

Explanation

Specified a minute that was not valid for the schedule time in the Timer Connector. Valid minutes that can be specified are 0-59.

Action

Specify a minute amount that is valid. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU009I The 'schedule' parameter converted to the masked format: '*masked schedule*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIU010E The 'schedule' parameter must be set to use the **Timer Connector**.

Explanation

The required parameter schedule was not specified in the Timer Connector.

Action

Specify the schedule parameter in the Connector.

CTGDIU011E Bad syntax for specified for the schedule. Valid syntax: <month> <mday> <dayofweek> <hour> <minute>

Explanation

Invalid syntax was specified for the schedule in the Timer Connector.

Action

Specify a valid syntax for the schedule. The contents of the schedule, month, weekday, hours, and day parameters should be reviewed to ensure valid parameters have been set for the schedule time.

CTGDIU012I Next run of Timer Connector will be at '*timestamp*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIU013I Sleeping for *number of seconds* seconds. Will wake up at '*timestamp*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIU014I Sleeping for *number of seconds* seconds.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP651I The connector will try to reprocess message: *msgID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP652I The connector will delete message: *msgID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP653I An HTTP client connection failed with error: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP654I Error checking task failed with error: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP655W Message: *msgID* from External system: *extSys* is with status 'HOLD'.

Explanation

The IF server could not reprocess an output queue message flagged with error.

Action

Set Action on error parameter to Retry/Delete or manually retry/delete the message from Message Reprocessing application.

CTGDJP656E The *variable name* parameter must be set to use the Connector.

Explanation

This error occurs if the required parameters for the connector are empty.

Action

Set the required parameters for the connector.

CTGDJP657E The *variable name* parameter must be set to a valid number.

Explanation

This error occurs if the parameter value is not valid.

Action

It should be a valid number.

CTGDJP658E The *variable name* parameter value must be within *Minimum Value* to *Maximum Value*.

Explanation

This error occurs if the parameter value is not within minimum and maximum values defined.

Action

The parameter value should be within minimum and maximum values defined.

CTGDJP601I New MxConnIterator instance created.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP602I New MxConnSync instance created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP603I New MxConnDelete instance created.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP604I Performing search.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJP605E Missing attribute for root MBO: *mboName*.**Explanation**

The provided entry does not contain an Attribute for the root MBO.

Action

Check the provided entry.

**CTGDKO001E Unable to open '*file name*' for modification.
An exception occurred: *exception info*****Explanation**

The file indicated in the error message that must be altered by the Update Installer cannot be opened.

Action

Contact IBM support.

CTGDKO002E Error closing '*file name*'. An exception occurred: *exception info*

Explanation

An error occurred while closing a file. If the file was being read, this error may be ignored. If the file was being written, all of the data may not have been written correctly.

Action

Inspect the file mentioned in the error message for correctness.

CTGDKO003E Usage: ASCIIFileUpdate file search replacement [LINE|TEXT]

Explanation

An incorrect call was made to ASCIIFileUpdate.

Action

If this message is seen while running the Update Installer, contact IBM support.

CTGDKO004E Unable to find '*file name*'.

Explanation

The file indicated in the error message that must be altered by the Update Installer cannot be found.

Action

Contact IBM support.

CTGDKO005E Error reading '*file name*'. An exception occurred: *exception info*

Explanation

The file indicated in the error message is not altered.

Action

Run the Update Installer again.

CTGDKO006E Error reading from input stream. An exception occurred: *exception info*

Explanation

An error occurred while reading the input stream from an opened file. The operation being performed did not complete.

Action

Run the Update Installer again.

CTGDKO007E Error processing file '*file name*'. An exception occurred: *exception info*

Explanation

The file indicated in the error message could not be read. The operation being performed did not complete.

Action

Run the Update Installer again.

CTGDKO008E Unable to create script file '*file name*'. An exception occurred: *exception info*

Explanation

An error occurred while trying to create a temporary script for execution.

Action

Inspect the accompanying exception information to fix the error and run the Update Installer again.

CTGDKO009E Error while executing an operating system command. An exception occurred: *exception info*

Explanation

An error occurred while executing a shell script.

Action

Inspect the accompanying exception information to fix the error and run the Update Installer again.

CTGDKO010W While executing an operating system command, a non-zero return code was returned. Return code=*return code*; Message: *message*

Explanation

A non-zero return code was found while executing a shell script.

Action

Inspect the additional information in the message. If this information indicates a fatal error, run the Update Installer again.

CTGDKO011I *component* already has this fix applied and will not be updated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO012E Unable to process fix file '*file name*'.

Explanation

The Update Installer was unable to process the fix file specified.

Action

Ensure the file specified is correct and exists. If so, contact IBM support.

CTGDKO013E The specified install directory '*directory*' does not exist.

Explanation

The Update Installer was unable to find the specified install directory.

Action

Contact IBM support.

CTGDKO014E No .registry file was found in the install directory, the file was empty, or it could not be read.

Explanation

The Update Installer was unable to find the .registry file in the install directory.

Action

Ensure the directory specified is correct and contains the .registry file. If it does, contact IBM support.

CTGDKO015E Unable to open the .registry file for writing.

Explanation

The fix has been applied, but the .registry file could not be updated.

Action

Reapply the fix, or update the .registry file manually.

CTGDKO016E Unable to create file or directory '*file or directory name*' when extracting from '*file name*'.

Explanation

A file or directory could not be created.

Action

Ensure that permissions are correct and there is enough space on the system and run the Update Installer again.

**CTGDKO017E Unable to extract '*file name*' from '*zip file*'.
An exception occurred: *exception info***

Explanation

An error occurred while attempting to extract a file from an archive.

Action

Inspect the exception information to fix the problem. If the problem persists, contact IBM support.

CTGDKO018E File '*file name*' does not exist in archive '*zip file*'.

Explanation

A file that should be present in the indicated archive cannot be found.

Action

Contact IBM support.

CTGDKO019E Unable to process .registry file in install directory '*directory*'.

Explanation

The .registry file in the indicated install directory could not be processed.

Action

See other messages issued for further information.

CTGDKO020I Unable to rollback; there are no fixes applied to this installation.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO021I Rolling back '*fix name*' using backup directory '*directory*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO022E Unable to create backup directory '*directory*' for fix '*fix name*'.

Explanation

The directory which will be used for backup files for this fix cannot be created.

Action

Ensure that permissions are correct and there is enough space on the system. Create the directory manually or run the Update Installer again.

CTGDKO023I Applying fix '*fix name*' using backup directory '*directory*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO024E The current fix cannot be applied because '*prereq*' is a pre-requisite.

Explanation

The installation is missing a pre-requisite fix.

Action

Apply the pre-requisite fix and run the Update Installer for this fix again.

CTGDKO025I The fix specified is already installed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO026I Backup directories will not be cleared, because the current fix is being applied to previously missing components.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO027I Updating *component*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO028E Unrecognized component '*component*' in fix.

Explanation

The fix is applied, but the fix file contains information about a component that is not valid.

Action

Contact IBM support.

CTGDKO029E During application of a fix to the Embedded Web Platform component, a required JAR file was not found.

Explanation

The fix file indicated and update to the Embedded Web Platform, but the JAR file which contains that fix cannot be found.

Action

Contact IBM support.

CTGDKO030I Usage: applyUpdates (-queryreg | -rollback | -update fix_file.zip [-clean [-silent]] | -queryfix fix_file.zip -enroll lum_file.zip -?

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO031I Backup directories will not be cleared, because this fix is not a fixpack.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO032E The level of the current installation is '*level*'. The level must be between '*number*' and '*number*' to apply this fix.**Explanation**

The current installation is not at an appropriate level to apply this fix.

Action

If the level of the current installation is greater than the maximum level, this fix does not need to be applied. Otherwise, bring the current installation up to the required level before installing this fix.

CTGDKO033I During installation of this fixpack, existing backup directories will be deleted.Are you sure you want to continue? [Y/N]:**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO034I Argument *name value*.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO035I The name of the LWI jar is: *jar name*;
Configuration ID is: *Configuration ID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO036I The fix will not be installed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO037I Final backup directory is: *directory*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO038I Reading manifest file...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO039I Reading .registry file...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO040I LWI JAR name: *jar_name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO041I LWI Service name: *service_name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO042I Call amcmigrate: *boolean*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO043I Unable to populate registry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO044I Found applied fix: *fix_name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO045I Updating .registry file...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO046I The file *file name* in the archive zip file is empty.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO047I Fix file is empty, unable to continue.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO048I Unable to read fix file '*file name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO049I File not found: *file name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO050I Unknown operating system: *operating system*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO051I Backing up *source file to target file*...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO052I Looking at *file name*...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO053I Writing *file name*...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO054I Creating directory *directory*...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO055I Applying fix, but it may be necessary to rollback and run ibmditk -tdishutdown before fix is applied correctly.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO056I No license to enroll.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO057I The full license is already enrolled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO058I The trial license is already enrolled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO059I Trial license successfully enrolled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO060E The trial license failed to enroll due to an internal error.

Explanation

An internal error has caused the trial license enrollment to fail.

Action

Attempt the license enrollment again. If the problem persists, contact IBM support.

CTGDKO061I Enrolling the full license requires that the trial license already be enrolled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO062I Full license successfully enrolled.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKO063E Full license failed to enroll due to an internal error.

Explanation

An internal error has caused the full license enrollment to fail.

Action

Attempt the license enrollment again. If the problem persists, contact IBM support.

CTGDKO064E Unrecognized license type: *license type*.

Explanation

An internal error has occurred.

Action

Contact IBM support.

CTGDKO065E An internal license enrollment error has occurred. Message: *message*

Explanation

An internal error has occurred.

Action

Attempt the enrollment again. If the problem persists, contact IBM support.

CTGDKO066E An internal license enrollment error has occurred. An exception occurred: *exception info*

Explanation

An internal error has occurred.

Action

Attempt the enrollment again. If the problem persists, contact IBM support.

CTGDKO067E Cannot find the full license file: *file name*.

Explanation

An internal error has occurred.

Action

Contact IBM support.

CTGDKO068E The license nodelock file '*file name*' does not contain valid license data.

Explanation

The license nodelock file does not contain valid data.

Action

Contact IBM support.

CTGDKO069E Fix pack installation has been rolled back as an error has occurred while installing the fix pack.

Explanation

There could be a problem in execution of a system command or insufficient disk space.

Action

Please see the logs for more details.

CTGDKO070E Unable to delete file or directory '*file or directory name*' .

Explanation

A file or directory could not be deleted.

Action

Ensure that permissions are correct and run the Update Installer again.

CTGDIR201E Either the 'url' or 'puturl' parameter must be set to use the URL Connector.

Explanation

The required parameter url or puturl was not specified in the URL Connector.

Action

Specify either the puturl or url parameter in the Connector.

CTGDIZ801E SOAPHeaderOutputAttributes class constructor failed.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDIZ802E Could not create Document Builder. Exception occurred: *exception*

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDIZ803E The java.lang.String passed is null.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDIZ804E Exception occurred while transforming DOM to String: *exception*

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDIZ805E The `org.w3c.dom.Node` passed is null.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDIZ806I Registered class '*class name*' for '*queue name*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ807E Invalid style '*style name*'. The supported styles are `Style.RPC` and `Style.DOCUMENT`.

Explanation

The specified WSDL file describes an operation of style that is not allowed.

Action

Select other operation from the specified WSDL file or use other WSDL file.

CTGDIZ808I The operation has *number of parameters* parameters.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ809E Number of parameters does not match WSDL. Expected *number of parameters* parameters, but received *number of parameters* parameters.

Explanation

The number of parameters for the operation specified in the entry or Java object, passed to the Function Component does not match the number of parameters specified in the WSDL file.

Action

Ensure the parameters match the parameters for the operation, specified in the WSDL file.

CTGDIZ810I Number of parameters to retrieve: *number of parameters*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ811I Starting to serialize the SOAP message Body.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ812I Must specify return type.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ813I Completed serializing the SOAP message Body.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ814I About to register class '*class name*' for XML QName.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ815I Registering class for XML QName '*XML qualified name*' ...

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ816I Completed registering class for XML QName.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ817E Cannot process SOAP response message: HTTP Content-type header is missing.

Explanation

The content type of the resource that is referenced is unknown. The URL of the web service provider cannot be used to get the content type.

Action

Specify valid URL of the web service provider.

CTGDIZ818E Unsupported content type *content type*.

Explanation

The web service provider has set up content type that is not supported.

Action

Ensure the web service provider has set up valid content type.

CTGDIZ819E The org.w3c.dom.Node passed is null.**Explanation**

An attribute that represents the SOAP body or the SOAP header is missing.

Action

Specify attributes that represent the SOAP body and SOAP header in the entry.

CTGDIZ820E Parameters must not be empty.**Explanation**

WSDL URL and operation name must be specified.

Action

Specify WSDL URL and operation name.

CTGDIZ821E SOAP operation '*operation name*' not found in WSDL '*WSDL URL*'.**Explanation**

SOAP operation was not found in the WSDL.

Action

Specify WSDL file that defines an operation.

CTGDIZ822E WSDL filename must not be empty!**Explanation**

The required parameter wsdlFile was not specified in the Axis Easy Web Service Server Connector.

Action

Specify the wsdlFile parameter in the Connector.

CTGDIZ823E Could not close file stream.**Explanation**

An I/O error occurred.

Action

Contact IBM support.

CTGDIZ824E The object has not been created properly.

Explanation

Internal error has occurred.

Action

Contact IBM support.

CTGDIZ825E Parameter '*parameter name*' of operation '*operation name*' is of an unsupported type: '*parameter type*'.

Explanation

The operation specifies parameter of Java type that cannot be mapped to xsd type.

Action

Ensure the operation has no parameters of unsupported type.

CTGDIZ826E Great-Grandparent config is not an instance of AssemblyLineConfig: *class name*.

Explanation

Great-Grandparent config is not an instance of AssemblyLineConfig.

Action

Contact IBM support.

CTGDIZ827I The web service operation is *name of operation*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ828E Error response received while invoking SOAP web service. The server returned: *HTTP response code*.

Explanation

The HTTP server hosting the SOAP web service returned an error response code.

Action

Examine the response code. Verify the web service is operational.

CTGDJL001W The 'PageSize' parameter set to an invalid value '*parameter value*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid PageSize parameter in the Connector if the default value is not wanted.

CTGDJL002W The 'PageSize' parameter was missing. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid PageSize parameter in the Connector if the default value is not wanted.

CTGDJL003W The 'PageSize' parameter is set to '*parameter value*' which is out of range. Valid range is between 1-'*number*'. The default value '*parameter value*' will be used instead.

Explanation

See message.

Action

Specify a valid PageSize parameter in the Connector if the default value is not wanted.

CTGDJL004I Modifying global group entry. The supplied member list is empty so all group members will be removed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJL005I Modifying local group entry. The supplied member list is empty so all group members will be removed.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ301I SOAP Body: ''SOAP body''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ302E Invalid value for 'returnXMLType': *parameter value*.

Explanation

See message.

Action

Specify a valid 'returnXMLType' parameter in the Function Component.

CTGDIZ303E Invalid value for 'inputXMLType': *parameter value*.

Explanation

See message.

Action

Specify a valid 'inputXMLType' parameter in the Function Component.

CTGDIZ304E The required parameter 'headerAndBodyTagsPresent' is missing.

Explanation

See message.

Action

Specify a valid 'headerAndBodyTagsPresent' parameter in the Function Component.

CTGDIZ305E Entry Attribute ''attribute name'' is missing.
Explanation

See message.

Action

Check the attributes in the entry.

CTGDIZ306I Unwrapped SOAP Body Object: *object*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ307I Unwrapped SOAP Header Object: *object*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ308I SOAP Header: *SOAP Header*.
Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ309E Could not parse unwrapped SOAP Body.
Explanation

See message.

Action

Check the SOAP message.

CTGDIZ310E The SOAP Header element must be namespace qualified.

Explanation

All immediate child elements of the SOAP Header element must be namespace-qualified.

Action

Check the SOAP message.

CTGDIZ311I The namespace URI of the DOM Element: *namespaceURI*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ312I The name of the DOM Element: *elementName*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ313I The value of the DOM Element: *elementValue*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ314I SOAP Message: *SOAP message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ315E The WrapSoap Function Component received an invalid object: *object*.

Explanation

The parameter of the perform method must be an object instance of Entry.

Action

Invoke the method perform with a parameter instance of Entry.

CTGDIZ316E The WrapSoap Function Component was passed an object of incorrect type. Exception occurred: *exception*

Explanation

The type of object expected by the WrapSoap Function Component depends on the value of the "Input the SOAP Body and Header As" configuration parameter. If a "String" is specified as the value of this parameter then the object passed must be an instance of java.lang.String. If "DOMElement" is specified, then an object of org.w3c.dom.Element must be passed.

Action

Pass the correct type of object to the perform method of WrapSoap Function Component.

CTGDIZ101I Exiting initialization early because Connector already initialized with a java.net.Socket object.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ102I Using the provided java.net.Socket object for client session.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ103E The 'inputType' parameter is set to an invalid value '*parameter value*'.

Explanation

See message.

Action

Specify a valid inputType parameter in the Connector.

CTGDIZ104I The parameter 'inputType' is set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ105E The 'returnXMLType' parameter is set to an invalid value '*parameter value*'.

Explanation

See message.

Action

Specify a valid returnXMLType parameter in the Connector.

CTGDIZ106I The parameter 'returnXMLType' is set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ107E Required Connector parameter 'useSSL' is not set.

Explanation

The specified Connector parameter useSSL is required, but not set.

Action

Set the Connector parameter useSSL.

CTGDIZ108E Required Connector parameter 'tcpPort' is not set.

Explanation

The specified Connector parameter tcpPort is required, but not set.

Action

Set the Connector parameter useSSL.

CTGDIZ109I The parameter 'useSSL' is set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ110I The parameter 'tcpPort' is set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ111I The parameter 'requireClientAuth' is set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ113E Called the getNextClient method and Connector is not configured as a server session. Use the getNextEntry method to retrieve the next client request.

Explanation

See message.

Action

Call the getNextEntry to retrieve the next client request.

CTGDIZ114I Connector terminated by external request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ115I Connector terminating by external request.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ116I Terminate server request received.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ117I Creating dummy connection using IP Address '*IP Address*' and port '*port number*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ118I Connector is already terminating. Not sending termination request.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ119I Sending termination request to Connector.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ120E Unable to terminate the Connector. No server Connector available or this Connector is no longer accepting connections.

Explanation

See message.

Action

Check the status of Server Connector.

CTGDIZ121E Called the getNextEntry and Connector is not configured as server session. Use the getNextClient method to retrieve the next client request.

Explanation

See message.

Action

Call the getNextClient to retrieve the next. client request.

CTGDIZ122I Processing a request for the hosted WSDL.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ123I Processing a SOAP request.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ124I Processed SOAP request: ''SOAP request''.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ125W The '\$operation' Attribute of the op-entry has not been set because there is no context or the context is not an AssemblyLine object.

Explanation

This can happen when this Connector is used outside the context of an AssemblyLine, for example, in script.

Action

Use this Connector only in the context of an AssemblyLine (i.e. by inserting the Connector in the AssemblyLine from the Config Editor), if the operation name needs to be available.

CTGDIZ126W The operation name cannot be extracted from the SOAP request message.

Explanation

The Connector could not find the XML element with the SOAP operation name in the first child of the SOAP Body element. Often this means that the SOAP request message was a generic Document style message, which is not associated with a SOAP operation.

Action

The web service client must use either RPC-style or Document Wrapped style SOAP request messages, if the Entry/AssemblyLine needs to be tagged with the operation name.

CTGDIZ127I Connector response HTTP status code set to '*status code*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ128I Connector response content type set to '*content type*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ129I Connector response content length set to '*content length*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ130I Connector response set to '*response value*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ131E Child of the Body element has not been found.**Explanation**

The SOAP message has empty Body or Envelope tags or the message is invalid.

Action

Check the SOAP message.

CTGDIZ132I Starting output of HTTP request headers...**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ133I *content length* set to '*content length value*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ134I *content type set to 'content type value'*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ135I *content location set to 'content location value'*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ136I *soap action set to 'soap action value'*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ137I *host name set to 'host name value'*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ138I **End of output of HTTP request headers.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ139I HTTP method set to '*HTTP Request*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ140I Requested HTTP resource set to '*file name*'.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIZ141E Unexpected end of data while reading.**Explanation**

See message.

Action

No action is required.

CTGDIZ142E Bad Request.**Explanation**

The request is neither GET nor POST request.

Action

See message.

CTGDIZ143E The authentication method is not recognized.**Explanation**

See message.

Action

Use another authentication method.

CTGDIZ144W The parameter 'requireClientAuth' is missing and is set to its default value: '*parameter value*'.

Explanation

The specified Connector parameter requireClientAuth is required, but not set. The reason might be a creation of the configuration with old IBM Security Directory Integrator 6.0 ConfigEditor, which does not have the parameter. Thus a default value is set.

Action

No action is required.

CTGDJZ101I XML SAX Parser thread running.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ102E XML SAX Parser only supports input.

Explanation

XML SAX Parser does not write, for now only reading is accepted.

Action

Use XML SAX Parser for reading and parsing only.

CTGDJZ103E There is no input stream provided to XML SAX Parser.

Explanation

The initialization of SaxContentHandler thread fails.

Action

Check the input stream (file).

CTGDJZ104E The XML SAX Parser parameter Read Timeout value has to be a positive number.

Explanation

See message.

Action

Enter a positive number for the read timeout parameter.

CTGDJZ105E The XML SAX Parser parameter Read Timeout value has to be number.

Explanation

See message.

Action

Type in a positive number read timeout parameter.

CTGDJZ106E Unable to read the Entry. Exception *exception class* occurred: *exception*

Explanation

An InterruptedException is encountered when the method readEntry is trying to read the next entry in the XML document.

Action

No action is required.

CTGDJZ107E Exceeded the stipulated wait period.

Explanation

There was no entry in the queue during the stipulated wait period.

Action

No action is required.

CTGDJZ108E The Entry from the queue is a message.class = *class name*, message = *message*.

Explanation

The next message from the queue is an instance of the class Exception.

Action

Analyse the exception.

CTGDJZ109E The method WriteEntry is not supported by the XML SAX Parser.

Explanation

See message.

Action

Use XML SAX parser only for reading and parsing.

CTGDJZ110I XML SAX Parser terminated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ111I Inside the isGroupTag method: tag=*tag*, groupTag=*group tag*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ112I Inside the characters method: *string*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ114I The method endDocument is invoked.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ115E XMLSAX Parser encountered an InterruptedException in the endDocument method while trying to receive notification of the end of the document: *exception*

Explanation

See message.

Action

No action is required.

CTGDJZ116I Inside the endElement method: *queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ117I Inside the endPrefixMapping method: *prefix*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

**CTGDJZ118I Inside the ignorableWhitespace method:
length=*length*.**

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ119I Inside the processingInstruction method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ120I Inside the setDocumentLocator method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ121I Inside the skippedEntity method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ122I Inside the startDocument method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ123I Inside the startElement method: local name=*local name*, queue name=*queue name*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ124E The method startElement encountered an InterruptedException: *exception*

Explanation

An InterruptedException is encountered when the method startElement is trying to receive notification of the start of an element.

Action

No action is required.

CTGDJZ125I Inside the startPrefixMapping method: prefix=*prefix*, uri=*uri*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ126I Inside the fatalError method: *exception*

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ127I Inside the error method.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ128I SAX Parse Warning:line:*line number*, ID:*ID*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ201I Parser will request namespace aware Parser.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ202I Parser will request validating Parser.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ203I Parser will not indent output.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ204E No output XSL file specified.**Explanation**

There is no output XSL file to transform internal format to the original format.

Action

Specify the output XSL file parameter.

CTGDJZ205E Trying to write XML with no output stream.**Explanation**

The output stream is null.

Action

Check the output mode.

CTGDJZ206I Initialize Output Document.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ207E Trying to read XML with no input stream.**Explanation**

The input stream is null.

Action

Check the input modes.

CTGDJZ208I Initialize Input Document.**Explanation**

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ209E No input XSL file specified.

Explanation

There is no input XSL file to transform the original format to the internal format.

Action

Specify the input XSL file parameter.

CTGDJZ210E The input XSL document has no root.

Explanation

Each XSL document must have a root tag.

Action

Check the root tag in the input XSL file.

CTGDJZ211E The XSL document has no children: *tag name*.

Explanation

The XSL document must have children elements.

Action

Check the children elements in the input XSL file.

CTGDJZ212I The XSL document has *number of children* children elements.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ213E Cannot parse the input XSL.

Explanation

The input XSL object is not an instance of String or StringReader.

Action

Check the validity of the XSL file.

CTGDJZ214E DOM node processing not supported.

Explanation

Cannot generate DOM input or output.

Action

No action is required.

CTGDJZ215E Expected child item at index '*index number*'.

Explanation

The node for this index is null.

Action

Check the content of XSL file.

CTGDJZ216I The XML Child node has no children so its being skipped.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDJZ217E The XSL does not conform to the defined format.

Explanation

Expect the node name to be 'Attribute'.

Action

Verify the content of XSL.

CTGDJZ218E XSL does not conform to the defined format.

Explanation

Expect the node name to be 'Value'.

Action

Verify the content of XSL.

CTGDJZ220E Incorrect node type.

Explanation

The node type must be TEXT_NODE, CDATA_SECTION_NODE or ELEMENT_NODE.

Action

Check the content of XSL.

CTGDJZ221I SAX Parse Warning: line:*line number*, ID:*ID*, message:*message*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE001I Connector could not set the starting change number to '*change number*'. The 'nsChangenumber' parameter will be ignored.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE002I The starting change number is '*change number*' and the 'iteratorStateKey' parameter is set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE003I Entry not found in change log with change number of '*change number*' and the 'ldapSearchBase' set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE004I Skipping entry with change number of '*change number*' and will try next entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE005I Timeout waiting for next changed entry.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE006E Could not retrieve last change number.

Explanation

The 'lastchangenumber' attribute is missing or its value is not a parsable string representing a long value.

Action

Make sure the z/OS LDAP Server is properly configured.

CTGDIE007W Unable to store the change number value '*change number*' in the System Store. Exception encountered: *exception*

Explanation

The System Store could be configured incorrectly.

Action

Make sure that the System Store is configured correctly.

CTGDIE008E Unable to parse entry because the entry is not a valid change log entry. The 'changes' and 'newrdn' attributes are missing. The entry operation was set to '*operation type*'.

Explanation

Your z/OS LDAP Server could be configured incorrectly.

Action

Make sure that your z/OS LDAP Server is properly configured.

CTGDIE009E Unable to parse the change log 'changes' attribute. See the exception message for more information.

Explanation

An error has occurred while the LDIF Parser was parsing the change log 'changes' attribute. The syntax of the change log information retrieved from the z/OS LDAP Server is probably invalid.

Action

Make sure that your z/OS LDAP Server is properly configured.

CTGDIE010E Restart info does not contain the attribute 'changeNumber'.

Explanation

An internal error occurred. The Checkpoint/Restart feature failed.

Action

Contact IBM support.

CTGDIE011I Reading entry in change log with change number of '*change number*' and the 'ldapSearchBase' set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE012I Found entry in change log with change number of '*change number*' and the 'ldapSearchBase' set to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDIE013W The iterator state key is not specified. No state will be stored. The Start At parameter's value will be used.

Explanation

See message.

Action

Specify the iterator state key if you want the state of the changelog connector to be saved.

CTGDKB001I Parameter '*parameter name*': *parameter value*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB002E Required parameter missing: '*parameter name*'.

Explanation

See message.

Action

Specify the required parameter in the Function Component.

CTGDKB003E Parameter '*parameter name*' is too long: '*parameter value*'. The maximum length of the parameter is *length*.

Explanation

See message.

Action

Specify the parameter with a valid length.

CTGDKB004I ATB_OK code is: *integer*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB005I APPC conversation successfully allocated.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB006E Could not allocate APPC conversation; return code:*return code*.

Explanation

See message.

Action

No action is required.

CTGDKB007E The perform method of the Function Component failed because the method was not passed an Entry object. Non-Entry objects are not supported.

Explanation

See message.

Action

Verify the perform method of the Function component is passed an Entry object.

CTGDKB008E Unable to retrieve the command output of the TSO command. The conversion failed and the C layer execute returned NULL.

Explanation

See message.

Action

No action is required.

CTGDKB009E Invalid data returned from C layer: *output*.

Explanation

See message.

Action

No action is required.

CTGDKB010I No output returned by the TS0 command.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB011I Command to execute: *command*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB012E Could not execute TS0 command. The command returned return code: *return code*.

Explanation

See message.

Action

Review the return code to determine the proper response.

CTGDKB013I TS0 command output: *command output*.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB014I Conversation deallocated successfully.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB015W Error on deallocating the conversation during termination: *error code*.

Explanation

See message.

Action

No action is required.

CTGDKB016E Error message: *error message*.

Explanation

See message.

Action

Review the exception to find further details on the error.

CTGDKB017I Parameter '*parameter name*' was transformed from '*parameter value*' to '*parameter value*'.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

CTGDKB018I Parameter '*parameter value*' transformed to upper case.

Explanation

No additional information is available for this message.

Action

Consult the Maintenance and Problem Determination Guide for suggestions for assessing system health.

Notices

This information was developed for products and services offered in the U.S.A. IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk, NY 10504-1785 U.S.A.

For license inquiries regarding double-byte character set (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

Intellectual Property Licensing
Legal and Intellectual Property Law
IBM Japan, Ltd.
19-21, Nihonbashi-Hakozakicho, Chuo-ku
Tokyo 103-8510, Japan

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law :

INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement might not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Any references in this information to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this IBM product and use of those Web sites is at your own risk.

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

IBM Corporation
2Z4A/101
11400 Burnet Road
Austin, TX 78758 U.S.A.

Such information may be available, subject to appropriate terms and conditions, including in some cases payment of a fee.

The licensed program described in this document and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement or any equivalent agreement between us.

Any performance data contained herein was determined in a controlled environment. Therefore, the results obtained in other operating environments may vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurement may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

Information concerning non-IBM products was obtained from the suppliers of those products, their published announcements or other publicly available sources. IBM has not tested those products and cannot confirm the accuracy of performance, compatibility or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

All statements regarding IBM's future direction or intent are subject to change or withdrawal without notice, and represent goals and objectives only.

All IBM prices shown are IBM's suggested retail prices, are current and are subject to change without notice. Dealer prices may vary.

This information is for planning purposes only. The information herein is subject to change before the products described become available.

This information contains examples of data and reports used in daily business operations. To illustrate them as completely as possible, the examples include the names of individuals, companies, brands, and products. All of these names are fictitious and any similarity to the names and addresses used by an actual business enterprise is entirely coincidental.

COPYRIGHT LICENSE:

This information contains sample application programs in source language, which illustrate programming techniques on various operating platforms. You may copy, modify, and distribute these sample programs in any form without payment to

IBM, for the purposes of developing, using, marketing or distributing application programs conforming to the application programming interface for the operating platform for which the sample programs are written. These examples have not been thoroughly tested under all conditions. IBM, therefore, cannot guarantee or imply reliability, serviceability, or function of these programs. You may copy, modify, and distribute these sample programs in any form without payment to IBM for the purposes of developing, using, marketing, or distributing application programs conforming to IBM's application programming interfaces.

Each copy or any portion of these sample programs or any derivative work, must include a copyright notice as follows:

© (your company name) (year). Portions of this code are derived from IBM Corp. Sample Programs. © Copyright IBM Corp. _enter the year or years_. All rights reserved.

If you are viewing this information in softcopy form, the photographs and color illustrations might not be displayed.

Trademarks

IBM, the IBM logo, and ibm.com[®] are trademarks or registered trademarks of International Business Machines Corp., registered in many jurisdictions worldwide. Other product and service names might be trademarks of IBM or other companies. A current list of IBM trademarks is available on the Web at "Copyright and trademark information" at www.ibm.com/legal/copytrade.shtml.

Adobe, Acrobat, PostScript and all Adobe-based trademarks are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States, other countries, or both.

IT Infrastructure Library is a registered trademark of the Central Computer and Telecommunications Agency which is now part of the Office of Government Commerce.

Intel, Intel logo, Intel Inside, Intel Inside logo, Intel Centrino, Intel Centrino logo, Celeron, Intel Xeon, Intel SpeedStep, Itanium, and Pentium are trademarks or registered trademarks of Intel Corporation or its subsidiaries in the United States and other countries.

Linux is a trademark of Linus Torvalds in the United States, other countries, or both.

Microsoft, Windows, Windows NT, and the Windows logo are trademarks of Microsoft Corporation in the United States, other countries, or both.

ITIL is a registered trademark, and a registered community trademark of the Office of Government Commerce, and is registered in the U.S. Patent and Trademark Office.

UNIX is a registered trademark of The Open Group in the United States and other countries.



Java and all Java-based trademarks and logos are trademarks or registered trademarks of Oracle and/or its affiliates.

Cell Broadband Engine is a trademark of Sony Computer Entertainment, Inc. in the United States, other countries, or both and is used under license therefrom.

Linear Tape-Open, LTO, the LTO Logo, Ultrium, and the Ultrium logo are trademarks of HP, IBM Corp. and Quantum in the U.S. and other countries.

Index

A

accessibility cxix
administrator response 4

C

component identifier 1

E

education cxix
explanation 4

F

format
 message 1
 message ID 1

I

IBM
 Software Support cxix
 Support Assistant cxix

M

message
 administrator response 4
 explanation 4
 operator response 4
 programmer response 4
message format 1
message ID format 1

O

operator response 4

P

problem-determination cxix
product identifier 1
programmer response 4

S

severity identifiers 3
subsystem identifier 1

T

training cxix
troubleshooting cxix



Printed in USA

GC27-2710-02

