

z/OS



TSO/E Messages

Version 2 Release 1

Note

Before using this information and the product it supports, read the information in "Notices" on page 651.

This edition applies to Version 2 Release 1 of z/OS (5650-ZOS) and to all subsequent releases and modifications until otherwise indicated in new editions.

© **Copyright IBM Corporation 1988, 2013.**

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

Figures v

Tables vii

About this document ix

Who should use this document ix

How this document is organized ix

Where to find more information x

How to send your comments to IBM xi

If you have a technical problem. xi

**z/OS Version 2 Release 1 summary of
changes xiii**

**Chapter 1. Session Manager Messages
(ADF...) 1**

**Chapter 2. MVSSERV user and system
programmer messages (CHS...) 11**

**Chapter 3. TSO/E terminal messages
(COF...) 47**

**Chapter 4. Information Center Facility
Messages (ICQ...) 51**

**Chapter 5. TSO/E terminal messages
(IDY...) 279**

**Chapter 6. TSO/E terminal messages
(IKJ...) 287**

**Chapter 7. TSO/E terminal messages
(INM...) 539**

**Chapter 8. TSO/E terminal messages
(IRX...) 585**

Appendix. Accessibility 647

Accessibility features 647

Using assistive technologies 647
Keyboard navigation of the user interface 647
Dotted decimal syntax diagrams 647

Notices 651

Policy for unsupported hardware. 652

Minimum supported hardware 653

Trademarks 653

Index 655

Figures

Tables

1. Programs associated with message identifiers 287
2. Messages associated with commands and service routines 289

About this document

This document supports z/OS® (5650-ZOS).

This document explains TSO/E messages and provides some diagnostic information for people who debug programs.

Note:

1. The Access Method Services commands and utilities, such as DELETE, PRINT, and LISTCAT, issue messages with the prefix IDC. *z/OS MVS System Messages, Vol 6 (GOS-IEA)*, contains their descriptions.
2. The TSO/E OPERATOR command issues messages with the prefix IKJ followed by a three-digit identifier. *z/OS MVS System Messages, Vol 9 (IGF-IWM)*, contains their descriptions.
3. The IPCS TSODATA Verb exit issues messages with the prefix IKJ. *z/OS MVS Dump Output Messages*, contains their descriptions.
4. Use of z/OS UNIX may cause messages with the prefix FSUM. Refer to *z/OS UNIX System Services Messages and Codes*, for a description of these messages.
5. TSO/VTAM messages with prefix IKT are described in *z/OS Communications Server: SNA Messages*.
6. Although messages are generally issued to the terminal, some of them may appear in the output listing from a background job.

Who should use this document

This document is intended for any TSO/E user who needs to find out more information about messages displayed on the screen, saved in a job log, or recorded in the system log.

How this document is organized

This document contains TSO/E messages with their prefixes or component names organized in alphabetical order.

- ADF — Chapter 1, “Session Manager Messages (ADF..),” on page 1 describes messages directed to a Session Manager user.
- CHS — Chapter 2, “MVSSERV user and system programmer messages (CHS..),” on page 11 describes messages directed to the terminal for MVSSERV users and MVSSERV messages directed to the trace data set for system programmers.
- COF — Chapter 3, “TSO/E terminal messages (COF..),” on page 47 describes the VLFNOTE command messages directed to the terminal user.
- ICQ — Chapter 4, “Information Center Facility Messages (ICQ..),” on page 51 describes messages directed to an Information Center Facility user or administrator at a terminal.
- IDY — Chapter 5, “TSO/E terminal messages (IDY..),” on page 279 describes messages issued by the TSOLIB command (introduced with TSO/E Release 5).
- IKJ — Chapter 6, “TSO/E terminal messages (IKJ..),” on page 287 describes TSO/E messages directed to a terminal user.
- INM — Chapter 7, “TSO/E terminal messages (INM..),” on page 539 describes TRANSMIT and RECEIVE messages directed to a terminal user.

- IRX — Chapter 8, “TSO/E terminal messages (IRX...),” on page 585 describes REXX messages directed to a terminal user.

Where to find more information

See *z/OS Information Roadmap* for an overview of the documentation associated with z/OS, including the documentation available for z/OS TSO/E.

How to send your comments to IBM

We appreciate your input on this publication. Feel free to comment on the clarity, accuracy, and completeness of the information or provide any other feedback that you have.

Use one of the following methods to send your comments:

1. Send an email to mhvrcfs@us.ibm.com.
2. Send an email from the "Contact us" web page for z/OS (<http://www.ibm.com/systems/z/os/zos/webqs.html>).
3. Mail the comments to the following address:
IBM Corporation
Attention: MHVRCFS Reader Comments
Department H6MA, Building 707
2455 South Road
Poughkeepsie, NY 12601-5400
US
4. Fax the comments to us, as follows:
From the United States and Canada: 1+845+432-9405
From all other countries: Your international access code +1+845+432-9405

Include the following information:

- Your name and address.
- Your email address.
- Your telephone or fax number.
- The publication title and order number:
z/OS V2R1.0 TSO/E Messages
SA32-0970-00
- The topic and page number that is related to your comment.
- The text of your comment.

When you send comments to IBM, you grant IBM a nonexclusive right to use or distribute the comments in any way appropriate without incurring any obligation to you.

IBM or any other organizations use the personal information that you supply to contact you only about the issues that you submit.

If you have a technical problem

Do not use the feedback methods that are listed for sending comments. Instead, take one of the following actions:

- Contact your IBM service representative.
- Call IBM technical support.
- Visit the IBM Support Portal at z/OS support page (<http://www.ibm.com/systems/z/support/>).

z/OS Version 2 Release 1 summary of changes

See the following publications for all enhancements to z/OS Version 2 Release 1 (V2R1):

- *z/OS Migration*
- *z/OS Planning for Installation*
- *z/OS Summary of Message and Interface Changes*
- *z/OS Introduction and Release Guide*

Chapter 1. Session Manager Messages (ADF...)

Component name	ADF
Program producing message	Session Manager
Audience and where produced	For Session Manager users
Message format	ADFYyyyn yyy Message serial number n Type code: A The user must take an action as a result of this message. I This message is informational only, and no action is required.
Comments	The words in the message text printed in lower case letters indicate that the system supplies specific information which varies depending on the circumstances. That information is available only when the system displays the message at the terminal. A plus sign (+) after the message text indicates that more information is available. To receive more information, type a question mark (?) and press the ENTER key.

ADF002I SYNTAX ERROR ON SESSION MANAGER LOGON PROCEDURE

Explanation: The PARM field of your Session Manager LOGON procedure contains incorrect values. See your TSO/E administrator to resolve the problem.

Module: ADFMDF03

ADF003I SESSION MANAGER HAS ABNORMALLY TERMINATED. CONTINUING WITHOUT THE SESSION MANAGER

Explanation: The Session Manager terminated because of an internal error. If you need to use the Session Manager, reissue the LOGON command and specify a Session Manager LOGON procedure. If the problem recurs, contact your TSO/E administrator for help.

ADF004I SESSION MANAGER TERMINATED - ERROR RETURN CODE FROM [text]

Explanation:

- text = ESTAE (SVC 60)
- text = TPUT (SVC 93)
- text = TGET (SVC 93)
- text = ATTACH OF MONITOR TASK ADFMDF01
- text = ATTACH OF MONITOR TASK ADFMDFOA
- text = ATTACH OF TERMINAL MONITOR PROGRAM
- text = ATTACH OF NON-APF AUTHORIZED TMP

The Session Manager terminated because it encountered an error while invoking a system function.

The TSO/E session will continue without the Session Manager. If you still want to use the Session Manager, reissue the LOGON command and specify a Session Manager LOGON procedure. If the problem recurs, contact your TSO/E administrator.

ADF005I • ADF012I

If you receive message "ATTACH OF NON-APF AUTHORIZED TMP" ensure that the TMP you are trying to invoke has been linked with AC(1) and resides in an authorized library. If either condition is not true, the specified TMP can only be invoked unauthorized.

The monitor task is ADFMDF0A.

Module: ADFMDF03

ADF005I **MODULE *name* SPECIFIED ON LOGON PROCEDURE NOT FOUND**

Explanation: The system could not find the default environment module specified as a parameter on the EXEC statement of your session manager LOGON procedure. The TSO/E session will continue, but you will not be able to use Session Manager. See your TSO/E administrator to resolve this problem.

Module: ADFMDF0A

ADF005A **PRESS ENTER KEY TO CONTINUE WITHOUT SESSION MANAGER**

Explanation: TSO/E encountered a condition that caused the Session Manager to end. You can continue to use TSO/E without Session Manager, or enter the LOGOFF command and contact your TSO/E administrator to resolve the problem. This message is issued after messages ADF005I and ADF006I.

Module: ADFMDF0A

ADF006I **ERROR IN MODULE *name* SPECIFIED ON LOGON PROCEDURE**

Explanation: The system found the default environment module specified as a parameter on the EXEC statement of your Session Manager LOGON procedure. However, one of the following problems occurred:

- The format of the load module was incorrect
- An error occurred when chaining through the load list elements
- The load module was not reentrant
- The load module was not from an APF-authorized library.

The CSECT containing the Session Manager defaults must be the entry point to the load module. The CSECT must also begin with the character string "ADFMDFLT". The TSO/E session will continue, but you will not be able to use the Session Manager. See your TSO/E administrator to resolve this problem.

Module: ADFMDF0A

ADF010I **COMMAND *command* NOT FOUND**

Explanation: The command entered is not a Session Manager command. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax.

Module: ADFICMDR

ADF011I **INVALID COMMAND MODIFIER: *modifier***

Explanation: You entered a command modifier that was either incorrect for the command, or did not have the correct syntax. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICQUE, ADFICDEF, ADFICMSC, ADFICRES, ADFICSAV

ADF012I **INVALID COMMAND SYNTAX: *command***

Explanation: You entered a command that did not have the correct syntax. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICMDR

ADF013I **INVALID OPERAND(S):** *operand*

Explanation: You entered a command operand that was either incorrect for the command, or did not have the correct syntax. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICCUR, ADFICDEF, ADFICMSC, ADFICFUN, ADFICPFK, ADFICPUT, ADFICQUE, ADFICRES, ADFICSAV, ADFICSCR, ADFICSNA, ADFICSTM, ADFICTER, ADFICWIN

ADF014I **MISSING OPERAND(S):** *command*

Explanation: The command you entered is missing a required operand. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICDEF, ADFICFUN, ADFICMSC, ADFICPFK, ADFICPUT, ADFICQUE, ADFICRES, ADFICSAV, ADFICSER, ADFICSNA, ADFICSTM, ADFICWIN

ADF015I **TOO MANY OPERANDS:** *command*

Explanation: The command you entered is followed by more operands than are acceptable. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICCUR, ADFICDEF, ADFICFUN, ADFICMDR, ADFICMSC, ADFICPFK, ADFICPUT, ADFICQUE, ADFICRES, ADFICSAV, ADFICSCR, ADFICSNA, ADFICSTM, ADFICTER, ADFICWIN

ADF016I **COMMAND MODIFIER MISSING:** *command*

Explanation: The command you entered is missing a required modifier. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICMDR

ADF017I **INVALID SCROLL AMOUNT:** *value*

Explanation: You entered a SCROLL command or pressed a program function key with an incorrect AMOUNT value, or the SCROLL command was syntactically incorrect. The valid scroll amount values are:

- Page or P
- Half or H
- Max or M
- A number from 1 to 999999 for SCROLL FORWARD or SCROLL BACKWARD
- A number from 1 to 32767 for SCROLL LEFT or SCROLL RIGHT

See *z/OS TSO/E Command Reference* for an explanation of the SCROLL command and its syntax, and reenter the command.

Module: ADFICSCR

ADF018I **ERROR IN SUBFIELD OF** *operand* **OPERAND**

Explanation: The subfield of the above *operand* that you entered is incorrect. For example, you entered too many subfields. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICFUN, ADFICMDR, ADFICPFK, ADFICPUT, ADFICSTM, ADFICTER, ADFICWIN

ADF019I **MISSING SUBFIELD FOR** *operand* **OPERAND**

Explanation: The operand specified above is missing a required subfield. See *z/OS TSO/E Command Reference* for an explanation of the Session Manager commands and their syntax, and reenter the command.

Module: ADFICFUN, ADFICPFK, ADFICSTM, ADFICTER, ADFICWIN

ADF021I WINDOW *window_name* NOT FOUND

Explanation: The *window_name* you entered does not exist. Use the QUERY.WINDOWS command to list the valid window names and reenter your command.

Module: ADFICCUR, ADFICMSC, ADFICRES, ADFICSAV, ADFICSCR, ADFICTER, ADFICWIN

ADF022I STREAM *stream_name* NOT FOUND

Explanation: The *stream_name* entered does not exist. Use the QUERY.STREAMS command to list the valid stream names and reenter your command.

Module: ADFICFUN, ADFICPFK, ADFICPUT, ADFICQUE, ADFICSNA, ADFICSTM, ADFICWIN, ADFIUSTR

ADF023I TEXT *text_string* NOT FOUND

Explanation: The Session Manager did not find the *text_string* that you specified on the FIND command. If you specified FIND.BACKWARD, the FIND command searches from the top line in the window backward to the first line in the stream. If you specify FIND.FORWARD, the FIND command searches forward from the current line to the last line in the stream.

Module: ADFICSCR

ADF025I STREAM *stream_name* IS FULL

Explanation: The specified stream is full and the stream is not able to wrap.

Module: ADFIMPUP

ADF027I WINDOW *window_name* COULD NOT BE DEFINED

Explanation: The window that you are attempting to define overlapped another window on the screen, or the maximum number of windows are already defined. See *z/OS TSO/E Command Reference* for an explanation of the DEFINE WINDOW and DELETE WINDOW commands and their syntax.

Module: ADFICWIN

ADF028I ERROR DURING *read from (or) write to* TERMINAL BY SESSION MANAGER

Explanation: You received incorrect data from the terminal (possibly from an unformatted screen) or the TPUT or TGET macro issued a non-zero return code. This is normally an informational message, but if the problem recurs, contact your TSO/E administrator for help.

Module: ADFMDOIO, ADFIUSTR

ADF029I SESSION MANAGER INTERNAL ERROR IN *module_name*

Explanation: An unexpected internal error occurred in a Session Manager routine. This is normally an informational message, but if the problem recurs, contact your TSO/E administrator for help.

Module: ADFIMDEL, ADFIMLLN

ADF030I WINDOW *window_name* ALREADY EXISTS

Explanation: The window that you are trying to define already exists. Use the QUERY.WINDOWS command to list the existing window names.

Module: ADFICWIN

ADF031I *window_name* VIEWING LINE *nnn*

Explanation: This message is in response to the FIND.LINE command, and indicates that the top of the specified window listed in the message text is line number *nnn*.

Module: ADFICSCR

ADF032A REISSUE THE FIND COMMAND WITH A DATA STRING

Explanation: You entered a FIND command but did not enter a data string to be found. Retype the FIND command, followed by the data string, then press the ENTER key.

Module: ADFICSCR

ADF033I END IGNORED DURING FULLSCREEN PROGRAM

Explanation: You entered the END command while a fullscreen program/command was in control. The END command can only be issued when you are not running a fullscreen program/command.

Module: ADFICMDR

ADF041A ENTER A NULL LINE TO RETURN TO FULLSCREEN PROGRAM

Explanation: A command running under ISPF option 6 (or a similar fullscreen program) has completed. To return to fullscreen support, enter a null line. To enter a null line under the Session Manager, press the ERASE EOF key, then press the ENTER key.

Typing a TSO/E command or any other input and pressing the ENTER key has the same result as entering a null line. Because ISPF is in control, TSO/E commands cannot be processed.

Module: ADFMDF02

ADF101I SMCOPY INTERNAL LOGIC ERROR - SMCOPY TERMINATED

Explanation: You entered an SMCOPY command, but SMCOPY ended because of an internal error. Contact your TSO/E administrator to resolve this problem.

Module: ADFMCPY

ADF102I INPUT SOURCE DATA SET COULD NOT BE OPENED - SMCOPY TERMINATED

Explanation: A system function (OPEN) failed when trying to open the source data set. The SMCOPY command ended unsuccessfully. Contact your TSO/E administrator to resolve this problem.

Module: ADFMCPY

ADF103I OUTPUT TARGET DATA SET COULD NOT BE OPENED - SMCOPY TERMINATED

Explanation: A system function (OPEN) failed when trying to open the output data set. The SMCOPY command ended unsuccessfully. Contact your TSO/E administrator to resolve this problem.

Module: ADFMCPY

ADF104I INPUT SOURCE DATA SET HAS INVALID RECORD FORMAT - SMCOPY TERMINATED

Explanation: The SMCOPY command ended unsuccessfully because the input data set has a not valid record format. The input data set must have either fixed- or variable-length record format. Reenter the SMCOPY command specifying a valid input data set and press the ENTER key.

Module: ADFMCPY

ADF105I OUTPUT TARGET DATA SET HAS INVALID RECORD FORMAT - SMCOPY TERMINATED

Explanation: The SMCOPY command ended unsuccessfully because the output data set has a not valid record format. The output data set must have either a fixed- or variable-length record format. Reenter the SMCOPY command specifying a valid output data set and press the ENTER key.

Module: ADFMCOPI

ADF106I ERROR DURING WRITE TO OUTPUT DATA SET - SMCOPY TERMINATED

Explanation: SMCOPY was terminated because of an I/O error during the copy operation. Retry the SMCOPY command. If the problem recurs, contact your TSO/E administrator to resolve the problem.

Module: ADFMCOPI

ADF107I ERROR DURING READ FROM INPUT DATA SET - SMCOPY TERMINATED

Explanation: SMCOPY was terminated because an I/O error was detected during the copy operation. Retry the SMCOPY command. If the problem recurs, contact your TSO/E administrator to resolve the problem.

Module: ADFMCOPI

ADF108I ERROR DURING WRITE TO OUTPUT SESSION MANAGER STREAM - SMCOPY TERMINATED

Explanation: SMCOPY was terminated because of a system error during the write-to-output operation. Retry the SMCOPY command. If the problem recurs, contact your TSO/E administrator to resolve the problem.

Module: ADFMCOPI

ADF109I ERROR DURING READ FROM INPUT SOURCE SESSION MANAGER STREAM - SMCOPY TERMINATED

Explanation: SMCOPY was terminated because of a system error during the read-from-input operation. Retry the SMCOPY command. If the problem recurs, contact your TSO/E administrator to resolve the problem.

Module: ADFMCOPI

ADF110I SESSION MANAGER NOT ACTIVE - SMCOPY IGNORED

Explanation: You entered a SMCOPY command, but because the Session Manager is not active, the SMCOPY command is ignored. To activate the Session Manager, enter the LOGON command using a Session Manager LOGON procedure.

Module: ADFMCOPI

ADF111I OUTPUT DATA SET NOT FOUND - ASSUMED TO BE NEW

Explanation: The data set that you specified as the target for the SMCOPY command did not exist. SMCOPY allocated it as a new data set.

Module: ADFMCOPI

ADF112I INPUT STREAM NAME NOT FOUND - SMCOPY TERMINATED +

Explanation: The SMCOPY command ended unsuccessfully because the specified Session Manager input stream could not be found. Use the QUERY.STREAMS command to list the existing stream names, and reissue the SMCOPY command.

ADF112A USE THE SESSION MANAGER "QUERY" COMMAND TO DISPLAY VALID STREAM NAMES

Module: ADFMCOPI

ADF113I OUTPUT STREAM NAME NOT FOUND - SMCOPY TERMINATED +

Explanation: The SMCOPY command ended unsuccessfully because the Session Manager output stream specified could not be found. Use the QUERY.STREAMS command to list the stream names, and reissue the SMCOPY command.

ADF113A USE THE SESSION MANAGER "QUERY" COMMAND TO DISPLAY VALID STREAM NAMES

Module: ADFMCOPI

ADF114I RECORD FORMAT OF DATA SET(S) NOT CONSISTENT WITH OPERATION BEING PERFORMED

Explanation: Session Manager data sets must have fixed- or variable-length record format. Reissue your Session Manager command, using data set(s) with the proper record format, or contact your TSO/E administrator for additional assistance.

Module: ADFMCOPI

ADF115I FROM DATA SET MEMBER NOT GIVEN - TEMPNAME ASSUMED

Explanation: You specified a partitioned data set on the FROMDATASET operand of an SMCOPY command, but you did not specify a member name. The Session Manager assumes a member name of TEMPNAME if a member named TEMPNAME exists. Otherwise, the Session Manager will prompt you for a new data set name.

Module: ADFMCOPI

ADF116I FROM DATA SET MEMBER NOT FOUND

Explanation: You specified a member of a partitioned data set on the FROMDATASET operand of an SMCOPY command, but the member name does not exist. The Session Manager prompts you for a new data set name.

Module: ADFMCOPI

ADF117I TO DATA SET MEMBER NOT GIVEN - TEMPNAME ASSUMED

Explanation: You specified a partitioned data set on the TODATASET operand of an SMCOPY command, but you did not specify a member name. The Session Manager assumes a member name of TEMPNAME.

Module: ADFMCOPI

ADF118I FROM DATA SET ORGANIZATION INVALID

Explanation: You specified a data set with a not valid data set organization on the FROMDATASET operand of the SMCOPY command. The only valid data set organizations for this operand are PO (partitioned data set) or PS (physical sequential). Reenter the SMCOPY command specifying a data set with a valid data set organization.

Module: ADFMCOPI

ADF119I TO DATA SET ORGANIZATION INVALID

Explanation: You attempted to execute an SMCOPY command. The TODATASET operand specified on the SMCOPY command refers to a data set with a data set organization that is not one of the valid types. The only valid data set organizations for this operand are PO (partitioned data set) or PS (physical sequential).

Module: ADFMCOPI

ADF120I FROM DATA SET LRECL INVALID

Explanation: You attempted to execute an SMCOPY command. The logical record length (LRECL) of the data set specified on the FROMDATASET operand of the SMCOPY command is not valid. This message is issued if the data set specified on the FROMDATASET operand has a LRECL greater than 256.

Module: ADFMCOPI

ADF121I TO DATA SET LRECL INVALID

Explanation: You attempted to execute an SMCOPY command. The logical record length (LRECL) of the data set specified on the TODATASET operand of the SMCOPY command is not valid. This message is issued if the data set has a LRECL greater than 256. The default LRECL for new data sets is 255.

Module: ADFMCOPI

ADF122I FROMSTREAM AND TOSTREAM CANNOT BE THE SAME

Explanation: You specified the same data set name on the FROMSTREAM and TOSTREAM operands on an SMCOPY command. The FROMSTREAM and TOSTREAM operands must specify different data set names.

Module: ADFMCOPI

ADF201I TEXT FOUND AT LINE *line_number*

Explanation: The text string specified in the SMFIND command is located at the line number specified.

Module: ADFMFIND

ADF202I TEXT NOT FOUND

Explanation: The Session Manager did not find the text_string that you specified on the SMFIND command.

If you specify BACKWARD, the SMFIND command searches from the last line in the stream to the first line of the stream. If you specify FORWARD, the SMFIND command searches from the first line in the stream to the last line in the stream.

Module: ADFMFIND

ADF203I SESSION MANAGER STREAM *stream_name* DOES NOT EXIST +

Explanation: You specified the stream name listed in the message in the SMFIND command, but it does not exist. Use the QUERY.STREAMS command to list existing stream names, and reenter the command.

ADF203A USE THE SESSION MANAGER "QUERY" COMMAND TO DISPLAY VALID STREAM NAMES

Module: ADFMFIND

ADF204I SESSION MANAGER NOT ACTIVE - SMFIND IGNORED

Explanation: You entered a SMFIND command, but the Session Manager is not active and the SMFIND command is ignored. To activate the Session Manager, reissue the LOGON command using a Session Manager LOGON procedure.

Module: ADFMFIND

ADF205I ERROR DURING READ WHILE SEARCHING STREAM - SMFIND TERMINATED

Explanation: SMFIND terminated because an error occurred while using a system function. Contact your TSO/E administrator to resolve the problem.

Module: ADFMFIND

ADF301I ERROR DURING WRITE TO SESSION MANAGER STREAM

Explanation: SMPUT terminated because an error occurred while using a system function. Contact your TSO/E administrator to resolve the problem.

Module: ADFMPUT

ADF302I SESSION MANAGER STREAM *stream_name* DOES NOT EXIST +

Explanation: The stream name you entered does not exist. Use the QUERY.STREAMS command to list existing stream names.

ADF302A USE THE SESSION MANAGER "QUERY" COMMAND TO DISPLAY VALID STREAM NAMES

Module: ADFMPUT

ADF303I SESSION MANAGER NOT ACTIVE - SMPUT IGNORED

Explanation: You attempted to issue an SMPUT command, but the Session Manager is not active and the SMPUT command is ignored. To activate the Session Manager, reissue the LOGON command using a Session Manager LOGON procedure.

Module: ADFMPUT

Chapter 2. MVSSERV user and system programmer messages (CHS...)

Component name	CHS
Program producing message	MVSSERV
Component ID	28507
Audience and where produced	For system programmers in the MVSSERV trace data set. MVSSERV users at their terminals.
Message format	CHS <i>xxxxyyz</i> or CHS <i>xxxxyyz</i> Use these full message IDs when reporting messages to IBM® support personnel. <i>yy</i> Message serial number <i>z</i> Type code: I Informational message (MVSSERV continues) E Error message (MVSSERV ends)
Comments	The words in the message text printed in italics indicate that MVSSERV supplies specific information which varies depending on the circumstances. That information appears when MVSSERV produces the message in the trace data set. If a trace data set is active for the MVSSERV session, terminal messages also appear in the MVSSERV trace data.

CHSCMI01I The control unit supports Read Partitioned Queries.

Explanation: MVSSERV must identify what communications program is running on the personal computer. As a first step, MVSSERV has determined that the control unit supports Read Partitioned Queries, indicating that the personal computer is using a protocol that supports structured fields.

This message is informational only.

Module: CHSTCMI

Audience: System programmer

CHSCMI02I The control unit does not support Read Partitioned Queries.

Explanation: MVSSERV must identify what communications program is running on the personal computer. MVSSERV has determined that the control unit does not support Read Partitioned Queries, indicating that the personal computer is using a protocol that does not support structured fields.

This message is informational only.

Module: CHSTCMI

Audience: System programmer

CHSCMI03E I/O error occurred while initializing communications.

Explanation: An I/O error occurred while MVSSERV was establishing communications with the personal computer. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support center.

Module: CHSTCMI

Audience: System programmer

CHSCMI04I Presentation space input was received and ignored.

Explanation: While communicating with the personal computer (PC), MVSSERV received a transmission that did not conform to the communications protocol. This could have been caused by the user pressing a function key on the PC keyboard or by a message being sent from another user. MVSSERV ignores the transmission and communication continues.

This message is informational only.

Module: CHSTCMI

Audience: System programmer

CHSCMI05E The PC's communication program is unknown.

Explanation: The MVSSERV communications component could not determine what communications program, if any, was running on the personal computer. MVSSERV is ending.

Make sure that the appropriate communications program is installed and running on the personal computer. If it is, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support center.

Module: CHSTCMI

Audience: System programmer

CHSCMI06I Please start the communications program on the PC.

Explanation: MVSSERV determined that the personal computer (PC) is not running the appropriate communications program. This message is displayed until you start the program on the PC, or until 30 seconds have elapsed.

Module: CHSTCMI

Audience: MVSSERV user

CHSCMI07E Error occurred loading module CHSTTCA.

Explanation: MVSSERV could not load CHSTTCA. MVSSERV is ending.

This error most likely occurred because load module CHSTTCA could not be found. Verify that CHSTTCA is installed in a STEPLIB or in a system library in the LINKLIST concatenation and is marked "executable".

If the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support center.

Module: CHSTCMI

Audience: System programmer

CHSCMI08E Error occurred loading module CHSTDCA.

Explanation: MVSSERV could not load CHSTDCA. MVSSERV is ending.

This error most likely occurred because load module CHSTDCA could not be found. Verify that CHSTDCA is installed in a STEPLIB or in a system library in the LINKLIST concatenation and is marked “executable”.

If the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support center.

Module: CHSTCMI

Audience: System programmer

CHSCMI09E Communications could not set the 3270 environment.

Explanation: The MVSSERV communications component could not issue the macros required to establish a 3270 fullscreen environment. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCMI

Audience: System programmer

CHSCMI10I MVSSERV did not receive the expected reply.

Explanation: MVSSERV received structured field input as a result of a Read Partitioned Query, but an expected reply was not found in the input from the personal computer.

Make sure that the appropriate communications program is installed and running on the personal computer. If it is, check the communications connection between the MVS™ TSO/E system and the personal computer. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCMI

Audience: System programmer

CHSCMI11E Error occurred loading the logo data.

Explanation: MVSSERV could not load the LOGO1 load module. MVSSERV is ending.

This error most likely occurred because LOGO1 could not be found. Verify that LOGO1 is installed in a STEPLIB or in a system library in the LINKLIST concatenation and is marked “executable”.

If the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCMI

Audience: System programmer

CHSCMI12E Error occurred loading module CHSTCUT.

Explanation: MVSSERV could not load CHSTCUT. MVSSERV is ending.

This error probably occurred because load module CHSTCUT could not be found. Verify that CHSTCUT is installed in a STEPLIB or in a system library in the LINKLIST concatenation and is marked “executable”.

If the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

CHSCMI13E • CHSCMI17E

Module: CHSTCMI

Audience: System programmer

CHSCMI13E The communications program was not running on the PC.

Explanation: MVSSERV has determined that the personal computer can support the Control Unit Terminal (CUT) communications protocol, but the appropriate PC communications program was not running. MVSSERV is ending.

Verify that the appropriate communications program is installed on the personal computer, and start the program. Check the communications connection between the MVS TSO/E system and the PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: MVSSERV

Audience: System programmer

CHSCMI14I Please press ENTER to continue.

Explanation: MVSSERV must identify the communications protocol that the personal computer is using. MVSSERV has determined that the PC is not using the Control Unit Terminal (CUT) protocol, and assumes that the PC is using VM/PC. After you press ENTER, MVSSERV invokes its VM/PC access method driver to try to establish communications with the PC.

Module: CHSTCMI

Audience: MVSSERV user

CHSCMI15I MVSSERV is invoking the access method driver *AMD_name*.

Explanation: The input parameter data set contained a TYPE(A) parameter specifying a user-defined access method driver (AMD). MVSSERV is loading and invoking the user-defined access method driver instead of an MVSSERV access method driver.

This message is informational only.

Module: CHSTCMI

Audience: System programmer

CHSCMI16E An error occurred loading access method driver *AMD_name*.

Explanation: The input parameter data set contained a TYPE(A) parameter specifying a user-defined access method driver (AMD). MVSSERV tried to load the access method driver into storage, and the load failed. MVSSERV is ending.

Verify that the AMD name is correctly specified in the input parameter data set. Also verify that the AMD load module is installed in a STEPLIB or in a system library in the LINKLIST concatenation and is marked "executable".

Module: CHSTCMI

Audience: System programmer

CHSCMI17E The user-defined access method driver was AMODE 24.

Explanation: A user-defined access method driver (AMD) was specified in the input parameter data set via the TYPE(A) parameter. MVSSERV tried to load the AMD into storage and determined that the AMD was in 24-bit addressing mode (AMODE 24). MVSSERV does not support user-defined AMDs in 24-bit addressing mode. MVSSERV is ending.

User-defined access method drivers must be in 31-bit addressing mode (AMODE 31). If the AMD was written in AMODE 31, check the link-edit characteristics to make sure they do not set the addressing mode to 24. If the AMD was written in AMODE 24, change it to AMODE 31.

For information about changing programs from 24- to 31-bit addressing mode, see *z/OS MVS Programming: Extended Addressability Guide*.

Module: CHSTCMI

Audience: System programmer

CHSCSI01E MVSSERV's service request routine failed.

Explanation: A failure occurred in the routine that passes service requests to a server from an MVS server, initialization/termination program, or access method driver. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter and repeat your previous session to obtain a more detailed trace data set. For further assistance, have the trace available and call IBM support personnel.

Module: CHSTCMI

Audience: System programmer

CHSCSI02I The requested server failed: *server_name*.

Explanation: The indicated server failed during processing. The server may have been requested by a personal computer requester or by another server using the SENDREQ macro. MVSSERV continues, but no further requests can be made to the server that failed or to other servers defined by the same initialization/termination program.

This message is informational only. If a dump data set was allocated for the MVSSERV session, MVSSERV may have provided a dump of the server failure. For information about allocating a dump data set, see *z/OS TSO/E Guide to SRPL*.

Module: CHSTCSI

Audience: System programmer

CHSCSI03I Reply data length exceeds the maximum allowed.

Explanation: The length of the reply data in the connectivity programming request block (CPRB) exceeds the limit set for it by the requester program. MVSSERV continues, and may be able to process other service requests.

Check the server and requester programs to establish an appropriate length for the reply data. Adjust the length specified by the requester or the length of the data supplied by the server.

If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCSI

Audience: System programmer

CHSCSI04I Reply parameter length exceeds the maximum allowed.

Explanation: The length of the reply parameter in the connectivity programming request block (CPRB) exceeds the limit set for it by the requester program. MVSSERV continues, and may be able to process other service requests.

Check the server and requester programs to establish an appropriate length for the reply parameter. Adjust the length specified by the requester or the length of the parameter supplied by the server.

If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCSI

Audience: System programmer

CHSCOM01I Data sent at *hh:mm:ss*, **length=length_of_data**, **RC=return_code**:

Explanation: This message indicates the time MVSSERV sent data to the personal computer, the length of the data (in bytes), and the return code from the TPUT or TPG macro. The time is given in the form of *hh:mm:ss*, where *hh* refers to the hour, *mm* to the minutes, and *ss* to the seconds. For information about the return code, see *z/OS TSO/E Programming Services*.

Module: MVSSERV The data sent follows this message in the trace data set.

This message is informational only.

Audience: System programmer

CHSCOM02I Data received at *hh:mm:ss*, **length=length_of_data** **RC=return_code**:

Explanation: This message indicates the time MVSSERV received data from the personal computer, the length of the data (in bytes), and the return code from the TGET macro. The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds. For information about the return code, see *z/OS TSO/E Programming Services*. The data received follows this message in the trace data set.

This message is informational only.

Module: CHSTCOM

Audience: System programmer

CHSCOM03E I/O error occurred sending data to the PC.

Explanation: A TPUT or TPG error prevented data from being sent to the personal computer. MVSSERV is ending. See message CHSCOM01I in the trace data set for more information about the data and the return code from the TPUT or TPG macro.

Module: CHSTCOM

Audience: System programmer

CHSCOM04E I/O error occurred receiving data from the PC.

Explanation: A TGET error prevented MVSSERV from receiving data from the personal computer. MVSSERV is ending. See message CHSCOM02I in the trace data set for more information about the data and the return code from the TGET macro.

Module: CHSTCOM

Audience: System programmer

CHSCOM05E I/O error occurred while trying to refresh the logo.

Explanation: The logo module failed when it was called to refresh (redisplay) the logo. The logo is not displayed. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCOM

Audience: System programmer

CHSCOM06E I/O error occurred resetting the screen environment.

Explanation: The MVSSERV I/O manager could not issue the macros required to reset a 3270 fullscreen environment. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCOM

Audience: System programmer

CHSCOM07I Could not send data; the host is disconnected.

Explanation: The TPUT or TPG macro failed because VTAM[®] detected that the line between the host and the Personal Computer was disconnected.

Check the communications connection between the MVS TSO/E system and the PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCOM

Audience: System programmer

CHSCOM08I Could not receive data; the host is disconnected.

Explanation: The TGET macro failed because VTAM detected that the line between the host and the Personal Computer was disconnected.

Check the communications connection between the MVS TSO/E system and the PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCOM

Audience: System programmer

CHSCOM09I Sending last transmission again; VTAM sent reshow request.

Explanation: The MVSSERV I/O manager received a VTAM reshow code, and is resending the last transmission.

This message is informational only.

Module: CHSTCOM

Audience: System programmer

CHSCOM10I Logo being refreshed; user pressed the PA2 key.

Explanation: The MVSSERV I/O manager received a user reshow code, and is refreshing (redisplaying) the logo.

This message is informational only.

Module: CHSTCOM

Audience: System programmer

CHSCOM11I Received data in EDIT mode; resetting fullscreen mode.

Explanation: MVSSERV received data in EDIT mode instead of the expected NOEDIT mode, and is resetting the fullscreen environment.

This message is informational only.

Module: CHSTCOM

Audience: System programmer

CHSCPS01E MVSSERV could not open the trace data set.

Explanation: MVSSERV was invoked with a parameter to record diagnostic information in a trace data set. MVSSERV could not open the trace data set to record the information. MVSSERV is ending without a trace data set.

The system programmer should verify that the trace data set is correctly allocated. The trace data set must be allocated to ddname CHSTRACE, and must have a logical record length of 80 and a fixed or fixed block format.

After verifying that the trace data set is correctly allocated, reissue MVSSERV. If the error continues, contact local support personnel or IBM support personnel for further assistance.

Module: CHSTCPS

Audience: MVSSERV user

CHSCPS02E MVSSERV could not load the required modules.

Explanation: MVSSERV was unable to load the modules it needed. MVSSERV is ending without a trace data set.

The system programmer should verify that MVSSERV can locate the load modules CHSTRUT and CHSTIOR in storage. CHSTRUT and CHSTIOR must be installed in a STEPLIB or a system library in the linklist concatenation, and must be marked "executable".

After verifying that the load modules are correctly installed, reissue MVSSERV. If the error continues, contact local support personnel or IBM support personnel for further assistance.

Module: CHSTCPS

Audience: MVSSERV user

CHSCPS03E MVSSERV could not set up the recovery environment.

Explanation: MVSSERV could not establish its recovery environment. MVSSERV is ending without a trace data set.

Reissue MVSSERV. If the error continues, contact local support personnel or IBM support personnel for further assistance.

Module: CHSTCPS

Audience: MVSSERV user

CHSCPS04E MVSSERV could not parse the command parameter.

Explanation: MVSSERV encountered an error while attempting to parse the MVSSERV command parameter. MVSSERV is ending without a trace data set.

Reissue MVSSERV. If the error continues, contact local support personnel or IBM support personnel for further assistance.

Module: CHSTCPS

Audience: MVSSERV user

CHSCPS05E MVSSERV could not set up the trace data set.

Explanation: MVSSERV was invoked with a parameter to record diagnostic information in the trace data set. MVSSERV failed while attempting to initialize the trace data set. MVSSERV is ending.

Reissue MVSSERV. If the error continues, contact local support personnel or IBM support personnel for further assistance.

Module: CHSTCPS

Audience: MVSSERV user

CHSCPS06E MVSSERV could not set up the server task.

Explanation: An error occurred while MVSSERV was attempting to initialize a server task. The error occurred in the modules CHSTIPM or CHSTSRV. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCPS

Audience: System programmer

CHSCPS07I MVSSERV could not set up the dump suppression table.

Explanation: An error occurred while MVSSERV was setting up the dump suppression data set. The dump suppression data set, allocated to ddname CHSABEND, contains a list of ABEND codes for which MVSSERV does not issue dumps. MVSSERV continues processing, but produces a dump for any ABEND that occurs.

This message is informational only.

Module: CHSTCPS

Audience: System programmer

CHSCPS08I MVSSERV is ending.

Explanation: MVSSERV is ending normally. MVSSERV passes control to the TSO/E terminal monitor program with a return code of zero.

This message is informational only.

Module: CHSTCPS

Audience: MVSSERV user

CHSCPS09E MVSSERV is ending; service error. Contact support personnel.

Explanation: MVSSERV is ending because an internal ABEND or error occurred. MVSSERV passes control to the TSO/E terminal monitor program with a return code of four.

The system programmer should scan the trace data set, if any, for more information. If there is no trace data set, the system programmer should allocate one. If a trace data set was not allocated or you did not use IOTRACE the first time, reissue MVSSERV with a trace data set and the IOTRACE parameter, then repeat your previous session. If the error continues, have the trace data available and call IBM support personnel for further assistance.

Module: CHSTCPS

Audience: MVSSERV user

CHSCPS10I An MVSSERV exception occurred. Contact support personnel.

Explanation: MVSSERV is ending normally. During the MVSSERV session, a non-critical exception occurred. The exception may have affected service request processing.

The system programmer should scan the trace data set, if any, for more information. If there is no trace data set, the system programmer should allocate one. If a trace data set was not allocated or you did not use IOTRACE the first time, reissue MVSSERV with a trace data set and the IOTRACE parameter, then repeat your previous session. If the error continues, have the trace data available and call local support personnel or IBM support personnel for further assistance.

Module: CHSTCPS

Audience: MVSSERV user

CHSCUT01I CUT access method driver is active.

Explanation: MVSSERV's Control Unit Terminal (CUT) access method driver is managing communications with the personal computer.

This message is informational only.

Module: CHSTCUT

Audience: System programmer

CHSCUT02E Internal processing error; could not obtain storage.

Explanation: MVSSERV's Control Unit Terminal (CUT) access method driver could not obtain the storage necessary to communicate with the personal computer. MVSSERV is ending.

Logon to TSO/E with a larger region size. Reissue MVSSERV with the IOTRACE parameter. If the error continues, adjust the region size accordingly. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSCUT03E The PC input state is not valid for the host's current state.

Explanation: The data from the personal computer had an input state that was not valid for the current state of the host's Control Unit Terminal (CUT) access method driver. The access method driver was expecting a different type of input and cannot continue communicating. MVSSERV is ending.

The personal computer's communication software is probably in error and needs to be corrected. Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set, then repeat your previous session. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSCUT04I CUT_FTNAK_IN received, last frame being sent to the PC again.

Explanation: The host sent data to the personal computer, but the personal computer did not accept it. The personal computer sent a PC negative acknowledgment to the host. The host is sending the last communications frame again.

This message is informational only.

Module: CHSTCUT

Audience: System programmer

CHSCUT05I A communications header from the PC was not valid.

Explanation: MVSSERV received a communications frame from the personal computer that had incorrect data in the frame header. MVSSERV sent a host negative acknowledgment to the Personal Computer.

This message is informational only.

Module: CHSTCUT

Audience: System programmer

CHSCUT06I User pressed the PF3 key, requesting termination.

Explanation: The user pressed the PF3 key to end the MVSSERV session. MVSSERV is ending normally.

This message is informational only.

Module: CHSTCUT

Audience: System programmer

CHSCUT07I A checksum indicator from the PC was not valid.

Explanation: All communications frames sent between MVSSERV and the personal computer contain a “checksum” indicator to detect possible line transmission errors. The checksum indicator detected an error in a communications frame from the personal computer. MVSSERV sent a host negative acknowledgment to the personal computer.

This message is informational only.

Module: CHSTCUT

Audience: System programmer

CHSCUT08I A sequence number from the PC was not valid.

Explanation: All communications frames sent between MVSSERV and the PC contain a sequence number. MVSSERV received a communications frame whose number was not in sequence with the previous frame. MVSSERV sent a host negative acknowledgment to the personal computer.

This message is informational only.

Module: CHSTCUT

Audience: System programmer

CHSCUT09E The host sent the maximum number of negative responses.

Explanation: The personal computer sent data with a frame error to the host three times, and MVSSERV responded with a negative response after each attempt. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and the personal computer. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSCUT11E A second failure occurred in the CUT access method driver.

Explanation: In an attempt to recover from a previous failure, another failure occurred in MVSSERV's Control Unit Terminal (CUT) access method driver during communications processing. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSCUT12E I/O routine failed; cannot communicate with the PC.

Explanation: An ABEND occurred in the MVSSERV I/O routine. MVSSERV cannot communicate with the personal computer. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSCUT13E A failure occurred in the CUT access method driver.

Explanation: A failure occurred in MVSSERV's Control Unit Terminal (CUT) access method driver communications module. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSCUT14E I/O error - cannot communicate with the PC.

Explanation: An I/O error occurred while trying to send or receive a transmission. Because MVSSERV can no longer communicate with the personal computer, MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and the personal computer. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSCUT15E Error occurred trying to build a service reply.

Explanation: An error occurred while MVSSERV was trying to build a service reply. MVSSERV ends communications with the Personal Computer and terminates.

If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTCUT

Audience: System programmer

CHSDCA01E Error occurred in VM/PC access method driver; retrying.

Explanation: An error occurred in MVSSERV's VM/PC access method driver. The error did not occur during an I/O operation, and MVSSERV is communicating with VM/PC to prepare for termination.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCA

Audience: System programmer

CHSDCA03E VM/PC access method driver failed before VM/PC session.

Explanation: A session between the host and VM/PC had not been established when an error occurred within MVSSERV's VM/PC access method driver. MVSSERV is ending.

This is probably an internal processing or programming error. Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCA

Audience: System programmer

CHSDCA04E Could not access server; CPRB was not valid.

Explanation: The connectivity programming request block (CPRB) that MVSSERV created is not valid. The request cannot be processed. MVSSERV is ending.

This is probably an internal processing or programming error. Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCA

Audience: System programmer

CHSDCA05E Could not access server; MVSSERV error.

Explanation: An MVSSERV error occurred while trying to access a VM/PC server. MVSSERV is ending.

This is probably an internal processing or programming error. Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCA

Audience: System programmer

CHSDCA06I PNAK received, response being sent to VM/PC again.

Explanation: The host sent data to VM/PC, but VM/PC did not accept it. VM/PC sent a PC negative acknowledgment (PNAK) to the host. The host is sending the transmission again.

This message is informational only.

Module: CHSTDCA

Audience: System programmer

CHSDCA07E VM/PC sent negative response.

Explanation: MVSSERV sent data to VM/PC, but VM/PC did not accept it. MVSSERV is ending.

MVSSERV sent the data three times and received a negative acknowledgment after each attempt. The problem may be caused by line transmission errors.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCA

Audience: System programmer

CHSDCA08I PNAK received, request being sent to VM/PC again.

Explanation: The host requested a session with VM/PC, but the transmission was not accepted by VM/PC. VM/PC sent a PC negative acknowledgment (PNAK) to the host. The host is retrying the transmission.

This message is informational only.

Module: CHSTDCA

Audience: System programmer

CHSDCA09E I/O error occurred in VM/PC access method driver.

Explanation: An error occurred in MVSSERV's VM/PC access method driver. The error occurred during an I/O operation, and the VM/PC access method driver cannot communicate with VM/PC to terminate with recovery. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCA

Audience: System programmer

CHSDCOM01I The following data is about to be sent to VM/PC:

Explanation: Data is about to be sent to VM/PC. The data follows this message in the trace data set.

This message is informational only.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM02E I/O error occurred sending data to VM/PC.

Explanation: An I/O error occurred while sending data from the host to VM/PC. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM03E I/O error occurred receiving data from VM/PC.

Explanation: An I/O error occurred while the host was receiving data from VM/PC. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM04E Communications header from VM/PC was not valid.

Explanation: MVSSERV received a communications header from VM/PC that was not valid. Without a correct communications header, MVSSERV cannot communicate with VM/PC. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM05E Data received from VM/PC was not valid.

Explanation: All transmissions between MVSSERV and VM/PC contain a “checksum” indicator to detect possible line transmission errors. The checksum indicator detected an error. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM06E Transmission type from VM/PC was not valid.

Explanation: The communications header contains a type field which tells MVSSERV the type of transmission received from VM/PC. The contents of this field are incorrect. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM07I Logo being refreshed; user pressed the PA2 key.

Explanation: The user pressed the PA2 key, making a reshow request. The MVSSERV logo is being refreshed (redisplayed).

This message is informational only.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM08I Sending last transmission again; VTAM sent reshow request.

Explanation: The previous transmission was sent to VM/PC again because VTAM sent a reshow request.

This message is informational only.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM09I User pressed the PF3 key, requesting termination.

Explanation: The user pressed the PF3 key to end MVSSERV. MVSSERV is ending normally.

This message is informational only.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM10E An attention interrupt was received from VTAM.

Explanation: MVSSERV received an attention interrupt from VTAM. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

CHSDCOM11E • CHSINF03E

Module: CHSTDCOM

Audience: System programmer

CHSDCOM11E I/O error occurred while trying to refresh the logo.

Explanation: An I/O error occurred while trying to refresh (redisplay) the MVSSERV logo. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and VM/PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTDCOM

Audience: System programmer

CHSDCOM12I Data received at *hh:mm:ss*, *length=length_of_data* *RC=return_code*:

Explanation: This message indicates the time MVSSERV received data from the personal computer, the length of the data (in bytes), and the return code from the TGET macro. The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds. For information about the return code, see *z/OS TSO/E Programming Services*. The data that was received follows this message in the trace data set.

This message is informational only.

Module: CHSTDCOM

Audience: System programmer

CHSINF01E VM/PC servers are not defined to MVSSERV.

Explanation: MVSSERV is using the VM/PC communications protocol, but does not have the VM/PC servers defined to it. MVSSERV is ending.

The system programmer should verify that the input parameter data set is correctly allocated and contains the name of the server initialization/termination program CHSFVMPC.

The input parameter data set must be allocated to the ddname CHSPARM, and must have a logical record length of 80 and a fixed or fixed block format. The data set can be allocated in the user's logon procedure, a CLIST, or an ISPF dialog, and must be allocated before MVSSERV is issued. The name CHSFVMPC must appear in columns 1-8 of a record in the input parameter data set.

Reissue MVSSERV, using the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call local support personnel or IBM support personnel for further assistance.

Module: CHSTINF

Audience: MVSSERV user

CHSINF02I VM/PC access method driver is active.

Explanation: The logo has been displayed and the host is ready to receive requests from the personal computer running VM/PC.

This message is informational only.

Module: CHSTINF

Audience: System programmer

CHSINF03E I/O error occurred while trying to display the logo.

Explanation: An I/O error prevented the logo from being displayed. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTINF

Audience: System programmer

CHSIPM01E Input parameter data set could not be opened.

Explanation: MVSSERV was unable to open the input parameter data set. MVSSERV is ending.

The system programmer should verify that the input parameter data set is correctly allocated. The data set must be allocated to ddname CHSPARM, and must have a logical record length of 80 and a fixed or fixed block format.

For more information about the input parameter data set and its contents, see *z/OS TSO/E Guide to SRPI*.

Reissue MVSSERV, using the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call IBM support personnel for further assistance.

Module: CHSTIPM

Audience: MVSSERV user

CHSIPM02I Input parameter data set was empty.

Explanation: The input parameter data set contained no records. MVSSERV processing continues, but no server tasks are attached.

The input parameter data set must contain the name of a server initialization/termination program in columns 1-8 of a record.

For more information about the input parameter data set and its contents, see *z/OS TSO/E Guide to SRPI*.

Specify the appropriate initialization/termination program names and reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call IBM support personnel.

Module: CHSTIPM

Audience: System programmer

CHSIPM03E I/O error occurred during parameter processing.

Explanation: The GET macro encountered an error while processing parameters from the input parameter (CHSPARM) data set. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTIPM

Audience: System programmer

CHSIPM04I The following input parameter was not valid:

Explanation: The line following this message in the trace data set contains a non-valid input record from the input parameter data set.

The first part of the record must be the name of a program. The name can have up to eight characters, including A-Z, 0-9, @, #, and \$. The first character cannot be 0-9. MVSSERV continues processing, but without input from the record.

For more information about the input parameter data set and its contents, see *z/OS TSO/E Guide to SRPI*.

Correct the input record and reissue MVSSERV. Use the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call IBM support personnel.

Module: CHSTIPM

Audience: System programmer

CHSIPM05E Internal processing error; could not obtain storage.

Explanation: The GETMAIN macro was unable to obtain storage for the control blocks CHSDCITT and CHSDRWA, and sent a non-zero return code to MVSSERV. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTIPM

Audience: System programmer

CHSIPM06I Input parameter data set could not be closed.

Explanation: MVSSERV received a non-zero return code from the CLOSE macro when it was unable to close the input parameter data set. MVSSERV continues processing, and the data set is closed by task termination when MVSSERV ends.

Module: CHSTIPM

Audience: System programmer

CHSIPM07I A TYPE keyword in an input record is not valid.

Explanation: A record in the input parameter data set contained the TYPE keyword parameter with a not valid parameter value. MVSSERV ignores the record and continues.

Correct the record in the input parameter data set. The possible values for the TYPE keyword parameter are:

- TYPE(I), indicating that the program named in columns 1-8 of the record is an initialization/termination program.
- TYPE(A), indicating that the program named in columns 1-8 of the record is a user-defined access method driver.

For more information about how to fill in the input parameter data set, see *z/OS TSO/E Guide to SRPI*.

Module: CHSTIPM

Audience: System programmer

CHSIPM08I Access method driver *AMD_name* was ignored.

Explanation: MVSSERV found more than one user-defined access method driver (AMD) specified in the input parameter data set. MVSSERV continues, using the first AMD specified, and ignores any other AMDs.

Correct the input parameter data set so that the keyword parameter TYPE(A) (for *access method driver*) appears in only one record. Other records can have the keyword parameter TYPE(I) or no parameter to indicate that they are the names of initialization/termination programs. For more information about how to fill in the input parameter data set, see *z/OS TSO/E Guide to SRPI*.

Module: CHSTIPM

Audience: System programmer

CHSREC01I MVSSERV's recovery manager received control.

Explanation: An ABEND occurred and the MVSSERV recovery manager received control at an ESTAE or ESTAI exit.

For more information about the error that occurred, see other messages in the trace data set. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTREC

Audience: System programmer

CHSREC02I ABEND code was *abend_code*, reason code was *reason_code*.

Explanation: A system or user ABEND occurred. An ABEND code with the prefix S refers to a system ABEND; an ABEND code with the prefix U refers to a user ABEND. For information about the ABEND code and the reason code, if any, see *z/OS MVS System Codes*.

For more information about the error that occurred, refer to other messages in the trace data set. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTREC

Audience: System programmer

CHSREC03I PSW at time of error was *program_status_word*.

Explanation: This message indicates the program status word that was current at the time an error occurred. For information about the contents of the PSW, see the *System/370 Extended Architecture Reference*

For more information about the error that occurred, refer to other messages in the trace data set. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTREC

Audience: System programmer

CHSREC04I Registers *first_register* to *last_register* were:

Explanation: This message indicates the contents of registers at the time an error occurred. The line following this message in the trace data set shows the contents of these registers. The contents of the registers are displayed from left to right in numerical order, each register's contents consisting of eight hexadecimal digits.

For more information about the error that occurred, refer to other messages in the trace data set. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTREC

Audience: System programmer

CHSREC06I Module=*module_name*, caller=*caller_name*, entry point=*entry_point_address*.

Explanation: This message indicates the module that was in control when an error occurred, the module that called it, and the entry point address at which the failing module received control.

For more information about the error that occurred, refer to other messages in the trace data set. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTREC

Audience: System programmer

CHSREC07I Displacement into failing module was *displacement*.

Explanation: This message indicates the displacement into a failing module where an error occurred. However, if the displacement value in the message text is negative, the value might not be valid. For example, if the PSW is outside the boundaries of the MVSSERV program, as in a system completion code 0C1 ABEND, the displacement in the message text will be a negative number.

For more information about the error that occurred, refer to other messages in the trace data set. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTREC

Audience: System programmer

CHSREC08I Retry in progress. Repeated retry request ignored.

Explanation: The recovery work area contained a valid retry address, but a previous retry attempt had not yet completed. The new retry was not attempted. MVSSERV is ending.

For more information about the error that occurred, refer to other messages in the trace data set. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTREC

Audience: System programmer

CHSREC09E MVSSERV is ending; system error. Contact support personnel.

Explanation: MVSSERV is ending because a system ABEND occurred. MVSSERV cannot recover, and percolates to IKJEFT04, the TSO/E terminal monitor program's ESTAI routine.

You may be able to obtain a dump by pressing the ENTER key when you see the READY message. The system programmer should scan the ABEND dump and the trace data set, if any, for more information.

Reissue MVSSERV. If the error continues, contact local support personnel. For further assistance, have the trace data and the dump information available and call IBM support personnel.

Module: CHSTREC

Audience: MVSSERV user

CHSRUT01E Recovery environment initialization failed.

Explanation: The ESTAE macro used to establish MVSSERV's recovery exit failed. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have this trace data available and call IBM support personnel.

Module: CHSTRUT

Audience: System programmer

CHSRUT02E Router linkage assist routine failed.

Explanation: The linkage assist routine of the MVSSERV router failed. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUT

Audience: System programmer

CHSRUTR01I Service request failed; service request is not supported.

Explanation: The data in field CRBF4 of the connectivity programming request block (CPRB) does not match a service request type that MVSSERV supports. MVSSERV continues, and may be able to process other service requests.

For information about the types of requests supported by MVSSERV and how to specify them in CPRB field CRBF4, see *z/OS TSO/E Guide to SRPI*. Correct the input to CRBF4 and reissue MVSSERV using IOTRACE to obtain a detailed trace data set. If the problem continues, scan the trace data set for more information. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR02I Service request failed; CPRB is not valid.

Explanation: The requester program passed non-valid input to MVSSERV in a connectivity programming request block (CPRB). The address of the CPRB, or an address in the CPRB, is not valid. MVSSERV continues, and may be able to process other service requests.

Verify that the addresses passed by the requester program are correct. If not, correct the input and reissue MVSSERV using IOTRACE to obtain a detailed trace data set. If the problem continues, scan the trace data set for more information. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR03I Server definition failed; insufficient storage.

Explanation: A define server request failed when the MVSSERV router issued a conditional GETMAIN for storage and the storage request was rejected. MVSSERV continues, and may be able to process other requests.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR04I Server definition failed; *server_name* is a duplicate name.

Explanation: A define server request was initiated for a server with the same name as a server already defined to MVSSERV. MVSSERV continues, and may be able to process other requests.

Change the duplicate server name in the DEFSERV macro in the server initialization/termination program. Reissue MVSSERV and repeat the request.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR05I Service request failed; *server_name* is not a defined server.

Explanation: A server request was initiated for a server not defined to MVSSERV. MVSSERV continues, and may be able to process other service requests.

Verify that the requester program names a server that is defined in a server initialization/termination program. Reissue MVSSERV with the IOTRACE parameter and repeat the request. If the problem continues, scan the trace data set for more information. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR06I Service request failed; *server_name* is in an inactive task.

Explanation: A service request was initiated for a server whose task was inactive. MVSSERV continues, and may be able to process other service requests.

A server task becomes inactive when one of the servers in the task fails. The server task remains inactive for the duration of the MVSSERV session.

Scan the trace data set for more information about the server that failed. Correct the failing server or remove it from the initialization/termination program. Reissue MVSSERV with the IOTRACE parameter and repeat the previous request. If the problem continues, scan the trace data set for more information. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR07I Server request failed; insufficient storage.

Explanation: A service request failed when the MVSSERV router issued a conditional GETMAIN for storage and the storage request was rejected. MVSSERV continues, and may be able to process other service requests.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR08E Router failed; CPRB is not valid.

Explanation: The MVSSERV router failed because the address of the connectivity programming request block (CPRB), or an address field within the CPRB, is not valid. MVSSERV continues, and may be able to process other service requests.

The MVS subtask containing the program that issued the CPRB is inactive for the duration of the MVSSERV session.

Verify that all the addresses passed in the CPRB match the AMODE of the program that issued the DEFSERV macro. If the program issuing the macro is AMODE 24, the high-order byte of each address in the CPRB must be zero. If the program issuing the macro is AMODE 31, the high-order byte of each address in the CPRB must be set to 1.

If the addresses in the CPRB have been verified and the problem continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR09E Router failed during initialization.

Explanation: The MVSSERV router failed during initialization. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR10E Router failed during a server definition.

Explanation: The MVSSERV router failed while processing a define server request. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR11E Router failed during a server request.

Explanation: The MVSSERV router failed while processing a server request. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR12I Reply data length exceeds the maximum allowed.

Explanation: The length of the reply data in the connectivity programming request block (CPRB) exceeds the limit set for it by the requester program. MVSSERV continues, and may be able to process other service requests.

Check the server and requester programs to establish an appropriate length for the reply data. Adjust the length specified by the requester or the length of the data supplied by the server.

If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: MVSSERV

Audience: System programmer

CHSRUTR13I Reply parameter length exceeds the maximum allowed.

Explanation: The length of the reply parameter in the connectivity programming request block (CPRB) exceeds the limit set for it by the requester program. MVSSERV continues, and may be able to process other service requests.

Check the server and requester programs to establish an appropriate length for the reply parameter. Adjust the length specified by the requester or the length of the parameter supplied by the server.

If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: MVSSERV

Audience: System programmer

CHSRUTR14I Service request was accepted for server *server_name*

Explanation: A server or user-defined access method driver issued a "send request" (SENDREQ) send a service request to the named server. MVSSERV accepted the request.

This message is informational only.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR15I Service request failed; the current server task is inactive.

Explanation: A server issued a service request (either DEFSEV or SENDREQ), but the server's subtask has already been set to inactive because of an error within the subtask. The server is being terminated and cannot make any further requests.

Scan the trace data set for further information. Other messages identify the error that occurred in the server's subtask. If you have not already used IOTRACE, you can reissue MVSSERV with the IOTRACE parameter and repeat your previous session to obtain a more detailed trace data set. For further assistance, have the trace available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR16E Service request failed; MVSSERV error.

Explanation: A server issued a service request (either DEFSEV or SENDREQ), but MVSSERV had a critical error and is ending. The server is being terminated and cannot make any further requests.

Scan the trace data set for further information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter and repeat your previous session to obtain a more detailed trace data set. For further assistance, have the trace available and call IBM support personnel.

Module: CHSTRUTR

Audience: System programmer

CHSRUTR17I Service request failed; AMDs cannot define servers.

Explanation: A user-defined access method driver (AMD) issued a DEFSEVR request, to define a server. Only SENDREQ requests are accepted from access method drivers.

MVSSERV continues, but without the server that would have been defined by the DEFSEVR request.

To correct the problem, remove all DEFSEVR requests from the access method driver. DEFSEVR requests should instead be issued by the server's initialization/termination program or by another server. For more information about how to define servers, see *z/OS TSO/E Guide to SRPI*.

Module: CHSTRUTR

Audience: System programmer

CHSSPR01I A syntax error was detected in the SRIU.

Explanation: The personal computer sent a service request that contained an SRIU (service request interchange unit) that is syntactically incorrect. An SRIU Acknowledge structured field is sent to the personal computer to inform the communications software of the error. See message CHSTSF11I in the trace data set for more information about the problem. MVSSERV processing continues.

Module: CHSTSPR

Audience: System programmer

CHSSRI01I Initialization/termination program *program_name* failed.

Explanation: The indicated initialization/termination program failed during execution. The program may have either set a non-zero return code or had an ABEND. If an ABEND occurred, this message is preceded by a diagnostic message in the trace data set. The servers that the initialization/termination program defines are inactive for the remainder of the MVSSERV session.

For information about initialization/termination programs and their return codes, see *z/OS TSO/E Guide to SRPI*. Correct the error in the initialization/termination program and reissue MVSSERV. Use the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call IBM support personnel.

Module: CHSTSRI

Audience: System programmer

CHSSRI02I Load failed for initialization/termination program *program_name*.

Explanation: MVSSERV could not load the indicated initialization/termination program at execution time. The servers that the initialization/termination program defines are inactive for the remainder of the MVSSERV session.

Verify that the initialization/termination program name is correctly specified in the input parameter data set. Also, verify that the initialization/termination program is in a STEPLIB or in a system library in the LINKLIST concatenation and is marked "executable".

Reissue MVSSERV, using the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call IBM support personnel.

Module: CHSTSRI

Audience: System programmer

CHSSRI03I The requested server failed.

Explanation: A requested server ABENDED during service request processing, and was unable to recover. MVSSERV continues and can accept requests for servers running in other subtasks, if any.

Correct the error in the server and reissue MVSSERV. Use the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call IBM support personnel.

Module: MVSSERV

Audience: System programmer

CHSSRI04E The server task failed during initialization.

Explanation: The MVS subtask containing the server failed during initialization processing. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTSRI

Audience: System programmer

CHSSRI05E The server task failed during a service request.

Explanation: The MVS subtask containing the server failed during service request processing. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTSRI

Audience: System programmer

CHSSRI06E The server task failed during termination.

Explanation: The MVS subtask containing the server failed during termination processing. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTSRI

Audience: System programmer

CHSSRV01E The server task could not be loaded.

Explanation: The LOAD macro sent a non-zero return code to MVSSERV after attempting to load module CHSTSRI. MVSSERV is ending.

Verify that CHSTSRI is in a STEPLIB or in a system library in the LINKLIST concatenation and is marked "executable".

Reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set, then repeat your previous session. If the error continues, have the trace data available and call IBM support personnel.

Module: CHSTSRV

Audience: System programmer

CHSSRV02I A server task could not be attached.

Explanation: The ATTACH macro sent a non-zero return code to MVSSERV after trying to attach a server task. MVSSERV continues, but that server task is inactive and MVSSERV cannot process requests for servers in that task.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTSRV

Audience: System programmer

CHSSRV03I A server task was detached; initialization failure.

Explanation: Initialization of a server task was unsuccessful. MVSSERV detaches the task and cannot process requests for servers in that task. MVSSERV continues to initialize other server tasks.

For any requests that MVSSERV does not process, examine the initialization/termination program for the corresponding servers. That initialization/termination program could not be initialized and probably contains an error.

Correct the error in the initialization/termination program and reissue MVSSERV. Use the IOTRACE parameter to obtain a detailed trace data set. If the error continues, have the trace data available and call IBM support personnel.

Module: CHSTSRV

Audience: System programmer

CHSTCA01E I/O error occurred while trying to display the logo.

Explanation: MVSSERV's Distributed Function Terminal (DFT) access method driver received an error code from the TPUT service when it attempted to display the MVSSERV logo. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a more detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA02E Internal processing error; could not obtain storage.

Explanation: MVSSERV's Distributed Function Terminal (DFT) access method driver could not obtain the storage necessary to communicate with the personal computer. MVSSERV is ending.

Log on to TSO/E with a larger region size. Reissue MVSSERV with the IOTRACE parameter. If the error continues, adjust the region size accordingly. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA03I User pressed the PF3 key, requesting termination.

Explanation: The user pressed the PF3 key to end the MVSSERV session. MVSSERV is ending normally.

This message is informational only.

Module: CHSTTCA

Audience: System programmer

CHSTCA04I ENTER key was pressed; entered data ignored.

Explanation: While MVSSERV was communicating with the personal computer, the user pressed the ENTER key. This key is ignored by MVSSERV while the MVSSERV logo is displayed.

This message is informational only.

Module: CHSTTCA

Audience: System programmer

CHSTCA05E Received transmission without destination/origin ID.

Explanation: While communicating with the personal computer, MVSSERV received a communications header that did not have the destination/origin ID. The personal computer's communication software is in error and must be corrected. MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and the personal computer. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA06I Presentation space input was received and ignored.

Explanation: While communicating with the personal computer (PC), MVSSERV received a transmission that did not conform to the communications protocol. This could have been caused by the user pressing a function key on the PC keyboard or by a message being sent from another user. The transmission is ignored and communication continues.

This message is informational only.

Module: CHSTTCA

Audience: System programmer

CHSTCA07E I/O error; cannot communicate with the PC.

Explanation: An I/O error occurred while trying to send or receive a transmission. Because MVSSERV can no longer communicate with the personal computer, MVSSERV is ending.

Check the communications connection between the MVS TSO/E system and the personal computer. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA08E Received transmission without structured fields.

Explanation: While communicating with the personal computer (PC), MVSSERV received a transmission that contained an incorrect format. The personal computer communication software is in error and must be corrected. MVSSERV is ending.

Module: CHSTTCA

Audience: System programmer

CHSTCA09I A sequence error on a service request was detected.

Explanation: The personal computer (PC) was sending a request to MVSSERV that required multiple transmissions. One of the transmissions to MVSSERV was duplicated or missing. The PC may re-transmit the request. If the PC does not re-transmit the request, or tries and fails, the MVSSERV session ends.

The personal computer's communication software is in error and must be corrected.

Check the communications connection between the MVS TSO/E system and the PC. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA10I Sequence error on service reply; retrying the reply.

Explanation: MVSSERV was sending a reply to the personal computer (PC) that required multiple transmissions. One of the transmissions that was received by the PC was duplicated or missing. MVSSERV will re-transmit the reply.

This message is informational only.

Module: CHSTTCA

Audience: System programmer

CHSTCA11E Sequence error on service reply; cannot retry the reply.

Explanation: MVSSERV was sending a reply to the personal computer that required multiple transmissions. One of the transmissions to the PC was duplicated or missing. MVSSERV re-transmitted the reply unsuccessfully three times; MVSSERV will end communications with the personal computer and terminate.

Check the communications connection between the MVS TSO/E system and the personal computer. If the remote 3270 operation is correct and the error continues, scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA12E Unknown error code in CCC Negative Acknowledge.

Explanation: A communication control construct (CCC) Negative Acknowledge transmission was received from the personal computer. The transmission contained an unrecognizable error code. The personal computer's communication software is in error and must be corrected. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set, then repeat your previous session. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA13I DFT access method driver is active.

Explanation: MVSSERV's Distributed Function Terminal (DFT) access method driver is managing communications with the personal computer.

This message is informational only.

Module: CHSTTCA

Audience: System programmer

CHSTCA14E Input from the PC was not valid.

Explanation: The transmission received from the personal computer did not conform to MVSSERV's Distributed Function Terminal (DFT) communications protocol. The personal computer communication software is in error and must be corrected. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set, then repeat your previous session. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA15E Error occurred trying to build a service reply.

Explanation: An error occurred while MVSSERV was trying to build a service reply. MVSSERV ends communications with the personal computer and terminates.

If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA16E I/O routine failed; cannot communicate with the PC.

Explanation: An ABEND occurred in the MVSSERV I/O routine. MVSSERV cannot communicate with the personal computer. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA17E A failure occurred in the DFT access method driver.

Explanation: A failure occurred in MVSSERV's Distributed Function Terminal (DFT) access method driver communications module. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA18E A second failure occurred in the DFT access method driver.

Explanation: In an attempt to recover from a previous failure, another failure occurred in MVSSERV's Distributed Function Terminal (DFT) access method driver during communications processing. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTCA19I Sending CCC Enable transmission again.

Explanation: MVSSERV sent a communication control construct (CCC) Enable structured field to the personal computer to enable it for communications. The attempt failed because the personal computer was not completely initialized. MVSSERV waits for one second and sends the enable request again.

This message is informational only.

Module: CHSTTCA

Audience: System programmer

CHSTCA20E The send buffer is too small to send a reply.

Explanation: The communications software on the personal computer sets the buffer size for a service reply. MVSSERV has determined that the size is too small to send any service replies. MVSSERV is ending.

Scan the trace data set for more information. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

Module: CHSTTCA

Audience: System programmer

CHSTRH01I Sent *frame_type* at *hh:mm:ss* **sequence=sequence_number** **session=session_id** **length=length_of_frame**:

Explanation: MVSSERV's VM/PC access method driver sent a communications frame to the personal computer. The communications frame is part of a protocol that establishes communications between MVSSERV and the personal computer.

This message indicates the type of communications frame sent, the time it was sent, the sequence number of the frame, the MVSSERV session ID, and the length of the frame (in bytes).

The type of frame will be one of the following:

- HACK -- host acknowledgment of PC transmission
- HNAK -- host negative acknowledgment of PC transmission
- HQNL -- host request - last frame
- HRNL -- host response - last frame
- HRR1 -- host response - first or intermediate frame
- HRFW -- host ready for work
- HRES -- host reset

The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds. The sequence indicates the frame's relative order in a series of frames that were sent (for example, a sequence of 00001 would indicate that this was the first frame sent). The session indicates the ID of the MVSSERV session, and the length indicates the length of the frame.

The contents of the communications frame follow this message in the trace data set.

This message is informational only.

Module: CHSTTRH

Audience: System programmer

CHSTRH02I Received *frame* at *hh:mm:ss*: **sequence=sequence_number** **session=session_id** **length=length_of_frame**:

Explanation: MVSSERV's VM/PC access method driver received a communications frame from the personal computer. The communications frame is part of a protocol that establishes communications between MVSSERV and the personal computer.

This message indicates the type of communications frame received, the time it was received, the sequence number of the frame, the MVSSERV session ID, and the length of the frame (in bytes). The type of frame will be one of the following:

- PACK -- PC acknowledgment of host transmission
- PNAK -- PC negative acknowledgment of host transmission
- PQNL -- PC request - last frame
- PQRI -- PC request - first or intermediate frame
- PRNL -- PC response - last frame

The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds. The sequence indicates the frame's relative order in a series of frames that were received (for example, a sequence of 00001 would indicate that this was the first frame received). The session indicates the ID of the MVSSERV session, and the length indicates the length of the frame.

The contents of the communications frame follow this message in the trace data set.

This message is informational only.

Module: CHSTTRH

Audience: System programmer

CHSTRH201I Sent *frame_type* at *hh:mm:ss* **sequence=sequence_number** **length=length_of_frame**:

Explanation: MVSSERV's CUT access method driver sent a communications frame to the personal computer. The communications frame is part of a protocol that manages communications between MVSSERV and the personal computer.

This message indicates the type of communications frame sent, the time it was sent, the sequence number of the frame, and the length of the frame (in bytes).

The type of frame will be one of the following:

CUT_FT.....

- ACKOUT -- host acknowledgment of PC transmission
- NAKOUT -- host negative acknowledgment of PC transmission
- SEQOTL -- service reply - last or only frame
- SEQOTI -- service reply - intermediate frame
- DISOUT -- host ending communications

The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds. The sequence indicates the frame's relative order in a series of frames that were sent (for example, a sequence of 001 would indicate that this was the first frame sent). The length indicates the length of the frame in bytes.

The contents of the communications frame follow this message in the trace data set.

This message is informational only.

Module: CHSTTRH2

Audience: System programmer

CHSTRH202I Received *frame_type* at *hh:mm:ss* **sequence=sequence_number** **length=length_of_frame**:

Explanation: MVSSERV's CUT access method driver received a communications frame from the personal computer. The communications frame is part of a protocol that manages communications between MVSSERV and the personal computer.

This message indicates the type of communications frame sent, the time it was sent, the sequence number of the frame, and the length of the frame (in bytes). The type of frame will be one of the following:

CUT_FT.....

- ACK_IN -- PC acknowledgment of host transmission
- NAK_IN -- PC negative acknowledgment of host transmission
- SEQINL -- service request - last or only frame
- SEQOTI -- service request - intermediate frame
- IM_ECF -- PC ready for work
- NO_ECF -- PC communications program is not running
- DIS_IN --PC ending communications

The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds. The sequence indicates the frame's relative order in a series of frames that were sent (for example, a sequence of 001 would indicate that this was the first frame sent). The length indicates the length of the frame in bytes.

The contents of the communications frame follow this message in the trace data set.

This message is informational only.

Module: CHSTTRH2

CHSTR01I • CHSTSF02I

Audience: System programmer

CHSTR01I VM/PC allocate request for *server_name*, server ID=*server_id*.

Explanation: This message identifies a server that has been requested from a personal computer running VM/PC. MVSSERV is requesting that VM/PC allocate the named server. The server ID is the sequence number of the allocate request.

This message is informational only.

Module: CHSTTRL

Audience: System programmer

CHSTRR01I CPRB request at *hh:mm:ss* server=*server_name* function=*service_function ID*.

Explanation: MVSSERV received a service request in a connectivity programming request block (CPRB) from the requester. This message indicates the time the CPRB was received, the name of the requested server, and the ID of the requested service function.

The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds.

If MVSSERV is invoked with the IOTRACE parameter, the contents of the CPRB follow this message in the trace data set.

This message is informational only.

Module: CHSTRRR

Audience: System programmer

CHSTRS01I CPRB reply at *hh:mm:ss* RC=*server_return_code* *server_name* RC=*MVSSERV_return_code*.

Explanation: MVSSERV sent a service reply in a connectivity programming request block (CPRB) to the requester. This message indicates the time the CPRB was sent, the return code from the server, and the return code from MVSSERV.

The time is given in the form of *hh:mm:ss*, where *hh* refers to the hours, *mm* to the minutes, and *ss* to the seconds.

The server return code is established by convention between the server and requester programs.

This message is informational only.

Module: CHSTRRS

Audience: System programmer

CHSTSF01I CCC Enable was processed.

Explanation: A communication control construct (CCC) Enable structured field was sent to the personal computer.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF02I CCC Sequence *frame_number* (last frame) was processed, length=*length of field*.

Explanation: A communication control construct (CCC) Sequence structured field was found and processed (sent or received). This was the last or only frame of the sequence. The sequence number of the frame and the length of the field in bytes are given.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF03I CCC Sequence *frame_number* was processed, *length=length_of_field*.

Explanation: A communication control construct (CCC) Sequence structured field was found and processed (sent or received). This was the first or intermediate frame of the Sequence field. The sequence number of the frame and the length of the field in bytes are given.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF04I SRIU Prefix was processed.

Explanation: A Service request interchange unit (SRIU) Prefix structured field was found and processed (sent or received).

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF05I SRIU Request command was processed, *length=length_of_field*.

Explanation: A Service request interchange unit (SRIU) Request Command structured field was received from the personal computer. The length of the field is given in bytes.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF06I SRIU Reply command was processed, *length=length_of_field*.

Explanation: A Service request interchange unit (SRIU) Reply Command structured field was sent to the personal computer. The length of the field is given in bytes.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF07I SRIU Parameter was processed, *length=length_of_field*.

Explanation: A Service request interchange unit (SRIU) Parameter structured field was found and processed (sent or received). The length of the field is given in bytes.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF08I SRIU Data was processed, length=length_of_field.

Explanation: A Service request interchange unit (SRIU) Data structured field was found and processed (sent or received). The length of the field is given in bytes.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF09I SRIU Suffix was processed.

Explanation: A Service request interchange unit (SRIU) Suffix structured field was found and processed (sent or received).

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF10I SRIU Acknowledge was processed, length=length_of_field:

Explanation: A Service request interchange unit (SRIU) Acknowledge structured field was found and processed (sent or received). The length of the field is given in bytes. The following message in the trace data set, CHSTSF11I, provides more information about the exception condition.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF11I SRIU exception class=exception_class, code=exception_code, object=exception_object, data:

Explanation: An exception condition occurred in relation to an SRIU Acknowledge structured field. For information about the exception class, code, and object, refer to the *IBM Programmer's Guide to Server-Requester*. The exception data, if any, follows this message in the trace data set.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF12I Unidentified structured field was processed, length=length_of_field.

Explanation: MVSSERV could not identify the structured field that it sent or received. The length of the field is given in bytes. The structured field is ignored.

Scan the trace data set to see the unidentified structured field. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: MVSSERV

Audience: System programmer

CHSTSF13I CCC Disable was processed.

Explanation: A communication control construct (CCC) Disable structured field was found and processed (sent or received).

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF14I CCC Acknowledge was processed.

Explanation: A communication control construct (CCC) Acknowledge structured field was found and processed (sent or received).

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF15I CCC Negative Acknowledge was processed, code=*return_code*.

Explanation: A communication control construct (CCC) Negative Acknowledge structured field was found and processed (sent or received). The possible return codes are:

- 0001 - Sequence error occurred, retrying
- 0002 - Sequence error, no retry

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF16I Unidentified CCC was processed, length=*length_of_field*.

Explanation: MVSSERV could not identify the type of communication control construct (CCC) structured field that it sent or received. The length of the field is given in bytes. The CCC structured field is ignored.

Scan the trace data set to see the unidentified CCC. If you have not already used IOTRACE, reissue MVSSERV with the IOTRACE parameter to obtain a detailed trace data set. For further assistance, have the trace data available and call IBM support personnel.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: MVSSERV

Audience: System programmer

CHSTSF17I Soft Error was processed, length=*length_of_field*:

Explanation: A Soft Error structured field was found and processed (sent or received).

The length of the field is given in bytes. The following message in the trace data set, CHSTSF18I, provides more information about the exception condition.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: CHSTTSF

Audience: System programmer

CHSTSF18I Soft Error exception `class=class, code=error_code, data:`

Explanation: A Soft Error structured field was generated to report information about a communications error.

For information about the exception class and code, see *IBM Programmer's Guide to Server-Requester Programming Interface for the IBM Personal Computer*. The exception data, if any, follows this message in the trace data set.

This message is informational only. The information is intended for support personnel who can use it to trace the flow of structured fields between the host and the PC.

Module: MVSSERV

Audience: System programmer

CHSTTP01I Internal trace table follows. Last entry is *nnn*:

Explanation: The execution path trace table follows this message in the trace data set. The execution path trace table shows the sequence in which MVSSERV modules called each other. Each call is represented by an entry, with the first four characters ("CHST") removed. Each call has an entry number. This message indicates the entry number (*nnn*) of the last call in the sequence.

This message is informational only.

Module: CHSTTTP

Audience: System programmer

CHSTTP02I *nnn xxxxxx nnn xxxxxx nnn xxxxxx nnn xxxxxx*

Explanation: This message displays one line of the path execution trace table. The execution path trace table shows the sequence in which MVSSERV modules called each other. Each call is represented by an entry. Each entry is preceded by an entry number (*nnn*). For a table with 256 entries, this messages appears 64 times.

Module: CHSTTTP

Audience: System programmer

Chapter 3. TSO/E terminal messages (COF...)

Component name	COF
Program producing message	VLFNOTE command
Audience and where produced	For terminal user: at the terminal. For system programmer: SYSTSPRT listing.
Message format	COFyyyyyI yyyyy Message serial number. I Information; no action is required.
Comments	The words enclosed in single quotation marks in the message text indicate that the system supplies specific information which varies depending on the circumstances. That information is available only when the system displays the message at the terminal.

COF10301I *keyword* [CLASS(*class_name*)] [DATASET(*dsname* [(*membername*)])] [VOLSER(*volser*)] VLF NOTIFICATION WAS SUCCESSFUL. or *keyword* CLASS(*class_name*) [MAJOR(*major_name*)] [MINOR(*minor_name*)] VLF NOTIFICATION WAS SUCCESSFUL.

Explanation: The IKJPARS TSO/E service routine completed syntax verification of the VLFNOTE command keywords and the virtual lookaside facility (VLF) made the requested change in its storage. This message displays the command parameters that you entered, in their entirety, regardless of whether you entered an allowable shortened form. Also, if you specified DSNAME as an alias for DATASET, the message displays DATASET. The *keyword* field is replaced by ADD, DELETE, or UPDATE.

System action: Processing continues.

User response: None

Module: VLFNOTE

Audience: VLFNOTE user

COF10302I *keyword* [CLASS(*class_name*)] [DATASET(*dsname*[(*membername*)])] [VOLSER(*volser*)] VLF NOTIFICATION FAILED. RETURN CODE=*nnnnnnnnn* REASON CODE=*nnnnnnnnn* or *keyword* CLASS(*class_name*) [MAJOR(*major_name*)] [MINOR(*minor_name*)] VLF NOTIFICATION FAILED. RETURN CODE=*nnnnnnnnn* REASON CODE=*nnnnnnnnn*

Explanation: The virtual lookaside facility (VLF) function that you attempted to invoke returned a non-zero return code or reason code, indicated in the message text. This message also displays the command parameters that you entered, in their entirety, regardless of whether you entered an allowable shortened form. If you specified DSNAME as an alias for DATASET, the message displays DATASET. The *keyword* field is replaced by ADD, DELETE, or UPDATE.

System action: Processing continues with no change made to VLF storage.

User response: See *z/OS MVS Programming: Authorized Assembler Services Reference ALE-DYN*, for an explanation of the displayed macro return and reason codes to determine what action should be taken. If 'DELETE CLASS' is displayed, see the description of the COFPURGE macro. For all other cases, see the description of the COFNOTIF macro.

Module: VLFNOTE

Audience: VLFNOTE user

COF10303I YOU ARE NOT AUTHORIZED TO [text]. YOUR INSTALLATION MUST AUTHORIZE USE OF THIS COMMAND.

Explanation: For the item *text* could appear the following:

- *text* = DELETE CLASS *class_name*
- *text* = DELETE A MAJOR FROM CLASS *class_name*
- *text* = SPECIFY ONLY ONE VOLUME

You issued the VLFNOTE command to delete a class, or a major name from an IBM supplied class, or an entire volume, but you are not authorized by your installation to use this function of the virtual lookaside facility (VLF).

System action: Processing continues with no change made to VLF storage.

User response: If you should be authorized to use this VLFNOTE command function, see your system programmer to obtain TSO/E operator authority. Otherwise, see *z/OS TSO/E Command Reference* for descriptions of the VLFNOTE command functions that do not require TSO/E operator authority.

Module: VLFNOTE

Audience: VLFNOTE user

COF10304I NO OPERANDS, COMMAND IGNORED. VLFNOTE COMMAND TERMINATED. NO VALID INPUT INFORMATION WAS SPECIFIED.

Explanation: You did not specify any operands on the VLFNOTE command.

System action: Processing continues with no change made to VLF storage.

User response: If you do not know the valid VLFNOTE operands, issue 'HELP VLFNOTE' for information about the VLFNOTE command. If you do not have TSO/E operator authority, see *z/OS TSO/E Command Reference* for descriptions of the VLFNOTE command functions that do not require TSO/E operator authority. Reissue the VLFNOTE command with the correct operands.

Module: VLFNOTE

Audience: VLFNOTE user

COF10305I NOT ENOUGH STORAGE TO EXECUTE COMMAND.

Explanation: A conditional GETMAIN for a buffer or work area failed.

System action: Processing continues with no change made to VLF storage.

User response: LOGON with a larger region to be able to execute the VLFNOTE command.

Module: VLFNOTE

Audience: VLFNOTE user

COF10306I COMMAND SYSTEM ERROR. *service_routine* ERROR CODE *error_code*.

Explanation: Either the TSO/E parse service routine or the TSO catalog information routine was not able to perform its normal function.

System action: Processing continues with no change made to VLF storage.

User response: See the description of *service_routine* in *z/OS TSO/E Programming Services* for an explanation of the displayed error code and information about how to correct the condition.

Module: VLFNOTE

Audience: VLFNOTE user

COF10307I INCORRECT COMBINATION OF PARAMETERS.

Explanation: You either did not specify a required parameter or you specified mutually exclusive parameters on the VLFNOTE command. Additional message text explains the specific error.

keyword1 AND *keyword2* WERE SPECIFIED BUT ARE MUTUALLY EXCLUSIVE.

Explanation: You can specify only one of the displayed keywords at a time on the VLFNOTE command.

'MAJOR' IS REQUIRED WITH 'MINOR' BUT WAS NOT SPECIFIED.

or

'CLASS' IS REQUIRED WITH 'MAJOR' BUT WAS NOT SPECIFIED.

or

'DATASET' IS REQUIRED WITH 'VOLSER' BUT WAS NOT SPECIFIED.

Explanation: On the VLFNOTE command, if you specify the second keyword displayed in the message, you also must specify the first keyword displayed.

NO 'MAJOR' OR 'DATASET' WAS SPECIFIED WITH 'ADD' AND 'CLASS'.

or

NO 'MAJOR' OR 'DATASET' WAS SPECIFIED WITH 'UPDATE' AND 'CLASS'.

Explanation: If you specify CLASS and either ADD or UPDATE on the VLFNOTE command, you must also specify the MAJOR or DATASET keyword.

NO 'MAJOR' OR 'DATASET' KEYWORD WAS SPECIFIED WITH 'ADD'.

or

NO 'MAJOR' OR 'DATASET' KEYWORD WAS SPECIFIED WITH 'UPDATE'.

Explanation: If you specify ADD or UPDATE on the VLFNOTE command, you must also specify the MAJOR or DATASET keyword.

NO 'DATASET', 'CLASS', OR 'VOLSER' KEYWORD WAS SPECIFIED WITH 'DELETE'.

Explanation: If you specify DELETE on the VLFNOTE command, you must also specify the DATASET, CLASS, or VOLSER keyword for the command to have any meaning.

NO 'MINOR' KEYWORD WAS SPECIFIED WITH 'ADD' AND 'MAJOR'.

or

NO 'MINOR' KEYWORD WAS SPECIFIED WITH 'UPDATE' AND 'MAJOR'.

Explanation: If you specify MAJOR and either ADD or UPDATE on the VLFNOTE command, you must also specify the MINOR keyword.

NO DATA SET MEMBER WAS SPECIFIED WITH 'ADD' AND 'DATASET'.

or

NO DATA SET MEMBER WAS SPECIFIED WITH 'UPDATE' AND 'DATASET'.

Explanation: If you specify the DATASET keyword and either ADD or UPDATE on the VLFNOTE command, you must also specify a data set member.

NO 'ADD', 'DELETE', OR 'UPDATE' KEYWORD WAS SPECIFIED.

Explanation: You did not specify a command keyword that describes the type of change made (addition, deletion, or update) on the VLFNOTE command.

System action: Processing continues with no change made to VLF storage.

User response: If you do not know the valid keywords and their combinations, issue 'HELP VLFNOTE' for information about the VLFNOTE command. If you do not have TSO/E operator authority, see *z/OS TSO/E Command Reference* for descriptions of the VLFNOTE command functions that do not require TSO/E operator authority. Reissue the VLFNOTE command with the correct keywords.

COF10308I

Module: VLFNOTE

Audience: VLFNOTE user

COF10308I DATA SET dsname NOT IN CATALOG.

Explanation: You did not specify the VOLSER keyword on the VLFNOTE command and the data set name that you specified is not in the system catalog.

System action: Processing continues with no change made to VLF storage.

User response: Either reissue the VLFNOTE command with the VOLSER keyword or catalog the data set and then reissue the VLFNOTE command. For more information about the VLFNOTE command, issue 'HELP VLFNOTE' or see *z/OS TSO/E Command Reference*.

Module: VLFNOTE

Audience: VLFNOTE user

Chapter 4. Information Center Facility Messages (ICQ...)

Component name	ICQ
Program producing message	Information Center Facility
Audience and where produced	For Information Center Facility users and administrators at their terminals. Most messages with IDs in the format ICQCxnnn are directed to a user; most messages with IDs in the format ICQAxnnn are directed to an administrator. Names directory (ICQCAnnn) and general (ICQGCnnn) messages are directed to either an administrator or user or both.
Message format	<p>ICQ<i>xxnnn</i></p> <p><i>xx</i> Information Center Facility component</p> <p>AB Courses (administrator)</p> <p>AD User types (administrator)</p> <p>AE Enroll (administrator)</p> <p>AI ISPF defaults (administrator)</p> <p>AM Application Manager (administrator)</p> <p>AN News (administrator)</p> <p>AP Printer Support (administrator)</p> <p>AS APPC/MVS Administration (administrator)</p> <p>CA Names Directory (user/administrator)</p> <p>CB Courses (user)</p> <p>CG Graphical Data Display Manager (user)</p> <p>CI APL Data Analysis Interface II (APLDI) (user)</p> <p>CL Conduit Dialogs (user)</p> <p>CN News (user)</p> <p>CP Printer Support (user)</p> <p>CR A Departmental Reporting System II (ADRS) (user)</p> <p>GA General Information (administrator)</p> <p>GC General (user/administrator)</p> <p>SP Space Management (user/administrator)</p> <p><i>nnn</i> Message serial number</p>
Comments	Italicized words indicate that the system supplies specific information which varies depending on the circumstances. That information is available only when the Information Center Facility displays the message at the terminal.

ICQAB000 Request only one action at a time.

Explanation: Type only one action character on the panel that displays this message, and press the ENTER key.

Module: ICQABC00, ICQABC50, ICQCBC00

ICQAB001 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open one of the required ISPF tables. (If your ISPF log is active, the table name is recorded in the log.) The ISPF TBCREATE, TBOPEN, or TBCLOSE service routine set a return code of 20, which indicates a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC00, ICQABC20, ICQABC40, ICQABC50

ICQAB002 The course was deleted after this list was displayed.

Explanation: Your request failed because another administrator deleted all Information Center Facility records for the course you selected. The deletion occurred between the time that you initially displayed the course list and the time that you selected the course.

Module: ICQABC50, ICQABC00

ICQAB003 A course with this name already exists.

Explanation: The Information Center Facility cannot accept the course name as entered because another course already has that name. You can either:

- View information about the existing course. Return to the first education service panel and reselect the ABSTRACT option.
- Change the course name and press the ENTER key to continue.
- Exit the education service by pressing the END PF key.

Module: ICQABC00

ICQAB004 A course with this IIPS ALIAS already exists.

Explanation: Your request failed because the IIPS alias you specified is already assigned to another course. No two courses can have the same alias. Thus, either the alias you attempted to assign is incorrect, or another course was assigned the alias by mistake. You need to determine which is the case.

The alias associates the course name the Information Center Facility uses with an actual course installed in IIPS. It must match the course name specified on the command the IIPS administrator used to add the course to your system (either the IIPS REGISTER COURSE command or the IIPS COURSE ON command).

Module: ICQABC00

ICQAB005 Maximum number of spaces has been exceeded.

Explanation: More than the maximum number of students are now registered for the course. The Information Center Facility allows you to exceed the maximum. This message is informational only.

Module: ICQABC50

ICQAB006 Request failed; system error. Press HELP.

Explanation: Your request failed because the course index table does not exist. The ISPF TBOPEN service routine set a return code of 8.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC00, ICQABC20, ICQABC40, ICQABC50

ICQAB007 COURSE NAME cannot end with *. Correct and press ENTER.

Explanation: The course name cannot end with an asterisk (*). Correct the name and press the ENTER key.

Module: ICQABC00

ICQAB008 Request failed; *user_id* was modifying the same course.

Explanation: Your attempt to update the course listing or course abstract failed, because another administrator was modifying information about the same course. (That administrator's user ID appears in the message.) The other administrator's updates occurred after you selected the course from the course list.

To see the updated course information, return to the panel displaying the list of courses and enter your request again. You then see any modifications the other administrator made. If necessary, you can change the information displayed.

Module: ICQABC00

ICQAB009 The course information was modified.

Explanation: The Information Center Facility updated the course information as you requested. The name of the modified entry appears first in the list of courses displayed. This message is informational only.

Module: ICQABC00

ICQAB010 *Specified_selection_character* not valid. To select a course, type S.

Explanation: The character you typed to select a course is not allowed. S is the only valid selection character on the panel.

Module: ICQABC50

ICQAB011 Resource in use. To retry, reselect; to cancel, press END.

Explanation: Your request failed because the required course index table is temporarily in use. Another administrator may be using it, or you may be using it in split screen mode. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, retype the action that you want and press the ENTER key. To cancel your request, press the END PF key.

Module: ICQABC00, ICQABC20, ICQABC40, ICQABC50

ICQAB012 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the required course index table is temporarily in use. Another administrator may be using it, or you may be using it in split screen mode. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQABC00, ICQABC20, ICQABC40, ICQABC50

ICQAB013 To save all changes, press END; to erase them, type CANCEL.

Explanation: To permanently save all the changes you made to the registration list, press the END PF key. To cancel all changes, type CANCEL on the COMMAND line and press the ENTER key.

Module: ICQABC50

ICQAB014 Request failed. Another administrator is modifying defaults.

Explanation: Your request to modify the administration defaults failed, because another administrator is currently modifying them or you are trying to modify them on the other part of a split screen. If another administrator is modifying defaults, you might want to find out who that administrator is and what updates the administrator is making.

To exit the education service, press the END PF key.

Module: ICQABC40

ICQAB015 Request cancelled. The registration list was not updated.

Explanation: The Information Center Facility did not update the course registration list because you typed CANCEL to cancel your request. This message is informational only.

Module: ICQABC50

ICQAB016 The administration defaults were modified.

Explanation: The Information Center Facility changed the administration defaults for the education service as you requested. This message is informational only.

Module: ICQABC40, ICQABEC0, ICQCBE40

ICQAB017 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not create the temporary table it uses to serialize updates to the administration defaults. The ISPF TBCREATE service routine set a return code of *return_code*.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC40

ICQAB018 Request cancelled. The student's name was not deleted.

Explanation: The Information Center Facility did not delete the selected name from the course registration list because you pressed the END PF key. This message is informational only.

Module: ICQABC50

ICQAB019 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open the abstract index table that is required to process your request. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB020 Request failed. Another administrator is processing course.

Explanation: Your request failed because the Information Center Facility could not obtain exclusive control of the course index table. Another administrator is using it, or you are using it in split screen mode. The ISPF TBCREATE service routine set a return code of 12.

To retry your request, press the ENTER key or reselect the course. To cancel your request, press the END PF key.

Module: ICQABC00, ICQABC20, ICQABC50

ICQAB021 IIPS ALIAS cannot end with *. Correct and press ENTER.

Explanation: The IIPS ALIAS cannot end with an asterisk (*). Correct the alias and press the ENTER key.

Module: ICQABC00

ICQAB022 No students are registered for this course.

Explanation: Information Center Facility records show no students registered for the course whose registration list you tried to modify. This message is informational only.

Module: ICQABC50

ICQAB023 Request failed. *Userid* is not in the names directory.

Explanation: The TSO/E user ID you specified is not in the Information Center Facility names directory. Therefore, you cannot add the name to the course registration list.

You can use the names service to add the user ID to the names directory, then retry your request. To retry, you must reselect the LISTS option to ensure that the Information Center Facility opens the updated version of the names directory.

Module: ICQABC50

ICQAB024 *Userid* is already registered for this course.

Explanation: The course registration list already contains the TSO/E user ID you attempted to add. No duplicates are allowed.

Module: ICQABC50

ICQAB025 *Userid* deleted. Registration list is now empty.

Explanation: The TSO/E user ID you deleted was the last one on the course registration list. The list is now empty. This message is informational only.

Module: ICQABC50

ICQAB026 Resource in use. To retry, reselect; to cancel, press END.

Explanation: Your request failed because the registration process table is temporarily in use. The ISPF TBCREATE service routine set a return code of 12.

To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQABC20

ICQAB027 The registration list for this course has been updated.

Explanation: The course registration list now includes all of the changes you made to it. This message is informational only.

Module: ICQABC50

ICQAB028 Another administrator just changed the name of this course.

Explanation: Another administrator changed the name of the course whose registration list you are about to update. The change occurred after you displayed the list but before you selected the course from the list. If you are in split screen mode, you may have changed the name of the course.

This message is informational only; you can continue with your work. However, note that the course registration list for the original course is now associated with the new course name. Students registered in the original course will see the word REGISTERED next to the new course name when they display the course list. The old course name will not be displayed.

ICQAB029 • ICQAB035

Module: ICQABC50

ICQAB029 Another administrator just changed information for course.

Explanation: Another administrator changed information about the course whose registration list you are about to update. The updates occurred after you displayed the list but before you selected the course from the list. If you are in split screen mode, you may have changed the information for the course.

To see the modified course information before continuing, press the END PF key to return to the first education service panel. On that panel, select the **ABSTRACT** option.

This message is informational only; you can continue with your work.

Module: ICQABC50

ICQAB030 Request deleted. *Course_name* no longer exists.

Explanation: You were not registered in the course identified in the message because that course has been deleted.

Module: ICQABC20

ICQAB031 Registration for *course_name* denied.

Explanation: An Information Center Facility administrator has denied your request for registration in the specified course. For more information, check with an administrator.

Module: ICQABC20

ICQAB032 *Specified_selection_character* not valid. To select, type a listed character.

Explanation: The character you typed to select a course or a request is not allowed on this panel. Use one of the characters listed in the panel instructions.

Module: ICQABC00, ICQABC20, ICQCBC00

ICQAB033 Request cancelled. Course registration list not updated.

Explanation: The Information Center Facility canceled your request to update the course registration list because you pressed the END PF key to cancel instead of retry your request.

This message is informational only.

Module: ICQABC50

ICQAB034 Request failed; system error. Press HELP.

Explanation: The Information Center Facility cannot process your request, because the names directory table does not exist. The ISPF TBOPEN service routine set a return code of 8.

User response: If you are a user, ask an Information Center Facility administrator whether the names directory has been created. If you are an administrator and the names directory has been created, contact a system programmer to resolve the problem.

Module: ICQABC50

ICQAB035 IIPS ADMINISTRATOR ID is not valid.

Explanation: The IIPS administrator ID that you specified is incorrect. Correct it and press the ENTER key.

Module: ICQABC20

ICQAB036 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not allocate the following data set:
data_set_name

The TSO/E ALLOCATE command processor set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB037 Request failed; system error. Press HELP.

Explanation: Your request failed because the following data set does not exist:
data_set_name

The TSO/E CLIST &SYSDSN built-in function set a return code other than 'OK'.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB038 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not read either the BCONFIG member of the IIPS-qualifier.OS.CTLCARD data set, or the output listing from the IISBATCH program. BCONFIG contains control statements for the IISBATCH program, which the Information Center Facility uses to process registration requests.

The system set return code *return_code* after attempting to read the following data set:

data_set_name

User response: Contact a system programmer or an IIPS administrator to resolve the problem.

Module: ICQABC20

ICQAB039 Request failed; installation error. Press HELP.

Explanation: Your request failed because the Information Center Facility cannot locate the course in which you are trying to register a student. The BCONFIG member of the IIPS-qualifier.OS.CTLCARD data set does not identify the data set in which the course resides.

BCONFIG must contain a DISKnn=YES statement for each data set that contains a course in which students can request registration via the Information Center Facility. The numbers nn identify the data set in which the course resides.

User response: Contact a system programmer or an IIPS administrator to resolve the problem.

Module: ICQABC20

ICQAB040 IIPS registration successful; registration list NOT updated.

Explanation: The student is successfully registered in the IIPS course, but the system could not update the Information Center Facility course registration list. Therefore, the registered student will not see the word REGISTERED next to the course name when displaying the course list.

Either the Information Center Facility could not open the course index table in write mode, or it could not close the table. The ISPF TBOPEN or TBCLOSE service routine set a return code of *return_code*.

User response: Contact your system programmer to resolve the problem.

If the student's user ID is in the names directory, you can update the course registration list yourself using the LISTS option on the first education service panel. The ISPF log data set contains the student's TSO/E user ID and the course name.

Module: ICQABC20

ICQAB041 Registration failed. Course deleted after user made request.

Explanation: Your attempt to register the user failed because the requested course no longer exists. Delete the request by typing D to the left of it.

Module: ICQABC20

ICQAB042 Request failed. The course has no IIPS alias assigned.

Explanation: Your attempt to register the user failed, because the course does not have an IIPS alias assigned to it. The IIPS alias associates the course name the Information Center Facility uses with an actual course installed in IIPS. The alias must match the course name specified on the command the IIPS administrator used to add the course to your system (either the IIPS REGISTER COURSE command or the IIPS COURSE ON command).

To specify an alias:

1. Select the ABSTRACT option on the first education service panel.
2. Request to modify the course listing.

Module: ICQABC20

ICQAB043 Unable to update registration list. Press HELP.

Explanation: Your request to update the registration list failed, because the Information Center Facility could not update the permanent registration process table. The ISPF TBSAVE service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB044 Registration failed; the request was saved.

Explanation: Your attempt to register the student in the IIPS course set a return code of *return_code*. Output from the IIPS REGISTER STUDENT command, which the Information Center Facility issues when processing a request, does not indicate that the registration succeeded.

It is your responsibility to use the diagnostic information displayed at your terminal to determine why the request failed and to correct the problem. The request is not lost.

Module: ICQABC20

ICQAB045 Registration failed; the request was deleted.

Explanation: The registration attempt failed, and the Information Center Facility was unable to reenter the request in the permanent registration process table. Therefore, the request no longer appears on the list of registration requests to be processed.

The ISPF log data set contains the registration information that was deleted (the course name, the student's name, and the student's TSO/E user ID).

You can either:

- Have the user request registration again.
- Register the student by issuing the IIPS REGISTER STUDENT command yourself, then update the course registration list directly using the LISTS option on the first education services panel.

Module: ICQABC20

ICQAB046 User: *user_name* Phone: *user_phone_number*.

Explanation: The Information Center Facility writes this message to the ISPF log data set to record information about the registration request being processed. It contains the name and telephone number of the person who requested registration.

Module: ICQABC20

ICQAB047 User's TSO/E ID: *user_id*.

Explanation: The Information Center Facility writes this message to the ISPF log data set to record information about the registration request being processed. It contains the TSO/E user ID of the person who requested registration.

Module: ICQABC20

ICQAB048 Course Name: *course_name*.

Explanation: The Information Center Facility writes this message to the ISPF log data set to record information about the registration request being processed. It contains the name of the course in which the user requested registration.

Module: ICQABC20

ICQAB049 IIPS ADMINISTRATOR PASSWORD is not valid.

Explanation: The IIPS administrator password that you specified is incorrect. Correct it and press the ENTER key.

Module: ICQABC20

ICQAB100 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not find the course index table. The ISPF TBOPEN service routine set a return code of 8. Someone might have inadvertently deleted or renamed the table.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC01, ICQANC02, ICQANC03

ICQAB101 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the course index table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, press the ENTER key. To cancel it, press the END PF key.

Module: ICQANC01, ICQANC02, ICQANC03

ICQAB102 Request failed; system error. Press HELP.

Explanation: Your request failed because the course index table is not allocated. The ISPF TBCREATE, TBOPEN, or TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC40, ICQABC50, ICQANC02, ICQANC03, ICQANC04

ICQAB103 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the course index table is temporarily in use. The ISPF TBCREATE service routine set a non-zero return code.

To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQANC00

ICQAB104 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the course index table is temporarily in use. The ISPF TBCREATE service routine set a non-zero return code.

To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQANC00

ICQAB105 • ICQAB112

ICQAB105 The course invocation failed.

Explanation: Your request to test the invocation parameters for the specified program, CLIST, or command failed with a return code of 20. Therefore, your request to invoke the following course failed:

course_name

Module: ICQABC00

ICQAB106 STUDENT NUMBER must be S followed by 1-9 characters (A-Z,0-9).

Explanation: The student number is incorrect. It must be S followed by 1-9 characters. Those characters can be letters (A-Z) or numbers (0-9). Correct the student number and press the ENTER key.

Module: ICQABEC0, ICQCB40

ICQAB107 Type high-level qualifier in IIPS DATA SET QUALIFIER field.

Explanation: Type the high-level qualifier your installation uses in IIPS data set names, and press the ENTER key. The default is IIPS.

Module: ICQABEJ0

ICQAB108 Request failed; system error. Press HELP.

Explanation: Your request failed because the data set that contains the course index table is not allocated. The ISPF TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC00

ICQAB109 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open the course index table. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC01, ICQANC02, ICQANC03

ICQAB110 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not copy your updates into the course index table. The ISPF TBCLOSE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC00, ICQANC01, ICQANC02, ICQANC03

ICQAB111 The modify request was cancelled.

Explanation: You canceled the modify request by pressing the END PF key on the previous panel. This message is informational only.

Module: ICQABC00

ICQAB112 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because someone else is using the course index table that contains the course you selected. The ISPF TBCREATE service routine set a non-zero return code.

To retry your request, press the ENTER key. To cancel it, press the END PF key.

Module: ICQANC03

ICQAB113 Type either a **COMMAND NAME**, **CLIST NAME**, or **PROGRAM NAME**.

Explanation: Type the name of the command, CLIST, or program that invokes the computer course you are adding or modifying. Specify any parameters required for invocation in the PARAMETERS field.

To test whether the command, CLIST, or program invokes the course correctly before continuing, type Y in the TEST INVOCATION PARAMETERS field.

Module: ICQABES0, ICQABEU0

ICQAB114 *Specified_selection_character* not valid. To delete a student, type **D**.

Explanation: The selection character you typed to the left of a student's name is not allowed there. To delete a student from the course, type D to the left of the name. To add a student to the registration list, type A on the COMMAND line.

Module: ICQABC50

ICQAB115 **USERID** must be 1-7 characters (A-Z, 0-9, \$, @, #); first not 0-9.

Explanation: The specified user ID is not valid. It must be 1 to 7 characters long, and can contain only characters A through Z, 0 through 9, @, #, or \$. However, the first character cannot be numeric (0 through 9). Correct the user ID and press the ENTER key.

Module: ICQABEI0

ICQAB116 The add request was cancelled.

Explanation: You canceled the add request by pressing the END PF key on the previous panel. This message is informational only.

Module: ICQABC00

ICQAB117 **TYPE OF RECORDING** must be a 2-digit number, 00-15.

Explanation: The value in the TYPE OF RECORDING field is not valid. It must be a two-digit number from 00 to 15. For a list of valid options, press the ENTER key while this HELP panel is displayed or request help on the panel that displayed this message.

You must type a valid number before continuing. To quit, press the END PF key.

Module: ICQABEC0

ICQAB118 **LOCATION NUMBER** must be a three-digit number, 000-999.

Explanation: The value in the LOCATION NUMBER field is not valid. It must be a three-digit number from 000 to 999. Your installation defines valid location numbers using the IIPS LOC command.

For more information, check with your system support group. You must type a valid number before continuing. To quit, press the END PF key.

Module: ICQABEC0

ICQAB119 **AREA NUMBER** must be a two-digit number, 00-99.

Explanation: The value in the AREA NUMBER field is not valid. It must be a two-digit number from 00 to 99. Your installation defines valid area numbers using the IIPS LOC command.

For more information, check with your system support group. You must type a valid number before continuing. To quit, press the END PF key.

Module: ICQABEC0

ICQAB120 • ICQAB127

ICQAB120 TSO/E ID must be 1-7 characters (A-Z, 0-9, \$, @, #); first not 0-9.

Explanation: The value in the TSO/E ID field is not valid. It must be 1 to 7 characters long, and can contain only characters A through Z, 0 through 9, @, #, or \$. However, the first character cannot be numeric (0 through 9).

To continue, correct the TSO/E ID and press the ENTER key. To quit, press the END PF key.

Module: ICQABE50

ICQAB121 IIPS ALIAS is required when AUTHOR:S TSO/E ID is specified.

Explanation: If you type the author's TSO/E ID, you must also type the course's IIPS alias. Users cannot access the IIPS course via the Information Center Facility until you specify the alias. It associates the course name the Information Center Facility uses with an actual course installed in IIPS.

The alias must match the course name specified on the command an IIPS administrator used to add the course to your system (either the IIPS REGISTER COURSE command or the IIPS COURSE ON command). If you do not know the alias, check with your system support group.

Module: ICQABE50

ICQAB122 IIPS ALIAS is required when condition is A, R, or U.

Explanation: If you type A, R, or U in the CONDITION field, you must also type the course's IIPS alias. User's cannot access the IIPS course via the Information Center Facility until you specify the alias. The alias associates the course name the Information Center Facility uses with an actual course installed in IIPS.

The alias must match the course name specified on the command an IIPS administrator used to add the course to your system (either the IIPS REGISTER COURSE command or the IIPS COURSE ON command). If you do not know the alias, check with your system support group.

Module: ICQABE50

ICQAB124 Request cancelled. The registration list was not updated.

Explanation: Either the registration failed, or you canceled registration processing by pressing the END PF key when prompted for your administrator ID or password.

Module: ICQABC20

ICQAB125 The registration list was updated.

Explanation: The registration list was updated as you requested. This message is informational only.

Module: ICQABC20

ICQAB126 Registration for a COMPUTER course is not allowed.

Explanation: Registration is unnecessary and not allowed for a COMPUTER course. The Information Center Facility does not process requests for registration in COMPUTER courses. You should delete the request.

Module: ICQABC20

ICQAB127 CLIST NAME must be 1-8 characters (A-Z, 0-9, \$, @, #); first not 0-9.

Explanation: The value in the CLIST NAME field is not valid. It must be 1 to 8 characters long, and can contain only characters A through Z, 0 through 9, @, #, or \$. However, the first character cannot be numeric (0 through 9).

To continue, correct the CLIST name and press the ENTER key. To quit, press the END PF key.

Module: ICQABES0, ICQABEU0

ICQAB128 COMMAND NAME must be 1-8 characters, A-Z, 0-9, \$, @, #; first not 0-9.

Explanation: The value in the COMMAND NAME field is not valid. The program name must be 1 to 8 characters long, and can contain only characters A through Z, 0 through 9, @, #, or \$. However, the first character cannot be numeric (0 through 9).

To continue, correct the program name and press the ENTER key. To quit, press the END PF key.

Module: ICQABES0, ICQABEU0

ICQAB129 PROGRAM NAME must be 1-8 characters, A-Z, 0-9, \$, @, #; first not 0-9.

Explanation: The value in the PROGRAM NAME field is not valid. The program name must be 1 to 8 characters long, and contain characters A through Z, 0 through 9, @, #, or \$. However, the first character cannot be numeric (0 through 9).

To continue, correct the program name and press the ENTER key. To quit, press the END PF key.

Module: ICQABES0, ICQABEU0

ICQAB200 Resource in use. To retry, reselect; to cancel, press END.

Explanation: Your request failed because the registration process table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQABC20

ICQAB201 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not copy your updates into the permanent course index table. The ISPF TBCLOSE service routine set a return code of 16, which indicates the data set that contains the table is not allocated. The table is normally allocated during LOGON processing.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB202 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open the registration process table required to process your request. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB203 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility was unable to create the registration process table. The ISPF TBCREATE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB204 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility was unable to obtain information about the registration process table, which is a required table. The ISPF TBQUERY service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

ICQAB205 • ICQAB211

Module: ICQABC20

ICQAB205 Resource in use. To retry, reselect; to cancel, press END.

Explanation: The Information Center Facility could not process your request because the registration request table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, retype your selection and press the ENTER key. To cancel your request, press the END PF key.

Module: ICQABC20

ICQAB206 There are no registration requests to process.

Explanation: No one has requested registration in any courses yet; therefore, there are no requests to process. Press the END PF key to leave the education service. This message is informational only.

Module: ICQABC20

ICQAB207 Someone else is processing registration requests. Try later.

Explanation: Your request to process registration requests failed because another administrator was processing registration requests. Only one administrator can perform that task at a time.

Module: ICQABC20

ICQAB208 Request failed. No IIPS data set qualifier is defined.

Explanation: Your request failed because the high-level data set qualifier for the IIPS data sets is undefined. Without the qualifier, the Information Center Facility cannot access the IIPS data sets required to process your request.

To specify the qualifier, select the DEFAULTS option on the first education service panel.

Module: ICQABC20

ICQAB209 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open the registration request table required to process your request. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB210 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the Information Center Facility names directory is temporarily in use. The ISPF TBOPEN service routine set a return code of 12 after attempting to open it.

To retry your request, press the ENTER key. To cancel your request, press the END PF key.

Module: ICQABC20, ICQABC50

ICQAB211 Request failed; system error. Press HELP.

Explanation: Your request failed because the data set that contains the registration process table is not allocated. The ISPF TBSAVE or TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB212 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not copy your updates into the permanent registration process table. The ISPF TBSAVE service routine set a return code of 20.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB213 Request failed; system error. Press HELP.

Explanation: Your request failed because the data set that contains the registration request table is not allocated. The ISPF TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB214 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not copy your updates into the permanent registration request table. The ISPF TBCLOSE service routine set a return code of 20.

User response: Contact a system programmer to resolve the problem.

Module: ICQABC20

ICQAB215 Registration initialization in progress. Please wait.

Explanation: The Information Center Facility opens the registration request table and names directory table, which causes a delay. This delay occurs only when the registration function is initialized. This message is informational only.

Module: ICQABC20

ICQAB216 Select only one request at a time.

Explanation: You can process only one registration request at a time. Type an action character next to only one request and press the ENTER key.

Module: ICQABC20

ICQAB217 Processing for first IIPS request in progress. Please wait.

Explanation: Initialization for the first IIPS request is in progress. The system is allocating the required data sets. Subsequent requests will take less time. This message is informational only.

Module: ICQABC20

ICQAB218 IIPS registration successful; no requests remain.

Explanation: The IIPS registration was successful. No more registration requests remain to be processed. This message is informational only.

Module: ICQABC20

ICQAB219 Request cancelled. Administration defaults not modified.

Explanation: The administration defaults were not modified, because you pressed the END PF key instead of the ENTER key. The ENTER key saves your changes; the END PF key cancels them. This message is informational only.

Module: ICQABC40

ICQAB220 List updated; another administrator changed course name.

Explanation: The course registration list is updated as you requested. However, an administrator changed the course name after you selected it from the course list.

This message is informational only. However, note that the course registration list for the original course is now associated with the new course name. Students registered in the original course will see the word REGISTERED next to the new course name when they display the course list. The old course name will not be displayed.

Module: ICQABC50

ICQAB221 List updated; someone else changed course information.

Explanation: The course registration list is updated as you requested. However, another administrator changed information about the course after you selected it from the course list. To see the modified course information before continuing, press the END PF key to return to the first education service panel. On that panel, select the **ABSTRACT** option.

This message is informational only; you can continue with your work.

Module: ICQABC50

ICQAB222 Request deleted; message sent to user.

Explanation: The user's registration request was successfully deleted. The user will receive a message stating that registration has been denied. This message is informational only.

Module: ICQABC20

ICQAB223 All registration requests have been processed.

Explanation: No registration requests are waiting to be processed. This message is informational only.

Module: ICQABC20

ICQAB224 Registration processing started.

Explanation: The system is allocating and opening the data sets required to process registration requests. This message is recorded in the ISPF log data set, and is informational only.

Module: ICQABC20

ICQAB225 IIPS registration was successful; registration list updated.

Explanation: The user is registered in the requested IIPS course, and the Information Center Facility course registration list has been updated. This message is informational only.

Module: ICQABC20

ICQAB226 Registration failed; the request was deleted.

Explanation: The registration attempt failed, and the Information Center Facility was unable to reenter the request in the permanent registration process table. Therefore, the request no longer appears on the list of registration requests to be processed. The ISPF log data set contains the registration information that was deleted (the course name, the student's name, and the student's TSO/E user ID).

You can either:

- Have the user request registration again.
- Register the student by issuing the IIPS REGISTER STUDENT command yourself, then update the course registration list directly using the LISTS option on the first education services panel.

Module: ICQABC20

ICQAB227 Registration successful; registration list NOT updated.

Explanation: The student is successfully registered in the IIPS course, but the system could not update the Information Center Facility course registration list. Therefore, the registered student will not see the word REGISTERED next to the course name when displaying the course list.

Either the Information Center Facility could not open the course index table in write mode, or it could not close the table. The ISPF TBOPEN or TBCLOSE service routine set a return code of *return_code*. Contact your system programmer to resolve the problem.

If the student's user ID is in the names directory, you can update the course registration list yourself using the LISTS option on the first education service panel. The ISPF log data set contains the student's TSO/E user ID and the course name.

Module: ICQABC20

ICQAB228 Registration processing cancelled. Request remains on list.

Explanation: You canceled registration request processing by pressing the END PF key. This message is informational only.

Module: ICQABC20

ICQAB229 Registration in progress. Please wait.

Explanation: The Information Center Facility invoked the IISBATCH program to process the registration request, which causes a delay. This message is informational only.

Module: ICQABC20

ICQAB402 The course listing was added.

Explanation: The course name appears on the course list, and any course information you entered is saved. This message is informational only.

Module: ICQANC01

ICQAB405 Course listing was added. Course abstract has no text.

Explanation: The course name appears on the course list, and any course information you entered is saved. However, the course abstract has no text. Anyone requesting to view the abstract receives a message indicating that the abstract has no text.

Module: ICQANC01

ICQAB500 No text added or changed; system error. Press HELP.

Explanation: A severe ISPF error occurred when the system attempted to save the text you added or changed. Any updates you made to the text are lost. However, the text of the existing abstract (if there is one) is unchanged.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC01, ICQANC02

ICQAB501 Abstract modified. Other changes, if any, made also.

Explanation: The Information Center Facility modified the course abstract. If you requested changes to the course information, the Information Center Facility made those changes as well.

This message is informational only.

Module: ICQANC01

ICQAB502 Request cancelled. The course abstract was not modified.

Explanation: The Information Center Facility did not modify the course abstract. Either you pressed the END PF key without modifying the abstract, or you typed CANCEL on the panel displaying the text. However, if you requested changes to other course information, those changes were made. This message is informational only.

Module: ICQANC02

ICQAB504 Course information was not modified. Abstract has no text.

Explanation: The course information was not modified. The course abstract has no text. Either you deleted the text or it had none and you added none. This message is informational only.

Module: ICQANC02

ICQAB505 Course information was modified. Abstract was not changed.

Explanation: The Information Center Facility modified the course information, but not the course abstract. This message is informational only.

Module: ICQANC02

ICQAB506 Course information was modified. Abstract has no text.

Explanation: The Information Center Facility modified the course information. The course abstract has no text. Either you deleted it, or there was no text and you added none. This message is informational only.

Module: ICQANC02

ICQAB602 The course listing was deleted.

Explanation: The Information Center Facility successfully deleted all records for the course you selected. This message is informational only.

Module: ICQANC03

ICQAB603 Another administrator already deleted the course listing.

Explanation: Another administrator deleted the course records you tried to delete. The deletion occurred after you displayed the course list, but before you selected the course.

This message is informational only.

Module: ICQANC03

ICQAB604 Request cancelled. The course listing was not deleted.

Explanation: The course listing was not deleted because you pressed the END PF key to cancel your request. This message is informational only.

Module: ICQANC03

ICQAB700 The course abstract has no text.

Explanation: The course abstract you tried to view has no text. This message is informational only.

Module: ICQCNC01

ICQAD000 USER TYPE cannot end with *. Correct and press ENTER.

Explanation: A user type name cannot end with an asterisk (*). Correct the name and press the ENTER key.

On panels that allow you to request a list of user types, you can type part of a user type name followed by an *. However, when adding a user type, you must specify the full name. You cannot request a list.

Module: ICQADC00

ICQAD001 No user types match the information in the USER TYPE field.

Explanation: No user types match the search criteria specified in the USER TYPE field. To add a user type, type A in the ACTION field and press the ENTER key.

To display a list or subset list of currently defined user types, type in the USER TYPE field:

- An asterisk (*)
- A blank
- Part of a name followed by an asterisk, for example,

USER TYPE ==> admin*

Module: ICQADC00

ICQAD003 Specified_selection_character is not valid. To select user type, type V, M or D.

Explanation: The character you used to select a user type is not allowed. Type either V to view, M to modify, or D to delete a user type, and press the ENTER key.

Module: ICQADE02

ICQAD004 Request failed; system error. Press HELP.

Explanation: Your request failed because the user types table does not exist. The ISPF TBOPEN service routine set a return code of 8. The table is normally created during installation.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00

ICQAD005 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the user types table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQADC00

ICQAD006 Request failed; system error. Press HELP.

Explanation: Your request failed because the data set containing the user types table is not allocated. The ISPF TBOPEN or TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00

ICQAD007 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open the user types table. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00

ICQAD009 The user type was deleted.

Explanation: The Information Center Facility deleted the user type you requested. This message is informational only.

Module: ICQADC00

ICQAD010 • ICQAD017

ICQAD010 Request failed; system error. Press HELP.

Explanation: Your request failed because the user types table does not exist. The ISPF TBOPEN service routine set a return code of 8. The user types table is normally created when the Information Center Facility is installed.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00

ICQAD011 Resource in use. To retry, press END; to quit, type CANCEL.

Explanation: Your request failed because the user types table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, press the END PF key. To cancel it, type CANCEL after the OPTION arrow and press the ENTER key.

Module: ICQADC00

ICQAD012 Request failed; system error. Press HELP.

Explanation: Your request failed because the data set containing the user types table is not allocated. The ISPF TBOPEN or TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00, ICQADC05

ICQAD013 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open the user types table. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00

ICQAD014 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not update and close the user types table. The ISPF TBCLOSE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00, ICQADC05

ICQAD015 The user type was added.

Explanation: The Information Center Facility added the user type you specified. This message is informational only.

Module: ICQADC00

ICQAD016 The user type was modified.

Explanation: The Information Center Facility modified the user type as you requested. This message is informational only.

Module: ICQADC00

ICQAD017 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not create the temporary table that it uses to pass parameters. The ISPF TBCREATE service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQADC00

ICQAD018 Specify ACTION or request a list of user types.

Explanation: Either:

- Type an action in the ACTION field. The panel displaying this message lists the acceptable actions.
- Request a list of user types. To request a list, in the USER TYPE field, type an asterisk (*), a blank, or part of a user type name followed by an asterisk. For example:

```
USER TYPE ==> admin*
```

Module: ICQADC00

ICQAD019 A user type with this name already exists.

Explanation: You cannot have duplicate user type names. You must either:

- Specify a different user type name.
- Type R in the ACTION field to replace the existing user type, if adding a user type.
- Press the END PF key to cancel your request.

Module: ICQADC00, ICQADC04

ICQAD020 Request cancelled. The user type was not added.

Explanation: The Information Center Facility did not add the user type because you canceled your request. This message is informational only.

Module: ICQADC00

ICQAD021 Request cancelled. The user type was not replaced.

Explanation: The Information Center Facility did not replace the user type because you canceled your request to modify it. This message is informational only.

Module: ICQADC00

ICQAD022 Request cancelled. The user type was not modified.

Explanation: The Information Center Facility did not modify the user type because you cancelled your request to modify it. This message is informational only.

Module: ICQADC00

ICQAD023 The user type does not exist. You cannot replace it.

Explanation: You tried to add a user type, but that user type already existed. You typed R to replace the user type, but at the same time you changed the user type name to one that does not exist.

You can either:

- Add the user type that does not yet exist by typing A. The Information Center Facility will then add a user type with that name.
- Replace the user type by retyping the existing user type name. The Information Center Facility will then delete and replace the user type.

Module: ICQADC00

ICQAD024 Request failed, severe error. Press HELP.

Explanation: Request failed because TBSAVE returned with a non-zero return code when the user types table was saved in your library.

User response: Contact your system programmer for assistance.

Module: ICQADC00

ICQAD025 • ICQAE002

ICQAD025 The user type was replaced.

Explanation: The Information Center Facility replaced the user type as you requested. This message is informational only.

Module: ICQADC00

ICQAD026 Request cancelled. The user type was not deleted.

Explanation: The Information Center Facility did not delete the user type because you canceled the delete request. This message is informational only.

Module: ICQADC00

ICQAD028 Type the name of the user type in the USER TYPE field.

Explanation: When adding a user type, you must specify the name of the user type in the USER TYPE field. Type the full name and press the ENTER key.

Module: ICQADE15

ICQAD030 To save all changes, press END; to erase them, type CANCEL.

Explanation: To save the user type information you entered, either press the END PF key, or type END on the COMMAND line and press the ENTER key. To erase all your entries, type CANCEL on the COMMAND line and press the ENTER key.

Module: ICQADC01, ICQADC02, ICQADC03, ICQADC04

ICQAD031 Select only one user type at a time.

Explanation: Type a selection character next to only one user type and press the ENTER key.

Module: ICQADC00

ICQAE000 Request cancelled. The user was not enrolled.

Explanation: The user was not enrolled because you pressed the END PF key, which canceled enrollment processing. This message is informational only.

Module: ICQAEC00

ICQAE001 Error closing the current application ID in library ICQAETAB.

Explanation: The system could not close the current ISPF application profile table in the newly enrolled user's profile library, ICQAETAB.

System action: Processing terminates.

User response: Determine if the enrolled user's profile library, ICQAETAB, has enough space to close the ICQZPROF profile table. Contact your system programmer for assistance.

Module: ICQAEC00

Audience: Information Center Facility administrator

ICQAE002 Enrollment failed. Obtain further help.

Explanation: The enrollment failed because one of the following commands failed:

- ACCOUNT ADD
- ACCOUNT CHANGE
- RACF® RDEFINE
- RACF ADDUSER TSO
- RACF ALTUSER TSO
- RACF PERMIT

- DEFINE ALIAS

The messages you saw displayed previously describe the error.

User response: To resolve the problem, contact the TSO/E administrator in charge of the command that failed.

Module: ICQAEC00

ICQAE003 *Specified_selection_character* **is not valid. Type correct_selection_character next to one entry.**

Explanation: The field indicated by the cursor contains a not valid character. Type *correct_selection_character* next to only one entry at a time.

Module: ICQAEE50

ICQAE004 **Type Y for either UPDATE RACF or UPDATE UADS, or both.**

Explanation: To enroll a TSO/E user, specify that the user information be stored in the RACF data base or the SYS1.UADS data set. If in doubt, consult the system programmer to find out whether the TSO/E logon process uses RACF, UADS, or both.

User response: Type Y (yes) in one or both of the fields to indicate where the user information should be stored.

Module: ICQAEE41

ICQAE005 **The user is enrolled. Created profile not changed.**

Explanation: You successfully enrolled the user, but chose not to change the enrolled user's profile. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAEC00

Audience: Information Center Facility administrator

ICQAE007 **The user is enrolled. No ISPF profile was created.**

Explanation: The user is enrolled, but the Information Center Facility was unable to allocate the ISPF profile data set. The ALLOCATE command failed with a return code of 12.

The user's profile contains the same information as the system default profile with only the JOB statement information changed.

Module: ICQAEC00

ICQAE008 **The user is enrolled.**

Explanation: The user has been enrolled by the Information Center Facility. This message is informational only.

Module: ICQAEC00

ICQAE009 **The user is enrolled. Created profile not modified.**

Explanation: You successfully enrolled the user, but chose not to change the enrolled user's profile. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAEC00

Audience: Information Center Facility administrator

ICQAE010 • ICQAE020

ICQAE010 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not open the user types table. The ISPF TBOPEN service routine set a return code of *return_code*.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE011 User's ISPF profile already exists; only user can modify it.

Explanation: The user already had an ISPF profile before enrollment. The Information Center Facility uses the same profile, which you cannot change.

Module: ICQAEC00

ICQAE013 Request failed; resource in use. Try later.

Explanation: Your request failed because the user types table is in use. The ISPF TBOPEN service routine set a return code of 12.

Press the END PF key to cancel your request, and try again later.

Module: ICQAEC00

ICQAE014 Request failed; system error. Press HELP.

Explanation: Your request failed because the system was unable to close the ISPF profile table. The ISPF TBCLOSE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE017 The specified user type requires an operator ID card.

Explanation: The user type you selected requires an operator ID card, but you typed N in the OPERATOR ID CARD field. Either type Y in that field, or specify a user type that does not require an operator ID card. If you type Y, you must insert the card before continuing enrollment processing to associate the card with the user.

(An operator ID card is a card the user must insert into a card reader when logging onto the system. The card is a security measure.)

Module: ICQAEC00

ICQAE018 Specified user type does not require an operator ID card.

Explanation: The user type you selected does not require an operator ID card, but you typed Y in the OPERATOR ID CARD field. Either type N in that field, or specify a user type that requires an operator ID card. If you require the user to insert a card, you must also insert the card before continuing enrollment processing to associate the card with the user.

(An operator ID card is a card the user must insert into a card reader when logging onto the system. The card is a security measure.)

Module: ICQAEC00

ICQAE020 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not open an ISPF defaults table. The ISPF TBOPEN service routine set a return code of *return_code*.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE021 The RACF PERMIT command for *resource* was successful.

Explanation: The Information Center Facility permitted the user to access the specified resource. This message is informational only.

User response: None

Module: ICQAEC00

ICQAE022 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not create the user's ISPF profile table. The ISPF TBCREATE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE023 Request failed; resources in use. Try later.

Explanation: Your request failed because the ISPF defaults table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12.

Press the END PF key to cancel your request, and try again later.

Module: ICQAEC00

ICQAE025 User type not defined. Choose another and retry.

Explanation: The user type you selected is not defined (that is, the user types table contains no entry for it). Respecify the user type.

Module: ICQAEC00

ICQAE026 The RACF RDEFINE command for *resource* failed.

Explanation: The RACF RDEFINE command failed to define the specified resource. The possible resources include:

- ACCTNUM -- account number
- TSOPROC -- logon procedure
- PERFGRP -- performance group
- TSOAUTH -- resources specified on the RACF Security Information panel

User response: Contact the system programmer to resolve the problem.

Module: ICQAEC00

ICQAE027 The RACF PERMIT command for *resource* failed.

Explanation: The RACF PERMIT command failed to permit the user to the specified resource. The possible resources include:

- ACCTNUM -- account number
- TSOPROC -- logon procedure
- PERFGRP -- performance group
- TSOAUTH -- resources specified on the RACF Security Information panel

User response: Contact the system programmer to resolve the problem.

Module: ICQAEC00

ICQAE028 ACCOUNT NUMBER is too long for enrollment in RACF.

Explanation: RACF account numbers can contain a maximum of 39 characters. The account number you typed contains more than 39 characters.

User response: Correct the account number and press the ENTER key.

ICQAE029 • ICQAE045

Module: ICQAEE40, ICQAEE41

ICQAE029 ACCOUNT NUMBER is not valid. Correct and press ENTER.

Explanation: The account number you typed is not valid. Account numbers can contain the characters A-Z, 0-9 , @, \$, &, or #. Account numbers can have the following lengths:

- For RACF, 1-39 characters
- For UADS, 1-40 characters

User response: Correct the account number and press the ENTER key.

Module: ICQAEC00

ICQAE040 The ACCOUNT ADD command executed successfully.

Explanation: The TSO/E ACCOUNT ADD command executed successfully. The user is now identified to TSO/E and the Information Center Facility. This message is informational only.

Module: ICQAEC00

ICQAE041 The ACCOUNT ADD command failed.

Explanation: The TSO/E ACCOUNT ADD command failed. The user is not identified to the Information Center Facility or TSO/E.

User response: Contact the system programmer to resolve the problem.

Module: ICQAEC00

ICQAE042 The user ID was updated.

Explanation: The system updated the user's TSO/E profile to include the information specified in the user type you selected. This message is informational only.

Module: ICQAEC00

ICQAE043 The user ID was not updated.

Explanation: The Information Center Facility did not update the user's TSO/E profile to include the information specified in the user type you selected.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE044 The user is defined to RACF.

Explanation: The user is now identified to RACF. This message is informational only.

Module: ICQAEC00

ICQAE045 The user is not defined to RACF.

Explanation: The user is not identified to RACF. The user remains enrolled, but the system neither added nor updated an entry for the user in the names directory. You can add a names directory entry yourself using the names service.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE046 The DEFINE ALIAS COMMAND executed successfully.

Explanation: The Information Center Facility successfully put a user catalog alias for the person's user ID into the master catalog. This message is informational only.

Module: ICQAEC00

ICQAE047 DEFINE ALIAS command failed.

Explanation: The DEFINE ALIAS command failed. The system did not put a user catalog alias for the person's user ID into the master catalog. However, the user remains enrolled. If the assigned user type caused the system to issue RACF commands, the person is also identified to RACF.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE048 RACF is not active.

Explanation: The user type you selected specifies parameters for RACF commands. However, RACF is not active on your system.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE049 Request failed. You lack authority to use ACCOUNT command.

Explanation: Because you are not authorized to issue the TSO/E ACCOUNT command, you cannot enroll users in the Information Center Facility.

Press the END PF key to cancel your request, and ask another Information Center Facility administrator to give you ACCOUNT authority.

Module: ICQAEC00

ICQAE050 THE RACF ADDSD COMMAND EXECUTED SUCCESSFULLY.

Explanation: The Information Center Facility successfully added a generic profile for the user being enrolled. This message is informational only.

Module: ICQAEC00

ICQAE051 THE RACF ADDSD COMMAND FAILED.

Explanation: The RACF ADDSD command failed. The user remains enrolled, but no generic profile has been created for the user being enrolled. The system neither added nor updated an entry for the user in the names directory. The names directory entry can be added by using the names service.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE052 THE RACF ALTUSER command executed successfully.

Explanation: The RACF ALTUSER command successfully added or altered a generic profile for the user being enrolled. This message is informational only.

User response: None

Module: ICQAEC00

ICQAE053 THE RACF ALTUSER command failed.

Explanation: The RACF ALTUSER command failed to alter a generic profile for the user being enrolled.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE055 THE RACF SETROPTS command executed successfully.

Explanation: The RACF SETROPTS command successfully defined a resource or updated a resource definition as part of the TSO/E user information. This message is informational only.

User response: None

Module: ICQAEC00

ICQAE056 THE RACF SETROPTS command failed.

Explanation: The RACF SETROPTS command failed to define a resource or update the resource definition as part of the TSO/E user information.

The problem is mostly likely because you lack authorization to use the SETROPTS command. The SETROPTS command must be issued successfully for the user to have access to the resources specified during their enrollment.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE057 The RACF ALTUSER command with the TSO operand failed.

Explanation: The RACF ALTUSER command with the TSO operand failed and the user is not identified to TSO/E and the Information Center Facility.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE058 Neither RACF nor UADS are available for enrollment.

Explanation: You tried to enroll a TSO/E user but your request failed because RACF is not active and SYS1.UADS is unavailable.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC41

ICQAE059 The RACF ADDUSER command with the TSO operand failed.

Explanation: The RACF ADDUSER command with the TSO operand failed and the user is not identified to TSO/E and the Information Center Facility.

User response: Contact a system programmer to resolve the problem.

Module: ICQAEC00

ICQAE061 Error copying ISPSPROF from the system file. Press HELP.

Explanation: While attempting to create the enrolled user's profile, the system could not copy the ISPSPROF profile table from the ICQTABL system profile library.

System action: Processing terminates.

User response: Determine if the ddname for the Information Center Facility system profile is allocated correctly and accessible to Application Manager dialogs. Contact your system programmer for assistance.

Module: ICQAEC00

Audience: Information Center Facility administrator

ICQAE062 Error copying ICQZPROF from the system file. Press HELP.

Explanation: While attempting to create the enrolled user's profile, the system could not copy the ICQZPROF profile table from the ICQTABL system profile library.

System action: Processing terminates.

User response: Determine if the ddname for the Information Center Facility system profile is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs. Contact your system programmer for assistance.

Module: ICQAEC00

Audience: Information Center Facility administrator

ICQAE063 Error copying ISPSPROF from the ISPF base tables. Press HELP.

Explanation: The ICQTABL profile library did not contain the profile member, ISPSPROF. The enroll processing then attempted to copy ISPSPROF from the ISPF base profile library, ISPTLIB.

System action: Processing terminates.

User response: Determine if the ddname for the ISPF base table library, ISPTLIB, is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs. Contact your system programmer for assistance.

Module: ICQAEC00

Audience: Information Center Facility administrator

ICQAE064 Error copying ISPPROF from the ISPF base tables. Press HELP.

Explanation: The ICQTABL profile library did not contain the profile member, ICQZPROF. The enroll processing then attempted to copy ICQZPROF from the ISPF base profile library, ISPTLIB.

System action: Processing terminates.

User response: Determine if the ddname for the ISPF base table library, ISPTLIB, is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs. Contact your system programmer for assistance.

Module: ICQAEC00

Audience: Information Center Facility administrator

ICQAI000 Request failed; system error. Press HELP.

Explanation: Your request failed because one or both of the profile tables do not exist. Normally, the system creates these tables when the Information Center Facility is installed.

User response: Contact a system programmer to resolve the problem.

Module: ICQAIC00

ICQAI001 Profile in use. To retry, press END; to quit, type CANCEL.

Explanation: Your request failed because one or both of the profile tables are in use. The ISPF TBOPEN service routine set a return code of 12.

To retry your request, press the END PF key. To cancel your request, type CANCEL after the OPTION arrow and press the ENTER key.

Module: ICQAIC00, ICQAIC01

ICQAI002 • ICQAI007

ICQAI002 Request failed; system error. Press HELP.

Explanation: Your request failed because one or both of the profile tables are not allocated. The ISPF TBOPEN or TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQAIC00

ICQAI003 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not open one or both of the profile tables. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQAIC00

ICQAI004 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not close one or both of the profile tables. The ISPF TBCLOSE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQAIC00

ICQAI005 Cannot update ISPF defaults in split screen. Press HELP.

Explanation: You cannot be in split screen when updating the ISPF defaults or an enrolled user's profile.

System action: The system waits for your response.

User response: To get out of split screen mode, press the SWAP PF key to display the opposite side of the split, and press the END PF key repeatedly until the screen is no longer split. Resume updating the ISPF defaults or the enrolled user's profile.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI006 Error restoring profile table for the current application ID.

Explanation: Your changes to either the Information Center Facility system default profile or an enrolled user's profile were saved, but your own profile table for the current ISPF application profile table could not be saved.

System action: The system saved the system default profile or the enrolled user's profile, but did not update your (administrator) profile.

User response: Access your profile member through the ISPF default processing available in ISPF. If this is not successful, check the allocation of your profile data set accessible through the ddname ISPPROF.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI007 Error restoring your profile table, ISPSPROF. Press HELP.

Explanation: Your changes to either the Information Center Facility system default profile or an enrolled user's profile were saved, but your own profile table, ISPSPROF, could not be re-opened.

System action: The system saved the system default profile or the enrolled user's profile, but did not update your (administrator) profile.

User response: Access your profile member through the ISPF default processing available in ISPF. If this is not successful, check the allocation of your profile data set accessible through the ddname ISPPROF.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI008 Profile tables copied from the ISPF base tables.

Explanation: The system profile tables were not available when the system was creating the profile for the enrolled user. However, the system used copies of the ISPF base profile tables that were available through the ddname ISPTLIB. This message is informational only.

System action: Processing continues. Profile tables were copied from the ISPF base profile tables.

User response: None.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI009 ISPF default processing failed. Required parameter missing.

Explanation: When invoking the ISPF default processing exec, ICQAIR00, the required parameter (profile ddname) was not passed.

System action: Processing terminates.

User response: If you were changing the Information Center Facility system default processing, check that you included the ICQTABL parameter in the invocation command for the function. If you were changing an enrolled user's profile, contact your system programmer for assistance.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI010 Request failed; system error. Press HELP.

Explanation: Your request failed because one or both of the profile tables do not exist. Normally, the system creates these tables when the Information Center Facility is installed.

User response: Contact a system programmer to resolve the problem.

Module: ICQAIC01

ICQAI011 Profile in use. To retry, reselect; to cancel, press END.

Explanation: Your request failed because one or both of the profile tables are in use. The ISPF TBOPEN service routine set a return code of 12.

User response: To retry your request, type a selection character after the OPTION arrow and press the ENTER key. To cancel your request, type CANCEL after the OPTION arrow and press the ENTER key.

Module: ICQAIC01

ICQAI012 Request failed; system error. Press HELP.

Explanation: Your request failed because one or both of the profile tables are not allocated. The ISPF TBCLOSE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQAIC01

ICQAI013 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not open one or both of the profile tables. The ISPF TBOPEN service routine set a return code of 20, which indicates a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQAIC00 ICQAIC01

ICQAI015 To save all changes, press END; to erase them, type CANCEL.

Explanation: To save all changes, press the END PF key. To cancel your changes, type CANCEL on the COMMAND line and press the ENTER key. This message is informational only.

Module: ICQAIC01

ICQAI020 Unable to close the profile table ISPSPROF. Press HELP.

Explanation: While changing the Information Center Facility system default profile, the system could not close your profile table, ISPSPROF.

System action: Processing terminates.

User response: Check the status of your data set available through the ddname ISPPROF. If the profile data set is full or has been freed, restart the Information Center Facility and try the function again.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI021 Error closing the profile table for the current application ID.

Explanation: While changing the Information Center Facility system default profile, the system could not close the current ISPF application profile table.

System action: Processing terminates.

User response: Check the status of your data set available through the ddname ISPPROF. If the profile data set is full or has been freed, restart the Information Center Facility and try the function again.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI022 Error opening ISPF base table ISPSPROF. Press HELP.

Explanation: While changing the Information Center Facility system default profile, the system could not access the ISPSPROF profile table.

System action: Processing terminates.

User response: Ensure that the ISPSPROF base table resides within the ISPF base table, ISPTLIB.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI023 System profile table ISPSPROF in use. Try again later.

Explanation: The ISPSPROF profile table was in use, most likely by another administrator changing the Information Center Facility system default profile.

System action: Processing terminates.

User response: Either determine who is currently using the system default profile and resolve the contention, or try again at a later time.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI024 Error opening ISPSPROF in the system defaults file. Press HELP.

Explanation: The system could not copy the ISPSPROF profile table from the Information Center Facility system defaults file.

System action: Processing terminates.

User response: Determine if the ddname for the Information Center Facility system default profile is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI025 Error opening the ISPF base table ISPPROF. Press HELP.

Explanation: The ICQTABL profile library did not contain the profile member, ICQZPROF. The enroll processing then attempted to copy ISPPROF from the ISPF base profile library, ISPTLIB.

System action: Processing terminates.

User response: Determine if the ddname for the ISPF base table library, ISPTLIB, is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI026 Error closing the current application ID in the defaults file.

Explanation: While changing the Information Center Facility system default profile, the system could not close the current ISPF application profile table in the passed Information Center Facility system defaults file. Changes made to the profile were not saved.

System action: Processing terminates.

User response: Determine if the ddname for the passed defaults file is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs. Retry the function.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI027 Error opening the current application ID in the defaults file.

Explanation: While changing the Information Center Facility system default profile, the system could not open the current ISPF application profile table in the passed Information Center Facility system defaults file. No changes were made to the passed profile tables.

System action: Processing terminates.

User response: Determine if the ddname for the passed system defaults file is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs. Retry the function.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI028 Error saving table ISPSPROF in the defaults file. Press HELP.

Explanation: While changing the Information Center Facility system default profile, the system could not save the ISPSPROF profile table in the passed Information Center Facility system defaults file. Any changes to the passed profile were not saved.

System action: Processing terminates.

User response: Determine if the ddname for the passed system defaults file is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs. Retry the function.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI029 Error saving the current application ID in the defaults file.

Explanation: While changing the Information Center Facility system default profile, the system could not save the current ISPF application profile table in the passed Information Center Facility system defaults file. Any changes to the passed profile were not saved.

System action: Processing terminates.

User response: Determine if the ddname for the passed system defaults file is allocated correctly and the data set allocated to that ddname is accessible to Application Manager dialogs. Retry the function.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI030 ISPF defaults application ID is not valid. Press HELP.

Explanation: The application ID for the ISPF defaults dialog application must be ICQZ, which is reserved.

System action: Processing terminates.

User response: Change the application ID of the ISPF defaults function to ICQZ.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI031 Application ID is in use. Invoking application using reserved ID.

Explanation: The invoking application is using ICQZ as an application ID. Do not use ICQZ because it is the reserved application ID for the ISPF defaults dialog function.

System action: Processing terminates.

User response: Use the Application Manager to change the application ID for the invoking application.

Module: ICQAIR00

Audience: Information Center Facility administrator

ICQAI032 Now editing the administrator's ISPF defaults.

Explanation: You specified Y in the CHANGE ISPF DEFAULTS for the ADMINISTRATOR field during the enroll process in ICF. Specifying Y allows you to change your own ISPF defaults.

System action: None

User response: The administrator edited a newly enrolled user's ISPF default information. You can now edit your own ISPF default information. This is an informational message.

Module: ICQAEC00

Audience: None

ICQAM007 Specified language is not an installation defined language.

Explanation: The language entered is not defined by your installation. Languages are defined by the QAMLANGL variable in the ICFENVIRON environment. Type an installation defined language.

Module: ICQAMCL0, ICQAMCM0, ICQASRP1

ICQAM008 Type Y or N in the Available field.

Explanation: Type Y (yes) or N (no) in the Available field to indicate whether the application should be made available for general use. If you type Y, the application will be available for general use. If you do not want the application available for general use, type N in the Available field and press ENTER.

This message is informational only.

Module: ICQAME20, ICQAME24, ICQAME30, ICQAME35, ICQAME36, ICQAME38

ICQAM009 *Specified_selection_character* is not valid on the option line of this panel.

Explanation: What you typed on the option line is not valid. Read the directions on the panel to find out what options are valid, and type a valid option.

Module: ICQAME13

ICQAM010 System error. Press HELP.

Explanation: None

User response: Try to resolve the system error or contact a system programmer for assistance. If the error cannot be resolved, type CANCEL on the command line to leave the panel.

Module: ICQAMCU0

ICQAM011 Changes accepted. Press END to exit.

Explanation: The selections, modifications, or both you just made were accepted. Pressing the END PF key caused the changes to be processed but did not cause you to leave the panel. Generally after making changes, you should press ENTER. To exit, press the END PF key.

Module: ICQAMCF0, ICQAMCP0

ICQAM012 REPLACE not specified. Language/Name/Level not unique.

Explanation: You specified N in the REPLACE option and the combination of language, application name, and level is not unique for the level you are modifying. Either enter a new application name or a different language or change the REPLACE option from N to Y.

Module: ICQAMCF0, ICQAMCP0

ICQAM013 *Specified_command* is not valid on the command line of this panel.

Explanation: What you typed on the command line is not valid on the panel. Read the directions on the panel to find out what commands are valid, and type a valid command.

Module: ICQAME10, ICQAME13, ICQAME16, ICQAME17, ICQAME21, ICQAME21, ICQAME26, ICQAME31, ICQAME32, ICQAME33, ICQAME34, ICQAME37, ICQAME39, ICQAME40, ICQAME41, ICQAME42, ICQAME60

ICQAM014 Enter the required field.

Explanation: You did not type any information in the field indicated by the cursor. Fill in the appropriate information or type CANCEL to exit the panel.

Module: ICQAME21, ICQAME31, ICQAME39

ICQAM015 Select only one entry at a time.

Explanation: You can select only one entry at a time. Type only one option next to an entry and press ENTER to process it.

Module: ICQAMCL0, ICQAMCM0, ICQASRP1

ICQAM016 Command conflict. END not processed.

Explanation: When you type an option and then press the END PF key, a command conflict results. To process an option, press ENTER.

Module: ICQAMCM0, ICQAMCP0

ICQAM017 • ICQAM032

ICQAM017 **Keyword is not valid.**

Explanation: The word in the Keyword field is not valid. Type a valid keyword.

Valid keywords contain 11 or fewer characters, the first of which must be alphabetic. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCP0, ICQAME31

ICQAM018 **Application Name is not valid.**

Explanation: The application name in the field indicated by the cursor is not valid. Application names must contain 12 or fewer characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCP0, ICQAME31, ICQAME39

ICQAM019 *Specified_action_character* **is not valid. Type one of the listed actions.**

Explanation: The action character you typed in the action field is not valid. Read the directions on the panel to find out what action characters are valid.

Module: ICQAME10, ICQAME17

ICQAM020 *Specified_selection_character* **is not valid. Type one of the listed selections.**

Explanation: The selection character you typed in the action field is not valid. Read the directions on the panel to find out what selection characters are valid.

Module: ICQAMCL0

ICQAM021 *** is allowed only at the end to request a list.**

Explanation: An * cannot be part of a name. It can only be used to obtain a list of items, either by being the only character in the field or at the end of a group of characters. If you type an * as a single character, you get an entire list. If you type an * at the end of a group of characters, you get a list of items beginning with those characters.

Module: ICQAME10, ICQAME21, ICQAME31

ICQAM030 **The application was not created.**

Explanation: The application you requested to add with an installation file was not created because you typed CANCEL on the Command line.

This message is informational only.

Module: ICQAMCP0, ICQAMCF0

ICQAM031 **The application does not need to be verified.**

Explanation: The application you requested to verify has already been verified. Either it was verified by selecting each of the options, or it was an installation file and someone verified it previously with the VERIFY option.

This message is informational only.

Module: ICQAMCP0, ICQAMCF0

ICQAM032 **Application cannot be made available until it is verified.**

Explanation: The Available field for an application cannot be changed to Y (yes) until the application is verified. Select the VERIFY option and when it completes successfully, change the Available field to Y (yes).

Module: ICQAMCP0, ICQAMCF0

ICQAM033 CANCEL was processed. Verification was stopped.

Explanation: When you typed CANCEL on the Command line of the panel where the error was detected, the verification process stopped.

This message is informational only.

Module: ICQAMCP0, ICQAMCF0

ICQAM034 Select option 1 to enter a valid language.

Explanation: The installation file you added does not have a valid language and cannot add the application. To save the application, select option 1 and enter a language defined by your installation.

Languages are defined by the QAMLANGL variable in the ICFENVIRON environment.

Module: ICQAMCP0, ICQAMCF0

ICQAM035 Select option 1 to enter a unique name/language combination.

Explanation: The installation file you added does not have a unique name/language combination and cannot add the application. To save the application, select option 1 and enter a unique name/language combination.

Module: ICQAMCP0, ICQAMCF0

ICQAM036 Select option 1 to enter a valid application name.

Explanation: The installation file you added is not defined with a valid application name and cannot add the application. To save the application, select option 1 and enter a valid application name.

Valid application names must contain 1 - 12 characters. These characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters. The first character cannot be numeric.

Module: ICQAMCP0, ICQAMCF0

ICQAM037 Select option 1 to enter the required language.

Explanation: The installation file you added does not have the required language for the application and cannot add the application. To save the application, select option 1 and enter the language for that application.

Module: ICQAMCP0, ICQAMCF0

ICQAM038 Verification completed successfully.

Explanation: The application that was added by an installation file has been verified. The application can now be made available to users.

This message is informational only.

Module: ICQAMCP0, ICQAMCF0

ICQAM039 Select option 5 to verify the installation file.

Explanation: When an installation file adds a function or an environment, the file must be verified before the function or environment can be made available to users. Select option 5 to allow the system to verify the installation file, and wait until a message confirms that verification is complete.

If an error is discovered during verification, you will see an error message and the panel on which the error was found. When the error is corrected, press END to continue verification. To stop verification, type CANCEL on the Command line.

This message is information only.

Module: ICQAMCF0

ICQAM040 Select option 3 to verify the installation file.

Explanation: When an installation file adds a panel, the file must be verified before the panel can be made available to users. Select option 3 to allow the system to verify the installation file, and wait until a message confirms that verification is complete.

If an error is discovered during verification, you will see an error message and the panel on which the error was found. When the error is corrected, press END to continue verification. To stop verification, type CANCEL on the Command line.

This message is information only.

Module: ICQAMCP0

ICQAM041 Application cannot be copied until it is verified.

Explanation: The application you selected to copy was created by an installation file that was not verified. Verification must take place before an application can be copied.

To verify the application's installation file, type M (modify) next to the application name and then select the VERIFY option.

Module: ICQAMCP0, ICQAMCF0

ICQAM042 Application does not exist. Blank the ID to remove it.

Explanation: The application indicated by the cursor does not exist and cannot be on the selection panel. To remove it, type blanks over the ID or over the default ID of ???.

Module: ICQAMCP0

ICQAM043 Option ID was not specified. Enter a unique ID.

Explanation: The application indicated by the cursor does not have an ID. Each option on a selection panel must be identified with a unique ID. Type an option ID over the default ID of ???.

Option IDs must contain 1-3 characters. The characters can be any combination of alphabetic (A-Z) or numeric (0-9).

Module: ICQAMCP0

ICQAM044 Language was defaulted to *default_language*.

Explanation: The application did not specify a language in the installation file. The default language was added.

To keep the default language, press ENTER. To change the default language, type over it and press ENTER.

Module: ICQAMCP0

ICQAM045 Application cannot be tested until it is verified.

Explanation: The application you requested to test has not been verified. Before you can test an application, it must be verified.

To verify an application, select the VERIFY option.

Module: ICQAMCP0

ICQAM046 Installation file saved but not verified.

Explanation: The installation file you loaded is saved but not verified. Before you can use the application added by an installation file, it must be verified.

To verify an installation file, select the VERIFY option.

Module: ICQAMCP0

ICQAM047 Name/Language exists at a higher level. Press HELP.

Explanation: You cannot create an application name that already exists at a higher level of administration than yours.

System action: The system waits for your response.

User response: To create an application with the same name as one at a higher level, copy the higher-level application down to your level of administration.

Module: ICQAMCF0, ICQAMCP0

Audience: Information Center Facility administrator

ICQAM048 Same language/name exists with a different application type.

Explanation: The specified language and name for the application is the same as another application with a different application type. You cannot specify the REPLACE option when the application type is different. Specify another language or application name.

Module: ICQAMCF0, ICQAMCP0

ICQAM049 Name/Language/Level already exists. Select option 1 for new name.

Explanation: When you are copying an application from a higher level of administration and that application exists with the same name at your level of administration, then give the new application a unique name.

System action: The system waits for your response.

User response: Select option 1 to give the application a new name.

Module: ICQAMCP0, ICQAMCF0

Audience: Information Center Facility administrator

ICQAM072 Group administration data set could not be allocated.

Explanation: The group administration data set could not be allocated for the new group identification specified.

System action: Processing terminates.

User response: First determine if the group allocation string, QAMALGRP, in the non-display panel, ICQSIEAM, is valid. Second, you need to be authorized to create data sets with the group prefix, QAMGPREF. If you are not, contact your system programmer for assistance.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM073 Group user data set could not be allocated. Press HELP.

Explanation: The group user data set could not be allocated for the new group identification specified.

System action: Processing terminates.

User response: First determine if the group allocation string, QAMALGRP, in the non-display panel, ICQSIEAM, is valid. Second, you need to be authorized to create data sets with the group prefix, QAMGPREF. If you are not, contact your system programmer for assistance.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM075 Group user master table could not be created. Press HELP.

Explanation: The group administration master table, ICQAGT10, could not be created in the group user library, ICQUGTAB.

System action: Processing terminates.

User response: Contact your system programmer.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM076 Group administration master table could not be saved.

Explanation: The group administration master table, ICQAGT10, could not be saved in the group administration library, ICQAGTAB.

System action: Processing terminates.

User response: Determine if the QAMALGRP group allocation string in the ICQSIEAM non-display panel allows enough space to save the table. If it does not contain enough space, delete the group user and group administration data sets, change the allocation string, and retry the function. Contact your system programmer for assistance.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM077 Group user master table could not be saved. Press HELP.

Explanation: The group user master table, ICQRGT10, could not be saved in the group user library, ICQUGTAB.

System action: Processing terminates.

User response: Determine if the QAMALGRP group allocation string in the ICQSIEAM non-display panel allows enough space to save the table. If it does not contain enough space, delete the group user and group administration data sets, change the allocation string, and retry the function. Contact your system programmer for assistance.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM078 Group user data set does not exist. Press HELP.

Explanation: The system found the specified group administration data set, but did not find the group user data set.

System action: Processing terminates.

User response: Do one of the following:

- Determine the location of the group user data set and name it with the current group prefix as the first qualifier, the specified group name as the next qualifier, and the string ICQRGTAB as the final qualifier (for example, PREFIX.GRPNAME.ICQRGTAB). Then retry your request.
- Delete the specified group administration data set and re-create the group.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM100 Application has dependent applications and cannot be deleted.

Explanation: The application you wanted to delete has another application dependent upon it. For example, an environment cannot be deleted if there is a function that requires it. To find out what applications are dependent, use the 'where used' (W) option.

Module: ICQAMCM0

ICQAM101 The application was not deleted.

Explanation: Because you pressed the END PF key on the delete confirmation panel, the application was not deleted. To delete the application, press ENTER on the delete confirmation panel.

This message is informational only.

Module: ICQAMCM0

ICQAM102 The selected application is not used anywhere.

Explanation: You typed a W next to an application to find out where it is used. The application you selected is not used by any other application.

This message is informational only.

Module: ICQAMCM0

ICQAM105 The application was deleted.

Explanation: The application you chose to delete was deleted.

This message is informational only.

Module: ICQAMCM0

ICQAM106 Use of this application was previously displayed.

Explanation: Information about where this application is used was previously displayed. It will be displayed again when you exit from this process.

This message is informational only.

Module: ICQAMCM0

ICQAM107 Select only one action at a time.

Explanation: Only one action can be selected at a time. Valid actions are:

- A or ADD on the COMMAND line
- M (modify), D (delete), C (copy), or W (where used) in the A column
- PF keys for scrolling
- Entries for subsetting in the Name, Type, and Language fields

Module: ICQAMCM0

ICQAM108 The enqueue table is busy. Try again later.

Explanation: To continue processing, you need exclusive control of the enqueue table. Someone else is using the enqueue table now. Try again later.

Module: ICQAMCM0

ICQAM109 No applications match the search criteria.

Explanation: No applications were found that match the search criteria specified on the panel. Check the spelling or type * for a list. For a partial list, type part of the search criteria followed by an *.

Module: ICQAMCM0

ICQAM110 *user_id* is using the master table. Try again later.

Explanation: To continue processing, you need exclusive control of the master table and exclusive control could not be obtained. Try again later. *user_id* is the user ID of the person who has control of the master table.

Module: ICQAMCM0

ICQAM111 *user_id* is using the update table. Try again later.

Explanation: To continue processing, you need exclusive control of the update table and exclusive control could not be obtained. Try again later. *user_id* is the user ID of the person who has control of the update table.

Module: ICQAMCM0

ICQAM112 Application Manager cannot be used in split screen.

Explanation: You cannot be in split screen when using the Application Manager.

To get out of split screen mode, press the SWAP PF key to display the opposite side of the split, and press the END PF key repeatedly until the screen is no longer split.

Module: ICQAMCM0

ICQAM121 Cannot view unverified application at higher level. Press HELP.

Explanation: You tried to view an unverified application at a higher level than your level of administration. You need to be authorized to view an unverified application at a higher level.

System action: Processing terminates.

User response: Have your system programmer check the QAMUNVW switch in the Application Manager Defaults non-display panel, ICQSIEAM. To give you authorization, the system programmer can change the switch from NO to YES.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM122 Cannot view unavailable application at higher level. Press HELP.

Explanation: You tried to view an unavailable application at a higher level than your level of administration. You need to be authorized to view an unavailable application at a higher level.

System action: Processing terminates.

User response: Have your system programmer check the QAMUNVW switch in the Application Manager Defaults non-display panel, ICQSIEAM. To give you authorization, the system programmer can change the switch from NO to YES.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM123 Cannot copy/export unverified application at higher level. Press HELP.

Explanation: You tried to copy or export an unverified application at a level higher than your level of administration. You need to be authorized to copy or export an unverified application at that level.

System action: Processing terminates.

User response: Have your system programmer check the QAMUNVCE switch in the Application Manager Defaults non-display panel, ICQSIEAM. To give you authorization, the system programmer can change the switch from NO to YES.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM124 Cannot copy/export unavailable application at higher level. Press HELP.

Explanation: You tried to copy or export an unavailable application at a level higher than your level of administration. You need to be authorized to copy or export an unavailable application at that level.

System action: Processing terminates.

User response: Have your system programmer check the QAMUNACE switch in the Application Manager Defaults non-display panel, ICQSIEAM. To give you authorization, the system programmer can change the switch from NO to YES.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM125 Applications may only be deleted at the group level. Press HELP.

Explanation: You tried to delete a system application when processing at the group level of administration.

System action: The system waits for your response.

User response: You are not authorized to delete a system application at the group level of administration.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM126 Applications may only be deleted at the private level. Press HELP.

Explanation: You tried to delete a system or group application when processing at the private level of administration.

System action: The system waits for your response.

User response: You are not authorized to delete a higher-level application at the private level of administration.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM127 Applications may only be modified at the group level. Press HELP.

Explanation: You tried to modify a system application when processing at the group level of administration.

System action: The system waits for your response.

User response: You are not authorized to modify a system application at the group level of administration.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM128 Applications may only be modified at the private level. Press HELP.

Explanation: You tried to modify a system or group application when processing at the private level of administration.

System action: The system waits for your response.

User response: You are not authorized to modify a higher-level application at the private level of administration.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM129 New group libraries allocated.

Explanation: You entered a new group ID to administer.

System action: The system allocates both the administrator and user group libraries and then creates the administrator and user master tables.

User response: None.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM130 Error creating group administration master table. Press HELP.

Explanation: An error occurred while creating the group administration master table.

System action: Processing terminates.

User response: Contact your system programmer.

Programmer response: Contact your IBM support personnel.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM131 Group administration library could not be allocated. Press HELP.

Explanation: The system could not allocate the group administration library because of lack of space, an incorrect allocation, no access authority for the user, or the library is already in use.

System action: Processing terminates.

User response: If the group administration library is in use by another user, try again later. If that does not resolve the problem, contact your system programmer.

Programmer response: You can do one of the following:

- Check the group allocation information in the non-display panel, ICQSIEAM, and allocate more space
- Correct the value of the QAMALGRP string in the non-display panel, ICQSIEAM
- Give access authority to the group administration library

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM132 Group user library could not be allocated. Press HELP.

Explanation: The system could not allocate the group user library because of lack of space, an incorrect allocation, no access authority for the user, or the library is already in use.

System action: Processing terminates.

User response: If the group user library is in use by another user, try again later. If that does not resolve the problem, contact your system programmer.

Programmer response: You can do one of the following:

- Check the user allocation information in the non-display panel, ICQSIEAM, and allocate more space
- Correct the value of the QAMALGRP string in the non-display panel, ICQSIEAM
- Give access authority to the group user library.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM133 Private library could not be allocated. Press HELP.

Explanation: The system could not allocate the private administration library because of lack of space, an incorrect allocation, no access authority for the user, or the library is already in use.

System action: Processing terminates.

User response: If the private administration library is in use by another user, try again later. If that does not resolve the problem, contact your system programmer.

Programmer response: You can do one of the following:

- Check the private allocation information in the non-display panel, ICQSIEAM, and allocate more space
- Correct the value of the QAMAPVTL string in the non-display panel, ICQSIEAM
- Give access authority to the private administration library.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM134 Group ID is required. Press HELP.

Explanation: You must specify a group ID that is not blank.

System action: The system waits for your response.

User response: Type a valid name for the group ID. The name can be up to 8 characters. The first must be A-Z, the remaining can be A-Z, 0-9, \$, #, or @.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM135 Group ID must be a valid name. Press HELP.

Explanation: You typed a group name that is not valid.

System action: The system waits for your response.

User response: Type a valid name for the group ID. The name can be up to 8 characters. The first must be A-Z, the remaining can be A-Z, 0-9, \$, #, or @.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM136 Not able to create valid data set name; check group prefix.

Explanation: The group prefix defined in the non-display panel, ICQSIEAM, is not valid.

System action: Processing terminates.

User response: Contact your system programmer.

Programmer response: Correct the group prefix definition in the non-display panel, ICQSIEAM.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM137 Name/Language/Level not unique for modify. Press HELP.

Explanation: The name and language must be unique when you modify an application, which is defined at your level of administration. Specifying YES in the REPLACE field is not allowed when you are modifying the name or language.

System action: The system waits for your response.

User response: If you want to replace another application with the updates you made, either use the COPY option

ICQAM138 • ICQAM193

on the List of Applications panel or choose a unique name and language combination for your application at your current level of administration.

Module: ICQAMCF0, ICQAMCP0

Audience: Information Center Facility administrator

ICQAM138 New private library created with prefix *prefix_name*.

Explanation: You successfully created a new private library with the prefix name, *prefix_name*. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM190 Application must be a panel. Press HELP.

Explanation: You tried to perform a hierarchy display on an application that was not a panel.

System action: The system waits for your response.

User response: Select a panel application.

Module: ICQAMCS0

Audience: Information Center Facility administrator

ICQAM191 Hierarchy not allowed for unverified applications. Press HELP.

Explanation: You tried to perform a hierarchy display on an unverified application.

System action: The system waits for your response.

User response: Either have your system programmer verify the application for you or verify it yourself.

Module: ICQAMCS0

Audience: Information Center Facility administrator

ICQAM192 Application must be available. Press HELP.

Explanation: You tried to perform a hierarchy display on an unavailable application at a level higher than your level of administration.

System action: The system waits for your response.

User response: Select an available application at your level of administration.

Module: ICQAMCS0

Audience: Information Center Facility administrator

ICQAM193 Panel has no options. Press HELP.

Explanation: The selected panel for the hierarchy display has no options.

System action: The system waits for your response.

User response: Select a panel that has options.

Module: ICQAMCS0

Audience: Information Center Facility administrator

ICQAM194 Hierarchy data set could not be allocated. Press HELP.

Explanation: The data set, which holds the hierarchy display, could not be allocated because of lack of space, no access authority for the user, one or more low-level qualifiers of the data set is not valid, or the record length is not valid.

System action: Processing terminates.

User response: Contact your system programmer.

Programmer response: You can do one of the following:

- Check the group allocation information in the non-display panel, ICQSIEAM, and allocate more space
- Give access authority to the data set that holds the hierarchy display
- Correct the QAMHIER string in the non-display panel, ICQSIEAM
- Correct the QAMHRECL string in the non-display panel, ICQSIEAM. The record length is 1 through 255.

Module: ICQAMCS0

Audience: Information Center Facility administrator

ICQAM195 Hierarchy could not be generated. Press HELP.

Explanation: The hierarchy data set could not be generated because the edit processing failed.

System action: Processing terminates.

User response: Contact your system programmer.

Programmer response: Contact your IBM support personnel.

Module: ICQAMCS0

Audience: Information Center Facility administrator

ICQAM196 Deletion of data set failed. Press HELP.

Explanation: The hierarchy data set could not be deleted because it is in use by another user.

System action: Processing terminates.

User response: Either determine who is using the current data set or try again later.

Module: ICQAMCS0

Audience: Information Center Facility administrator

ICQAM197 Maximum hierarchy nesting level has been reached. Press HELP.

Explanation: The maximum hierarchy nesting level has been reached for the hierarchy display. Some applications in the hierarchy are not displayed.

System action: The system waits for your response.

User response: Create another hierarchy level by specifying the action character H next to the last data set displayed on the previous panel.

Module: ICQAMCS2

Audience: Information Center Facility administrator

ICQAM198 *Applications not shown.

Explanation: The maximum hierarchy nesting level has been reached. Some applications in the hierarchy are not displayed.

System action: The system waits for your response.

User response: Create another hierarchy level by specifying the action character H next to the last data set displayed on the previous panel.

ICQAM199 • ICQAM208

Module: ICQAMCS2

Audience: Information Center Facility administrator

ICQAM199 *Deleted

Explanation: The specified application in the hierarchy display has been deleted and could not be found. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCS2

Audience: Information Center Facility administrator

ICQAM200 CANCEL processed. Panel was not saved.

Explanation: Because you typed CANCEL on the command line, your work was not saved. If you were modifying an existing panel, the modifications were not saved. If you were creating a new panel, the new panel was not saved.

This message is informational only.

Module: ICQAMCP0

ICQAM204 Select option 1 to define the panel name.

Explanation: Every panel must have a name. Choose option 1 to define a panel name.

Module: ICQAMCP0

ICQAM205 Conflicting action characters entered.

Explanation: The characters entered would cause conflicting actions. Read the directions on the panel and try again with different action characters.

Module: ICQAMCP0

ICQAM206 Requested application not found.

Explanation: You entered a locate command, but no match was found. The cursor is positioned on the command line.

Module: ICQAMCP0

ICQAM207 Search argument is not valid.

Explanation: Type a valid search argument. Valid search arguments contain 12 or fewer characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCP0

ICQAM208 Option ID is not valid.

Explanation: Type a valid option ID. Valid option IDs contain 3 or fewer characters. The characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCP0

ICQAM209 Model ISPF Panel name is not valid.

Explanation: The model ISPF panel name you entered is not a valid name.

Module: ICQAMCP0

ICQAM221 The start-up application entered does not exist.

Explanation: The start-up application you entered does not exactly match any previously defined application. Check the spelling or type an * for a list of valid applications. For a partial list, type part of an application name followed by an *.

Module: ICQAMCP0

ICQAM222 The termination application entered does not exist.

Explanation: The termination application you entered does not exactly match any previously defined application. Check the spelling or type an * for a list of valid applications. For a partial list, type part of an application name followed by an *.

Module: ICQAMCP0

ICQAM223 The panel was modified.

Explanation: The panel was saved with the modifications you made.

This message is informational only.

Module: ICQAMCP0

ICQAM224 The panel was copied.

Explanation: The panel was copied as you requested.

This message is informational only.

Module: ICQAMCP0

ICQAM225 The panel was added.

Explanation: The panel was added as you requested.

This message is informational only.

Module: ICQAMCP0

ICQAM226 Option ID is not unique. Choose another.

Explanation: The option ID you entered next to an item in the list is the same as another option ID in the list.

Enter a unique option ID. Option IDs contain 1 to 3 characters. The characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCP0

ICQAM227 Option must have an ID.

Explanation: An option must have an ID before it can be moved. Enter an option ID in the ID field. A valid option ID contains 1 to 3 characters. The characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCP0

ICQAM228 Cannot move item out of selected list.

Explanation: The applications that you selected have option IDs and are at the top of the list of applications. Below them are the deselected applications without option IDs. You cannot move selected options before or after deselected options. You can select an application by typing an option ID next to it.

Module: ICQAMCP0

ICQAM229 Type Y or N in the Primary Panel field.

Explanation: Type Y (yes) or N (no) in the Primary Panel field to indicate whether the panel will be primary.

Module: ICQAME21

ICQAM300 The environment was modified.

Explanation: The changes you made to the environment were saved and the environment was modified.

This message is informational only.

Module: ICQAMCF0

ICQAM301 Select option 1 to enter the required application name.

Explanation: Each application must have a name. Before you continue, select option 1 to enter the application name.

Module: ICQAMCF0

ICQAM302 CANCEL was processed. Environment was not saved.

Explanation: You typed CANCEL on the command line and pressed ENTER or the END PF key. The modifications or additions you made to the environment were not saved.

This message is informational only.

Module: ICQAMCF0

ICQAM303 The environment was added.

Explanation: The information you entered was saved and the environment was added.

This message is informational only.

Module: ICQAMCF0

ICQAM304 Data Set name is not valid.

Explanation: The data set name indicated by the cursor is not valid. To continue processing, type a qualified data set name.

Valid data set names contain one or more qualifiers. Each qualifier contains 8 or fewer characters, the first of which must be alphabetic or special. The other characters for each qualifier can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Valid data set names without quotes can contain no more than 42 characters including the periods that separate one qualifier from another.

Module: ICQAMCF0

ICQAM305 Data Set name cannot be blank if Name specified.

Explanation: When you type a ddname in the Name field, you must also type a data set name in the Data Set field.

Valid data set names contain one or more qualifiers. Each qualifier contains 8 or fewer characters, the first of which must be A-Z or one of the following: \$, #, @. The other characters for each qualifier can be A-Z, 0-9, or the special characters \$, #, @.

Valid data set names contain no more than 44 characters including the periods that separate one qualifier from another.

Module: ICQAME32

ICQAM306 The first Name cannot be blank.

Explanation: The first line on which you enter a data set in the Data Set field, must also contain a ddname in the Name field. Enter a valid ddname.

A valid ddname consists of 1 to 8 characters, the first of which must be A-Z or one of the following: \$, #, @. The remaining characters can be A-Z, 0-9, or the special characters \$, #, @.

Module: ICQAMCF0

ICQAM307 Name is not valid.

Explanation: The ddname indicated by the cursor is not valid. Before you continue, change the name to a valid ddname.

A valid ddname consists of 1 to 8 characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCF0

ICQAM308 Variable Name is not valid.

Explanation: The variable name indicated by the cursor is not valid. Change the name to a valid name.

A valid variable name contains 8 or fewer characters, the first of which must be alphabetic. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAME32

ICQAM309 Select option 1 to define the function name.

Explanation: To define a function name, select option 1. A function name consists of 12 or fewer characters, the first of which must be alphabetic. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCF0

ICQAM310 Name is not unique.

Explanation: The ddname indicated by the cursor is not unique. Before you continue, change the name to a unique ddname.

A ddname consists of 1 to 8 characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCF0

ICQAM311 CANCEL was processed. Function was not saved.

Explanation: You typed CANCEL on the COMMAND line of a previous panel and the function was canceled. The additions or modifications were not saved.

This message is informational only.

Module: ICQAMCF0

ICQAM312 • ICQAM318

ICQAM312 The function was copied.

Explanation: The function that you selected to copy was copied.

This message is informational only.

Module: ICQAMCF0

ICQAM313 Select option 1 to define the environment name.

Explanation: To define an environment name, select option 1. An environment name must consist of 12 or fewer characters, the first of which must be alphabetic. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAMCF0

ICQAM314 The Variable Name is required. Press HELP.

Explanation: If you type information in the Value or Description field, then you must also type a variable name in the Name field.

If you type M to modify a longer value, you must also have a variable name in the Name field.

User response: Type a variable name in the Name field.

Module: ICQAME32

ICQAM315 Number of concatenated data sets exceeds limit.

Explanation: You can have no more than *maximum number* data sets in the concatenation. You have exceeded that limit.

Module: ICQAMCF0

ICQAM316 First keyword not valid. Press HELP for syntax rules.

Explanation: The first keyword in the command indicated by the cursor is not valid. The first keyword must be one of the following:

- PANEL(panel_name)
- CMD(command)
- PGM(program_name)

These are the same keywords used by the ISPF SELECT command. Change the keyword to match one of the above.

Module: ICQAME34

ICQAM317 The environment was copied.

Explanation: The environment that you selected to copy was copied.

This message is informational only.

Module: ICQAMCF0

ICQAM318 The environment entered does not exist.

Explanation: The environment you entered does not exist. Check the spelling or type an * for a list of environments. For a partial list, type part of an environment name followed by an *.

Module: ICQAMCF0

ICQAM319 ISPF Application ID is not valid.

Explanation: The ISPF application ID entered is not valid. A valid ISPF application ID consists of 4 or fewer characters, the first of which must be alphabetic. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAME31, ICQAME39

ICQAM320 The function was modified.

Explanation: The changes you made to the function were saved and the function was modified.

This message is informational only.

Module: ICQAMCF0

ICQAM321 The function was added.

Explanation: The information you entered was saved and the function was added.

This message is informational only.

Module: ICQAMCF0

ICQAM322 More than the maximum of *maximum number* variables were specified.

Explanation: The maximum number of variables is determined by your installation in the variable QAMVMAX. You have exceeded that maximum and must now delete the excess variables, or type CANCEL on the Command line.

User response: Contact your system programmer for assistance.

Module: ICQAMCF0

ICQAM323 END ignored. Press ENTER to modify variable.

Explanation: When you type M in the A column and press END, a command conflict results. To modify the variable, leave M in the A column and press ENTER. To exit the panel, blank out the M and press END.

Module: ICQAMCF0

ICQAM324 Type M in the action field to modify the variable.

Explanation: The variable you tried to modify does not fit on the value line.

To modify a variable with a long value that contains characters of the double-byte character set (DBCS), type M in the action (A) field.

User response: To modify a variable with a long value so that it can include DBCS characters, type M in the action (A) field.

The variable has been reset to its original value.

Module: ICQAME32

ICQAM325 Type is not valid. Use ISPF, CLIST, EXEC, INPUT or OUTPUT.

Explanation: You specified a file type that is not valid.

System action: The system waits for your response.

User response: Type one of the following file types:

- ISPF for ISPF files
- CLIST for CLIST files
- EXEC for REXX execs
- INPUT for any other file type to be used for input
- OUTPUT for any other file type to be used for output

ICQAM326 • ICQAM403

Module: ICQAMCF0

Audience: Information Center Facility administrator

ICQAM326 NAME must have a value when TYPE is specified.

Explanation: You specified a file type, but did not specify a file name.

System action: The system waits for your response.

User response: Specify a file name.

Module: ICQAMCF0

Audience: Information Center Facility administrator

ICQAM327 Name/Language combination exists at a higher level.

Explanation: You created an application and gave it a name or language that already exists. The name/language combination must be unique.

System action: The system waits for your response.

User response: Either copy the name/language combination and give it a different name or specify a unique name/language combination.

Module: ICQAMCF0

Audience: Information Center Facility administrator

ICQAM328 TYPE must have a value when NAME is specified.

Explanation: You specified a file name, but did not specify a file type.

System action: The system waits for your response.

User response: Specify a file type.

Module: ICQAMCF0

Audience: Information Center Facility administrator

ICQAM329 More than one data set was defined to the output file name.

Explanation: When defining libraries for a function application, more than one data set was allocated to the file name or ddname with a file type of OUTPUT.

System action: The system waits for your response.

User response: Concatenate only one data set to the file name with a file type of OUTPUT.

Module: ICQAMCF0

Audience: Information Center Facility administrator

ICQAM400 No entries match the specified information.

Explanation: No entries could be found that match the information you typed. Check the spelling or type an * for a list. For a partial list, type part of the search criteria followed by an *.

Module: ICQAMCL0

ICQAM403 Programming error. Press HELP.

Explanation: A not valid parameter was passed, which resulted in a return code of *return_code*. A list of return codes and their meanings follow.

RC	Cause
12	Table to be searched is not open.
16	Scan failed with return code 16.
20	Severe error in table processing.
24	TBSARG failed. Check the field parameter.
100	Not valid PANEL parameter.
101	Not valid TABLE parameter.
102	Not valid NAMECOND parameter.
103	Not valid LOOKFOR parameter.

Module: ICQAMCLO

ICQAM404 No entries were selected from the list.

Explanation: The panel displayed a list of entries that matched the specified search criteria. You did not select an entry. To select an entry, type S next to it and press ENTER.

This message is informational only.

Module: ICQAMCLO

ICQAM405 Cannot view unavailable higher level application. Press END.

Explanation: You cannot view unavailable applications that are not authorized for your level of administration.

System action: The system waits for your response.

User response: Press the END PF key to view the next application.

Module: ICQAMCV0

Audience: Information Center Facility administrator

ICQAM406 Cannot view unverified higher level application.

Explanation: You cannot view unverified applications that are not authorized for your level of administration.

System action: The system waits for your response.

User response: Select another application to view.

Module: ICQAMCV0

Audience: Information Center Facility administrator

ICQAM410 Positional variable number is not numeric. Execution ended.

Explanation: The number of positional variables in the parameter list passed must be numeric and must be the first variable in the list.

System action: Processing terminates.

Programmer response: Correct the parameter list to start with either the number of positional variables to process or zero to indicate that there are no positional variables. If the variables passed are all keywords, the number of positional variables is zero.

Module: ICQGCR99

Audience: Application Manager programmer

ICQAM411 Missing positional variable name. Execution ended.

Explanation: The number of positional variables processed in the parameter list was not equal to the positional number specified in the first variable of the list passed.

System action: Processing terminates

Programmer response: Correct the list passed to contain the correct number of positional variables that are being passed.

Module: ICQGCR99

Audience: Application Manager programmer

ICQAM412 Enter value for positional parameter *parameter_name*.

Explanation: A value is missing for a positional parameter in the parameter list passed.

System action: The system prompts you for the missing value.

Programmer response: Specify the missing value.

Module: ICQGCR99

Audience: Application Manager programmer

ICQAM413 Keyword *keyword* is not valid. It will be ignored.

Explanation: A keyword specified in the parameter list passed does not correspond to a keyword passed in the template.

System action: None. This message is informational only.

Programmer response: Correct the template or the parameter list passed.

Module: ICQGCR99

Audience: Application Manager programmer

ICQAM421 Member name *member_name_1* was truncated to *member_name_2*.

Explanation: The member name specified in the export control list (list of applications to be exported) was longer than 8 characters and was truncated to a length of 8.

System action: Mass file processing continues.

User response: None. This message is informational only.

Module: ICQAMRME

Audience: Application Manager administrator

ICQAM422 Error - data row missing in *application_name* application table.

Explanation: An application was in the process of being exported, but the data row of the application table was missing.

System action: Processing for the application terminates, but mass file processing continues to the next application.

User response: Check the table or try to export the application manually through the Application Manager dialogs.

Module: ICQAMRM1

Audience: Application Manager administrator

ICQAM423 Error - couldn't find a unique member name for *application_name* in data set:

Explanation: An application was either being exported or copied and a member name, unique in the data set, could not be constructed. The member name is constructed when the original member name (either specified or taken from the application name) is not unique. The construction process truncates the member name to 6 characters and appends a 2-digit number, starting with 01 and incrementing to 99. If a unique name still cannot be found, this message is issued.

System action: Processing for the application terminates, but mass file processing continues to the next application.

User response: Remove or rename the members in the output or backup installation file data set and process the application again. It is suggested that you use empty output and backup data sets.

Module: ICQAMRM1, ICQAMRML

Audience: Application Manager administrator

ICQAM424 Export record number *record_number* ignored; missing required field.

Explanation: A record in the export control list (list of applications to be exported) did not contain all the required fields and was ignored.

System action: Processing continues.

User response: Check the indicated record and make the appropriate corrections. You can export the application by using mass export processing with the corrected record or by using the Application Manager dialogs.

Module: ICQAMRME

Audience: Application Manager administrator

ICQAM425 Member name *member_name* has been copied to the following data set:

Explanation: An application was copied into the specified output data set.

System action: Mass file processing continues.

User response: None. This message is informational only.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM501 Request failed; system error. Press HELP.

Explanation: The ALLOCATE command failed while trying to allocate the temporary data set needed for the edit of the help text.

User response: Contact your system programmer for assistance.

Module: ICQAMCH0

ICQAM502 Request failed; system error. Press HELP.

Explanation: The LMINIT service failed for the temporary edit data set needed for the help text. Contact your system programmer for assistance.

Module: ICQAMCH0

ICQAM503 Request failed; system error. Press HELP.

Explanation: The LMOPEN service failed for the temporary edit data set needed for the help text.

User response: Contact your system programmer for assistance.

Module: ICQAMCH0

ICQAM504 • ICQAM603

ICQAM504 Enter either an ISPTUTOR panel or a tutorial command.

Explanation: You can enter either an ISPTUTOR panel name or a tutorial command on this panel, but not both. You can also leave both of these fields blank.

Module: ICQAMCH0

ICQAM505 The help text is too wide to be saved.

Explanation: The help text you entered is too wide to be saved. Help text must be no wider than 58 characters. To save the help information, adjust the text to fit within 58 columns without scrolling left or right.

User response: To display a line containing column numbers, type col's in the line number field to the left of the text.

Module: ICQAMCH2, ICQAMCH3

ICQAM507 The help text was saved.

Explanation: The help text you entered was saved and will be displayed when a user selects the DESCRIBE option. This message is informational only.

User response: None

Module: ICQAMCH2, ICQAMCH3

ICQAM600 User library is being updated.

Explanation: The user library is in the process of being updated.

This message is appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCU0

ICQAM601 Administrator library is being updated.

Explanation: The administrator library is in the process of being updated.

This message is appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCU0

ICQAM602 User library updates are incomplete.

Explanation: An error occurred that caused processing to end before the updates to the user library were completed.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

ICQAM603 Administrator library updates are incomplete.

Explanation: An error occurred that caused processing to end before the updates to the administrator library were completed.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

ICQAM604 Updates are complete.

Explanation: The updates you made are completed.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCU0

ICQAM605 Updates are restarting.

Explanation: The update process was temporarily stopped but now the updates are restarting.

This message is informational only.

Module: ICQAMCU0

ICQAM608 No new table names can be generated.

Explanation: No new table names are available to create an application table.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

ICQAM609 The table to be replaced is no longer available.

Explanation: The table name you requested to replace does not exist. Message HELP is not available on-line.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

ICQAM610 System user library is being updated.

Explanation: The system level user library is being updated. This message is informational only.

System action: The system copies the processed updates from the system level administrator library to the system level user library.

User response: None.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM611 Group user library is being updated.

Explanation: The group user library is being updated. This message is informational only.

System action: The system copies the processed updates from the group level administrator library to the group level user library.

User response: None.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM613 System administrator library is being updated.

Explanation: The system level administrator library is being updated. This message is informational only.

System action: The system processes the user-initiated updates at the system level and updates the administrator library to reflect the changes.

User response: None.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM614 Group administrator library is being updated.

Explanation: The group level administrator library is being updated. This message is informational only.

System action: The system processes the user-initiated updates at the group level and updates the administrator library to reflect the changes.

User response: None.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM615 Private library is being updated.

Explanation: The private level administrator library is being updated. This message is informational only.

System action: The system processes the user-initiated updates at the private level and updates the administrator library to reflect the changes.

User response: None.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM620 System user library updates are incomplete.

Explanation: Updates to the system user library were interrupted by a severe error during the final phase of processing. Updates to the system user library were not completed. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates with severe error.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM621 Group user library updates are incomplete.

Explanation: Updates to the group user library were interrupted by a severe error during the final phase of processing. Updates to the group user library were not completed. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates with severe error.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM623 System administrator library updates are incomplete.

Explanation: Updates to the system administrator library were interrupted by a severe error during the initial phase of processing. Updates to the system administrator library were not completed. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates with severe error.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM624 Group administrator library updates are incomplete.

Explanation: Updates to the group administrator library were interrupted by a severe error during the initial phase of processing. Updates to the group administrator library were not completed. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates with severe error.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM625 Private library updates are incomplete.

Explanation: Updates to the private library were interrupted by a severe error during the initial phase of processing. Updates to the private library were not completed. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates with severe error.

User response: Contact your system programmer for assistance.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM630 Invoking panel *panel_name* does not exist.

Explanation: The specified invoking panel, *panel_name*, was not found in the master table at your level of administration.

System action: Processing continues.

User response: Edit the installation file and check the spelling of the invoking panel name and language. If name and language are correct, add the panel application. If the name and language are not correct, correct the spelling and try again, or modify it directly through Application Manager dialogs.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM631 *Selection_id* not a unique selection ID on panel *panel_name*.

Explanation: The specified ID on the *INVOKING_PANEL entry in the installation file has already been used as a selection ID on the panel, *panel_name*.

System action: Processing continues.

User response: Edit the installation file and change the selection ID specified on the *INVOKING_PANEL entry with the panel, *panel_name*, and install the application again or modify the panel, *panel_name*, directly through Application Manager dialogs.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM633 Application *name* or *language* is not an option on panel *panel_name*.

Explanation: The name or language combination specified on the *AFTER entry in the installation file is not an option on the invoking panel specified in *panel_name*.

System action: Processing continues.

User response: Edit the installation file and check the spelling of the name and language on the *AFTER entry corresponding to the *INVOKING_PANEL entry with the name, *panel_name*. If the spelling is incorrect, correct it and install the file again or modify the invoking panel directly through Application Manager dialogs.

ICQAM636 • ICQAM700

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM636 Invoking panel *panel_name* has been updated.

Explanation: The invoking panel with the name of *panel_name* has been updated successfully. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM637 Update of invoking panel *panel_name* was not successful.

Explanation: The invoking panel with the name *panel_name* was not updated successfully.

System action: Processing continues.

User response: Determine, from the information given in messages preceding this message, why the update failed and correct the situation by updating the invoking panel directly through Application Manager dialogs.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM638 Application *application_name* is not unique.

Explanation: The specified application name has already been added as a selection on the invoking panel. The installation file has a duplicate *INVOKING_PANEL entry.

System action: Processing continues.

User response: Either specify a different application name as a selection on the invoking panel or type CANCEL to exit.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM639 Panel *panel_name* cannot have itself as a selection.

Explanation: The panel application you are installing is also specified as an *INVOKING_PANEL entry.

System action: Processing continues.

User response: Specify another panel application.

Module: ICQAMCU0

Audience: Information Center Facility administrator

ICQAM700 The pre-initialization exit routine failed.

Explanation: The routine written by your installation for the pre-initialization exit function failed and issued a return code greater than 0.

User response: Contact your system programmer for assistance.

Module: ICQAMLD1

ICQAM701 The application initialization routine failed.

Explanation: The routine for the initialization of the application failed.

User response: Contact your Information Center Facility administrator or a system programmer for assistance.

Module: ICQAMLD2

ICQAM702 The application that was invoked failed.

Explanation: The application you selected was invoked, but it failed and issued a non-zero return code.

User response: Contact your Information Center Facility administrator or a system programmer for assistance.

Module: ICQAMLD2

ICQAM703 The application is not available.

Explanation: The application you requested is not available to users at this time.

User response: Contact your Information Center Facility administrator for assistance.

Module: ICQAMLD2, ICQAMLI0

ICQAM704 Application was not previously defined.

Explanation: The application you requested was not previously defined and could not be found.

User response: Contact your Information Center Facility administrator for assistance.

Module: ICQAMLI0

ICQAM705 No tutorial exists for this application.

Explanation: There is no tutorial for the application specified.

User response: Contact your Information Center Facility administrator for assistance.

Module: ICQAMLD2, ICQAMLI0

ICQAM706 Severe error. Reason code *reason_code*. Press HELP.

Explanation: A severe error occurred that resulted in a reason code of *reason_code*. A list of reason codes and their meanings follow:

RSN	Cause
100	PARSE error.
104	Multiple specification error-- two or more of APPLNAME, KEYWORD, or TABLE, which are mutually exclusive, were specified.
108	PARM value is too long.
110	PQUERY failed.
130	Information needed to invoke the application was not found. (DATA row missing.)
134	Incorrect application type. Application must be a panel or a function.
138	Invocation command has not been defined.
140	Too many variables are defined to the function and environment (if one exists).
142	ISPF SELECT command failed. Error message follows: <i>error_message</i>
144	The value of NEXTOPT will not fit in the invocation command.
146	The value of PARM will not fit in the invocation command.
148	Too many data sets are defined for a function library.

ICQAM707 • ICQAM713

RSN	Cause
150	The LIBDEF service failed while allocating the libraries for the application.
152	The ALTLIB command failed while allocating the libraries for the application.
199	The routine that searches for keywords failed.

Module: ICQAMLI0

ICQAM707 Environment for this function or tutorial is unavailable.

Explanation: The environment for the function or tutorial you requested is not available.

User response: Contact your Information Center Facility administrator for assistance.

Module: ICQAMLI0

ICQAM708 The application returned a return code of *return_code*.

Explanation: The application you selected was invoked, but it issued a non-zero return code of *return_code*.

A non-zero return code might be normal.

User response: If you feel this is an error, contact your Information Center Facility administrator.

Module: ICQAMLD2

ICQAM710 Invocation of application *application_name* failed.

Explanation: The application that you were trying to invoke has failed. This message and the name or keyword of the failing application is logged in the user's ISPF log data set.

This is one of a series of messages that provide information about the failing application.

Module: ICQAMLER

ICQAM711 Invoking module was *module_name* at *error_location*.

Explanation: The invocation of the application failed. This message and the name of the calling module and the id point within that module are logged in the user's ISPF log data set.

This is one of a series of messages that provide information about the failing application.

Module: ICQAMLER

ICQAM712 Error message follows.

Explanation: This message appears in the user's ISPF log data set and precedes error message text.

This is one of a series of messages that provide information about the failing application.

Module: ICQAMLER

ICQAM713 Application invocation failed. Table name *table_name*.

Explanation: The invocation of an application failed and the application name and keyword are unknown. The application is identified by its table name because neither application name nor keyword are known.

This information is logged in the user's ISPF log data set and is one of a series of messages that provides information about the failing application.

Module: ICQAMLER

ICQAM714 Severe error while invoking exit. Press HELP.

Explanation: A severe error with a return code of 12 occurred while invoking exit *exit_name*. The resulting ABEND code is *abend_code_number* with a reason code of *reason_code_number*.

Module: ICQAMLD1, ICQAMLF0

ICQAM715 Severe error in exit. Press HELP.

Explanation: A severe error with a return code of 16 occurred in exit *exit_name*. The resulting ABEND code is *abend_code_number* with a reason code of *reason_code_number*.

Module: ICQAMLD1, ICQAMLF0

ICQAM716 Severe error invoking exit. Press HELP.

Explanation: A severe error with a return code of 20 was detected in exit *exit_name*. The resulting reason code is *reason_code_number*.

Module: ICQAMLD1, ICQAMLF0

ICQAM717 Exit requested termination. Press HELP.

Explanation: Exit *exit_name* requested to terminate with a return code of 12. The resulting reason code is *reason_code_number*.

Module: ICQAMLD1, ICQAMLF0

ICQAM720 No HELP information is available.

Explanation: HELP information for the panel is not available.

User response: Contact your Information Center Facility administrator for assistance.

Module: ICQAMLD2

ICQAM721 Duplicate keyword. Use selection ID to select.

Explanation: The keyword you typed on the Command line to select an option is not unique. Use the selection ID next to the keyword to select the option.

Module: ICQAMLD2

ICQAM730 Mass installation file processing has begun.

Explanation: Mass file processing has started.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM731 Mass installation file processing has ended.

Explanation: Mass file processing has ended.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM732 • ICQAM738

ICQAM732 Backup files will reside in data set:

Explanation: You requested backup (BACKUP=Y). The back up files will reside in the data set allocated to the backup library, ICQBACK.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM733 Output installation files will reside in data set:

Explanation: The output installation files will reside in the data set allocated to the output library, ICQOUT.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM734 Severe error - mass processing terminated.

Explanation: Mass file processing has ended with a severe error.

System action: Processing terminates.

User response: Check the messages issued before this message for an indication of what happened. These messages might also explain what you need to do to correct the error.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM735 Severe error - output library *library_name* is not allocated.

Explanation: The output installation library was not allocated before the execution of the mass file processing function.

System action: Processing terminates.

User response: Allocate the output installation library and re-execute the mass file processing function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM737 Severe error - the following output data set is not partitioned:

Explanation: The output installation data set was not allocated as a partitioned data set.

System action: Processing terminates.

User response: Allocate the data set as a partitioned data set.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM738 Severe error - backup library *library_name* is not allocated.

Explanation: You requested backup (BACKUP=Y), but the backup library was not allocated before the execution of the mass file processing function.

System action: Processing terminates.

User response: Allocate the backup library and re-execute the mass file processing function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM739 Severe error - the following backup data set is not partitioned:

Explanation: You requested backup (BACKUP=YES), but the allocated backup data set was not a partitioned data set.

System action: Processing terminates.

User response: Allocate the data set as a partitioned data set.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM740 Severe error - the following upgrade data set is not partitioned:

Explanation: The allocated upgrade data set was not a partitioned data set.

System action: Processing terminates.

User response: Allocate the data set as a partitioned data set.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM741 Severe error - export library ICQEXPT is not allocated.

Explanation: The mass export library, ICQEXPT, was not allocated before the execution of the mass export function.

System action: Processing terminates.

User response: Allocate the mass export library and re-execute the mass export function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM742 Severe error - following export control data set is not sequential:

Explanation: The allocated export control data set was not a sequential data set.

System action: Processing terminates.

User response: Allocate the data set as a sequential data set.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM743 Severe error - administrator library *library_name* is not allocated.

Explanation: The system administrator library specified in *library_name* was not allocated before the execution of the mass file processing function. ICQAMTAB is the default.

System action: Processing terminates.

User response: Allocate the system administrator data set to ICQAMTAB and re-execute the mass file processing function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM744 • ICQAM749

ICQAM744 Severe error - administrator library ICQXATAB is not allocated.

Explanation: The administrator library, ICQXATAB, was not allocated before the execution of the mass file processing function.

System action: Processing terminates.

User response: Allocate the administrator data set to ICQXATAB and re-execute the mass file processing function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM745 Severe error - user library ICQXUTAB is not allocated.

Explanation: The user library, ICQXUTAB, was not allocated before the execution of the mass file processing function.

System action: Processing terminates.

User response: Allocate the user data set to ICQXUTAB and re-execute the mass file processing function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM746 Severe error - libraries *administrator_library* & *user_library* are not the same level.

Explanation: The administrator and user libraries allocated to ICQXATAB and ICQXUTAB are not at the same administration level (system, group, or private).

System action: Processing terminates.

User response: Allocate the matching administrator and user libraries to ICQXATAB and ICQXUTAB, respectively, and re-execute the mass file processing function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM747 Severe error - unable to gain exclusive access to *administrator_library_name*.

Explanation: The administrator library is in use by another user and is not available.

System action: Processing terminates.

User response: Try again later or ask that user to stop using the library.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM748 Severe error - *user_id* is using the update table. Try again later.

Explanation: The update table is in use by another user and is not available.

System action: Processing terminates.

User response: Try again later or ask that user to stop using the update table.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM749 Severe error - *user_id* is using the master table. Try again later.

Explanation: The master table is in use by another user and is not available.

System action: Processing terminates.

User response: Try again later or ask that user to stop using the master table.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM750 Severe error - no master table exists in ICQXATAB.

Explanation: A system, group, or private master table does not exist in the administrator library, ICQXATAB.

System action: Processing terminates.

User response: Check that the administrator library, ICQXATAB, is allocated to a valid administrator tables data set, which contains the appropriate master table.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM751 Severe error - working master *table_name* does not exist in ICQXATAB.

Explanation: A system, group, or private working master table does not exist in the administrator library, ICQXATAB.

System action: Processing terminates.

User response: Create a working master table with the same administrator tables data set using the Application Manager dialogs.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM752 Severe error - lookup table ICQAMT80 does not exist in *library_name*.

Explanation: A system lookup table does not exist in the administrator library specified in the *library_name*. ICQAMTAB is the default.

System action: Processing terminates.

User response: Locate a backup copy of the lookup table or use a copy from a different system administrator library.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM753 *data_set_name*

Explanation: Indicates the name of the data set to which the immediately preceding message is referring.

System action: Processing continues or terminates based on the preceding message.

User response: Determine from the preceding message what needs to be done.

Module: ICQAMRMP, ICQAMRML, ICQAMRM1, ICQAMRME

Audience: Application Manager administrator

ICQAM754 Severe error - parameter *keyword* value *value* is not valid.

Explanation: The keyword and value specified for a parameter in the invocation of the cataloged JCL procedure, ICQMIFP, is not valid.

System action: Processing terminates.

User response: Replace the incorrect value with a valid value and re-execute the JCL.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM755 • ICQAM760

ICQAM755 Severe error - one or more parameters are blank.

Explanation: One or more parameter keyword values were specified as blanks in the invocation of the cataloged JCL procedure, ICQMIFP.

System action: Processing terminates.

User response: Specify correct value(s) and re-execute the JCL.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM756 Severe error - table service error action on table_name table value.

Explanation: A severe error was encountered while processing table services.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the message for the specific action and contact your system programmer.

Programmer response: Check the return codes from the specific action against the table. Return codes are described in *z/OS ISPF Services Guide*.

Module: ICQAMRMP, ICQAMRML, ICQAMRME

Audience: Application Manager administrator

ICQAM757 Severe error - following installation data set is not partitioned:

Explanation: The installation data set was not allocated as a partitioned data set.

System action: Processing terminates.

User response: Allocate the data set as a partitioned data set.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM759 Severe error - interrupted updates exist.

Explanation: The update table contained an update control row indicating that an interrupted update exists.

System action: Processing terminates.

User response: Re-enter Application Manager to process the interrupted update and then re-execute the mass file processing function.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM760 Mass export processing has begun.

Explanation: You requested mass export (MODE=EXP) and the mass export process has begun.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRME

Audience: Application Manager administrator

ICQAM761 Severe error - following export control data set couldn't be accessed:

Explanation: The export control data set is read in total using the EXECIO command. A severe error was encountered when reading the file.

System action: Processing terminates.

User response: Check the export control data set or the allocation to the export library, ICQEXPT. The export library data set must be a sequential data set that contains data and you must have the appropriate access authority to that data set.

Module: ICQAMRME

Audience: Application Manager administrator

ICQAM762 Severe error - the following export control data set is empty:

Explanation: The export control data set contained no data.

System action: Processing terminates.

User response: Check the export control data set allocated to the export library, ICQEXPT, and add the required data.

Module: ICQAMRMP

Audience: Application Manager administrator

ICQAM763 Mass export ended successfully.

Explanation: You requested mass export (MODE=EXP) and the mass export process has completed successfully.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRME

Audience: Application Manager administrator

ICQAM764 Severe error - mass export ended with a severe error.

Explanation: You requested mass export (MODE=EXP) and the mass export process has completed with a severe error.

System action: Processing terminates.

User response: Check the messages issued before this message to determine the cause of the error. These messages explain what you need to do to correct the error.

Module: ICQAMRME

Audience: Application Manager administrator

ICQAM765 Error - mass export ended with at least 1 file not processed.

Explanation: You requested mass export (MODE=EXP) and the mass export process has completed with at least one file not successfully processed.

System action: Processing continues.

User response: Check the messages issued before this message to determine why one or more applications were not processed.

Module: ICQAMRME

Audience: Application Manager administrator

ICQAM766 • ICQAM770

ICQAM766 Error - *application_name* does not exist in the master table *table_name*.

Explanation: The application you requested to export does not exist in the master table, *library_name*. The master table is contained in the administrator tables data set that is allocated to the ICQXATAB library.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check either the application contained in the export control data set or the upgrade file, or verify that the appropriate tables data set is allocated to ICQXATAB, the administrator library.

Module: ICQAMRM1

Audience: Application Manager administrator

ICQAM767 Error - *application_name* table names could not be resolved.

Explanation: The application is being exported and the table names within the specified application could not be resolved to their proper names.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Review the messages issued before this message. If you cannot resolve the names, contact your system programmer.

Programmer response: Check the resolve table names subroutine to isolate the problem.

Module: ICQAMRM1

Audience: Application Manager administrator

ICQAM768 *application_name* was successfully exported to:

Explanation: The application was successfully exported. The application name and language are identified and the target data set and member are identified.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRM1

Audience: Application Manager administrator

ICQAM769 Error - *application_name* could not be exported.

Explanation: The application was being exported and encountered an error. The export could not be performed.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the messages issued before this message to determine why that application could not be exported.

Module: ICQAMRM1

Audience: Application Manager administrator

ICQAM770 Begin processing mass upgrade and load.

Explanation: You requested mass install (MODE=INST) and the mass upgrade and load process has begun.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM771 Processing INSTALL|UPGRADE data set:

Explanation: You requested mass install (MODE=INST). The data set allocated to the install library, ICQINST, or the associated data set for the upgrade library, ICQUPGR (if allocated), is identified.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM772 Error - action on table_name table value failed.

Explanation: A severe error in table services has occurred.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the message for the specific action and contact your system programmer.

Programmer response: Check the return codes from the specific action against the table. Return codes are described in *z/OS ISPF Services Guide*.

Module: ICQAMRM1

Audience: Application Manager administrator

ICQAM773 Mass upgrade and load completed successfully.

Explanation: You requested mass install (MODE=INST) and the mass upgrade and load process has completed successfully.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM774 Error - mass upgrade and load completed - error exception(s) noted.

Explanation: You requested mass install (MODE=INST) and the mass upgrade and load process has completed with at least one file not processed successfully.

System action: Processing continues.

User response: Check the messages issued before this message to determine which applications failed and the reasons for the failure.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM775 Severe error - mass upgrade and load incomplete.

Explanation: You requested mass install (MODE=INST) and the mass upgrade and load process has ended with a severe error.

System action: Processing terminates.

User response: Check the messages issued before this message to determine the reason for the failure.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM776 Severe error - error copying file *file_name* to output library.

Explanation: You requested mass install (MODE=INST) and the mass upgrade and load process encountered a severe error while using LMCOPY to copy a member from the installation file data set to the output file data set.

System action: Processing terminates.

User response: Check the output file data set allocated to the output library, ICQOUT, for space problems in the partitioned data set or in the directory.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM777 Error - format of *file_name* file *member_name* is not valid; file skipped.

Explanation: An installation file or upgrade file did not contain the full application identification information (name, language, and type).

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the specified installation or upgrade member and make appropriate changes. Then, either process through mass upgrade and load; or manually upgrade and install the application using the Application Manager dialogs.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM778 Severe error - *name* is not found in the system master tables.

Explanation: The specified Application Manager name and language combination (AMNAME and AMLANG) does not exist in the system master table. The default library is ICQAMTAB.

System action: Processing terminates.

User response: Check the specified application name and language and verify the allocation to the system administrator library, ICQAMTAB.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM779 Initiate creation of backup using the export function.

Explanation: You requested backup (BACKUP=Y) and the upgrade and load process has begun to create the installation file in the backup library by using the export function.

System action: Processing continues.

User response: None. This is an informational message only. Refer to messages issued before this message to identify the name of the application being backed up.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM780 Backup successfully created.

Explanation: You requested mass install (MODE=INST) and the mass upgrade and load process has successfully exported the application to the backup library.

System action: Processing continues.

User response: None. This message is informational only. Refer to messages issued before this message to identify the name of the application being backed up.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM781 Severe error - backup could not be created - processing terminates.

Explanation: You requested backup (BACKUP=Y) and the back up of an application was being processed by mass upgrade and load using the export function. The application could not be backed up.

System action: Processing terminates

User response: Check the messages issued before this message to determine the specific reason for the failed operation.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM782 Install initiated for file *member_name*, application *application_name*.

Explanation: You requested mass install (MODE=INST) and the mass upgrade and load process has started to load the specified application contained in the installation file *member_name*.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM783 Error - installation failed.

Explanation: An application could not be successfully loaded.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the messages issued before this message to determine the specific reason for the failed operation and to identify the name of the application.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM784 Installation completed successfully.

Explanation: The application was successfully loaded, verified, and made available.

System action: Processing continues.

User response: None. This message is informational only. Refer to messages issued before this message to identify the name of the application loaded.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM785 Upgrade of *installation_member_name* application *application_name* using *upgrade_member_name* begun.

Explanation: The upgrade of the installation file has started for the specified application using the upgrade file member.

System action: Processing continues.

User response: None. This message is informational only.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM786 No upgrade or installation files to process.

Explanation: One of the following occurred:

- There were no upgrade or installation file members to process
- Upgrade or installation members could not be identified.

System action: Processing continues.

User response: Refer to messages issued before this message to identify names of upgrade or installation members.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM787 Severe error - error accessing *file_name* file.

Explanation: A severe error was encountered when the specified file was accessed using library management (LM) services.

System action: Processing terminates.

User response: Check the messages issued before this message to determine the specific reason for the failed operation. If you cannot resolve the problem, contact your system programmer.

Programmer response: Check the return codes from the LM service that caused the error. Return codes are described in *z/OS ISPF Services Guide*.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM788 Error - upgrade failed - installation will not be attempted.

Explanation: The upgrade of an application failed and processing for the application ends.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the messages issued before this message to determine the specific reason for the failed operation and to identify the name of the application.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM789 Upgrade completed successfully.

Explanation: The application was successfully upgraded.

System action: Processing continues.

User response: None. This message is informational only. Refer to messages issued before this message to identify the name of the application that was upgraded.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM790 Error - export failed - upgrade/install not done for file *member_name*.

Explanation: The export of an application failed and processing for the application ends.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the messages issued before this message to determine the specific reason for the failed operation and to identify the name of the application.

Module: ICQAMRML

Audience: Application Manager administrator

ICQAM791 Error - bad *entry_name* command - CMD(, PGM(, or PANEL(expected.

Explanation: A syntax error for an installation-file entry (invocation, init, term, or tutorial) was detected in an installation file during the loading of a function application.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the messages issued before this message to identify the name of the application and the member name of the installation file in the output library. Examine the installation file for errors.

Module: ICQAMCF0

Audience: Application Manager administrator

ICQAM792 Error - option selection IDs are not valid - duplicates exist.

Explanation: Duplicate selection IDs were detected in an installation file during the loading of a panel application.

System action: Processing for the application terminates, but mass processing continues to the next application.

User response: Check the messages issued before this message to identify the name of the application and the member name of the installation file in the output library. Examine the installation file for errors.

Module: ICQAMCP0

Audience: Application Manager administrator

ICQAM793 Severe error - data not saved; not enough PDS or directory space in:

Explanation: A space error was detected in the specified partitioned data set.

System action: Processing terminates.

User response: Check the space allocated to the specified data set and re-allocate it with more space or with more directories. Also check the messages issued before this message to determine where processing ended so that, if you want to restart, you can process any applications that were not processed.

Module: ICQAMRML, ICQAMRM1

Audience: Application Manager administrator

ICQAM794 Severe error - the following data set could not be saved:

Explanation: A severe error was encountered when attempting to save a member in the specified data set.

System action: Processing terminates.

User response: Check the allocation for the specified data set. Space problems would have been detected previously. Note that you need to have appropriate access authority to the data set.

Module: ICQAMRML, ICQAMRM1

Audience: Application Manager administrator

ICQAM800 Project is not valid.

Explanation: The word in the Project field is not valid. Type a valid project name.

Valid project names contain 1-8 characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

Module: ICQAME80

ICQAM801 File Name is not valid.

Explanation: The word in the File Name field is not valid. Type a valid file name.

Valid file names contain 1-8 characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

ICQAM802 • ICQAM808

To request a list of valid file names, type a valid first character or group of characters followed by an *.

Module: ICQAME80

ICQAM802 File Type is not valid.

Explanation: The word in the File Type field is not valid. Type a valid file type.

Valid file types contain 1-8 characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

To request a list of valid file types, type a valid first character or group of characters followed by an *.

Module: ICQAME80

ICQAM803 Member is not valid.

Explanation: The word in the Member field is not valid. Type a valid member name.

Valid member names contain 1-8 characters, the first of which must be alphabetic or special. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or special (\$,#,@) characters.

To request a list of valid members, type a valid first character or group of characters followed by an *.

Module: ICQAME80

ICQAM804 * is only valid as the last character in a name.

Explanation: An * cannot be part of a data set name or member name. It can only be used to obtain a list of names, either by being the only character in the field or at the end of a group of characters.

- To get an entire list, type an * as a single character.
- To get a list of names beginning with specific characters, type the specific characters followed by an *.

Module: ICQAME80

ICQAM805 Data set name is not valid. Correct and press ENTER.

Explanation: The data set name in the Other data set field is not valid. Check the spelling or type another name.

An * cannot be used in the Other data set field to get a list.

Module: ICQAME80

ICQAM806 The specified data set was not found.

Explanation: The data set you specified does not exist. Check the spelling or type another name.

For a list of data sets, type an * in the appropriate Data set field. For a partial list, type part of a File Name or File Type followed by an *.

Module: ICQAMCI0, ICQASRP3, ICQASRT1

ICQAM807 No data sets match the information specified.

Explanation: No data sets exist that match the information you specified. Check the spelling or type another name.

Module: ICQAMCI0, ICQASRP3

ICQAM808 Selected data set is sequential; cannot have members.

Explanation: The data set you selected from the list is a sequential data set and sequential data sets do not have members. Therefore you cannot specify a member name in the Member field.

Module: ICQAMCI0

ICQAM809 The data set is partitioned; specify a member or *.

Explanation: The data set you selected from the list is a partitioned data set with members. Either specify a member name or type an * for a list of members.

Module: ICQAMCI0

ICQAM810 The specified member was not found.

Explanation: The member name you specified does not exist. Check the spelling, or request a list of members. You can request a list in one of two ways:

- Type * in the Member field.
- Type the data set name with no member name in the Other data set field.

Module: ICQAMCI0, ICQASRT1

ICQAM811 The data set is neither partitioned nor sequential.

Explanation: The organization of the data set you specified is neither (PO) partitioned nor (PS) sequential. Only PO or PS data sets are allowed.

Module: ICQAMCI0, ICQASRT1

ICQAM812 The data set is sequential; do not specify a member.

Explanation: The data set you specified is a sequential data set and sequential data sets have no members. To continue processing, blank out the member.

Module: ICQAMCI0, ICQASRT1

ICQAM813 The data set is sequential and cannot have members.

Explanation: The data set you specified is a sequential data set and sequential data sets have no members to list. To continue processing, blank out the member name.

Module: ICQAMCI0, ICQASRT1

ICQAM814 Type one of the listed values at the cursor position.

Explanation: The possible values for the field indicated by the cursor are listed on the panel. Type one of those listed values in the field. No other value is accepted.

Module: ICQAME80

ICQAM815 A member list is not available. Press HELP.

Explanation: Because of a system error, a member list is not available for the data set you specified. LMINIT issued a return code of *return_code*. A list of possible return codes are:

RC	Cause
8	Data set not allocated.
12	Not valid parameter value.
16	Truncation or translation error in accessing dialog variables.
20	Severe error; unable to continue.

The reasons for this are:

- *ISPF_short_error_message*
- *ISPF_long_error_message*

Module: ICQAMCI0, ICQASRT1

ICQAM816 The specified data set has no members.

Explanation: The data set you specified does not have any members so a list of members is not available. To create a member:

- Specify a member name.
- Type Y in the Edit Data field.
- Create an installation file in the member.

Module: ICQAMCI0, ICQASRT1

ICQAM817 Request failed; system error. Press HELP.

Explanation: Your request for a list of members failed because the LMMLIST service issued a return code of *return_code*. A list of possible return codes and their meanings are:

RC	Cause
16	Truncation or translation error in accessing dialog variables.
20	Severe error; unable to continue.

User response: Contact your system programmer for assistance.

Module: ICQAMCI0, ICQASRT1

ICQAM818 No members match the information specified.

Explanation: The specified data set has no members that match the search criteria. Check the spelling or type different search criteria.

Module: ICQAMCI0, ICQASRT1

ICQAM820 A data set list is not available; system error.

Explanation: A list of data sets is not available because ICQGCCC00 issued a return code of 16, indicating a severe error.

User response: Contact your system programmer for assistance.

Module: ICQAMCI0, ICQASRP3

ICQAM821 A member list is not available; system error.

Explanation: A list of members from the specified data set is not available because the LMOPEN service issued a return code of *return_code*. A list of possible return codes and their meanings follow:

RC	Cause
8	Data set cannot be opened.
16	Truncation or translation error in accessing dialog variables.
20	Severe error; unable to continue.

User response: Contact your system programmer for assistance.

Module: ICQAMCI0, ICQASRT1

ICQAM822 Unexpected data found on record *record_number*. Data ignored.

Explanation: Extraneous information was found on a record in the installation file. Certain installation file records require that the record header be on one line and the data on the following line. When data appears on the same line as the header, it is ignored, which causes an error later.

User response: If you need assistance, contact your system programmer, or see *z/OS TSO/E Customization*.

This message is written to the ISPF log data set and is displayed in line mode. No on-line HELP is available.

Module: ICQAMCI2

ICQAM823 Installation file is empty.

Explanation: The data set to be loaded as an installation file is empty and contains no records.

For information about the records that go into an installation file, see *z/OS TSO/E Customization*.

Module: ICQAMCI2

ICQAM824 Installation file is incomplete.

Explanation: The specified data set to be loaded as an installation file does not contain enough data. The file must contain:

1. An *APPLICATION MANAGER INSTALLATION FILE record
2. A *SYSTEM MVS TSO/E record
3. A *PANEL, *FUNCTION, or *ENVIRONMENT record

For more information about installation files, see *z/OS TSO/E Customization*.

Module: ICQAMCI2

ICQAM825 File specified is missing first installation record.

Explanation: The data set to be loaded as an installation file must contain the following as its first record that is not a comment:

- *APPLICATION MANAGER INSTALLATION FILE

For more information about installation files, see *z/OS TSO/E Customization*.

Module: ICQAMCI2

ICQAM826 *SYSTEM must be second record in the file.

Explanation: The data set to be loaded as an installation file must contain the following as its second record that is not a comment:

- *SYSTEM MVS TSO/E

For more information about installation files, see *z/OS TSO/E Customization*.

Module: ICQAMCI2

ICQAM827 *SYSTEM record is incorrect.

Explanation: The data set to be loaded as an installation file must contain the following as its second record that is not a comment:

- *SYSTEM MVS TSO/E

*SYSTEM must be in columns 1-7 and the 12 characters "MVS TSO/E" must be within columns 9-72.

For more information about installation files, see *z/OS TSO/E Customization*.

Module: ICQAMCI2

ICQAM828 Record 3 must contain the application type.

Explanation: The data set to be loaded as an installation file must contain one of the following as its third record that is not a comment:

- *PANEL, *FUNCTION, or *ENVIRONMENT

ICQAM831 • ICQAM836

For more information about installation files, see *z/OS TSO/E Customization*.

Module: ICQAMCI2

ICQAM831 Expected a record header on *record_number*. Record ignored.

Explanation: The specified record does not begin with an *. All record headers in an installation file must begin with an * in column 1. If the line is a continuation of a previous record, it must have a blank in column 1.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM832 *log data*

Explanation: This message contains the data that appears in the ISPF log data set and displays it in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM833 Record type on record *record_number* not recognized. Record ignored.

Explanation: The specified record is not a valid type. For information on the types of records that go into an installation file, see *z/OS TSO/E Customization*.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM834 Information found beyond column 72 on record *record_number* and ignored.

Explanation: The specified record contains text after column 72. No characters are allowed after column 72.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM835 Extra tutorial found on record *record_number*; **record_type* ignored.

Explanation: The installation file specified more than one tutorial record for the function. Tutorial records headers are:

- *ISPTUTOR_PANEL
- *TUTORIAL_COMMAND

The first tutorial record is accepted, even when it is blank. The tutorial record(s) following it are ignored.

This message appears in the ISPF log data set and is displayed in line mode. No on-line HELP is available.

Module: ICQAMCI2

ICQAM836 Unable to edit the requested data. Press HELP.

Explanation: Edit services are not available for the requested data. ISPF issued a return code of either 14 or 20 with the following reasons:

- *ISPF_short_error_message*
- *ISPF_long_error_message*

User response: Contact your system programmer for assistance.

Module: ICQAMCI2

ICQAM837 Unable to load the requested data. Press HELP.

Explanation: The requested data was not loaded and ISPF issued a return code of either 14 or 20 with the following reasons:

- *ISPF_short_error_message*
- *ISPF_long_error_message*

User response: Contact your system programmer for assistance.

Module: ICQAMCI2

ICQAM838 Data for *record_type on record record_number truncated to length record_length.

Explanation: The specified record exceeded the maximum length allowed and was truncated to the maximum allowable length.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM839 Duplicate option on record record_number. *OPTION is ignored.

Explanation: An option function in the installation file is not unique. The *OPTION record containing that function is ignored.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM840 Select a member and press ENTER. To exit, press END.

Explanation: You pressed ENTER on the member selection list panel without making a selection.

System action: The system waits for your response.

User response: Select a member by typing S next to the member and press ENTER. To cancel out of the selection list, press END.

Module: ICQAMRY0, ICQASRP1

Audience: Information Center Facility administrator

ICQAM841 Select only one action at a time.

Explanation: You can select only one member at a time and only one action at a time. For example, if you type an action character next to a member to select it, you cannot press the DOWN PF key to scroll through the member list.

Module: ICQAMCI0

ICQAM842 The installation data was saved.

Explanation: The installation data you were modifying is saved. Typically after making modifications, you press the ENTER key. This time you pressed the END PF key, which sometimes cancels data; however, the data was saved.

This message is informational only.

Module: ICQAMCI0

ICQAM843 Selected data set is partitioned, specify a member or *.

Explanation: The data set you selected is partitioned and contains members. If what you have specified in the Member field is correct, press ENTER. Otherwise, specify a new member or type an * to see a list of members from which to select.

Module: ICQAMCI0

ICQAM844 • ICQAM850

ICQAM844 Missing ddname on record *record_number*. Using ???????? as the ddname.

Explanation: The installation file did not have a ddname on the *LIBRARY record. ???????? was used for a ddname.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM845 Unknown character in column 1 on record *record_number*. Blank assumed.

Explanation: Records must begin with an * in column one. If the record continues to another line, a blank must be in column one. Any other character is ignored and changed to a blank.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

Module: ICQAMCI2

ICQAM846 *AFTER or *POSITION entry must follow *INVOKING_PANEL entry.

Explanation: Either an *INVOKING_PANEL entry is not followed by an *AFTER or *POSITION entry or an *AFTER or *POSITION entry appears without a corresponding *INVOKING_PANEL entry. You must pair an *INVOKING_PANEL entry with either an *AFTER or *POSITION entry.

System action: The system waits for your response.

User response: Pair the entries correctly in the installation file.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM847 FILE option not available. Press HELP.

Explanation: You cannot add an application with an installation file because table services (ICQGCL10) could not open the Application Manager installation table. You can add applications by selecting one of the other options.

User response: Contact your Information Center Facility administrator or a system programmer for assistance.

Module: ICQAMCI0

ICQAM848 Loading installation data from *installation_file_name*.

Explanation: This message is written to the ISPF log data set and is an identifying title for installation file error messages that are also written to the ISPF log data set. It identifies the data set or data set member that was being loaded when the errors occurred.

Module: ICQAMCI2

ICQAM849 Data for **record_type* on record *record_number* cannot contain DBCS data.

Explanation: Double-byte character set (DBCS) data is not allowed.

This message appears in the ISPF log data set and is displayed in line mode. Message HELP is not available on-line.

User response: Remove any DBCS data.

Module: ICQAMCI2

ICQAM850 *INVOKING_PANEL entry with name *panel_name* will not be processed.

Explanation: Errors occurred while processing the definition of the *INVOKING_PANEL entry in the installation file. The entry is not processed.

System action: Processing continues.

User response: Check that you correctly defined the installation file entry specified in *panel_name* and install the application again.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM851 Selection ID *selection_id* on *INVOKING_PANEL entry is not valid.

Explanation: The selection ID specified on the *INVOKING_PANEL entry is not valid. A valid selection ID contains 3 characters and can be a combination of A-Z, 0-9, \$, #, or @.

System action: Processing continues.

User response: Correct the selection ID in the installation file and install the application again.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM852 Must specify a numeric value on *POSITION entry. Press HELP.

Explanation: You did not specify a numeric value on the *POSITION entry.

System action: Processing continues.

User response: Type a numeric value on the *POSITION entry. A valid numeric value contains 3 characters, from 0 to 999.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM853 Position *number* on *POSITION entry is not valid. Must be numeric.

Explanation: The value specified in *number* on the *POSITION entry is not valid. The value must be numeric. A valid numeric value contains 3 characters, from 0 to 999.

System action: Processing continues.

User response: Change the value to a numeric value on the *POSITION entry.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM854 Must specify an invoking panel name for *INVOKING_PANEL entry.

Explanation: The name of the invoking panel is missing from the *INVOKING_PANEL entry.

System action: Processing continues.

User response: Find the *INVOKING_PANEL entry that does not have a name specified and type a name for the invoking panel.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM855 Must specify a selection ID for *INVOKING_PANEL entry.

Explanation: The selection ID is missing from the *INVOKING_PANEL entry.

System action: Processing continues.

User response: Find the *INVOKING_PANEL entry that does not have a selection ID specified and type a selection ID. A valid selection ID contains 3 characters and can be a combination of A-Z, 0-9, \$, #, or @.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM856 • ICQAM862

ICQAM856 Must specify application name for *AFTER entry.

Explanation: The application name is missing from the *AFTER entry.

System action: Processing continues.

User response: Find the *AFTER entry that does not have an application name specified and type an application name.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM857 Must specify application language for *AFTER entry.

Explanation: The application language is missing from the *AFTER entry.

System action: Processing continues.

User response: Find the *AFTER entry that does not have an application language specified and type an application language.

Module: ICQAMCI2

Audience: Information Center Facility administrator

ICQAM858 No selection made.

Explanation: You pressed END to cancel out of a member selection list. You did not select a member.

System action: The system waits for your response.

User response: Either press END to exit from upgrade processing or choose to redisplay a member list and make a selection.

Module: ICQAMRY0, ICQASRP1

Audience: Information Center Facility administrator

ICQAM860 Export option not available. Press HELP.

Explanation: You cannot export an application to an installation file because table services (ICQGCL10) could not open the Application Manager installation table.

User response: Contact your Information Center Facility administrator or a system programmer for assistance.

Module: ICQAMCX0

ICQAM861 END pressed; the application was not exported.

Explanation: Your request to export the application was canceled because you pressed the END PF key. This message is informational only.

User response: None

Module: ICQAMCX0

ICQAM862 The data set is partitioned; specify a member.

Explanation: You requested a partitioned data set to be created.

User response: Specify a member name for that data set.

Module: ICQAMCX0

ICQAM863 Data already exists; specify another name or change REPLACE to Y.

Explanation: The sequential data set or member of a partitioned data set already exists.

User response: Either change the name or change REPLACE to Y to replace the existing data.

Module: ICQAMCX0

ICQAM864 Unable to export to the requested data set. Press HELP.

Explanation: Export services are not available for the requested data set. ISPF issued a return code of either 14 or 20 with the following reasons:

- *ISPF_short_error_message*
- *ISPF_long_error_message*

User response: Contact your system programmer for assistance.

Module: ICQAMCX0

ICQAM865 Application exported to *data_set_name*.

Explanation: The requested application was successfully exported to the installation file. This message is informational only.

User response: None

Module: ICQAMCX0

ICQAM866 CANCEL typed; the application was not exported.

Explanation: Because you typed CANCEL on the command line, the application was not exported. To export the application, select the export option. This message is informational only.

User response: None

Module: ICQAMCX0

ICQAM867 Unable to export the application. Severe error; press HELP.

Explanation: The application table does not have a data row.

User response: Contact your system programmer for assistance.

Module: ICQAMCX0

ICQAM868 Unable to export the application. Severe error; press HELP.

Explanation: The application table names one of the following:

- An environment
- A start-up function
- A termination function

However, Application Manager cannot access this environment or function table.

User response: Try again later.

Module: ICQAMCX0

ICQAM869 Unable to export the application. Severe error; press HELP.

Explanation: The application table names one of the following:

- An environment
- A start-up function
- A termination function

However, this environment or function does not have a data row.

ICQAM870 • ICQAM881

User response: Contact your system programmer for assistance.

Module: ICQAMCX0

ICQAM870 Unable to export the application. Severe error; press HELP.

Explanation: The logical record length is not large enough to fit the data for the installation file. The minimum logical record length to contain the data is *record_length*, provided you are using a data set with fixed format records (DSORG=F or FB).

If you are using variable format records (DSORG=V or VB), the minimum logical record length is *record_length*.

User response: Specify the minimum logical record length as displayed in the message explanation.

Module: ICQAMCX2

ICQAM871 END pressed; the data set was not created.

Explanation: Because you pressed END, your request to create a new data set was canceled. This message is informational only.

User response: None

Module: ICQAMCX0

ICQAM872 Request failed; system error. Press HELP.

Explanation: Your request failed because the system encountered a severe error during space management.

User response: Contact your Information Center Facility administrator or system programmer to resolve the problem.

ICQAM873 END pressed; a data set was not selected.

Explanation: Your request to select the data sets listed was canceled. This message is informational only.

User response: None

Module: ICQAMCX0

ICQAM880 Upgrade process cancelled.

Explanation: You either did not initiate the upgrade process and you pressed END to cancel or edited the upgrade members and pressed END instead of ENTER.

System action: The system canceled the upgrade process.

User response: None.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM881 Upgrade process completed successfully.

Explanation: You successfully upgraded the installation file. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM882 Installation file data valid.

Explanation: The installation file name has been validated and a member has been selected from the installation file member list.

System action: The system waits for your response.

User response: Press ENTER to continue with the upgrade process or press END to cancel.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM883 Upgrade file data valid. Press ENTER to upgrade member.

Explanation: The upgrade file has been validated and a member has been selected from the upgrade file member list.

System action: The system waits for your response.

User response: Press ENTER to upgrade the selected member.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM884 Member does not exist.

Explanation: The member specified was not found.

System action: The system waits for your response.

User response: Type an existing member name or press END to cancel.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM885 Data saved. Press ENTER to process or press END to cancel.

Explanation: Data has been changed and saved after you edited either the installation or upgrade file member.

System action: The system waits for your response.

User response: Press ENTER to continue the upgrade process or press END to cancel.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM886 Upgrade interrupt changes saved. Press ENTER to continue.

Explanation: The upgrade process was interrupted because of an error detected in the upgrade file. The error has been corrected and the changes saved.

System action: The system waits for your response.

User response: Press ENTER to re-initiate the upgrade process or press END to cancel.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM887 Upgrade interrupt corrections cancelled. Press END to exit.

Explanation: The upgrade process was interrupted because of an error found in the upgrade file. You chose to cancel out of the edit session by pressing END or typing CANCEL.

System action: The system waits for your response.

User response: Press END to cancel out of the upgrade process completely.

ICQAM888 • ICQAM892

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM888 Upgrade process cancelled.

Explanation: You chose to cancel out of the edit session by pressing END.

System action: The system waits for your response.

User response: Either press ENTER to continue with the upgrade process or press END to cancel.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM889 Data set validated. Press ENTER to continue; END to cancel.

Explanation: A selection was made from the list of data sets. The data set has been validated.

System action: The system waits for your response.

User response: Press ENTER to continue with the upgrade process or press END to cancel.

Module: ICQAMRY0

Audience: Information Center Facility administrator

ICQAM890 *SYSTEM record is not correct in upgrade file.

Explanation: The second header line of any upgrade file must contain the value *SYSTEM MVS TSO/E. Any number of spaces may separate the items in the record.

System action: The system waits for your response.

User response: The cursor is positioned at the entry that is not correct. Fix the entry and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM891 Upgrade file ID does not match installation file.

Explanation: The identification portion of the upgrade file does not match the identification portion of the installation file being upgraded. The third, fourth, and fifth non-comment lines must have values of an application type, application name, and application language, respectively. They must match the corresponding lines from the installation file.

System action: The system waits for your response.

User response: The cursor is positioned at the entry that is not correct. Fix the entry and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM892 Upgrade entry type is not valid.

Explanation: The value immediately following the upgrade entry is not a valid record type for an installation file.

System action: The system waits for your response.

User response: The cursor is positioned at the entry that is not correct. Fix the entry and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM893 Required values for upgrade entry not found. Press HELP.

Explanation: The installation type being upgraded requires more values to be present on the line of the upgrade entry indicated at the cursor position.

System action: The system waits for your response.

User response: Type the required values for the upgrade entry where the cursor is positioned and press END. The required value for a function installation file is *KEYWORD. The required values for a panel installation file are *KEYWORD, *PANEL_TITLE, *PRIMARY_PANEL, and *MODEL_ISPF_PANEL (if the panel is not ICQAMED1).

To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM894 Cannot add entry of type *entry_type*.

Explanation: ADD is not a valid action for the entry type specified.

System action: The system waits for your response.

User response: Type another entry type where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM895 Cannot delete entry of type *entry_type*. Press HELP.

Explanation: DELETE is not a valid action for the entry type specified.

System action: The system waits for your response.

User response: Type another entry type where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM896 Installation file ID is not valid. Press HELP.

Explanation: The installation file being upgraded does not have the required first line of identification: *APPLICATION MANAGER INSTALLATION FILE.

System action: The system waits for your response.

User response: Add the first line of identification, *APPLICATION MANAGER INSTALLATION FILE, and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM897 Installation file record length must be *record_length*.

Explanation: In order for the upgrade to take place, the installation file must have a record length of *record_length*. Currently the record length of the installation file is not long enough.

System action: The system waits for your response.

User response: To complete the upgrade process, do one of the following:

- Re-allocate the installation file data set with a record-length of *record_length*
- Edit the upgrade file to shorten the upgrade entry lines so as to fit within the current installation file record length. Note that the record length required for the installation file is equal to the longest non-comment upgrade line size plus two lines.

ICQAM898 • ICQAM903

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM898 Error accessing upgrade file. Press HELP.

Explanation: An error occurred while reading the upgrade file for processing.

System action: The system waits for your response.

User response: Pressing HELP displays additional information about the error. Contact your system programmer for assistance.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM899 Error accessing installation lookup table. Press HELP.

Explanation: An error occurred while reading the installation file lookup table, ICQAMT80.

System action: The system waits for your response.

User response: If the lookup table was “open” at the start of the upgrade process, then retrying the upgrade process might resolve the error. If the lookup table is not open, contact your system programmer.

Programmer response: Allocate the lookup table, ICQAMT80, to the correct library for your installation.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM901 -----

Explanation: The line of dashes is not a message. It is used to surround the message or note lines indicating whether the upgrade was successful.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM902 UPGRADE OF THE INSTALLATION FILE *file_name*

Explanation: The first of two lines indicate whether the upgrade of the specified installation file was successful. If the upgrade was successfully completed, a note line is followed by message ICQAM903. If conflicts were found, a message line is followed by message ICQAM904.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM903 WAS SUCCESSFULLY COMPLETED.

Explanation: The second of two note lines indicating that the upgrade of the specified installation file was successful.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

ICQAM904 CONFLICTS FOUND.

Explanation: The second of two message lines indicating that there were conflicts found in the specified installation file. These conflicts are specified with additional message lines in the upgraded installation file.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM905 ADD PERFORMED. THE ENTRY ADDED WAS: *entry_name*

Explanation: This is a note line found directly above each entry that was added to the installation file as a result of the upgrade processing.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM906 ADD NOT PERFORMED. DUPLICATE ENTRY FOUND.

Explanation: This message line indicates that an ADD entry in the upgrade file could not be performed because the entry to be added conflicts with an existing entry in the installation file. Following this message, the entry that was to be added is commented out.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM907 DELETE NOT PERFORMED. ENTRY NOT FOUND.

Explanation: This message line indicates that a DELETE entry in the upgraded installation file could not be found.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM908 DELETE PERFORMED. THE ENTRY DELETED WAS:

Explanation: This note line is directly above each entry that was deleted from the installation file as a result of the upgrade processing. The deleted entries appear as note lines.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM909 REPLACE NOT PERFORMED. ENTRY NOT FOUND:

Explanation: This message line indicates that a REPLACE entry in the upgrade file could not be found. The entries to be replaced appear as message lines following this message.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM911 REPLACE NOT PERFORMED. DUPLICATE ENTRY FOUND.

Explanation: This message line indicates that a REPLACE entry in the upgrade file could not be performed because the entry to be replaced conflicts with an existing entry in the installation file. The entry that was to be replaced follows this message.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM912 REPLACE PERFORMED. THE ENTRY REPLACED WAS:

Explanation: This note line is directly above each entry that was replaced from the installation file as a result of the upgrade processing. The replaced entries appear as note lines.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM913 ENTRY REPLACED WITH:

Explanation: This note line is directly above the entry that replaced the existing entry. This message is informational only.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM914 WAS TO BE REPLACED BY:

Explanation: The commented lines following this message contain data to replace an existing entry, but either the entry to be replaced was not found or the new entry is a duplicate.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM915 THE FOLLOWING 2 COMMENTS CORRESPOND TO 1 INSTALLATION LINE:

Explanation: When an entry is displayed as a comment and the comment exceeds the maximum comment line length, the entry is displayed on two comment lines, which represent the original entry line.

System action: The system waits for your response.

User response: Edit the changes and press END to save the upgraded installation file or type CANCEL to cancel the edit session. Note that any message or note lines are not saved as part of the upgraded installation file.

Module: ICQAMRY2

ICQAM916 *WITH keyword missing from REPLACE entry. Press HELP.

Explanation: All REPLACE entries require a line containing the *WITH keyword on a line by itself. This line separates the portion being replaced from the portion that it is being replaced with.

System action: The system waits for your response.

User response: Add the *WITH keyword where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM917 Entry type doesn't match type being replaced.

Explanation: The upgrade REPLACE entry has a record type that is not equal to the record type that it is being replaced with. The upgrade entry portion following the *WITH keyword must begin with a record type.

System action: The system waits for your response.

User response: Add a record type that matches the record type being replaced where the cursor is positioned. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM918 *AFTER or *POSITION keyword missing.

Explanation: The *AFTER or *POSITION keyword is required for the *INVOKING_PANEL entry.

System action: The system waits for your response.

User response: Add the *AFTER or *POSITION keyword where the cursor is positioned. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM919 Library type value missing from LIBRARY entry.

Explanation: The LIBRARY upgrade entry must contain a library type on the same line as the LIBRARY keyword and the library name value. Valid library type values are ISPF, EXEC, CLIST, INPUT, and OUTPUT.

System action: The system waits for your response.

User response: Add a valid library type where the cursor is positioned. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM920 Upgrade file identification is not valid.

Explanation: The first non-comment line of an upgrade file must contain APPLICATION MANAGER UPGRADE FILE.

System action: The system waits for your response.

User response: Do one of the following:

- Edit the upgrade file by adding the first identification line, APPLICATION MANAGER UPGRADE FILE, or
- Specify a different upgrade file to process.

To cancel the upgrade process, press END.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM921 Entry incomplete. More lines expected for entry.

Explanation: The upgrade entry that precedes the cursor position is not complete. More variables are required for the record type being upgraded.

System action: The system waits for your response.

User response: Add the required lines where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM922 Header line (with * in first column) missing.

Explanation: The previous entry is complete and the start of another entry marked with an asterisk in the first column is missing.

System action: The system waits for your response.

User response: Add the * in the first column where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM923 Value length exceeded limit of *value_length*.

Explanation: The value of the upgrade entry indicated at the cursor position has too many characters.

System action: The system waits for your response.

User response: Specify a value that is equal to or less than *value_length* where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM924 Character found in first column is not valid.

Explanation: The character in the first column is not valid for an upgrade file.

System action: The system waits for your response.

User response: If the record is a comment line, then type /* in the first two columns. Otherwise, type a blank or an * as the first character.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM925 Entry type cannot be upgraded. Press HELP.

Explanation: The upgrade entry type indicated at the cursor position cannot be upgraded. You cannot ADD, DELETE, or REPLACE the entry type.

System action: The system waits for your response.

User response: Delete the upgrade entry for the record type shown and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM926 Upgrade action is not valid.

Explanation: The upgrade action immediately following the asterisk is not valid. Valid values are ADD_, DELETE_, and REPLACE_.

System action: The system waits for your response.

User response: Type ADD_, DELETE_, or REPLACE_ where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM927 Extra data found on upgrade line.

Explanation: The upgrade record indicated at the cursor position has extra (unrelated) data that needs to be removed.

System action: The system waits for your response.

User response: Remove the extra data where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM928 No upgrade record to process.

Explanation: The upgrade file does not contain ADD, DELETE, or REPLACE entries. The installation file was not upgraded.

System action: The system waits for your response.

User response: Check that the file you are editing is the correct upgrade file. If it is, add the ADD_, DELETE_, or REPLACE_ entries and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM929 Value length may not exceed *value_length* characters per line.

Explanation: The value of the upgrade entry indicated at the cursor position has too many characters per line.

System action: The system waits for your response.

User response: Specify a value that is equal to or less than *value_length* where the cursor is positioned and press END. To cancel the edit session, press END or type CANCEL.

Module: ICQAMRY2

Audience: Information Center Facility administrator

ICQAM930 • ICQAM934

ICQAM930 New group *group_name* established with prefix *prefix_name*.

Explanation: You successfully established a new Application Manager group with the newly created group prefix, *prefix_name*. This group is to be used during application invocation. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM931 Application invocation group *group_name* established.

Explanation: You successfully established a new Application Manager group to be used during application invocation. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM932 No change made to group specification.

Explanation: You pressed END on the Group Specification panel. No changes were made to the Application Manager group specification to be used during application invocation. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM933 Group specification was removed.

Explanation: You typed a null value or blanked out the Group ID field. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM934 Error obtaining previous group specification. Press HELP.

Explanation: An error occurred while attempting to retrieve the previous group specification. The system could not read the profile member, ICQGROU.P.

System action: Processing terminates.

User response: If you are an administrator, check to see if you have READ authority over the profile data set. If you are a user, contact your system programmer.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM935 Error saving group specification. Press HELP.

Explanation: An error occurred while attempting to save the previous group specification. The system could not read the profile member, ICQGROU.P.

System action: Processing terminates.

User response: If you are an administrator, check to see if you have ALTER authority over the profile data set. If you are a user, contact your system programmer.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM936 Error deleting previous group specification.

Explanation: An error occurred while attempting to delete the previous group specification. The system could not read the profile member, ICQGROU.P.

System action: Processing terminates.

User response: If you are an administrator, check to see if you have ALTER authority over the profile data set. If you are a user, contact your system programmer.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM937 Specified group does not exist.

Explanation: You typed a group name that does not exist.

System action: The system waits for your response.

User response: Change the group name to an existing one or type a partial group name with an * as the last character, or an * to receive a list of groups.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM938 Group prefix is not valid.

Explanation: The specified group prefix defined in the ICQSIEAM non-display panel is not valid.

System action: The system waits for your response.

User response: Check the value of the QAMGPREF string in the ICQSIEAM non-display panel. The value should contain a valid data set name. Contact your system programmer for assistance.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM939 Group name is not valid.

Explanation: You typed a group name that is not valid on the Group Specification panel.

System action: The system waits for your response.

User response: Change the group name to an existing one or type a partial group name with an * as the last character, or an * to receive a list of groups.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM940 • ICQAM944

ICQAM940 * is only valid as the last character in the group name.

Explanation: You typed an * where it is not valid.

System action: The system waits for your response.

User response: Type either a group name, a partial group name with an * as the last character, or an * to receive a selection list of groups.

Module: ICQAMRG0

Audience: Information Center Facility administrator

ICQAM941 No groups found to match specified criteria. Press HELP.

Explanation: You typed a partial group name with an * as the last character, but the system did not find the specified value.

System action: The system waits for your response.

User response: Correct the specified name or type an * to generate a selection list of existing groups. If you do not find the group you want, check the current group prefix value in the non-display panel, ICQSIEAM.

Module: ICQAMRG1

Audience: Information Center Facility administrator

ICQAM942 No group selected.

Explanation: You pressed END on the List of Groups panel without selecting a group. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMRG1

Audience: Information Center Facility administrator

ICQAM943 Not authorized to read *group_name* user data set. Press HELP.

Explanation: You do not have authority to read the specified user data set.

System action: The system waits for your response.

User response: Type or select another group name.

Module: ICQAMRG1

Audience: Information Center Facility administrator

ICQAM944 Not authorized to write to *group_name* user data set. Press HELP.

Explanation: You do not have authority to write to the specified user data set or the data set is full.

System action: The system waits for your response.

User response: Either type or select another group name or compress the data set. If compressing the data set does not resolve the problem, contact your system programmer for assistance.

Module: ICQAMRG1

Audience: Information Center Facility administrator

ICQAM945 Not authorized to write to *group_name* administrator data set.

Explanation: Either you do not have authority to write to the specified administrator data set or the data set is full.

System action: The system waits for your response.

User response: Either type or select another group name or compress the data set. If compressing the data set does not resolve the problem, contact your system programmer for assistance.

Module: ICQAMRG1

Audience: Information Center Facility administrator

ICQAM946 Group administration data set does not exist. Press HELP.

Explanation: You selected a group where the user data set exists, but the administrator data set does not.

System action: The system waits for your response.

User response: Either delete the group user data set associated with the selected group and re-create the group by typing the group name on the Group Identification panel, or select another group to administer.

Module: ICQAMRG1

Audience: Information Center Facility administrator

ICQAM947 Error allocating group administrator data set. Press HELP.

Explanation: The system could not allocate the group administration data set.

System action: The system waits for your response.

User response: Correct the QAMALGRP group allocation string defined in the ICQSIEAM non-display panel and retry the function.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM948 Error allocating group user data set. Press HELP.

Explanation: The system could not allocate the group user data set.

System action: The system waits for your response.

User response: Correct the QAMULGRP group allocation string defined in the ICQSIEAM non-display panel and retry the function.

Module: ICQAMCM0

Audience: Information Center Facility administrator

ICQAM949 Group does not exist. Press HELP.

Explanation: The specified group name does not exist.

System action: The system waits for your response.

User response: Type another group name, or a partial group name with an * as the last character, or an * to receive a selection list of existing groups.

Module: ICQAMRG1

Audience: Information Center Facility administrator

ICQAM951 • ICQAM960

ICQAM951 No HELP defined for this application.

Explanation: HELP information for the application has not been defined. This message is informational only.

User response: None

Module: ICQAMCV0

ICQAM952 No VARIABLES defined for this application.

Explanation: No variables have been defined for the application. This message is informational only.

User response: None

Module: ICQAMCV0

ICQAM953 No COMMANDS defined for this application.

Explanation: No commands have been defined for the application. This message is informational only.

User response: None

Module: ICQAMCV0

ICQAM954 No LIBRARIES defined for this application.

Explanation: No libraries have been defined for the application. This message is informational only.

User response: None

Module: ICQAMCV0

ICQAM955 No OPTIONS defined for this panel.

Explanation: No options have been defined for the panel. This message is informational only.

User response: None

Module: ICQAMCV0

ICQAM956 This application cannot be viewed, it has no DATA row.

Explanation: To view the application, a data row must exist.

User response: Contact your system programmer for assistance.

Module: ICQAMCV0

ICQAM957 No HELP TEXT defined for this application.

Explanation: HELP text has not been defined for this application. However, a tutorial is available. This message is informational only.

User response: None

Module: ICQAMCV0

ICQAM960 Language/Name is unique. Specify N for REPLACE.

Explanation: There is no language and application with the name you specified. The name is unique. Therefore, there is nothing to be replaced.

User response: Type N (no) in the REPLACE field.

Module: ICQAMCF0, ICQAMCP0

ICQAM961 Environment was added and replaced existing application.

Explanation: The environment was added as you requested. Because you specified Y (yes) in the REPLACE field, the environment also replaced an existing application.

This message is informational only.

Module: ICQAMCF0, ICQAMCP0

ICQAM962 Function was added and replaced existing application.

Explanation: The function was added as you requested. Because you specified Y (yes) in the REPLACE field, the function also replaced an existing application.

This message is informational only.

Module: ICQAMCF0, ICQAMCP0

ICQAM963 Panel was added and replaced existing application.

Explanation: The panel was added as you requested. Because you specified Y (yes) in the REPLACE field, the panel also replaced an existing application.

This message is informational only.

Module: ICQAMCF0, ICQAMCP0

ICQAM964 Environment was copied and replaced existing application.

Explanation: The environment that you selected to copy was copied. Because you specified Y (yes) in the REPLACE field, the environment also replaced an existing application.

This message is informational only.

Module: ICQAMCF0, ICQAMCP0

ICQAM965 Function was copied and replaced existing application.

Explanation: The function that you selected to copy was copied. Because you specified Y (yes) in the REPLACE field, the function also replaced an existing application.

This message is informational only.

Module: ICQAMCF0, ICQAMCP0

ICQAM966 Panel was copied and replaced existing application.

Explanation: The panel that you selected to copy was copied. Because you specified Y (yes) in the REPLACE field, the panel also replaced an existing application.

This message is informational only.

Module: ICQAMCF0, ICQAMCP0

ICQAM967 Unverified installation file replaced existing application.

Explanation: The installation file you loaded is saved, but not verified. Because you specified Y (yes) in the REPLACE field, the installation file also replaced an existing application.

Before you can use the application added by an installation file, it must be verified. To verify an installation file, select the VERIFY option.

Module: ICQAMCF0, ICQAMCP0

ICQAM980 Requested data set is not available. Try again later.

Explanation: The specified data set to be validated is not available.

System action: Processing continues.

User response: Reinitiate the upgrade process when the data set is available for processing at a later time.

Module: ICQAMRY0, ICQASRP3, ICQASRT1

Audience: Information Center Facility administrator

ICQAM981 Error processing the requested data set. Press HELP.

Explanation: A system error occurred while validating the specified data set.

System action: Processing terminates.

User response: Check the status of the data set to see whether it is correctly allocated. Contact your system programmer for further assistance.

Module: ICQAMRY0, ICQASRP3, ICQASRT1

Audience: Information Center Facility administrator

ICQAM990 File name in use for your output request. Press HELP.

Explanation: The application you selected requires an output file that is being used by an application you had already started. Either you specified the same file name for two different applications or you specified the file name more than once for each user session.

System action: The application is not invoked.

User response: Complete or terminate the processing of the current or previous application and try again. If you continue to have the same problem, contact your system programmer.

Programmer response: Ensure that the output names are unique across applications.

Module: ICQAMLF1

Audience: Application Manager user

ICQAM991 Allocation failed for the output data set. Press HELP.

Explanation: The invocation of the application failed. Either another user is invoking the same application or the specified data set does not exist.

System action: The application is not invoked.

User response: Check that the output data set exists. If it exists, try again later. If you continue to have the same problem, contact your system programmer.

Programmer response: Ensure that the data sets allocated to the application are valid.

Module: ICQAMLF1

Audience: Application Manager user

ICQAM992 File name in use for your input request. Press HELP.

Explanation: An input allocation request has been specified for a file name (ddname) that is currently in use. The input data set can be shared, but you must use the same concatenation sequence for the data sets.

System action: The application is not invoked.

User response: Complete or terminate the processing of the current or previous application and try again. If you continue to have the same problem, contact your system programmer.

Programmer response: Ensure that you are using the same concatenation sequence for the data sets and using the same library names across applications.

Module: ICQAMLF1

Audience: Application Manager user

ICQAM993 Allocation failed for the input data set. Press HELP.

Explanation: The invocation of the application failed. Either another user is invoking the same application or the specified data set does not exist.

System action: The application is not invoked.

User response: Check that the input data set exists. If it exists, try again later. If you continue to have the same problem, contact your system programmer.

Programmer response: Ensure that the data sets allocated to the application are valid.

Module: ICQAMLF1

Audience: Application Manager user

ICQAM994 Concatenation of the data set failed. Press HELP.

Explanation: A system failure occurred during the concatenation of the data set.

System action: Processing terminates.

User response: Contact your system programmer.

Programmer response: Contact your IBM support personnel.

Module: ICQAMLF1

Audience: Application Manager user

ICQAN000 ITEM cannot end with *. Correct and press ENTER.

Explanation: The name of a news item cannot end with an asterisk (*). Correct the item name and press the ENTER key.

Module: ICQANC00

ICQAN001 CATEGORY cannot end with *. Correct and press ENTER.

Explanation: A category name cannot end with an asterisk (*). Correct the category name and press the ENTER key.

Module: ICQANC00

ICQAN002 No news items match the information specified.

Explanation: No news items match the information specified in the ITEM, CATEGORY, BEGIN DATE, and PRIORITY fields. Either:

- Change some of the information displayed and press the ENTER key.
- Request a list of news items and select from the list.
- Type NEW on the COMMAND line to display any news that has been added since you last viewed news.
- Add a news item by typing A on the COMMAND line and pressing the ENTER key.
- Leave the news service by pressing the END PF key.

Module: ICQANC00

ICQAN003 No news items are available. To exit news, press END.

Explanation: There are no news items to view. To exit the news service, press the END PF key. Administrators can add news items by typing A on the COMMAND line and pressing the ENTER key.

Module: ICQANC00, ICQCNC00

ICQAN004 • ICQAN102

ICQAN004 *Specified_selection_character* is not valid. To select item, type C, D, M, P, or V.

Explanation: The only *valid_selection_characters* are C for copy, D for delete, M for modify, P for print, and V for view. Type one of those letters next to the news item and press the ENTER key.

Module: ICQANE10

ICQAN005 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility cannot create the temporary table to hold the information you supplied. The ISPF TBCREATE service routine set a return code of 8 or higher.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC00, ICQCNC00

ICQAN007 Type Y, N, or * in the PRIORITY field.

Explanation: The only values allowed in the PRIORITY field are Y, N, or *. To see only news items of high priority, type Y. To see only news items of lower priority, type N. To see both types, type *. Press the ENTER key to display the news items.

Module: ICQANE00

ICQAN008 Type Y or N in the PRIORITY field.

Explanation: Type Y or N in the PRIORITY field to indicate whether the news item you are adding is of high (Y) or low (N) priority.

Module: ICQANE01, ICQANE40, ICQANE60

ICQAN009 Type the name of the news item in the ITEM field.

Explanation: You must give the news item you are adding a name. Type the name in the ITEM field. The name can be up to forty characters long, and cannot end with an asterisk (*).

Module: ICQANE01, ICQANE40, ICQANE60

ICQAN100 Request failed; system error. Press HELP.

Explanation: Your request failed because the Information Center Facility could not find the news index table. The ISPF TBOPEN service routine set a return code of 8. Someone might have inadvertently deleted or renamed the table.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC00, ICQANC01, ICQANC02, ICQANC03, ICQANC10, ICQCNC00

ICQAN101 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the news index table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12.

User response: To retry your request, press the ENTER key. To cancel it, press the END PF key.

Module: ICQANC00, ICQANC01, ICQANC02, ICQANC03, ICQCNC00

ICQAN102 Request failed; system error. Press HELP.

Explanation: Your request failed because the news index table is not allocated. The ISPF TBCLOSE, TBOPEN, or TBCREATE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC00, ICQANC01, ICQANC02, ICQANC03, ICQANC10, ICQCNC00

ICQAN104 Resource in use. To retry, press ENTER; to cancel, press END.

Explanation: Your request failed because the required news index table is temporarily in use.

To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQANC00

ICQAN106 END DATE must be the same as or later than BEGIN DATE.

Explanation: Change either the END DATE or the BEGIN DATE field. The end date cannot come before the begin date.

Module: ICQANC00

ICQAN107 Someone else is maintaining the news now. Try later.

Explanation: Your conversion request failed because the news table is in use. The ISPF TBCREATE or TBOPEN service routine set a return code of 12 after attempting to open the table.

Press the END PF key to cancel your request and try later.

Module: ICQANC10

ICQAN109 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not open the news index table. The ISPF TBOPEN service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC00, ICQANC01, ICQANC02, ICQANC03, ICQANC10, ICQCNC00

ICQAN110 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not copy your updates into the news index table. The ISPF TBCLOSE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC00, ICQANC01, ICQANC02, ICQANC03

ICQAN111 Request failed; system error. Press HELP.

Explanation: Your request failed because the system could not create the news index table. The ISPF TBCREATE service routine set a return code of 20, which indicates that a severe error occurred.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC00, ICQANC10

ICQAN112 Resource in use. To retry, reselect; to cancel, press END.

Explanation: Your request failed because someone else is using the news table that contains the news item you selected. The ISPF TBCREATE service routine set a non-zero return code.

To retry the request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQANC00, ICQANC03

ICQAN115 Request failed; system error. Press HELP.

Explanation: Your request failed because of an error related to the news index table. After determining that the table did not exist, the Information Center Facility attempted to create it using the ISPF TBCREATE service. However, TBCREATE set a return code of 8, which indicates the table is already created.

User response: Contact a system programmer to resolve the problem.

ICQAN400 • ICQAN407

Module: ICQANC00, ICQANC10

ICQAN400 A news item matching this description already exists.

Explanation: A news item with the same name, category, begin date, and priority as you specified already exists. You can either:

- Press the END PF key to cancel your request.
- Change the information you typed to make the news item unique. Changing the end date only is not sufficient. You must change at least one field other than END DATE.
- If adding a news item, you can replace the existing news item with the one you are adding. To request replacement, type Y in the REPLACE ITEM field and press the ENTER key.

Module: ICQANC00, ICQANC01

ICQAN402 The news item was added.

Explanation: The Information Center Facility added the news item you specified. This message is informational only.

Module: ICQANC01

ICQAN403 The modified copy of the news item was added.

Explanation: The Information Center Facility added the news item you copied and modified. This message is informational only.

Module: ICQANC01

ICQAN404 The news item was added. It is not in the list shown here.

Explanation: The Information Center Facility added the news item you requested. It does not appear in the subset of news items on the panel displaying this message, however, because it does not fit in that subset of items. That is, the description of the new news item does not match the information you specified to obtain the list displayed.

Module: ICQANC01

ICQAN405 News item description was added. The news item has no text.

Explanation: The Information Center Facility added the news item you requested, but it has no text. You either pressed the END PF key or typed CANCEL on the COMMAND line while the panel for typing the text was displayed.

Users and administrators see the name and description of the news item in lists of news items. If they request to view the item, they receive a message stating the item has no text.

Module: ICQANC01

ICQAN406 Modified copy of news added. It is not in list shown here.

Explanation: The Information Center Facility added the news item you copied and modified. The news item does not appear in the subset of news items listed on the previous panel, however, because it does not fit in that subset of items. That is, the description of the new news item does not match the information you specified to obtain the list displayed.

Module: ICQANC00

ICQAN407 The news item was replaced.

Explanation: The Information Center Facility replaced the old news item with the news item you requested to add. This message is informational only.

Module: ICQANC02

ICQAN408 The news item was modified. It is not in list shown here.

Explanation: The Information Center Facility modified the news item as you requested. The modified item does not appear in the subset of news items listed, however, because it no longer fits in the subset. That is, the description of the news item does not match the information you specified to obtain the list displayed.

Module: ICQANC00

ICQAN409 News item with no text added. It is not in list shown here.

Explanation: The Information Center Facility modified the news item as you requested. The modified item does not appear in the subset of news items listed, however, because it does not fit in that subset. That is, the description of the new news item does not match the information you specified to obtain the list displayed.

Module: ICQANC00

ICQAN500 No text added or changed; system error. Press HELP.

Explanation: A severe ISPF error occurred when the Information Center Facility attempted to save the text you added or changed. Any updates you made to the text are lost. However, the text of the existing news item (if there is one) is unchanged.

User response: Contact a system programmer to resolve the problem.

Module: ICQANC01, ICQANC02

ICQAN501 The news item was modified.

Explanation: The Information Center Facility modified the news item. This message is informational only.

Module: ICQANC00, ICQANC02

ICQAN502 Request cancelled. The news item was not modified.

Explanation: The Information Center Facility did not modify the news item because you pressed the END PF key or typed CANCEL on the COMMAND line to cancel your request. This message is informational only.

Module: ICQANC00, ICQANC02

ICQAN504 News item description not modified. News item has no text.

Explanation: The Information Center Facility did not modify the item description.

The news item has no text. Either you deleted the text, or it had none and you added none.

This message is informational only.

Module: ICQANC02

ICQAN505 News item description was modified. Text was not changed.

Explanation: The Information Center Facility modified the item description as you requested. The text remains the same. This message is informational only.

Module: ICQANC00

ICQAN506 News item description was modified. News item has no text.

Explanation: The Information Center Facility modified the item description as you requested.

The news item has no text. Either the original news item had no text, you deleted the text, or you replaced the news item with an item that had no text. This message is informational only.

Module: ICQANC02

ICQAN602 • ICQAN701

ICQAN602 The news item was deleted.

Explanation: The Information Center Facility deleted the news item you requested. This message is informational only.

Module: ICQANC03

ICQAN603 Another administrator already deleted the news item.

Explanation: Another administrator deleted the news item you selected. The deletion occurred after you displayed the list of news items, but before you selected the item. This message is informational only.

Module: ICQANC03

ICQAN604 Request cancelled. The news item was not deleted.

Explanation: The Information Center Facility did not delete the specified news item because you pressed the END PF key to cancel the request. This message is informational only.

Module: ICQANC03

ICQAN605 Request cancelled. The news item was not added.

Explanation: The Information Center Facility did not add the specified news item because you pressed the END PF key to cancel the request. This message is informational only.

Module: ICQANC00

ICQAN606 Request cancelled. The news item was not replaced.

Explanation: The Information Center Facility did not replace the specified news item because you pressed the END PF key to cancel the request. This message is informational only.

Module: ICQANC00, ICQANC02

ICQAN607 News item description not replaced. News item has no text.

Explanation: The Information Center Facility did not replace the item description.

The news item has no text. The original news item had no text, and you did not replace it.

This message is informational only.

Module: ICQANC02

ICQAN608 Request cancelled. The news item was not copied.

Explanation: The Information Center Facility did not copy the news item, because you pressed the END PF key to cancel the request. This message is informational only.

Module: ICQANC00

ICQAN700 The news item has no text.

Explanation: The news item you requested to view or copy has no text. This message is informational only.

Module: ICQCNC01

ICQAN701 News table *ICQANTnn* exists. No conversion will be done.

Explanation: Your request to convert the news table to the TSO/E Release 3 level failed because the conversion probably has already been done.

Module: ICQANC10

ICQAP000 The print definition was added.

Explanation: Your request to add a print definition has completed successfully. This message is informational only.

Module: ICQAPC00

ICQAP001 Request failed, system error. Press HELP.

Explanation: You tried to copy or modify a printer that has a font table associated with it. Your request failed because the system was unable to open the font table. The ISPF TBOPEN service routine set a return code of 8.

User response: Contact a system programmer to resolve the problem.

Module: ICQAPC00

ICQAP002 Printer busy. To retry, repeat; to cancel, press END.

Explanation: Your request failed because another administrator is currently modifying the print definition you selected. Until the other administrator finishes, you cannot access this print definition.

Module: ICQAPC00

ICQAP003 The add request was cancelled.

Explanation: You asked to add a print definition and then canceled your request. All data changes you made during the process have been ignored. This message is informational only.

Module: ICQAPC00

ICQAP004 Another administrator deleted the definition.

Explanation: Since the original list of printers was displayed, another administrator has deleted the print definition that you tried to access. This message is informational only.

Module: ICQAPC00

ICQAP005 Type only A-Z, 0-9, @, #, \$, or -.

Explanation: The data in the field indicated by the cursor must be 1 to 8 characters long, and contain the characters A through Z, 0 through 9, @, #, \$, or a dash. However, the first character cannot be numeric (0 through 9).

You can type one or more of the following: letters, numbers, @, #, or \$. However, you can type only one dash in the field.

Module: ICQAPE30

ICQAP007 Data set not found; correct and press ENTER.

Explanation: Your test of the print definition failed because the following data set could not be found:

data_set_name

Verify that the data set is cataloged and spelled correctly. Correct your entry and press the ENTER key on the previous panel to repeat the test.

Module: ICQAPC00

ICQAP008 Change Printer Location or Print Format to make a unique pair.

Explanation: Another print definition contains the same Printer Location or Print Format. The contents of the Printer Location and Print Format fields must be unique across all print definitions. Change one or both of these fields to create a unique combination before you leave the panel. To see a list of existing print formats and print locations, type an asterisk (*) in those fields.

Module: ICQAPC00, ICQCPC00

ICQAP009 Type only A-Z, 0-9, @, #, \$. First not 0-9.

Explanation: The data in the field where the cursor is positioned must be 1 to 8 characters long, and contain the characters A through Z, 0 through 9, @, #, or \$. However, the first character cannot be numeric (0 through 9).

Module: ICQAPE50, ICQAPE53, ICQAPE57, ICQGAMR2

ICQAP010 No printer types match the specified information.

Explanation: You specified part of a printer type, followed by an asterisk (*) to see a list of previously defined printer types. Currently there are no printer types that begin with the characters you specified.

Module: ICQAPC00

ICQAP011 No printer types are defined.

Explanation: You typed an asterisk (*) to see a list of previously defined printer types. Currently there are no printer types defined in the printer support table.

Module: ICQAPC00

ICQAP012 No printer type was selected.

Explanation: A list of printer types was displayed, based upon your request. You viewed the list but did not select a printer type. This message is informational only.

Module: ICQAPC00

ICQAP013 A printer type was selected.

Explanation: A list of printer types was displayed and you selected one. This message is informational only.

Module: ICQAPC00

ICQAP014 The NAME updates were cancelled.

Explanation: You pressed the END PF key on the NAME panel, cancelling any changes you had made. This message is informational only.

Module: ICQAPC00

ICQAP015 Test of print function completed. Press HELP for details.

Explanation: Your request completed. In case of an error, note the information below for the system programmer. If you are using an IBM-supplied print function (ICQCPC10 or ICQCPC15) and the return code is 0 on this panel, then your test of the print function completed without error. For more information concerning the IBM-supplied print function and its return codes, see *z/OS TSO/E Programming Services*. Check your output to verify that the print function is operating correctly.

Printer location	Printer location
Printer format	Printer format
Print function	Name of CLIST, program, or command
Return code	Return code from print function
Print data set	Name of the data set you are trying to print
Function message	Message returned by print function
	Note: If there is no function message, this field will not be displayed at your terminal.
Invocation	The CLIST ISPF SELECT statement that was issued to invoke the print function.
	Note: If the invocation is truncated, the bottom of the panel will display a message to that effect.

Module: ICQAPC00

ICQAP016 Define a print function in one of the 3 entry fields.

Explanation: You did not define a print function. In the appropriate field, type the name of a CLIST, a TSO/E command, or a program that can send data to a printer.

IBM provides two print functions, both CLISTs, that you can specify:

- ICQCPC10 performs printing using the utility program IEBGENER.
- ICQCPC15 performs printing using the TSO/E command PRINTDS.

As an alternative, you can substitute any other print function (CLIST, command processor, or program) that may have originated at your or another installation.

Module: ICQAPE80

ICQAP017 Any changes to NAME information were saved.

Explanation: You pressed the ENTER key on the NAME panel, temporarily saving any changes you had made. When you press the END PF key on the panel for adding or modifying a printer, the changes will be recorded and will then be immediately accessible to all TSO/E Information Center Facility users.

If you did not make any changes to name information before you pressed the ENTER key on the NAME panel, no changes were saved.

This message is informational only.

Module: ICQAPE30

ICQAP018 Select "1" and change Printer Location or Print Format.

Explanation: Your request to update the print definition failed. Another print definition contains the same Printer Location and Print Format. The Printer Location and Print Format must be a unique pair.

Select option 1, Identification, and press the ENTER key. On the following panel, change the Printer Location or Print Format field, or both, to make the pair unique. To see a list of existing printer locations and print formats, type an asterisk (*) in those fields.

Module: ICQAPC00

ICQAP019 Select "1" and change Printer Location or Print Format.

Explanation: When you initiate a copy operation, you must change either the Printer Location or Print Format field of the print definition to give the new print definition a unique identification.

Select option 1, Identification, and press the ENTER key. On the following panel, change the Printer Location or Print Format field, or both, to make the pair unique. To see a list of existing printer locations and print formats, type an asterisk (*) in those fields.

Module: ICQAPC00 ICQAPM20

ICQAP021 Printer support table was converted.

Explanation: You invoked the printer support function. The system could not find the printer support table ICQAPT10, but found a previous version, ICQAPT00 from TSO/E Release 3. The contents of ICQAPT00 were copied to ICQAPT10.

This message is informational only.

Module: ICQAPC00

ICQAP022 • ICQAP029

ICQAP022 If System Name is specified, Printer Name is required.

Explanation: You specified a System Name without specifying the name of a printer attached to the system. To specify a printer, type the name of the printer as it is defined to the system.

Module: ICQAPE30

ICQAP023 File member not found.

Explanation: You supplied a partitioned data set name as input for the TEST function, but the member you specified was not found in the data set. Check the spelling of the member and retry. If necessary, check the members of the data set and specify another. The member must already exist and already have in it the data that is to be used for the print function test.

Module: ICQAPC00

ICQAP024 TEST request was cancelled.

Explanation: You pressed the END PF key and the system cancelled the test of the print function. This message is informational only.

Module: ICQAPC00

ICQAP025 * can only be the last character.

Explanation: You typed an asterisk (*) in the field where the cursor is positioned. The asterisk must be the last character. When you type an asterisk as the last character in this field, it indicates that a list of items that start with the characters to the left of the asterisk is to be displayed. You can then select one of the items from the list.

Module: ICQAPE30

ICQAP026 Make only one selection at a time.

Explanation: You made more than one selection on the panel. Make only one selection and press the ENTER key.

Module: ICQAPC00, ICQCPC00

ICQAP027 Request failed; system error. Press HELP.

Explanation: The printer table did not exist. Then the system created a printer table and successfully wrote it to permanent storage, but was unable to open the newly created table. The ISPF TBOPEN service set a return code of 8.

User response: Contact a system programmer to resolve the problem.

Module: ICQAPC00

ICQAP028 Blank lines may not be deleted.

Explanation: Blank lines at the top of the fonts list may not be deleted. Only lines that have been filled in as font entries can be deleted by typing D on them.

Module: ICQCPC20

ICQAP029 Printer support table was created. It is empty. Press HELP.

Explanation: The system could not find the printer support table ICQAPT10 and initialized one for you. The table is empty. The system also could not find the previous version, ICQAPT00 from TSO/E Release 3. Unless your installation has deliberately deleted the printer support table(s), this is an error condition.

If this is the first time you have used the print function, your installation might not have correctly installed the printer support table supplied with TSO/E Release 3. Otherwise, your installation may have inadvertently deleted the printer support table, ICQAPT00 or ICQAPT10, or incorrectly allocated the data set to the printer support file, ICQAPTAB.

User response: If necessary, contact a system programmer to resolve the problem.

Module: ICQAPC00

ICQAP030 Type only one function name.

Explanation: You entered more than one print function name on the panel. You can type only one function name, which must be the name of a CLIST, a command, or a program.

Module: ICQAPE80

ICQAP031 Request failed; system error. Press HELP.

Explanation: You requested to delete a print definition. Although the definition was successfully deleted from the printer support table, the system was unable to delete the font table associated with the print definition. The ISPF TBERASE service routine set a non-zero return code.

User response: Check the ISPF log for TBERASE results and contact a system programmer to delete the font table.

Module: ICQAPC00

ICQAP033 The print definition was copied.

Explanation: Your request to copy a print definition has completed successfully. This message is informational only.

Module: ICQAPC00

ICQAP034 Printer Location may not contain an apostrophe or parenthesis.

Explanation: You typed an apostrophe (') or parenthesis as one of the characters in the Printer Location field. Those characters are not valid in the Printer Location field. Type a valid character, and press the ENTER key.

Module: ICQAPE30

ICQAP035 SYSOUT Class must be 1 character, A-Z, 0-9, or *.

Explanation: You typed a character other than A through Z, 0 through 9, or * in the SYSOUT Class field. The SYSOUT Class must be one of these characters. Leave the field blank if no SYSOUT Class is to be specified.

Module: ICQAPE50

ICQAP036 Type only A-Z, 0-9, @, #, or \$ at cursor position.

Explanation: The cursor is positioned at the field in error. This field may contain only the characters A through Z, 0 through 9, @, #, and \$. Do not leave blanks between characters.

Module: ICQAPE30, ICQAPE50, ICQAPE51, ICQAPE52, ICQAPE53, ICQAPE57

ICQAP037 The maximum of 1000 fonts has been defined.

Explanation: No more sets of fonts (font tables) can be defined. To make room for more font tables, you can delete unnecessary print definitions that have font tables associated with them.

To minimize the number of font tables in the future, you can share font tables among multiple print definitions. When a print definition is copied, the original font table is shared unless it is modified.

Module: ICQAPC00

ICQAP038 Font number not valid; higher than allowed.

Explanation: You selected a font with a number that exceeds the maximum number of selectable fonts for this print definition. If you are an administrator modifying the print definition, you can increase this number. If you are a user selecting the order in which the fonts are to be used, assign font numbers that are less than or equal to the Number of Fonts displayed on the panel.

Module: ICQCPC20

ICQAP039 • ICQAP047

ICQAP039 The print definition was modified.

Explanation: Your request to modify a print definition has completed successfully. This message is informational only.

Module: ICQAPC00

ICQAP040 Type only A-Z, 0-9 at cursor position.

Explanation: The cursor is positioned at the field in error. Type only the characters A through Z and 0 through 9 in the field.

Module: ICQAPE30, ICQAPE50, ICQAPE52, ICQAPE57

ICQAP041 Displayed Name is required.

Explanation: The Displayed Name field must be filled for each font. This is a required field. Press ENTER for information about what to type in the fields on the Print Fonts panel.

Module: ICQCPC20

ICQAP042 Device Name is required.

Explanation: The Device Name field must be filled for each font. This is a required field. Press ENTER for information about what to type in the fields on the Print Fonts panel.

Module: ICQCPC20

ICQAP043 Fill in Per Group fields from left to right.

Explanation: The Per Group field consists of eight subfields which must be filled in from left to right. Blank subfields are not valid if there is a subfield to the right that has a number in it.

Module: ICQAPE52, ICQAPE57

ICQAP044 To delete, type D; to select, type number from a minimum number to a maximum number.

Explanation: You selected a font with a letter other than D, or with a number that was not within the listed range. To delete a font, type D. To select a font, type a number within the listed range.

Module: ICQAPE70

ICQAP045 To select a font, type a number from a minimum number to a maximum number.

Explanation: You selected a font with the wrong character. To select a font, type a font number that is within the listed range.

Module: ICQCPE10

ICQAP046 No print formats match the specified information.

Explanation: You specified part of a print format, followed by an asterisk (*) to see a list of previously defined print formats. Currently there are no print formats that begin with the characters you specified.

Module: ICQAPC00

ICQAP047 No print formats are defined.

Explanation: You typed an asterisk (*) to see a list of previously defined print formats. Currently there are no print formats defined in the printer support table.

Module: ICQAPC00

ICQAP048 No print format was selected.

Explanation: A list of print formats was displayed, based upon your request. You viewed the list but did not select a print format. This message is informational only.

Module: ICQAPC00

ICQAP049 A print format was selected.

Explanation: A list of print formats was displayed and you selected one. This message is informational only.

Module: ICQAPC00

ICQAP050 The print definition was deleted.

Explanation: Your request to delete a print definition has completed successfully. This message is informational only.

Module: ICQAPC00

ICQAP051 The copy request was cancelled.

Explanation: You were copying a print definition and then canceled your request. All data changes you made during the process have been ignored.

This message is informational only.

Module: ICQAPE10, ICQAPC00

ICQAP052 The modify request was cancelled.

Explanation: You selected to modify a print definition and then canceled your request. All data changes you made during the process have been ignored. This message is informational only.

Module: ICQAPC00

ICQAP053 The delete request was cancelled.

Explanation: You selected to delete a printer and then canceled your request. This message is informational only.

Module: ICQAPC00

ICQAP054 The sum of the Per Group fields exceeds 255.

Explanation: The Per Group field consists of eight subfields. The sum of the values in the subfields cannot exceed 255. To stay within this limit, modify the values so that they add up to no more than 255.

Module: ICQAPE57

ICQAP055 Print function could not be invoked. Press HELP for details.

Explanation: Your request failed, because the Information Center Facility attempted to invoke the print function (by calling the ISPF SELECT service) and encountered a severe error. When you receive this message, press the HELP PF key at your terminal and note the information displayed for your Information Center Facility administrator or system programmer.

Printer location
Printer format
Print function
ISPF SELECT message

Printer location
Printer format
print function
Message returned by ISPF SELECT service
Note: For more information concerning the ISPF SELECT service, see *z/OS ISPF Services Guide*.

ICQAP056 • ICQAP061

Invocation The ISPF SELECT service invoked via the CLIST command to activate the print function
Note: If the invocation is truncated, the bottom of the panel will display a message to that effect.

Module: ICQCPC30

ICQAP056 Any changes to the previous panel were cancelled.

Explanation: You pressed the END PF key on the previous panel, cancelling any changes you had made on that panel. This message is informational only.

Module: ICQAPE30, ICQAPE50, ICQAPE51, ICQAPE52, ICQAPE53, ICQAPE54, ICQAPE55, ICQAPE56, ICQAPE57, ICQAPE60, ICQAPE80

ICQAP057 The SPECIFIC updates were cancelled.

Explanation: You pressed the END PF key on the SPECIFIC panel, cancelling any changes you had made. This message is informational only.

Module: ICQAPE60

ICQAP058 The FONT updates were cancelled.

Explanation: You typed CANCEL on the COMMAND line of the FONTS panel, cancelling any changes you had made.

This message is informational only.

Module: ICQAPC00

ICQAP059 The FUNCTION updates were cancelled.

Explanation: You pressed the END PF key on the FUNCTION panel, cancelling any changes you had made. This message is informational only.

Module: ICQAPC00

ICQAP060 Any changes to the previous panel were saved.

Explanation: You pressed the ENTER key on the previous panel, temporarily saving any changes you had made on that panel. When you press the END PF key on the panel named Print Definition (panel ICQAPM20), the print definition will be updated with the changes you made.

This message is informational only.

Module: ICQAPE30, ICQAPE50, ICQAPE51, ICQAPE52, ICQAPE53, ICQAPE54, ICQAPE55, ICQAPE56, ICQAPE57, ICQAPE60, ICQAPE80

ICQAP061 Any changes to SPECIFIC information were saved.

Explanation: You pressed the ENTER key on the SPECIFIC panel, temporarily saving any changes you had made. When you press the END PF key on the panel for adding or modifying a printer, any changes will be recorded and will then be immediately accessible to all TSO/E Information Center Facility users.

If you did not make any changes to SPECIFIC information before you pressed the ENTER key on the SPECIFIC panel, no changes were saved.

This message is informational only.

Module: ICQAPE60

ICQAP062 Any changes to FONTS information were saved.

Explanation: You pressed the END key on the FONTS panel, temporarily saving any changes you had made. When you press the END PF key on the panel for adding or modifying a printer, any changes will be recorded. If ONLINE is set to Y, the changes will then be immediately accessible to all TSO/E Information Center Facility users.

If you did not make any changes to FONTS information before pressing the END PF key on the FONTS panel, no changes were saved.

This message is informational only.

Module: ICQAPC00

ICQAP063 Any changes to FUNCTION information were saved.

Explanation: You pressed the ENTER key on the FUNCTION panel, temporarily saving any changes you had made. When you press the END PF key on the panel for adding or modifying a printer, any changes will be recorded and will then be immediately accessible to all TSO/E Information Center Facility users.

If you did not make any changes to FUNCTION information before you pressed the ENTER key on the FUNCTION panel, no changes were saved.

This message is informational only.

Module: ICQAPE80

ICQAP064 No locations match the specified information.

Explanation: You specified part of a printer location, followed by an asterisk (*) to see a list of previously defined printer locations. Currently there are no printer locations that begin with the characters you specified.

Module: ICQAPC00

ICQAP065 No locations are defined.

Explanation: You typed an asterisk (*) or part of a printer location followed by an asterisk (*) to see a list of previously defined printer locations. Currently there are no printer locations defined in the printer support table.

Module: ICQAPC00

ICQAP066 If Translate Code is specified, Module Name is required.

Explanation: You specified a translate code without specifying the name of the modify module that will use the translate code. Specify the modify module in the Module Name field.

Module: ICQAPE51 ICQAPE57

ICQAP067 If Flash Count is specified, Flash Name is required.

Explanation: You specified the number of copies to be printed from an overlay without specifying the name of the overlay. Specify the overlay name in the Flash Name field.

Module: ICQAPE51 ICQAPE57

ICQAP068 No location was selected.

Explanation: A list of printer locations was displayed, based upon your request. You viewed the list but did not select a location. This message is informational only.

Module: ICQAPC00

ICQAP069 A location was selected.

Explanation: A list of printer locations was displayed and you selected one. This message is informational only.

Module: ICQAPC00

ICQAP071 Members and Directory cannot both be "N".

Explanation: You typed a value of N (no) for both Members and Directory. Both entries cannot be N, because this would prevent printing any part of a partitioned data set. Change one or both of the entries to Y (yes).

Module: ICQAPE53

ICQAP073 Last Line must be greater than or equal to First Line.

Explanation: When specifying lines to be printed, you typed a line number in the Last Line field that was less than the line number in the First Line field. To correct your entry, change the values so that the Last Line field contains a number greater than or equal to the number in the First Line field.

Module: ICQAPE55

ICQAP074 If First Column or Length is specified, Lines are required.

Explanation: You typed a number in the First Column or Length field, specifying the column location or length of a field that contains embedded line numbers. You must also specify the actual embedded line numbers in the First Line or Last Line fields, to indicate the range of lines that you want to print.

Module: ICQAPE55

ICQAP075 Type one of the listed values at the cursor position.

Explanation: Type one of the possible values in the field where the cursor is positioned. The possible values are listed on the same line.

Module: ICQAPE54

ICQAP076 Type FOLD or TRUN or nothing at the cursor position.

Explanation: The only valid entries at the cursor position are FOLD or TRUN or blanks.

If you want input lines to be truncated when they exceed the length specified in the field Maximum Length, type TRUN.

If you want lines to continue on the next line when they exceed the length specified in Maximum Length, type FOLD.

If you leave the Excess Length field blank, Maximum Length is ignored, but input lines will be truncated if they exceed the printer's default line length.

Module: ICQAPE54

ICQAP077 Select Function and specify a print function first.

Explanation: You requested to specify print parameters or test a print definition. Before doing so, you must first define a print function. To define a print function, select the Function option and press the ENTER key. On the Print Function panel, specify a print function.

Module: ICQAPM20

ICQAP078 If Maximum Length is specified, Excess Length is required.

Explanation: You typed a number in the Maximum Length field, specifying the maximum length for the printed line. You must also type FOLD or TRUN in the Excess Length field.

If you want input lines to continue on the next printed line when they exceed the maximum length, type FOLD.

If you want input lines to be truncated when they exceed the maximum length, type TRUN.

Module: ICQAPE54

ICQAP080 SYSOUT Class must be 1 character, A-Z or 0-9.

Explanation: You typed a character other than A through Z or 0 through 9 in the SYSOUT Class field. The SYSOUT Class must be one of these characters. Leave the field blank if no SYSOUT Class is to be specified.

Module: ICQAPE54

ICQAP081 To Column must be greater than or equal to From Column.

Explanation: When specifying columns to be printed, you typed a number in the To Column field that was less than the number in the From Column field. To correct your entry, change the values so that the To Column field contains a number greater than or equal to the number in the From Column field.

Module: ICQAPE56

ICQAP082 Select "1" and specify Printer Location and Print Format.

Explanation: You selected to ADD a print definition. On the previous panel, you must select option 1, Identification. Option 1 allows you to specify the printer location and print format for the new print definition.

Module: ICQAPM20

ICQAP083 If Last Line is specified, First Line is required.

Explanation: When specifying lines to be printed, you typed a number in the Last Line field but did not type a number in the corresponding First Line field. To correct your entry, type in the First Line field the number of the line where you want printing to begin.

Module: ICQAPE55

ICQAP084 If To Column is specified, From Column is required.

Explanation: When specifying columns to be printed, you typed a number in the To Column field but did not type a number in the corresponding From Column field. To correct your entry, type in the From Column field the number of the column where you want printing to begin.

Module: ICQAPE56

ICQAP085 Type a number greater than zero at the cursor position.

Explanation: On the previous panel, type a number greater than zero in the field where the cursor is positioned.

Module: ICQAPE56

ICQAS100 Specify one of the listed actions.

Explanation: You did not select a valid option from the list. The request must be one of the displaced items. For example, if the actions listed are:

- E - Edit
- B - Browse
- C - Copy
- D - Delete

and you choose to browse, then you must enter a 'B' in the action column next to the entry you want to browse.

Module: ICQASRP1

ICQAS101 Do not specify more than one action.

Explanation: You specified more than one entry on which to perform an action.

User response: Place only one action character in the action column.

Module: ICQASE02, ICQASE16

ICQAS102 Name the system data file to administer.

Explanation: A system data file name was not entered.

User response: Enter a valid system data file. This file must be a VSAM key-sequenced data set. To obtain a list of system data file names, you may enter an * after a file name qualifier. For example: SYS1.* displays a list of data sets beginning with SYS1.

Module: ICQASE02, ICQASE04, ICQASE08, ICQASE10, ICQASE12, ICQASE28, ICQASE30, ICQASE32, ICQASE72, ICQASE74, ICQASE76, ICQASE98

ICQAS103 APPC administration is currently in operation. Press HELP.

Explanation: You have attempted to initiate a second APPC/MVS administration session (for example, using split screen mode). Only one active session per user is allowed at a time.

Module: ICQASRM0

ICQAS400 An action must be requested from list of Side Information.

Explanation: No action or command was entered.

User response: You must specify an action:

- E - Edit
- B - Browse
- C - Copy
- D - Delete.

To add a new entry, you may enter 'A' on the command line.

Module: ICQASRP1

ICQAS401 The new Side Information identifications must differ from original.

Explanation: While copying side information, you did not change either the symbolic destination name or the "to" system data file name.

User response: Change the symbolic destination name or the "to" system data file name to make this entry different from the source combination of symbolic destination name and system data file name.

Module: ICQASE76

ICQAS402 Side Information does not exist.

Explanation: No side information existed for the combination of the "current" system data file and symbolic destination name specified.

User response: Exit the panel and reselect side information administration to refresh the list.

Module: ICQASRS0

ICQAS403 Side Information already exists.

Explanation: The attempt to add or copy side information failed because the side information already exists for the specified combination of the "to" system data file and the symbolic destination name.

User response: Browse the existing side information entry and, if necessary, edit the entry or add a new entry under a unique combination of symbolic destination name and "to" system data file.

Module: ICQASRS0

ICQAS405 There is no Side Information in the system data file.

Explanation: No side information entries were found in the specified “current” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS410 Side Information has been added.

Explanation: Side information has been successfully added to the specified “to” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS411 Side Information has been added. Warning: Error freeing resources.

Explanation: Side information has been successfully added to the specified “to” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: If the user attempts new requests, they may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS412 Side Information has not been added. Operation not performed.

Explanation: During the addition of side information, an EXIT/END command was issued before the process was completed. The side information was not added to the specified “to” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS413 Side Information has not been added. System data file is full.

Explanation: The request to add side information failed because there is no more space in the specified “to” system data file.

User response: Check your installation VSAM procedures to increase the size of the system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS414 Side Information has not been added. Access denied.

Explanation: You lack the proper authorization to add side information to the specified “to” system data file.

User response: Contact your security administrator.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS420 Side Information has been copied.

Explanation: The side information has been successfully copied to the specified “to” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS421 Side Information has been copied. Warning: Error freeing resources.

Explanation: Side information has been successfully copied to the specified “to” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS422 Side Information has not been copied. Operation not performed.

Explanation: During the copy of side information, an EXIT/END command was issued before the process was completed. The side information was not copied to the specified “to” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS423 Side Information has not been copied. System data file is full.

Explanation: The request to copy side information failed because there is no more space in the specified “to” system data file.

User response: Check your installation VSAM procedures to increase the size of the system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS424 Side Information has not been copied. Access denied.

Explanation: You lack the proper authorization to copy side information to the specified “to” system data file.

User response: Contact your security administrator.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS430 Side Information has been updated.

Explanation: Side information has been successfully updated in the “current” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS431 Side Information has been updated. Warning: Error freeing resources.

Explanation: Side information has been successfully updated in the “current” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If the problems persists, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS432 Side Information has not been updated. Operation not performed.

Explanation: During the update of side information, an EXIT/END command was issued before the process was completed. The side information was not updated in the “current” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS433 Side Information has not been updated. System data file is full.

Explanation: The request to update side information failed because there is no more space in the “current” system data file.

User response: Check your installation VSAM procedures to increase the size of the system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS434 Side Information has not been updated. Access denied.

Explanation: You lack the proper authorization to update side information in the “current” system data file.

User response: Contact your security administrator.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS440 Side Information has been deleted.

Explanation: Side information has been successfully deleted from the “current” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS441 Side information has been deleted. Warning: Error freeing resources.

Explanation: Side information has been successfully deleted in the “current” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If the problems persists, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS442 Side Information has not been deleted. Operation not performed.

Explanation: During the update of side information, an EXIT/END command was issued before the process was completed. The side information was not deleted from the “current” system data file.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS443 Side Information has not been deleted. Access denied.

Explanation: You lack the proper authorization to delete side information in the “current” system data file.

User response: Contact your security administrator.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS450 Side Information could not be browsed. Access denied.

Explanation: You lack the proper authorization to browse side information in the “current” system data file.

User response: Contact your security administrator.

Module: ICQASRS0

Audience: Information Center Facility administrator

ICQAS500 An action must be requested from list of TP Profiles.

Explanation: No action or command was entered.

User response: You must specify an action:

- E - Edit
- B - Browse
- C - Copy
- D - Delete
- N - New Alias
- S - Activation Status.

To add a new entry, you may enter 'A' on the command line.

Module: ICQASRP1

ICQAS501 The TP Profile identification must differ from the original.

Explanation: You have not changed either the transaction program profile name, level, ID, or the "to" system data file, which represents the source of the copy.

User response: Change the transaction program profile name, level, ID, the "to" system data file, or all.

Module: ICQASRT1, ICQASE28

ICQAS502 Value must be YES or NO.

Explanation: A "YES", "Y", "NO", or an "N" are acceptable entries in this field.

Module: ICQASE08, ICQASE10, ICQASE28, ICQASE30, ICQASE32, ICQASE36, ICQASE38, ICQASE40, ICQASE44, ICQASE48, ICQASE52, ICQASE56, ICQASE64

ICQAS503 Generic Userid not valid when TP Schedule Type is STD.

Explanation: The Generic Userid field, (the transaction program "owner") must be blank when the transaction program schedule type is "STD".

Module: ICQASE10, ICQASE30, ICQASE38

ICQAS504 TP Profile does not exist.

Explanation: No transaction program profile exists for the combination of the "current" system data file and the specified transaction program profile name, level, and ID. The list of transaction program profiles may show entries that no longer exist because you do not have exclusive access to the "current" system data file.

User response: Exit the panel and reselect transaction program profile administration to refresh the list.

Module: ICQASRT0

ICQAS505 No TP Profiles in the system data file.

Explanation: There are no transaction program profile entries in the specified system data file.

Module: ICQASRT0

ICQAS506 TP Profiles already exists.

Explanation: The attempt to add or copy a transaction program profile failed because a profile already exists for the specified combination of the "to" system data file and transaction program profile identification (transaction program profile name, level, and ID).

User response: Browse the existing transaction program profile entry and, if necessary, edit the existing entry or add

a new entry under a unique combination of transaction program profile name, level, ID, and the “to” system data file.

Module: ICQASRT0

ICQAS507 List of Scheduler Classes is not available. Press HELP.

Explanation: The list of scheduler classes is empty.

User response: The information necessary to establish the scheduler class list is contained in the APPC/MVS administration defaults panel. See *z/OS TSO/E Customization* for adding scheduler classes to the defaults panel.

Module: ICQASRT1

ICQAS508 Scheduler Class list may be incomplete. Press HELP.

Explanation: One or more of the scheduler classes defined in the APPC/MVS administration defaults panel was not valid and was discarded.

User response: Check the APPC/MVS administration defaults panel to ensure that the list of scheduler classes is valid.

Module: ICQASRT1

ICQAS509 Value must be STD or MULTI.

Explanation: There are two valid transaction program schedule types, STD (standard) and MULTI (multitrans).

User response: Change the transaction program schedule type to either STD or MULTI.

Module: ICQASE10, ICQASE30, ICQASE38

ICQAS510 TP Profile has been added.

Explanation: A transaction program profile has been successfully added to the specified “to” system data file.

Module: ICQASRT0

ICQAS511 TP Profile has been added. Warning: Error freeing resources.

Explanation: A transaction program profile has been successfully added to the specified “to” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT0

ICQAS512 TP Profile has not been added. Operation not performed.

Explanation: During the addition of a transaction program profile, an EXIT/END command was issued before the process was completed. The transaction program profile was not added to the specified “to” system data file.

Module: ICQASRT0

ICQAS513 TP Profile has not been added. Access denied.

Explanation: You lack the proper authorization to add a transaction program profile to the specified “to” system data file.

User response: Contact your security administrator.

Module: ICQASRT0

ICQAS515 TP Profile has not been added. Syntax error was detected.

Explanation: In processing a request to add an ASCH transaction program profile to the specified “to” system data file, syntax errors were detected in the associated JCL.

User response: Browse your ISPF log data set for the specific error messages. Add the ASCH transaction program profile with syntactically correct JCL.

Module: ICQASRT0

ICQAS516 TP Profile has not been added. APPC is not present.

Explanation: APPC/MVS is not present and the REQAPPC variable was set to 0N. If REQAPPC is 0N, the APPC/MVS administration utility provides syntax checking of the JCL associated with an ASCH transaction program profile only when APPC/MVS is present; it rejects the profile when APPC/MVS is not present.

Note: This message is only issued when running MVS/SP 4.1.0.

User response: Set REQAPPC to 0FF to turn off syntax checking. It is suggested that the activation status be inactive.

Module: ICQASRT0

ICQAS517 TP Profile has not been added. System data file is full.

Explanation: The request to add a transaction program profile failed because there is no more space in the specified “to” system data file.

User response: Check your installation VSAM procedures to increase the size of the system data file.

Module: ICQASRT0

ICQAS518 TP Profile has been added but APPC is not present.

Explanation: The transaction program profile has been successfully added to the “to” system data file. However, because the APPC/MVS is not present, syntax checking was not performed.

Module: ICQASRT0

ICQAS520 TP Profile has been copied.

Explanation: The transaction program profile has been successfully copied to the “to” system data file.

Module: ICQASRT0

ICQAS521 TP Profile has been copied. Warning: Error freeing resources.

Explanation: A transaction program profile has been successfully copied to the specified “to” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT0

ICQAS522 TP Profile has not been copied. Operation not performed.

Explanation: During the copy of a transaction program profile, an EXIT/END command was issued before the process was completed. The transaction program profile was not copied to the specified “to” system data file.

Module: ICQASRT0

ICQAS523 TP Profile has not been copied. Access denied.

Explanation: You lack the proper authorization to copy an ASCH transaction program profile to the specified “to” system data file.

User response: Contact your security administrator.

Module: ICQASRT0

ICQAS525 TP Profile has not been copied. Syntax error was detected.

Explanation: In processing a request to copy an ASCH transaction program profile to the specified “to” system data file, syntax errors were detected in the associated JCL.

User response: Browse your ISPF log data set for the specific error messages. Copy the ASCH transaction program profile using syntactically correct JCL.

Module: ICQASRT0

ICQAS526 TP Profile has not been copied. APPC is not present.

Explanation: APPC/MVS is not present and the REQAPPC variable was set to 0N. If REQAPPC is 0N, the APPC/MVS administration utility provides syntax checking of the JCL associated with an ASCH transaction program profile only when APPC/MVS is present; it rejects the profile when APPC/MVS is not present.

Note: This message is only issued when running MVS/SP 4.1.0.

User response: Set REQAPPC to 0FF to turn off syntax checking. It is suggested that the activation status be inactive.

Module: ICQASRT0

ICQAS527 TP Profile has not been copied. System data file is full.

Explanation: The request to copy a transaction program profile failed because there is no more space in the specified “to” system data file.

User response: Check your installation VSAM procedures to increase the size of the system data file.

Module: ICQASRT0

ICQAS528 TP Profile has been copied but APPC is not present.

Explanation: The transaction program profile has been successfully copied to the “to” system data file. However, because the APPC/MVS is not present, syntax checking was not performed.

Module: ICQASRT0

ICQAS530 TP Profile has been updated.

Explanation: A transaction program profile has been successfully updated to the “current” system data file.

Module: ICQASRT0

ICQAS531 TP Profile has been updated. Warning: Error freeing resources.

Explanation: A transaction program profile has been successfully updated to the “current” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT0

ICQAS532 TP Profile has not been updated. Operation not performed.

Explanation: During the update of a transaction program profile, an EXIT/END command was issued before the process was completed. The transaction program profile was not updated to the “current” system data file.

Module: ICQASRT0

ICQAS533 TP Profile has not been updated. Access denied.

Explanation: You lack the proper authorization to update a transaction program profile to the “current” system data file.

User response: Contact your security administrator.

Module: ICQASRT0

ICQAS535 TP Profile has not been updated. Syntax error was detected.

Explanation: In processing a request to update a transaction program profile to the “current” system data file, syntax errors were detected in the associated JCL.

User response: Browse your ISPF log data set for the specific error messages. Update the ASCH transaction program profile using syntactically correct JCL.

Module: ICQASRT0

ICQAS536 TP Profile has not been updated. APPC is not present.

Explanation: APPC/MVS is not present and the REQAPPC variable was set to 0N. If REQAPPC is 0N, the APPC/MVS administration utility provides syntax checking of the JCL associated with an ASCH transaction program profile only when APPC/MVS is present; it rejects the profile when APPC/MVS is not present.

Note: This message is only issued when running MVS/SP 4.1.0.

User response: Set REQAPPC to 0FF to turn off syntax checking. It is suggested that the activation status be inactive.

Module: ICQASRT0

ICQAS537 TP Profile has not been updated. System data file is full.

Explanation: The request to update a transaction program profile failed because there is no more space in the “current” system data file.

User response: Check your installation VSAM procedures to increase the size of the system data file.

Module: ICQASRT0

ICQAS538 TP Profile has been updated but APPC is not present.

Explanation: The transaction program profile was successfully updated in the “current” system data file. However, because APPC/MVS is not present, syntax checking was not performed.

Module: ICQASRT0

ICQAS540 TP Profile has been deleted.

Explanation: The transaction program profile has been successfully deleted from the “current” system data file.

Module: ICQASRT0

ICQAS541 TP Profile has been deleted. Warning: Error freeing resources.

Explanation: A transaction program profile has been successfully deleted from the “current” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT0

ICQAS542 TP Profile has not been deleted. Operation not performed.

Explanation: During the deletion of a transaction program profile, an EXIT/END command was issued before the process was completed. The transaction program profile was not deleted from the “current” system data file.

Module: ICQASRT0

ICQAS543 TP Profile has not been deleted. Access denied.

Explanation: You lack the proper authorization to delete a transaction program profile in the “current” system data file.

User response: Contact your security administrator.

Module: ICQASRT0

ICQAS550 TP Profile Alias has been added.

Explanation: The transaction program profile alias has been successfully added to the “current” system data file.

Module: ICQASRT0

ICQAS551 Identification of TP Profile Alias and Existing Profile must differ.

Explanation: The combination of the transaction program profile name, level, and ID specified for the transaction program profile alias cannot be the same as the existing transaction program profile.

User response: Change the transaction program profile name, level, ID specified, or all for the transaction program profile alias.

Module: ICQASE68

ICQAS552 TP Profile Alias has been added. Warning: Error freeing resources.

Explanation: A transaction program profile alias has been successfully added to the “current” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT0

ICQAS553 TP Profile Alias has not been added. Operation not performed.

Explanation: During the addition of a transaction program profile alias, an EXIT/END command was issued before the process was completed. The transaction program profile was not deleted from the “current” system data file.

Module: ICQASRT0

ICQAS554 TP Profile Alias has not been added. Access denied.

Explanation: You lack the proper authorization to add a transaction program profile alias to the “current” system data file.

User response: Contact your security administrator.

ICQAS556 • ICQAS564

Module: ICQASRT0

ICQAS556 TP Profile Alias has not been added. Existing TP already an alias.

Explanation: The existing transaction program profile specified is already an alias for another transaction program profile. You cannot create an alias of a transaction program profile alias.

User response: Add an alias of the existing transaction program profile, not of its alias.

Module: ICQASRT0

ICQAS557 TP Profile Alias has not been added. Existing TP not found.

Explanation: The transaction program profile alias was not added because the existing transaction program profile that the user specified could not be found in the "current" system data file. The list of transaction program profiles may show entries that no longer exist because you do not have exclusive access to the specified system data file.

User response: Exit the panel and reselect transaction program profile administration to refresh the list.

Module: ICQASRT0

ICQAS558 TP Profile Alias already exists.

Explanation: The specified transaction program profile alias already exists.

User response: To add an alias, enter a transaction program profile name, level, or ID that is not already an entry in the "current" system data file.

Module: ICQASRT0

ICQAS559 TP Profile Alias has not been added. System data file is full.

Explanation: The request to add a transaction program profile failed because there is no more space in the specified "current" system data file.

User response: Check your installation VSAM procedures to increase the size of the system data file.

Module: ICQASRT0

ICQAS560 TP Profile could not be browsed. Access denied.

Explanation: You lack the proper authorization to browse a transaction program profile in the specified "current" system data file.

User response: Contact your security administrator.

Module: ICQASRT0

ICQAS562 JCL delimiter is not unique. Enter a unique delimiter.

Explanation: The APPC/MVS administration processing could not generate a unique JCL delimiter value for the JCL associated with the ASCH transaction program profile being processed.

User response: Enter a value that does not appear in the JCL stream. Allowable characters are: A-Z, 0-9, @, #, \$. Lowercase letters are converted to uppercase.

Module: ICQASRF0

Audience: Information Center Facility administrator

ICQAS564 Trans. Sched. Delimiter not unique. Enter a unique delimiter.

Explanation: APPC/MVS administration processing could not generate a unique transaction scheduler delimiter for the scheduler data of the transaction program profile being processed.

User response: Enter a value that does not appear in the scheduler data. Allowable characters are: A-Z, 0-9, @, #, \$. Lowercase letters are converted to uppercase.

Module: ICQASRF0

Audience: Information Center Facility administrator

ICQAS565 Warning: REQAPPC is OFF. Press HELP for more information.

Explanation: The requirement for APPC/MVS to be present has been set to OFF. If REQAPPC is set to OFF, Add, Copy, and Edit of an ASCH transaction program will be performed with no syntax checking of the associated JCL.

Note: This message is only issued when running MVS/SP 4.1.0.

User response: You may continue with the unchecked JCL syntax or change the setting of REQAPPC by issuing the following line command: REQAPPC ON.

Module: ICQASRT1

Audience: Information Center Facility administrator

ICQAS566 Value must be ALWAYS, ERROR, or NEVER

Explanation: This value represents the disposition of the transaction program message log. The Keep Message Log values are defined as the following:

ALWAYS

Generate a message log entry for all output

ERROR

Generate a message log entry for errors associated with transaction program execution

NEVER

Do not generate any log entries.

User response: Enter ALWAYS, ERROR, or NEVER in the Keep Message Log field.

Module: Many Information Center Facility panels.

ICQAS567 Value must be OLD, NEW, or MOD.

Explanation: Data Set Status values are defined as the following:

OLD Data set is an existing file. Records written to this file will overwrite existing records.

NEW Data set is being created. Records are written to a fresh file.

MOD Data set is an existing cataloged file. New records that are written to this file will be appended after the existing records.

User response: Enter OLD, NEW, or MOD in the Data Set Status field.

Module: Many Information Center Facility panels.

ICQAS568 Value must be ACTIVE or INACTIVE

Explanation: This value represents the disposition of the transaction program as to whether it can be accessed and run. The Active Status values are defined as the following:

ACTIVE

The transaction program can be accessed and run.

INACTIVE

The transaction program cannot be accessed and run due to problems within the transaction program or in the resources it uses.

User response: Enter ACTIVE or INACTIVE in the New Status field.

Module: ICQASE70

ICQAS570 TP Profile Alias has been deleted.

Explanation: The transaction program profile has been successfully deleted from the specified “current” system data file.

Module: ICQASRT0

ICQAS571 TP Profile Alias has been deleted. Warning: Error freeing resources.

Explanation: A transaction program profile has been successfully deleted from the “current” system data file. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT0

ICQAS572 TP Profile Alias has not been deleted. Operation not performed.

Explanation: During the deletion of a transaction program profile, an EXIT/END command was issued before the process was completed. The transaction program profile was not deleted from the “current” system data file.

Module: ICQASRT0

ICQAS573 TP Profile Alias has not been deleted. Access denied.

Explanation: You lack the proper authorization to delete a transaction program profile from the specified “current” system data file.

User response: Contact your security administrator.

Module: ICQASRT0

ICQAS575 TP Profile and one TP Profile Alias have been deleted.

Explanation: The transaction program profile and one transaction program profile alias have been successfully deleted from the specified “current” system data file.

Module: ICQASRT0

ICQAS576 TP Profile and *alias_number* TP Profile Aliases have been deleted.

Explanation: The transaction program profile and *alias_number* aliases have been successfully deleted from the specified “current” system data file.

Module: ICQASRT0

ICQAS580 Scheduler Data could not be browsed. System failure.

Explanation: Scheduler data could not be browsed because a severe error occurred during the attempt to enter an ISPF browse session against the data set containing the scheduler data.

User response: You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT2

ICQAS581 No scheduler data available.

Explanation: Scheduler data could not be browsed because there is no scheduler data associated with the specified transaction program profile.

Module: ICQASRT2

ICQAS582 Scheduler Data could not be updated. System failure.

Explanation: Scheduler data could not be updated because a severe error occurred during the attempt to enter an ISPF edit session against the data set containing the scheduler data.

User response: You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT2

ICQAS583 JCL Data could not be browsed. System failure.

Explanation: JCL data could not be browsed because a severe error occurred during the attempt to enter an ISPF browse session against the data set containing the JCL.

User response: You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRT1

ICQAS584 No JCL data available.

Explanation: The JCL data could not be browsed because there is no JCL associated with this transaction program profile.

Module: ICQASRT1

ICQAS585 JCL Data could not be updated. System failure.

Explanation: JCL data could not be updated because a severe error occurred in the attempt to enter an ISPF edit session against the data set containing the JCL.

Module: ICQASRT1

Audience: Information Center Facility administrator

ICQAS590 Message data set entered incorrectly. Press HELP.

Explanation: You have entered the data set name incorrectly.

User response: Enter a valid data set name. The default value for the message data set is *&SYSUID*. *&SYSWUID*.JOBLOG, where *&SYSUID* and *&SYSWUID* are system variables.

No quotes are allowed. You may enter *&SYSUID* only as the first qualifier and *&SYSWUID* only as the second or third qualifier. No other system variables are allowed.

Module: Many Information Center Facility panels.

ICQAS591 Press ENTER to finalize the *action* operation.

Explanation: You have entered all of the information necessary to Add, Copy, or Edit a transaction program profile and are now asked to confirm this request.

User response: Press ENTER to confirm the request or press EXIT/CANCEL to nullify the request.

Module: ICQASRT0 ICQASRT1

Audience: Information Center Facility administrator

ICQAS592 A data set list is not available for this field.

Explanation: The specification of an "*" implies a request for a data set list. Data set lists are not available for the specification of the Other Partitioned Or Sequential Data Set field.

User response: Enter a valid data set name.

Module: ICQASE20

ICQAS593 The Transaction Scheduler value *scheduler_value* is not supported.

Explanation: The specified transaction scheduler has not been defined to APPC/MVS administration. The list of valid transaction schedulers and corresponding scheduler exits is contained in the APPC/MVS administration defaults panel.

User response: Either use a defined transaction scheduler or modify the APPC/MVS administration defaults panel to include the new transaction scheduler and its corresponding scheduler exit.

Module: ICQASRP2

Audience: Information Center Facility administrator

ICQAS594 TP Profile contains the unsupported scheduler exit *exit_name*.

Explanation: The specified scheduler exit has not been defined to APPC/MVS administration. The specified transaction program profile was entered into the system data file using a scheduler exit that is not presently defined to APPC/MVS administration. The list of valid transaction schedulers and corresponding scheduler exits is contained in the APPC/MVS administration defaults panel. Using the specified transaction program profile as the source of a copy or edit will fail.

User response: Either use a different transaction program profile or modify the APPC/MVS administration defaults panel to include the needed transaction scheduler and its corresponding scheduler exit.

Module: ICQASRT0

Audience: Information Center Facility administrator

ICQAS596 Requested action is not allowed on a TP Profile Alias.

Explanation: The selected transaction program profile is a transaction program profile alias and the only allowable requests are:

- B - Browse
- D - Delete

User response: Change the requested action or select a different transaction program profile.

Module: ICQASRT0

Audience: Information Center Facility administrator

ICQAS700 Database Token is not available.

Explanation: The retrieval of the data base token associated with the specified system data file failed. A data base token is defined when the system data file is created. The system data file might not have a data base token defined for it.

User response: Check your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRM0

Audience: Information Center Facility administrator

ICQAS701 Database Token could not be updated.

Explanation: The request to modify the data base token value associated with the specified system data file failed. A data base token is defined when the system data file is created. The system data file might not have a data base token defined for it or you may lack the authority to change the data base token.

User response: Check your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRM0

Audience: Information Center Facility administrator

ICQAS900 A list is not available for this field.

Explanation: The "*" implies a request for a list of allowable values. No list of values is available for this field.

User response: Enter a valid value.

Module: ICQASE10, ICQASE12, ICQASE30, ICQASE32, ICQASE38, ICQASE40, ICQASE74, ICQASE76, ICQASE80, ICQASE90, ICQASE94, ICQASE98

ICQAS901 List is to be refreshed, take no action at this time.

Explanation: A new system data file name has been entered and validated. The current list is associated with the "old" system file. Entries showing on the list are from the previous system data file. An action against one of these entries is not valid.

User response: Press ENTER on the previous panel to allow the list to be refreshed.

Module: ICQASRP1

Audience: Information Center Facility administrator

ICQAS903 Operation failure. System errors in APPC Administration Utility.

Explanation: A severe error has occurred in the APPC/MVS administration utility causing a system failure.

User response: You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRM0, ICQASRS0, ICQASRT0

ICQAS904 Request succeeded. Warning: Error freeing resources.

Explanation: A request was successful. However, an error occurred in the APPC/MVS administration utility while freeing storage or data sets.

User response: New requests may fail. You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRM0, ICQASRT0

ICQAS906 Enter the required value.

Explanation: The field cannot remain blank. Processing requires an entry for this field.

User response: Enter a valid value for this field. The on-line HELP for the panel will describe the allowable characters for this field.

Module: ICQASE08, ICQASE10, ICQASE28, ICQASE30, ICQASE38, ICQASE68, ICQASE74, ICQASE76, ICQASE80, ICQASE90, ICQASE94

ICQAS907 This is not an allowable value. Press HELP.

Explanation: One or more of the characters entered in this field is not valid.

User response: Enter a valid value. The on-line HELP for the panel describes the valid characters for this field.

Module: ICQASERP1, ICQASERP2

ICQAS910 Request failed; system error related to filename file.

Explanation: A problem occurred while attempting to write to this file, causing a system error. The request failed.

User response: You can exit APPC/MVS administration and try again. If problems persist, contact your system programmer.

Module: ICQASRM0, ICQASRS0, ICQASRT0

ICQAS912 Incorrect subset information specified

Explanation: The subset character (*) was used incorrectly.

User response: If you want to generate a list of system files, enter the first qualifier and a "." or a partial qualifier with an "*" suffix. For example: SYS1.* or SYS1.PARM*

If you are attempting to generate a list of side information or transaction program profiles, enter the subset character as the suffix character after a partial name. For example: TPNA*

Module: ICQASE02, ICQASE04, ICQASE08, ICQASE10, ICQASE12, ICQASE28, ICQASE30, ICQASE32, ICQASE72, ICQASE74, ICQASE76, ICQASE98

ICQAS914 Operation failed. System error in APPC Administration.

Explanation: A system error in APPC/MVS administration occurred.

User response: You can exit APPC/MVS administration and try again. If problems persist, contact your system programmer.

Module: ICQASRF0, ICQASRM0, ICQASRP1, ICQASRP2, ICQASRT1

ICQAS915 * Press ENTER to confirm delete request *****

Explanation: You have entered all of the information necessary to delete an entry and are now asked to confirm the request.

User response: Press ENTER to confirm the request or press EXIT/CANCEL to nullify the delete request.

Module: ICQASRS0, ICQASRT0

ICQAS916 Selected data set is not a VSAM data set

Explanation: The specified system data file must be a VSAM key-sequenced data set.

User response: Enter or select another file. To obtain a list of file names, enter the first qualifier and a "." followed by either an "*" or a partial name with an "*" suffix. For example: SYS1.*

Module: ICQASRM0, ICQASRP1, ICQASRP2, ICQASRP3, ICQASRT1

ICQAS918 Do not specify a member for a VSAM data set.

Explanation: A VSAM key-sequenced data set cannot have a member.

User response: Enter or select another file with no member specified. The system data file must be a VSAM key-sequenced data set. To obtain a list of file names, enter the first qualifier and a "." followed by either an "*" or a partial name with an "*" suffix. For example: SYS1.*

Module: Many Information Center Facility panels.

ICQAS921 Enter an "S" to select one of the listed options.

Explanation: "S" is the selection value recognized.

User response: Enter one "S" to the side of the option you want.

Module: ICQASRP1

Audience: Information Center Facility administrator

ICQAS922 filetype file could not be allocated.

Explanation: Allocation of the file specified failed.

User response: Exit APPC/MVS administration. Check to see if *user_prefix.TEMP.filetype* already exists. If the data set does exist, delete it and try to re-enter APPC/MVS administration. If problems persist, contact your system programmer.

Module: ICQASRM0, ICQASRT0

ICQAS923 System data file does not exist.

Explanation: The specified system data file does not exist.

User response: Enter or select another file. To obtain a list of file names, enter the first qualifier and a "." followed by either an "*" or a partial name with an "*" suffix. For example: SYS1.*

Module: ICQASRM0, ICQASRP1, ICQASRP2, ICQASRS0, ICQASRT0, ICQASRT1

ICQAS924 System data file could not be allocated.

Explanation: The system data file could not be allocated.

User response: Verify that there are no conflicting allocations against the specified system data file.

Module: ICQASRM0, ICQASRS0, ICQASRT0

ICQAS927 Note: APPC Administration uses your ISPF log. Press HELP.

Explanation: The APPC/MVS administration utility generates output in the form of messages and echo lines for each operation. After each operation, APPC/MVS administration copies these messages and echo lines to your ISPF log data set. This log data set is not allocated at this time.

User response: To browse this log, you may split the screen and choose ISPF option 7.5, Dialog Test - Log.

Module: ICQASRM0

ICQAS928 Update failed. Original data was lost. Press HELP.

Explanation: An edit request consisted of the deletion of data followed by the addition of the updated data. The operation failed after the deletion of original data.

User response: Browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRS0, ICQASRT0

ICQAS930 Request succeeded. Warning: Error reallocating system data file.

Explanation: The request to Add or Copy to a system data file that is not the "current" system data file was successful. However, the reallocation of the current system data file failed.

Module: ICQASRS0, ICQASRT0

ICQAS931 Severe error from APPC administration utility.

Explanation: A severe error has occurred in the APPC/MVS administration utility while processing this request.

User response: You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRS0, ICQASRT0

ICQAS932 Unrecognized error from APPC administration utility.

Explanation: An error has occurred in the APPC/MVS administration utility which could not be interpreted by APPC/MVS administration.

User response: You can exit APPC/MVS administration and try again. If problems persist, browse your ISPF log data set for more detailed messages and contact your system programmer.

Module: ICQASRS0, ICQASRT0

ICQAS933 • ICQAS939

ICQAS933 Access denied to system data file.

Explanation: You lack the authorization to access the specified data file.

User response: Contact your security administrator.

Module: ICQASRM0, ICQASRS0, ICQASRT0

ICQAS934 Quotes are not valid for the system data file.

Explanation: You have entered the system data file name with quotes surrounding it. Quotes are not allowed.

User response: Enter the system data file without quotes.

Module: Many Information Center Facility panels.

ICQAS935 Command conflict. *command* not processed.

Explanation: One of the listed actions and a command may be processed, but not both at the same time.

User response: Select an action or enter a command.

Module: ICQASRP1

ICQAS936 Select a Scheduler Class and press ENTER. To exit, press END.

Explanation: You pressed ENTER on the scheduler class selection list panel without making a selection.

User response: Select a scheduler class by typing "S" next to the scheduler class and press ENTER. To cancel out of the selection list, press END.

Module: ICQASRP1

ICQAS937 No selection made.

Explanation: You pressed END to cancel out of a scheduler class or data set selection list. You did not make a selection.

User response: Either redisplay a selection list and make a selection or:

- For scheduler class: Enter a scheduler class value or proceed without a scheduler class value for the transaction program profile.
- For system file: Enter a data set name.

Module: ICQASRP1, ICQASRP3

ICQAS938 *command* is not valid on the command line of this panel.

Explanation: The specified entry on the command line is not valid.

User response: Either blank out the entry on the command line or enter a valid command.

Module: Many Information Center Facility panels.

ICQAS939 Command conflict. EXIT not Processed.

Explanation: You entered a command on the command line and then pressed EXIT.

User response: Either enter a command on the command line and press ENTER, or blank out the command and press EXIT.

Module: Many Information Center Facility panels.

ICQCA000 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not create your private names library. The ISPF ALLOCATE or ISPF TBCREATE service routine set a non-zero return code.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAC00

ICQCA001 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not allocate your private names library to a file. The ALLOCATE service routine set a non-zero return code.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAC00

ICQCA002 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not access your private names directory. The ISPF TBOPEN service routine set a return code of 20.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAC00

ICQCA003 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not access the master names directory. The ISPF TBOPEN service routine set a return code of 20.

User response: Contact an Information Center Facility administrator or a system programmer to resolve the problem.

Module: ICQCAC00

ICQCA004 The master directory has been updated.

Explanation: The updates you made have now been saved in the master names directory. This message is informational only.

Module: ICQCAC00

ICQCA005 The private directory is in use. Try later. ICQCA005

Explanation: Your request failed, because your private names directory is temporarily in use. The ISPF TBOPEN service routine set a return code of 12, indicating that the table is already open and someone else is using it.

Press the END PF key to cancel the request and try again later.

Module: ICQCAL06

ICQCA006 Previously postponed updates copied into master directory.

Explanation: When you or another administrator last attempted to update the master directory, the system could not copy the updates and, therefore, postponed them. The updates that were previously postponed have now been copied into the master names directory. This message is informational only.

Module: ICQCAC00

ICQCA007 • ICQCA014

ICQCA007 Names directory is already in use. Try later.

Explanation: Your request failed, because the names directory is in use. Another application might be updating the master update table. Try again later.

Module: ICQCAL06

ICQCA008 Request failed; system error. Get help.

Explanation: Your request failed, because the Information Center Facility could not create the master update table, which it uses to save the updates being made to the master directory. The ISPF TBCREATE service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC00

ICQCA009 Names directory already in use by *user_id*. Try later.

Explanation: Your request failed, because the administrator identified in the message is already using the master names directory. Try again later.

Module: ICQCAL06

ICQCA010 Request failed; system error. Press HELP.

Explanation: The table library that contains the master names table is not allocated. It is normally allocated during logon processing. The ISPF TBCREATE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC00

ICQCA011 Request failed; system error. Get help.

Explanation: Your request failed, because the Information Center Facility could not access the master ENQ table. The ISPF TBOPEN service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC00

ICQCA012 Previous updates by *user_id* incomplete.

Explanation: The previously postponed updates that were made by the Information Center Facility administrator identified in the message could not be copied into the master directory.

User response: Press the END PF key to cancel the request and try again later, or contact a system programmer to resolve the problem.

Module: ICQCAL06

ICQCA013 Directory in use. To retry, reselect; to postpone, END.

Explanation: Your request failed, because the master ENQ table is temporarily in use. To retry the request, make the selection again; to postpone, press the END PF key.

Module: ICQCAL06

ICQCA014 Unable to update master directory; updates postponed.

Explanation: The updates could not be saved in the master names directory. The Information Center Facility will attempt to make the updates when an administrator enters the names service again and selects one of the options (NAMES, GROUPS, or REQUESTS). This message is informational only.

Module: ICQCAC00

ICQCA015 Request failed; system error. Press HELP.

Explanation: An error occurred while the Information Center Facility was trying to create the master names directory. The ISPF TBSAVE routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC00

ICQCA016 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not create the master ENQ table. The ISPF TBSAVE service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC00, ICQCAC10, ICQCAC20, ICQCAC30

ICQCA017 Request failed; system error. Press HELP.

Explanation: Your request failed, because the table library that contains the name directory tables is not allocated. It is normally allocated during logon processing. The ISPF TBCREATE service routine set a return code of 16.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC00

ICQCA018 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not create the update requests table. The ISPF TBCREATE routine set a return code of 20.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC00

ICQCA019 The master NAMES.TEXT data set is updated.

Explanation: You chose option 4 to update the master NAMES.TEXT data set. The Information Center Facility used the information from the master names directory to update the master NAMES.TEXT data set. The update was successful.

It is important to update the master NAMES.TEXT data set whenever the master names directory is updated, because the TRANSMIT and RECEIVE command might use the information in the master NAMES.TEXT data set.

This message is informational only.

Module: ICQCAC00

ICQCA100 Specified_selection_character is not valid. Type V, M, or D.

Explanation: The only valid selection characters are:

- V** to view more information about the name
- M** to modify the name
- D** to delete the name from the master directory

To view, modify, or delete a name, type V, M, or D to the left of the name, and press the ENTER key.

To add a name, type A on the COMMAND line.

Module: ICQCAC10

ICQCA101 *Specified_selection_character* is not valid. Type V, M, D, or C.

Explanation: The only valid selection characters are:

- V to view more information about the name
- M to modify the name
- D to delete the name from your private directory or request to delete it from the master directory
- C to request that an administrator copy the name from your private directory into the master directory

To view, modify, delete, or copy a name, type V, M, D, or C to the left of the name, and press the ENTER key.

To add a name, type A on the COMMAND line.

Module: ICQCAC10

ICQCA103 To update both directories, type Y; to update private, N.

Explanation: The MASTER DIRECTORY field indicates whether you want to request that an Information Center Facility administrator copy this update into the master names directory. Type either Y or N in that field.

To update your private directory and to send a request to update the master names directory, type Y in the MASTER DIRECTORY field. The Information Center Facility updates your private directory right away. When the administrator processes your request (accepts or rejects it), you receive a message to that effect. If your request is accepted, delete your copy of the name so that you will be able to use future master directory changes for this name.

To update only your private directory, type N in the MASTER DIRECTORY field.

Module: ICQCAE13, ICQCAE22, ICQCAE27

ICQCA104 DIRECTORY ID is not valid. Press HELP for rules.

Explanation: The directory ID you typed is not valid. It can contain one to seven alphanumeric characters (A-Z, 0-9, @, #, or \$), but the first must be A-Z, @, #, or \$.

Either correct the directory ID and press the ENTER key, or press the END PF key to cancel your request.

Module: ICQAAE10, ICQCAE10, ICQAAE13, ICQCAE13

ICQCA105 Type a directory ID in the DIRECTORY ID field.

Explanation: You must type a unique name in the DIRECTORY ID field. This information is required.

The directory ID can be used later as a TRANSMIT/RECEIVE nickname when using the TRANSMIT command.

Module: ICQAAE13, ICQCAE13

ICQCA106 *Specified_selection_character* is not valid. Type E, V, or M.

Explanation: The only valid selection characters are:

- E to enroll a user in the names directory
- V to view more information about the name
- M to modify the name

To select a name, type E, V, or M to the left of the name, and press the ENTER key.

Module: ICQCAC10

ICQCA107 Request only one action at a time.

Explanation: You cannot request to view (V), modify (M), or enroll (E) a name in the Information Center Facility at the same time you request to enroll (E) a new user in the names directory.

Either type V, M or E next to a name, or type E on the COMMAND line.

Module: ICQCAC10

ICQCA108 No names in the directory match the specified information.

Explanation: No names in the directory match the information you specified on the panel showing the search criteria. You should check:

- The spelling of the name and any other information you typed. If the information is incorrect, correct it and press the ENTER key.
- The private directory you are using to ensure it is the correct one. To find out which directory you are using, select the CHANGE option on the NAMES menu panel.

You can try searching both the master and the private directories by typing "BOTH" in the DIRECTORY field.

Module: ICQCAC10

ICQCA109 Request cancelled. The entry was not added to the directory.

Explanation: The name was not added to the directory, because you pressed the END PF key. Pressing that key cancels the request.

This message is informational only.

Module: ICQCAC10

ICQCA110 Request cancelled. The name was not modified in the directory.

Explanation: The name was not changed in the directory, because you pressed the END PF key. Pressing that key cancels the request. This message is informational only.

Module: ICQCAC10

ICQCA111 Select only one entry at a time.

Explanation: You can type only one selection character next to an entry in the list. Type one selection character, and press the ENTER key.

Module: ICQCAC10, ICQCAC20

ICQCA112 DIRECTORY ID already in master directory. Type a unique one.

Explanation: The name you specified in the DIRECTORY ID field already exists as the directory ID or group name for another name or group in the master directory. Duplicates are not allowed. Type a unique name, and press the ENTER key.

Module: ICQCAC10

ICQCA113 DIRECTORY ID already in private directory. Type a unique one.

Explanation: The name you specified in the DIRECTORY ID field has already been used as the directory ID or group name for another name or group in your private directory. Duplicates are not allowed. Type a unique name, and press the ENTER key.

Module: ICQCAC10

ICQCA116 The name was modified in the master directory.

Explanation: You typed M next to a master directory name, modified the name, and pressed the ENTER key. The modified name was saved in the master directory.

This message is informational only.

Module: ICQCAC10

ICQCA117 Name added to private directory; update request sent.

Explanation: The name was added to your private directory, and a request was sent to an administrator to add the name to the master directory.

This message is informational only.

Module: ICQCAC10

ICQCA118 The name was modified in the private directory.

Explanation: You typed M next to a private directory name, modified the name, left N (no update) in the MASTER DIRECTORY field, and pressed the ENTER key. The modified name was saved in the private directory.

This message is informational only.

Module: ICQCAC10

ICQCA121 The name was added to the master directory.

Explanation: The name has been added to the master directory as you requested.

This message is informational only.

Module: ICQCAC10

ICQCA122 Request cancelled. Name not deleted from the directory.

Explanation: The requested name was not deleted from the directory, because you pressed the END PF key on the panel for confirming the deletion.

This message is informational only.

Module: ICQCAC10

ICQCA123 The name was deleted from the master directory.

Explanation: To delete a master directory name, you typed D to the left of the name, and pressed the ENTER key. You then confirmed the deletion by pressing the ENTER key. You have deleted the name from the master directory.

This message is informational only.

Module: ICQCAC10

ICQCA124 Request cancelled. Delete request not sent.

Explanation: Your request to delete an entry from the master directory was not sent, because you typed CANCEL on the COMMAND line and pressed the ENTER key.

This message is informational only.

Module: ICQCAC10

ICQCA125 The name was deleted from the private directory.

Explanation: To delete a private directory name, you typed D to the left of a name marked with >, and pressed the ENTER key. You then confirmed the deletion by pressing the END PF key. You have deleted the name from your private directory.

This message is informational only.

Module: ICQCAC10

ICQCA126 Select only one user type.

Explanation: You can select only one user type. Type an S next to the user type you want, and press the ENTER key.

Module: ICQCAC10

ICQCA127 "C" is not valid for names already in the master directory.

Explanation: An entry that has a > to the left of it is a private directory entry; all others are master directory entries. You typed C next to a master directory name. You may not request to copy (C) a master directory entry into the master directory, because it is already there.

You can request that an administrator copy (C) a name from your private directory into the master directory, by typing C next to the private directory name.

Module: ICQCAC10

ICQCA128 Request sent to administrator for processing later.

Explanation: The Information Center Facility placed your request to update the master names directory on a list awaiting approval by the administrator. When the administrator processes the request (accepts or rejects it), you receive a message to that effect. This message is informational only.

Module: ICQCAC10

ICQCA129 Request failed; resource in use. Retry.

Explanation: Your request failed, because you and another Information Center Facility administrator are requesting to update the master directory at the same time. Try the update again.

Module: ICQCAC10, ICQCAC20

ICQCA130 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility cannot access the table that contains the list of requests. The ISPF TBCLOSE service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC10, ICQCAC20

ICQCA131 Type a last name in the LAST NAME field.

Explanation: You must type a last name in the LAST NAME field. This information is required.

Module: ICQCAE12

ICQCA132 Type user type or blanks in USER TYPE field.

Explanation: You typed * to see a list of user types. The Information Center Facility displayed the panel listing the user types, but you pressed the END PF key instead of selecting one of the user types for this name. You can do one of the following:

- Type a valid user type name in the USER TYPE field.
- Replace the * with a blank to bypass specifying a user type.

ICQCA133 • ICQCA140

- Press the ENTER key to see the list again.
- Press the END PF key to cancel the request.

Module: ICQCAC10

ICQCA133 Request only one action at a time.

Explanation: You cannot request to view (V), modify (M), or delete (D) a name at the same time you request to add (A) a name. Either type V, M, or D next to a name, or type A on the COMMAND line.

Module: ICQCAC10

ICQCA134 Request only one action at a time.

Explanation: You cannot request to view (V), modify (M), delete (D), or copy (C) a name at the same time you request to add (A) a name. Either type V, M, D, or C next to a name, or type A on the COMMAND line.

Module: ICQCAC10

ICQCA136 The name was added to the private directory.

Explanation: The requested name was added to the private directory, as you requested.

This message is informational only.

Module: ICQCAC10

ICQCA137 Update request sent; private directory modified.

Explanation: The requested entry was modified in your private directory and a request sent to the administrator to copy the changes into the master directory. When the administrator processes the request (either accepts or rejects it), you receive a message to that effect.

This message is informational only.

Module: ICQCAC10

ICQCA138 DIRECTORY ID not valid; * allowed only at end to get a list.

Explanation: To request a list of directory IDs, * can be appended to a part of the directory ID. Otherwise, the directory ID can contain one to seven alphanumeric characters (A-Z, 0-9, @, #, or \$), but the first must be A-Z, @, #, or \$. Correct the directory ID, and press the ENTER key.

Module: ICQAAE10, ICQCAE10

ICQCA139 User not enrolled. No user type specified in directory.

Explanation: The user was not enrolled because the USER TYPE field is blank. Request to modify the name by typing M to the left of it, and type a valid user type.

Module: ICQCAC10

ICQCA140 Request failed; system error. Press HELP.

Explanation: Your request failed, because the user types table does not exist. The ISPF TBOPEN service routine set a return code of 8. The table is normally created during installation.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC10

ICQCA141 Resource in use. To retry, press ENTER; to cancel, END.

Explanation: Your request failed, because the user types table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12. To retry your request, press the ENTER key; to cancel it, press the END PF key.

Module: ICQCAC10

ICQCA142 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not open the user types table. The ISPF TBOPEN service routine set a return code of 20.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC10

ICQCA143 Type a user ID in the USER ID field.

Explanation: You must type a user ID in the USER ID field. The user ID identifies the person to the Information Center Facility and can be up to seven characters. Type a valid user ID, and press the ENTER key.

Module: ICQAAE13

ICQCA144 Specify USER TYPE or press ENTER for list.

Explanation: Type a valid user type in the USER TYPE field. To see a list of valid user types, press the ENTER key.

Module: ICQCAC10

ICQCA145 User cannot be enrolled. No user ID in directory.

Explanation: The user cannot be enrolled because the USER ID field is blank. Request to modify the name by typing M to the left of it, and type a valid user ID.

Module: ICQCAC10

ICQCA146 User cannot be enrolled. The USER TYPE is not valid.

Explanation: The user cannot be enrolled because the user type in the user types table is not valid. You can either:

- Modify the name by typing M to the left of it, and typing a valid user type in the USER TYPE field.
- Invoke the user type function to define the user type.

Module: ICQCAC10

ICQCA147 Resource in use. To retry, press ENTER; to cancel, END.

Explanation: Your request failed, because the user types table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12. To retry your request, press the ENTER key. To cancel it, press the END PF key.

Module: ICQCAC10

ICQCA150 Name not modified; no changes made.

Explanation: You did not make any changes to the name, so it was not modified in the directory.

This message is informational only.

Module: ICQCAC10

ICQCA151 Type MASTER, PRIVATE, or BOTH in the DIRECTORY field.

Explanation: The information you typed in the DIRECTORY field is not valid. Type MASTER, PRIVATE, or BOTH to indicate whether you want to search the master directory, private directory, or both directories. BOTH is the default.

Module: ICQCAE10, ICQCAE20

ICQCA152 USER ID is not valid. Press HELP for rules.

Explanation: The user ID on the panel that displayed this message is not valid. You may have changed it on that panel or the previous panel. To continue, you must type a valid user ID containing one to seven characters (A-Z, 0-9, \$, @, #). The first character must be A through Z, \$, @, or #.

Module: ICQAAE13

ICQCA153 User cannot be enrolled. The user ID is not valid.

Explanation: You cannot enroll a user in the names directory unless the user ID is valid. You must modify the name in the names directory so that it contains a valid user ID, then retry enrolling that user.

Module: ICQCAC10

ICQCA200 Request cannot be sent; some entries do not exist in directory.

Explanation: You requested to copy a private directory group into the master directory. When you created the group, you used one or more master directory entries as entries in your private directory group. Since the time you created your group, one or more of the master directory entries in your group have been deleted from the master directory.

To find out which entries no longer exist in the directory, view your private directory group. You will see the directory IDs of the deleted entries with question marks in the other fields. If you delete these entries from your private directory group, then you will be able to send the copy request.

If you know what information the deleted groups contained, you can:

1. Modify your private directory group by deleting the entries that were deleted from the master directory, that is, those indicated by the question marks when you view the group.
2. Add the entries that were deleted from the master directory to your private directory and then to your private directory group. Entries must exist in the directory before they can be added to a group.
3. Type C to the left of your private directory group to copy it to the master directory. When you send the copy request, an administrator will also receive a request to add any entries in your group to the master directory if they do not already exist there.

Module: ICQCAC20

ICQCA201 No changes made. Group not added; no request sent.

Explanation: You requested to modify a master directory group, but made no changes. Therefore, no changes are made to the master directory and the group is not added to your private directory.

This message is informational only.

Module: ICQCAC20

ICQCA203 The group was modified in the master directory.

Explanation: You typed M next to a master directory group, modified the group, and pressed the END PF key. The modified group was saved in the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA204 The group was modified in the private directory.

Explanation: You typed M next to a private directory group, modified the group, left N (no update) in the MASTER DIRECTORY field, and pressed the END PF key. The modified group was saved in the private directory.

This message is informational only.

Module: ICQCAC20

ICQCA205 *Specified_group_name* already in master directory. Type a unique GROUP NAME.

Explanation: The name you typed in the GROUP NAME field already exists in the master directory as a group name or as a directory ID for a name. Type a unique group name, and press the ENTER key.

Module: ICQCAC20

ICQCA206 *Specified_group_name* already in private directory. Type a unique GROUP NAME.

Explanation: The name you typed in the GROUP NAME field already exists in your private directory as a group name or as a directory ID for a name. Type a unique group name, and press the ENTER key.

Module: ICQCAC20

ICQCA207 Request failed; system error. Press HELP.

Explanation: An error occurred while you were trying to modify a group in the master directory. The ISPF TBSAVE service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC20

ICQCA208 Request failed; system error. Press HELP.

Explanation: An error occurred while you were trying to modify a group in your private directory. The ISPF TBSAVE service routine set a non-zero return code.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAC20

ICQCA209 The group was deleted from the private directory.

Explanation: You typed D to the left of a private directory group (one marked with a >) and pressed the ENTER key. You then pressed the ENTER key again on the confirm deletion panel.

The group has been deleted from your private directory.

This message is informational only.

Module: ICQCAC20

ICQCA210 Group not deleted; system error. Press HELP.

Explanation: An error occurred while the Information Center Facility was trying to delete the requested group. The ISPF TBSAVE service routine set a non-zero return code.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAC20

ICQCA211 The group was not deleted from the private directory.

Explanation: The requested group was not deleted from your private directory, because you pressed the END PF key on the delete confirmation panel. Pressing that key cancels the request.

This message is informational only.

Module: ICQCAC20

ICQCA212 Group added to private directory; update request sent.

Explanation: You typed M next to a master directory group, modified the group, typed Y (yes, update) in the MASTER DIRECTORY field, and pressed the END PF key. The modified group was added to your private directory, and a request was sent to an administrator to update the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA213 Some group entries do not exist in the master directory.

Explanation: Some entries in the group you requested to view have been deleted from the master directory. For those entries, you see only the group name or directory ID of the entry with question marks in the other fields. The question marks indicate that the information is not available. Since the time you added these entries to your group, they have been deleted from the master directory.

You can delete those entries from your group or request that they be added again to the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA215 Specified_selection_character is not valid. To view an entry, type V.

Explanation: The only valid selection character is V. To view more information about an entry, type V to the left of the entry, and press the ENTER key.

Module: ICQCAC20, ICQCAC30

ICQCA216 No groups match the specified information.

Explanation: There are no groups that match the information you specified. You should check:

- The spelling of the information you typed. If the information is incorrect, correct it and press the ENTER key.
- The private directory you are using to ensure it is the correct one. To find out which directory you are using, select the CHANGE option on the NAMES menu panel.

Module: ICQCAC20

ICQCA217 The delete request was not passed to an administrator.

Explanation: You typed D to the left of a master directory group (one not marked with a >) and pressed the ENTER key. You then pressed the END PF key on the confirm deletion panel. Pressing the END PF key on that panel cancels the request.

This message is informational only.

Module: ICQCAC20

ICQCA218 The delete request was passed to an administrator.

Explanation: You typed D to the left of a master directory group (one not marked with a >) and pressed the ENTER key. You then pressed the ENTER key again on the confirm deletion panel.

The group has not yet been deleted from the master directory. An administrator will receive your deletion request, evaluate it, and accept or reject it. You will then receive a message describing the administrator's action.

This message is informational only.

Module: ICQCAC20

ICQCA219 Request failed; system error. Press HELP.

Explanation: An error occurred while the Information Center Facility was trying to invoke the names directory interface. The interface set a return code of *return_code*.

User response: Contact an Information Center Facility administrator or a system programmer to resolve the problem.

Module: ICQCAC20

ICQCA220 Copy request sent to administrator for processing later.

Explanation: You requested to copy a group from your private directory into the master directory. An administrator will receive your copy request, evaluate it, and accept or reject it. You will then receive a message describing the administrator's action.

If the group you requested to copy contains entries that do not exist in the master directory, then the Information Center Facility will send a request to an administrator to add those entries to the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA221 GROUP NAME is not valid. Press HELP for rules.

Explanation: The group name you typed is not valid. The group name can be one to seven alphanumeric characters (A-Z, 0-9, @, #, or \$), but the first must be A-Z, @, #, or \$. Correct the group name and press the ENTER key.

Module: ICQAAE27, ICQCAE27, ICQCAE28

ICQCA222 The group was added to the directory.

Explanation: The group you just created has been added to the directory.

This message is informational only.

Module: ICQCAC20

ICQCA223 Type the name of the group in the GROUP NAME field.

Explanation: You must type a group name in the GROUP NAME field. The group name can be one to seven alphanumeric characters (A-Z, 0-9, @, #, or \$), but the first must be A-Z, @, #, or \$. The information in the GROUP NAME field is required.

Module: ICQCAC20

ICQCA224 Request cancelled. The group was not added.

Explanation: The group was not added to the directory, because you typed CANCEL on the COMMAND line after beginning to create a group. Therefore, you canceled the addition request.

This message is informational only.

Module: ICQCAC20

ICQCA225 Request cancelled. The group was not modified.

Explanation: The group was not modified in the directory, because you typed CANCEL on the COMMAND line after you began to modify an existing group. Therefore, you canceled the modify request.

This message is informational only.

Module: ICQCAC20

ICQCA226 • ICQCA233

ICQCA226 The group was not added; it has no entries.

Explanation: The group was not added to the directory, because it does not contain any entries.

This message is informational only.

Module: ICQCAC20

ICQCA227 The entry is not in the names directory.

Explanation: You cannot view the entry, because it does not exist in the master directory.

Module: ICQCAC20, ICQCAC30

ICQCA228 "V" is not valid on a blank row.

Explanation: You cannot type V in the action field to the left of a blank row. Typing V indicates that you want to view more detailed information about what is described on that row.

Module: ICQCAC20

ICQCA229 *Specified_selection_character* is not valid. To view, type V; to delete, type D.

Explanation: You can type only V or D to the left of an entry. To view more information about an entry, type V. To delete an entry from the group, type D.

Module: ICQCAC20

ICQCA230 Group not added to private directory; it has no entries.

Explanation: You typed M next to a master directory group, left N (no update) in the MASTER DIRECTORY field, and deleted all the entries in the group. Because you deleted all the entries in the group, the Information Center Facility will not add it to your private directory.

The master directory group will not be changed.

This message is informational only.

Module: ICQCAC20

ICQCA231 Delete request sent; group not added to private directory.

Explanation: You typed M next to a master directory group, typed Y (yes, update) in the MASTER DIRECTORY field, and deleted all the entries in the group. Because you deleted all the entries in the group, the Information Center Facility will send a request to an administrator to delete the group from the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA232 No changes made to private directory; request not sent.

Explanation: You typed M next to a private directory group, typed Y (yes, update) in the MASTER DIRECTORY field, and pressed the END PF key. Because you made no changes to the group, the Information Center Facility made no changes to the private directory and sent no request to modify the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA233 Group not modified; no changes made.

Explanation: You typed M next to a master directory entry, but you did not modify the entry. Therefore, no changes were made to the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA234 Group deleted from the private directory; it had no entries.

Explanation: You modified a group in your private directory by deleting all the entries in it. Because you deleted all the entries in the group, that group will be deleted from your private directory.

This message is informational only.

Module: ICQCAC20

ICQCA235 Specified_selection_character is not valid. Type V, M, D or C.

Explanation: The only valid selection characters are:

- V to view the entries in a private directory group or a master directory group.
- M (beside a private directory group), to modify a group in your private directory. If you type Y in the MASTER DIRECTORY field, you also request to update the master directory.
- M (beside a master directory entry), to create a new private directory group that is a modified version of what is in the master directory group being modified. If you type Y in the MASTER DIRECTORY field, you also request to update the master directory.
- D (beside a private directory group), to delete the group from your private directory. If you type Y in the MASTER DIRECTORY field, you also request to delete the group from the master directory.
- D (beside a master directory group), to request that the group be deleted from the master directory.
- C (beside a private directory group), to copy a group from your private directory to the master directory.

Type V, M, D, or C to the left of one group at a time and press the ENTER key.

To add a group, type A on the COMMAND line.

Module: ICQCAC20

ICQCA236 Request cancelled. No entries were added to the group.

Explanation: No entries were added to the existing group, because you typed CANCEL on the COMMAND line of the panel for adding entries to a group.

This message is informational only.

Module: ICQCAC20

ICQCA238 No entries were added to the group.

Explanation: You typed A on the COMMAND line of the previous panel and pressed the ENTER key, so that you could add entries to an existing group. However, when you pressed the END PF key on the panel for adding the entries, the panel contained no entries. Type some information for the entries you want to add before you press the END PF key. If you want to add entries, the information for those entries must be displayed when you press the END PF key.

This message is informational only.

Module: ICQCAC20

ICQCA239 Update request sent; addition to private failed.

Explanation: Your request to copy the changes for the group into the master directory has been sent to an administrator, but the Information Center Facility encountered an error trying to add the modified copy of the group to your private directory. Your private directory is full. The ISPF TBSAVE service routine set a non-zero return code.

User response: Press the END PF key to cancel the request and contact an Information Center Facility administrator to resolve the problem.

ICQCA240 • ICQCA245

Module: ICQCAC20

ICQCA240 Request only one action at a time.

Explanation: You cannot request to view (V), modify (M), delete (D), or copy (C) a group at the same time you request to add (A) a group. Either type V, M, D, or C next to a group, or type A on the COMMAND line.

Module: ICQCAC20

ICQCA241 "C" is not valid for groups already in master directory.

Explanation: An entry that has a > to the left of it is a private directory entry; all others are master directory entries. You typed C next to a master directory group. You may not request to copy (C) a master directory entry into the master directory, because it is already there.

You can request that an administrator copy (C) a group from your private directory into the master directory, by typing C next to the private directory group.

Module: ICQCAC20

ICQCA242 Request only one action at a time.

Explanation: You cannot request to view (V), modify (M), or delete (D) a group at the same time you request to add (A) a group. Either type V, M, or D next to a group, or type A on the COMMAND line.

Module: ICQCAC20

ICQCA243 The group has *x number* entries; the maximum permitted is 254.

Explanation: Only 254 entries are permitted in a group. Group entries can be either names or other groups. You have tried to create a group with *x number* entries or enlarge an existing group to *x number* entries. To save the group, delete the extra entries.

To create groups that encompass more people, you can nest groups within groups. Each group can contain up to 254 entries, and subgroups can also contain 254 entries.

Module: ICQCAC20

ICQCA244 *Specified_selection_character* is not valid. Type V, M or D.

Explanation: The only valid selection characters are:

- V to view the entries in a master directory group
- M to modify the group in the master directory
- D to delete the group from the master directory

Type V, M, or D to the left of the group, and press the ENTER key.

To add a group, type A on the COMMAND line.

Module: ICQCAC20

ICQCA245 The group was deleted from the master directory.

Explanation: You typed D to the left of a group and pressed the ENTER key. You then pressed the ENTER key again on the confirm deletion panel.

The group was deleted from the master directory. No other groups in the master directory contained the deleted group. If any private directory group(s) contained a reference to the deleted group, the reference will be replaced with the words DIRECTORY ID = *deleted_group_name* in the LAST OR GROUP NAME field, and all other fields will be filled with question marks.

This message is informational only.

Module: ICQCAC20

ICQCA246 The group was not deleted from the master directory.

Explanation: You typed D to the left of a group and pressed the ENTER key. You then pressed the END PF key on the confirm deletion panel. Pressing the END PF key on that panel cancels the deletion.

This message is informational only.

Module: ICQCAC20

ICQCA247 The duplicate entries were not added to the group.

Explanation: One or more of the entries you tried to add to the group were already in the group. The system checks the directory IDs or group names to see what members are already in the group.

This message is informational only.

Module: ICQCAC20

ICQCA248 Duplicate entries have been deleted.

Explanation: You asked to add the same entry to the group more than once. Any duplicate requests have been deleted, and the entry will be added to the group only once.

Module: ICQCAC20

ICQCA249 Group deleted from the master directory; it had no entries.

Explanation: You modified a group in the master directory by deleting all the entries in it. Because you deleted all the members of the group, that group will be deleted from the master directory.

Module: ICQCAC20

ICQCA250 Group deleted from private directory; delete request sent.

Explanation: You typed M to the left of a private directory group (one marked with a >) and pressed the ENTER key. You then deleted all the entries in that group, typed Y in the MASTER DIRECTORY field, and pressed the END PF key.

The group was deleted from the private directory and a request to delete the group from the master directory has been sent to an administrator. The administrator will receive your request, evaluate it, and accept or reject it. You will then receive a message describing the administrator's action.

This message is informational only.

Module: ICQCAC20

ICQCA251 Request failed; system error. Press HELP.

Explanation: The Information Center Facility encountered an error while attempting to add a group to your private directory.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAC20

ICQCA252 No changes made to master directory; group added to private.

Explanation: The group you modified was a master directory entry. No change was made to the master directory, but the modified version of the group has been added to your private names directory.

This message is informational only.

Module: ICQCAC20

ICQCA254 The group has 254 entries which is the maximum number permitted.

Explanation: You typed M to modify a group and then typed A to add entries to the group. However, the group already contained the maximum number of entries permitted.

To create groups that encompass more people, you can have your group contain other groups, each with 254 entries.

Module: ICQCAC20

ICQCA255 The group and all references to it have been deleted.

Explanation: You typed D to the left of a private directory group (one marked with a >) and pressed the ENTER key. You then pressed the ENTER key again on the confirm deletion panel.

The group was deleted from the private directory. Other group(s) in the private directory contained references to the deleted group, and those references have also been deleted.

This message is informational only.

Module: ICQCAC20

ICQCA256 Group modified in private directory; update request sent.

Explanation: The group was modified in your private directory, and a request has been sent to an administrator to update the master directory.

If the administrator accepts your request and the group already existed in the master directory, the group will be modified in the master directory according to your specifications. If the administrator accepts your request and the group did not already exist in the master directory, it will be added.

Module: ICQCAC20

ICQCA257 Group deleted from private; references changed to master entry.

Explanation: You typed D to the left of a private directory group (one marked with a >) and pressed the ENTER key. You then pressed the ENTER key again on the confirm deletion panel.

The group was deleted from the private directory. Because there is a master directory group with the same GROUP NAME as the group you just deleted and because other groups in your private directory contained a reference to the group you just deleted, you had to decide whether you wanted to replace the references to the deleted group with the master directory group. You pressed the END PF key on the panel that prompted you for that decision. Pressing the END PF key replaces the references to the private directory group with references to the master directory group.

This message is informational only.

Module: ICQCAC10, ICQCAC20

ICQCA258 Group deleted from private directory; no request sent.

Explanation: You modified a group in your private directory by deleting all the entries in it. Because you deleted all the entries in the group, that group will be deleted from your private directory. However, no request to delete the group from the master directory will be sent.

This message is informational only.

Module: ICQCAC20

ICQCA259 The group and all references to it have been deleted.

Explanation: You typed D to the left of a group and pressed the ENTER key. You then pressed the ENTER key again on the confirm deletion panel.

The group was deleted from the master directory. Other group(s) in the master directory contained references to the deleted group, and those references have also been deleted. If any private directory group(s) contained a reference to the deleted group, the reference will be replaced with the words "DIRECTORY ID = the directory ID of the deleted group" in the LAST OR GROUP NAME field and all other fields will be filled with question marks.

This message is informational only.

Module: ICQCAC20

ICQCA260 Copy request not sent. *group_name* is imbedded in itself.

Explanation: You typed C next to a private directory group to request that the group be copied to the master directory. The Information Center Facility cannot send the copy request, because *group_name* contains *group_name* as an imbedded group. A group cannot contain itself.

An example of an imbedded group is:

- 1. Group A contains Group B and Group C
- 2. Group B contains Group A and Group D

Groups C and D contain only names, not other groups. Group A is the imbedded group.

To find out where your imbed occurs, view *group_name*. Then view the entries in *group_name* to find out which entry also contains *group_name*. Be careful how you solve this problem. In the example, deleting group A from Group B would permit you to send the copy request, but it might cause you problems later when you want to use Group B and you expect it to contain Group A.

Module: ICQCAC20

ICQCA261 Group not modified. *group_name* is imbedded in itself.

Explanation: You typed M to the left of a private directory group (one marked with a >) and pressed the ENTER key. You then changed some information about the group and typed Y in the MASTER DIRECTORY field. The group was modified in your private directory. However, the Information Center Facility cannot send a request to modify the group in the master directory, because the private directory group, *group_name*, contains *group_name* imbedded within itself. A group cannot contain itself. An example of a group imbedded in itself is:

- 1. Group A contains Group B and Group C
- 2. Group B contains Group A and Group D

Groups C and D contain only names, not other groups. Group A is the imbedded group.

To find out where your imbed occurs, view *group_name*. Then view the entries in *group_name* to find out which entry also contains *group_name*. Be careful how you solve this problem. In the example, deleting Group A from Group B would permit you to send a request to modify the master directory, but it might cause you problems later when you want to use Group B and you expect it to contain Group A.

Module: ICQCAC20

ICQCA262 No changes made to the private directory.

Explanation: You typed M next to a private directory group and left N (no update) in the MASTER DIRECTORY field, but you pressed the END PF key without modifying the group. Therefore, no changes are made to the private directory.

This message is informational only.

Module: ICQCAC20

ICQCA263 No changes made; group not added to private directory.

Explanation: You typed M next to a master directory group, left N (no update) in the MASTER DIRECTORY field, and pressed the END PF key. Ordinarily this would create a modified copy of the master directory group in your private directory, however you did not change any information about the group. The Information Center Facility does not copy the master directory group to your private directory, unless you change it. You should not need an exact copy of the master directory group in your private directory, because you have access to the master directory.

This message is informational only.

Module: ICQCAC20

ICQCA264 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility cannot access the table that contains the list of requests. The ISPF TBOPEN service routine set a return code greater than 12.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC20

ICQCA265 Group modified; request not sent. Some entries not in directory.

Explanation: You typed M to the left of a private directory group (one marked with a >) and pressed the ENTER key. You then changed some information about the group and typed Y in the MASTER DIRECTORY field.

The group was modified in your private directory, but the Information Center Facility cannot send a request to update the master directory. When you created or modified the group, you used one or more master directory entries. Since that time, those master directory entries have been deleted from the master directory.

The entries that have been deleted from the master directory are those that you saw on the panel for modifying a group. They contain question marks in all fields except the LAST OR GROUP NAME field. If you delete those entries from your private directory group, then you will be able to send your request.

If you know what information the deleted group(s) contained, you can add the groups to your private directory and then send a request to update the master directory.

Module: ICQCAC20

ICQCA266 Group added; request not sent. *group_name* imbedded in itself.

Explanation: You typed M to the left of a master directory group (one not marked with a >) and pressed the ENTER key. You then changed some information about the group and typed Y in the MASTER DIRECTORY field. The group was added to your private directory. However, the Information Center Facility cannot send a request to modify the group in the master directory, because the private directory group, *group_name*, contains *group_name* imbedded within itself. A group cannot contain itself.

An example of an imbedded group is:

- 1. Group A contains Group B and Group C
- 2. Group B contains Group A and Group D

Groups C and D contain only names, not other groups. Group A is the imbedded group.

To find out where your imbed occurs, view *group_name*. Then view the entries in *group_name* to find out which entry also contains *group_name*. Be careful how you solve this problem. In the example, deleting Group A from Group B would permit you to send a request to modify the master directory, but it might cause you problems later when you want to use Group B and you expect it to contain Group A.

Module: ICQCAC30

ICQCA267 Unable to access private directory. Press HELP.

Explanation: The ISPF TBCLOSE or TBCREATE service routine issued a non-zero return code. Errors were encountered while trying to obtain write access to the private directory.

System action: Processing terminates.

User response: Either correct the problem or contact your system programmer.

Module: ICQCAC00

ICQCA301 Resource in use. To retry, select REQUESTS and press ENTER.

Explanation: The update requests table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12. To retry, select the REQUESTS option again and press the ENTER key. To cancel the request and try later, press the END PF key.

Module: ICQCAC30

ICQCA302 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not open the unresolved update requests table, which contains the requests that you viewed but did not process. The ISPF TBOPEN routine set a return code of 20.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC30

ICQCA303 Resource in use. To retry, select REQUESTS and press ENTER.

Explanation: Your request failed, because another administrator is presently merging user requests. The ISPF TBOPEN service routine set a return code of 12. To retry, select the REQUESTS option on the first names directory panel. To cancel the request and try later, press the END PF key.

Module: ICQCAC30

ICQCA304 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not access the update requests table, which contains the requests that were added since the last time you viewed requests. The ISPF TBOPEN service routine set a return code of 20.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC30

ICQCA305 The entry is not in the master directory.

Explanation: The entry the user requested that you modify or delete does not exist in the master directory. The entry must exist in order for you to accept the request. You may have deleted the entry or changed the directory ID since the request was made. You can either reject the request, or add an entry with the same directory ID and then accept the request.

Module: ICQCAC30

ICQCA306 The directory ID is already in the master directory.

Explanation: An entry with a directory ID matching the directory ID of the name that the user requested you add is already in the master directory. You can either reject the request, or delete the existing entry and then accept the request. If you delete the existing entry, be sure to check all the information in both entries. Although the directory IDs match, the other information could be quite different.

Module: ICQCAC30

ICQCA307 Request cancelled. The entry was not deleted.

Explanation: You typed A in the action field to the left of a deletion request. However, on the panel for confirming the deletion, you pressed the END PF key. Pressing the END PF key cancels deletion of the entry from the directory.

This message is informational only.

Module: ICQCAC30

ICQCA308 The update was made to the master directory.

Explanation: The requested update has been made in the master directory.

This message is informational only.

Module: ICQCAC30

ICQCA309 *Specified_selection_character* is not valid. Type V, A, or R.

Explanation: The only valid selection characters are:

- V to view a request
- A to accept a request
- R to reject a request

Type V, A, or R to the left of one request, and press the ENTER key.

Module: ICQCAC30

ICQCA310 The group is not in the master directory.

Explanation: The group that the user asked to modify or delete does not exist in the master directory. You may have deleted the group or changed the name since the request was made. You can either:

- Reject the request.
- Add or change the group name, and then accept the request.

Module: ICQCAC30

ICQCA311 The directory ID is already in the master directory.

Explanation: An entry with a directory ID matching the group name that the user requested you add is already in the master directory.

You can either reject the request, or delete the existing entry and then accept the request. If you delete the existing entry, be sure to check all the information in both entries. Although the directory IDs match, the other information could be quite different.

Module: ICQCAC30

ICQCA312 Update request rejected; user notified.

Explanation: Because you typed R in the action field to the left of the update request, you rejected the request. Therefore, the master directory has not been updated. The user who requested the update will receive a message to that effect.

Module: ICQCAC30

ICQCA313 There are no update requests to process.

Explanation: There are no requests from users to update the master directory.

This message is informational only.

Module: ICQCAC30

ICQCA314 Request cannot be accepted; some entries not in directory.

Explanation: The request cannot be accepted, because some of the entries within the group are not in the master directory. Add those entries to the directory first, and then accept the request.

Module: ICQCAC30

ICQCA316 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not save the new update requests that were added to the unresolved update requests table. The ISPF TBSAVE service routine set a non-zero return code.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAC30

ICQCA320 Request to add *directory_id_or_group_name* was accepted.

Explanation: The administrator accepted your request to add an entry to the master directory.

This message is informational only.

Module: ICQCAC30

ICQCA321 Request to delete *directory_id_or_group_name* was accepted.

Explanation: The administrator accepted your request to delete an entry from the master directory.

This message is informational only.

Module: ICQCAC30

ICQCA322 Request to modify *directory_id_or_group_name* was accepted.

Explanation: The administrator accepted your request to modify an entry in the master directory.

This message is informational only.

Module: ICQCAC30

ICQCA323 Request to add *directory_id_or_group_name* was denied.

Explanation: The administrator denied your request to add an entry to the master directory.

This message is informational only.

Module: ICQCAC30

ICQCA324 Request to delete *directory_id_or_group name* was denied.

Explanation: The administrator denied your request to delete an entry from master directory.

This message is informational only.

Module: ICQCAC30

ICQCA325 Request to modify *directory_id_or_group name* was denied.

Explanation: The administrator denied your request to modify an entry in the master directory.

This message is informational only.

Module: ICQCAC30

ICQCA700 *Specified_selection_character* is not valid. To select an entry, type V or S.

Explanation: The only valid selection characters are:

V to view more information about an entry

S to select an entry

Type V or S to the left of an entry, and press the ENTER key.

Module: ICQCAE24, ICQCAE40 (or the panel specified on invocation)

ICQCA701 You can select only *maximum number* entry(s) at a time.

Explanation: You selected more items than allowed. Select no more than the number of items indicated in the message, and press the ENTER key.

Module: ICQCAL00

ICQCA710 No entries were selected from one or more lists.

Explanation: You requested one or more lists of entries, but did not select at least one entry from every list. Lists of entries are displayed, if you:

- Type part of a name or group followed by *.
- Type information about the name or group you are adding in the LAST OR GROUP NAME, FIRST OR NICKNAME, USERID, DEPARTMENT OR DESCRIPTION fields, and that information does not uniquely identify the individual or group.

When you see the list of entries, you can type S to the left of one or more entries to select additions for the new group. You do not have to select entries from the list. If you do not select an entry from the list, you must delete the LAST OR GROUP NAME, FIRST OR NICKNAME, USERID, and DEPARTMENT OR DESCRIPTION FIELDS.

Module: ICQCAL00

ICQCA711 Request cancelled. No processing was done.

Explanation: You requested a list of entries and then typed CANCEL on the COMMAND line. This message is informational only.

Module: ICQCAL00

ICQCA712 No directory entries match the specified information.

Explanation: The information you specified does not exist in the directory. You should check:

- The spelling of the name and any other information you typed. information you typed. If the information is incorrect, correct it and press the ENTER key.
- The private directory you are using to ensure it is the correct one. To find out which directory you are using, select the CHANGE option on the NAMES menu panel.

If you are trying to add entries to a group, the entries must exist in the directory before you add them to a group.

Module: ICQCAL00

ICQCA713 Request failed; system error. Press HELP.

Explanation: Your request failed, because the master names directory table is not allocated. The ISPF TBOPEN service routine set a return code of 16.

User response: Contact a system programmer to resolve the error.

Module: ICQCAL00

ICQCA714 Request failed; system error. Press HELP.

Explanation: Your request failed, because the master names directory table does not exist. The ISPF TBOPEN service routine set a return code of 8.

User response: Contact a system programmer to resolve the error.

Module: ICQCAL00

ICQCA715 Directory in use. To retry, press ENTER; to cancel, END.

Explanation: Your request failed, because the Information Center Facility could not open the master names directory table. This table is temporarily in use. The ISPF TBOPEN service routine set a return code of 12. To retry the request, press the ENTER key; to try later, press the END PF key.

Module: ICQCAL00

ICQCA716 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not open the master names directory table. The ISPF TBOPEN service routine set a return code of 20.

User response: Contact a system programmer to resolve the problem.

Module: ICQCAL00

ICQCA717 Request failed; system error. Press HELP.

Explanation: Your request failed, because the private names directory table is not allocated. The ISPF TBOPEN service routine set a return code of 16.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAL00

ICQCA718 Request failed; private directory is in use. Try later.

Explanation: Your request failed, because the private names directory you tried to access was temporarily in use. The ISPF TBOPEN service routine set a return code of 12, indicating that the table is already open. Someone else may be using the directory. You should make sure you are accessing the directory you want. To find out which directory you are using, select the CHANGE option on the NAMES menu panel.

Either end split screen use of the directory, or press the END PF key to cancel the request and try again later.

Module: ICQCAL00

ICQCA719 Request failed; system error. Press HELP.

Explanation: Your request failed, because the Information Center Facility could not open your private names directory. The ISPF TBOPEN service routine set a return code of 20.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCAL00

ICQCA720 A private directory entry with the same directory ID exists.

Explanation: A private directory entry with the same directory ID or group name exists, therefore you cannot select the master directory entry. You created the private directory entry by modifying a copy of the master directory entry. The Information Center Facility, therefore, lets the private entry take precedence over the master entry.

If you copied the entry into your private directory without modifying it, the private and master entries contain identical information. If you modified the master entry and copied it into your private directory, the private and master entries contain different information.

To select the master directory entry, you can either:

- Delete your private directory entry, or
- Change the directory ID or group name in the private directory entry.

Module: ICQCAL00

ICQCA721 None of the entries in the group are accessible.

Explanation: You tried to view or select a group, but the system cannot display any entries in that group. The group does contain entries, but the system cannot find them. This situation can occur when the following conditions are all present:

- You are trying to view or select a group from your private directory.
- The group you are trying to view or select contains only master directory entries.
- Either the master directory is not available, or the master directory entries in your private directory group have been deleted from the master directory.

ICQCA722 • ICQCA800

To view the group, select the NAMES option on the first Information Center Facility panel, and then select the GROUPS option on the first names directory panel.

Module: ICQCAL00

ICQCA722 The group contains entry(s) that are not accessible.

Explanation: You tried to view or select a group, but the system cannot find all the entries in that group. This situation can occur when the following conditions are all present:

- You are trying to view or select a group from your private directory.
- The group you are trying to view or select contains one or more master directory entries.
- Either the master directory is not available, or one or more of the master directory entries in your private directory group have been deleted from the master directory.

To view the group, select the NAMES option on the first Information Center Facility panel, and then select the GROUPS option on the first names directory panel.

Module: ICQCAL00

ICQCA731 A different private directory is in use. Press HELP.

Explanation: You have another private names directory in use and must close all names directories. To close all directories, do the following:

- Swap (PF9) to the other screen
- Display the first panel of the names directory (ICQCAM00)
- Select the CLOSE option (option 3)

When the directories have been closed in all the screens, you can return to the original screen and redefine a prefix for the private directory.

Module: ICQCAL06

ICQCA732 Type a valid directory prefix at the cursor position.

Explanation: To change the prefix of your private names directory to access a different directory, type a valid prefix in the PRIVATE DIRECTORY PREFIX field indicated by the cursor.

A valid prefix contains 1-8 characters, the first of which must be alphabetic or national. The remaining characters can be any combination of alphabetic (A-Z), numeric (0-9), or national (\$, #, @) characters.

Module: ICQCAE17

ICQCA733 Directories were successfully closed.

Explanation: The names directories were successfully closed.

Module: ICQCAC00

ICQCA734 Request failed; system error. Press HELP.

Explanation: The ISPF TBSTATS service failed with a return code of 20 for table *table_name*.

Module: ICQCAC00

ICQCA800 System error accessing nicknames file. Press HELP.

Explanation: If you are:

- A user, your updates have been saved. However the Information Center Facility also attempted to access the TRANSMIT/RECEIVE nicknames data set corresponding to your private directory, and this attempt failed. Contact an Information Center Facility administrator to resolve the problem.

- An administrator requesting to update the master TRANSMIT/RECEIVE nicknames data set, your request failed. Contact a system programmer to resolve the problem.

Module: ICQCACN1

ICQCA801 System error allocating nicknames file. Press HELP.

Explanation: If you are:

- A user, your updates have been saved. However the Information Center Facility also attempted to allocate the TRANSMIT/RECEIVE nicknames data set corresponding to your private directory, and this attempt failed. Contact an Information Center Facility administrator to resolve the problem.
- An administrator requesting to update the master TRANSMIT/RECEIVE nicknames data set, your request failed. Contact a system programmer to resolve the problem.

Module: ICQCACN1

ICQCA802 System error enlarging nicknames file. Press HELP.

Explanation: If you are:

- A user, your updates have been saved. However the Information Center Facility also attempted to enlarge the TRANSMIT/RECEIVE nicknames data set corresponding to your private directory, and this attempt failed. Contact an Information Center Facility administrator to resolve the problem.
- An administrator requesting to update the master TRANSMIT/RECEIVE nicknames data set, your request failed. Contact a system programmer to resolve the problem.

Module: ICQCACN1

ICQCA803 System error creating nicknames file. Press HELP.

Explanation: If you are:

- A user, your updates have been saved. However, the Information Center Facility also attempted to create a TRANSMIT/RECEIVE nicknames data set corresponding to your private directory, and this attempt failed. Contact an Information Facility Administrator to resolve the problem.
- An administrator requesting to update the master TRANSMIT/RECEIVE nicknames data set, your request failed. Contact a system programmer to resolve the problem.

Module: ICQCACN1

ICQCA804 System error allocating user's NAMES.TEXT file. Press HELP.

Explanation: If you are:

- A user, your updates have been saved. However, the Information Center Facility also attempted to allocate your NAMES.TEXT data set, and this attempt failed. Contact an Information Facility Administrator to resolve the problem.
- An administrator requesting to update the master TRANSMIT/RECEIVE nicknames data set, your request failed. The Information Center Facility failed to allocate your NAMES.TEXT file. Contact a system programmer to resolve the problem.

Module: ICQCACN1

ICQCA805 System error editing user's NAMES.TEXT file. Press HELP.

Explanation: If you are:

- One of three things has occurred: your NAMES.TEXT data set is in use, possibly on the other part of a split screen, or your NAMES.TEXT data set is full, or a system error occurred. If you are:
 - A user, your updates have been saved. However, the Information Center Facility also attempted to edit your NAMES.TEXT data set, and this attempt failed. Contact an Information Facility administrator if you cannot resolve the problem.

ICQCB000 • ICQCB006

- An administrator requesting to update the master TRANSMIT/RECEIVE nicknames data set, your request failed. The Information Center Facility failed to edit your NAMES.TEXT file. Contact a system programmer if you cannot resolve the problem.

Module: ICQCACN1

ICQCB000 Request failed; system error. Press HELP.

Explanation: The Information Center Facility was unable to display the list of courses. The table that contains the list does not exist. The ISPF TBOPEN service routine set a return code of 8.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

ICQCB001 Request failed; system error. Press HELP.

Explanation: The Information Center Facility is unable to access the table containing the list of courses. The ISPF TBOPEN service routine set a return code of *return_code*.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

ICQCB002 Request failed; system error. Get help.

Explanation: A severe error occurred when ISPF attempted to call *program_name*. ISPF set a return code of 20. The error might have occurred because the program is not in either a system execution library (for example LINKLIB or LPALIB), or a library concatenated with the ISPLLIB ddname.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

ICQCB003 Course information was changed since list was displayed.

Explanation: Between the time you selected the list and the present, an administrator has changed information about the course. If the change made by the administrator still allows your request to be honored, the system will honor the request. However, the change might cause a condition that makes it impossible to honor your request.

Module: ICQCBC00

ICQCB004 "A" is valid only if the condition is AVAILABLE.

Explanation: You cannot audit (A) the requested IIPS course because it does not have a course condition of AVAILABLE.

Module: ICQCBC00

ICQCB005 "T" valid for IIPS course only if condition is REGISTERED.

Explanation: You cannot take (T) the requested IIPS course because you are not registered in it. The word REGISTERED does not follow the course name on the course list. The course condition also prevents you from requesting registration in the course. You can request registration only if the condition is A (AVAILABLE) or R (REGISTER ONLY).

Module: ICQCBC00

ICQCB006 "R" valid only if condition is AVAILABLE or REGISTER ONLY.

Explanation: You can register (R) in a course only if that course has a condition of AVAILABLE or REGISTER ONLY.

Module: ICQCBC00

ICQCB007 "W" is valid only for courses marked AUTHOR.

Explanation: You can produce a course only if you are the author of the course. The Information Center Facility does not recognize you as the author. There are three types of allowable courses (IIPS, classroom, and computer), but only IIPS courses can be assigned AUTHOR as a course type.

System action: The system waits for your response.

User response: Contact your Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

Audience: Information Center Facility user

ICQCB008 You are already registered for this course.

Explanation: You are already registered in the requested course. You cannot register again.

If the course is an IIPS course and REGISTERED appears after the course name on the course list, you can request to take the course. Type T in the action field to the left of the course name.

Module: ICQCBC00

ICQCB009 No course listings are available to view.

Explanation: You asked to view the list of courses, but currently no courses are available for you to view.

User response: For more information, contact the Information Center Facility administrator.

Module: ICQCBC00

ICQCB010 Resource in use. To retry, reselect; to cancel, press END.

Explanation: Your request failed because one of the tables the education service requires is temporarily in use. Retry your selection.

Module: ICQCBC00

ICQCB011 "T" valid for IIPS course only if condition is REGISTERED.

Explanation: You cannot take (T) the requested IIPS course because you are not registered in it. The word REGISTERED does not follow the course name on the course list.

You can request registration in the course. After the administrator accepts your request at some later date, you see the word REGISTERED after the course name and can then request to take the course.

Although you cannot take the course without first registering, you can view (V) the course abstract. If the condition is AVAILABLE, you can also audit (A) the course.

Module: ICQCBC00

ICQCB012 AUTHOR NUMBER must be A followed by 1-9 characters (A-Z, 0-9).

Explanation: The author number is incorrect. It must be A followed by 1-9 characters. Those characters can be letters (A-Z) or numbers (0-9). Correct the author number and press the ENTER key.

Module: ICQCB050

ICQCB014 The course is unavailable. Try later.

Explanation: You are registered for the course you asked to take (T), but it is currently unavailable. The administrator sets the UNAVAILABLE condition when a course is being changed or updated.

User response: Contact the Information Center Facility administrator to determine when the requested course will be available.

Although the course itself is unavailable, you can view (V) the course abstract.

ICQCB015 • ICQCB023

Module: ICQCBC00

ICQCB015 "R" is not required for COMPUTER courses.

Explanation: You cannot and need not register for COMPUTER courses. If the course condition is AVAILABLE, you can take the course by typing T in the action field to the left of the course name.

Module: ICQCBC00

ICQCB019 "A" and "T" are not valid actions for CLASSROOM courses.

Explanation: Classroom course are courses presented in a classroom. Therefore, you cannot take or audit them via the Information Center Facility. You can only use the Information Center Facility to request registration in classroom courses.

Specify a different action or choose another course.

Module: ICQCBC00

ICQCB020 Request already accepted. It has not yet been processed.

Explanation: The Information Center Facility recorded your previous request for registration in this course. An administrator will process it later. After the request is processed, you either:

- See the word **REGISTERED** after the course name in the list of courses. REGISTERED indicates you are registered and can take the course.
- Receive a message stating that your request was denied.

This message is informational only.

Module: ICQCBC00

ICQCB021 Request accepted for processing later.

Explanation: The Information Center Facility has recorded your registration request. An administrator will process it later. After the request is processed, you either:

- See the word **REGISTERED** after the course name in the list of courses. REGISTERED indicates you are registered and can take the course.
- Receive a message stating that your request was denied.

This message is informational only.

Module: ICQCBC00

ICQCB022 Request not recorded; system error. Press HELP.

Explanation: Your request for registration was not passed on to an administrator for processing. Attempts to record your request in the registration request table failed because the data set in which the table resides is not allocated.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

ICQCB023 Request not recorded; system error. Press HELP.

Explanation: The Information Center Facility did not record your request for registration because of an error encountered when the ISPF TBCLOSE service tried to close the registration request table.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

ICQCB024 Resource in use. To retry, reselect; to cancel, press END.

Explanation: You asked to be registered for a course. However, the Information Center Facility cannot record your request because another user is simultaneously trying to register in a course. This condition is typically temporary.

To retry your request, retype your selection and press the ENTER key. To cancel your request, press the END PF key.

Module: ICQCBC00

ICQCB025 Request not recorded; system error. Press HELP.

Explanation: The Information Center Facility normally records your request for registration in a table so the administrator can honor or deny your request. This table, the registration request table, does not exist and cannot be created. The TBCREATE or TBCLOSE service routine set a non-zero return code.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

ICQCB026 Request not recorded; system error. Press HELP.

Explanation: The Information Center Facility did not record your request for registration because of an error encountered when the TBOPEN service tried to open the registration request table.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCBC00

ICQCB027 "T" is valid only if the COMPUTER course is AVAILABLE.

Explanation: You cannot take (T) the requested COMPUTER course because it is not marked AVAILABLE. Either specify a different action, select a different course, or press the END PF key to leave education services.

Module: ICQCBC00

ICQCB028 Request failed; system error. Press HELP.

Explanation: Your request to take or audit the COMPUTER course failed because the program, CLIST, or command that invokes the course (*course_name*) failed. It ended with a return code of 20.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQABC00

ICQCG000 Unable to allocate format file. Contact administrator.

Explanation: Your request failed, because the Information Center Facility was unable to allocate the format file (data set) to a file. The TSO/E ALLOCATE command failed.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCGC00

ICQCG001 Unable to allocate data file. Contact administrator.

Explanation: Your request failed, because the Information Center Facility was unable to allocate the data file you requested. The TSO/E ALLOCATE command failed.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCGC00

ICQCG002 • ICQCG010

ICQCG002 No files match the specified information.

Explanation: No files match the information you typed in the PROJECT, FILE NAME, and FILE TYPE fields. Change the information in one or more of those fields and press the ENTER key.

Module: ICQCGC00, ICQCGC01, ICQCGC02

ICQCG004 The Interactive Chart Utility is not available.

Explanation: You cannot use the Interactive Chart Utility (ICU). Either your company does not have ICU installed, or it is temporarily inaccessible.

User response: For more information, contact an Information Center Facility administrator.

Module: ICQCGC00

ICQCG005 Unable to allocate image file. Contact administrator.

Explanation: The Information Center Facility was unable to allocate the image file you requested.

User response: Contact the Information Center Facility administrator to resolve the problem.

Module: ICQCGC01

ICQCG006 Unable to allocate object file. Contact administrator.

Explanation: The Information Center Facility was unable to allocate the object file you requested.

User response: Contact the Information Center Facility administrator to resolve the problem.

Module: ICQCGC01

ICQCG007 The Image Symbol Set Editor is not available.

Explanation: You cannot use the Image Symbol Set Editor (ISE). Either your company does not have ISE installed, or it is temporarily inaccessible.

User response: For more information, contact an Information Center Facility administrator.

Module: ICQCGC01

ICQCG008 The Vector Symbol Set Editor is not available.

Explanation: You cannot use the Vector Symbol Editor (VSE). Either your company does not have VSE installed, or it is temporarily inaccessible.

User response: For more information, contact an Information Center Facility administrator.

Module: ICQCGC02

ICQCG009 The specified alternate symbol library cannot be found.

Explanation: The alternate symbol library specified either is not cataloged or does not exist. You can type the name of a different alternate symbol library or request a list of libraries and select one from the list. To request a list, in the FILE NAME or FILE TYPE fields, type an asterisk (*) or part of a name followed by an asterisk.

Module: ICQCGC00

ICQCG010 Unable to allocate vector file. Contact administrator.

Explanation: The Information Center Facility was unable to allocate the vector file you requested.

User response: Contact the Information Center Facility administrator to resolve the problem.

Module: ICQCGC02

ICQCG011 Library at cursor must be Alternate Symbol Library 1.

Explanation: You must change the order in which you listed the alternate symbol libraries. The library at the cursor position must be first because it has the largest block size.

Module: ICQCGC00

ICQCG012 Inconsistent Symbol Library block sizes. Press HELP.

Explanation: The default symbol library, *symbol_library_name*, has a larger block size than all the alternate symbol libraries you specified. Re-allocate the first alternate symbol library you specified with a block size larger than or equal to *block_size*.

User response: If you need help re-allocating the data set, contact your Information Center Facility administrator.

Module: ICQCGC00

ICQCG015 Unable to allocate the symbol libraries.

Explanation: The Information Center Facility was unable to allocate the symbol libraries. The ALLOCATE command failed because the file name, ADMSYMBL, is in use.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCGC00

ICQCG017 Request failed; system error. Press HELP.

Explanation: Your request failed because of a severe error in CLIST ICQCGC00.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCGC00, ICQCGC01, ICQCGC02

ICQCI000 Number at cursor must be between a minimum number and a maximum number.

Explanation: The number in the field at the cursor is not valid. In that field, type a number in the range shown in the message.

Module: ICQCIE34, ICQCIE51, ICQCIE52, ICQCIE61, ICQCIE62

ICQCI005 Number at cursor must be equal to or greater than a minimum number.

Explanation: The number in the field at the cursor is not valid. In that field, type a number equal to or greater than the number shown in the message.

Module: ICQCIE34

ICQCI006 Unable to allocate a file on VOLUME *specified_volume_name*

Explanation: The Information Center Facility was unable to allocate a file on the volume you specified. Either:

- Allow TSO/E to select a volume for you. Leave the VOLUME field blank and press the ENTER key.
- Use the TSO/E error messages that follow this message to determine why your request failed, and correct the problem.

User response: If you are unable to solve the problem, contact an Information Center Facility administrator.

Module: ICQCIC30

ICQCI007 Unable to allocate requested query file.

Explanation: The Information Center Facility was unable to allocate the following query file:

data_set_name

Use the TSO/E error messages that follow this message to determine why your request failed.

ICQCI008 • ICQCI013

User response: If you need help, contact an Information Center Facility administrator.

Module: ICQCIC30

ICQCI008 VOLUME is not valid. Correct or leave blank.

Explanation: The volume serial number you specified is not valid for TSO/E volumes. The value can contain only characters A-Z, 0-9, @, \$, or #. Either correct the name, or leave the field blank to allow TSO/E to select a volume for you.

User response: If you are unable to solve the problem, contact an Information Center Facility administrator.

Module: ICQCIE34, ICQCIE51, ICQCIE52, ICQCIE61, ICQCIE62

ICQCI009 Type name of definition file or request list and select.

Explanation: The PROJECT information is required. In the FILE NAME and FILE TYPE fields, you can type:

- The full names
- An asterisk (*) or part of a name followed by an asterisk. You then see a list of definition files that match the information you typed; you can select one from the list.

Module: ICQCIC30

ICQCI010 FIELD NAME not valid. Use only characters A-Z, 0-9, or /.

Explanation: The value in FIELD NAME is not valid. A field name can contain only characters A-Z, 0-9, or /. Correct the name and press the ENTER key.

Module: ICQCIE35

ICQCI011 FIELD TYPE is not valid. Type C, D, E, F, N, P, or Z.

Explanation: The field type you entered is not valid. The only acceptable field types are:

- C - character data
- D - zoned decimal
- E - floating-point decimal (either short or long)
- F - integer (fixed point decimal)
- N - numeric
- P - packed decimal
- Z - zoned decimal

Correct the field type and press the ENTER key. For more information concerning APLDI, see *APL Data Interface II TSO, Description/Options*

Module: ICQCIE35

ICQCI012 *Field_name* must contain a number.

Explanation: The value in *field_name* is not valid. That field must contain a number (0-9). Correct the error and press the ENTER key.

Module: ICQCIE35

ICQCI013 FILE ID not valid. Valid characters are A-Z, 0-9, @, \$, or #.

Explanation: The value in the FILE ID field is not valid. The file ID can contain only characters A-Z, 0-9, @, \$, or #. Correct the file ID and press the ENTER key.

Module: ICQCIE35

ICQCI014 **DECIMAL PLACES must be 0 or blank when FIELD TYPE is C.**

Explanation: The value in FIELD TYPE is C, which indicates the field will contain character data. Therefore, the non-zero value in DECIMAL PLACES is unacceptable; character fields do not contain decimal places.

Either change the field type or type a zero or blank for the number of decimal places.

Module: ICQCIE35

ICQCI015 **The definition file has been saved.**

Explanation: The Information Center Facility saved the definition file for you. This message is informational only.

Module: ICQCIE35

ICQCI016 **Error in definition file data. Fix field at cursor or CANCEL.**

Explanation: Data in the definition file is incorrect. The cursor points to the field in error. You can either:

- Correct the error. You can save the definition file only after you correct the error.
- Erase all changes you have made to the file since the beginning of this edit session or since you last entered the SAVE command. To erase the changes, type CANCEL on the COMMAND line.

Module: ICQCIE35

ICQCI017 **Edit cancelled. Definition file not saved or replaced.**

Explanation: You entered the CANCEL command while editing a definition file. The Information Center Facility deleted the changes you made to the definition file since the beginning of this edit session or since you last entered the SAVE command. The previous copy of the definition file (if there is one) is still available, along with any changes made in previous edit sessions or changes you saved during this session.

This message is informational only.

Module: ICQCIC35

ICQCI018 **Command at cursor position is not valid. Type D, I, or R.**

Explanation: The command you specified on the line indicated by the cursor is incorrect. To delete the line, type D; to insert a new line, type I; to repeat the line, type R.

Module: ICQCIC35

ICQCI019 **Type name for query file 2 or leave blank and press ENTER.**

Explanation: You selected your first query file from a list. Either supply a name for the second query file, or leave the fields blank to show that you want to use only one query file.

Module: ICQCIC50

ICQCI020 **The *specified_command* is not valid on COMMAND line of this panel.**

Explanation: The command you typed on the COMMAND line is not valid. To save the changes you have made to the definition file, type SAVE. To cancel changes you have made but not yet saved, type CANCEL. The previous copy of the definition file (if there is one) is still available, along with any changes made in a previous edit session or changes you saved during this edit session.

Module: ICQCIC35

ICQCI021 **To edit the definition file, type Y; to proceed, type N.**

Explanation: Before you create the query file, you can edit the definition file. To edit the file, type Y. To bypass editing, type N.

Module: ICQCIC35

ICQCI022 Definition file not found. Change name or request to edit it.

Explanation: The definition file you specified does not exist. You can either:

- Use a different definition file. Change the PROJECT, FILE NAME, or FILE TYPE field.
- Create a definition file with the specified name. Type Y in the EDIT DEFINITION FILE field.

Module: ICQCIC30

ICQCI023 Size estimate failed. Possible definition file error.

Explanation: You selected the CREATE option on the ALPDI selection panel. The APLDI DISIZE program completed with a non-zero return code. Verify that the file you used is correct.

User response: If you need help, contact an Information Center Facility administrator.

Module: ICQCIC30

ICQCI024 Select query file 1 from the list displayed.

Explanation: To select the first query file the APLDI DIUTIL program is to use, type S in the action field to the left of it and press the ENTER key.

Module: ICQCIC50

ICQCI025 Select query file 2 from the list displayed.

Explanation: To select the second query file the APLDI program DIUTIL is to use, type S in the action field to the left of it and press the ENTER key.

Module: ICQCIC50

ICQCI026 Unable to allocate the new query file.

Explanation: The Information Center Facility is unable to allocate your query file. Use the TSO/E error messages accompanying this message to help solve the problem.

User response: If you need help, contact an Information Center Facility administrator.

Module: ICQCIC50

ICQCI027 Select the DICNTL file to control BULK DELETE processing.

Explanation: Type S in the action field to the left of the DICNTL file to be used to control bulk delete processing. This file must have been created in a previous step using the DICNTL function of APLDI.

Module: ICQCIC50

ICQCI028 Select the DICNTL file to control UNLOAD processing.

Explanation: Type S in the action field to the left of the DICNTL file to be used to control the DIUNLOAD program. This file must have been created in a previous step using the DICNTL function of APLDI.

Module: ICQCIC60

ICQCI029 The *specified_command* is not valid on the COMMAND line of this panel.

Explanation: Only ISPF commands or TSO/E commands prefixed by tso are valid on the COMMAND line of the panel displaying this message.

Module: ICQCIC35, ICQGCC00

ICQCI030 Unable to allocate DICNTL file. CC = *return_code*.

Explanation: The Information Center Facility was unable to allocate your DICNTL file. Use the TSO/E error messages accompanying this message to solve the problem.

User response: If you need help, contact an Information Center Facility administrator.

Module: ICQCIC50

ICQCI031 Type name for DICNTL file or leave blank and press ENTER.

Explanation: To use a file that the APLDI DICNTL service previously created, type the information requested in the fields displayed and press the ENTER key. To select from a list of files, in the FILE NAME and FILE TYPE fields, type an asterisk (*) or part of a name followed by an asterisk.

If you do not want to use a file DICNTL created, leave the FILE NAME field blank and press the ENTER key.

Module: ICQCIC60

ICQCI032 Unable to allocate sequential file; condition code = *return_code*.

Explanation: The Information Center Facility was unable to allocate your sequential file for the APLDI DIUNLOAD program. Use the TSO/E error messages accompanying this message to solve the problem.

User response: If you need help, contact an Information Center Facility administrator.

Module: ICQCIC60

ICQCI033 DIUNLOAD failed: CC = *return_code*. Files might be incomplete.

Explanation: The APLDI DIUNLOAD program ended with the condition code specified in the message. Use any additional information that the APLDI program DIUNLOAD displays to solve the problem.

User response: If you need help, contact an Information Center Facility administrator.

Module: ICQCIC60

ICQCI034 File *sequential_data_set_name* created.

Explanation: The APLDI DIUNLOAD program successfully created the sequential file identified in the message. This message is informational only.

Module: ICQCIC60

ICQCI035 *Sequential.data.set1 - number* sequential files created.

Explanation: The APLDI DIUNLOAD program successfully created the number of sequential files reported in the message. If you overestimated the number of records, one or more of these files might be empty.

This message is informational only.

Module: ICQCIC60

ICQCI036 Change name of new query file; file 1 or 2 has same name.

Explanation: The name you specified for the new query file is unacceptable because it duplicates the name of query file 1 or query file 2. Type a different name and press the ENTER key.

Module: ICQCIC50

ICQCI037 Type a name for a workspace or leave blank and press ENTER.

Explanation: Either type the name of the query workspace or leave the WORKSPACE NAME field blank. If you leave it blank, the Information Center Facility uses the default workspace.

Module: ICQCIC10

ICQCI038 Type a number in the RECORD LENGTH field.

Explanation: The RECORD LENGTH field is required. It provides the estimated length of records in the sequential files that the APLDI DIUNLOAD program created. To calculate the record length, add the lengths of all the fields in a query file record.

Module: ICQCIC60

ICQCI039 Type a number in the NUMBER OF RECORDS field.

Explanation: Type the number of DICNTL records that you created using the APLDI DICNTL program.

The number of records in the DICNTL file determines how many sequential files DIUNLOAD creates. Each DICNTL record causes DIUNLOAD to create a new sequential file that contains the records from the query file and the DICNTL record. If you overestimate the number, DIUNLOAD creates extra empty files.

Module: ICQCIC60

ICQCI040 FILE TYPE with suffix *number* exists. REPLACE or change name.

Explanation: A file with the same name as the one you are trying to create already exists. Either:

- Type Y in the REPLACE field to replace the existing file.
- Type a different name in the FILE NAME field.

Module: ICQCIC30, ICQCIC60

ICQCI041 Request failed; *reason_for_failure*.

Explanation: The Information Center Facility is unable to access the data set.

User response: Either select another data set or contact an Information Center Facility administrator for help.

The Information Center Facility issued this message because the TSO/E CLIST built-in function SYSDSN returned a condition other than "OK" or "DATASET NOT FOUND". For more information concerning the CLIST built-in functions, see *z/OS TSO/E CLISTS*.

Module: ICQGCC00

ICQCI042 Unable to allocate new query or temporary file.

Explanation: The Information Center Facility was unable to allocate either the new query file or the workspace file you specified. Use the TSO/E error messages accompanying this message to solve the problem.

User response: If you need help, contact an Information Center Facility administrator.

Module: ICQCIC30

ICQCI043 File size is being estimated. Please wait.

Explanation: This message is a progress message that does not have on-line help. The file size estimate may take some time.

Module: ICQCIC30

ICQCI044 File size is being calculated. Please wait.

Explanation: This message is a progress message that does not have on-line help. The file size calculation may take some time.

Module: ICQCIC30

ICQCI045 Files are being allocated. Please wait.

Explanation: This message is a progress message that does not have on-line help. The allocation of files may take some time.

Module: ICQCIC30

ICQCI046 DICREATE program is running. Please wait.

Explanation: This message is a progress message that does not have on-line help. The DICREATE program may take some time to run.

Module: ICQCIC30

ICQCI047 Values for *field_name* must be numeric.

Explanation: The value at the cursor position contains a character or characters that are not numeric. Correct the value and press the ENTER key.

Module: ICQCIE35

ICQCI048 An error was detected. The TSO/E error message is shown.

Explanation: The message shown above is displayed in line mode TSO/E with message ICQCI049, a TSO/E allocate error message, and the allocate command causing the error. For more information regarding the TSO/E error message, look in the appropriate section of this document, *z/OS TSO/E Messages*.

Module: ICQCIC30

ICQCI049 To aid in correcting the error, note the message.

Explanation: The message shown above is displayed in line mode TSO/E with message ICQCI048, a TSO/E allocate error message, and the allocate command causing the error. Note the allocate command causing the error, because the system is not storing this information. The information will be lost when you clear your screen.

For more information regarding the TSO/E error message, look in the appropriate section of this document, *z/OS TSO/E Messages*.

Module: ICQCIC30

ICQCL011 The selected product is not installed.

Explanation: The option you selected on the previous panel requires a licensed program that is not installed on your system. As a result, that option is not available to you.

User response: Choose another option, or press the END PF key. If you have any questions about what licensed programs are available, contact an Information Center Facility administrator.

Module: ICQGCMO5

ICQCL012 Any changes to invocation parameters on page *number* were saved.

Explanation: The changes you made to the values of the parameters on the previous page were saved. If you made no changes, the invocation parameters have not been changed.

This message is informational only.

Module: ICQCCLC10

ICQCL013 Profile data set not found. Change PROFILE or SESSION MGR.

Explanation: You entered the following data set name in the PROFILE field:

data_set_name

ICQCL015 • ICQCN000

There is no data set with this name. Check to see if you typed the name incorrectly. If you did, then correct it and press the ENTER key. You can proceed from that point.

If the name is typed correctly, then the profile data set you are trying to use does not exist. You can continue without the Session Manager by typing N in the SESSION MGR field.

Module: ICQCLC10

ICQCL015 Workspace exists. Type a new name or type Y to replace.

Explanation: There is already a workspace in your library with the name you supplied in the WORKSPACE NAME field. Before the workspace you want to use can be copied to your library, you must decide either to replace the workspace that is in your library with the one you asked for, or to rename the one you asked for. To replace the workspace, type Y in the REPLACE EXISTING field. To rename the copied workspace, type N in the REPLACE EXISTING field, and type a unique workspace name in the NEW NAME field.

Module: ICQCLC20

ICQCL019 NEW NAME is required when REPLACE EXISTING is N.

Explanation: When you enter N in the REPLACE EXISTING field, you indicate that you do not want your old workspace to be replaced with the one you are requesting. If you want to keep the old workspace, you must supply in the NEW NAME field a new name for the workspace you are requesting. If you do not want to keep the old workspace, change the N in the REPLACE EXISTING field to Y.

Module: ICQCLE30

ICQCL021 Request cancelled. Parameters on page *number* not updated.

Explanation: On the page given in the message, you pressed the END PF key. If you made any changes to the values of the invocation parameters on that page, those changes were canceled.

If you did not intend to cancel those changes, select the PARMS option, return to that page, change the values of the parameters again, and press the ENTER key.

Module: ICQCLC10

ICQCL022 The installation defaults are displayed.

Explanation: When you type D on the COMMAND line, the default values for the invocation parameters on that page are displayed. To accept them as they are, press the ENTER key. If you want to change any of them, type the values you want over the displayed ones. When you are finished, press the ENTER key. This message is informational only.

Module: ICQCLC10

ICQCN000 No news items match the information specified.

Explanation: No news items match the information you specified in the ITEM, CATEGORY, and DATE fields. You can:

- Change some of the information displayed and press the ENTER key.
- Request a list of news items and choose from the list. To request a list, type * in one or more fields. In the ITEM and CATEGORY fields, you can also type part of a name followed by an asterisk.
- Type NEW on the COMMAND line to display any news that has been added since you last viewed news.
- Leave the news service by pressing the END PF key.

Module: ICQCNC00

ICQCNC001 *Specified_selection_character* is not valid. To view an item, type V.

Explanation: The character you typed in the action field to the left of a news item is not allowed. To view a news item, type V to the left of it and press the ENTER key. To leave the news service, press the END PF key.

Module: ICQCNC00

ICQCNC002 No news has been added since you last viewed news.

Explanation: No new news items have been added since you last viewed a list of news items. You can view a list of news items in several ways:

- By typing NEW on the command line to display only the items changed since you last viewed a list of news items
- By typing the information necessary to restrict the list of news items on the first panels in the news service
- By leaving asterisks (*) in every field in the first panel in the news service

A news item is removed from NEW news when you view the list containing that news item. You do not actually have to view the news item itself. This message is informational only.

Module: ICQCNC00, ICQCNC00

ICQCNC003 News has been added since you last viewed news.

Explanation: One or more news items have been added since you last viewed any news. To see the news that has been added:

1. Select the NEWS option to display the first news service panel.
2. Type NEW on the COMMAND line of that panel and press the ENTER key.

Unless you view either a news item or a list of news items after receiving this message, you receive it again when you log on and enter the Information Center Facility.

Module: ICQCNC10

ICQCNC004 Select only one news item at a time.

Explanation: You can type a selection character next to only one news item at a time. After processing that news item, you again see the news list and then can select another item.

Module: ICQCNC00, ICQCNC00

ICQCNC005 News item was deleted after this list was displayed.

Explanation: An administrator deleted the news item you requested to view. The deletion occurred after you displayed the news list but before you selected the news item. You can either request a different news item or press the END PF key to leave the news service.

Module: ICQCNC00

ICQCNC200 *value* is not valid on the command line of this panel.

Explanation: You typed a value that is not valid on the command line of the Printer Specification panel.

System action: The system waits for your response.

User response: Check the value and either correct it or blank it out.

Module: ICQCNC20

Audience: Information Center Facility user

ICQCN201 Item successfully printed.

Explanation: The specified item successfully printed. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN202 No matches for printer criteria found. Press HELP.

Explanation: The system did not find the specified printer type.

System action: The system waits for your response.

User response: Type a valid printer type or an * to receive a selection list of existing printers.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN203 Specify printer format or part of format with * suffix.

Explanation: You did not type a value on the Printer format field.

System action: The system waits for your response.

User response: Type a printer format, or a partial printer format with an * as the last character, or an * to receive a selection list of printer formats.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN205 Specify printer location or *.

Explanation: You did not type a value on the Printer location field.

System action: The system waits for your response.

User response: Type a printer location or an * to receive a selection list of printer locations.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN206 * is only valid as the last character in the printer format.

Explanation: You typed an * that was not the last character on the Printer format field.

System action: The system waits for your response.

User response: Type a value for the printer format, or a partial printer format with an * as the last character, or an * to receive a selection list of printer formats.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN207 * is only valid as the last character in the printer type.

Explanation: You typed an * that was not the last character on the Printer type field.

System action: The system waits for your response.

User response: Type a value for the printer type, or a partial printer type with an * as the last character, or an * to receive a selection list of printer types.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN208 Number of copies must be within the range 1 through 255.

Explanation: You did not type a valid number of copies.

System action: The system waits for your response.

User response: Type a number from 1 to 255.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN209 The requested item has no text. Press HELP.

Explanation: You specified an item that has no lines of text.

System action: The system waits for your response.

User response: Either edit that item and add lines of text, or select another item to print.

Module: ICQCNR20

Audience: Information Center Facility user

ICQCN210 Error allocating print file. Press HELP.

Explanation: The specified print file could not be allocated.

System action: The system waits for your response.

User response: Check to see if your current TSO/E prefix and the system default volume are allocated correctly. If that does not resolve the problem, check if an old copy of the print data set beginning with your current TSO/E prefix and ending with ICQCNPRT.LIST has been exclusively allocated to another user. Correct the allocation or contact your system programmer for assistance.

Module: ICQCNR20

Audience: Information Center Facility administrator

ICQCN211 Error allocating file to the item to be printed. Press HELP.

Explanation: The specified item could not be allocated to a file for copying to the print file.

System action: The system waits for your response.

User response: Check if another user has exclusively allocated the requested item and resolve the contention. If this is not the case, contact your system programmer.

Module: ICQCNR20

Audience: Information Center Facility administrator

ICQCN212 Error opening the item to be printed. Press HELP.

Explanation: The item to be printed could not be opened.

System action: The system waits for your response.

User response: Check if another user has exclusive access to the requested item and resolve the contention. If this is not the case, contact your system programmer.

Module: ICQCNR20

Audience: Information Center Facility administrator

ICQCN213 Error copying item to the print data set. Press HELP.

Explanation: An error occurred while copying the requested item to be printed to the print data set.

System action: The system waits for your response.

User response: Contact your system programmer.

Module: ICQCNR20

Audience: Information Center Facility administrator

ICQCN215 Print format is not valid.

Explanation: The specified print format is not a valid name. A valid print format contains 1-8 alphanumeric characters. The first can be A-Z or 0-9, the remaining characters can be A-Z, 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Type a valid print format, or a partial format with an * as the last character, or an * to receive a selection list of print formats.

Module: ICQCNR20

Audience: Information Center Facility administrator

ICQCN216 Printer type is not valid.

Explanation: The specified printer type is not a valid name. A valid printer type contains 1-8 alphanumeric characters, which can be A-Z or 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Specify a valid printer type, or a partial type with an * as the last character, or an * to receive a selection list of printer types.

Module: ICQCNR20

Audience: Information Center Facility administrator

ICQCN217 Printer location cannot contain an apostrophe or parenthesis.

Explanation: The printer location field contains an apostrophe or parenthesis, which is not allowed.

System action: The system waits for your response.

User response: Remove the apostrophe or parenthesis and specify a valid printer location or an *.

Module: ICQCNR20

Audience: Information Center Facility administrator

ICQCP001 Request failed; printer table or font table error. Press HELP.

Explanation: Your request for a printer failed because the system was unable to access the printer support table or fonts table. The ISPF TBOPEN service routine set a return code of 8. The CLIST sent a return code of 28 (for printer table) or 32 (for fonts table) to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00, ICQCPC10

ICQCP002 Request failed; printer service busy. Try later.

Explanation: Your request for a printer failed because the printer support table or fonts table was in use. The ISPF TBOPEN service routine set a return code of 12. The CLIST sent a return code of 28 (for printer table) or 32 (for fonts table) to the calling application. Make your request again later.

Module: ICQCPC00, ICQCPC10

ICQCP003 Request failed; printer table or font table error. Press HELP.

Explanation: Your request for a printer or font failed because the printer support table or fonts table library was not allocated. The ISPF TBOPEN service routine set a return code of 16. The CLIST sent a return code of 28 (for printer table) or 32 (for fonts table) to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00, ICQCPC10

ICQCP004 Request failed; printer table or font table error. Press HELP.

Explanation: Your request for a printer or font failed because the system encountered a severe error when trying to open the printer support table or fonts table. The ISPF TBOPEN service routine set a return code of 20. The CLIST sent a return code of 28 (for printer table) or 32 (for fonts table) to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00, ICQCPC10, ICQCPC15

ICQCP005 Request failed; system error. Press HELP.

Explanation: Your print request failed because the data set to be printed *data_set_name* cannot be found.

The data set name could have been obtained from the DSNNAME parameter of CLISTs ICQCPC00, ICQCPC10, ICQCPC15, the printer support table ICQAAPT10, or the temporary table QCPPRINT.

CLIST *CLIST_name* sent a return code of 12 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00, ICQCPC10, ICQCPC15

ICQCP006 Request failed; system error. Press HELP.

Explanation: Your print request failed because no print function was defined for the print definition you selected. The CLIST sent a return code of 4 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00

ICQCP007 Request failed; system error. Press HELP.

Explanation: CLIST ICQCPC00 contained a VERIFY request with extraneous parameters or improper syntax. The CLIST sent a return code of 36 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00

ICQCP008 Request failed; system error. Press HELP.

Explanation: CLIST ICQCPC00 contained a VERIFY request with the CHARS parameter, but no font table exists for the specified print definition. The CLIST sent a return code of 32 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00

ICQCP009 • ICQCP014

ICQCP009 Request failed; system error. Press HELP.

Explanation: CLIST ICQCPC00 contained a VERIFY request with the CHARS parameter, but one or more of the character sets specified was not defined. The unverified character sets are:

unverified font names

The CLIST sent a return code of 20 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00

ICQCP010 Request failed; system error. Press HELP.

Explanation: Your print request failed because the mutually exclusive ALLOCATION keywords BURST and NOBURST, HOLD and NOHOLD, or all have both been specified in the invocation. The CLIST sent a return code of 36 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC10

ICQCP011 Printer not found. Try another or press HELP.

Explanation: The specified print definition does not exist in the printer support table. If you specified a print definition, check to see that it is spelled correctly. Otherwise, copy the information displayed below and give it to you Information Center Facility administrator.

The CLIST *CLIST_name* set a non-zero return code. The *PLOC* or *PFORM* parameter set to *the contents of PLOC* or *PFORM* was not found.

Module: ICQCPC00, ICQCPC10, ICQCPC15

ICQCP012 Request failed; system error. Press HELP.

Explanation: Your print request failed, because the invocation of the print CLIST *CLIST_name* specified parameters PLOC and PFORM incorrectly. If the CLIST specifies one of the parameters, it must specify both, and neither can contain an asterisk.

- PLOC specified: *location*
- PFORM specified: *print_format*

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC10, ICQCPC15

ICQCP013 Request failed; system error. Press HELP.

Explanation: Your print request failed, because the invocation of the print CLIST *CLIST_name* contained neither the parameter NOTABLE nor the parameters PLOC and PFORM. Also, the temporary table used to pass the print characteristics did not exist. The CLIST sent a return code of 32 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC10, ICQCPC15

ICQCP014 Request failed; system error. Press HELP.

Explanation: Your print request failed, because the invocation of the print CLIST ICQCPC10 contained the parameter NOTABLE, but the parameters PLOC/PFORM or SYSOUT were not specified. The CLIST sent a return code of 16 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC10

ICQCP015 Request failed; system error. Press HELP.

Explanation: Your print request failed, and the IEBGENER printing utility set a return code of *return_code*. Refer to *MVS/370 Utilities* for an explanation of the IEBGENER return code. The print CLIST sent a return code of 24 to the calling application.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC10

ICQCP016 Request failed; system error. Press HELP.

Explanation: Your print request failed when one of the ALLOCATE parameters for the IEBGENER utility caused IEBGENER to set a non-zero return code. The messages from ALLOCATE are displayed on the following panel.

The print CLIST sent a return code of *return_code* to your calling application. If the print CLIST set a return code of 12, the input data set that you were trying to print (SYSUT1) is in error. If the print CLIST set a return code of 16, the printer (SYSUT2) is in error.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC10

ICQCP017 Printing failed; severe error. Press HELP for details.

Explanation: Your request failed, because the invoked print function encountered an error. For more information concerning the IBM-supplied print function and its return codes, see *z/OS TSO/E Programming Services*.

Printer location	Printer location
Printer format	Printer format
Print function	Name of CLIST, program, or command
Return code	Return code from print function
Print data set	Name of the data set you are trying to print
Function message	Message returned by print function Note: If there is no function message, this field will not be displayed at your terminal.
Invocation	The ISPF SELECT service invoked via the CLIST command to activate the print function

Module: ICQCPC00

ICQCP018 Print function could not be invoked. Press HELP for details.

Explanation: Your request failed, because the Information Center Facility attempted to invoke the print function (by calling the ISPF SELECT service) and encountered a severe error. When you receive this message, press the HELP PF key at your terminal and note the information displayed for your Information Center Facility administrator or system programmer.

Printer location	Printer location
Printer format	Printer format
Print function	Print function
ISPF SELECT message	Message returned by ISPF SELECT service Note: For more information concerning the ISPF SELECT service, see <i>z/OS ISPF Services Guide</i> .
Invocation	The ISPF service invoked via the CLIST command to activate the print function

Module: ICQCPC00

ICQCP019 No printer was selected.

Explanation: You pressed the END PF key without selecting a printer. If you wanted to select a printer and can reaccess the List of Printers panel, reaccess the panel, select a printer, and press the ENTER key. The CLIST sent a return code of 8 to the calling application.

Module: ICQCPC00

ICQCP030 Conflicting PRINTDS parameters were specified. Press HELP.

Explanation: Your print request failed, because the print CLIST ICQCPC15 detected conflicting parameters of the PRINTDS command. Press the HELP PF key while this message is displayed and you will see a panel that lists the two conflicting parameters. You must delete one of the conflicting parameters from the call to CLIST ICQCPC15.

The CLIST sent a return code of 16 to the calling application.

Module: ICQCPC15

ICQCP031 PRINTDS failed. Press HELP.

Explanation: Your print request failed because the TSO/E PRINTDS command detected an error. Press the HELP PF key while this message is displayed and you will see a panel that lists one or more error messages from PRINTDS.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC15

ICQCP032 PRINTDS issued a warning. Press HELP.

Explanation: The TSO/E PRINTDS command issued a warning about your print request.

System action: The system attempts to execute your print request properly.

User response: Press the HELP PF key while this message is displayed and you will see a panel that lists one or more warning messages from PRINTDS. Contact an Information Center Facility administrator to resolve the warning.

Module: ICQCPC15

ICQCP033 Conflicting parameters were specified. Press HELP.

Explanation: Your print request failed, because the print CLIST detected conflicting print parameters.

System action: The CLIST sent a return code of 36 to the calling application.

User response: Press the HELP PF key while this message is displayed and you will see a panel that lists the two conflicting parameters. One of these parameters must be deleted from the call to the CLIST. Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCPC00

ICQCR001 Select the name of the workspace to copy data FROM.

Explanation: Select the name of the workspace from which you want to copy data. To select a workspace, type S in the action field to the left of the workspace name, and press the ENTER key.

Module: ICQCRC30

ICQCR002 Select the name of the workspace to copy data TO.

Explanation: Select the name of the workspace into which you want to copy data. To select a workspace, type S in the action field to the left of the workspace name, and press the ENTER key. The Information Center Facility then copies the data into that workspace.

Module: ICQCRC30

ICQCR003 Type the name of the workspace to copy data TO.

Explanation: To identify the workspace into which you want to copy data, type the information requested in the PROJECT and WORKSPACE NAME fields. To display a list of workspaces from which to choose, in the WORKSPACE NAME field, type an asterisk (*) or part of a name followed by an asterisk.

Module: ICQCRC30

ICQCR004 The workspace has been saved.

Explanation: The Information Center Facility saved the CONTINUE workspace that was created when you terminated APL. This message is informational only.

Module: ICQGCC40

ICQCR005 The workspace has not been saved.

Explanation: The Information Center Facility deleted the changes you made to the CONTINUE workspace that was created when you terminated APL. When you exited the workspace, the Information Center Facility asked you if you wanted to save a copy of it under the name shown on the panel. You chose not to save it by typing N in the SAVE field. The previous copy (if any) is still available.

Module: ICQGCC40

ICQCR006 The selected file does not exist. Select another one.

Explanation: The following file does not exist:

Data_set_name

Perhaps you deleted the data set on one part of a split screen and tried to select it on the other.

Module: ICQGCC00

ICQCR007 Workspace name CONTINUE is not allowed. Type a new name.

Explanation: You cannot use the workspace name CONTINUE because APL creates a workspace with that name when you terminate APL. Type a different name and press the ENTER key.

Module: ICQCRC10, ICQGCC40

ICQCR008 Workspace name RECOVER is not allowed. Type a new name.

Explanation: Because the Information Center Facility reserves the name RECOVER for its own use, you cannot use that name. Type a different workspace name and press the ENTER key.

Module: ICQGCC40

ICQGA000 CLIST or REXX exec *member_name* beginning execution.

Explanation: The CLIST or REXX exec member specified in the message has started executing. This message is displayed when the trace facility is active for the executing CLIST or REXX exec.

Module: ICQASERE0, ICQASRF0, ICQASRM0, ICQASRP1, ICQASRP2, ICQASRP3, ICQASRR0, ICQASRS0, ICQASRT0, ICQASRT1, ICQASRT2

ICQGA001 CLIST/REXX exec *member_name* exiting; final condition code *condition_code*

Explanation: The CLIST or REXX exec member identified in the message abended. The message lists the final condition code from the member.

The Information Center Facility writes this message to the ISPF log when the trace facility is active for the executing CLIST or REXX exec.

ICQGA002 • ICQGA010

Module: ICQASRE0, ICQASRF0, ICQASRM0, ICQASRP1, ICQASRP2, ICQASRP3, ICQASRR0, ICQASRS0, ICQASRT0, ICQASRT1, ICQASRT2

ICQGA002 CLIST or REXX exec trace is not active.

Explanation: You entered the TRACEOFF command, but the trace facility is not active. This message is informational only.

Module: All Information Center Facility selection panels

ICQGA003 CLIST or REXX exec trace is turned off.

Explanation: The TRACEOFF command executed successfully. The trace facility is no longer active. This message is informational only.

Module: All Information Center Facility selection panels

ICQGA004 CLIST or REXX exec member name required. TRACEOFF is set.

Explanation: When you enter a TRACE3 command, you must specify the name of the CLIST or REXX exec member to be traced. For example, to trace the CLIST member named ICQANC00, type:

```
TRACE3.ICQANC00
```

Because you entered TRACE3 without specifying a member name, the trace facility was turned off.

Module: All Information Center Facility selection panels

ICQGA005 CLIST/REXX exec member *member_name* will be traced on the screen.

Explanation: The TRACE3 command executed successfully. However, the name of the CLIST or REXX exec has not been verified.

The TRACE3 command uses the ISPF log service to write messages to the ISPF LOG data set. In addition, TRACE3 writes the CLIST or REXX exec name to the screen and displays each CLIST statement, REXX instruction, TSO/E command, and subcommand before execution.

To turn trace off, type TRACEOFF on the OPTION line of an Information Center Facility selection panel.

This message is informational only.

Module: All Information Center Facility selection panels

ICQGA006 CLIST or REXX exec tracing will be at level *trace_level*.

Explanation: The TRACE1 or 2 command executed successfully.

The TRACE1 and TRACE2 commands both use the ISPF log service to write messages to the ISPF log data set. In addition, TRACE1 shows the control flow between (or among) nested CLISTs and REXX execs. As each CLIST or REXX exec is invoked, its name is written to the screen. TRACE2 provides the same trace as TRACE1, and also displays each CLIST statement, REXX instruction, TSO/E command, and subcommand before execution.

To turn trace off, type TRACEOFF on the OPTION line of an Information Center Facility selection panel.

This message is informational only.

Module: All Information Center Facility selection panels

ICQGA010 Converting table - *table_name*

Explanation: Application Manager is in the process of converting the table to upper case. This message is informational only. No on-line HELP is available.

Module: ICQAMCTC

ICQGA011 Help table - *table_name*

Explanation: Application Manager is in the process of converting the help table to upper case. This message is informational only. No on-line HELP is available.

Module: ICQAMCTC

ICQGA012 Conversion routine ended abnormally.

Explanation: The conversion routine ended while accessing the table to be converted.

User response: Contact your system programmer for assistance. No on-line HELP is available.

Module: ICQAMCTC

ICQGA020 Beginning conversion process.

Explanation: The conversion process from the previous release of TSO/E to the new release of TSO/E has begun. This message is informational only.

System action: Processing continues.

User response: None.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA021 Beginning conversion of administrator and user libraries.

Explanation: The conversion of administrator and user libraries has begun. This message is informational only.

System action: Processing continues.

User response: None.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA022 Master table *table_name* converted and renamed to *new_table_name*.

Explanation: The *table_name* table has been converted and renamed to the *new_table_name*. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA023 *application_name* table *table_name* converted.

Explanation: The specified application has been converted. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA024 Administrator and user libraries have been converted.

Explanation: The conversion process for the administrator and user libraries has been completed. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA025 Conversion process is complete.

Explanation: The conversion process has been completed. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA026 Converted *administration_table* tables reside in *dsname*.

Explanation: The converted tables reside in *dsname*. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA027 LIBDEF issued for ISPMLIB was unsuccessful.

Explanation: The specified data set in the MESSAGES keyword parameter does not exist, is missing, or is not valid. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Check the value of the MESSAGES keyword parameter for a valid data set name. The data set name must be fully qualified and *without* single quotation marks.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA028 Error opening enqueue table *table_name*.

Explanation: The enqueue table is being used by another user. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing continues.

User response: Try again later or determine who is using the table and ask that user to not use the table.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA029 Error saving application *application_name* table *table_name*.

Explanation: An I/O error occurred while processing the specified application. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Ensure that the help table is present with the application table or contact your system programmer for assistance.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA030 LIBDEF issued for ISPMLIB was unsuccessful.

Explanation: The specified data set in the PANELS keyword parameter does not exist, is missing, or is not valid. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Check the value of the PANELS keyword parameter for a valid data set name. The data set name must be fully qualified and *without* single quotation marks.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA031 Application manager library *file_name* was not allocated.

Explanation: The administrator and user libraries have not been previously allocated to file names ICQAMTAB and ICQCMTAB, respectively.

System action: Processing terminates.

User response: Allocate the file names ICQAMTAB and ICQCMTAB to the respective data sets.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA032 Conversion cannot occur when *user_id* is in Application Manager.

Explanation: The conversion must be done outside of Application Manager. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Exit out of Application Manager and try again.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA033 Interrupted updates. Complete the updates prior to conversion.

Explanation: The update table exists and indicates there is an interrupted update. The updates must be complete before conversion. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Either complete the updates and continue with the conversion process or delete the update table and start again.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA036 Master table *table_name* doesn't exist.

Explanation: The master table does not exist. You might have incorrectly allocated the file names ICQAMTAB and ICQCMTAB, respectively. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Check the file names ICQAMTAB and ICQCMTAB and reallocate them if necessary.

ICQGA037 • ICQGC000

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA037 Error opening *table_name* table.

Explanation: The specified table could not be opened because of an I/O error, an incorrect volume, or a hardware problem. The table is not converted. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Contact your system programmer.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA038 Error creating *table_name* table.

Explanation: The specified table could not be opened because another user is using the same table name. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: Try again later or determine who is using the table and ask that user to not use the table.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGA039 Error allocating *dsname* data set.

Explanation: The specified data set could not be allocated because either the data set already exists or you already ran the conversion routine. This message appears in the ISPF log data set and is displayed in line mode.

System action: Processing terminates.

User response: If the data set exists, replace it with another data set name. If you already ran the conversion routine, check to see if you specified the correct data set name or contact your system programmer.

Module: ICQAMCR1

Audience: Information Center Facility administrator

ICQGC000 Request failed. To retry, repeat. Press HELP for details.

Explanation: Your request failed, because data required by the Information Center Facility was not available. This is normally a temporary condition. Repeating the action on the previous panel will restart the function. If this condition persists, note the information displayed on the message help panel at your terminal for the Information Center Facility administrator or system programmer.

CLIST name	CLIST that was executing when the failure occurred
Failing step	Location in the CLIST where the failure occurred
ISPF service	ISPF service that was issued
	Note: For more information concerning the ISPF service, see <i>z/OS ISPF Services Guide</i> .
Return code	Return code from the ISPF service
Table name	Table that the ISPF service was operating against
Description	Error text set by the ISPF service

Module: ICQAPC00

ICQGC001 Request failed; system error. Press HELP for details.

Explanation: Your request failed, because the Information Center Facility invoked an ISPF service that encountered a severe error. Pay attention to the information displayed on the message help panel at your terminal for the Information Center Facility administrator or system programmer.

CLIST name	CLIST that was executing when the failure occurred
Failing step	Location in the CLIST where the failure occurred
ISPF service	ISPF service that was issued Note: For more information concerning the ISPF service, see <i>z/OS ISPF Services Guide</i> .
Return code	Return code from the ISPF service
Table name	Table that the ISPF service was operating against
Description	Error text set by the ISPF service

Module: ICQAPC00

ICQGC003 Cursor field may not contain an apostrophe (').

Explanation: You typed an apostrophe (') as one of the characters in the field indicated by the cursor. An apostrophe is not valid in that field. Type a valid character, and press the ENTER key.

Module: ICQCME15

ICQGC010 Selected_product is not available at this installation.

Explanation: The option you selected requires a licensed program that is not installed on your system. As a result, that option is not available to you.

User response: Choose another option or press the END PF key. If you have any questions concerning what functions are available, contact an Information Center Facility administrator.

Module: ICQCIC00, ICQCIC10, ICQCRC00

ICQGC011 CONTINUE workspace was copied into RECOVER workspace.

Explanation: The Information Center Facility copied the CONTINUE workspace into the RECOVER workspace. You can access this workspace by typing RECOVER in the WORKSPACE name field. This message is informational only.

Module: ICQCIC10, ICQCRC10, ICQCRC20, ICQCRC30

ICQGC012 File already exists. Type a new name or type Y to replace.

Explanation: The file you specified already exists. To replace the file, type Y in the REPLACE field. If you want to keep the file, type a different name in the PROJECT, FILE NAME, or FILE TYPE field.

Module: ICQCIC30, ICQCIC50, ICQCIC60

ICQGC013 No files match the information specified. Type another name.

Explanation: The file you specified does not exist or could not be accessed. You can either:

- Type a different file name by changing the PROJECT, FILE NAME, or FILE TYPE field.
- Select a file from a list obtained by:
 - Typing a partial name followed by * in the FILE NAME, or FILE TYPE fields
 - Typing * in the FILE NAME or FILE TYPE fields.

Module: ICQAPC00, ICQCIC10, ICQCIC30, ICQCIC40, ICQCIC50, ICQCIC60, ICQCMC10, ICQCMC40

ICQGC014 * not valid. Type a full name.

Explanation: You cannot append * to get a list when you are naming a file. You must type a complete name. To obtain further help for typing a name, press the ENTER key.

Module: ICQCIE32, ICQCIE33, ICQCRE10, ICQCRE11, ICQGCE40, ICQGCE41

ICQGC015 Unable to copy workspace. Try later.

Explanation: An error occurred while copying another user's private workspace. This error can occur if someone else is using the workspace at the same time you try to access it.

User response: The condition is typically temporary, so try again later. If the problem persists, contact an Information Center Facility administrator.

Module: ICQCIC10, ICQCLC20, ICQCRC20, ICQCRC30

ICQGC016 Workspace not found. Type another name.

Explanation: The workspace you specified does not exist or could not be accessed. You can either:

- Type a different workspace name by changing the WORKSPACE NAME field.
- Select a workspace from a list obtained by either:
 - Typing a partial name followed by * in the WORKSPACE NAME field
 - Typing * in the WORKSPACE NAME field.

Module: ICQCIC10, ICQCRC20, ICQCRC30, ICQGCC30

ICQGC017 Workspace exists. Type a new name or type Y to replace.

Explanation: The workspace you specified already exists. To replace the old workspace, type Y in the REPLACE field. If you want to keep the old workspace, change the workspace name.

Module: ICQCRC10, ICQGCC40

ICQGC018 Request failed; system error. Press HELP.

Explanation: A system error occurred while CLIST *CLIST_name* was executing the *command_name* command. The CLIST set a return code of *return_code*. A short explanation of the CLISTS and their associated commands follows.

User response: Contact the Information Center Facility administrator to resolve any of the following errors.

CLIST: ICQCIC30 COMMAND: OPEN DISIZE

An error occurred while opening the file created by ICQCIC40.

CLIST: ICQCIC30 COMMAND: ALLOC ALPHA

An error occurred while allocating a file to contain the alternate alphabet specified in CLIST ICQCIC20 in the variable ICQALPH.

CLIST: ICQCIC30 COMMAND: OPEN ALPHA

An error occurred while opening the file to contain the alternate alphabet.

CLIST: ICQCIC30 COMMAND: WRITE ALPHA

An error occurred while writing a record into the file to contain the alternate alphabet.

CLIST: ICQCIC30 COMMAND: CLOSE ALPHA

An error occurred while closing the file containing the alternate alphabet.

CLIST: ICQCIC30 COMMAND: ALLOC DATA

An error occurred while allocating the data file.

CLIST: ICQCIC30 COMMAND: ALLOC DEF

An error occurred while allocating the definition file.

CLIST: ICQCIC30 COMMAND: ALLOC *filename*

An error occurred while allocating the file shown in the message. Possible file names are TEMP and DIFILEy, where "y" is blank or the character specified in the FILE ID column of the definition file.

CLIST: ICQCIC35 COMMAND: ALLOC DEF

An error occurred while allocating the definition file.

CLIST: ICQCIC35 COMMAND: OPEN DEF

An error occurred while opening the definition file.

CLIST: ICQCIC35 COMMAND: READ DEF

An error occurred while reading the definition file to create a table for editing.

CLIST: ICQCIC35 COMMAND: ALLOC DESC

An error occurred while allocating a new definition file.

CLIST: ICQCIC35 COMMAND: OPEN DESC

An error occurred while opening the definition file, but before saving it.

CLIST: ICQCIC35 COMMAND: PUT DESC

An error occurred while writing into the definition file while saving it.

CLIST: ICQCIC35 COMMAND: CLOSE DESC

An error occurred while closing the definition file after saving it.

CLIST: ICQCIC40 COMMAND: ALLOC LIST

An error occurred while allocating a file to contain the output from the DISIZE program.

CLIST: ICQCIC40 COMMAND: ALLOC DEF

An error occurred while allocating the definition file.

CLIST: ICQCIC40 COMMAND: RUN DISIZE

An error occurred while running the DISIZE program.

CLIST: ICQCIC50 COMMAND: ALLOC QUERY 1

An error occurred while allocating query file 1.

CLIST: ICQCIC50 COMMAND: ALLOC QUERY 2

An error occurred while allocating query file 2.

CLIST: ICQCIC50 COMMAND: RUN DIUTIL

An error occurred while running the DIUTIL program.

CLIST: ICQCIC60 COMMAND: ALLOC QUERY

An error occurred while allocating the query file.

CLIST: ICQCIC60 COMMAND: ALLOC DICNTL

An error occurred while allocating the DICNTL file.

CLIST: ICQCIC60 COMMAND: ALLOC ALPH

An error occurred while allocating the file to contain the alternate alphabet.

CLIST: ICQCIC60 COMMAND: OPEN ALPH

An error occurred while opening the file to contain the alternate alphabet.

CLIST: ICQCIC60 COMMAND: WRITE ALPH

An error occurred while writing into the file to contain the alternate alphabet.

CLIST: ICQCIC60 COMMAND: CLOSE ALPH

ICQGC019 • ICQGC021

An error occurred while closing the file to contain the alternate alphabet.

CLIST: ICQCIC60 COMMAND: RUN DIUNLOAD

An error occurred while running the program DIUNLOAD.

CLIST: ICQGCC00 COMMAND: ALLOC LISTCDD

An error occurred while allocating the file to contain the output from the LISTCAT command.

CLIST: ICQGCC00 COMMAND: OPEN LISTCDD

An error occurred while opening the file containing the output from the LISTCAT command.

CLIST: ICQGCC00 COMMAND: TBCREATE

An error occurred while creating the table to contain the list of files.

CLIST: ICQGCC30 COMMAND: ALLOC

An error occurred while allocating a file to contain the output from the LISTCAT command.

CLIST: ICQCIC30 COMMAND: OPEN

An error occurred while opening the file containing the output from the LISTCAT command.

CLIST: ICQGCC30 COMMAND: GETFILE

An error occurred while reading from the file containing the output from the LISTCAT command.

CLIST: ICQGCC30 COMMAND: LOOKUP OWNER

An unidentified error occurred in the LISTCAT command.

Module: ICQCIC30, ICQCIC35, ICQCIC40, ICQCIC50, ICQCIC60, ICQGCC00

ICQGC019 *Specified_selection_character* **not valid. Type correct_selection_character next to the item desired.**

Explanation: Next to the item required, type:

- C to copy, D to delete, or M to modify a printer definition.
- S to select a printer type, a printer format or a printer definition.
- A font order number to select a font.

All of the above options are not available in every situation. Choose the instruction which applies.

Module: ICQAPE00, ICQAPE40, ICQAPE41, ICQCPE00, ICQCPE10

ICQGC020 **Workspace not saved. To save it, type a new name.**

Explanation: The Information Center Facility was unable to copy the CONTINUE workspace into the workspace you specified. To save the workspace, specify another name. If you do not need to save the workspace, type N in the SAVE CURRENT WORKSPACE field.

Module: ICQGCC40

ICQGC021 *** not allowed in PROJECT field. Correct and press ENTER.**

Explanation: You cannot use * in the PROJECT field of a file name.

To get a list of files under a certain PROJECT, type a partial name followed by * in the FILE NAME, FILE TYPE, or WORKSPACE NAME fields. You then see a list of the files that match the information you entered. You can also type * in those fields to display all the files under the PROJECT name.

Module: Many Information Center Facility CLISTs

ICQGC022 Name not valid; * allowed only at end to request a list.

Explanation: To request a list of files matching the information you specify, you can type a partial name followed by * in the FILE NAME, FILE TYPE, or WORKSPACE NAME fields. You can also type only * in those fields to display all the files under the project name or library number.

Module: Many Information Center Facility CLISTs

ICQGC023 Workspace name not valid. Use A-Z, 0-9. Start with A-Z.

Explanation: You cannot use the characters #, \$, or @ in the name of a workspace. Workspace names consist of letters (A-Z) and numbers (0-9). The first character must be a letter.

Module: ICQCIE10, ICQCIE20, ICQCLE30, ICQCRE10, ICQCRE11, ICQCRE20, ICQCRE30, ICQGCE40, ICQGCE41

ICQGC024 To save a workspace, PROJECT field must be your user ID.

Explanation: To save a workspace, the PROJECT field must contain the user ID with which you logged on. Correct the project name, and press the ENTER key.

Module: ICQCRE30, ICQGCE40, ICQGCE41

ICQGC025 Request failed. You cannot access another user's workspace.

Explanation: To access a workspace, the PROJECT name must be the same as the user ID with which you logged on. Correct the PROJECT name and press the ENTER key.

Module: ICQCIE10, ICQCIE20, ICQCRE20

ICQGC026 Request failed. You cannot copy from another user's workspace.

Explanation: To copy from a workspace, the PROJECT name must be the same as the user ID with which you logged on.

Module: ICQCRE30

ICQGC027 To create a workspace, PROJECT must be your user ID.

Explanation: To create a workspace, the PROJECT field must be the same as the user ID with which you logged on. Correct the project name and press the ENTER key.

Module: ICQCRE10, ICQCRE11

ICQGC028 APL failed. Press HELP.

Explanation: APL terminated with a return code of *return_code*. A common return code is 0C4. It is often caused by specifying a file that does not contain a valid APL workspace.

User response: If you cannot solve the problem, contact an Information Center Facility administrator.

Module: ICQCIC10, ICQCRC10, ICQCRC20, ICQCRC30

ICQGC029 Library number not allowed for PROJECT. Type your user ID.

Explanation: You cannot specify an APL library number in the PROJECT field. You must specify the user ID with which you logged on when creating or saving a workspace.

Module: ICQCRE30

ICQGC030 Type a number (0-9) at the cursor position.

Explanation: You must type a number (0-9) at the cursor position.

Module: Many Information Center Facility CLISTs and panels

ICQGC031 • ICQGC039

ICQGC031 Type the required information at the cursor position.

Explanation: You must type information in the field indicated by the cursor.

Module: Many Information Center Facility CLISTs and panels

ICQGC032 At the cursor, type one of the values listed.

Explanation: The field indicated by the cursor contains inappropriate information. Type one of the choices listed for that field.

Module: Many Information Center Facility CLISTs and panels

ICQGC033 Type a number between a minimum number and a maximum number at the cursor position.

Explanation: You must enter a number between a minimum number and a maximum number in the field indicated by the cursor.

Module: Many Information Center Facility CLISTs and panels

ICQGC034 * may be entered only as the last character.

Explanation: You cannot type * except as the last character in a field. Type * only to request a list. For example, to request a list of all entries beginning with SP, type SP*.

Module: ICQAPE30

ICQGC035 Entry must be 1-8 characters (A-Z, 0-9, @, #, \$); first not 0-9.

Explanation: The entry you typed is not valid. Correct the entry, and press the ENTER key.

The entry must contain one to eight characters (A-Z, 0-9, @, #, \$). The first character must be a letter, @, #, or \$.

Module: Many Information Center Facility CLISTs and panels

ICQGC036 Specified_command is not valid on the COMMAND line of this panel.

Explanation: Specified_command is the command you entered. It is not valid on the COMMAND line of this panel. Type a valid command.

Module: Many Information Center Facility CLISTs and panels

ICQGC037 Type Y for yes or N for no at the cursor position.

Explanation: You must type either Y to indicate yes or N to indicate no at the cursor position.

Module: Many Information Center Facility CLISTs and panels

ICQGC038 Type number digits at the cursor position.

Explanation: You must type number digits at the cursor position.

Module: ICQCBE50

ICQGC039 * is not allowed.

Explanation: You cannot type * in the field indicated by the cursor. Correct the entry and press the ENTER key.

Module: ICQCBE50

ICQGC040 Type a letter or number (A-Z, 0-9) at the cursor position.

Explanation: You entered a character that is not a letter or number. Type a letter (A-Z) or number (0-9) at the cursor position.

Module: ICQADE06

ICQGC041 Type a hexadecimal number using the characters 0-9, A-F.

Explanation: You must type a hexadecimal number (0-9, A-F) in the field indicated by the cursor.

Module: ICQADE06

ICQGC042 Data set name not valid. Correct and press ENTER.

Explanation: The data set name you typed is not valid. Correct the data set name and press the ENTER key.

Each part (qualifier) for a data set name must contain one to eight characters (A-Z, 0-9, @, #, \$). The first character must be a letter, @, #, or \$. Here is an example of a valid data set name with three qualifiers:

Model data set ==> 'KCN.A.B'

Module: ICQADE10, ICQADE13, ICQCME20

ICQGC043 Specified command is not valid. Type one of the listed options.

Explanation: The information in the OPTION field must be either one of the options listed on the panel, a valid ISPF command, or a TSO/E command preceded by TSO and a space. Type a valid command or option.

Module: ICQAMLD2

ICQGC044 Type one of the listed terminal types.

Explanation: The terminal type you specified is not allowed. Type one of the terminal types listed on the panel and press the ENTER key.

Module: ICQAEE70, ICQAIE00

ICQGC045 Type DATA, STD, MAX or PART in the SCREEN FORMAT field.

Explanation: In the SCREEN FORMAT field, type:

- DATA - If you want the screen size to be based on the data width.
- STD - If you want the screen to be 80 characters wide.
- MAX - If you want the screen to be 132 characters wide.
- PART - Only on a 3290 terminal, if you want the maximum screen size available.

For the 3278 Model 5 terminal, the SCREEN FORMAT field can contain:

- DATA - If DATA is specified, ISPF will automatically switch between "default" format (24 lines by 80 characters) and "native" format (27 lines by 132 characters) based on the width of the data to be displayed.
- STD or MAX - If STD or MAX is specified, ISPF will hold the screen format constant.

For the 3290 terminal, type PART in the SCREEN FORMAT field if you want the screen size to be the maximum available on a 3290 terminal. If you type PART and the 3290 is configured to support partitions, ISPF formats the screen depending on the 3290 screen configuration:

- 31 rows by 80 columns
- 62 rows by 80 columns
- 31 rows by 160 columns
- 62 rows by 160 columns

In addition, the SPLITIV command is enabled when the 3290 is configured to support hardware partitions. If the 3290 is not configured to support hardware partitions, then the default mode depends on the definition of the terminal to the system.

Module: ICQAEE70, ICQAIE00

ICQGC046 The specified terminal type has 12 PF keys.

Explanation: Only the 3278, 3278CF, 3278KN, and 3290A terminals are equipped with 24 PF keys. If you are defining one of these terminals, you can type 12 or 24 in the NUMBER OF PF KEYS field. Otherwise, you must type 12 in the NUMBER OF PF KEYS field.

Module: ICQAEE70, ICQAIE00

ICQGC047 Type N, B, or a special character for the INPUT FIELD PAD.

Explanation: The character entered in the INPUT FIELD PAD field indicates how you want the system to pad input fields on panels. Type:

- N - If you want the input fields to be padded with null characters.
- B - If you want the input fields to be padded with blanks.
- A special character - If you want the input fields to be padded with a special character. This special character must not be the same character used as the COMMAND DELIMITER. It cannot be a letter except N for nulls or B for blanks.

Module: ICQAEE70, ICQAIE00

ICQGC048 Type 12 or 24 in NUMBER OF PF KEYS field.

Explanation: The 3278, 3278CF, 3278KN, and 3290A terminals are equipped with 24 PF keys. If you are defining one of these terminals, you can type 12 or 24 in the NUMBER OF PF KEYS field. If the terminal has only 12 PF keys, you must type 12 in the NUMBER OF PF KEYS field.

Module: ICQAEE70, ICQAIE00

ICQGC049 Type a number at the cursor position.

Explanation: Type a number composed of the digits 0-9 at the cursor position and press the ENTER key.

Module: ICQCIE10, IQCCIE20, ICQCIE32, ICQCIE33, ICQCIE34, ICQCIE40, ICQCIE51, ICQCIE52, ICQCIE60, ICQCIE61, ICQCIE62, ICQCME45, ICQCRE20, ICQCRE30

ICQGC050 Type PD to print/delete a data set, K to keep, D to delete.

Explanation: Type one of the following letters or letter combinations:

- PD** to print the data set to the SYSOUT class or local printer you have indicated. The system will delete the data set after printing it.
- K** to keep the data set without printing it.
- D** to delete the data set without printing it.

Module: ICQAEE80, ICQAIE01

ICQGC051 Type either a SYSOUT CLASS or a LOCAL PRINTER ID.

Explanation: Because you typed PD (print & delete) in the PROCESS OPTION field, you must type either:

- The SYSOUT CLASS defined by your installation (to have the log or list data set printed on a system printer).
- The LOCAL PRINTER ID defined by your installation (to have the log or list data set printed on a local printer).

If you type K or D in the PROCESS OPTION field, the SYSOUT CLASS and LOCAL PRINTER ID fields can be blank.

Module: ICQAEE80, ICQAIE01

ICQGC052 Type a SYSOUT CLASS or a LOCAL PRINTER ID, but not both.

Explanation: Do not specify both the SYSOUT CLASS and the LOCAL PRINTER ID fields. Because you typed PD (print and then delete) in the PROCESS OPTION field, you must specify either:

- The SYSOUT CLASS defined by your installation (to have the log or list data set printed on a system printer).
- The LOCAL PRINTER ID defined by your installation (to have the log or list data set printed on a local printer).

Module: ICQAEE80, ICQAIE01

ICQGC053 For LOG, SECONDARY PAGES must be 0 when PRIMARY PAGES is 0.

Explanation: Either type a non-zero value in the PRIMARY PAGES field, or type 0 in the SECONDARY PAGES field. If no primary pages are allocated (PRIMARY PAGES = 0), then no secondary pages can be allocated.

You should specify primary/secondary allocation parameters in terms of the anticipated number of pages of printout. PRIMARY PAGES specifies the number of pages initially allocated. SECONDARY PAGES specifies the number of additional pages the system allocates for the data set if it runs out of primary space.

Module: ICQAEE80, ICQAIE01

ICQGC054 Date must be in *date_format*; *mm*, *dd*, *yy* must be numbers.

Explanation: You must type the date in the format that was defined for your system during installation. That format is *letters and separators in the format set up for your installation*.

Replace the letters in the format with numbers:

- For *mm*, type a number from 1 to 12 for the month.
- For *dd*, type a number from 1 to 31 for the day.
- For *yy*, type the last two digits of the year. For example, for 1986, type 86.

Module: ICQGIECP

ICQGC055 Type a number from 1 to 12 for the month.

Explanation: In the DATE field, you must type a number from 1 to 12 to indicate the required month.

Module: ICQGIECP

ICQGC056 Type a number from 1 to *number* for the day.

Explanation: In the DATE field, you must type a number from 1 to *number* to indicate the required day.

Module: ICQGIECP

ICQGC057 Type a request either on COMMAND line or in the action field.

Explanation: You typed an action character on the COMMAND line and next to an entry in a list. Type the action character in either one place or the other, and press the ENTER key.

Module: ICQANE10, ICQAPE00

ICQGC058 The date cannot be verified.

Explanation: The Information Center Facility does not recognize the date format set up by your installation. The Installation Date Format field was improperly coded on the System Installation Panel ICQSIE00.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQGIECP

ICQGC060 • ICQGC071

ICQGC060 Type one of the highlighted options after the OPTION arrow.

Explanation: You pressed the ENTER key without selecting an option. To select an option, type the corresponding number or letter after the OPTION arrow, and press the ENTER key. After the OPTION arrow, you can also type a valid ISPF command or a TSO/E command. The command must be preceded by the word "TSO" and a space.

Module: Any Information Center Facility selection panel

ICQGC061 To return to top selection panel, press the END PF key.

Explanation: To exit from the panel that displayed this message, type END on the COMMAND line and press the ENTER key, or press the END PF key.

On the COMMAND line, you can also type a valid ISPF command or a TSO/E command preceded by TSO and a space.

Module: ICQGAM01, ICQGCM06, ICQGCM07

ICQGC063 Requested service not available. To exit, press END.

Explanation: The panel that displayed this message is provided to allow your Information Center to add the requested service to the Information Center Facility. To exit, press the END PF key or type END on the COMMAND line and press the ENTER key.

Module: ICQGAM01, ICQGCM06, ICQGCM07

ICQGC064 INPUT FIELD PAD must be different from COMMAND DELIMITER.

Explanation: You cannot use the same character for the INPUT FIELD PAD and COMMAND DELIMITER. Change one of them.

Module: ICQAEE70, ICQAIE00

ICQGC065 User types sorted successfully.

Explanation: You should see this message only when you install a new release of the Information Center Facility. The user types are now sorted so that they can be used for the new release.

Module: ICQADC05

ICQGC066 Data set name is not valid. Correct and press ENTER.

Explanation: The data set name you typed is not valid. Correct the data set name and press the ENTER key.

Each part (qualifier) for a data set name must contain one to eight characters (A-Z, 0-9, @, #, \$). The first character must be a letter, @, #, or \$. Here is an example of a valid data set name with three qualifiers:

Model data set ==> 'KCN.A.B'

Module: ICQAPE90, ICQCLE11, ICQCLE22, ICQCME4A, ICQCME44

ICQGC070 The data accessed by this function has not been converted.

Explanation: A table from a previous release exists on your system.

User response: Contact an Information Center Facility administrator to convert the table or to allocate the correct table library.

Module: ICQGCC50

ICQGC071 Request failed; system error. Press HELP.

Explanation: Your request failed, because the following tables have not been converted to the current release level:
table names

The ISPF TBOPEN service routine set a return code of 12.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQGCC50

ICQGC072 Request failed; system error. Press HELP.

Explanation: Your request failed, because the following required library is not allocated:

library_name

The ISPF TBOPEN service routine set a return code of 16.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQGCC50

ICQGC073 Request failed; system error. Press HELP.

Explanation: A severe error occurred while the Information Center Facility was trying to verify the table level. The ISPF TBOPEN service routine set a return code of 20 while attempting to access a table from an earlier release.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQGCC50

ICQGC074 Request failed; system error. Press HELP.

Explanation: Your request failed, because the system encountered an error while verifying the input data to a CLIST program.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQGCC50

ICQGC075 Request failed; system error. Press HELP.

Explanation: Your request failed, because the system encountered an error during space management.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCGC00, ICQCGC01, ICQCGC02

ICQGC076 Request failed; system error. Press HELP.

Explanation: Your request failed, because the system could not access the data set you requested.

User response: Press the END PF key to cancel the request, and contact an Information Center Facility administrator to resolve the problem.

Module: ICQCGC00, ICQCGC01, ICQCGC02

ICQGC077 Request failed; system error. Press HELP.

Explanation: Your request failed, because the system encountered a severe error while processing the LISTDSI CLIST statement.

User response: Contact an Information Center Facility administrator to resolve the problem.

Module: ICQCGC00, ICQCGC01, ICQCGC02

ICQGC078 Request failed; data set not allocated.

Explanation: Due to an allocation error, space management could not create the data set indicated by the cursor.

The data set might not be cataloged. Space management does not handle uncataloged data sets. If this is the problem, you can use the UTILITIES option on the primary ISPF/PDF selection panel to catalog the data set.

ICQGC080 • ICQGC101

There might not be enough space on any volume to allocate the data set. If this is the problem, delete the data sets that you no longer need.

Module: ICQCGC00, ICQCGC01, ICQCGC02

ICQGC080 To select an item, type S next to it; to delete it, type D.

Explanation: To select an item, type S. To delete an item, type D. After typing S or D, press the ENTER key.

Module: ICQGCC00 ICQASE22

ICQGC081 Type S or D next to only one item at a time.

Explanation: You have typed S or D next to more than one *item*. Select or delete only one at a time.

Type only one of those characters and press the ENTER key.

Module: ICQGCC00

ICQGC082 *Data_set_name* was deleted.

Explanation: Your request to delete the data set completed successfully. This message is informational only.

Module: ICQGCC00

ICQGC083 *Data_set_name* was not deleted.

Explanation: Your data set was not deleted because you pressed the END PF key or typed CANCEL on the COMMAND line and pressed the ENTER key.

This message is informational only.

Module: ICQGCC00

ICQGC084 Request failed. The data set was not deleted.

Explanation: Your request failed, because the system could not delete the data set. Some possible causes for the failure of your deletion request are:

- The data set was migrated to tape. The tape must be mounted for you to access it.
- The data set is being used by another person. You must wait until that person is no longer using it.

Module: ICQGCC00

ICQGC085 Conversion routine ended abnormally.

Explanation: You cannot convert the tables from one release to another because table services (ICQGCL10) could not open one of the tables.

User response: Contact your system programmer for assistance.

Module: ICQGACR3

ICQGC101 Table already exists and REPLACE was not specified.

Explanation: TBCREATE tried to create a table that already exists. No REPLACE parameter was specified.

User response: Contact your system programmer for assistance.

Module: ICQGCL10

ICQGC102 Table does not exist.

Explanation: TBOPEN tried to open a table that does not exist.

User response: Contact your system programmer for assistance.

Module: ICQGCL10

ICQGC103 System error in table service.

Explanation: The ICQGCL10 module performed the requested service and encountered an error. No suitable message is available for the error condition.

User response: Contact your system programmer for assistance.

Module: ICQGCL10

ICQGC104 Table service failed for table_description. Return code return_code.

Explanation: The ICQGCL10 module performed the requested service and there was an error. This message is logged in the user's ISPF log data set and contains the service name (TBOPEN, TBCREATE, TBCLOSE, TBSAVE), the table description, and the return code from the service.

Module: ICQGCL10

ICQGC105 Table service called by module_name, id point id_point.

Explanation: The ICQGCL10 module performed the requested service and encountered an error. This message is logged in the user's ISPF log data set and contains the service name (TBOPEN, TBCREATE, TBCLOSE, TBSAVE), the calling module name (from the FROMMOD parameter) and the id point (from the FROMID parameter).

Module: ICQGCL10

ICQGC106 Error message follows:

Explanation: The ICQGCL10 module performed the requested service and encountered an error. This message is logged in the user's ISPF log data set and is used to guide the user in reading the log. It is followed by messages ICQGC107 and ICQGC108.

Module: ICQGCL10

ICQGC107 SERVICE requested:

Explanation: The ICQGCL10 module performed the requested service and encountered an error. This message is logged in the user's ISPF log data set and is used as a lead-in for message ICQGC108 that contains the actual service requested (as passed in the SERVICE parameter).

Module: ICQGCL10

ICQGC108 Text_of_error_message

Explanation: The ICQGCL10 module performed the requested service and encountered an error. This message is logged in the user's ISPF log data set and contains as much of the service call (from the SERVICE parameter) as can fit in the log data set. This may be logged multiple times, each time a portion of the service call is added.

Module: ICQGCL10

ICQGC350 Print request processing ended successfully.

Explanation: The print request completed successfully and the data is to be printed at the selected printer. This message is informational only.

System action: See the explanation.

User response: None.

ICQGC351 • ICQGC355

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC351 No selections made.

Explanation: You did not select from the selection list and pressed END. This message is informational only.

System action: See the explanation.

User response: None.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC352 Data set not found.

Explanation: The specified data set was not found in the list of data sets.

System action: The system waits for your response.

User response: Check the spelling of the data set name.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC353 Request failed; system error. Press HELP.

Explanation: The print request failed.

System action: Processing terminates.

User response: Press HELP to display additional information about the error.

User response: Contact your system programmer for further assistance.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC354 CANCEL honored.

Explanation: You typed CANCEL on the command line of the member selection list panel. Selections are not processed.

System action: See the explanation.

User response: None.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC355 Member list is not available. Press HELP.

Explanation: Because of a system error, a member list is not available for the data set you specified. The LMINIT service issued a return code. A list of possible return codes and their meanings follow:

RC	Cause
8	Data set not allocated.
12	Parameter value is not valid.
16	Truncation or translation error in accessing dialog variables.
20	Severe error; unable to continue.

System action: Processing terminates.

User response: Contact your system programmer for further assistance.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC356 Member list is not available. System error.

Explanation: A list of members from the specified data set is not available because the LMOPEN service issued a return code. A list of possible return codes and their meanings follow:

RC	Cause
8	Data set cannot be opened.
16	Truncation or translation error in accessing dialog variables.
20	Severe error; unable to continue.

System action: Processing terminates.

User response: Contact your system programmer for further assistance.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC357 Specified data set has no members.

Explanation: The data set you specified does not have any members so a list of members is not available.

System action: The system waits for your response.

User response: Check to see if you specified the correct partitioned data set.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC358 Data set is sequential; do not specify a member.

Explanation: The data set you specified is a sequential data set and sequential data sets have no members.

System action: The system waits for your response.

User response: To continue processing, blank out the member.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC359 * is only valid as the last character in the field.

Explanation: You cannot type an * in the field name.

System action: The system waits for your response.

User response: Remove the * that is not valid and correct the field name, using an * only as the last character.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC360 Project name is required.

Explanation: The project name was left blank.

System action: The system waits for your response.

User response: Type the project name or type the data set name in the Other data set field.

ICQGC361 • ICQGC365

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC361 Project name is not valid.

Explanation: The value in the project name field is not valid. Valid project names contain 1-8 characters, the first of which must be A-Z, \$, #, or @. The remaining characters can be any combination of A-Z, 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Type a valid project name.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC362 File name is not valid.

Explanation: The value in the file name field is not valid. Valid file names contain 1-8 characters, the first of which must be A-Z, \$, #, or @. The remaining characters can be any combination of A-Z, 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Type a valid file name. To request a list of valid file names, type a valid first character or group of characters followed by an * or an * by itself.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC363 File type is not valid.

Explanation: The value in the file type field is not valid. Valid file types contain 1-8 characters, the first of which must be A-Z, \$, #, or @. The remaining characters can be any combination of A-Z, 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Type a valid file type. To request a list of valid file types, type a valid first character or group of characters followed by an * or an * by itself.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC364 Member name is not valid.

Explanation: The value in the member name field is not valid. Valid member names contain 1-8 characters, the first of which must be A-Z, \$, #, or @. The remaining characters can be any combination of A-Z, 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Type a valid member name. To request a list of valid members, type a valid first character, a group of characters followed by an *, or an asterisk by itself.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC365 Specified name for the data set is not valid.

Explanation: The specified data set name is not valid. Valid data set names contain one or more qualifiers connected by periods. Each qualifier contains 1-8 characters, the first of which must be A-Z, \$, #, or @. The other characters for each qualifier can be any combination of A-Z, 0-9, \$, #, or @.

Valid data set names can contain a maximum of 44 characters including the periods that connect one qualifier to another.

System action: The system waits for your response.

User response: To continue processing, type a qualified data set name.

Module: ICQGCE35, ICQASE02, ICQASE04, ICQASE08, ICQASE10, ICQASE12, ICQASE20, ICQASE28, ICQASE30, ICQASE32, ICQASE40, ICQASE72, ICQASE74, ICQASE76, ICQASE98

Audience: Information Center Facility user

ICQGC366 Number of copies must be within the range 1-255.

Explanation: One of the following occurred:

- The value for the copies field was left blank
- The specified value is not a numeric character
- The specified value is zero or greater than 255.

System action: The system waits for your response.

User response: Type a number from 1 to 255.

Module: ICQGCE35

Audience: Information Center Facility user

ICQGC367 Data set name is incorrectly quoted.

Explanation: You either specified a character other than a single quotation mark or the data set has no single quotation marks.

System action: The system waits for your response.

User response: Remove the single quotation marks in the fields other than the Other data set field, or change the character to a single quotation mark.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC368 Data set is not allocated. Press HELP.

Explanation: The specified data set is not allocated.

System action: The system waits for your response.

User response: Check the spelling of the data set or type the name of a data set that has already been allocated.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC369 Data set is not available. Press HELP.

Explanation: The specified data set is not available. Either you are not authorized to use the data set or it is in use by another user.

System action: The system waits for your response.

User response: If you need to be authorized, contact your Information Center Facility administrator or system programmer. If the data set is in use by another user, try again later.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC370 Specified entry is not valid on the command line of this panel.

Explanation: The specified entry on the command line of the Print Request panel is not valid.

System action: The system waits for your response.

User response: Either blank out the value on the command line or type a valid entry.

ICQGC371 • ICQGC376

Module: ICQGCE35

Audience: Information Center Facility user

ICQGC371 Specify print format or part of format with * suffix.

Explanation: The print format field was left blank.

System action: The system waits for your response.

User response: Type the print format or part of the format with an * suffix in the print format field.

Module: ICQGCE35

Audience: Information Center Facility user

ICQGC373 Printer location cannot contain an apostrophe or parenthesis.

Explanation: The printer location field contains an apostrophe or parenthesis. These characters are not allowed.

System action: The system waits for your response.

User response: Remove the apostrophe or parenthesis in the printer location field.

Module: ICQGCE35

Audience: Information Center Facility user

ICQGC374 Member not found.

Explanation: The member specified for the partitioned data set was not found.

System action: The system waits for your response.

User response: Either check the spelling of the member name or request a member selection list by entering an * in the file member field.

Module: ICQGCR70

Audience: Information Center Facility user

ICQGC375 Specify file name or part of name with * suffix.

Explanation: The file name field was left blank.

System action: The system waits for your response.

User response: Type a file name or part of the name with an * suffix or an * by itself in the file name field.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC376 Specify file type or part of type with * suffix.

Explanation: The file type field was left blank.

System action: The system waits for your response.

User response: Type a file type or part of the type with an * suffix or an * by itself in the file type field.

Module: ICQGCE35, ICQASE20

Audience: Information Center Facility user

ICQGC377 Specify a printer location or *.

Explanation: The printer location field was either left blank or the specified value contains a group of characters and an *.

System action: The system waits for your response.

User response: Type a printer location or an * by itself in the printer location field.

Module: ICQGCE35

Audience: Information Center Facility user

ICQGC378 Print format is not valid.

Explanation: The value in the print format field is not valid. A valid print format value contains 1-8 characters, the first of which must be A-Z, \$, #, or @. The remaining characters can be any combination of A-Z, 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Type one of the following in the print format field:

- A valid print format
- An * by itself
- A valid first character followed by an *
- A valid group of characters followed by an *

Module: ICQGCE35

Audience: Information Center Facility user

ICQGC379 Printer type is not valid.

Explanation: The value in the printer type field is not valid. A valid printer type value contains 1-8 characters, which can be A-Z, 0-9, \$, #, or @.

System action: The system waits for your response.

User response: Type one of the following in the printer type field:

- A valid print type
- An * by itself
- A valid first character followed by an *
- A valid group of characters followed by an *

Module: ICQGCE35

Audience: Information Center Facility user

ICQGC401 Selection character is not valid. Enter S or blank.

Explanation: The value in the selection column is not valid.

System action: The system waits for your response.

User response: Type an S or a blank in the S column.

Module: ICQGCE50

Audience: Information Center Facility user

ICQGC402 Members processed. Press END to exit or type CANCEL.

Explanation: The selected members on the Member List panel have been processed.

System action: The system waits for your response.

User response: Press END to exit or type CANCEL to cancel.

Module: ICQGCE50

Audience: Information Center Facility user

ICQGC403 • ICQGC991

ICQGC403 *Specified_entry* is not valid on the command line of this panel.

Explanation: The specified entry on the command line of the Member List panel is not valid.

System action: The system waits for your response.

User response: Either blank out the entry on the command line or type a valid entry.

Module: ICQGCE50

Audience: Information Center Facility user

ICQGC404 Command conflict. END not processed.

Explanation: You selected members, but typed CANCEL on the command line and then pressed END.

System action: The system waits for your response.

User response: Either type CANCEL on the command line and press ENTER to cancel; or blank out CANCEL on the command line and press END to process the selections.

Module: ICQGCE50

Audience: Information Center Facility user

ICQGC989 The user's specified private table data set, *dsname*, is unavailable. Processing will continue without private-level tables.

Explanation: The table data set is unavailable. Another user may have allocated the data set with a disposition of OLD.

System action: Processing continues.

User response: Try again later.

Module: ICQICF

Audience: Information Center Facility user

ICQGC990 Error allocating ISPF profile. The error message is above.

Explanation: The user's ISPF profile was not allocated. The error message displayed above contains more information.

This message is displayed in line mode. Message HELP is not available.

System action: Processing terminates.

User response: Contact your system programmer for assistance.

Module: ICQICF

Audience: Information Center Facility user

ICQGC991 Error copying ISPF profile for use by the Information Center Facility.

Explanation: The user's ISPF profile was not copied. This message is displayed in line mode. Message HELP is not available.

System action: Processing terminates.

User response: Contact your system programmer for assistance.

Module: ICQICF

Audience: Information Center Facility user

ICQGC992 Error copying ISPF edit profile for use by the Information Center Facility.

Explanation: The user's ISPF edit profile was not copied. This message is displayed in line mode. Message HELP is not available.

System action: Processing terminates.

User response: Contact your system programmer for assistance.

Module: ICQICF

Audience: Information Center Facility user

ICQGC993 ISPF may not be active when this command is entered.

Explanation: ISPF is active. It must not be active when you issue ICQICF. This message is displayed in line mode. Message HELP is not available.

System action: Processing terminates.

User response: Contact your system programmer for assistance.

Module: ICQICF

Audience: Information Center Facility user

ICQGC994 The user's specified group table data set, *dsname*, does not exist. Processing will continue without group-level applications.

Explanation: The data set required for group table applications does not exist.

System action: Processing continues.

User response: Do one of the following:

- Select the group Application Manager to have the tables created for you.
- Select the Group Specification panel and change the name of the group you were using.

Module: ICQICF

Audience: Information Center Facility user

ICQGC995 Error allocating the user's group table library, *library_name*. Processing will continue without the group library.

Explanation: The allocation was unsuccessful. Another user may have allocated the data set with a disposition of OLD.

System action: Processing continues.

User response: Try again later or contact your system programmer.

Module: ICQICF

Audience: Information Center Facility user

ICQGC996 The user's specified private table data set, *dsname*, does not exist. Processing will continue without private-level applications.

Explanation: The data set required for private-level applications does not exist.

System action: Processing continues.

User response: Do one of the following:

- If you do not want to have your own private applications, ignore this message.
- To create the required data set for private-level applications, select the private Application Manager through the Programmer Services panel.

Module: ICQICF

ICQGC997 • ICQSP001

Audience: Information Center Facility user

ICQGC997 Error allocating the user's private table library, *library_name*. Processing will continue without private-level applications.

Explanation: The allocation was unsuccessful.

System action: Processing continues.

User response: Do one of the following:

- If you do not have private applications defined, ignore this message.
 - If you have private-level applications, contact your system programmer.
 - To create your own applications, select the private Application Manager through the Programmer Services panel.
-

ICQGC998 The user's specified group table data set specification is not valid. Processing will continue without group-level applications.

Explanation: An error reading the ICQGROUP member of the ISPF.PROFILE data set occurred.

System action: Processing continues.

User response: Do one of the following:

- Delete the ICQGROUP member from your ISPF.PROFILE data set and reselect an application group on the Programmer Services panel.
- If the error continues, contact your system programmer.

Module: ICQICF

Audience: Information Center Facility user

ICQGC999 The user's specified group table data set specification, *dsname*, is unavailable. Processing will continue without group-level applications.

Explanation: The table data set is unavailable. Another user may have allocated the data set with a disposition of OLD.

System action: Processing continues.

User response: Try again later.

Module: ICQICF

Audience: Information Center Facility user

ICQSP000 Space management successfully managed the data set.

Explanation: Space management successfully managed the following data set for you:

data_set_name

Space management checked the specified data set:

- If the data set needed more space, space management compressed or enlarged it.
- If the data set did not exist, space management created it.

You can continue to use the data set. This message is informational only.

Module: ICQSPC00

ICQSP001 The specified data set does not need more space.

Explanation: Space management checked the following data set and found that it has not reached its space limit:

data_set_name

Space management did nothing to the data set. You can continue to use the data set. This message is informational only.

Module: ICQSPC00

ICQSP002 Space management compressed the data set currently in use.

Explanation: Space management successfully compressed the following data set:

data_set_name

Either the data set reached its space limit and needed to be compressed or the application using space management requested an unconditional compress.

You can continue to use the data set. This message is informational only.

Module: ICQSPC00

ICQSP003 The directory of the data set currently in use was enlarged.

Explanation: Space management enlarged the directory of the following data set because it was running out of space:

data_set_name

You can continue to use the data set. This message is informational only.

Module: ICQSPC00

ICQSP004 Space management increased the amount of primary space.

Explanation: Space management increased the primary space quantity of the following data set because it was running out of space:

data_set_name

You can continue to use the data set. This message is informational only.

Module: ICQSPC00

ICQSP005 The amount of directory and primary space was increased.

Explanation: Space management enlarged the directory and primary space quantity of the following data set:

data_set_name

You can continue to use the data set. This message is informational only.

Module: ICQSPC00

ICQSP006 Space management created a data set; application request.

Explanation: Space management created the following data set for you:

data_set_name

Space management created the data set because the application using space management specified ALLOCATENEW=YES as input to CLIST ICQSPC00. This message is informational only.

Module: ICQSPC00

ICQSP010 A space management input parameter is not valid.

Explanation: An application using space management specified an incorrect parameter as input to the space management CLIST, ICQSPC00. The data set being managed is:

data_set_name

Check the invocation of CLIST ICQSPC00, correct any errors, and invoke the CLIST again.

ICQSP011 • ICQSP015

Module: ICQSPC00, ICQSPE02

ICQSP011 DSNAME is not valid.

Explanation: An application using space management specified the following as the name of the data set that CLIST ICQSPC00 is to manage:

data_set_name

That name is not a valid data set name. For information about naming a data set, see *z/OS TSO/E User's Guide*. In addition, note that you must enclose a fully-qualified data set name in quotes.

Correct the data set's name and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP012 SPACEFULL is not valid. It must be an integer, 0 - 100.

Explanation: An application using space management specified the SPACEFULL parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the percentage that the data set can be full before it is compressed or enlarged.

Either correct the value of the SPACEFULL parameter or omit the parameter and use its default value, which is 80; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP013 SPACEINCREASE is not valid. It must be an integer.

Explanation: An application using space management specified the SPACEINCREASE parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the percentage that the primary extent of the data set is to be increased in size when the data set is enlarged.

Either correct the value of the SPACEINCREASE parameter or omit the parameter and use its default value, which is 50; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP014 KBYTESFREE is not valid. It must be an integer or blank.

Explanation: An application using space management specified the KBYTESFREE parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the minimum number of kilobytes that must be free in the data set. If this amount of space is not free, space management compresses or enlarges the data set.

Correct the KBYTESFREE parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP015 DIRFULL is not valid. It must be an integer, 0 - 100.

Explanation: An application using space management specified the DIRFULL parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the percentage that the directory of the data set must be full before it is compressed or enlarged.

Either correct the DIRFULL parameter or omit the parameter and use its default value, which is 80; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP016 DIRINCREASE is not valid. It must be an integer.

Explanation: An application using space management specified the DIRINCREASE parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the percentage that the directory of data set is to be increased when the data set is enlarged.

Either correct the DIRINCREASE parameter or omit the parameter and use its default value, which is 50; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP017 DIRBLOCKSFREE is not valid. It must be an integer or blank.

Explanation: An application using space management specified the DIRBLOCKSFREE parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the minimum number of directory blocks that the data set must have free. If this number of directory blocks is not free, space management compresses or enlarges the data set.

Correct the DIRBLOCKSFREE parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP018 RECALL is not valid. It must be YES or NO.

Explanation: An application using space management specified the RECALL parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates whether to recall the data set if HSM has migrated it.

Either correct the value of the RECALL parameter or omit the parameter and use its default value, which is YES; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP019 PROTECTNEW is not valid. It must be YES or NO.

Explanation: An application using space management specified the PROTECTNEW parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates whether a new data set is to have RACF protection.

Either correct the value of the PROTECTNEW parameter or omit the parameter and use its default value, which is NO; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP021 RACFUACC is not valid. It must be NONE, READ, UPDATE or ALTER.

Explanation: An application using space management specified the RACFUACC parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the universal RACF access that a new or enlarged data set is to have. Space management

ICQSP022 • ICQSP025

uses this parameter if RACF 1.6 or an earlier release of RACF is installed on your system or if the data set specified is not protected with a discrete RACF profile.

Either correct the value of the RACFUACC parameter or omit the parameter and use its default value, which is NONE; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP022 ALLOWPASSWORDS is not valid. It must be YES or NO.

Explanation: An application using space management specified the ALLOWPASSWORDS parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates whether space management is to manage password-protected data sets. If ALLOWPASSWORDS=YES, space management prompts the user for the password when it is needed. If ALLOWPASSWORDS=NO, space management does not manage password-protected data sets.

Either correct the value of the ALLOWPASSWORDS parameter or omit the parameter and use the default value, which is NO; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP023 REALLOCATENEW is not valid. It must be YES or NO.

Explanation: An application using space management specified the REALLOCATENEW parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates whether to enlarge the data set if it is running out of space.

Either correct the value of the REALLOCATENEW parameter or omit the parameter and use its default value, which is YES; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP024 ALLOCATENEW is not valid. It must be YES, NO, or ASK.

Explanation: An application using space management specified the ALLOCATENEW parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

If the specified data set does not exist, this parameter tells space management to create a new data set (YES), not to create a new data set (NO), or to ask the user whether to create a new data set (ASK).

Either correct the value of the ALLOCATENEW parameter or omit the parameter and use its default value, which is ASK; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP025 PRIMSPACE is not valid. It must be an integer or blank.

Explanation: An application using space management specified the PRIMSPACE parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the number of primary space units to be used when creating a new data set.

Correct the value of the PRIMSPACE parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP026 SECSPACE is not valid. It must be an integer or blank.

Explanation: An application using space management specified the SECSPACE parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the number of secondary space units to be used when creating a new data set.

Correct the value of the SECSPACE parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP027 UNITS not valid. It must be TRACKS, CYLINDERS, or blank.

Explanation: An application using space management specified the UNITS parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the space units to be used when creating a new data set. Use the BLKSIZE parameter to specify the space units in blocks.

Correct the value of the UNITS parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP028 DIRBLOCKS is not valid. It must be an integer or blank.

Explanation: An application using space management specified the DIRBLOCKS parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the number of directory blocks to be allocated for a new data set.

Correct the value of the DIRBLOCKS parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP029 BLKSIZE not valid. It must be an integer, 1-32760, or blank.

Explanation: An application using space management specified *block_size* for the BLKSIZE parameter when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the block size to be used when creating a new data set.

Correct the value of the BLKSIZE parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP030 LRECL is not valid. It must be an integer, 1-32756, or blank.

Explanation: An application using space management specified the LRECL parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the logical record length to be used when creating a new data set.

Correct the value of the LRECL parameter and invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP031 RECFM is not valid. It must be alphabetic or blank.

Explanation: An application using space management specified the RECFM parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates the record format to be used when creating a new data set.

Correct the RECFM parameter and invoke CLIST ICQSPC00 again. See the description of the ALLOCATE command in *z/OS TSO/E Command Reference* for the correct values of RECFM.

Module: ICQSPE02

ICQSP032 LIKE is not valid. It must be a valid data set name or blank.

Explanation: An application using space management specified an incorrect value for the LIKE parameter when it invoked CLIST ICQSPC00.

This parameter identifies the data set that is to be used as a model when creating the following data set:

data_set_name

Correct the data set name and invoke CLIST ICQSPC00 again. Note that you must enclose a fully-qualified data set name in quotes.

Module: ICQSPE02

ICQSP035 INFOPANEL is not valid. It must be non-blank.

Explanation: An application using space management specified a blank value for the INFOPANEL parameter when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter identifies the panel that is to be displayed when space management is obtaining more space for the specified data set.

Either provide a correct value for the INFOPANEL parameter or omit the parameter and use its default value, which is ICQSPE00; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP036 ASKPANEL is not valid. It must be non-blank.

Explanation: An application using space management specified a blank value for the ASKPANEL parameter when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter identifies the panel that asks users whether they want to create a new data set. The application using space management must also specify ALLOCATENEW=ASK to ask users whether they want to create a new data set.

Correct the ASKPANEL parameter or omit the parameter and use its default value, which is ICQSPE01; then invoke CLIST ICQSPC00 again.

Module: ICQSPE02

ICQSP037 VERIFYPARMS is not valid. It must be YES or NO.

Explanation: An application using space management specified the VERIFYPARMS parameter incorrectly when it invoked CLIST ICQSPC00 to manage the following data set:

data_set_name

This parameter indicates whether to check the syntax of the input parameters of CLIST ICQSPC00.

Either correct the VERIFYPARMS parameter or omit the parameter and use its default value, which is YES; then invoke CLIST ICQSPC00 again.

Module: ICQSPC00

ICQSP040 Space management could not manage the specified data set.

Explanation: Space management could not manage data set

data_set_name for one of these reasons:

- A LISTDSI error occurred.
- The data set is not partitioned or sequential.
- An error occurred creating or enlarging the data set.
- The application invoked CLIST ICQSPC00 using a parameter that prevented the data set from being managed.
- An allocation error occurred.

Check the invocation of CLIST ICQSPC00, make any corrections necessary, and invoke the CLIST again. If the invocation is correct, contact an Information Center Facility administrator.

Module: ICQSPC00

ICQSP041 The data set could not be managed; it is password protected.

Explanation: The following data set is password-protected and space management could not manage it:

data_set_name

When the ALLOWPASSWORDS parameter of CLIST ICQSPC00 is NO, space management does not manage a password-protected data set. To have space management manage this data set, specify ALLOWPASSWORDS=YES and invoke CLIST ICQSPC00 again.

Module: ICQSPC00

ICQSP042 Data set could not be managed; not sequential or partitioned.

Explanation: The following data set is not sequential or partitioned:

data_set_name

Space management manages only sequential (PS) or partitioned (PO) data sets. Check the organization of specified data set.

Module: ICQSPC00

ICQSP043 A LISTDSI error occurred. Press HELP.

Explanation: The following LISTDSI error occurred when space management was trying to obtain information about a data set:

LISTDSI error

The data set being managed is:

data_set_name

For information about the LISTDSI CLIST statement, see *z/OS TSO/E CLISTS*.

Module: ICQSPC00

ICQSP044 The data set specified does not exist and cannot be created.

Explanation: The following data set does not exist:

data_set_name

When the ALLOCATENEW parameter of CLIST ICQSPC00 is NO, space management does not create the new data set. To have space management create the data set, specify ALLOCATENEW=YES and invoke the CLIST again. To have space management ask the user whether to create the data set, specify ALLOCATENEW=ASK and invoke the CLIST again.

ICQSP045 • ICQSP049

Module: ICQSPC00

ICQSP045 The data set was not created; insufficient authority.

Explanation: Space management could not create the following data set because you do not have the RACF authority to create it:

data_set_name

Request RACF authorization from the owner or the security administrator.

Module: ICQSPC00

ICQSP046 Data set was not created; allocation error.

Explanation: The following allocation error occurred when space management tried to create a data set:

allocation error

The data set that could not be created is:

data_set_name

Possible reasons for the error are that an uncataloged data set with the same name resides on the volume that space management is using or there is not enough space on any volume to allocate it.

User response: You can use the UTILITIES option on the primary ISPF/PDF selection panel to catalog the uncataloged data set and invoke CLIST ICQSPC00 again. To obtain more space, contact the system programmer.

Module: ICQSPC00

ICQSP047 Data set was not created. ADDSD return code = *ADDSD return_code*.

Explanation: An error occurred when space management used the RACF command, ADDSD, to protect the following new data set:

data_set_name

Space management was trying to protect the data set using the following value for the RACFUACC parameter of CLIST ICQSPC00:

universal RACF access

User response: For information about the return codes of the ADDSD command, see *z/OS Security Server RACF Command Language Reference*.

Module: ICQSPC00

ICQSP048 Data set was not created; user request.

Explanation: You replied no when asked if you wanted to create the following data set:

data_set_name

Module: ICQSPC00

ICQSP049 Data set was not compressed. IEBCOPY return code = *IEBCOPY_return_code*.

Explanation: Space management could not compress the following partitioned data set:

data_set_name

An error occurred when space management used IEBCOPY to copy the data from the original data set to a larger data set.

For information about the return codes of IEBCOPY, see *z/OS DFSMSdfp Utilities*.

Module: ICQSPC00

ICQSP050 The data set was not enlarged; application request.

Explanation: Space management cannot enlarge the following data set:

data_set_name

When the REALLOCATENEW parameter of CLIST ICQSPC00 is NO, space management does not enlarge the data set if it is running out of space. To have space management enlarge the data set, specify REALLOCATENEW=YES and invoke the CLIST again.

Module: ICQSPC00

ICQSP051 The data set was not enlarged; insufficient authority.

Explanation: Space management could not enlarge the following data set because it is RACF-protected and you do not have sufficient authority to enlarge it:

data_set_name

Request authorization from the data set owner or the security administrator.

Module: ICQSPC00

ICQSP052 The data set was not enlarged; allocation error.

Explanation: Space management could not enlarge the following data set because an error occurred during allocation:

data_set_name

The allocation error was:

allocation error

For information about the ALLOCATE command, see *z/OS TSO/E Command Reference*.

Module: ICQSPC00

ICQSP053 The data set was not enlarged; ADDSD return code = *ADDSO_return_code*.

Explanation: Space management attempted to enlarge and protect the following data set:

data_set_name

An error occurred when space management used the RACF command, ADDSD, to protect the enlarged data set. The enlarged data set is not available, but the original data set is available.

For information about the return codes of the ADDSD command, see *z/OS Security Server RACF Command Language Reference*.

Module: ICQSPC00

ICQSP054 The data set was not enlarged; PERMIT return code = *PERMIT_return_code*.

Explanation: An error occurred enlarging the following data set:

data_set_name

The error occurred when space management issued the PERMIT command to give the appropriate RACF protection to the enlarged data set.

For information about the return codes of the PERMIT command, see *z/OS Security Server RACF Command Language Reference*.

Module: ICQSPC00

ICQSP055 • ICQSP431

ICQSP055 The data set was not enlarged; IEBCOPY return code = *IEBCOPY_return_code*.

Explanation: Space management could not enlarge the following partitioned data set:

data_set_name

An error occurred when space management used IEBCOPY to copy the data from the original data set to a larger data set.

For information about the return codes of IEBCOPY, see *z/OS DFSMSdfp Utilities*.

Module: ICQSPC00

ICQSP056 The data set was not enlarged; DELETE return code = *DELETE_return_code*.

Explanation: Space management copied the data in the following data set to a larger temporary data set:

data_set_name

An error occurred when space management tried to delete the original data set. Space management must delete the original data set so that it can change the name of the temporary data set to the name of the original data set.

For information about the DELETE command, see *z/OS TSO/E Command Reference*.

Module: ICQSPC00

ICQSP057 Data set was enlarged but renamed; an enlarge error occurred.

Explanation: To enlarge the following data set:

data_set_name

space management temporarily changed its name to:

temporary_data_set_name

Space management was not able to change the temporary data set name to the original name.

User response: Try to rename the data set using the RENAME command. If that fails, contact an Information Center Facility administrator. For information about the RENAME command, see *z/OS TSO/E Command Reference*.

Module: ICQSPC00

ICQSP058 Data set was not enlarged; IEBGENER return code = *IEBGENER_return_code*.

Explanation: Space management could not enlarge the following sequential data set:

An error occurred when space management used IEBGENER to copy the data from the original data set to a larger data set.

For information about the return codes of IEBGENER, see *z/OS DFSMSdfp Utilities*.

Module: ICQSPC00

ICQSP431 You are not authorized to read the specified data set.

Explanation: Space management could not obtain information about the following data set because RACF determined that you are not authorized to read it:

data_set_name

Request authorization to read the data set from the data set owner or the security administrator at your installation.

Module: ICQSPC00

ICQSP432 Data set not available; migrated and not recalled.

Explanation: Space management could not access the following data set because HSM migrated it and the application using space management specified not to recall it.

data_set_name

The RECALL=NO parameter of CLIST ICQSPC00 indicates that HSM is not to recall a data set that it migrated. To have HSM recall the data set, either specify RECALL=YES or omit the parameter and use its default value, which is YES.

Module: ICQSPC00

ICQSP433 Data set not available; HSM migrated to a non-DASD device.

Explanation: Space management could not obtain information about the following data set because HSM migrated it to a non-DASD device:

data_set_name

To access the data set, have it restored to a DASD device and invoke CLIST ICQSPC00 again.

Module: ICQSPC00

ICQSP434 Data set not available; it is not on a DASD device.

Explanation: Space management could not obtain information about the following data set because either it does not reside on a DASD device, or it resides on a mass storage device.

data_set_name

Have the data set restored to a direct access device and invoke CLIST ICQSPC00 again.

Module: ICQSPC00

ICQSP435 Data set not available; volume containing it is not mounted.

Explanation: Space management could not obtain information about the following data set because the volume containing it is not mounted.

data_set_name

Have the volume on which the data set resides mounted and invoke CLIST ICQSPC00 again.

Module: ICQSPC00

Chapter 5. TSO/E terminal messages (IDY...)

Component name	IDY
Program producing message	TSOLIB command
Audience and where produced	For terminal user: at the terminal. For system programmer: SYSPRINT listing.
Message format	<p><i>IDYxxyyy</i> <i>xx</i> System module prefix (in decimal). <i>yyy</i> Message serial number identifying the program that issued the message. <i>n</i> Type code:</p> <ul style="list-style-type: none"> A Action. The terminal user must perform the action specified in the message text. E Error; processing terminates. I Information; no action is required.
Comments	<p>The words printed in italics in the message text indicate that the system supplies specific information which varies depending on the circumstances. That information is available only when the system displays the message at the terminal.</p> <p>A plus sign (+) after the message text indicates that more information is available on-line. To receive more information, type a question mark (?) and press the Enter key. Many messages in this section have no message ID (number). These messages follow and refer back to a message marked with a plus sign (+).</p>

IDY00001I TSOLIB terminated. Insufficient virtual storage to satisfy request.+

Explanation: The TSOLIB command processor needs to obtain more virtual storage than is currently available.

System action: The TSOLIB command processor abnormally terminates.

User response: Try to deactivate some libraries, or obtain a larger region size. For help, contact the person who defines your region size.

Module: IDYTSLIB, IKJDYLB2

Audience: TSOLIB user

IDY00007I TSOLIB terminated. Extraneous information specified.+

Explanation: You specified two or more operands on the TSOLIB command that conflict with one another. This message is accompanied by one of the following messages describing what operands are in error.

Specify a data set list or DDNAME only when activating a TSOLIB library.

Specify the COND or UNCOND operands only when activating a TSOLIB library.

System action: The TSOLIB command processor terminates.

User response: Check the operands entered to see which of the operands was in error.

Module: IDYTSLIB

IDY00009I • IDY00014I

Audience: TSOLIB user

IDY00009I TSOLIB terminated. Member names are not allowed.+

Explanation: You specified a member name in the list of data sets for the DATASET or DSNAME operand. A member name is not allowed.

System action: The TSOLIB command processor terminates.

User response: Issue the TSOLIB command specifying only the names of partitioned data sets in the list of data set names.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00010I TSOLIB terminated. Exceeded maximum number of data sets.+

Explanation: You specified more than 15 data sets in the list of data sets for the DATASET or DSNAME operand.

System action: The TSOLIB command processor terminates.

User response: Issue the TSOLIB command specifying no more than 15 data set names.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00012I TSOLIB terminated. Incorrect use of * operand.+

Explanation: You specified an asterisk when activating a TSOLIB load library. This is not valid.

System action: The TSOLIB command processor terminates.

User response: Issue the TSOLIB command specifying a correct operand.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00013I TSOLIB terminated. *value* is not valid for the *operand* operand.+

Explanation: The *value* you have specified for the named operand is not valid. The only valid operands are COND, NOCOND, or QUIET.

System action: The TSOLIB command processor terminates.

User response: Specify either COND, NOCOND, or QUIET.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00014I TSOLIB terminated. DDNAME *ddname* not previously allocated.+

Explanation: The *ddname* you specified as a load module library is either not permanently allocated or not allocated at all.

System action: The TSOLIB command processor terminates.

User response: Before issuing the TSOLIB command, issue the ALLOCATE command specifying a list of data sets and the same file name you specified for the TSOLIB command. Then, reissue the TSOLIB command. This process ensures that the *ddname* is permanently allocated. When you are ready to deactivate the *ddname*, you can also free the file name with the FREE command.

If you access dynamic allocation directly using SVC 99, you need to specify the permanently allocated attribute. For more information about this attribute, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00015I TSOLIB terminated. Load library already active and COND operand was specified.

Explanation: Using the COND operand, you specified that you wanted a load library activated only if a library was not already active.

System action: The TSOLIB command processor terminates.

User response: Issue the TSOLIB command with the DISPLAY operand. From the messages TSOLIB displays, decide if you want to activate the load library with the NOCOND operand.

Module: IKJDYLB2

Audience: TSOLIB user

IDY00016I TSOLIB terminated. DDNAME *ddname* is allocated to the terminal.+

Explanation: The specified ddname that is to act as the TSOLIB library is allocated to the terminal. TSOLIB does not allow you to use the terminal as the device from which to fetch load modules.

System action: The TSOLIB command processor terminates.

User response: Issue the ALLOCATE command specifying a list of data sets, or an existing allocation using the FILE parameter.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00017I TSOLIB terminated. Severe error occurred in IKJDAIR.+

Explanation: The TSO/E program IKJDAIR encountered an error when attempting to check the allocation of a ddname. This message is accompanied by the following message:

IKJDAIR return code is *return_code*.

System action: The TSOLIB command processor terminates.

User response: Reissue the TSOLIB command. If the problem recurs, contact your system programmer for assistance, or consult *z/OS TSO/E Programming Services* to interpret the return code.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00019I TSOLIB terminated. Severe error allocating data sets for the DATASET operand.+

Explanation: Dynamic allocation encountered an error when attempting to allocate a data set.

This message is accompanied by one of the following messages which further describes the reason the TSOLIB command failed.

System action: The TSOLIB command processor terminates.

[Message text returned by dynamic allocation regarding the SVC99 error.]

User response: Check the specified data set to see if the cause of the error can be determined.

Dynamic allocation return code *return_code* **reason code** *reason_code*.

User response: Contact your system programmer or consult *z/OS MVS Programming: Authorized Assembler Services Guide* to interpret the return and reason codes.

Data set *dsname* **is not a partitioned data set.**

User response: A data set that is not partitioned is specified in the list of data sets. Only partitioned data sets can be specified using the TSOLIB command. Issue the TSOLIB command specifying only the names of partitioned data sets.

Module: IKJDYALC

IDY00020I • IDY00024I

Audience: TSOLIB user

IDY00020I Unable to free previously allocated data sets. Enter ? for more information.+

Explanation: Dynamic allocation encountered an error when attempting to deallocate a data set.

System action: This is a warning. The TSOLIB command continues after issuing the message. If you issued the TSOLIB command to DEACTIVATE or RESET TSOLIB load libraries, these libraries will no longer be searched. The allocation of the ddname specified in the message will not change. This message is accompanied by further messages describing the reason the TSOLIB command failed:

[Message text is provided by dynamic allocation regarding the SVC99 error.]

User response: Check the specified ddname to see if the cause of the error can be determined.

Dynamic allocation return code *return_code* **reason code** *reason_code*

User response: Contact your system programmer for assistance, or consult *z/OS MVS Programming: Authorized Assembler Services Guide* to interpret the return and reason codes.

Module: IKJDYALC

Audience: TSOLIB user

IDY00022I Current search order (by DDNAME) is:

Explanation: You specified the TSOLIB command with the DISPLAY operand. The TSOLIB command processor issues this message to show any ddnames that are currently being searched.

System action: This is information only.

User response: None.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00023I DDNAME = *ddname*

Explanation: You specified the TSOLIB command with the DISPLAY operand. The TSOLIB command processor displays the active one.

System action: This is information only.

User response: None.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00024I DDNAME = *ddname* (STACKED)

Explanation: You specified the TSOLIB command with the DISPLAY operand. The TSOLIB command processor displays one or a set of ddnames. The first ddname displayed with message IDY00023I is the active one. All other ddnames displayed are stacked and inactive.

To activate a stacked ddname, you need to invoke the TSOLIB command with the DEACTIVATE operand.

System action: This is information only.

User response: None.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00028I Current Load Library not established by TSOLIB.

Explanation: TSOLIB detected that the current load library was not activated by the TSOLIB command processor. Maybe a STEPLIB was coded within the logon procedure.

System action: This is information only.

User response: None.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00029I There are no libraries identified for TSOLIB being searched.

Explanation: You specified the TSOLIB command with the DISPLAY operand, but all activated levels have been deactivated previously with the DEACTIVATE operand. The TSOLIB command processor issues this message to show that no levels are currently being searched.

System action: This is information only.

User response: Use the ACTIVATE operand to activate one or more levels for searching.

Module: IDYTSLIB, IKJDYLB2

Audience: TSOLIB user

IDY00030I TSOLIB terminated. Too many libraries activated.+

Explanation: The TSOLIB command processor needs to obtain more virtual storage than is currently available. The message is accompanied by the following message:

TSOLIB return code *return_code*

System action: The TSOLIB command processor abnormally terminates.

User response: Try to deactivate some libraries, or obtain a larger region size. For help, contact the person who defines your region size.

Module: IKJDYLB2

Audience: TSOLIB user

IDY00032I TSOLIB terminated. Unable to establish recovery environment.+

Explanation: The TSOLIB command processor could not establish recovery. This message is accompanied by the following message:

ESTAE macro return code is *return_code*

System action: The TSOLIB command processor terminates.

User response: Reissue the TSOLIB command. If the problem recurs, contact your system programmer for assistance.

Module: IDYTSLIB

Audience: TSOLIB user

IDY00041I TSOLIB abnormally terminated.+

Explanation: An unexpected error occurred in the TSOLIB command, causing it to abnormally terminate. The message is accompanied by the following message:

(SYSTEM|USER) ABEND CODE *abend_code* **REASON CODE** *reason_code*

System action: The TSOLIB command processor abnormally terminates.

User response: Contact your system programmer for assistance in diagnosing problems with the TSOLIB command processor.

IDY00042I • IDY00045I

Module: IKJDYTB2

Audience: TSOLIB command user

IDY00042I TSOLIB terminated. A valid TSOLIB environment could not be found.+

Explanation: Using the DEACTIVATE command operand the system expected to find a previously activated TSOLIB environment, but could not find one for the current request.

System action: The TSOLIB command processor terminates.

User response: Use the TSOLIB command with its DISPLAY operand to determine the number of stacked activation requests. If the TSOLIB command causing this message is issued from a CLIST or REXX exec, contact your system programmer for assistance in diagnosing problems with the TSOLIB environment.

Module: TSOLIB

Audience: TSOLIB command user

IDY00043I TSOLIB terminated. A valid TSOLIB environment does not exist.+

Explanation: To invoke the TSOLIB command you need to be in TSO/E READY mode. The message is accompanied by the following message:

The TSOLIB command processor cannot be invoked in a dynamic TSO/E environment.

System action: The TSOLIB command processor terminates.

User response: Invoke the TSOLIB command from a valid TSO/E environment (READY mode).

Module: IDYTSLCH

Audience: TSOLIB command user

IDY00044I TSOLIB terminated. A valid TSOLIB environment does not exist.+

Explanation: The TSOLIB command needs to be invoked either from TSO/E READY mode, or from an unauthorized TSO/E environment. The message is accompanied by the following message:

The TSOLIB command processor cannot be invoked in an APF-authorized environment.

System action: The TSOLIB command processor terminates.

User response: Invoke the TSOLIB command from a valid TSO/E environment (READY mode) or from an unauthorized environment.

Module: IDYTSLCH

Audience: TSOLIB command user

IDY00045I TSOLIB terminated. A valid TSOLIB environment does not exist.+

Explanation: The TSOLIB command needs to be invoked either from TSO/E READY mode, or from an unauthorized TSO/E environment. The message is accompanied by the following message:

The TSOLIB command with the ACTIVATE, DEACTIVATE, or RESET operands cannot be invoked in an isolated TSO/E environment.

System action: The TSOLIB command processor terminates.

User response: Invoke the TSOLIB command from a valid TSO/E environment (READY mode) or from an unauthorized environment.

Module: IDYTSLCH

Audience: TSOLIB command user

IDY00046I TSOLIB terminated. A valid TSOLIB environment does not exist.+

Explanation: The TSOLIB command needs to be invoked either from TSO/E READY mode, or from an unauthorized TSO/E environment. The message is accompanied by the following message:

The TSOLIB command with the ACTIVATE, DEACTIVATE, or RESET operands must be invoked from the TSO/E READY environment.

System action: The TSOLIB command processor terminates.

User response: Invoke the TSOLIB command from a valid TSO/E environment (READY mode) or from an unauthorized environment.

Module: IDYTSLCH

Audience: TSOLIB command user

IDY00047I TSOLIB terminated. Internal processing error.+

Explanation: The TSOLIB command processor detected an internal error. The message is accompanied by the following message:

Internal processing RC = *return_code*

System action: The TSOLIB command processor terminates.

System action: The TSOLIB command processor terminates.

User response: Contact your system programmer for assistance in diagnosing the internal processing return code.

User response: None

Module: IKJCMDPC

Audience: TSOLIB command user

IDY00048I TSOLIB terminated. Internal processing error.+

Explanation: The TSOLIB command processor detected an internal error. The message is accompanied by the following message:

Internal processing RC = *return_code* ERROR = *error_code*

System action: The TSOLIB command processor terminates.

User response: Contact your system programmer for assistance in diagnosing the internal processing return and error codes.

User response: None

Module: IKJCMDPC

Audience: TSOLIB command user

IDY00049I TSOLIB terminated. Internal processing error.+

Explanation: The TSOLIB command processor detected an internal error. The message is accompanied by the following message:

Internal processing RC = *return_code* ABEND = *abend_code* REASON = *reason_code*

System action: The TSOLIB command processor abnormally terminates.

System action: The TSOLIB command processor terminates.

User response: Contact your system programmer for assistance in diagnosing the internal processing return code, abend code, and the abend reason code.

User response: None

Module: IKJCMDPC

IDY00050I • IDY00052I

Audience: TSOLIB command user

IDY00050I 'DAIRFAIL MSG1'+

Explanation: The TSOLIB command processor encountered an error when invoking IKJEFF02. IKJEFF02 returns a buffer containing a DAIRFAIL error message 'DAIRFAIL_MSG1'. This message might be accompanied by another DAIRFAIL message 'DAIRFAIL_MSG2':

'DAIRFAIL_MSG2'

System action: The TSOLIB command processor terminates.

User response: Reissue the TSOLIB command. If the problem recurs, contact your system programmer for assistance, or consult *z/OS TSO/E Programming Services* to interpret the DAIRFAIL messages.

Module: IKJDYALC

Audience: TSOLIB user

IDY00051I TSOLIB terminated. Authorization failure.+

Explanation: The TSOLIB command processor is not authorized for opening a ddname. The message is accompanied by the following message:

Unable to OPEN the library or libraries specified on the DATASET or FILE operand.

System action: The TSOLIB command processor abnormally terminates.

User response: Get access for the data set to be opened by the TSOLIB command processor.

Module: IKJDYDCB

Audience: TSOLIB command user

IDY00052I TSOLIB terminated. Authorization failure.+ Unable to deactivate the active TSOLIB library.

Explanation: The TSOLIB command processor is not authorized to close the active ddname. The TSOLIB command processor lost access to any data set associated with the active ddname.

System action: The TSOLIB command processor abnormally terminates.

User response: Get access to the data set in question. Reissue the command again, or logoff and logon to close the open data control block.

Module: IKJDYDCB

Audience: TSOLIB command user

Chapter 6. TSO/E terminal messages (IKJ...)

Component name	IKJ
Program producing message	TSO/E
Audience and where produced	For terminal user: at the terminal. For system programmer: SYSPRINT listing.
Message format	IKJxxyyyn xx System module prefix (in decimal). yyy Message serial number identifying the program that issued the message. n Type code: <ul style="list-style-type: none"> • A Action. The terminal user must perform the action specified in the message text. • E Error; processing terminates. • I Information; no action is required.
Comments	The words printed in italics in the message text indicate that the system supplies specific information which varies depending on the circumstances. That information is available only when the system displays the message at the terminal. A plus sign (+) after the message text indicates that more information is available on-line. To receive more information, type a question mark (?) and press the Enter key. Many messages in this section have no message ID (number). These messages follow and refer back to a message marked with a plus sign (+).

Table 1. Programs associated with message identifiers. This table correlates ranges of IKJ-prefixed message numbers with the programs that issue them. Messages relating to licensed programs can be found in the licensed program documentation and are not contained in this publication.

Message numbers	Command Processor or problem program
52300-52599	EDIT Command Processor
52600-52699	COPY Command Processor (licensed program)
52700-52799	MERGE Command Processor (licensed program)
52800-52899	LIST Command Processor (licensed program)
52900-52999	FORMAT Command Processor (licensed program)
54000-54999	Terminal I/O Controller
55000-55049	OPERATOR Command Processor
55050-55099	SEND Command Processor
55300-55319, 55361-55362	CONSOLE Command Processor
55321-55327	GETMSG Service Routine
55351-55357	CONSPROF Command Processor
55363-55365	Message Translation
56000-56049	CALL Command Processor
55100-55117	PARMLIB Command Processor
56050-56099	RUN Command Processor
56100-56149, 59162-59164	ALLOCATE Command Processor

Table 1. Programs associated with message identifiers (continued). This table correlates ranges of IKJ-prefixed message numbers with the programs that issue them. Messages relating to licensed programs can be found in the licensed program documentation and are not contained in this publication.

Message numbers	Command Processor or problem program
56150-56169	FREE Command Processor
56190-56219	CANCEL/STATUS Command Processor
56220-56249	GNRLFAIL/DAIRFAIL Service Routine
56250-56289	SUBMIT Command Processor
56290-56299	VSAMFAIL/GNRLFAIL Service Routine
56300-56399	OUTPUT Command Processor
56400-56499, 56625-56626	LOGON/LOGOFF Command Processor
56500-56550	EXEC Command Processor
56550-56599	ACCOUNT Command Processor
56600-56649	Terminal Monitor Program
56650-56654	TIME Command Processor
56655-56672	TERMINAL Command Processor
56673-56699	PROFILE Command Processor
56700-56749	COMMAND SCAN/PARSE Service Routines
56750-56769	GETLINE/PUTLINE/PUTGET Service Routines
56770-56788	RACONVRT Command Processor
56800-56849	HELP Command Processor
56850-56900	DAIRFAIL Service Routine
56950-56961	LISTBC Command Processor
57002-57664, 57766-57667	TEST Command Processor
57700-57714	TEST Command Processor
57665, 57668, 57800-57803	TESTAUTH Command Processor
58100-58199	PROTECT Command Processor
58200-58299	RENAME Command Processor
58300-58399	LISTALC Command Processor
58400-58499	LISTDSI CLIST statement
58500-58599	LISTDS Command Processor
58600-58610	DEFAULT Service Routine
58611-58629	SYNC Command Processor
59001-59056	PRINTDS Command Processor
59100-59120, 59165	OUTDES Command Processor
59200-59209	WHEN Command Processor
60739-60743	ATTRIB Command Processor
68000-68099	COBOL Command Processor (licensed program)
74000-74099	ASM Command Processor (licensed program)
76000-76999	LINK/LOADGO Command Processor
78000-78099	FORT Command Processor (licensed program)
79000-79099	EXEC Command Processor

Table 1. Programs associated with message identifiers (continued). This table correlates ranges of IKJ-prefixed message numbers with the programs that issue them. Messages relating to licensed programs can be found in the licensed program documentation and are not contained in this publication.

Message numbers	Command Processor or problem program
79101-79106	TSOEXEC Command Processor
79150-79159	Exit Handler
79301-79342	ALTLIB Command Processor

Note: IKT-prefixed messages are issued by VTIOC (VTAM terminal I/O coordinator).

Table 2. Messages associated with commands and service routines. This table correlates commands and service routines with the message ranges they issue. Messages relating to licensed programs can be found in the licensed program documentation and are not contained in this publication.

Command Processor or service routine	Prefix and serial No. (xxyyy)
ACCOUNT Command Processor	56550-56599
ALLOCATE Command Processor	56100-56149, 59162-59164
ALTLIB Command Processor	79301-79342
ASM Command Processor (licensed program)	74000-74099
ATTRIB Command Processor	60739-60743
CALL Command Processor	56000-56049
CANCEL/STATUS Command Processor	56190-56219
COBOL Command Processor (licensed program)	68000-68099
COMMAND SCAN/PARSE Service Routines	56700-56749
CONSOLE Command Processor	55300-55319, 55361-55362
CONSPROF Command Processor	55351-55357
COPY Command Processor (licensed program)	52600-52699
DAIRFAIL Service Routine	56850-56900
DAIRFAIL Service Routine	56220-56249
DEFAULT Service Routine	58600-58610
EDIT Command Processor	52300-52599
EXEC/WHEN/READ Command Processor	56500-56550
EXEC/WHEN/READ Command Processor	79000-79099
Exit Handler	79150-79159
FORMAT Command Processor (licensed program)	52900-52999
FORT Command Processor (licensed program)	78000-78099
FREE Command Processor	56150-56169
GETLINE/PUTLINE/PUTGET Service Routine	56750-56769
GETMSG Service Routine	55321-55327
GNRFAIL/DAIRFAIL Service Routine	56220-56249
HELP Command Processor	56800-56849
LINK/LOADGO Command Processor	76000-76999
LIST Command Processor (licensed program)	52800-52899
LISTALC Command Processor	58300-58399

None

Table 2. Messages associated with commands and service routines (continued). This table correlates commands and service routines with the message ranges they issue. Messages relating to licensed programs can be found in the licensed program documentation and are not contained in this publication.

Command Processor or service routine	Prefix and serial No. (xyyy)
LISTBC Command Processor	56950-56961
LISTDS Command Processor	58500-58599
LISTDSI CLIST statement	58400-58499
LOGON/LOGOFF Command Processor	56400-56499
MERGE Command Processor (licensed program)	52700-52799
Message Translation	55363-55365
OPERATOR Command Processor	55000-55049
OUTDES Command Processor	59100-59120, 59165
OUTPUT Command Processor	56300-56399
PARMLIB Command Processor	55100-55117
PRINTDS Command Processor	59001-59056
PROFILE Command Processor	56673-56699
PROTECT Command Processor	58100-58199
RACONVRT Command Processor	56770-56788
RENAME Command Processor	58200-58299
RUN Command Processor	56050-56099
SEND Command Processor	55050-55099
SUBMIT Command Processor	56250-56289
SYNC Command Processor	58611-58629
TERMINAL Command Processor	56655-56672
Terminal I/O Controller	54000-54999
Terminal Monitor Program	56600-56649
TEST Command Processor	57002-57664, 57666, 57667, 57700-57714
TESTAUTH Command Processor	57665, 57668, 57800-57803
TIME Command Processor	56650-56654
TSOEXEC Command Processor	79101-79106
VSAMFAIL/GNRLFAIL Service Routine	56290-56299
WHEN Command Processor	59200-59209

None *command_name*

Explanation: This is the MODE message. It is issued:

- By the system after an attention interruption. The STAX macro in IKJCT469 points to the text. The PUTGET in IKJCT472 also points to the text in case a question mark was entered.
- By IKJCT462 when the SYSOUT data set has been printed and 'PAUSE' was specified.
- By IKJCT463 after a not valid subcommand (subcommand syntactically invalid, or not a valid subcommand) if the commands are coming from the terminal.
- By IKJCT463 after SAVE subcommand finished. If allocation of the SAVE data set failed and subcommands are coming from the terminal, get another subcommand.
- By IKJCT463 after the HELP command processor finished.

- By IKJCT463 if there is a parse error and input is coming from the terminal, or if parse cannot prompt the user due to noprompt mode and input is coming from the terminal.

Module: IKJCT462, IKJCT463

Program: OUTPUT

None READY

Explanation: The TMP is requesting entry of the next command.

Module: IKJEFT02, IKJEFT03

Program: TMP

None TEST

Explanation: TEST is prompting for the next subcommand. The user should enter the next TEST subcommand.

Module: IKJEGMNL

Program: TEST

IKJ000 - IKJ999 Messages

<p>Messages in the range IKJ000 - IKJ999 are not included in this document, because these messages are issued by MVS. See <i>z/OS MVS System Messages, Vol 9 (IGF-IWM)</i> for their documentation.</p>

IKJ52021I INVALID COMMAND

Explanation: A not valid subcommand or subcommand abbreviation name for TEST has been entered.

Module: IKJEGMNL

Program: TEST

IKJ52301I DATA SET *dsname* NOT ALLOCATED, TOO MANY DATA SETS +

Explanation: DAIR return code is 16, and TIOT is full.

USE FREE COMMAND TO FREE UNUSED DATA SETS

Explanation: The user has allocated the maximum number of data sets. FREE will deallocate data sets.

Module: IKJEBEIN, IKJEBESA, IKJEBEUI

Program: EDIT

IKJ52302I DATA SET *dsname* NOT ALLOCATED, DATA SET NOT ON VOLUME +

Explanation: In IKJEBEIN, DAIR return code is 8, DARC=X'0000', and CTRC=X'0008'. In IKJEBESA, DAIR return code is 12, DARC=X'6708'.

CATALOG INFORMATION INCORRECT

Explanation: The data set has been scratched without being uncataloged.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52303I DATA SET *dsname* NOT ALLOCATED, REQUIRED VOLUME NOT MOUNTED +

Explanation: The volume serial number for the data set cannot be found.

VOLUME OR CVOL NOT ON SYSTEM AND CANNOT BE ACCESSED

Explanation: DAIR return code is 8 or 12, with DARC=X'0000' and CTRC=X'0008', or DARC=X'1704', or DARC=X'0218'.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52304I UTILITY DATA SET NOT ALLOCATED, SYSTEM OR INSTALLATION ERROR + or DATA SET *dsname* NOT ALLOCATED, SYSTEM OR INSTALLATION ERROR +

Explanation: An error occurred for which no specific diagnostic message exists. The second-level message indicates the actual error condition.

DYNAMIC ALLOCATION ERROR CODE *error_code*

Explanation: DAIR return code is 12. The dynamic allocation return code (DARC) is not equal to a value specifically tested in producing a particular diagnostic message.

CATALOG ERROR CODE *error_code*

Explanation: DAIR return code is 8. The catalog return code (CTRC) is not a value specifically tested.

CATALOG I/O ERROR

Explanation: DAIR code is 8, CTRC=X'001C'.

Module: IKJEBEIN, IKJEBESA, IKJEBEUI

Program: EDIT

IKJ52305I DATA SET *dsname* NOT ALLOCATED, NOT ENOUGH SPACE ON VOLUMES + UTILITY DATA SET NOT ALLOCATED, NOT ENOUGH SPACE ON VOLUME +

Explanation: DAIR return code is 12, dynamic allocation return code (DARC)=X'4714'.

USE DELETE COMMAND TO DELETE UNUSED DATA SETS

Explanation: The DELETE command can be used to scratch unnecessary data sets. If this does not alleviate the problem, installation action is required to make more direct access space available to TSO/E users.

Module: IKJEBEUI

Program: EDIT

IKJ52306I DATA SET *dsname* ALREADY IN USE, TRY LATER + DATA SET IS ALLOCATED TO ANOTHER USER OR JOB

Explanation: A SHR allocation failed because another user or job has allocated the data set with a disposition of OLD, or an OLD allocation failed because the data set is allocated to another user or job (SHR or OLD disposition).

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52307I DATA SET *dsname* NOT IN CATALOG

Explanation: DAIR return code is 12, dynamic allocation return code (DARC)=X'1708' (LOCATE return code is 8).

Module: IKJEBEIN

Program: EDIT

IKJ52308I MEMBER *member* NOT IN DATA SET *dsname*

Explanation: A BLDL failed (return code 4) for a member of an existing partitioned data set. The OLD keyword was specified on the EDIT command.

Module: IKJEBEIN

Program: EDIT

IKJ52309I DATA SET *dsname* NOT USABLE + UTILITY DATA SET NOT USABLE +

Explanation: The data set specified is allocated but cannot be used because of an open failure or permanent I/O error.

I/O SYNAD ERROR *xxxx*

Explanation: The message is issued by IKJEBECO, IKJEBEFC, and IKJEBEUT subsequent to SYNAD exit processing; *xxxx* is the SYNAD information returned to the exit routine.

CANNOT OPEN DATA SET

Explanation: The message is issued by IKJEBEFC, IKJEBECO, and IKJEBEIN on all OPEN failures (bit 4 of DCBOFLGS not equal to binary 1).

MAXIMUM DIRECTORY BLOCKS EXCEEDED

Explanation: The data set you are trying to edit is too large. You can either compress the data set, or divide it into multiple data sets.

OPEN ERROR CODE *error_code*

Explanation: An error occurred while opening the data set.

Module: IKJEBEFC, IKJEBEIN, IKJEBEUI, IKJEBEUT

Program: EDIT

IKJ52310I INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS

Explanation: A partially-qualified name of less than 44 characters was specified on the EDIT command or SAVE subcommand; when fully qualified, the data set name length exceeds the legal maximum of 44 characters.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52311I MEMBER *member* SPECIFIED BUT *dsname* NOT A PARTITIONED DATA SET

Explanation: A member name was specified for a sequential data set.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52312I INSUFFICIENT STORAGE TO EXECUTE *command* or *subcommand*

Explanation: A conditional GETMAIN for a buffer or work area failed.

Module: IKJEBECH, IKJEBECI, IKJEBEDC, IKJEBEDE, IKJEBEDO, IKJEBEEN, IKJEBEFI, IKJEBEFO, IKJEBEIN, IKJEBEIP, IKJEBEIS, IKJEBELI, IKJEBELT, IKJEBEMA, IKJEBEME, IKJEBEMR, IKJEBERE, IKJEBERN, IKJEBERU, IKJEBESA, IKJEBESC, IKJEBESU, IKJEBETA, IKJEBEUI, IKJEBEUP, IKJEBEVE

Program: EDIT

IKJ52313I COMMAND SYSTEM ERROR +

Explanation: A system function or TSO/E service routine was not able to perform its normal function.

service_routine **ERROR CODE** *error_code*

Explanation: TSO/E *service_routines* are PARSE, DAIR, SCAN (command scan), PUTLINE, GETLINE, PUTGET, DEFAULT, and DAIRFAIL. System functions for which this message applies are: OBTAIN, BLDL, and DEVTYPE.

Module: IKJEBECH, IKJEBECL, IKJEBEDE, IKJEBEDO, IKJEBEEN, IKJEBEFL, IKJEBEFO, IKJEBEIN, IKJEBEIP, IKJEBEIS, IKJEBELI, IKJEBELT, IKJEBEMA, IKJEBEME, IKJEBEMR, IKJEBERE, IKJEBERU, IKJEBESE, IKJEBESC, IKJEBETA, IKJEBEUP, IKJEBEVE

Program: EDIT

IKJ52314I DATA SET *dsname* RESIDES ON MULTIPLE VOLUMES, NOT SUPPORTED

Explanation: DAIR return code is 12 and DARC=X'041C'.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52315I DATA SET *dsname* CANNOT BE RESOLVED, SYSTEM ERROR +

Explanation: The system was unable to fully qualify the data set name.

DEFAULT ERROR CODE *error_code*

Explanation: IKJDFLT (DEFAULT) return code is 4 or 12.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52316I DATA SET *dsname* WILL CREATE AN INVALID CATALOG STRUCTURE +

Explanation: IKJDFLT (DEFAULT) return code is 16.

A QUALIFIER CANNOT BE BOTH AN INDEX AND THE LAST QUALIFIER OF A DATA SET NAME

Explanation: The data set specified is already an index level in the catalog.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52317I DATA SET *dsname* NOT ON A DIRECT ACCESS DEVICE, NOT SUPPORTED

Explanation: DAIR return code is 12, DARC=X'0404'; only direct access devices are supported for dynamic allocation.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52318I DATA SET *dsname* NOT ALLOCATED + UTILITY DATA SET NOT ALLOCATED +

Explanation: The direct access device could not be obtained.

NO UNIT AVAILABLE

Explanation: No device was available (not on-line, mounted, shareable, and so on).

INVALID UNIT IN USER ATTRIBUTE DATA SET

Explanation: A not valid unit name was supplied. The user is not authorized to use the device.

Module: IKJEBEIN, IKJEBESA, IKJEBEUI

Program: EDIT

IKJ52319I DATA SET *dsname* NOT ALLOCATED, SHARED +

Explanation: The data set is permanently allocated as SHR and cannot be allocated as OLD without deallocation.

USE FREE COMMAND TO FREE DATA SET

Explanation: The user can deallocate the data set through the FREE subcommand if it is allocated to him.

Module: IKJEBESA

Program: EDIT

IKJ52320I DATA SET OR MEMBER NOT FOUND, ASSUMED TO BE NEW

Explanation: User did not specify OLD or NEW on the EDIT command, and the data set was not found in a catalog. The user is placed in INPUT mode.

Module: IKJEBEIN

Program: EDIT

IKJ52321I RECOVER KEYWORD IGNORED. YOUR PROFILE SPECIFIES NO RECOVER

Explanation: The EDIT recover option must be specified in the user's profile to be allowed.

Module: IKJEBEIN

Program: EDIT

IKJ52330I [*text*] ORGANIZATION OF DATA SET *dsname* NOT ACCEPTABLE

Explanation: For the item *text* could appear the following:

- *text* = ISAM
- *text* = DIRECT
- *text* = PDSE
- *text* = VSAM
- *text* = UNKNOWN

The data set being edited does not have a valid organization.

ORGANIZATION MUST BE PARTITIONED OR SEQUENTIAL

Explanation: Only a member of a partitioned data set or a sequential data set (DSORG=PO or PS) can be edited or saved.

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52331I RECORD FORMAT *ccc* NOT ACCEPTABLE

Explanation: The data set being edited has a record format of other than F, FB, FBS, V or VB.

(The data set specified on the EDIT command may contain ANSI or machine control characters.)

Module: IKJEBEIN, IKJEBESA

Program: EDIT

IKJ52332I RECORD FORMAT V NOT ACCEPTABLE FOR *type*

Explanation: The data set type being edited required fixed record format.

Module: IKJEBEIN

Program: EDIT

IKJ52333I INVALID BLOCK VALUE, USING *value* +

Explanation: A not valid block size was entered with the BLOCK operand for a new data set.

MAXIMUM BLOCK VALUE IS DEVICE TRACK SIZE

MAXIMUM BLOCK VALUE IS SYSGEN OPTION

BLOCK MUST BE A MULTIPLE OF LINE FOR RECORD FORMAT F DATA SETS

BLOCK VALUE MUST EXCEED LINE BY AT LEAST 4 FOR RECORD FORMAT V DATA SETS

Explanation: The value was not an integer multiple of 'line', or the value was less than line+4, or the value exceeded the device track size or default value in CSECT IKJEBEPD.

Module: IKJEBEIN

Program: EDIT

IKJ52334I [*text*] IGNORED, ONLY VALID FOR NEW DATA SET

Explanation: For the item *text* could appear the following:

- *text* = BLOCK
- *text* = LINE

LINE, BLOCK, or both were specified for an old data set. The operands are valid only for new data sets.

Module: IKJEBEIN

Program: EDIT

IKJ52335I INVALID LINE VALUE FOR *language*, USING *value* +

Explanation: The value entered with the LINE operand does not conform to data set type requirements.

language **REQUIRES A LINE SIZE OF 80**

LINE SIZE FOR *type* MAY NOT EXCEED *line_size*

LRECL FIELD NOT INITIALIZED, BLOCK SIZE SUBSTITUTED

Explanation: The first two messages are applicable if the line size was greater than zero. The third message is issued if an LRECL value of zero is set in the format 1 DSCB.

Module: IKJEBEIN

Program: EDIT

IKJ52336I *value* INVALID LINE VALUE FOR *type* DATA SET

Explanation: The LRECL value is not valid; it does not meet data set type requirements.

Module: IKJEBEIN

Program: EDIT

IKJ52337I INVALID LINE NUMBER *nnnnn* ENCOUNTERED IN FIRST LINE OF DATA SET or INVALID LINE NUMBER *nnnnn* ENCOUNTERED, LINE NUMBER PRECEDING IS *nnnnn* +

Explanation: A not valid line number was encountered. Either the line numbers are out of sequence, or a data set is not line numbered (sequence field contains non-numeric characters). The data set being edited must be line numbered.

USE EDIT WITH NONUM OPERAND

type **DATA SET MUST CONTAIN VALID LINE NUMBERS**

Explanation: Either the data set must contain line numbers, or it can be edited using the NONUM operand on entry.

Module: IKJEBECO

Program: EDIT

IKJ52338I DATA SET *dsname* NOT LINE NUMBERED USING NONUM

Explanation: The data set to be edited is being initially copied and NONUM is allowed. NUM is the default with the EDIT command for this data set type.

Module: IKJEBECO

Program: EDIT

IKJ52339I *dsname* ALREADY EXISTS

Explanation: DAIR return code is 8. Prompt message IKJ52340A or IKJ52341A is issued.

Module: IKJEBESA

Program: EDIT

IKJ52340A ENTER NEW NAME OR HIT CARRIER RETURN TO REUSE DATA SET

Explanation: The message is issued for action after IKJ52339I if the data set is sequential.

Module: IKJEBESA

Program: EDIT

IKJ52341A ENTER NEW MEMBER OR HIT CARRIER RETURN TO REUSE MEMBER

Explanation: The message is issued after IKJ52339I if the data set is a member of a partitioned data set.

Module: IKJEBESA

Program: EDIT

IKJ52342I INVALID LINE SIZE FOR NUM +

Explanation: The value specified by the LINESIZE operand on the TERMINAL command is too small for the number of characters entered.

LINE TOO SHORT FOR LINE NUMBERS

Explanation: Reenter the TERMINAL command, increasing the LINESIZE (integer) operand to allow for a greater number of characters.

Module: IKJEBEIN

Program: EDIT

IKJ52343I RECORD FORMAT F NOT ACCEPTABLE FOR GOFORT(FREE) +

Explanation: A fixed record format was specified for data set type GOFORT(FREE).

RECORD FORMAT V IS REQUIRED

USE EDIT WITHOUT SPECIFYING LINE OPERAND

Explanation: The LINE operand is not valid for this data set type; records are variable.

Module: IKJEBEIN

Program: EDIT

IKJ52344I • IKJ52364I

IKJ52344I *nnnnn* LINE(S) TRUNCATED, INDIVIDUAL LINE LENGTH(S) EXCEEDED DATA SET MAXIMUM LINE LENGTH

Explanation: The user entered a change that added enough characters to exceed the maximum permissible line length.

Module: IKJEBECH

Program: EDIT

IKJ52360I INVALID LINE NUMBER FIELD SPECIFIED (*start column, end column*) +

Explanation: The NUM operand subfield was specified incorrectly for an ASM data set or specified for other than an ASM data set.

STARTING COLUMN MUST BE WITHIN THE RANGE 73-80

LINE NUMBER FIELD FALLS OUTSIDE RECORD SIZE

LINE NUMBER FIELD OPERANDS ARE VALID FOR ASM DATA SETS ONLY

Explanation: The line number field for an ASM data set is restricted to columns 73-80 of the 80 column line allowed. No other data set types may use this operand.

Module: IKJEBEIN

Program: EDIT

IKJ52361I ASIS INVALID FOR *type* DATA SET, USING CAPS

Explanation: The ASIS operand was specified for a data set type which requires that letters be converted to uppercase.

Module: IKJEBEIN

Program: EDIT

IKJ52362I NONUM INVALID FOR *type* DATA SET, USING NUM OPTION

Explanation: The user specified NONUM with a data set type which must be line numbered.

Module: IKJEBEIN

Program: EDIT

IKJ52363I *function* INVALID FOR *language* or *type* +

Explanation: SCAN was specified for a non-scannable type (the CASCAN switch in the processor table is off, or syntax checking is not valid for the data set); or UNNUM was specified for a data set type that either requires line numbers or requires a data exit routine for renumbering.

Module: IKJEBEIN, IKJEBESC, IKJEBEUN

Program: EDIT

IKJ52364I *function* NOT AVAILABLE FOR *language* or *type* **REQUIRED PROGRAM NOT AVAILABLE
PROGRAM NO LONGER USABLE**

Explanation: The syntax checker is not in the user's system or is not operational.

Module: IKJEBEDX, IKJEBEIN, IKJEBESC

Program: EDIT

IKJ52365I INVALID SOURCE MARGIN (*startcol*),(*endcol*) +

Explanation: PLI or PLIF subfield was specified incorrectly; the default is (2,72).

SPECIFIED SOURCE MARGIN FALLS OUTSIDE LINE LIMITS

Explanation: The specified source margins are not valid; they fall outside the line size limits.

Module: IKJEBEIN

Program: EDIT

IKJ52366I INVALID SUBCOMMAND *subcommand_name*

Explanation: The specified subcommand is not found in the IBM or user subcommand table.

Module: IKJEBEMA

Program: EDIT

IKJ52367I WARNING, SCAN MAY BE INCOMPLETE +

Explanation: CASCRC20 bit is on in IKJEBCA; the checker failed but is again operational.

type **SYNTAX CHECKER FAILED BUT SUCCESSFULLY RECOVERED**

Explanation: The syntax checker failed during line scanning, but was successfully deleted, reloaded, and re-called for initial entry (and for line-translation, if a run-time data set is required).

Module: IKJEBESC

Program: EDIT

IKJ52368I EDITF LANGUAGE PROCESSOR FAILED BUT WAS SUCCESSFULLY RECOVERED

Explanation: The language processor failed, but recovered successfully.

Module: IKJEBESC

Program: EDIT

IKJ52400I INPUT TERMINATED, NEXT LINE NUMBER IS *nnnnn*

Explanation: An error was received from a syntax checker during input mode, indicating that an error was detected in the syntax of the line just checked.

Module: IKJEBEIM, IKJEBEIP

Program: EDIT

IKJ52402I LINE NUMBER LIMIT *nnnnn* EXCEEDED

Explanation: The line number limit exceeded in WRITE operation with numbered data set.

Module: IKJEBEUT

Program: EDIT

IKJ52422I *command/subcommand* ENDED DUE TO ERROR +

Explanation: This message is issued by IKJEBAE when the EDIT command has abended and the ESTAE exit has control, or by IKJEBECI when a command processor which is invoked under EDIT has ended abnormally. IKJEBAE will fill in the command name as the user entered it to enter EDIT; IKJEBECI will fill in the name of the EDIT subcommand.

[*text*] **COMPLETION CODE IS** *xxxx*

- *text* = SYSTEM
- *text* = USER

IKJ52423I • IKJ52427I

Explanation: The system or user completion code is filled in by the module issuing the first-level message.

Module: IKJEBEAE, IKJEBECI

Program: EDIT

IKJ52423I *type* DATA SET CANNOT BE RUN

Explanation: A user has attempted to run a data set that is not an executable type.

Module: IKJEBERU

Program: EDIT

IKJ52424I SYSTEM ERROR +

Explanation: An error was detected in initialization (IKJEBEIN) or in deleting the utility data set (IKJEBEEX).

UTILITY DATA SET NOT DEALLOCATED, DYNAMIC ALLOCATION ERROR CODE *error_code*

Explanation: IKJEBEEX was unable to delete the utility data set due to an error in dynamic allocation.

DATA SET *dsname* NOT DEALLOCATED, DYNAMIC ALLOCATION ERROR CODE *error_code*

Explanation: Deallocation failed for a data set in IKJEBEIN, DAIR return code is 8 or 12. Control returns to the TMP.

UTILITY DATA SET NOT DEALLOCATED, CATALOG ERROR CODE *error_code*

Explanation: A catalog error occurred in deleting the utility data set in IKJEBEEX.

DATA SET *dsname* NOT DEALLOCATED, CATALOG ERROR CODE *code*

Explanation: DAIR return code is 8. Data set could not be deallocated by IKJEBEIN.

FILE *ddname* NOT FOUND

Explanation: In IKJEBEIN, the end of TIOT was reached without finding the *ddname* returned by IKJDAIR.

Module: IKJEBEEX, IKJEBEIN

Program: EDIT

IKJ52425I COMMAND NOT FOUND - *command_name*

Explanation: A command processor invoked as a subcommand of EDIT cannot be found by the system.

Module: IKJEBECI

Program: EDIT

IKJ52426I EDIT SESSION CANCELED

Explanation: EDIT's recovery routine has received control because of an error and has canceled the EDIT session.

Module: IKJEBEAE

Program: EDIT

IKJ52427I SAVE CANNOT COMPLETE TO DATASET SPECIFIED

Explanation: There is not enough space either in the data set specified, on the volume on which that data set resides, or in the directory of the partitioned data set. For more information about the default values for the EDIT command, see *z/OS TSO/E Command Reference*.

The number of entries that fit in a directory block depends on how much information the directory contains for each entry.

Module: IKJEBEAE

Program: EDIT

IKJ52428I ENTER SAVE SPECIFYING A NEW DATASET NAME

Explanation: An out of space condition will not allow completion of a SAVE request to this data set. A new data set name should be chosen.

Module: IKJEBEAE

Program: EDIT

IKJ52428I YOUR EDIT WORKFILE HAS BEEN KEPT. TO RECOVER IT USE EDIT WITH 'RECOVER' KEYWORD.

Explanation: This message is issued for one of the following conditions:

- The user was canceled while in EDIT and the data set has been modified.
- The user specified 'RETAIN' to message IKJ52432A.
- A second ABEND has occurred after a non-recoverable ABEND was processed.

Module: IKJEBEEX

Program: EDIT

IKJ52429I RECOVERY OF WORKFILE NOT POSSIBLE. EDIT TERMINATED + EDIT WORKFILE WAS NOT FOUND OR NOT USABLE

Explanation: The user specified the RECOVER keyword on the EDIT command, and a recoverable workfile was not found or was not usable. Either the user's previous EDIT session completed normally, or there was an error attempting to recover the workfile.

Module: IKJEBERC

Program: EDIT

IKJ52430I A RECOVERED COPY OF YOUR DATA SET IS BEING USED WITH THE FOLLOWING OPTIONS: *option_1 ... option_n*

Explanation: The user has initiated the recovery of a data set. The message is issued to inform him of the parameters associated with this edit session.

Module: IKJEBEAR

Program: EDIT

IKJ52431I A RECOVERABLE WORKFILE EXISTS CONTAINING DATA SET *dsname*

Explanation: The user specified a data set name and the RECOVER keyword on the EDIT command. However, the data set name (*dsname*) does not match the data set name in recoverable workfile.

- or -

The user did not specify the RECOVER keyword on the EDIT command, and a recoverable workfile was found containing that data set name. In either case, the user is prompted for a decision via message IKJ52433A.

Module: IKJEBERC

Program: EDIT

IKJ52432A ENTER SAVE, RETAIN OR ANY OTHER EDIT SUBCOMMAND + ENTER — 'SAVE' SPECIFYING A DIFFERENT DATASET NAME. 'RETAIN' TO END THIS EDIT SESSION BUT LEAVE YOUR EDIT WORKFILE. USE EDIT'S 'RECOVER' KEYWORD TO RE-EDIT IT. - or - ENTER ANY OTHER VALID EDIT SUBCOMMAND.

Explanation: An attempt to save has failed because there was not enough space available on the volume. The second-level message describes the options available to the user. This message is issued when the user's profile has the RECOVER attribute.

Module: IKJEBEAE

IKJ52433A • IKJ52504I

Program: EDIT

IKJ52433A DO YOU WISH TO RECOVER THIS DATA SET? REPLY YES OR NO.

Explanation: This message follows message IKJ52431I and is requesting a decision from the user.

If the reply is NO, the user has indicated that recovery is not necessary and the data set information in the recoverable workfile will be permanently lost with no possible means of recovery later. The workfile will be re-used to hold data set information for the current EDIT data set.

If the reply is YES, the data set in the workfile will be recovered.

Module: IKJEBEAR

Program: EDIT

IKJ52500I [DOWN TERMINATED AT] END OF DATA [, LAST LINE IS --]

Explanation: IKJEBECH issues the message on return code 4 from IKJEBEUT following return code 0. IKJEBELT issues it after return code 4 from IKJEBEUT after entry with option code X'02'. IKJEBEDO issues the message on return code 4 from IKJEBEUT after reading next record. IKJEBEDO is the only module putting the insertions in the message. The second insertion is used when the current line is to be listed at the terminal (VERIFY ON specified).

Module: IKJEBECH, IKJEBELT, IKJEBEDO

Program: EDIT

IKJ52501I NO LINES IN DATA SET

Explanation: The message is issued on return code 4 from IKJEBEFC or IKJEBEUT.

Module: IKJEBEBO, IKJEDEDE, IKJEBEDO, IKJEBEFL, IKJEBEFO, IKJEBELT, IKJEBERE, IKJEBERU, IKJEBESC, IKJEBEUN

Program: EDIT

IKJ52502I DATA SET NOT LINE NUMBERED

Explanation: Line numbers have been referenced or required, and CANONUM switch in the communication area is on.

Module: IKJEDEDE, IKJEBELT, IKJEBESC, IKJEBEUN

Program: EDIT

IKJ52503I INVALID LINE NUMBER RANGE *first_linenum - last_linenum*

Explanation: The user has entered operands with *first_linenum* to *last_linenum*. The message is issued without line numbers for the CHANGE, DELETE, LIST, and SCAN subcommands. The RENUM subcommand includes the line numbers in the error message text, to indicate that the user specified a not valid range of line numbers by making the first line number's value exceed the value of the last line number in the range.

Module: IKJEBECH, IKJEDEDE, IKJEBELT, IKJEBERE, IKJEBERN, IKJEBESC

Program: EDIT

IKJ52504I LINE NUMBER *nnnnn* NOT FOUND

Explanation: IKJEBEUT return code 4 indicates that the line to be changed, deleted, listed, or renumbered does not exist.

Module: IKJEBECH, IKJEDEDE, IKJEBELT, IKJEBERE, IKJEBERN

Program: EDIT

IKJ52505I TOP OF DATA SET

Explanation: The top of the data set has been reached.

Module: IKJEBECH, IKJEBEDE, IKJEBELT, IKJEBERE, IKJEBERN

Program: EDIT

IKJ52506I TEXT NOT FOUND

Explanation: IKJEBECG issues the message on return code X'08' from IKJEBESE. IKJEBEFI issues the message on return code of 4 from IKJEBEUT.

Module: IKJEBECH, IKJEBEFI

Program: EDIT

IKJ52507I LINE *nnnnn* TRUNCATED +

Explanation: IKJEBECH issues the message on return code 4 from IKJELE when CANONUM=0 or CADSCODE is not equal to CATEXT. IKJEBEIM, IKJEBEIP, and IKJEBEIS issue the message on return code 4 from IKJELE. IKJEBERE issues the message when renumbering a NONUM variable data set and the length of the line is within 8 characters of the LRECL.

LINE LENGTH IS *nnnnn*

Explanation: The length of the truncated line is indicated.

Module: IKJEBECH, IKJEBEIM, IKJEBEIP, IKJEBEIS, IKJEBERE

Program: EDIT

IKJ52550I NO OPERAND, SUBCOMMAND IGNORED

Explanation: CAOPERND shows there are no operands present.

Module: IKJEBEME

Program: EDIT

IKJ52551I *character* NOT AVAILABLE ON THIS TERMINAL

Explanation: The terminal you are using does not use that character.

Module: IKJEBEME

Program: EDIT

IKJ52552I EDIT DATA SET *edit_dsname* AND SAVE DATA SET *save_dsname* ARE NOT COMPATIBLE +

Explanation: The save data set is a PDE, and its record format, block size, or logical record length are not compatible with that of the utility data set.

EDIT DATA SET HAS *format* RECORD FORMAT, SAVE DATA SET HAS *save_format* RECORD FORMAT, USE ANOTHER DATA SET

EDIT DATA SET HAS LINE SIZE *edit_line_size*, SAVE DATA SET HAS LINE SIZE *save_line_size*, USE ANOTHER DATA SET

EDIT DATA SET HAS BLOCK LENGTH *edit_block_length*, SAVE DATA SET HAS BLOCK LENGTH *save_block_length*, USE ANOTHER DATA SET

Module: IKJEBESA

Program: EDIT

IKJ52553I • IKJ52560I

IKJ52553I SAVED, DATA SET IS EMPTY

Explanation: IKJEBEFC return code is 4.

Module: IKJEBESA

Program: EDIT

IKJ52554I BLOCK VALUE TOO LARGE FOR OUTPUT DEVICE, NOTHING SAVED

Explanation: The block size of the data set is greater than the device track length.

Module: IKJEBESA

Program: EDIT

IKJ52555I NOTHING SAVED

Explanation: The data set has been modified and the user has entered END without saving. Prompt with IKJ52563A and proceed based on the response.

Module: IKJEBEEN

Program: EDIT

IKJ52556I TABSET OF *mmm* EXCEEDS MAXIMUM DATA LENGTH OF *length*

Explanation: The tabset specification is larger than the data record length.

Module: IKJEBETA

Program: EDIT

IKJ52557I ONLY FIRST 10 VALID TABS USED

Explanation: The user has entered more than the ten allowed tab settings.

Module: IKJEBETA

Program: EDIT

IKJ52558I LINE OVERFLOW, NEW LINE CREATED

Explanation: The message is issued when IKJEBELE return code is 4 and CADSCODE=CATEXT.

Module: IKJEBECH

Program: EDIT

IKJ52559I MISSING COUNT OR STRING

Explanation: No operands were present; the user cannot be prompted.

Module: IKJEBECH

Program: EDIT

IKJ52560I LINE NUMBER LENGTH EXCEEDS LINE SIZE

Explanation: Data length is less than the line number length; renumbering is impossible.

Module: IKJEBERE

Program: EDIT

IKJ52561I INSERT TERMINATED NEXT LINE NUMBER IS *linenum*

Explanation: No room in data set to insert the line. IKJEBEUT return code is 0 and record key of next record=record key of line to be inserted.

Module: IKJEBEIS

Program: EDIT

IKJ52562I TABSET OF 0 or 1 IGNORED

Explanation: Zero cannot be specified on TABSET.

Module: IKJEBETA

Program: EDIT

IKJ52563A ENTER SAVE OR END

Explanation: This message follows message IKJ52555I.

Module: IKJEBEEN

Program: EDIT

IKJ52564A ENTER COUNT OR STRING -

Explanation: No operands were entered on the CHANGE subcommand. The user is prompted for the missing operands.

Module: IKJEBECH

Program: EDIT

IKJ52565I SCAN FOR LINE NUMBER REFERENCE IN LINE *linenum* INCOMPLETE +

Explanation: A referenced line number in the specified line is not present in the data set. This message applies only to the BASIC data set type.

SYNTAX ERROR OR INVALID LINE REFERENCE ENCOUNTERED

Explanation: The user has either a syntax error in the statement or the line reference is not valid.

Module: IKJEBERN

Program: EDIT

IKJ52567A ENTER DATA SET TYPE

Explanation: The data set type keyword was not entered on the EDIT command and cannot be defaulted through data set naming conventions.

Module: IKJEBEIN

Program: EDIT

IKJ52568I MISSING DATA SET TYPE

Explanation: The data set type is not entered on the EDIT command and the user has invoked EDIT within a procedure. EDIT is unable to prompt the user for data set type.

Module: IKJEBEIN

Program: EDIT

IKJ52569I WARNING, RENUMBERING DATA SET MAY CAUSE LOSS OF DATA +

Explanation: The user is renumbering an unnumbered data set. The user will be prompted for the required action.

DATA POSITIONS *start_position-end_position* **WILL BE OVERLAID WITH LINE NUMBERS**

Explanation: Records are of fixed length.

LINES CONTAINING MORE THAN *number* **CHARACTERS WILL BE TRUNCATED**

Explanation: Records are of variable length.

Module: IKJEBERE

Program: EDIT

IKJ52570I LIB OPERAND IGNORED FOR *type* **DATA SET**

Explanation: The LIB operand is valid only for those types supported by the RUN command.

Module: IKJEBERU

Program: EDIT

IKJ52571I SAVE REJECTED, DATA SET *dsname* **IS PARTITIONED WITH THE PRINT CONTROL ATTRIBUTE +**

Explanation: The EDIT input data set is partitioned and contains print control characters. The SAVE subcommand is disabled because control characters in the input member have been blanked out when the EDIT utility data set was initialized.

ANOTHER DATA SET MUST BE USED FOR SAVING

Explanation: The user must SAVE into a sequential data set or a different partitioned data set.

Module: IKJEBESA

Program: EDIT

IKJ52572I WARNING, DATA SET *dsname* **WILL BE SAVED WITHOUT PRINT CONTROL CHARACTERS**

Explanation: The data set being edited will no longer have control characters on saving. If control characters are to be retained in the old data set, the user should save the edited data set in a new permanent data set without control characters. Message IKJ52573A will prompt the user for reuse or a new dsname.

Module: IKJEBESA

Program: EDIT

IKJ52573A ENTER NEW DATA SET NAME OR HIT CARRIER RETURN TO REUSE *dsname*

Explanation: This is the prompt for action after warning message IKJ52572I. The record format after SAVE will reflect absence of control characters.

Module: IKJEBESA

Program: EDIT

IKJ52574I UNABLE TO RENUMBER, "NEW LINENUM" *new_linenum* **IS INVALID + FOR "OLD LINENUM"**
old_linenum, **"NEW LINENUM" MUST EXCEED** *line_number_previous_to_old_linenum*

Explanation: The line previous to the *old_linenum* specification has a key greater than or equal to the *new_linenum* entry. This makes the assignment of *new_linenum* as the first renumbered line impossible.

Module: IKJEBERE

Program: EDIT

IKJ52575I UNABLE TO RENUMBER, INSUFFICIENT LINE NUMBER ASSIGNMENTS AVAILABLE + INCLUDE MORE LINES IN RANGE, SPECIFY A SMALLER "NEW LINENUM", AND/OR USE A SMALLER INCREMENT

Explanation: Renumbering of a single line or range of lines has been requested. The request cannot be satisfied because the renumbering process would cause one or more lines to be assigned line number(s) greater than the line number following the specified range.

Module: IKJEBERE

Program: EDIT

IKJ52576I *subcommand_name* SUBCOMMAND CANCELLED DUE TO ERROR IN type EXIT PROCESSING + DATA EXIT ROUTINE *program_name* OUTPUT INCLUDED LINE NUMBER *invalid_line_number*, CONTAINS NON-NUMERIC CHARACTER(S) DATA EXIT ROUTINE *program_name* OUTPUT INCLUDED LINE NUMBER *invalid_line_number*, EXCEEDED BY PREVIOUS LINE NUMBER *line_number*.

Explanation: The output of the data exit routine contains a not valid line number.

Module: IKJEBEDX

Program: EDIT

IKJ52577I RENUM OF LINE RANGE NOT SUPPORTED FOR BASIC DATA SETS

Explanation: The terminal user entered the 'end linenum' operand (4th positional operand) on a RENUM subcommand for the ITF:BASIC data set type. Partial RENUM is not supported for type BASIC.

Module: IKJEBERE

Program: EDIT

IKJ52578I NO LINES FOUND IN SPECIFIED LINE RANGE

Explanation: The user entered a subcommand that specified a line range, and there were no lines within the specified range.

Module: IKJEBELT

Program: EDIT

IKJ52579I INVALID OPERANDS *description*

Explanation: For the item *description* could appear the following:

- *description* = INVALID FOR COUNT FOR END OF RANGE SPECIFICATION
- *description* = FIRST LINE TO BE MOVED/COPIED DOES NOT EXIST
- *description* = QUOTED STRING NOT FOUND
- *description* = END OF RANGE MUST BE GREATER THAN OR EQUAL TO THE BEGINNING OF THE RANGE
- *description* = INVALID FOR COUNT
- *description* = TRYING TO MOVE/COPY INTO LINE RANGE

The user entered the MOVE or COPY subcommand with not valid operands. The explanations of the not valid operands appear in the message as *description*, and will vary according to the nature of the not valid entry.

Module: IKJEBEMC

Program: EDIT

IKJ52580I BASIC DATA SETS NOT SUPPORTED BY MOVE OR COPY

Explanation: The user tried to move or copy data in an ITF:BASIC type data set. The TSO/E MOVE and COPY subcommands cannot operate on data sets of this type.

Module: IKJEBEMC

IKJ52581I • IKJ52586I

Program: EDIT

IKJ52581I BROADCAST LIMIT VALUE *value* NOT VALID - VALUE MUST BE FROM 1 TO 1000

Explanation: The broadcast limit value is specified incorrectly on the IKJBCAST macro invocation; it must be a number in the range 1 to 1000. The broadcast limit value is the number of notice messages to be reserved in SYS1.BROADCAST.

Module: IKJBCAST

Program: IKJBCAST

IKJ52582I LOGTIME VALUE *value* INVALID

Explanation: The logtime value is specified incorrectly on the IKJTZO macro invocation; it must be a number in the range 1 to 16777215. The logtime value is the number of seconds to wait before the 'LOGON PROCEEDING' message is issued.

Module: IKJTZO

Program: IKJTZO

IKJ52583I LOGLINE VALUE *value* INVALID

Explanation: The logline value is specified incorrectly on the IKJTZO macro invocation; it must be a number in the range 1 to 16777215. The logline value is the number of lines that may be entered before an attempt to LOGON is canceled.

Module: IKJTZO

Program: IKJTZO

IKJ52584I EDIT MACRO PREVIOUSLY USED

Explanation: The IKJEDIT macro was specified twice in a single assembly step. Specify it only once.

Module: IKJEDIT

Program: IKJEDIT

IKJ52585I EDIT OPERAND *value* INVALID [*text*] OR MISSING VALUE

Explanation: For the item *text* could appear the following:

- *text* = DATA SET TYPE
- *text* = USER EXIT NAME
- *text* = CHECKER NAME
- *text* = PROMPTER NAME

You specified the operand value identified in the message incorrectly, or you did not specify a value for it. Type a valid value for the edit operand and invoke the IKJEDIT macro again.

Module: IKJEDIT

Program: IKJEDIT

IKJ52586I EDIT OPERAND VALUE INVALID [*text*] FOR DATA SET TYPE *type*

Explanation: For the item *text* could appear the following:

- *text* = VARIABLE DEFAULT
- *text* = VARIABLE MAXIMUM
- *text* = FIXED DEFAULT
- *text* = FIXED MAXIMUM
- *text* = RECFM
- *text* = BLOCK SIZE

The operand value you specified is not compatible with the data set type on the invocation of the IKJEDIT macro.

Module: IKJEDIT

Program: IKJEDIT

IKJ52587I EDIT OPERAND *data_set_type* DATA SET TYPE PREVIOUSLY SPECIFIED

Explanation: The indicated data set type was previously defined on the same invocation of the IKJEDIT macro. Define each data set type only once.

Module: IKJEDIT

Program: IKJEDIT

IKJ52588I [*text*] *operand_value* LONGER THAN EIGHT CHARACTERS

Explanation: For the item *text* could appear the following:

- *text* = PROMPTER NAME
- *text* = USER EXIT NAME
- *text* = CHECKER NAME
- *text* = DATA SET NAME

The value of the operand identified in the message must have a maximum length of eight characters on the invocation of the IKJEDIT macro.

Module: IKJEDIT

Program: IKJEDIT

IKJ52590I USER EXIT CAN ONLY BE SPECIFIED FOR NON-STANDARD DATA SET TYPES - *exit_name* IS IGNORED

Explanation: The indicated exit name was specified for a standard data set type on the invocation of the IKJEDIT macro. The indicated exit name was ignored, because user exits can be specified only for non-standard data set types.

Module: IKJEDIT

Program: IKJEDIT

IKJ52591I EDIT OPERAND FIXED OR VARIABLE INVALID HYPHEN MISSING

Explanation: The value specified for either the FIXED or the VAR operand on the invocation of the IKJEDIT macro is missing a hyphen. The correct syntax for the operand value is 'default-maximum'. Notice that the default and maximum logical record length values are separated by a hyphen.

Module: IKJEDIT

Program: IKJEDIT

IKJ52592I DATEXIT NAME *name* LONGER THAN EIGHT CHARACTERS

Explanation: The indicated RENUM user exit name is longer than eight characters. The exit name must be eight characters or less in length.

Module: IKJEDIT

Program: IKJEDIT

IKJ52593I EDIT OPERAND *name* INVALID DATEXIT NAME OR MISSING VALUE

Explanation: The indicated RENUM user exit name is not a valid name, or it is missing. The first character of the RENUM user exit name must be an alphabetic or a national character.

Module: IKJEDIT

Program: IKJEDIT

IKJ52594I MORE THAN 26 DATA SET TYPES WERE SPECIFIED - ONLY FIRST 26 UNIQUE DATA SET TYPES PROCESSED

Explanation: You attempted to define more than 26 data set types on an invocation of the IKJEDIT macro. Only the first 26 data set types were defined.

Module: IKJEDIT

Program: IKJEDIT

IKJ52595I MORE THAN 10 NON-STANDARD DATA SET TYPES WERE SPECIFIED - *type* IS IGNORED.

Explanation: You attempted to define more than 10 non-standard data set types on an invocation of the IKJEDIT macro. The first 10 data set types were processed, but the indicated data set type was ignored.

Module: IKJEDIT

Program: IKJEDIT

IKJ54001I TIME SHARING IS STOPPING IMMEDIATELY

Explanation: The operator entered 'FSTOP' in response to message IKJ024D, so all output queued for terminals will be lost.

Module: IEDAYO

Program: TIOC

IKJ54003I SYSTEM FAILURE - PLEASE LOGON AGAIN

Explanation: The TSBOCAB bit has been set for this user due to abnormal address space termination.

Module: IEDAYO

Program: TIOC

IKJ54012A ENTER LOGON -

Explanation: Something other than LOGON was entered, and the terminal was not yet in a TSO/E session.

Module: IEDAYL

Program: TIOC

IKJ54013I LOGON FAILED, INVALID COMMAND

Explanation: Something other than LOGON has been entered three times in succession. If the terminal is a dial-type, it will be disconnected.

Module: IEDAYL

Program: TIOC

IKJ54014I YOUR TERMINAL IS NOT USABLE WITH TSO/E

Explanation: Either the device flags in the terminal table entry for this terminal indicate it cannot be used with TSO, or the line was not opened for output.

Module: IEDAYL

Program: TIOC

IKJ54016I MAXIMUM USERS LOGGED ON, TRY LATER

Explanation: The number of users currently logged on is equal to or greater than the current maximum permissible number of users.

Module: IEDAYL

Program: TIOC

IKJ54018A MESSAGE TOO LONG, REENTER INPUT

Explanation: The input just entered is longer than the maximum specified by the CUTOFF macro in the MCP.

Module: IEDQA4

Program: TIOC

IKJ55000I OPERATOR COMMAND NOT AUTHORIZED FOR *user_id* + YOUR INSTALLATION MUST AUTHORIZE USE OF OPERATOR COMMANDS

Explanation: SVC100 (IKJEFF00) returned a non-zero code to IKJEE100 indicating that the user entered the OPERATOR command and did not have authority, or that SVC100 could not complete the check of the user's authority.

Module: IKJEFF00

Program: OPERATOR

IKJ55001I DATA IGNORED IN THE OPERAND FIELD + OPERATOR COMMAND SHOULD HAVE NO OPERANDS

Explanation: The ECTNOPD field of the ECT equaled zero indicating that the OPERATOR command has been entered with operands. They are ignored, and processing continues.

Module: IKJEE100

Program: OPERATOR

IKJ55002A OPERATOR or OPER

Explanation: A mode message is put out to the terminal when operator mode is first entered, after an attention interruption, or if a subcommand terminates abnormally.

Module: IKJEE100, IKJEE150

Program: OPERATOR

IKJ55003I INVALID SUBCOMMAND *subcommand_name* + OPERATOR SUBCOMMANDS ARE CANCEL/DISPLAY/MONITOR/ SEND/STOPMN/END/HELP/SLIP

Explanation: The subcommand entered under OPERATOR was not valid. The return code from SVC100 (IKJEFF00) was 4 if the error was detected in SVC100.

Module: IKJEFF00, IKJEE100

Program: OPERATOR

IKJ55004I COMMAND SYSTEM ERROR + *service_routine* ERROR CODE IS *error_code*

Explanation: The OPERATOR command processor received a not valid return code from a service routine.

Module: IKJEE100

Program: OPERATOR

IKJ55005I • IKJ55051I

IKJ55005I **INVALID OPERAND** *operand* + **OPERAND SYNTACTICALLY INCORRECT OR VALID ONLY FROM SYSTEM OPERATOR CONSOLE**

Explanation: SVC100 (IKJEFF00) returned a code of 8 indicating that the operand field for the subcommand entered was not coded correctly at a terminal.

Module: IKJEFF00

Program: OPERATOR

IKJ55006I **MISSING OPERAND + OPERATOR SUBCOMMANDS MUST HAVE OPERANDS**

Explanation: The user must enter operands on OPERATOR subcommands.

Module: IKJEE100

Program: OPERATOR

IKJ55007I **UNABLE TO PROCESS ATTENTION** + *service_routine* **ERROR CODE IS** *return_code*

Explanation: A service routine (TGET, STACK, PUTLINE, GETLINE, COMMAND SCAN) returned a non-zero return code.

Module: IKJEE150

Program: OPERATOR

IKJ55008I *command/subcommand* **ABENDED DUE TO AN ERROR + COMPLETION CODE IS** *xxxx*

Explanation: This STAE exit is entered if either OPERATOR or one of its subcommands terminates abnormally.

Module: IKJEEIA0

Program: OPERATOR

IKJ55009I **SUBCOMMAND IS TOO LONG + COMMAND LENGTH EXCEEDS MAXIMUM**

Explanation: The subcommand entered exceeds 118 characters, the maximum length allowed for a non-SEND OPERATOR subcommand. Reenter the subcommand with less than 119 characters.

Module: IKJEE100

Program: OPERATOR

IKJ55050I **USERID '**' COULD NOT BE RESOLVED +**

Explanation: The user specified USER(*) on the SEND command in the background, and the user ID was not available.

The SEND command with the USER(*) operand will not run in the background unless RACF is installed and is active or the ASXBUSER field is filled in before module IKJEFT01 receives control.

Module: SEND

Audience: SEND user

IKJ55051I **NOT ALLOWED TO SEND MESSAGES TO USER(S)** *user_id_list*, **MESSAGE CANCELLED.**

Explanation: The security authorization facility (SAF) and the security server (such as RACF) indicate that you do not have the authority to send messages to users listed in the *user_id_list*.

System action: The system cancels the message for the specified users.

User response: Contact your security administrator.

Programmer response: Determine if the user should be allowed to send messages to the specified users. If the user is allowed, give the appropriate access authority to that user's profile by issuing the RACF PERMIT command with

the SMESAGE resource class. For more information about the SMESAGE resource class, see *z/OS Security Server RACF Security Administrator's Guide*.

Module: IKJEES00 IKJEES11

Audience: SEND user

IKJ55052I USER(S) *user_id_list* NOT ALLOWED TO VIEW THE MESSAGE, MESSAGE CANCELLED.

Explanation: The security authorization facility (SAF) and the security server (such as RACF) indicate that the specified users in the *user_id_list* do not have a security label that is equal to or greater than your security label.

System action: The system cancels the message for the specified users.

User response: To view your message, the specified users must log on with a security label that is equal to or greater than your security label. When they have done so, send your message again.

Module: IKJEES00 IKJEES11

Audience: SEND user

IKJ55053I SEND UNSUCCESSFUL. SEND IS NOT ACTIVE.

Explanation: Your installation indicated in the SEND PARMLIB control block that SEND be deactivated. For further assistance, contact your system programmer.

Module: IKJEES00

Audience: SEND user

IKJ55054I SEND UNSUCCESSFUL. MESSAGES CANNOT BE STORED FOR USER(S) "USERID.LIST" AT THIS TIME.

Explanation: Your installation indicated in the SEND PARMLIB control block that messages are not to be saved for the users specified. For further assistance, contact your system programmer.

Module: IKJEES00

Audience: SEND user

IKJ55055E SEND TERMINATED. THE COMMAND WAS NOT INVOKED AUTHORIZED.

Explanation: SEND determined that it was not running in an authorized environment and terminated. SEND must be invoked authorized. Contact your system programmer for further assistance.

Module: IKJEES00

Audience: SEND user

IKJ55056E SEND TERMINATED. THE MESSAGE LOG COULD NOT BE ALLOCATED. + DYNAMIC ALLOCATION ERROR CODE OF *cc* AND INFORMATION REASON CODE OF *reason_code*. FOR USERID *user_id*

Explanation: SVC 99 could not allocate the user log for the user ID specified. For a description of dynamic allocation return codes and reason codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: IKJEES00

Audience: SEND user

IKJ55057E SEND TERMINATED. I/O ERROR ON *user_id* USER LOG.

Explanation: When attempting to save a message in the specified user's user log, an I/O error occurred. For further assistance, contact your system programmer.

Module: IKJEES00

Audience: SEND user

IKJ55058I USER LOG DOES NOT EXIST FOR USER(S) *user_id_list* AND THE BROADCAST DATA SET CANNOT BE USED, MESSAGE CANCELLED.

Explanation: The specified users do not have individual user logs and the USEBROD operand of the SEND PARMLIB parameter is specified as OFF, indicating that the message cannot be stored in the broadcast data set. The users must issue the LISTBC command or log on requesting mail to create their user logs.

System action: The system does not save the message.

User response: Either send the message at a later time after the users have issued the LISTBC command or have logged on requesting mail, or contact your security administrator.

Programmer response: Either have the specified users issue the LISTBC command, log on requesting mail, or allocate an individual user log for them.

Module: SEND

Audience: SEND user

IKJ55072I USER(S) *user_id* NOT LOGGED ON OR TERMINAL DISCONNECTED, MESSAGE CANCELLED

Explanation: The system did not send your message to the users identified in IKJ55072I because of one of the following reasons:

- users were not logged on
- user terminals were disconnected
- neither the sending nor the target system supports SEND in a SYSPLEX
- the sending or the target system does not support SEND in a SYSPLEX

To have the people receive the message when they log on, specify the LOGON parameter on the SEND command.

Module: IKJEES00 IKJEES11

Audience: SEND user

IKJ55074I NO SPACE IN BROADCAST DATA SET FOR [*text*]

Explanation: For the item *text* could appear the following:

- *text* = MAIL TO <userid>
- *text* = NOTICES
- *text* = USERIDS

<userid>

The user for whom mail cannot be saved.

The broadcast data set does not have space available to add the indicated material.

System programmer response: Increase the number of records used for notices in the broadcast data set. For information about changing the amount of space for notices and customizing how users send and retrieve messages, see *z/OS TSO/E Customization*. You can also use individual user logs instead of the broadcast data set to store messages. This reduces possible contention on the broadcast data set.

User response: Try again later. The broadcast data set or individual user log may then have space available to store the indicated material. If the problem persists, inform your system programmer.

Module: IKJEES10

Audience: SEND user

IKJ55075I BROADCAST DATA SET NOT USABLE + I/O SYNAD ERROR CANNOT OPEN DATA SET

Explanation: There was either an OPEN error or an I/O error on the broadcast data set.

INSTALLATION MUST REFORMAT

Explanation: The broadcast data set was not initialized or was not in the correct format.

Module: IKJEEES10

Audience: SEND user

IKJ55077I USER(S) *user_id_list* NOT ACCEPTING MESSAGES, MESSAGE CANCELLED

Explanation: A SEND command specifying 'NOW' was issued for a user who is in no-intercom mode. The message was not sent.

Module: IKJEEES00 IKJEEES11

Audience: SEND user

IKJ55080I MESSAGE TRUNCATED TO 115 CHARACTERS

Explanation: The message text is greater than 115 characters in length.

Module: IKJEEES00 IKJEEES11

Audience: SEND user

IKJ55081I COMMAND SYSTEM ERROR + *service_routine* ERROR CODE *error_code*

Explanation: A service routine (indicated) terminated abnormally.

Module: IKJEEES00 IKJEEES10 IKJEEES11

Audience: SEND user

IKJ55082I NOT ENOUGH STORAGE TO EXECUTE COMMAND

Explanation: A conditional GETMAIN returned a code of 4 indicating it could not satisfy the request.

Module: IKJEEES00 IKJEEES10

Audience: SEND user

IKJ55083I USER(S) *user_id_list* AT BUSY TERMINAL(S) MESSAGE CANCELED

Explanation: There are insufficient output buffers available for the user ID(s). The SEND command was specified with NOWAIT and NOW, or defaulted to a busy terminal.

Module: IKJEEES00 IKJEEES11

Audience: SEND user

IKJ55084I USERIDS AFTER 20TH IGNORED

Explanation: The first twenty user IDs in the *user_id_list* were processed. All others were ignored.

Module: IKJEEES00 IKJEEES11

Audience: SEND user

IKJ55085I UNDEFINED USERID(S) *user_id_list* + USERID NOT FOUND IN MAIL DIRECTORY

Explanation: There is no entry in the broadcast data set for the indicated user ID(s).

Module: IKJEEES10

Audience: SEND user

IKJ55088I CONSOLE ID *id* IS OUT OF THE VALID RANGE.

Explanation: You issued the SEND command with a console ID that is not defined.

System action: The SEND command waits for the user to enter a valid Console ID.

User response: Issue the SEND command with a valid console ID.

Module: IKJEES00

Audience: SEND user

IKJ55089I ERROR IN SEND COMMAND PROCESSING. MESSAGE NOT SENT TO CONSOLE *console*
CONVCON RETURN CODE is *xx*.

Explanation: An internal error occurred in the TSO/E SEND command. The message was not sent to the specified console. The CONVCON service, which detected the error, returned the non-zero return code *XX*.

System action: SEND command processing ends.

User response: Note the CONVCON return code and ask your system programmer to contact the IBM support personnel.

Module: IKJEES00

Audience: SEND user

IKJ55100I THE PARMLIB REQUEST WAS SUCCESSFUL. +

Explanation: Your PARMLIB request has completed successfully. This message is informational only.

System action: The PARMLIB command is ending successfully.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55101E THE PARMLIB REQUEST WAS UNSUCCESSFUL. +

Explanation: Your PARMLIB request failed.

System action: Processing for the PARMLIB command is ending.

User response: See the next message on your screen for more information.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55102E YOU ARE NOT AUTHORIZED TO USE THE PARMLIB COMMAND.

Explanation: You have insufficient RACF authority to use the PARMLIB command.

System action: The PARMLIB command is not issued.

User response: You need authority to use the PARMLIB command. To use the LIST or CHECK operand, you need read access to the PARMLIB resource. To use the UPDATE operand, you need update authority to the PARMLIB resource. Contact your security administrator for assistance or for more information.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55103E PARMLIB COULD NOT SET UP THE RECOVERY ENVIRONMENT.

Explanation: The PARMLIB command could not establish its recovery environment.

System action: Processing for the PARMLIB command is ending.

User response: Reissue the PARMLIB command. If the error occurs again, contact local support personnel for

further assistance. Your local support personnel may need to contact the IBM support personnel to resolve this problem.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55104E THE PARMLIB UPDATE ROUTINE FAILED FOR *stmt_name*.

Explanation: The PARMLIB update routine for the specified statement failed during its attempt to update the TSO/E system parameters.

System action: Processing for the PARMLIB command is ending.

User response: Reissue the PARMLIB command. If the error occurs again, contact your local support personnel for further assistance. Your local support personnel may need to contact the IBM support personnel to resolve this problem.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55105E THE PARMLIB CLEANUP ROUTINE FAILED FOR *stmt_name*.

Explanation: The PARMLIB cleanup routine for the specified statement failed while attempting to release the storage that its corresponding update routine had obtained.

System action: Processing for the PARMLIB command is ending. There may be some residual storage from the PARMLIB routine remaining in the common storage area.

User response: Contact your local support personnel for further assistance. Your local support personnel may need to contact the IBM support personnel to resolve this problem.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55106E YOUR AUTHORITY TO USE THE PARMLIB COMMAND COULD NOT BE VERIFIED.

Explanation: The system could not verify whether you are authorized to use the PARMLIB command. The RACROUTE macro of RACF ended with a return code of 04.

System action: Processing for the PARMLIB command is ending.

User response: Contact your security administrator for assistance. For more information, see *z/OS Security Server RACF Security Administrator's Guide*.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55107I SYSTEM DEFAULTS WERE UPDATED USING MEMBER *member* OF DATASET *dataset_name*

Explanation: A PARMLIB UPDATE request completed successfully using SYS1.PARMLIB member IKJTSOxx. This message is informational only.

System action: Parameters specified in IKJTSOxx are now in effect on the system.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55108E THE PARMLIB LIST ROUTINE FAILED FOR *command_name*.

Explanation: The PARMLIB list routine for the specified command failed during its attempt to list the TSO/E system parameters.

System action: Processing for the PARMLIB command is ending.

IKJ55110E • IKJ55114I

User response: Reissue the PARMLIB command. If the error occurs again, contact your local support personnel for further assistance. Your local support personnel may need to contact the IBM support personnel to resolve this problem.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55110E UPDATE REQUEST FAILED FOR MEMBER *member* OF DATASET *dataset_name*.

Explanation: The UPDATE request failed for SYS1.PARMLIB member IKJTSoxx. System parameters were not updated.

System action: Processing for the PARMLIB command is ending.

User response: See related messages for more information and contact your local support personnel for further assistance. Your local support personnel may need to contact the IBM support personnel to resolve this problem.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55111E THE PARMLIB SYNTAX CHECK WAS UNSUCCESSFUL. +

Explanation: Your PARMLIB CHECK request failed. System parameters were not updated.

System action: Processing for the PARMLIB command is ending.

User response: See other messages on your screen for more information.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55112E SYNTAX ERRORS WERE FOUND IN MEMBER *member* OF DATASET *dataset_name*.

Explanation: The PARMLIB syntax checker identified syntax errors in SYS1.PARMLIB member IKJTSoxx. System parameters were not updated.

System action: Processing for the PARMLIB command is ending.

User response: See other messages on your screen for more information.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55113I THE PARMLIB SYNTAX CHECK WAS SUCCESSFUL. +

Explanation: The PARMLIB CHECK request completed successfully. System parameters were not updated. This message is informational only.

System action: The PARMLIB command is ending successfully.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55114I NO SYNTAX ERRORS WERE DETECTED IN MEMBER *member* OF DATASET *dataset_name*.

Explanation: The PARMLIB syntax checker did not detect any errors in SYS1.PARMLIB member IKJTSoxx. The member is syntactically valid for use with the UPDATE operation. System parameters were not updated.

System action: The PARMLIB command is ending successfully.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55115E THE PARMLIB CHECK ROUTINE FAILED FOR *stmt_name*.

Explanation: The PARMLIB check routine failed for a reason not directly related to the syntax of the statement.

System action: Processing for the PARMLIB command is ending.

User response: Reissue the PARMLIB command. If the error continues, contact your local support personnel for further assistance. Your local support personnel may need to contact the IBM support personnel to resolve this problem.

Module: IKJPRMLB

Audience: PARMLIB user

IKJ55116E THE PARMLIB LIST REQUEST WAS UNSUCCESSFUL. +

Explanation: Your PARMLIB LIST request failed. This message appears in relation to errors involving the TSO/E and RACF environments.

System action: Processing for the PARMLIB command is ending.

User response: See the next message on your screen for more information.

Module: PARMLIB

Audience: PARMLIB user

IKJ55117E THE PARMLIB REQUEST WAS UNSUCCESSFUL. +

Explanation: Your PARMLIB request failed.

System action: Processing for the PARMLIB command is ending.

User response: See the next message on your screen for more information.

Module: PARMLIB

Audience: PARMLIB user

IKJ55118E PARMLIB TERMINATED. THE COMMAND WAS NOT INVOKED AUTHORIZED

Explanation: The PARMLIB command processor determined that it was not running in an authorized environment and terminated. PARMLIB must be invoked authorized.

System action: The PARMLIB command is rejected.

User response: Contact your system programmer.

IKJ55120E THE ROUTE KEYWORD IS NOT ALLOWED WITH THE PARMLIB CHECK KEYWORD.

Explanation: The ROUTE parameter is not applicable for the PARMLIB CHECK command.

System action: The PARMLIB command is rejected.

User response: Re-enter the PARMLIB CHECK command without the ROUTE parameter.

IKJ55121I SYSTEM DEFAULTS WERE UPDATED ON SYSTEM *system_name* USING PARMLIB MEMBER *name* OF DATASET *dataset_name*.

Explanation: A PARMLIB UPDATE request completed successfully on the named system using the settings obtained from the specified PARMLIB member.

System action: The TSO/E settings specified in the named PARMLIB member are now effective on the named system.

IKJ55123E • IKJ55125E

IKJ55123E UPDATE REQUEST FAILED ON SYSTEM *system_name* WITH RETURN CODE *return_code* REASON CODE *reason_code*

Explanation: An attempt was made to update the TSO/E settings by means of the PARMLIB UPDATE command, however, the request failed on the named system.

System action: The PARMLIB command is terminated.

User response: Examine the return and reason code (both shown in decimal) for possible causes:

RC	RSN	Cause
8	6	TSO/E on the failing system could not obtain an output buffer.
12	nn	A z/OS service call failed. nn is the return code given by the failing service.
16	nn	An abend occurred. nn is the abend code.

Issue the PARMLIB command again. If the problem re-occurs, contact your local support personnel for problem analysis.

IKJ55124E UNABLE TO FORWARD REQUEST — JESXCF IS NOT ACTIVE

Explanation: An attempt was made to update/query the TSO/E PARMLIB settings for/from another TSO/E system participating in the sysplex. Since JESXCF or JES is not active or currently not available, TSO/E is not able to forward the PARMLIB command to the designated system.

System action: The PARMLIB command is rejected.

User response: Issue the PARMLIB command again later when JESXCF is active.

IKJ55125E IXZXTSOI FUNCTION CALL FAILED. RETURN CODE *return_code* REASON CODE *reason_code*

Explanation: JESXCF reported an error condition while TSO/E attempted to transfer the PARMLIB command to the designated system.

System action: The PARMLIB command is rejected.

User response: Examine the return and reason code in the message for the cause of the failure. See the following table for more information about the return/reason codes.

RC	RSN	Cause
4	20	An error occurred while processing the PARMLIB UPDATE/LIST command on one of the systems identified by the ROUTE parameter. See the following message for more details.
4	24	An error occurred while processing the PARMLIB UPDATE/LIST command on one of the system named by the ROUTE parameter.
4	28	JESXCF was not able to obtain the required storage to return the information provided by the remote TSO/E routine to the PARMLIB command processor.
4	36	An internal JESXCF error occurred.
4	44	The system name specified by the ROUTE parameter is valid but not active.
4	48	The current level of the Job Entry Subsystem (JES) does not support TSO Generic Resource.
4	56	The group name specified by the ROUTE parameter is valid, but no system in the group is active.
4	68	Incorrect version identifier found in the parameter list passed to JESXCF by the PARMLIB command processor.

All other return/reason codes indicate a severe error condition. Contact the IBM support personnel for problem analysis.

Issue the PARMLIB command again later. If the problem occurs again, contact your local support personnel for problem analysis.

IKJ55126E UNKNOWN SYSTEM NAME OR GROUP NAME *name*

Explanation: The system name or group name specified in the ROUTE parameter is not defined. If the name identifies a system, the system might not be active in the sysplex or the operating system running on that system is not on the appropriate level.

System action: The PARMLIB command is rejected.

User response: Issue the PARMLIB command again with a valid system/group name.

IKJ55127E PARMLIB COMMAND REJECTED — NOT RUNNING IN A SYSPLEX ENVIRONMENT

Explanation: The ROUTE parameter was specified on the PARMLIB command, but the system is either

- not running in a sysplex
- the sysplex consists of one active system only

System action: The PARMLIB command is rejected.

User response: Reenter the PARMLIB command without the ROUTE keyword.

IKJ55128E REMOTE SYSTEM *system_name* **FAILED, RETURN CODE** *return_code* **REASON CODE** *reason_code*

Explanation: An abend occurred while handling a PARMLIB UPDATE/LIST command on another system. The reason code shows the abend code associated with the error.

System action: The PARMLIB command is terminated.

User response: Examine the reason code (abend code) for possible causes. If necessary, contact your local support personnel for further assistance.

IKJ55130E THE LIST REQUEST FAILED ON SYSTEM *name* **RETURN CODE** *return_code* **REASON CODE** *reason_code*

Explanation: An attempt was made to obtain the TSO/E settings by means of the PARMLIB LIST command, however, the request failed on the named system.

System action: The PARMLIB command is terminated.

User response: Examine the return and reason code (both shown in decimal) for possible causes:

RC	RSN	Cause
8	6	TSO/E on the failing system could not obtain an output buffer for the PARMLIB settings to be passed back.
12	nn	A z/OS service call failed. nn is the return code given by the failing service.
16	nn	An abend occurred. nn is the abend code.

Issue the PARMLIB command again. If the problem re-occurs, contact your local support personnel for problem analysis.

IKJ55131E SEVERE ERROR OCCURRED ON SYSTEM *name.service* **FAILED WITH RETURN CODE** *return_code*

Explanation: An attempt was made to update or query the TSO/E settings for or from another system in the sysplex, but the remote system failed. TSO/E on the remote system encountered an error condition while calling a system service.

System action: Processing continues.

User response: Examine the return code of the failing service for the cause of the error. If the failing service is IKJBCMSG,

IKJ55132E • IKJ55136E

Return Code 04= TIME_OUT
08= SVC99_FAILED
12= ENQ_FAILED
16= NO_EESCB_PTR
1080= DDNAME_NOT_FOUND

Contact your local support personnel for further assistance. Your local support personnel can contact the IBM support personnel to resolve the problem.

IKJ55132E ERROR OCCURRED DURING CLEANUP PROCESSING OF PARMLIB COMMAND.

Explanation: The general cleanup of the PARMLIB command processing failed.

System action: Processing for the PARMLIB command is ending. There may be some residual storage from the PARMLIB routine remaining in the common storage area.

User response: Contact your local support personnel for further assistance.

IKJ55133E ERROR OCCURRED DURING PARMLIB LIST PROCESSING

Explanation: The PARMLIB LIST command failed.

System action: Processing for the PARMLIB command is ending.

User response: See the next message on your screen for more information.

IKJ55134E ERROR OCCURRED DURING PARMLIB CHECK PROCESSING

Explanation: The PARMLIB CHECK command failed.

System action: Processing for the PARMLIB command is ending.

User response: See the next message on your screen for more information.

IKJ55135I REQUEST TO SWITCH BROADCAST DATA SET DETECTED WHILE PROCESSING PARMLIB MEMBER IKJTSOxx. CONFIRM THE SWITCH FROM *current-data-set-name* ON VOLUME *current-volser* TO *new-data-set-name* ON VOLUME *new-volser*. + REPLY YES TO SWITCH, NO TO CANCEL PROCESSING OF THIS PARMLIB MEMBER.

Explanation: The command PARMLIB UPDATE(xx) was issued and the IKJTSOxx member of parmlib specifies a broadcast data set different from the current one. The message contains the name and volume serial for both the current broadcast data set and the new broadcast data set.

System action: After a reply of "YES" is received, the current broadcast data set is unallocated and the new one is allocated.

User response: Reply "YES" to confirm the broadcast data set switch. Any reply other than "YES" will cancel processing of the IKJTSOxx parmlib member.

Module: IKJPRMLB

IKJ55136E LOCATE FAILED FOR BROADCAST DATA SET *dsname*. LOCATE RETURN CODE *retcode*.

Explanation: This message is issued when a PARMLIB UPDATE(xx) or a SET IKJTSO=xx command is being processed. The broadcast data set name specified in the DATASET subfield of the BROADCAST keyword of the IKJTSOxx parmlib member could not be found with the LOCATE macro. The LOCATE macro return code is displayed in the message.

Refer to *z/OS DFSMSdfp Advanced Services* for more information on the meaning of the LOCATE return code.

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: Verify that the data set name is specified correctly. Verify that the data set is cataloged. If the data set being specified is not a cataloged data set, you must specify the volume on which the data set resides by using the VOLUME subfield of the BROADCAST keyword. Verify that the volume on which the data set resides is a DASD volume and is mounted and available.

Module: IKJEESPR

IKJ55137E LOCATE ERROR FOR BROADCAST DATA SET *dsname*. +

Explanation: This message is issued when a PARMLIB UPDATE(xx) or a SET IKJTSO=xx command is being processed. A LOCATE macro error occurred while trying to retrieve catalog information for the broadcast data set specified in the DATASET subfield of the BROADCAST keyword of the IKJTSOxx parmlib member.

In addition to this message, one of the following messages will also be issued to describe the error: IKJ55138E, IKJ55139E, IKJ55140E, or IKJ55141E.

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: For additional information, refer to the second level message.

Also, you may be able to avoid this error by using the VOLUME subfield of the BROADCAST keyword to specify explicitly the volume on which the broadcast data set resides.

Module: IKJEESPR

IKJ55138E DATA SET IS MIGRATED.

Explanation: This is a second level message for message IKJ55137E. The broadcast data set named in IKJ55137E has been migrated. You cannot specify a migrated broadcast data set.

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: Do not specify a migrated data set as the broadcast data set.

Module: IKJEESPR

IKJ55139E DATA SET RESIDES ON MULTIPLE VOLUMES. IT MUST RESIDE ON A SINGLE VOLUME.

Explanation: This is a second level message for message IKJ55137E or IKJ55143E. The broadcast data set named in IKJ55137E or IKJ55143E is a multivolume data set. It should not be used for a broadcast data set.

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: Specify a broadcast data set that resides on a single volume.

Module: IKJEESPR

IKJ55140E LOCATE DID NOT RETURN A VOLUME NAME.

Explanation: This is a second level message for message IKJ55137E. The LOCATE macro failed to return the volume name of a cataloged data set. (This is a LOCATE internal error.)

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: You can try specifying a different broadcast data set. You can also try specifying the VOLUME subfield of the BROADCAST keyword to name explicitly the volume on which the broadcast data set resides, or try reallocating and recataloging the broadcast data set.

Module: IKJEESPR

IKJ55141E LOCATE INDICATED DATA SET NAME IS AN ALIAS, BUT NO PRIMARY NAME WAS RETURNED.

Explanation: This is a second level message for message IKJ55137E. The LOCATE macro found that the specified broadcast data set name is an alias, but LOCATE failed to return its primary name. (This is a LOCATE internal error.)

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: Try using the primary name of the broadcast data set, rather than an alias name. If you specify an alias name, you cannot specify the VOLUME subfield of the BROADCAST keyword. If you specify the primary name, you can use the VOLUME subfield of the BROADCAST keyword to indicate the volume you want.

Module: IKJEESPR

IKJ55142E BROADCAST DATA SET *dsname* NOT FOUND ON VOLUME *volname*.

Explanation: This message is issued when a PARMLIB UPDATE(xx) or a SET IKJTSO=xx command is being processed. The OBTAIN macro determined that the broadcast data set specified in the DATASET subfield of the BROADCAST keyword of the IKJTSOxx parmlib member was not on the volume specified by the VOLUME subfield.

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: Verify that you have specified the broadcast data set name correctly in the DATASET subfield of the BROADCAST keyword. Also, verify that you have specified the correct volume in the VOLUME subfield of the BROADCAST keyword.

Module: IKJEESPR

IKJ55143E OBTAIN FAILED FOR BROADCAST DATA SET *dsname* USING VOLUME *volname*. +

Explanation: This message is issued when a PARMLIB UPDATE(xx) or a SET IKJTSO=xx command is being processed. An OBTAIN macro error occurred while trying to verify that the broadcast data set was on the specified volume.

In addition to this message, message IKJ55139E or IKJ55144E will also be issued to describe the error.

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: For additional information, refer to message IKJ55139E or IKJ55144E.

Module: IKJEESPR

IKJ55144E OBTAIN MACRO RETURN CODE *retcode*.

Explanation: This is a second level message for message IKJ55143E. You specified a broadcast data set name and volume on the BROADCAST keyword of the IKJTSOxx parmlib member during a PARMLIB UPDATE(xx) or SET IKJTSO=xx command. However, the OBTAIN macro returned a non-zero return code (as shown in the message) when trying to verify that the data set was on the specified volume.

For more information on the meaning of the OBTAIN return code, refer to *z/OS DFSMSdfp Advanced Services*.

System action: The PARMLIB UPDATE(xx) or SET IKJTSO=xx command fails.

User response: In addition to looking up the meaning of the OBTAIN return code, you should also verify the following:

- The broadcast data set name was specified correctly in the DATASET subfield of the BROADCAST keyword of IKJTSOxx.
- The volume name was specified correctly in the VOLUME subfield of the BROADCAST keyword of IKJTSOxx.
- The volume specified is the volume on which the broadcast data set actually resides.
- The volume specified is mounted and available. The volume specified must refer to a DASD volume.
- The broadcast data set is not a multivolume data set.

Module: IKJEESPR

IKJ55301I THE CONSOLE COMMAND HAS TERMINATED. + THE RECOVERY ENVIRONMENT COULD NOT BE ESTABLISHED.

Explanation: The CONSOLE command attempted to establish task level recovery and due to an internal error, recovery could not be established.

System action: The CONSOLE command ends with a return code of 16.

User response: Ask your local support personnel to contact IBM support personnel regarding this error.

Module: IKJCNSOL

Audience: CONSOLE user

IKJ55302I THE CONSOLE SESSION IS ALREADY ACTIVE.

Explanation: You specified the ACTIVATE keyword on the CONSOLE command and a console session is already active. This message is informational only.

System action: The CONSOLE command ends with a return code of 4.

Module: IKJCN SOL IKJCNASR

Audience: CONSOLE user

IKJ55303I THE CONSOLE COMMAND HAS TERMINATED. + AN ERROR OCCURRED DURING CONSOLE INITIALIZATION. THE MCSOPER RETURN CODE WAS *return_code* AND THE REASON CODE WAS *reason_code*.

Explanation: The CONSOLE command attempted to establish a console session with MVS console services, but the attempt failed. The MCSOPER macro, used to invoke MVS console services, returned the indicated return code and reason code.

System action: The CONSOLE command ends with a return code of 40.

User response: See *z/OS MVS Programming: Authorized Assembler Services Reference LLA-SDU* for an explanation of the MCSOPER return code and reason code. Take the action suggested in the explanation for the particular return code.

If *return_code* from MCSOPER is 4, after a CONSOLE ACTIVATE, then the console name is already in use. Use a different console name.

Module: IKJCNASR

Audience: CONSOLE user

IKJ55304I THE SYSCMD KEYWORD REQUIRES A SUBFIELD (value).

Explanation: You specified the SYSCMD keyword on the CONSOLE command without a subfield (value). The SYSCMD keyword must be followed by a system command enclosed in parentheses. An example is CONSOLE SYSCMD(D T).

System action: The CONSOLE command ends with a return code of 60.

User response: Correct the command syntax and issue the command again.

Module: IKJCN SOL IKJCNASR

Audience: CONSOLE user

IKJ55305I THE CONSOLE COMMAND HAS TERMINATED. + USER *user_id* DOES NOT HAVE CONSOLE COMMAND AUTHORITY.

Explanation: You do not have the authority to issue the CONSOLE command. Your installation must authorize use of this command.

System action: The CONSOLE command ends with a return code of 36.

User response: Contact your security administrator for assistance.

Module: IKJCN SOL IKJCNASR

Audience: CONSOLE user

IKJ55306A PRESS THE ATTENTION KEY AGAIN TO EXIT THE CONSOLE COMMAND. ANY OTHER RESPONSE WILL RETURN TO SUBCOMMAND PROMPT.

Explanation: The CONSOLE command prompted you for information and you pressed the attention key. This message is issued to give you the option of either pressing the attention key again to end the console conversational mode, or pressing the enter key to return to the CONSOLE prompt. Data entered in response to this message will be ignored by the CONSOLE command.

IKJ55307I • IKJ55310I

System action: The CONSOLE command waits for the user to respond.

User response: Press the attention key to end console conversational mode or press the Enter key to return to the CONSOLE prompt.

Module: IKJCN SOL IKJCN CAT

Audience: CONSOLE user

IKJ55307I THE CONSOLE COMMAND HAS TERMINATED. + A CONSOLE SESSION IS NOT ACTIVE.

Explanation: You specified the DEACTIVATE keyword on the CONSOLE command, but the CONSOLE command detected that no session is currently active.

System action: The CONSOLE command ends with a return code of 20.

User response: If you want to end the console session, no action is required. If you want to activate a new console session, issue the CONSOLE command without the DEACTIVATE keyword.

Module: IKJCN SOL IKJCN ASR

Audience: CONSOLE user

IKJ55308I THE CONSOLE COMMAND HAS TERMINATED. + THE CONSOLE COMMAND DETECTED AN INTERNAL ERROR xxx DURING PROCESSING.

Explanation: An internal error occurred during CONSOLE command processing or during message processing. The CONSOLE command received the error code xxx.

System action: The CONSOLE command ends with a return code of 28.

User response: Note this message and the displayed error code and ask your system programmer to report the problem to the IBM support personnel.

Module: IKJCN ASR

Audience: CONSOLE user

IKJ55309I THE CONSOLE COMMAND HAS TERMINATED. + CONSOLE COMMAND INITIALIZATION FAILED.

Explanation: An error was detected during CONSOLE command initialization.

System action: The CONSOLE command ends with a return code of 52.

User response: Ask your system programmer to contact the IBM support personnel regarding this error.

Module: IKJCN SOL

Audience: CONSOLE user

IKJ55310I THE CONSOLE REQUEST COULD NOT BE PROCESSED. + CONSOLE DEACTIVATION IS IN PROGRESS.

Explanation: The CONSOLE command could not process your request because it detected that console deactivation is currently in progress.

System action: The CONSOLE command ends with a return code of 24.

User response: Activate a console session by issuing the CONSOLE command. Enter the request again after the console session is active.

Module: IKJCN SOL

Audience: CONSOLE user

IKJ55311I THE CONSOLE COMMAND HAS TERMINATED. + *keyword* AND *keyword* ARE MUTUALLY EXCLUSIVE KEYWORDS.

Explanation: You specified two keywords on the CONSOLE command that are mutually exclusive. This message displays the two keywords in error.

System action: The CONSOLE command ends with a return code of 60.

User response: Check the keywords specified on the command and determine which one is needed. Issue the CONSOLE command again with the correct keyword.

Module: IKJCNSOL

Audience: CONSOLE user

IKJ55312I THE CONSOLE COMMAND HAS TERMINATED. + THE COMMAND BUFFER COULD NOT BE PARSED.

Explanation: The parse routine detected an error while parsing the CONSOLE command buffer.

System action: The CONSOLE command ends with a return code of 60.

User response: Check the keywords specified on the command and issue the command again.

Module: IKJCNSOL

Audience: CONSOLE user

IKJ55313I THE CONSOLE COMMAND HAS TERMINATED. + AN ERROR OCCURRED DURING CONSOLE TERMINATION. THE MCSOPER RETURN CODE WAS *return_code* AND THE REASON CODE WAS *reason_code*.

Explanation: The CONSOLE attempted to end the console session with MVS console services, but the attempt failed. The MCSOPER macro, used to invoke MVS console services, returned the indicated return code and reason code.

System action: The CONSOLE command ends with a return code of 48.

User response: See *z/OS MVS Programming: Authorized Assembler Services Reference LLA-SDU* for an explanation of the MCSOPER return code and reason code. Take the action suggested in the explanation for the particular return code.

Module: IKJCNASR

Audience: CONSOLE user

IKJ55314I A SEVERE ERROR OCCURRED DURING CONSOLE PROCESSING. + SYSTEM ABEND *abend_code*, REASON CODE *reason_code*.

Explanation: The CONSOLE command or a related console service encountered an abend during processing. The displayed system abend code and reason code indicate the error.

System action: The CONSOLE command ends with a return code of 28.

System programmer response: Check the system dump that was taken to determine the cause of the abend. See *z/OS MVS System Codes* for an explanation of the system abend and reason codes.

User response: Note the message ID and system abend and reason codes. Contact your system programmer with this information.

Module: IKJCNSOL IKJCNASR

Audience: CONSOLE user

IKJ55315I THE SUBFIELD OF THE SYSCMD KEYWORD MUST HAVE A TERMINATING PARENTHESIS.

Explanation: You specified the SYSCMD keyword on the CONSOLE command, but you omitted the right parenthesis after the subfield (value). The subfield must be enclosed in parentheses. An example is CONSOLE SYSCMD (D T).

System action: The CONSOLE command ends with a return code of 60.

User response: Check the command syntax and issue the command again with a right parenthesis after the SYSCMD keyword subfield.

Module: IKJCNSOL IKJCNASR

Audience: CONSOLE user

IKJ55316I THE NAME KEYWORD IS NOT VALID WHEN A CONSOLE SESSION IS ACTIVE. + THE CURRENT CONSOLE NAME IS *consname*.

Explanation: You specified the NAME keyword on the CONSOLE command and a console session is already active. The name of the current console session is *consname*. The NAME keyword is valid only when you are activating a console session.

System action: The CONSOLE command ends with a return code of 56.

User response: If you want to use the console name you specified, issue a CONSOLE DEACTIVATE command to end the current console session. Then issue the CONSOLE command specifying the new console name.

Module: IKJCNSOL

Audience: CONSOLE user

IKJ55317I THE CONSOLE COMMAND HAS TERMINATED. + THE PUTGET SERVICE ROUTINE RETURN CODE WAS *xx*.

Explanation: The CONSOLE command attempted to obtain user input but the attempt failed. The PUTGET service routine, which was used to process the terminal input, returned the indicated error return code.

System action: The CONSOLE command ends with a return code of 32.

User response: Use the PUTGET return code to determine the reason for the failure and correct the error. For an explanation of the return code, see *z/OS TSO/E Programming Services*.

Module: IKJCNSOL

Audience: CONSOLE user

IKJ55318I THE *command* COMMAND COULD NOT BE ATTACHED. THE ATTACH RETURN CODE WAS *xx*.

Explanation: The CONSOLE command attempted to attach the TSOEXEC or HELP command processor, but the attempt failed.

System action: The CONSOLE prompt is displayed.

User response: See *z/OS MVS Programming: Authorized Assembler Services Reference ALE-DYN* for an explanation of ATTACH macro return codes. Take the action suggested in the explanation for the particular return code.

Module: IKJCNSOL

Audience: CONSOLE user

IKJ55319I THE SYSTEM COMMAND WAS NOT PROCESSED. + THE COMMAND IS TOO LONG.

Explanation: The MVS system or subsystem command that you entered on the CONSOLE command is longer than the maximum length allowed. The maximum length allowed by MVS Console Services (MCS) is 126 characters.

System action: The system or subsystem command is not passed to MVS Console Services (MCS) for processing. If command mode is being used, the CONSOLE command ends with a return code of 64. If conversational mode is being used, the CONSOLE prompt appears.

User response: Enter the command again, ensuring that the length of the command is 126 characters or less.

Module: IKJCNASR

Audience: CONSOLE user

IKJ55321I GETMSG PROCESSING HAS TERMINATED. THE PARAMETER LIST IS NOT VALID.

Explanation: You invoked the GETMSG service with a parameter list that is not valid.

System action: The service ends with a return code of 32.

User response: Check the parameter list that you passed to the service.

Module: IKJCNUGW

Audience: GETMSG user

IKJ55322I GETMSG PROCESSING HAS TERMINATED. THE MCSOPMSG RETURN CODE WAS *return_code* AND THE REASON CODE WAS *reason_code*.

Explanation: The GETMSG service attempted to obtain a message from MVS console services, but the attempt failed. The MCSOPMSG macro returned an unexpected return code and reason code.

System action: The service ends with a return code of 36.

User response: See *z/OS MVS Programming: Authorized Assembler Services Reference LLA-SDU* for an explanation of the MCSOPMSG macro return code and reason code. Take the action indicated for the particular return code.

Module: IKJCNAGW

Audience: GETMSG user

IKJ55323I GETMSG PROCESSING HAS TERMINATED. A CONSOLE SESSION IS NOT ACTIVE.

Explanation: You invoked the GETMSG service but a console session has not been established by the CONSOLE command.

System action: The service ends with a return code of 20.

User response: Enter the CONSOLE command to establish a console session.

Module: IKJCNUGW

Audience: GETMSG user

IKJ55324I GETMSG PROCESSING HAS TERMINATED. RECOVERY COULD NOT BE ESTABLISHED.

Explanation: The GETMSG service attempted to establish task-level recovery and due to an internal error, recovery could not be established.

System action: The service ends with a return code of 16.

User response: Ask your system programmer to report this problem to the IBM support personnel.

Module: IKJCNUGW

Audience: GETMSG user

IKJ55325I THE GETMSG REQUEST COULD NOT BE PROCESSED. CONSOLE DEACTIVATION IS IN PROGRESS.

Explanation: You invoked the GETMSG service while console deactivation was in progress.

System action: The service ends with a return code of 24.

User response: After deactivation is complete, issue the CONSOLE command to establish another console session.

Module: IKJCNAGW

Audience: GETMSG user

IKJ55327I GETMSG PROCESSING HAS TERMINATED. + SYSTEM ABEND *abend_code*, REASON CODE *reason_code*.

Explanation: The GETMSG service encountered an abend during processing. The displayed system abend code and reason code indicate the error.

System action: The service ends with a return code of 28.

System programmer response: Check the system dump that was taken to determine the cause of the abend. See *z/OS MVS System Codes* for an explanation of the system abend and reason codes.

User response: Note the message ID and system abend and reason codes. Contact your system programmer with this information.

Module: IKJCNUGW

Audience: GETMSG user

IKJ55351I SOLDISPLAY(YES/NO) SOLNUM(*size*) UNSOLDISPLAY(YES/NO) UNSOLNUM(*size*)

Explanation: You issued the CONSPROF command with no operands. This is an informational message indicating the current settings of your CONSOLE profile.

System action: The CONSPROF command ends with a return code of 0.

Module: IKJCNPRF

Audience: CONSPROF user

IKJ55352I THE CONSPROF COMMAND HAS TERMINATED. + RECOVERY COULD NOT BE ESTABLISHED.

Explanation: The CONSPROF command attempted to establish task-level recovery and due to an internal error, recovery could not be established.

System action: The CONSPROF command ends with a return code of 16.

User response: Ask your system programmer to contact IBM support personnel about this problem.

Module: IKJCNPRF

Audience: CONSPROF user

IKJ55353I THE CONSPROF COMMAND HAS TERMINATED. + USER *user_id* DOES NOT HAVE CONSOLE COMMAND AUTHORITY.

Explanation: You do not have authority to issue the CONSPROF command. The CONSPROF command requires CONSOLE command authority.

System action: The CONSPROF command ends with a return code of 8.

User response: Contact your security administrator for assistance.

Module: IKJCNPRF

Audience: CONSPROF user

IKJ55354I THE CONSPROF COMMAND HAS TERMINATED. + THIS COMMAND MUST BE INVOKED WITH APF AUTHORIZATION.

Explanation: The CONSPROF command can run only in an APF-authorized environment.

System action: The CONSPROF command ends with a return code of 4.

System programmer response: Make sure that the CONSPROF command resides in an authorized library and that the CONSPROF command name is placed in the authorized command name table. See *z/OS TSO/E Customization* for more information.

User response: Inform your system programmer that you received this message.

Module: IKJCNPRF

Audience: CONSPROF user

IKJ55355I THE CONSPROF COMMAND HAS TERMINATED. + SYSTEM ABEND *abend_code*, **REASON CODE** *reason_code*.

Explanation: The CONSPROF command encountered an abend during processing.

System action: The CONSPROF command ends with a return code of 20.

System programmer response: Check the system dump that was taken to determine the cause of this abend. See *z/OS MVS System Codes* for an explanation of the system abend and reason codes.

User response: Note the message ID and system abend and reason codes. Contact your system programmer with this information.

Module: IKJCNPRF

Audience: CONSPROF user

IKJ55356I THE CONSPROF COMMAND HAS TERMINATED. + THE COMMAND BUFFER COULD NOT BE PARSED.

Explanation: The parse routine detected an error while parsing the CONSPROF command buffer.

System action: The CONSPROF command ends with a return code of 12.

User response: Check your command syntax and issue the command again.

Module: IKJCNPRF

Audience: CONSPROF user

IKJ55357I THE VALUE SPECIFIED ON THE *keyword* **KEYWORD IS GREATER THAN THE MAXIMUM VALUE. + THE MAXIMUM VALUE OF** *nnnnn* **WAS USED INSTEAD OF THE VALUE SPECIFIED.**

Explanation: You specified a size for either the solicited or unsolicited message table that is greater than the maximum size allowed by your installation. The maximum size allowed by your installation for the indicated message table is *nnnnn*. This is the size that will be used.

In the message, *keyword* is either SOLNUM (solicited message table) or UNSOLNUM (unsolicited message table).

System action: The CONSPROF command ends successfully.

User response: Note the size of the message table that will be used for your console session.

Module: IKJCNPRF

Audience: CONSPROF user

IKJ55361I THE UNSOLICITED MESSAGE TABLE HAS REACHED *nnn%* **CAPACITY.**

Explanation: Unsolicited messages are being routed to the user's console at a greater rate than they are being processed. The unsolicited message table is *nnn%* full. This situation typically occurs when you have specified that unsolicited messages are not to be displayed at your terminal and either:

- The application responsible for retrieving the messages (using the GETMSG service) is processing them at a slower rate than they are being sent.
- No application is retrieving messages.

This situation may also occur when unsolicited messages are being displayed at the terminal and the unsolicited message traffic is greater than the CONSOLE command can process.

System action: Processing continues.

User response: You may need to take action to correct the situation and prevent messages from being lost. This depends on whether your installation has written an exit routine to correct the situation.

IKJ55362I • IKJ55363I

- If unsolicited messages are not currently being displayed at your terminal, you may need to begin displaying these messages until the number of messages in the table decreases. Issue the CONSPROF UNSOLDISPLAY(YES) command to begin displaying unsolicited messages. If the current size of the unsolicited message table is less than the maximum size allowed by your installation, you can optionally increase the table size using the CONSPROF command with the UNSOLNUM keyword. To display the current size of the unsolicited message table, issue the CONSPROF command with no operands.
- If unsolicited messages are currently being displayed at your terminal, see your system programmer for assistance in resolving this problem.

Module: CONSOLE

Audience: CONSOLE user

IKJ55362I THE SOLICITED MESSAGE TABLE HAS REACHED *nnn*% CAPACITY.

Explanation: Solicited messages are being routed to the user's console at a greater rate than they are being processed. The solicited message table is *nnn*% full. This situation typically occurs when you have specified that solicited messages are not to be displayed at your terminal and either:

- The application responsible for retrieving the messages (using the GETMSG service) is processing them at a slower rate than they are being sent.
- No application is retrieving messages.

This situation may also occur when solicited messages are being displayed at the terminal and the solicited message traffic is greater than the CONSOLE command can process.

System action: Processing continues.

User response: You may need to take action to correct the situation and prevent messages from being lost. This depends on whether your installation has written an exit routine to correct the situation.

- If solicited messages are not currently being displayed at your terminal, you may need to begin displaying these messages until the number of messages in the table decreases. Issue the CONSPROF SOLDISPLAY(YES) command to begin displaying solicited messages. If the current size of the solicited message table is less than the maximum size allowed by your installation, you can optionally increase the table size using the CONSPROF command with the SOLNUM keyword. To display the current size of the solicited message table, issue the CONSPROF command with no operands.
- If solicited messages are currently being displayed at your terminal, see your system programmer for assistance in resolving this problem.

Module: IKJCNANT

Audience: CONSOLE user

IKJ55363I A MESSAGE COULD NOT BE TRANSLATED TO *language*. + *language* IS NOT AN ACTIVE LANGUAGE FOR TRANSLATION.

Explanation: An attempt was made to display a message in the indicated language, but the language is not active in the MVS message service.

System action: Processing continues. If a secondary language was specified (by your installation or with the PROFILE command) and that language is also not active, or if no secondary language was specified, the message is issued in US English.

User response: Ask your system administrator to activate the language you want. When the language is active, messages will be displayed in the specified language if translated versions of the messages are available.

Module: IKJTRANS

Audience: Any TSO/E user

IKJ55364I **MESSAGES WILL NOT BE TRANSLATED TO** *language*. + *language* **IS NOT SUPPORTED BY THE DEVICE THAT THE USER IS CURRENTLY USING.**

Explanation: An attempt was made to display a message in the indicated language, but the language is not supported by your terminal. The language specified requires double-byte character set (DBCS) data and your terminal does not support DBCS data.

System action: Processing continues. If a secondary language was specified (by your installation or with the PROFILE command) and that language also requires DBCS, or if no secondary language was specified, all subsequent messages are issued in US English for the duration of your TSO/E session.

User response: If you require this language, log off from your device, then log on to a device that supports double-byte character set (DBCS) data.

Module: IKJTRANS

Audience: Any TSO/E user

IKJ55365I **A MESSAGE COULD NOT BE TRANSLATED TO** *language*. + **THE MVS MESSAGE SERVICE RETURN CODE WAS** *return_code* **AND THE REASON CODE WAS** *reason_code*.

Explanation: An attempt was made to display a message in the indicated language, but an unexpected error occurred in the MVS message service.

System action: Processing continues. If a secondary language was specified (by your installation or with the PROFILE command) and the message cannot be issued in the secondary language, or if no secondary language was specified, the message is issued in US English.

System programmer response: Refer to the description of the TRANMSG macro in *z/OS MVS Programming: Assembler Services Reference ABE-HSP* for an explanation of the return and reason codes. Take the action suggested for the particular return code.

User response: Ask your system administrator to activate the language you want. When the language is active, messages will be displayed in the specified language if translated versions of the messages are available.

Module: IKJTRANS

Audience: Any TSO/E user

IKJ56000I **COMMAND SYSTEM ERROR + RETURN CODE is** *return_code*

Explanation: The parse return code is non-zero.

BLDL I/O ERROR

Explanation: The BLDL macro instruction returned a return code greater than 4.

Module: IKJEFT08

Program: TMP/CALL

IKJ56001I *member* **SPECIFIED BUT** *dsname* **NOT A PARTITIONED DATA SET**

Explanation: The data set organization that was passed by DAIR to CALL was not '02'X (partitioned). The CALL target data set must be a partitioned data set.

Module: IKJEFT08

Program: TMP/CALL

IKJ56002I *dsname* **NOT USABLE + CANNOT OPEN DATA SET BLDL I/O ERROR**

Explanation: The open flags were not set in the DCB for the data set.

Module: IKJEFT08

Program: TMP/CALL

IKJ56003I • IKJ56054I

IKJ56003I PARM FIELD TRUNCATED TO 100 CHARACTERS

Explanation: The user entered a parameter string longer than 100 characters. The data has been truncated.

Module: IKJEFT08

Program: TMP/CALL

IKJ56004I DATA SET *dsname* NOT IN CATALOG

Explanation: DAIR return code equaled 8. Catalog error of 8 or greater. The data set was not found in the catalog.

Module: IKJEFT08

Program: TMP/CALL

IKJ56005I MEMBER *member* NOT IN DATA SET *dsname* MEMBER *member* NOT FOUND WITHIN THE STANDARD SEARCH ORDER

Explanation: The specific member name was not found in the directory for the specified data set or the standard search order (TSOLIB (TASKLIB), STEPLIB, JOBLIB, LPA, LINKLIST).

Module: IKJEFT08

Program: TMP/CALL

IKJ56006I TEMPNAME ASSUMED AS A MEMBER NAME

Explanation: A member name was not specified, and TEMPNAME default is used.

Module: IKJEFT08

Program: TMP/CALL

IKJ56007I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: Parse error code was 16.

Module: IKJEFG00

Program: CALL

IKJ56052I COMMAND SYSTEM ERROR + *service_routine* ERROR CODE *error_code*

Explanation: A non-zero return code was received from the STACK or PARSE service routine.

Module: IKJEFR00

Program: RUN

IKJ56053I PARM FIELD TRUNCATED TO 100 CHARACTERS

Explanation: The length of the PARM string entered by the user was longer than 100 characters.

Module: IKJEFR00

Program: RUN

IKJ56054I *type* INVALID DATA TYPE

Explanation: The user was prompted for a data type, and supplied a not valid type.

Module: IKJEFR00

Program: RUN

IKJ56055I *option IGNORED FOR compiler PROCESSING*

Explanation: The combination of the compiler specified (for example: ASM, COBOL, GOFORT, FORT, PLI, VSBASIC) and one or more options (for example: SPREC, LPREC, TEST, NOTEST, GO, NOGO, STORE, NOSTORE, PAUSE, NOPAUSE, SOURCE, OBJECT, SIZE) specified is not valid for the RUN command.

The RUN command ignores the specified options when constructing the input to the specified compiler.

Module: IKJEFR00

Program: RUN

IKJ56056I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: Non-zero return code from a conditional GETMAIN.

Module: IKJEFR00

Program: RUN

IKJ56057I CREATED DATA SET NAME, *dsname* OBJ EXCEEDS 44 CHARACTERS

Explanation: The length of the data set name created for OBJ is longer than 44.

Module: IKJEFR00

Program: RUN

IKJ56101I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: Parse issued a GETMAIN and no space was available.

Module: IKJEFD30 IKJEFD32 IKJEFD33 IKJEFD34

Audience: ALLOCATE user

IKJ56104I COMMAND SYSTEM ERROR + [*text*] ERROR CODE *error_code*

Explanation: For the item *text* could appear the following:

- *text* = PARSE
- *text* = GENTRANS
- *text* = COMMAND SCAN

GENTRANS or command scan returned a non-zero return code, or parse returned a code other than 0, 4, or 16. In the message text *error_code* is the code returned by parse, GENTRANS, or command scan.

Module: IKJEFD30 IKJEFD32 IKJEFD33 IKJEFD34

Audience: ALLOCATE user

IKJ56107I [*text*] QUANTITY EXCEEDS MAXIMUM ALLOWABLE MAXIMUM OF 65535 FOR BLOCK AND AVBLOCK. MAXIMUM OF 16777215 FOR SPACE, SPACE INCREMENT AND DIR

Explanation: For the item *text* could appear the following:

- *text* = BLOCK SIZE
- *text* = AVBLOCK
- *text* = SPACE
- *text* = SPACE INCREMENT
- *text* = DIR

The value for the specified parameter is greater than the maximum.

Module: IKJEFD37

Audience: ALLOCATE user

IKJ56109I DATA SETS NOT CONCATENATED +

Explanation: The request to concatenate a list of data sets could not be performed.

COMBINING UNLIKE DATA SET ORGANIZATIONS IS INVALID

Explanation: The DSORG for all the data sets in the list is not the same.

NUMBER OF DATA SETS EXCEEDS MAXIMUM, MAXIMUM IS 16 PARTITIONED OR 255 SEQUENTIAL DATA SETS

Explanation: The number of data sets in the list is greater than the maximum.

[text] INVALID WITH CONCATENATION REQUEST

- *text* = NEW
- *text* = MOD
- *text* = SYSOUT

Explanation: Data sets to be concatenated must be OLD or SHR. Status of NEW, MOD, or SYSOUT is invalid.

FAILURE TO ALLOCATE DATA SET *dsname*

Explanation: One of the data sets in the list could not be allocated.

DATA SET ORGANIZATION NOT SEQUENTIAL OR PARTITIONED

Explanation: One of the data sets in the list had a DSORG other than sequential or partitioned.

DATA SET NAME ASTERISK (*) INVALID WITH CONCATENATION REQUEST

Explanation: Asterisk (*) was specified as a data set name in the list.

Module: IKJEF34 IKJEF37

Audience: ALLOCATE user

IKJ56110I DATA SET *dsname* NOT ALLOCATED, MORE THAN 255 VOLUME SERIAL NUMBERS SPECIFIED

Explanation: The number of volume serial numbers specified on the VOLUME parameter exceeds the maximum.

Module: IKJEF30

Audience: ALLOCATE user

IKJ56111I DATA SET *dsname* NOT ALLOCATED, DELETE INVALID FOR MEMBERS OF PARTITIONED DATA SETS

Explanation: A disposition of DELETE was specified with a member of a partitioned data set.

Module: IKJEF30 IKJEF32

Audience: ALLOCATE user

IKJ56112A ENTER 'FREE' or 'END' + ENTER 'FREE' TO FREE AND REALLOCATE THE FILE filename OR 'END' TO TERMINATE THE COMMAND

Explanation: The filename specified on the FILE parameter is in use.

Module: IKJEF32 IKJEF34

Audience: ALLOCATE user

IKJ56113I INVALID RESPONSE, *xxxx*

Explanation: Only 'FREE' or 'END' is valid in reply to message IKJ56112A.

Module: IKJEF36

Audience: ALLOCATE user

IKJ56113A REENTER +

Explanation: Issued following message IKJ56113I:

ENTER 'FREE' TO FREE AND RE-ALLOCATE THE FILE filename, OR 'END' TO TERMINATE THE COMMAND

Explanation: The filename specified on the FILE parameter is in use.

Module: IKJEFD36

Audience: ALLOCATE user

IKJ56114A DDNAME ON ALTFIL KEYWORD MUST BE FOR A SYSIN DATA SET

Explanation: ALTFIL is a keyword of the ALLOCATE command. The ddname on the ALTFIL keyword was not a SYSIN data set. For more information on the ALLOCATE command, see *z/OS TSO/E Command Reference*.

Module: IKJEFD38

Audience: ALLOCATE user

IKJ56120I *dcb_keyword* IS IGNORED WHEN THE USING KEYWORD IS SPECIFIED

Explanation: The USING keyword was specified with one of the DCB operands (that is, an operand that also appears on the ATTRIB command). The DCB operand is ignored and ALLOCATE processing continues.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56121I ALLOCATION REQUEST IS REJECTED; THE LIKE KEYWORD IS VALID ONLY WHEN THE DATASET KEYWORD IS SPECIFIED

Explanation: The LIKE operand was specified but a new data set was not specified (that is, the DATASET keyword was omitted).

ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56122I DATASET *dsname* IS NOT ALLOCATED; ONLY STATUS OF NEW IS ACCEPTED WITH THE LIKE KEYWORD

Explanation: The LIKE operand was specified with a status of other than new. ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56123I ALLOCATION REQUEST IS REJECTED; ONLY ONE DATA SET NAME IS VALID ON THE DATASET KEYWORD WHEN THE LIKE FUNCTION IS REQUESTED

Explanation: The LIKE keyword was specified with more than one data set name on the DATASET keyword. ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56124I DATA SET IS NOT ALLOCATED; ATTRIBUTES OF DATA SET *like_dsname* NOT OBTAINABLE +

Explanation: The LIKE keyword was specified but the attributes of the model data set cannot be obtained due to the failure of data management macros. ALLOCATE processing terminates.

A more specific second-level message will be issued upon request:

- VOLUME ON WHICH MODEL DATA SET RESIDES IS NOT MOUNTED.
- ENTRY FOR DATA SET FOUND IN CATALOG, BUT DATA SET IS NOT FOUND ON INDICATED VOLUME.
- I/O ERROR OR ERROR IN VOLUME TABLE OF CONTENTS.
- ERROR IN ALLOCATE COMMAND PROCESSOR.
- UNABLE TO READ CATALOG ENTRY FOR MODEL DATA SET.
- UNABLE TO DETERMINE SPACE ALLOCATED TO MODEL DATA SET.
- UNABLE TO OPEN MODEL DATA SET.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56130I DATA SET *dsname* IS NOT ALLOCATED. RACF IS NOT ACTIVE OR IS NOT INSTALLED.

Explanation: The PROTECT keyword has been specified and RACF is either not installed or installed but not active. ALLOCATE processing terminates.

Module: IKJEFD32

Audience: ALLOCATE user

IKJ56131I ALLOCATION REQUEST IS REJECTED; THE PROTECT FUNCTION IS VALID ONLY WHEN A DATA SET NAME IS SPECIFIED

Explanation: The PROTECT keyword has been specified but a data set name has not been specified. ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56132I DATA SET *dsname* IS NOT ALLOCATED; THE PROTECT FUNCTION IS INVALID WHEN FCB IS SPECIFIED

Explanation: The PROTECT keyword was specified with the FCB keyword. The keywords are mutually exclusive. ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56133I DATA SET IS NOT ALLOCATED; THE PROTECT FUNCTION IS INVALID FOR DATA SET *dsname*

Explanation: The PROTECT keyword has been specified, but Dynamic Allocation (SVC99) has found the PROTECT function to be invalid for the specified DASD or tape data set.

ALLOCATE processing terminates.

Module: IKJEFD32

Audience: ALLOCATE user

IKJ56134I DATA SET *dsname* IS NOT ALLOCATED; THE PROTECT KEYWORD IS INVALID WITH A STATUS OF OTHER THAN NEW OR MOD

Explanation: The PROTECT keyword was specified with a status of other than NEW or MOD. Only NEW and MOD are valid.

ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56135I DATA SET *dsname* IS NOT ALLOCATED; THE COPIES KEYWORD IS INVALID WHEN THE DATASET KEYWORD IS SPECIFIED

Explanation: The COPIES keyword was specified with the DATASET keyword. These keywords are mutually exclusive.

ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56136I ALLOCATION REQUEST IS REJECTED; THE COPIES KEYWORD IS INVALID WITH A STATUS OTHER THAN SYSOUT

Explanation: The COPIES keyword was specified with a status other than SYSOUT. Only SYSOUT is valid. ALLOCATE processing terminates.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56137I DATA SET *dsname* IS NOT ALLOCATED; YOUR USERID IS NOT DEFINED TO RACF

Explanation: The PROTECT keyword was specified but your user ID is not defined to RACF. ALLOCATE processing terminates.

Module: IKJEFD32

Audience: ALLOCATE user

IKJ56138I ALLOCATE REQUEST IGNORED; SYSTEM IS NOT AT REQUIRED LEVEL TO SUPPORT THE *keyword* KEYWORD

Explanation: Your system does not support the ALLOCATE keyword indicated in the message text. You do not have the required level of MVS/System Product installed.

Module: IKJEFD32

Audience: ALLOCATE user

IKJ56139I ALLOCATE REQUEST IGNORED; THE NUMBER OF CHARACTER SETS EXCEEDS THE MAXIMUM + THE MAXIMUM NUMBER OF CHARACTER SETS IS FOUR

Explanation: Your allocation request is ignored because you specified more than the maximum number (four) of character sets on the CHARS operand of the ALLOCATE command. Reenter the ALLOCATE command with four or less character sets.

Module: IKJEFD37

Audience: ALLOCATE user

IKJ56140I ALLOCATE REQUEST IGNORED; THE NUMBER OF GROUP VALUES EXCEEDS THE MAXIMUM + THE MAXIMUM NUMBER OF GROUP VALUES IS EIGHT

Explanation: You entered more than eight group values on the COPIES operand of an ALLOCATE command. The maximum number of group values allowed on an ALLOCATE command is eight. Reenter the ALLOCATE command with eight or less values.

Module: IKJEFD37

Audience: ALLOCATE user

IKJ56141I ALLOCATE REQUEST IGNORED; THE SUM OF THE GROUP VALUES EXCEED THE MAXIMUM + THE MAXIMUM SUM OF GROUP VALUES ALLOWED IS 255

Explanation: You entered a group value or a series of group values on the COPIES operand of an ALLOCATE command. That group value was greater than 255 or the sum of the series of group values was greater than 255. The maximum number of group values that can be allocated is 255. Reissue the ALLOCATE command with a smaller group value total.

Module: IKJEFD37

Audience: ALLOCATE user

IKJ56142I MAXIMUM OF 128 OUTPUT DESCRIPTORS EXCEEDED, ALLOCATE TERMINATED

Explanation: There were more than 128 output descriptors specified on the ALLOCATE command. Because the limit is exceeded, the command is terminated.

Module: IKJEFD37

Audience: ALLOCATE user

IKJ56143I INVALID REFERENCE, ALLOCATE TERMINATED

Explanation: One of the following references specified on the ALLOCATE command was not valid:

- At least one of the specified output descriptors
- A referenced ddname.

User response: Check and correct the list of output descriptors and ddname references and reissue the command.

Module: IKJEFD35

Audience: ALLOCATE user

IKJ56144E ALLOCATE TERMINATED DUE TO INSTALLATION EXIT IKJEFD47

Explanation: An error occurred in IKJEFD47, the initialization exit for the ALLOCATE command. The exit issued a return code of 16 requesting termination.

System action: The ALLOCATE command terminates with a return code of 12.

User response: Contact your system programmer.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56145E ALLOCATE TERMINATED DUE TO INSTALLATION EXIT IKJEFD47 + ALLOCATE TERMINATED WITH REASON CODE *value*

Explanation: An error occurred in IKJEFD47, the initialization exit for the ALLOCATE command.

System action: The ALLOCATE command terminates with a return code of 12 and the specified reason code from the exit.

User response: Make a note of the reason code and contact your system programmer.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56146E ALLOCATE TERMINATED DUE TO INSTALLATION EXIT IKJEFD49

Explanation: An error occurred in IKJEFD49, the termination exit for the ALLOCATE command. The exit issued a return code of 16 requesting termination.

System action: The ALLOCATE command terminates with a return code of 12.

User response: Contact your system programmer.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56147E ALLOCATE TERMINATED DUE TO INSTALLATION EXIT IKJEFD49 + ALLOCATE
TERMINATED WITH REASON CODE *value*

Explanation: An error occurred in IKJEFD49, the termination exit for the ALLOCATE command.

System action: The ALLOCATE command terminates with a return code of 12 and the specified reason code from the exit.

User response: Make a note of the reason code and contact your system programmer.

Module: IKJEFD30

Audience: ALLOCATE user

IKJ56150I NOT ENOUGH VIRTUAL STORAGE TO EXECUTE COMMAND

Explanation: Parse return code was 16.

Module: FREE

Audience: FREE user

IKJ56152I COMMAND SYSTEM ERROR + PARSE ERROR CODE *error_code*

Explanation: Parse error code was other than 16.

Module: FREE

Audience: FREE user

IKJ56154I [*datatype*] NOT DEALLOCATED, [*command_name*] INVALID WITH [*status*]

Explanation: For the item *datatype* could appear the following:

- *datatype* = FILE *filename*
- *datatype* = DATA SET *dsname*
- *datatype* = ATTRIBUTE LIST *list*

For the item *command_name* could appear the following:

- *command_name* = KEEP
- *command_name* = DELETE
- *command_name* = CATALOG
- *command_name* = UNCATALOG

For the item *status* could appear the following:

- *status* = DEST
- *status* = HOLD
- *status* = NOHOLD

An invalid command was specified for data disposition under current status.

Module: FREE

Audience: FREE user

IKJ56155I DATA SET *dsname* NOT DEALLOCATED, DELETE INVALID FOR MEMBERS OF PARTITIONED
DATA SETS

Explanation: DELETE was specified for a member of a partitioned data set.

Module: FREE

Audience: FREE user

IKJ56156I • IKJ56191I

IKJ56156I ALL FILES NOT DEALLOCATED - UNABLE TO OBTAIN SUFFICIENT INFORMATION +
DYNAMIC ALLOCATION ERROR CODE IS *error_code*

Explanation: An error occurred during the information retrieve function of dynamic allocation.

Module: FREE

Audience: FREE user

IKJ56157E OUTPUT DESCRIPTOR *outdes* DOES NOT EXIST

Explanation: The output descriptor you specified on the FREE command was never created, or has already been freed.

System action: The FREE command terminates.

User response: None

Module: IKJEFD20

Audience: FREE user

IKJ56158E BATCH OUTPUT DESCRIPTOR *outdes* HAS NOT BEEN FREED +

Module: IKJEFD20

IKJ56159E BATCH OUTPUT DESCRIPTORS CANNOT BE FREED

Explanation: You either specified the REUSE option on the OUTDES command, or the output descriptor on the FREE command. The output descriptor you specified was created using the OUTPUT JCL statement, and cannot be freed dynamically.

System action: The FREE or OUTDES command terminates.

User response: The output descriptor will be freed either after the job runs, or after you log off.

Module: FREE or OUTDES

Audience: FREE or OUTDES user

IKJ56190I JOB *jobname(jobid)* AWAITING NETWORK SERVICES + optional second-level message from subsystem or JOB *jobname(jobid)* AWAITING NETWORK SERVICES, IN HOLD STATUS + optional second-level message from subsystem

Explanation: The job is on the subsystem spool and is awaiting networking services (unless the job is in held status). The job entry subsystem may supply a second-level message to provide more details.

Module: IKJEFF52

Program: STATUS

IKJ56191I STATUS FAILED - INVALID SSCS BIT SETTINGS FROM JOB ENTRY SUBSYSTEM

Explanation: Invalid parameters were returned to STATUS from the job entry subsystem.

At least one of the bits SSCSJACT, SSCSEXCQ, or SSCSOUTQ must be turned on in the SSCSARAY for a JOBNAM(JOBID) entry if both register 15 and SSOBRETN are zero when control is returned to the STATUS command. See module IKJEFF52's listing and mapping macro IEFJSSOB (with SSOB and SSCS control blocks) for further details.

Module: IKJEFF52

Program: STATUS

IKJ56192I **JOB *jobname(jobid)* ON OUTPUT QUEUE, IN HOLD STATUS + optional second-level message from subsystem**

Explanation: The job has completed execution and its output is being processed by the job entry subsystem (unless the output is held). The job entry subsystem may supply a second-level message to provide more details.

Module: IKJEFF52

Program: STATUS

IKJ56193I ***subsystemname* SUBSYSTEM ERROR, UNDEFINED RETURN CODE *return_code* + RETRY COMMAND, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER**

Explanation: An error was detected by the job entry subsystem while performing the cancel or status function. Error codes are listed in the IEFSSOB macro.

Module: IKJEFF49, IKJEFF52, IKJEFF54

Program: CANCEL/STATUS

IKJ56194I **JOBID *jobid* HAS INVALID SYNTAX FOR *subsystem* SUBSYSTEM + USE STATUS COMMAND TO OBTAIN VALID JOBIDS FOR THE JOBNAME**

Explanation: The active job entry subsystem, whose name is inserted in the message, found a syntax error in the indicated jobid.

If the command is STATUS, it also issues message IKJ56205I and gives the status of the jobname only. The second-level message is only inserted for the CANCEL command.

Module: IKJEFF49, IKJEFF52, IKJEFF54

Program: CANCEL/STATUS

IKJ56195I **JOB *jobname(jobid)* COMBINATION INVALID + USE STATUS COMMAND TO OBTAIN VALID JOBIDS FOR THE JOBNAME**

Explanation: The job entry subsystem has detected an invalid JOBNAME/JOBID combination. Either the jobname or the jobid (but not both) exists on a queue in the job entry subsystem.

If the command is STATUS, no second-level message is issued. STATUS also issues message IKJ56205I and gives the status of the jobname only.

Module: IKJEFF49, IKJEFF52, IKJEFF54

Program: CANCEL/STATUS

IKJ56196I **DUPLICATE JOBS WITH JOBNAME *jobname*, USE CORRECT JOBNAME(JOBID) COMBINATION + USE STATUS COMMAND TO OBTAIN VALID JOBIDS FOR THE JOBNAME**

Explanation: Several jobs exist with the same jobname. A jobid is required to identify the specific job.

Module: IKJEFF49, IKJEFF54

Program: CANCEL

IKJ56197I **JOB *jobname(jobid)* WAITING FOR EXECUTION, IN HOLD STATUS + optional second-level message from subsystem**

Explanation: The job was found on a pre-execution queue of the job entry subsystem. The optional insert indicates whether the job is held. The job entry subsystem can supply a second-level message to provide more details.

Module: IKJEFF52

Program: STATUS

IKJ56198I INVALID CANCEL REQUEST - *jobname(jobid)* IS AN ACTIVE TSO/E USER OR STARTED TASK + THESE JOB TYPES MAY NOT BE CANCELED UNLESS THEY ARE ON AN OUTPUT QUEUE

Explanation: The job entry subsystem has detected that the inserted job is active and also represents a TSO/E user or a started task. Operator commands only may be used to cancel these job types when they are active.

Module: IKJEFF54

Program: CANCEL/STATUS

IKJ56199I JOB *jobname(jobid)* NOT CANCELED BECAUSE ON OUTPUT QUEUE + USE PURGE KEYWORD OR OUTPUT COMMAND TO CANCEL OUTPUT

Explanation: The job was not canceled by the job entry subsystem. Use PURGE keyword on the CANCEL command to cancel output or use the OUTPUT command to delete held output.

Module: IKJEFF54

Program: CANCEL

IKJ56200I YOU ARE NOT AUTHORIZED TO CANCEL JOB *jobname*

Explanation: The security label you are logged on with is not equal to or greater than the security label of the specified job.

System action: The system denies your request. The job is not canceled.

User response: Log on with a valid security label and reissue the CANCEL command.

Module: IKJEFF54

Audience: CANCEL user

IKJ56202I JOB *jobname(jobid)* NOT FOUND

Explanation: The specified job is not in the system.

Module: IKJEFF52, IKJEFF54

Program: CANCEL/STATUS

IKJ56205I STATUS INFORMATION FOLLOWS FOR JOBNAME ONLY

Explanation: Message IKJ56194I or IKJ56195I is issued before this message. The STATUS command then obtains the status of the jobname only from the job entry subsystem, and issues the appropriate status message(s).

Module: IKJEFF52

Program: STATUS

IKJ56208A *text_from_user-supplied_installation_exit*+ ENTER REPLY FOR INSTALLATION EXIT

Explanation: Your installation-supplied exit (IKJEFF53) has provided this prompting message.

Module: IKJEFF51

Program: CANCEL/STATUS

IKJ56208I JOB *jobname* REJECTED - JOBNAME MUST BE YOUR USERID PLUS AT LEAST ONE CHARACTER

Explanation: The IBM-supplied installation exit (IKJEFF53) produces this message if the jobname does not equal your user ID, plus at least one character for a CANCEL command.

Module: IKJEFF51

Program: CANCEL/STATUS

IKJ56211I **JOB *jobname(jobid)* EXECUTING, IN HOLD STATUS + optional second-level message from subsystem**

Explanation: The job is executing after being given control by the initiator. If the job is held on the queue, its output will be held after the job completes execution. The job entry subsystem may supply a second-level message to provide more details.

Module: IKJEFF52

Program: STATUS

IKJ56216I **NO JOBS FOUND + SYSTEM QUEUES WERE SEARCHED FOR JOB NAMES EQUAL TO YOUR USERID PLUS ONE CHARACTER**

Explanation: The STATUS command was specified with no operands, and there were no jobs in the system with a jobname of your user ID plus one character.

Module: IKJEFF52

Program: STATUS

IKJ56217I ***command_name* WITH no OPERANDS FAILED, USERID IS NOT AVAILABLE IN THE BACKGROUND + SPECIFY JOBNAME ON THE *command_name* COMMAND**

Explanation: No user ID was available when executing STATUS command in the background, but STATUS with no operands would cause a search for job names which start with a user ID.

Module: IKJEFF50

Program: STATUS

IKJ56218I ***command_name* COMMAND FAILED - UNABLE TO PROMPT USER FROM INSTALLATION EXIT + MISSING REPLY FOR 80 characters of message**

Explanation: No reply could be obtained for the message because the user is in noprompt mode, or the command is in a command procedure executed in noprompt mode.

Module: IKJEFF51

Program: CANCEL/STATUS

IKJ56219I **UNABLE TO DIAGNOSE INSTALLATION EXIT RETURN CODE *return_code* + CALL YOUR SYSTEM PROGRAMMER**

Explanation: An unexpected return code from an installation-supplied exit (IKJEFF53) was returned. The defined return codes are 0, 4, 8, 12, and 16.

Module: IKJEFF51

Program: CANCEL/STATUS

IKJ56220I ***type* NOT *operation*, TOO MANY DATA SETS + MAXIMUM NUMBER OF DATA SET ALLOCATIONS ALLOWED BY YOUR SESSION HAS BEEN REACHED, YOU SHOULD FREE UNUSED DATA SETS**

Explanation: The type, name, and operation inserts indicate the requested dynamic allocation function. An example is DATA SET name NOT ALLOCATED.

The dynamic allocation error code is 0238 or 043C. For a description of dynamic allocation return codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56221I *type* NOT operation, VOLUME NOT AVAILABLE +

Explanation: Requested volume not available.

VOLUME *volser* IS ALLOCATED TO ANOTHER JOB OR USER, TRY LATER

Explanation: The dynamic allocation error code is 0220.

VOLUME *volser* NECESSARY TO SATISFY YOUR REQUEST NOT ON SYSTEM, AND CANNOT BE MOUNTED

Explanation: The dynamic allocation error code is 0218.

This message indicates that the volume specified as input to dynamic allocation is not mounted on any of the devices associated with the specified or defaulted UNIT parameters. Some possible reasons for this error are:

- The dynamic allocation tried to use a VIO-eligible unit, but the data set name was not a temporary dsname (DSN=&&dsname).
- The dynamic allocation tried to put a data set with a non-temporary dsname (DSN=dsname) onto a real DASD volume but
 1. No volume serial number was supplied, and
 2. no volumes on the system were mounted with a USE attribute of STORAGE.

The volume serial number appears in the message only if the user supplied it on the ALLOCATE command.

VOLUME *volser* CURRENTLY MOUNTED ON AN INELIGIBLE DEVICE

Explanation: The dynamic allocation error code is 022C.

One possible reason for this error is that the dynamic allocation specified a valid volume serial number along with an invalid UNIT name.

For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56222I SPACE REQUEST REJECTED BY INSTALLATION EXIT, INSTALLATION EXIT REASON CODE IS *reason_code*

Explanation: The dynamic allocation return code is 47B0, and *return_code* is the error code (hexadecimal) returned by the installation exit. For a description of dynamic allocation error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56223I SPACE REQUEST DENIED BY INSTALLATION EXIT, INSTALLATION EXIT REASON CODE IS *reason_code*

Explanation: The dynamic allocation error code is 47B4 and *reason_code* is the error code (hexadecimal) returned by the installation exit. For a description of dynamic allocation return codes and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56224I INVALID SYSOUT CLASS

Explanation: The dynamic allocation error code is 032C. For a description of dynamic allocation return codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56225I *type* ALREADY IN USE, TRY LATER + DATA SET IS ALLOCATED TO ANOTHER JOB OR USER

Explanation: The dynamic allocation error code is 0210. For a description of dynamic allocation return codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56226I INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS

Explanation: The dynamic allocation error code is 0334. For a description of dynamic allocation return codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56227I MAXIMUM GENERATED DDNAMES LIMIT REACHED

Explanation: On a request to generate a ddname for a dynamic allocation, the system detected that the task was at its maximum allowable limit of 65,535 for system generated ddnames. The dynamic allocation error code is 04F4. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56228I DATA SET *dsname* NOT IN CATALOG or CATALOG CANNOT BE ACCESSED

Explanation: DISP=OLD was specified. The dynamic allocation error code is 1708, 5708, or 5710. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56229I *type_name* NOT *operation*, DADSM ERROR +

Explanation: The dynamic allocation error code is 4704, and the DADSM return code is 04.

DUPLICATE DATA SET NAME ON VOLUME *volser*

Explanation: The name of the data set is the same as an existing data set name.

VOLUME *volser* VTOC IS FULL

Explanation: The dynamic allocation error code is 4708, and the DADSM return code is 08.

RECORD LENGTH GREATER THAN *volser* TRACK CAPACITY

Explanation: The dynamic allocation error code is 4718, and the DADSM return code is 18.

type_name NOT *operation*, CATALOG ERROR +**DATA SET NAME CONFLICTS WITH EXISTING DATA SET NAME OR USER IS NOT AUTHORIZED TO PERFORM OPERATION.**

Explanation: DISP=NEW was specified. The dynamic allocation error code is 1708, 5708, or 5710. Refer to the explanation of MVS message IEF2871, return codes 2 and 3 in *z/OS MVS System Messages, Vol 8 (IEF-IGD)*.

AN INCORRECT PASSWORD MAY HAVE BEEN ENTERED FOR THE CATALOG

Explanation: A password-protected catalog could not be accessed because an incorrect password was entered. Messages IEC113I or IEC331I may also be issued. (See *z/OS MVS System Messages, Vol 8 (IEF-IGD)*.) For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

IKJ56230I • IKJ56231I

Module: CALLER

Program: DAIRFAIL

IKJ56230I *type_name* NOT operation, MEMBER OF CONCATENATION

Explanation: Dynamic allocation error code is 045C. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56231I *type_name* NOT operation, SYSTEM OR INSTALLATION ERROR UNKNOWN *routine* CODE - NOTIFY YOUR INSTALLATION MANAGER OF ERROR CODE *return_code*

Explanation: The *routine* insert is DYNAMIC ALLOCATION, CATALOG, DADSM, LOCATE, OBTAIN, or SCRATCH.

The OBTAIN error code is 6710 or 6714, or the DADSM error code is 4710 or 4730. See note 3.

When the 'routine' insert is LOCATE, the dynamic allocation error code is 17xx. xx is the reason code displayed in the message. The dynamic allocation error code indicates whether the error is from LOCATE. See notes 2 and 3.

The dynamic allocation error code is 77xx. xx is the scratch error code. See note 3.

The TSO/E routine IKJEFF18 cannot identify the error code. See notes 2 and 3.

UNKNOWN *routine* CODE - NOTIFY YOUR INSTALLATION MANAGER OF RETURN CODE *return_code*

Explanation: The *routine* insert is DAIR or DYNAMIC ALLOCATION.

The TSO/E routine IKJEFF18 cannot identify the return code. See notes 1 and 4.

OBTAIN or DADSM I/O ERROR *volser*

Explanation: The OBTAIN or DADSM error code is 670C or 470C. See note 3.

TEXT UNIT *number* CONTAINS INVALID PARAMETER

Explanation: The dynamic allocation error code is 035C. See note 2.

TEXT UNIT *number* CONTAINS INVALID KEY

Explanation: The dynamic allocation error code is 0360. See note 2.

REQUEST BLOCK FORMAT INVALID

Explanation: The dynamic allocation error code is 036C. See note 2.

TEXT UNIT *number* CONTAINS INVALID NUMBER

Explanation: The dynamic allocation error code is 0374. See note 2.

TEXT UNIT *number* CONTAINS DUPLICATE KEYS

Explanation: The dynamic allocation error code is 0378. See note 2.

TEXT UNIT *number* CONTAINS INVALID LENGTH

Explanation: The dynamic allocation error code is 037C. See note 2.

ESTAE ENVIRONMENT COULD NOT BE ESTABLISHED

Explanation: The dynamic allocation error code is 047C. See note 2.

LOCATE I/O ERROR

Explanation: The dynamic allocation error code is 1718. See note 2.

CATALOG SPACE EXHAUSTED ON CONTROL VOLUME *volser*

Explanation: The dynamic allocation error code is 5714. See note 2.

CATALOG I/O ERROR *volser*

Explanation: The dynamic allocation error code is 5718 or 571C. See note 2.

REQUEST BLOCK EXTENSION FORMAT INVALID

Explanation: The dynamic allocation error code is 03A8. See note 2.

REQUEST BLOCK EXTENSION FORMAT INVALID, NO CPPL SPECIFIED

Explanation: The dynamic allocation error code is 03AC. See note 2.

DYNAMIC ALLOCATION REASON CODE IS *error_code*

Explanation: The dynamic allocation error code is indicated in the message. See note 2.

Note:

1. DAIR return codes are in *z/OS TSO/E Programming Services*.
2. Dynamic allocation return, informational, error codes, and text unit key descriptions are in *z/OS MVS Programming: Authorized Assembler Services Guide*.
3. Catalog (ATLAS, CATALOG, LOCATE, and RDJFCB macros) and DADSM (OBTAIN, RENAME, and RENAME, and SCRATCH macros) are in *MVS Catalog Administration Guide*.
4. DADSM return codes that TSO/E cannot identify are in *DADSM Diagnosis Guide and Reference*.

Module: CALLER

Program: DAIRFAIL

IKJ56232I *type_name* NOT ON VOLUME AS INDICATED IN THE CATALOG OR VOL PARAMETER +
PLEASE DELETE CATALOG ENTRY (USE DELETE COMMAND WITH NOSCRATCH KEYWORD)
AND RECREATE DATA SET IF NECESSARY

Explanation: The dynamic allocation error code is 6708. The catalog information is incorrect for one of the following reasons:

- Only a catalog entry was created. This could have been done with a utility or through an incomplete creation of the data set.
- The DELETE command had incomplete execution.
- The data set was scratched by a cleanup routine but never uncataloged.
- The volume was restored to a level without the data set and the catalog is not on the same volume.

For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56233I *type* NOT *operation*, THE OVERRIDING DISPOSITION KEY IS NOT COMPATIBLE WITH THE
FILE TYPE OF THE DD.

Explanation: You either specified the overriding path disposition when the DD was for a standard data set, or you specified the overriding data set disposition when the DD was for a hierarchical file (a z/OS UNIX System Services data set). The dynamic allocation error code is 03B0. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56234I ATTR-LIST-NAME *name* NOT FOUND

Explanation: The dynamic allocation error code is 0454. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56235I MEMBER *member* SPECIFIED BUT *dsname* NOT A PARTITIONED DATA SET

Explanation: The dynamic allocation error code is 0330. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56236I FILE [*text*] INVALID, FILENAME RESTRICTED

Explanation: For the item *text* could appear the following:

- *text* = STEPLIB
- *text* = USERCAT
- *text* = JOBLIB
- *text* = STEPCAT
- *text* = JOBCAT

The dynamic allocation error code is 0364. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56238I DATA SET *dsname* NOT ALLOCATED, UNKNOWN ERROR DURING RECALL

Explanation: The dynamic allocation error code is 1704. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56239I *type* NOT *operation*, *name* CURRENTLY ALLOCATED AS A DUMMY + FREE FILE *name* AND RE-ENTER COMMAND

Explanation: The dynamic allocation error code is 410. The DAIR return code is 14. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56240I DATA SET *dsname* NOT ALLOCATED, DATA SET is MIGRATED AND WAS NOT RECALLED.

Explanation: The dynamic allocation error code is 0278. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56241I *type* NOT *operation* + DATA SET IS ALLOCATED TO ANOTHER JOB OR USER

Explanation: The dynamic allocation error code is 020C. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Explanation: The dynamic allocation error code is 0214. If *type* is SYSOUT DATA SET, the operation was probably attempted on an internal reader. If it was, consider increasing the number of internal readers. If the operation was not attempted on an internal reader, the job entry subsystem encountered a problem when allocating the SYSOUT data set (e.g. insufficient virtual storage). For more information, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Explanation: The dynamic allocation error code is 021C.

REQUEST REQUIRES MORE SMS-MANAGED VOLUMES THAN ARE ELIGIBLE

Explanation: The dynamic allocation error code is 026C.

REQUEST REQUIRES MORE NON-SMS MANAGED VOLUMES THAN ARE ELIGIBLE

Explanation: The dynamic allocation error code is 0270.

Module: CALLER

Audience: Either increase the number of JES internal readers or run fewer tasks that commit JES internal readers.

NO UNIT AVAILABLE

Audience: Either increase the number of JES internal readers or run fewer tasks that commit JES internal readers.

SPECIFIED UNIT IS UNDEFINED

Program: DAIRFAIL

IKJ56242I DATA SET *dsname* NOT ALLOCATED, RECALL CONVERTED TO BACKGROUND REQUEST BY SYSTEM

Explanation: The dynamic allocation error code is 1732. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56243I DATA SET *dsname* NOT ALLOCATED, RECALL CONVERTED TO BACKGROUND REQUEST BY USER

Explanation: The dynamic allocation error code is 1734. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56244I *type* NOT operation, DIRECTORY LARGER THAN SPACE AVAILABLE

Explanation: The dynamic allocation error code is 4738. The DADSM code is 38. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56245I *type* NAME NOT operation, NOT ENOUGH SPACE ON VOLUME + USE DELETE COMMAND TO DELETE UNUSED DATA SETS

Explanation: The dynamic allocation error code is 4714. The DADSM code is 14. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56246I *type_name* NOT ALLOCATED, FILE IN USE

Explanation: The dynamic allocation error code is 0410. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56247I *type NOT operation, IS NOT ALLOCATED*

Explanation: The dynamic allocation error codes are 0438 or 0440. This message is issued for all requests except concatenation.

Descriptions for:

- DAIR return codes are in *z/OS TSO/E Programming Services*.
- Dynamic allocation error codes are in *z/OS MVS Programming: Authorized Assembler Services Guide*.
- Catalog (ATLAS, CATALOG, LOCATE, and RDJFCB macros) and DADSM (OBTAIN, RENAME, and RENAME, and SCRATCH macros) are in *MVS Catalog Administration Guide*.

For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56248I *type NOT operation, REQUESTED AS NEW BUT CURRENTLY ALLOCATED*

Explanation: The dynamic allocation error code is 0448. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56249I *type NOT operation, CURRENTLY ALLOCATED WITH DISPOSITION OF DELETE*

Explanation: The dynamic allocation error code is 044C. For a description of the dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56250I **JOB** *jobname(jobid)* **SUBMITTED**

Explanation: The job has been entered for batch processing.

Module: IKJEFF05

Program: SUBMIT

IKJ56251I **USER NOT AUTHORIZED FOR** *command_name* **+ YOUR INSTALLATION MUST AUTHORIZE USE OF THIS COMMAND YOUR TSO/E ADMINISTRATOR MUST AUTHORIZE USE OF THIS COMMAND**

Explanation: The user is not authorized to use the foreground-initiated background (FIB) commands: CANCEL, OUTPUT, STATUS, and SUBMIT.

Module: IKJEFF01, IKJEFF56

Program: SUBMIT, CANCEL/STATUS

IKJ56252I **COMMAND SYSTEM ERROR -** *service_routine* **ERROR CODE** *error_code*

Explanation: For the SWA manager insert, the return code to IKJEFF04 was non-zero from a request for the JCT or ACT control block's address.

For the DEFAULT insert there was an unidentifiable return code to IKJEFF17 from IKJDFLT (CSECT IKJEFF17 is in assembly module IKJEFF16).

Module: IKJEFF04, IKJEFF16

Program: SUBMIT

IKJ56254I JOBNAME TRUNCATED NOT ENOUGH ROOM ON YOUR JOB CARD TO INSERT JOBNAME CHARACTER(S) *characters*

Explanation: The user supplied a job card in the input data set(s) for SUBMIT and either JOBCHAR keyword was specified on the SUBMIT command or the jobname was the user ID, so SUBMIT prompted the user for jobname character(s). When SUBMIT tried to insert the character(s), it could not find enough blanks either following the jobname or to the right of the JOB or operand field. SUBMIT inserts as many characters as possible and continues execution.

USERID PLUS JOBNAME CHARACTERS CANNOT EXCEED MAXIMUM JOBNAME LENGTH OF EIGHT

Explanation: The user supplied or had a JOB card generated that had a jobname matching the active TSO/E user ID or the user keyword value, if supplied on the SUBMIT command. SUBMIT obtained the jobname character(s) from a JOBCHAR keyword on the SUBMIT command or in its prompt for jobname character(s).

The jobname constructed from user ID plus the jobname character(s) would have exceeded the maximum jobname length of eight characters, so it was truncated. Otherwise, it would cause a JCL error when the job executed in the background.

Module: IKJEFF13

Program: SUBMIT

IKJ56256I JOB *jobname* AND ANY FOLLOWING JOBS NOT SUBMITTED

Explanation: An error in processing the jobname occurred, and that job along with any remaining jobs has not been submitted. Message IKJ56291I is also issued to describe the SUBMIT output data set error.

Module: IKJEFF05

Program: SUBMIT

IKJ56257I JOBNAME SUBMTJB GENERATED, USERID IS NOT AVAILABLE + SUPPLY A JOB CARD OR SPECIFY USER AND JOBCHAR KEYWORDS SO JOBNAME IS GENERATED FROM USERID PLUS THE CHARACTERS

Explanation: No user ID was available when executing SUBMIT command in the background, but a user ID is needed to generate a jobname with user ID plus jobname characters.

Module: IKJEFF08

Program: SUBMIT

IKJ56258I *command_name* FAILED, YOUR INSTALLATION DOES NOT SUPPORT THE HOLD KEYWORD + YOUR USER PROFILE DOES NOT CONTAIN A HOLD MSGCLASS VALUE. PLEASE INFORM YOUR TSO/E ADMINISTRATOR.

Explanation: You cannot use the HOLD keyword on the SUBMIT command unless your TSO/E Administrator has placed a default value for HELD MSGCLASS in your entry in the User Attributes Table.

Module: IKJEFF15

Program: SUBMIT

IKJ56259I *command_name* COMMAND ENDED DUE TO FIB SVC *macroname* ERROR CODE *error_code* + RETRY COMMAND, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER

Explanation: A macro was issued by FIB (foreground-initiated background) SVC 100 and the macro routine failed with the inserted error code.

If *macroname* is not used, the error code is from SVC 100 (or an unidentified return code from a module attached by SVC 100).

Return code 88 indicates invalid input to the SVC - either an unauthorized command code in the FIBID field of the input parameter list, or an invalid pointer to the protected step control block (PSCB) (JSCBPSCB pointer not equal to CPPLPSCB POINTER), or the high-order bit is not on in the pointer to the input parameter list (register 1->pointer->FIBPARMS).

IKJ56260I • IKJ56265I

Module: IKJEFD35

Program: SUBMIT, CANCEL/STATUS

IKJ56260I INSUFFICIENT STORAGE TO EXECUTE *command_name* COMMAND

Explanation: IKJEFF05 could not do a GETMAIN for enough buffer space for a submitted data set.

The virtual storage required to contain the job stream (a job stream submitted via the SUBMIT * command), could not be obtained. The command is terminated without submitting the job stream.

Module: IKJEFF04, IKJEFF05

Program: SUBMIT

IKJ56261I RECORD LENGTH OF DATA SET *dsname* NOT 80

Explanation: The data set submitted did not have logical records of 80 bytes. The block size need not be 80, but LRECL must be 80, because the records are treated as standard JCL cards. Data pointed to by DD cards may be in other types of data sets. The user must re-create the JCL data set with an LRECL of 80. The ALLOCATE command may be used, or EDIT a new CNTL-type data set.

Module: IKJEFF05

Program: SUBMIT

IKJ56262I MEMBER *member* NOT IN DATA SET *dsname*

Explanation: The partitioned data set member specified could not be found. A FIND macro was issued for the membername after the dsname was successfully allocated, and a code of 4 was returned.

Issue a LISTDS command for the dsname, with member option. This will tell what members are in the data set and the SUBMIT command can be reissued with the correct member name.

Module: IKJEFF05

Program: SUBMIT

IKJ56263I RECORD FORMAT FOR DATA SET *dsname* NOT FIXED

Explanation: The data set being submitted did not have a record format of fixed or fixed blocked. All JCL must be in a fixed or fixed blocked data set, but data pointed to by DD cards can be in other types of data sets. The user must re-create the data set with a RECFM=F or FB. The ALLOCATE command may be used, or EDIT a new data set with CNTL as the data set type.

Module: IKJEFF05

Program: SUBMIT

IKJ56264I *keyword* IGNORED BECAUSE JOB CARD WAS SUPPLIED + THIS KEYWORD IS ONLY USED WHEN A JOB CARD IS GENERATED

Explanation: *keyword* can be NOTIFY, NONNOTIFY, PASSWORD, or NOPASSWORD.

Module: IKJEFF05

Program: SUBMIT

IKJ56265I INPUT DATA SET *dsname* NOT USABLE + CANNOT OPEN DATA SET

Explanation: The OPEN failed for the indicated submitted data set.

FIND I/O ERROR

Explanation: The FIND for the indicated member of the submitted data set failed with a return code of 8.

I/O SYNAD ERROR *xxxx*

Explanation: The SYNAD exit was entered during I/O for the indicated submitted data set. *xxxx* is the SYNADAF I/O error information.

THE DATA SET IS EMPTY

Explanation: The data set has been allocated as new and is empty.

User response: Either enter data into the data set or reuse the command with another data set and resubmit it.

Module: IKJEFF05

Program: SUBMIT

IKJ56266I UNABLE TO DIAGNOSE EXIT RETURN CODE *return_code*

Explanation: The SUBMIT installation exit (IKJEFF10) returned a return code that was not 0, 4, 8, 12, or 16.

Module: IKJEFF09

Program: SUBMIT

IKJ56268I INVALID DATA SET NAME *dsname*, EXCEEDS 44 CHARACTERS

Explanation: After the appropriate qualifiers were added to the name of the data set to be submitted, the name exceeded the limit of 44 characters. This situation is detected in CSECT IKJEFF17 of assembly module IKJEFF16.

Module: IKJEFF16

Program: SUBMIT

IKJ56269I DATA SET *dsname* NOT FOUND

Explanation: The name of the data set to be submitted is not in the system catalog. The IKJDFLT (DEFAULT) service routine detected this error after the TSO/E identification qualifier was added to the unqualified input data set name. IKJEFF17 is the CSECT in assembly module IKJEFF16 which calls IKJDFLT and detects the error condition.

Module: IKJEFF16

Program: SUBMIT

IKJ56270I *keyword1* NOT INSERTED BECAUSE *keyword2* SPECIFIED + IF A JOB CARD WERE GENERATED WITH *keyword1* AND NO *keyword3* KEYWORD, AS REQUESTED, THE JOB WOULD FAIL

Explanation: This message is only produced if RACF is installed. Keyword inserts can be:

keyword1	keyword2	keyword3
USER	NOPASSWORD	PASSWORD
PASSWORD	NOUSER	USER

Module: IKJEFF08

Program: SUBMIT

IKJ56271I PASSWORD IGNORED, RACF IS NOT IN THE SYSTEM + CONTACT YOUR TSO/E ADMINISTRATOR

Explanation: The PASSWORD keyword on SUBMIT is ignored unless RACF is installed.

Module: IKJEFF08

Program: SUBMIT

IKJ56272I ORGANIZATION OF DATA SET *dsname* NOT SEQUENTIAL OR PARTITIONED

Explanation: The indicated data set that was submitted does not have the proper data set organization (DSORG=PS or DSORG=PO). All JCL must be in a sequential or partitioned data set, but data pointed to by DD cards may be in other types of data sets.

Module: IKJEFF05

IKJ56273I • IKJ56281I

Program: SUBMIT

IKJ56273I MEMBER *member* SPECIFIED BUT DATA SET *dsname* NOT A PARTITIONED DATA SET

Explanation: The submitted data set is sequential, so it may not have a member specified on the SUBMIT command.

Module: IKJEFF05

Program: SUBMIT

IKJ56274A ENTER INPUT JOB STREAM:

Explanation: A SUBMIT * command has been issued as a primary command. You must now enter the input job stream.

Module: IKJEFF04

Program: SUBMIT

IKJ56275A SHOULD INPUT JOB STREAM BE SUBMITTED? ENTER – YES OR NO: + RESPOND ‘YES’ TO HAVE THE INPUT JOB STREAM PROCESSED. RESPOND ‘NO’ TO INDICATE THAT THE INPUT JOB STREAM IS NOT TO BE PROCESSED.

Explanation: The PAUSE keyword was selected and the end of the job stream has been encountered.

To submit the job enter ‘yes’ to cancel the job, enter ‘no’.

Module: IKJEFF04

Program: SUBMIT

IKJ56276A INPUT NOT ACCEPTED, LENGTH EXCEEDS 80 CHARACTERS – REENTER LAST LINE:

Explanation: The job just entered in the job stream exceeds 80 characters. Reenter the lines with the correct length of 80 characters or less.

Module: IKJEFF04

Program: SUBMIT

IKJ56277I END AND/OR PAUSE OPERANDS WERE IGNORED + END AND PAUSE ARE ONLY VALID WHEN NOT IN EDIT MODE AND WHEN “*” IS SPECIFIED FOR THE DATA SET NAME LIST

Explanation: The END and PAUSE operands are ignored under two conditions. One is when a data set name has been specified and the other is in EDIT mode when “*” has been requested (SUBMIT *) for a data set name or the data set name list. In this instance, one of these conditions was encountered, and END or PAUSE was bypassed.

Module: IKJEFF04

Program: SUBMIT

IKJ56280A *exit_message* + ENTER REPLY FOR EXIT

Explanation: The inserted message text is supplied by the SUBMIT installation exit (IKJEFF10) and it prompts the user for a reply.

Module: IKJEFF09

Program: SUBMIT

IKJ56281I NO JOBS SUBMITTED BECAUSE UNABLE TO PROMPT + NOPROMPT SET IN TSO/E PROFILE, OR PROMPTING IS OFF FOR AN EXEC OR CLIST

Explanation: This message should be preceded by a message from the parse service routine (for PASSWORD keyword specified) or the LOGON command processor (for submitted LOGON command) telling what information was missing or invalid.

Module: IKJEFF08

Program: SUBMIT

IKJ56282I *command_name* **COMMAND FAILED - UNABLE TO PROMPT USER + MISSING REPLY FOR**
exit_message **FROM EXIT**

Explanation: SUBMIT was unable to issue prompting message IKJ56280A because the user is in noprompt mode, or the SUBMIT command was executed in a command procedure and the PROMPT keyword was not used. The PUTGET macro returned a code of 12. Exit message is 80 characters of the installation exit's insert for message IKJ56280A.

Module: IKJEFF09

Program: SUBMIT

IKJ56283I *exit_message*

Explanation: The inserted message text is supplied by the SUBMIT installation exit (IKJEFF10). The exit will use a return code to tell SUBMIT whether to terminate or continue execution after the message has been issued.

Module: IKJEFF09

Program: SUBMIT

IKJ56284I **UNABLE TO ISSUE MESSAGE BECAUSE** [*reason*] **WITH ID** *error_id* {*error_type*} **ERROR**
DESCRIPTION UNABLE TO ISSUE MESSAGE WITH PROMPT FOR REPLY + NOPROMPT SET
IN TSO/E PROFILE, OR PROMPTING IS OFF FOR AN EXEC OR CLIST (PUTGET R.C. IS
return_code)

Explanation: For the item *reason* could appear the following:

- *reason* = ZERO PARAMETER LIST PTR (REG 1 OR PTR TO MSGLST)
- *reason* = ZERO POINTER TO MESSAGE CSECT
- *reason* = ZERO CPPL POINTER WHEN PUTLINE/PUTGET
- *reason* = ID NOT FOUND IN MESSAGE CSECT
- *reason* = PUTLINE WAS UNSUCCESSFUL
- *reason* = INCOMPATIBLE PARAMETERS (NEED MTOLDPTR NON-ZERO WHEN MT200LDSW ON)
- *reason* = FIRST BUFFER NOT SUPPLIED
- *reason* = SECOND BUFFER NOT SUPPLIED
- *reason* = FIRST BUFFER LENGTH ZERO

For the item *error_type* could appear the following:

- *error_type* = TO TERMINAL
- *error_type* = AS PUTGET
- *error_type* = WITH A SECOND LEVEL

The TSO/E message issuing routine IKJEFF02 detected an error in its input parameter list (mapped by IKJEFFMT macro) or an error return code from a call of either the PUTGET or PUTLINE service routine. It issues the requested message first, if possible.

The second-level message appears only for a PUTGET failure.

If a PUTLINE operation has failed, the GNRLFIL service routine IKJEFF19 also diagnoses the PUTLINE error and issues a message.

If there is a PUTGET error, the message is issued as a PUTLINE operation. If there is a PUTLINE error, the message is issued as a write-to-programmer message.

Module: IKJEFF02

Program: SUBMIT

IKJ56285I *reason* **MESSAGE NOT EXTRACTED FOR ID** *message_number*

Explanation: The TSO/E message issuing routine IKJEFF02 detected an error in its input parameters (mapped by IKJEFFMT macro) defining the calling program's storage area to be used for returning the text of the message (extracting the message).

In the message text, reason is one of the following:

- **FIRST BUFFER NOT SUPPLIED** - The length of the first buffer was supplied, but no address for that buffer.
- **SECOND BUFFER NOT SUPPLIED** - The length of the second buffer was supplied, but no address for that buffer.
- **FIRST BUFFER LENGTH ZERO** - The first buffer length was zero, meaning the caller did not want the first-level message returned. However, the second buffer length was not zero, meaning the caller wanted the second-level message returned. This is an invalid request.

Module: IKJEFF02

Program: SUBMIT

IKJ56286I **SYSTEM OR INSTALLATION ERROR. REPORT THE FOLLOWING MESSAGE TO YOUR TSO/E ADMINISTRATOR.**

Explanation: This message precedes all error messages issued by the TSO/E message issuing routine IKJEFF02.

Module: IKJEFF02

Program: SUBMIT

IKJ56287I **JOB** *jobname* **NOT SUBMITTED - INVALID ENTRY CODE FOR** *modulename*

Explanation: Jobname is the last jobname being processed, and it must be resubmitted.

Modulename can be IKJEFF05 or IKJEFF15. IKJEFF05 will only accept a value of 2 or 3 in the HTCODE field of the SUBMIT history table. IKJEFF15 will accept 1 or 4.

Module: IKJEFF05, IKJEFF15

Program: SUBMIT

IKJ56288I *command_name* **FAILED - LOGON ACCOUNTING INFORMATION EXCEEDS 142 CHARACTERS**

Explanation: The user's accounting information is longer than 142 characters. IKJEFF04 references account fields in the account control table (ACT) created when the user logged on to TSO/E to re-create the accounting information in job card format.

SUBMIT modules IKJEFF08 and IKJEFF09 use the accounting information, and expect the above limit.

Module: IKJEFF04

Program: SUBMIT

IKJ56289I *command_name* **FAILED - LOGON ACCOUNTING INFORMATION WON'T FIT ON JOB STATEMENT**

Explanation: If SUBMIT must generate a JOB statement, it has room to insert 54 characters followed by a comma on the job card, and 67 characters on each of two continuation cards. Thus, the accounting information, re-created from the account control table (ACT) control block for the user, may be up to 190 characters in length (counting two commas used as breaking points for inserts). However, if there are too few commas between fields, it may be impossible to create two or three inserts of the correct length.

Module: IKJEFF04, IKJEFF08

Program: SUBMIT

IKJ56291I [command/program] FAILED DATA SET *type* HAD A VSAM *typemacro* ERROR *error_description* RETRY, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER (error field=X'*nnnn*' R15=X'*nnnn*')

Explanation: For the SUBMIT command this message indicates that the INTRDR data set, used to pass JCL to the job entry subsystem, had an error detected by the indicated VSAM I/O macro. This may be the result of a JCL error. The job entry subsystem, not VSAM, handles I/O to the SUBMIT command's internal reader, and uses only a subset of the VSAM error codes. The field will contain VSAM physical I/O error information if VSAM supplied it. In the message text:

command/program

The command or program executing when the error occurred.

type The name or description of the data set:

- *dsname*
- *ddname*

typemacro

The VSAM I/O macro that detected the error.

nnnn The error code.

rrrr The reason code in register 15.

Module: CALLER

Program: VSAMFAIL/GNRLFAIL

IKJ56292I [*text*] FOR IKJEFF19 GNRLFAIL/VSAMFAIL ROUTINE

Explanation: For the item *text* could appear the following:

- *text* = UNABLE TO ISSUE FAILURE MESSAGE TO TERMINAL
- *text* = UNABLE TO ISSUE FAILURE MESSAGE FOR ID *user_id*
- *text* = INCOMPLETE FAILURE MESSAGE ISSUED BECAUSE *error_description*

The input parameter list to IKJEFF19 contained one of the following errors:

- Register 1 did not point to the address of the GPFARMS parameter list for IKJEFF19.
- The GFCALLID field was outside the defined range (see IKJEFFGF mapping macro).
- The GFCBPTR field was zero when GFCALLID indicated a VSAM or SSREQ ID.
- The GFCPLP field was zero when GFWTPSW was off (default of PUTLINE).

This message also appears if the message issuing routine IKJEFF02 returned a non-zero return code from PUTLINE.

Module: IKJEFF19

Program: VSAMFAIL/GNRLFAIL

IKJ56293I *command/program* FAILED - [*text*] HAD *error* RETRY, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER (REGISTER 15=*rrrr*)

Explanation: For the item *text* could appear the following:

- *text* = PARSE SERVICE ROUTINE
- *text* = PUTLINE SERVICE ROUTINE
- *text* = *ssname* SUBSYSTEM
- *text* = INTERFACE *description*

This message describes the error detected by the parse service routine if the return code was not 0, 4, or 20. It is also issued for errors from the PUTLINE service routine or the subsystem interface request routine (IEFSSREQ). In the message text:

command/program

The command or program executing when the error occurred.

ssname The name of the subsystem containing the error.

description

The description of the interface containing the error.

rrrr The reason code in register 15.

Following is a list of return codes (in decimal) and their meaning detected by IEFSSREQ:

IKJ56294I • IKJ56310I

RC	Cause
0	Successful completion; request went to a subsystem
4	Subsystem does not support this function
8	Subsystem exists, but is not up
12	Subsystem does not exist
16	Function not completed; error
20	Logical error (bad SSOB format or length, staging area limit size exceeded)

Module: CALLER**Program:** VSAMFAIL/GNRLFAIL**IKJ56294I** *command/program* ENDED DUE TO ERROR, [*text*] ABEND CODE *abend_code***Explanation:** For the item *text* could appear the following:

- *text* = SYSTEM
- *text* = USER

The message indicates the abend detected by the calling routine (STAE, STAI, ESTAE, ESTAI). This message should only be issued if the terminal monitor program's STAI routine is being bypassed. In the message text *command/program* is the command or program executing when the abend occurred.

For an explanation of the abend code listed in the message, see *z/OS MVS System Codes*.

Module: CALLER**Program:** VSAMFAIL/GNRLFAIL**IKJ56295I** THE OUTPUT LINE DESCRIPTOR PASSED TO IKJEFF02 IS ABOVE 16 MEGABYTES. IT IS IGNORED.

Explanation: An output line descriptor address (OLD) passed to IKJEFF02 via the input parameter list is above 16 MB. You must place the output line descriptor in storage below 16 MB or remove the OLD request from the routine that invoked IKJEFF02.

Module: IKJEFF02**Program:** IKJEFF02**IKJ56309I** UNABLE TO OPEN DATA SET *dsname*

Explanation: IKJCT469 was unable to OPEN the PRINT data set, or IKJCT463 was unable to OPEN the SAVE data set.

Module: IKJCT469, IKJCT463**Program:** OUTPUT**IKJ56310I** INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS WHEN QUALIFIED

Explanation: An unqualified data set name was entered. It will exceed maximum length when 'OUTLIST' is appended. IKJCT473 checks the SAVE data set and the PRINT data set after parse has prefixed the user ID.

Module: IKJCT473**Program:** OUTPUT

IKJ56311I NOT AUTHORIZED TO ISSUE OUTPUT ON JOB *jobname*

Explanation: You do not have the proper authority to issue the OUTPUT command on the specified job. The subsystem return code was zero, but the SSOBRETN field of the SSOB was 32.

This message is issued only in a JES3 environment and indicates that a JES3 installation exit has denied access to the job.

Module: IKJCT462

Program: OUTPUT

IKJ56312I NOT ENOUGH VIRTUAL STORAGE TO EXECUTE *command/subcommand*

Explanation: This message is issued when:

- IKJCT463 detects a return code=16 from parse (no space for PDL).
- IKJCT463 detects a return code=8 from command scan.
- IKJCT467 detects a return code=28 from PUTGET.
- IKJCT469 detects a return code=16 from parse (no space for PDL).

Module: IKJCT463, IKJCT467, IKJCT469

Program: OUTPUT

IKJ56313I COMMAND SYSTEM ERROR *macro/service* **routine** ERROR CODE *error_code*

Explanation: This message is issued when:

- IKJCT463 detects either a return code=4 from command scan (invalid parameters were passed), or any non-zero return code with no meaning.
- IKJCT463 detects either a parse return code=12 (invalid parameters passed) or non-zero return code other than 4, 8, or 16, which had no meaning.
- IKJCT463 detects a non-zero return code from the ATTACH macro.
- IKJCT467 detects a non-zero return code from PUTGET.
- IKJCT469 detects a non-zero return code from the ESTAE macro.
- IKJCT469 detects a return code=12 from parse. Invalid parameters were passed to parse or IKJCT469 detected an unidentifiable return code.
- IKJCT469 detects a non-zero return code from the STAX macro.
- IKJCT472 detects a return code other than 0 or 4 from PUTGET. The user's subcommand could not be retrieved after an attention.
- IKJCT472 detects a non-zero return code from the STATUS macro.

Module: IKJCT463, IKJCT467, IKJCT469, IKJCT472

Program: OUTPUT

IKJ56318I [*text*] ENDED DUE TO ERROR, SYSTEM ABEND CODE *abend_code*

Explanation: For the item *text* could appear the following:

- *text* = *command*
- *text* = HELP

Either IKJCT460 detected an abend code other than 913 or x37 in the ESTAE exit work area, or IKJCT463's STAI exit got control when the HELP command processor abended.

command ENDED DUE TO ERROR, SYSTEM ABEND CODE *abend_code*

NOT ENOUGH DIRECT ACCESS SPACE TO CONTAIN ALL RECORDS IN DATA SET *dsname*

INVALID PASSWORD SPECIFIED FOR DATA SET *dsname*

Explanation: IKJCT460 detected an abend code of B37, D37, or E37. Space failure occurred while writing to a PRINT

IKJ56319I • IKJ56328A

or SAVE data set, or IKJCT460 detected an abend code of 913.

Module: IKJCT460, IKJCT463

Program: OUTPUT

IKJ56319I INTERRUPTED OUTPUT RESUMED

Explanation: IKJCT471 detected INTRPMSG switch set by IKJCT462 if the sysout data set was previously checkpointed and HERE specified on the command or if HERE was specified on the CONTINUE subcommand entered after the attention interrupt.

Module: IKJCT471

Program: OUTPUT

IKJ56320I NO HELP OUTPUT FOR JOB *jobname(jobid)* in CLASS *class_name*

Explanation: The "Printing" function was requested and subsystem return code was 0 but SSOBRETN field contained 4 or 8 (if the job was purged after the work was done). Requested class has no output for the specified job.

Module: IKJCT462

Program: OUTPUT

IKJ56321I COMMAND NOT AUTHORIZED FOR *user_id* + YOUR INSTALLATION MUST AUTHORIZE USE OF THIS COMMAND

Explanation: SVC 100 return code=80. The terminal user does not have the 'JCL' privilege specified in his UADS.

Module: IKJCT466

Program: OUTPUT

IKJ56323I INVALID SUBCOMMAND *subcommand_name*

Explanation: Either the command scan return code=0 and CSOA flag bits=08 (the subcommand is syntactically invalid), or the subcommand is syntactically valid but is not one of the allowable subcommands (CONTINUE, SAVE, HELP, END) or an acceptable abbreviation.

Module: IKJCT463

Program: OUTPUT

IKJ56325I *dsname* SAVED

Explanation: The end of data on the sysout data set was found during subcommand mode. The sysout data set was completely copied into the SAVE data set.

Module: IKJCT470

Program: OUTPUT

IKJ56328A *message_text_from_installation_exit* + ENTER REPLY FOR INSTALLATION EXIT

Explanation: The installation exit (IKJEFF53) return code=4. The exit has supplied the first-level message text to be printed at the terminal. The user is expected to reply to the message.

Module: IKJCT469

Program: OUTPUT

IKJ56328I *message_text_from_installation_exit*

Explanation: The installation exit (IKJEFF53) return code=8. The user entered a job name which did not meet the requirements of the exit. If the IBM-supplied exit is used, the jobname must start with the user ID. Also, the IBM-supplied message text is: JOB 'jobname' REJECTED - JOBNAME MUST BE YOUR USERID OR MUST START WITH YOUR USERID.

Module: IKJCT469

Program: OUTPUT

IKJ56330I **ORGANIZATION OF DATA SET** *dsname* **NOT ACCEPTABLE + ORGANIZATION MUST BE PARTITIONED OR SEQUENTIAL**

Explanation: The PRINT or SAVE data set specified has an unsupported data set organization.

Module: IKJCT473

Program: OUTPUT

IKJ56332I **UNABLE TO DIAGNOSE INSTALLATION EXIT RETURN CODE** *return_code*

Explanation: The installation exit (IKJEFF53) returned a non-zero return code other than 4, 8, 12, or 16, and OUTPUT attaches no meaning to it. The IBM-supplied exit only returns 0, 8, and 12.

Module: IKJCT469

Program: OUTPUT

IKJ56333I **MISSING REPLY FOR** *message* **FROM INSTALLATION EXIT**

Explanation: The user's terminal was in noprompt mode. Therefore when IKJCT469 got a return code of 4 from the installation exit (IKJEFF53), and went to IKJCT467 to issue the exit message and get a reply, PUTGET (prompt) returned a code of 12. IKJCT467 detects this return code and issues this message.

Module: IKJCT467

Program: OUTPUT

IKJ56339I **NO HELD OUTPUT FOR JOB** *jobname*

Explanation: The 'Printing', 'Deleting', or 'Routing' function was requested and subsystem return code was 0 but SSOBRETN field contained 4. No class was given so all held classes were searched and either no held output was found for the specified job, or no held output that you are authorized to access was found for the specified job.

Module: IKJCT462

Program: OUTPUT

IKJ56340I **JOB** *jobname* **NOT FOUND**

Explanation: The subsystem return code was zero, but the SSOBRETN field was 8. The job was not found in the system.

Module: IKJCT462

Program: OUTPUT

IKJ56341I *command* **COMMAND INVALID DUE TO CONFLICTING KEYWORDS**

Explanation: Mutually exclusive keywords were given on the command, (for example, PRINT with NEWCLASS, or NEWCLASS with DELETE).

Module: IKJCT469

Program: OUTPUT

IKJ56342I *command* ENDED DUE TO FIB SVC [*text*] ERROR CODE *error_code* REENTER COMMAND, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER

Explanation: For the item *text* could appear the following:

- *text* = ATTACH
- *text* = STAX
- *text* = STATUS

The ATTACH, STAX, or STATUS macro failed while being used by SVC100 (return code=84). If none of the above, the SVC 100 return code is 88 (register 0 contained an invalid indicator), or SVC100 return code was not recognizable (other than 0, 12, 80, 84, or 88). In the message text *command* is the command executing when the abend occurred. *error_code* is the error code identifier.

Module: IKJCT466

Program: OUTPUT

IKJ56343I NO HELD OUTPUT FOR JOB *jobname* IN CLASS(ES) REQUESTED

Explanation: The 'Deleting' or 'Routing' function was requested, and subsystem return code was 0, but the SSOBRETN field contained a 4. The requested classes have either no held output for the specified job, or no held output that you are authorized to access for the specified job. no output for the specified job.

Module: IKJCT462

Program: OUTPUT

IKJ56344I DATA SET *dsname* SKIPPED, INTERRUPTED DURING PREVIOUS OUTPUT COMMAND + IF 'KEEP' WAS SPECIFIED, RETRIEVE THE DATA SET BY REENTERING THE COMMAND WITH 'BEGIN'

Explanation: The user attempted to access a sysout data set which had been checkpointed during a previous OUTPUT session (SSSORBA field is non-zero). Because the user specified NEXT on his command, the checkpointed data set is not printed.

Module: IKJCT462

Program: OUTPUT

IKJ56345I *subsystem* SUBSYSTEM INTERFACE ERROR, RETURN CODE *return_code* + REENTER COMMAND, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER

Explanation: A subsystem return code is either 4 (the subsystem does not support the function) or 20 (logical error).

Module: IKJCT462

Program: OUTPUT

IKJ56346I *subsystem* SUBSYSTEM ERROR, RETURN CODE *return_code* + REENTER COMMAND, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER

Explanation: IKJCT462 detected a subsystem return code of 12 (subsystem does not exist) or 16 (the function was not completed); or, any non-zero return code when IKJCT462 or IKJCT464 indicated to the subsystem that processing is complete.

Module: IKJCT462, IKJCT464

Program: OUTPUT

IKJ56347I COMMAND FAILED *subsystem* SUBSYSTEM NOT ACTIVE + RETRY WHEN SUBSYSTEM IS ACTIVE

Explanation: A subsystem return code=8 was detected. The subsystem was not active.

Module: IKJCT462

Program: OUTPUT

IKJ56348I **DUPLICATE JOB NAMES *jobname*, CORRECT JOBNAME (*jobid*) COMBINATION REQUIRED + STATUS COMMAND MAY BE USED TO OBTAIN A UNIQUE JOBID**

Explanation: A code of 20 is in the SSOBRETN field from the subsystem. Duplicate jobnames exist, therefore a unique jobid is necessary.

Module: IKJCT462

Program: OUTPUT

IKJ56349I **JOB *jobname(jobid)* COMBINATION INVALID + STATUS COMMAND MAY BE USED TO OBTAIN A UNIQUE JOBID**

Explanation: A code of 24 is in the SSOBRETN field from the subsystem. The jobid was incorrect for that jobname.

Module: IKJCT462

Program: OUTPUT

IKJ56350I **UNABLE TO PROCESS JOB *jobname* AT THIS TIME, TRY LATER**

Explanation: The subsystem return code is 0, but the SSOBRETN field is 16. The job is within the subsystem but is not yet available to the terminal user.

Module: IKJCT462

Program: OUTPUT

IKJ56351I **INVALID REMOTE STATION ID *destination id***

Explanation: The subsystem return code was 0, but the SSOBRETN field contained a 28. The subsystem did not find the station id in its table of valid ids.

Module: IKJCT462

Program: OUTPUT

IKJ56353I **SSOBRETN FIELD FROM SUBSYSTEM IS *nnn* UNABLE TO DIAGNOSE + REENTER COMMAND, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER**

Explanation: A subsystem return code is 0, but the SSOBRETN field contained a code other than 0, 4, 8, 12, 16, 20, 24, or 28.

Module: IKJCT462

Program: OUTPUT

IKJ56357I **DATA SET *dsname* PARTITIONED, NO MEMBER NAME GIVEN-'TEMPNAME' USED**

Explanation: The PRINT or SAVE data set which the user specified was partitioned, but no member name was given.

TEMPNAME is the default.

Module: IKJCT473

Program: OUTPUT

IKJ56358I **INVALID SEARCH ARGUMENTS, SSOBRETN CODE *nnn* + REENTER COMMAND, THEN IF ERROR CALL YOUR SYSTEM PROGRAMMER**

Explanation: The subsystem return code is 0, and the SSOBRETN field is 12. The SSSO control block contained invalid data.

Module: IKJCT462

IKJ56400A • IKJ56407I

Program: OUTPUT

IKJ56400A ENTER LOGON OR LOGOFF

Explanation: The LOGON parameters are invalid and the user is in no prompt mode.

Module: IKJEFLEA

Program: LOGON

IKJ56401I INVALID COMMAND SYNTAX

Explanation: A command was entered during LOGON and the command name was invalid.

Module: IKJEFLEA

Program: LOGON

IKJ56402I RECONNECT SPECIFIED – OTHER OPERANDS IGNORED

Explanation: LOGON RECONNECT was specified along with other operands.

Module: IKJEFLE

Program: LOGON

IKJ56403I PERFORMANCE GROUPS NOT AUTHORIZED FOR USE BY USERID *user_id*

Explanation: Performance groups were included on the LOGON command but the user is not authorized in UADS to use performance groups.

Module: IKJEFLE

Program: LOGON

IKJ56404I PERFORMANCE GROUP *group* NOT AUTHORIZED FOR USERID *user_id*

Explanation: Performance group *group* was included on the LOGON command but the user is not authorized in UADS to use performance group *nnn*.

Module: IKJEFLE

Program: LOGON

IKJ56405I PERFORMANCE GROUP *group* NOT DEFINED TO SYSTEM

Explanation: The system does not recognize performance group *group*.

Module: IKJEFLE

Program: LOGON

IKJ56406I ABEND WHILE PROCESSING BROADCAST MESSAGES, LOGON PROCEEDING.

Explanation: LISTBC was used during LOGON and an ABEND occurred during LISTBC.

Module: IKJEES71

IKJ56407I PASSWORD INVALID FOR USERID

Explanation: LOGON RECONNECT was entered but the password entered did not match previous password.

Module: IKJEFLE

Program: LOGON

IKJ56408I PASSWORD REQUIRED FOR LOGON RECONNECT

Explanation: LOGON RECONNECT was entered but no password was given. The previous session's password must be given.

Module: IKJEFLE

Program: LOGON

IKJ56409I TSOLOGON RECONNECT REJECTED – USERID *user_id* NOT FOUND

Explanation: LOGON RECONNECT entered, but the user ID entered was not found by TIOC.

Module: IKJEFLE

Program: LOGON

IKJ56410I *command* COMMAND NOT ACCEPTED DURING LOGON

Explanation: A command other than LOGON/LOGOFF was entered during LOGON processing.

Module: IKJEFLEA

Program: LOGON

IKJ56411I TSO LOGON RECONNECT REJECTED – USERID *user_id* IN USE

Explanation: LOGON RECONNECT was entered, but *user_id* was found by TIOC to be in use and LOGONHERE support was not active. Contact your system programmer or see *z/OS TSO/E Customization* for more information about activating LOGONHERE support.

Module: IKJEFLEA

Program: LOGON

IKJ56412I DEST *dest* NOT DEFINED TO SUBSYSTEM, DEFAULT DEST TO BE USED

Explanation: The UADS value for DEST is not defined to subsystem.

Module: IKJEFLE

Program: LOGON

IKJ56413I LOGON REJECTED BY RACF INSTALLATION EXIT

Explanation: The LOGON was rejected by the RACF installation exit. This message is followed by message IKJ56418I. You should contact your installation manager to determine why the LOGON was rejected.

Module: IKJEFLE

Program: LOGON

IKJ56414I NEW PASSWORD IS INVALID FOR RACF

Explanation: The new password or passphrase is invalid for RACF. One or more of the reasons listed below can be possible reasons that a password or passphrase is considered invalid:

- The new password or passphrase is not syntactically valid or violates one of the RACF implemented rules. For example, it might be too short, might have too many repeated characters, or might not have a required mix of character types. If this is a password, it might contain special characters that are not allowed by RACF.
- A password or passphrase change is disallowed at this time because the minimum password-change interval (MINCHANGE interval) has not passed.
- The password is still in the password history file of recently used passwords, as maintained (optionally) by RACF.
- A RACF password exit has rejected the password or passphrase.

Module: IKJEFLE

IKJ56415I • IKJ56420I

Program: LOGON

IKJ56415I CURRENT PASSWORD HAS EXPIRED - PLEASE ENTER NEW PASSWORD

Explanation: The current password has expired and a new password is required.

Module: IKJEFLE

Program: LOGON

IKJ56416I RACF RACINIT ERROR CODE *error_code*, [*text*] TERMINATED RACF OIDCARD ERROR CODE *error_code*, LOGON TERMINATED

Explanation: For the item *text* could appear the following:

- *text* = LOGON
- *text* = LOGOFF

The LOGON or LOGOFF was terminated with RACF error code *error_code*. This message is followed by message IKJ56418I. You should contact your installation manager to determine why RACF issued the error code.

Module: IKJEFLE

Program: LOGON

IKJ56417I GROUP *group_id* NOT AUTHORIZED

Explanation: The specified *group_id* was not authorized for use by this user.

Module: IKJEFLE

Program: LOGON

IKJ56418I CONTACT YOUR TSO ADMINISTRATOR

Explanation: This message is issued when an error occurs that may require the installation manager's intervention to correct. The message issued before this one describes the error situation.

Module: IKJEFLE

Program: LOGON

IKJ56419I [*text*] IGNORED FOR NON-RACF USER

Explanation: For the item *text* could appear the following:

- *text* = NEW PASSWORD
- *text* = GROUP

Either the new password or the GROUP keyword was ignored for a user not defined to RACF. This message is followed by message IKJ56418I. You should contact your installation manager to be defined to RACF.

Module: IKJEFLE

Program: LOGON

IKJ56420I USERID *user_id* NOT AUTHORIZED TO USE TSO

Explanation: The user ID entered on the LOGON command was not found in UADS or not authorized to use TSO.

Module: IKJEFLE

Program: LOGON

IKJ56421I **Userid or password is invalid.**

Explanation: The password entered is not authorized for user ID being logged on.

PASSWORD NOT AUTHORIZED FOR USERID. NEW PASSWORD IGNORED.

Explanation: The user has entered an invalid password for this user ID and a new password. The system recognized that the original password is invalid and ignores any attempt to change the password.

User response: Enter a valid password for this user ID in the password field. If you want to change the current password, or need to enter a new password because the original password is expired, enter a new password in the new password field. Then press Enter.

Module: IKJEFLE

Program: LOGON

IKJ56422I **ACCOUNT NUMBER *account_number* NOT AUTHORIZED**

Explanation: The account number entered on the LOGON command is not valid for user ID and password.

Module: IKJEFLE

Program: LOGON

IKJ56423I **REGION SIZE *size* EXCEEDS LIMIT SIZE *limit***

Explanation: The region size specified on the LOGON command exceeds the size specified in the UADS for that user ID and password.

Module: IKJEFLE

Program: LOGON

IKJ56424I **PROCEDURE NAME *name* NOT AUTHORIZED**

Explanation: The procedure name specified on the LOGON command is not defined for this user ID, password, and account number.

User response: If the user is defined to RACF, check that the user has a valid TSO/E segment. Also, make sure the procedure resides in a data set that is part of the procedure library concatenation for TSO/E.

Module: IKJEFLE

Program: LOGON

IKJ56425I **LOGON rejected, UserID *user_id* already logged on to the system *system name*.**

Explanation: The user ID specified on the LOGON command is currently in use. To proceed, either press the ENTER key, or specify the LOGON or LOGOFF command.

LOGON REJECTED, RACF TEMPORARILY REVOKING USER ACCESS

Explanation: The LOGON was rejected because RACF was temporarily revoking user access. This message is followed by message IKJ56418I. Contact your installation manager to determine why access was revoked.

Module: IKJEFLE, IKJEFLI

Program: LOGON

IKJ56426I **[*text*] IGNORED, RACF IS NOT IN THE SYSTEM**

Explanation: For the item *text* could appear the following:

- *text* = NEW PASSWORD
- *text* = GROUP

The new password or GROUP keyword was ignored because RACF is not in the system. This message is followed by message IKJ56418I. You should contact your installation manager.

IKJ56427I • IKJ56433I

Module: IKJEFLE

Program: LOGON

IKJ56427I ATTENTION IGNORED , SYSTEM ERROR, LOGON RESUMED GETLINE ERROR PUTLINE ERROR

Explanation: ATTENTION is being ignored. A non-zero return code from GETLINE or PUTLINE was received.

Module: IKJEFLG

Program: LOGON

IKJ56428I LOGON REJECTED, TOO MANY ATTEMPTS

Explanation: The number of times a user has been prompted for a valid LOGON command exceeds the maximum.

Module: IKJEFLEA

Program: LOGON

IKJ56429A REENTER –

Explanation: After an unauthorized parameter has been entered, reenter correct parameter.

Module: IKJEFLE

Program: LOGON

IKJ56430I TSO LOGON rejected - maximum number of users reached.

Explanation: While attempting to logon, the maximum number of users was reached. You might be attempting to reconnect to a LOGON session that no longer exists. Attempt to logon again later, or contact your system programmer for assistance.

Module: IKJEFLE

Program: LOGON

IKJ56431I LOGON TERMINATED. NOT AUTHORIZED TO THIS TERMINAL.

Explanation: The specified user or group is not authorized to the terminal.

Module: IKJEFLE

Program: LOGON

IKJ56432I TSOLOGON RECONNECT REJECTED – NOT AUTHORIZED TO THIS TERMINAL

Explanation: RECONNECT keyword was specified but the user or previous group is not authorized to the terminal.

Module: IKJEFLE

Program: LOGON

IKJ56433I OPERATOR ID CARD IS NOT AUTHORIZED

Explanation: The operator identification card inserted into the card reader is not valid for this user. Message IKJ56437A follows this message.

Module: IKJEFLE

Program: LOGON

IKJ56434I OPERATOR ID CARD IS REQUIRED

Explanation: OIDCARD keyword was not specified but an operator identification card is required for this user. Message IKJ56437A follows this message.

Module: IKJEFLE

Program: LOGON

IKJ56435I NOT A VALID OPERATOR ID CARD

Explanation: A non-recognizable operator identification card was inserted into the card reader by the user. Message IKJ56437A follows this message.

Module: IKJEFLE

Program: LOGON

IKJ56436I LOGON TERMINATED. OPERATOR ID CARD NOT SUPPORTED FOR THIS TERMINAL TYPE

Explanation: An operator identification card is required for this user, but is not supported for this terminal type.

Module: IKJEFLE

Program: LOGON

IKJ56437A [text] OPERATOR ID CARD –

Explanation: For the item *text* could appear the following:

- *text* = ENTER
- *text* = REENTER

This message is issued following messages IKJ56433I, IKJ56434I, and IKJ56435I. Insert the operator identification card into the card reader. If you are not defined to RACF, enter a null line.

Module: IKJEFLE

Program: LOGON

IKJ56438I USE OF GROUP HAS BEEN REVOKED

Explanation: A user has been revoked from a group, as indicated by RACINIT return code 36. Message IKJ56439A follows this message.

Module: IKJEFLE

Program: LOGON

IKJ56439A REENTER NEW GROUP NAME

Explanation: This message immediately follows message IKJ56438I. Enter the requested data.

Module: IKJEFLE

Program: LOGON

IKJ56440I TSOLOGON RECONNECT REJECTED – PASSWORD INVALID FOR RACF

Explanation: The previous session's password is not the same as the password in the RACF PROFILE.

Module: IKJEFLE

Program: LOGON

IKJ56441I • IKJ56447A

IKJ56441I TSOLOGON RECONNECT REJECTED – USER NOT DEFINED TO GROUP

Explanation: The user is no longer authorized to access the group specified in the previous session.

Module: IKJEFLE

Program: LOGON

IKJ56442I TSOLOGON RECONNECT REJECTED BY RACF INSTALLATION EXIT

Explanation: The installation exit returned a non-zero return code for RACINIT.

Module: IKJEFLE

Program: LOGON

IKJ56443I TSOLOGON RECONNECT REJECTED – USER ACCESS REVOKED BY RACF

Explanation: The user's access to the system has been revoked before the attempt to reconnect.

Module: IKJEFLE

Program: LOGON

IKJ56444I TSOLOGON RECONNECT REJECTED – USE OF GROUP HAS BEEN REVOKED

Explanation: The user's access to the group has been revoked before the attempt to reconnect.

Module: IKJEFLE

Program: LOGON

IKJ56445I RE-LOGON ATTEMPT FAILED BECAUSE A CROSS MEMORY ENVIRONMENT WAS ESTABLISHED FOR THIS ADDRESS SPACE

Explanation: Issue the LOGOFF command when the current session is completed. This message is the second-level message for message IKJ56446I; that is, you receive it immediately after you receive message IKJ56446I.

Module: IKJEFL00

Program: LOGON/LOGOFF

IKJ56446I LOGOFF MUST BE ISSUED BEFORE ISSUING LOGON WITH CURRENT USERID +

Explanation: The user attempted to issue the logon command from an active TSO/E session after having established a cross memory environment. The initiator will not start a new job step in an address space that has an existing cross memory environment. The user must first issue the LOGOFF command before re-logging on.

Issue the LOGOFF command when the current session is complete.

Module: IKJEFL00

Program: LOGON/LOGOFF

IKJ56447A Reenter the new password in the (NEW) PASSWORD field for verification

Explanation: You entered a new password in either the PASSWORD or the NEW PASSWORD field, depending on the logon panel in use. LOGON prompts you to enter the new password again for verification.

System action: If you enter the same password as the first time you entered the new password, the password is changed provided that it meets the password criteria. If the validation fails, you receive another message indicating that the password validation failed.

User response: Enter the same new password that you entered previously.

Module: IKJEFLNL

Audience: TSO/E user

IKJ56448I The password entered does not match the password previously entered

Explanation: You have reentered your new password and it does not match the previously entered new password.

System action: LOGON proceeds as if you entered an invalid password (invalid characters, for example) and prompts you to enter the data again.

User response: Press ENTER (without entering a password) and proceed without changing your password, or enter a new password (you will be prompted to enter the password again for validation).

Module: IKJEFLNL

Audience: TSO/E user

IKJ56449A Enter the requested information in the indicated field

Explanation: The user is being prompted to enter data in an installation-defined field on the logon panel. This message is displayed on the logon panel when the installation exits (IKJEFLN1 and IKJEFLN2) do not supply a message and request that a field be prompted on the logon panel.

System action: LOGON displays the panel with the above message area.

User response: Enter the requested data in the requested installation-defined field.

Module: IKJEFLNL

Audience: TSO/E user

IKJ56450I LOGON PROCEEDING

Explanation: This message is issued because of the LOGON timer expiration.

Module: IKJEFLH

Program: LOGON

IKJ56451I LOGON [text] INSTALLATION EXIT ERROR or ABEND xxxx

Explanation: For the item *text* could appear the following:

- *text* = TERMINATED
- *text* = ATTEMPTING RETRY

Error detected in the installation exit routine. The error codes are in *z/OS MVS System Messages, Vol 9 (IGF-IWM)* following message IKJ603I. The ABEND codes are in *z/OS MVS System Codes*.

Module: IKJEFLI, IKJEFLGB

Program: LOGON

IKJ56452I TSOLOGON TERMINATED, SYSTEM ERROR SYSTEM ERROR, LOGON [text]

Explanation: For the item *text* could appear the following:

- *text* = TERMINATED
- *text* = ATTEMPTING RETRY

An error occurred while scheduling the user's session. Possible causes are SYSLBC or SYSUADS is missing from the master scheduler's TIOT, LOGON cannot open the UADS, an I/O error was encountered while accessing UADS, or a subsystem name was used for the LOGON procedure name.

This message can occur also during LOGOFF processing if the error occurs in the LOGON/LOGOFF verification routine.

System programmer response: If the error was due to the user using a subsystem name as a LOGON procedure, remove that procedure name from the user's definition. For more information on setting up LOGON processing, see *z/OS TSO/E Customization*.

Module: IKJEFLI, IKJEFLGB

IKJ56453I •

Program: LOGON

IKJ56453I SESSION CANCELLED

Explanation: The session was canceled by the operator, system, or LOGON.

Module: IKJEFLC

Program: LOGON

IKJ56454I LOGON TERMINATED *programname* ERROR *xxxx*

Explanation: An error occurred in the named program.

When the program is IKTLOGR and the return code is 12, it means either the USERMAX limit in the TSOKEYxx member has been exceeded or the CLSDST PASS to the old address space failed.

When the program is IKTLOGR and the return code is 16, it means reconnect was disabled by RECONLIM=0 in the TSOKEYxx parmlib member. For more information about the TSOKEYxx settings, see z/OS MVS Initialization and Tuning Reference.

When the program is IKTLOGR and the return code is 26, it means reconnect failed because a previous reconnect attempt was already in progress. Wait and try again later.

Module: IKJEFLA, IKJEFLC, IKJEFLE, IKJEFLEA, IKJEFLI

Program: LOGON

IKJ56455I *user_id* LOGON IN PROGRESS AT *time* ON *date*

Explanation: Validation of LOGON command is complete.

Module: IKJEFLE

Program: LOGON

IKJ56456I INCONSISTENT AUTHORIZATION FOR *user_id*

Explanation: The data or control field in UADS is invalid; a return code of 4 from FIND was issued against the UADS.

Module: IKJEFLE

Program: LOGON

IKJ56457I LOGON FAILED [*text*] +

Explanation: An error occurred in the job scheduling routine. Based on the following additional text, the cause of the problem is as follows:

System action: LOGON processing ends.

System programmer response: A re-IPL may be all that is required if the problem is due to storage fragmentation. If this is not successful, increase the space defined for SQA/CSA and re-IPL. If the problem persists, contact your IBM support personnel.

User response: Contact your system programmer.

text = **ALLOCATION UNSUCCESSFUL**

Explanation: A data set that appeared on a DD statement in your LOGON procedure could not be allocated.

User response: Correct your LOGON procedure or contact your system programmer.

text = **DATA SET REQUESTED IN LOGON PROCEDURE ALREADY IN USE**

Explanation: A data set that appeared on a DD statement in your LOGON proc has been allocated by another job or user with DISP=OLD. You will be unable to logon until this data set is no longer allocated with DISP=OLD.

User response: Try again.

text = **I/O ERROR ON PROCLIB**

Explanation: A logical I/O error has been encountered on a procedure library data set while trying to read your logon procedure. This might have been accompanied by a physical I/O error.

User response: Contact your system programmer.

text = **JCL ERROR IN LOGON PROCEDURE**

Explanation: A JCL error was encountered while processing your logon procedure.

User response: Correct the logon procedure or contact your system programmer.

text = **PROCLIB DATA SET COULD NOT BE OPENED**

Explanation: Only one step is allowed in your logon procedure.

User response: Correct your logon procedure or contact your system programmer.

text = **MULTIPLE STEPS SPECIFIED IN LOGON PROCEDURE**

Explanation: The most likely cause is that the data set could not be accessed due to an error such as a reference to an incorrect data set name or JCL error.

User response: Review your JCL and referenced data set names to be certain they are all correct; then try again.

text = **PROGRAM ERROR**

Explanation: The job scheduler rejected your logon for one of the following reasons:

1. The most likely reason is that you specified a region size for your logon that is not available on your system.
For region requests smaller than 16 MB - either this amount of private area storage is unavailable below 16 MB in virtual storage or an installation exit rejected your request.
For region requests larger than 16 MB - either this amount of private and extended storage is unavailable or an installation exit rejected your request.
2. The virtual storage manager abended.
3. The job scheduler was unable to create an address space because it found inappropriate data in a control block.
4. A program check occurred in the initiator.
5. The operator restarted the processor during your logon attempt.
6. A machine check occurred during your logon attempt.

System programmer response: Contact your IBM support personnel.

User response:

- For reason 1: Try to log on again using a different region size. Try a smaller region size, or use your installation-defined procedure for specifying the region size you require. Alternatively try to log on with a larger region size than originally requested.
 - For other reasons: Try again. If the problem persists, contact your system programmer.
-

text = **STEPLIB DATA SET COULD NOT BE OPENED**

Explanation: The most likely cause is that the data set could not be accessed due to an error such as a reference to an incorrect data set name or JCL error.

User response: Review your JCL and referenced data set names to be certain they are all correct; then try again.

- **IKJ56466I**

text = **SYSTEM ERROR**

Explanation: Likely, there is insufficient SQA/CSA space available for the needed set of page and segment tables, or address space control blocks (ASCBs), and so forth. However, your system may have experienced an internal processing error during LOGON.

Module: IKJEFLI

Program: LOGON

IKJ56458I BROADCAST DATA SET NOT USABLE, I/O SYNAD ERROR

Explanation: LISTBC was invoked during LOGON, and an I/O error occurred.

Module: IKJEES75

Audience: LISTBC user

IKJ56459I BROADCAST DATA SET NOT USABLE, CANNOT OPEN DATA SET.

Explanation: LISTBC was invoked during LOGON. The DCBOFLAGS indicated that the broadcast data set was not opened.

Module: IKJEES75 IKJEES70

Audience: LISTBC user

IKJ56461I BROADCAST DATA SET NOT USABLE, INSTALLATION MUST REFORMAT

Explanation: LISTBC was invoked during LOGON. The broadcast data set was not initialized or was not in the correct format.

Module: IKJEES70

Audience: LISTBC user

IKJ56464I You have entered unacceptable characters in the highlighted field(s)

Explanation: The highlighted field will accept certain characters but not all characters. You have entered an invalid character for this field.

System action: You are prompted to enter valid characters in the field.

User response: Enter valid characters in the highlighted field.

Module: LOGON command processor

Audience: TSO/E user

IKJ56465I Press PF1 or PF13 for help

Explanation: A message has been presented on the logon panel. If you need help, press either the PF1 or PF13 program function key and a help panel will be displayed.

System action: LOGON displays the help panel with the above message area.

User response: If you want to read the help text, press the PF1 or PF13 program function key.

Module: LOGON command processor

Audience: TSO/E user

IKJ56466I Help not available

Explanation: You requested help for a particular field, and no help text was defined for that field in the logon help panel CSECT.

System action: LOGON displays the panel with the above message in the message area, and prompts you again for

the data that was requested when you entered the help request.

User response: Report this situation to your system programmer. Your system programmer should add help text for the field in the logon help panel CSECT.

Module: LOGON command processor

Audience: TSO/E user

IKJ56467I Logon rejected — User *user_id* already logged on to system *system name*.

Explanation: An attempt was made to logon to one of the systems in the sysplex, but the user is already logged on.

System action: The LOGON command terminates.

User response: If applicable, issue the logon command using the reconnect option.

**IKJ56468I Unable to reconnect user *user_id*— remote JESXCF is downlevel.
— local JES does not support TSO/GR.
— CLSDST PASS to old address space failed or USERMAX exceeded.
— reconnect disabled by RECONLIM=0 in TSOKEYxx parmlib member.**

Explanation: LOGON was attempted with the reconnect option but the user was not logged on to the system. TSO/E was not able to determine where the user might be logged on for one of the following reasons:

- Remote JESXCF is not at the latest level.
- Local JES does not support TSO/E Generic Resource Support.

Or TSO/E found the user but was not able to reconnect them for one of the following reasons:

- CLSDST PASS to their old address space failed.
- USERMAX limit in the TSOKEYxx parmlib member was exceeded.
- Reconnect was disabled by RECONLIM=0 in TSOKEYxx.

System action: The LOGON request is rejected.

User response: Contact your system programmer for assistance.

IKJ56470I *user_id* LOGGED OFF TSO AT *time* ON *date* + LAST STEP COMPLETION CODE WAS *code*

Explanation: This is the end of the terminal session. The last step completion code for non job-scheduling subroutine return codes.

Module: IKJEFLL

Program: LOGON

IKJ56471I SECLABEL *seclabel* NOT AUTHORIZED FOR THIS USERID

Explanation: The security authorization facility (SAF) and the security server (such as RACF) indicate that you are not authorized to log on with the specified security label (SECLABEL).

System action: The system prompts you for a valid security label.

System programmer response: If the user should be allowed to specify the security label displayed in the message, authorize that user by using the RACF PERMIT command. For more information about the PERMIT command, see *z/OS Security Server RACF Command Language Reference*.

User response: Log on with a valid security label or contact your security administrator.

Module: IKJEFLE2

Audience: LOGON user

IKJ56472A REENTER NEW SECLABEL

Explanation: RACF indicates that you are not authorized to log on, in line mode, with the specified security label (SECLABEL).

System action: The system prompts you for a valid security label.

System programmer response: If the user should be allowed to specify the security label displayed in the message, authorize that user by using the RACF PERMIT command. For more information about the PERMIT command, see *z/OS Security Server RACF Command Language Reference*.

User response: Log on with a valid security label or contact your security administrator.

Module: IKJEFLE2

Audience: LOGON user

IKJ56473I A default SECLABEL could not be obtained for this user ID.

Explanation: You have not been assigned a default security label (SECLABEL). A valid security label must be entered before you can log on to the system.

System action: You are not allowed to log on. The system either prompts you for a valid security label, if you are defined to RACF; or logs you off, if you are not defined to RACF.

System programmer response: Do one of the following:

- If the user is defined to RACF, then permit that user to a security label using the RACF PERMIT command. If you want the user to have a default security label, use the RACF ALTUSER command. You must also permit the user to the default security label.
- If the user is not defined to RACF, the user cannot log on. To allow the user to log on, you must define the user to RACF and permit that user to a security label using the RACF PERMIT command.

For more information about the RACF PERMIT and ALTUSER commands, see *z/OS Security Server RACF Command Language Reference*.

User response: Either enter a valid security label for this logon session or contact your system programmer.

Module: IKJEFLE2

Audience: LOGON user

IKJ56479I COMMAND *command_name* NOT FOUND OR REXX IDENTIFIER IS MISSING + SUPPLY /* REXX */ AS THE FIRST RECORD TO EXECUTE AS A REXX EXEC OR, FOR AN EXPLICIT EXEC, SUPPLY THE EXEC KEYWORD ON THE EXEC COMMAND

Explanation: If you are executing a CLIST, check that the command you specified is either valid or spelled correctly.

If you are executing a REXX exec, the first record must be /* REXX */. For an explicit exec, supply the EXEC keyword on the EXEC command. For example,

```
EX ABC(MYEXEC) exec
```

Module: Exec processing

Audience: Exec user

IKJ56480I THE PROCEDURE NAME *xxx* IS A GENERIC NAME - PLEASE COMPLETE IT

Explanation: A generic default procedure name was obtained from the RACF data base. You must enter a valid name. (You are defined to PROC01 and PROC02 via a generic name PROC*, and must enter either PROC01 or PROC02.

Module: IKJEFLE2

IKJ56481I **The PROCEDURE NAME *xxx* IS A DEFAULT - YOU MAY CHANGE IT**

Explanation: You did not supply a logon procedure name. Logon processing selected one of the procedures that you are authorized to use. You can either use this name or change it.

Module: IKJEFLE2

IKJ56482I **THE PROCEDURE NAME *xxx* HAS NOT BEEN DEFINED FOR USE**

Explanation: One of the following occurred:

- The procedure name entered has not been defined to the RACF data base.
The RACF administrator must first define the procedure name as a RACF resource and then give you access via the PERMIT command. (However, if the procedure is not in the procedure library, the attempt will still fail.)
- The RACF class TSOPROC is not active.
The RACF administrator must activate the RACF class TSOPROC via the SETROPTS command.

Module: IKJEFLE2

Program: LOGON

IKJ56483I **THE PROCEDURE NAME *xxx* HAS NOT BEEN AUTHORIZED FOR THIS USERID**

Explanation: The procedure name entered has been defined to the RACF data base. However, you are not allowed to use it.

Module: IKJEFLE2

Program: LOGON

IKJ56484I **THE ACCOUNT NUMBER *account_number* IS A GENERIC NAME - PLEASE COMPLETE IT**

Explanation: A generic default account number was obtained from the RACF data base. You must enter a valid number. (For example, if you are defined to D8801P and D8802P via a generic name D880*, you must enter either D8801P or D8802P.)

Module: IKJEFLE2

Program: LOGON

IKJ56485I **THE ACCOUNT NUMBER *account_number* IS A DEFAULT - YOU MAY CHANGE IT**

Explanation: You did not supply an account number. Logon processing selected one of the account numbers that you are authorized to use. You can either use this number or change it.

Module: IKJEFLE2

Program: LOGON

IKJ56486I **THE ACCOUNT NUMBER *xxx* HAS NOT BEEN DEFINED FOR USE**

Explanation: One of the following occurred:

- The account number entered has not been defined to the RACF data base.
The RACF administrator must first define the account number as a RACF resource and then give you access via the PERMIT command. (However, if the procedure is not in the procedure library, the logon attempt will still fail).
- The RACF class ACCTNUM is not active.
The RACF administrator must activate the RACF class ACCTNUM via the SETROPTS command.

Module: IKJEFLE2

Program: LOGON

IKJ56487I • IKJ56493I

IKJ56487I THE ACCOUNT NUMBER *xxx* HAS NOT BEEN AUTHORIZED FOR THIS USERID

Explanation: The account number entered has been defined to the RACF data base, however, this particular user ID is not allowed to use it.

Module: IKJEFLE2

Program: LOGON

IKJ56488I NO PERFORMANCE GROUPS EXIST FOR THIS USERID

Explanation: You entered a performance group, but no performance groups are defined for your user ID.

Module: IKJEFLE3

Program: LOGON

IKJ56489I THE PERFORMANCE GROUP *xxx* HAS NOT BEEN DEFINED FOR USE

Explanation: The performance group entered has not been defined to the RACF data base. The RACF administrator must first defined the performance group as a RACF resource and then give you access via the PERMIT command. (However, if the procedure is not in the procedure library, the logon attempt will still fail.)

Module: IKJEFLE3

Program: LOGON

IKJ56490I THE PERFORMANCE GROUP *xxx* HAS NOT BEEN AUTHORIZED FOR THIS USERID

Explanation: The performance group entered has been defined to the RACF data base. However, your user ID is not allowed to use it.

Module: IKJEFLE3

Program: LOGON

IKJ56491I RACF IS NOT ACTIVE

Explanation: This message is issued when logon tries to extract information from the RACF data base or is trying to verify the information entered by the user.

Module: IKJEFLJU IKJEFLE2

Program: LOGON

IKJ56492I SYSTEM ERROR - LOGON TERMINATED

Explanation: An error occurred during logon processing. A message also went to the system console with additional information.

System action: The LOGON command processor terminates.

User response: Contact your system programmer for assistance.

Module: IKJEFLJU IKJEFLE2

Program: LOGON

IKJ56493I TSOLOGON RECONNECT REJECTED. TERMINAL CAN NOT BE USED AT THIS TIME.

Explanation: The user was trying to log on to a terminal that cannot be used on this day, or at this time of day.

Module: IKJEFLE3

Program: LOGON

IKJ56494I LOGON TERMINATED. TERMINAL CAN NOT BE USED AT THIS TIME.

Explanation: The user was trying to log on to a terminal that cannot be used on this day, or at this time of day.

Module: IKJEFLE3

Program: LOGON

IKJ56495I LOGON TERMINATED. USER *user_id* IS NOT DEFINED TO ANY PROCEDURE NAMES

Explanation: The user was trying to log on but does not have any procedure names defined to RACF.

Module: IKJEFLE2

Program: LOGON

IKJ56496I DEFAULT ACCOUNT NUMBERS COULD NOT BE OBTAINED - ENTER ACCOUNT NUMBER

Explanation: A default account number was not defined for the user.

System action: LOGON prompts the user to enter a valid account number.

User response: Enter a valid account number. If you do not know what account numbers are valid for that user ID, contact the RACF administrator.

Module: IKJEFLE2

Program: LOGON

IKJ56497I DEFAULT PROCEDURE NAMES COULD NOT BE OBTAINED - ENTER PROCEDURE NAME

Explanation: A default procedure name was not defined for the user.

System action: LOGON prompts the user to enter a valid procedure name.

User response: Enter a valid procedure name. If you do not know what procedure names are valid for that user ID, contact the RACF administrator.

Module: IKJEFLE2

Program: LOGON

IKJ56498I TSOLOGON RECONNECT REJECTED. IT IS NOW OUTSIDE YOUR AUTHORIZED HOURS OF USE

Explanation: Your TSO/E administrator must authorize the use of TSO for your user ID at this day and time.

Module: IKJEFLE3

Program: LOGON

IKJ56500I COMMAND *command_name* NOT FOUND

Explanation: A CLIST or REXX exec to be implicitly executed could not be found. The error message displays the command that was not found. Check that the command you specified is valid or spelled correctly.

Module: IKJCT420 IKJCT43D IKJCT43E

Audience: EXEC user

IKJ56501I REQUESTED INPUT DATA SET IS EMPTY

Explanation: A data set requested as an input data set for a CLIST or REXX exec contains no records.

Module: IKJCT43D

Audience: EXEC user

IKJ56502I ORGANIZATION OF [text] NOT ACCEPTABLE ORGANIZATION MUST BE PARTITIONED OR SEQUENTIAL

Explanation: For the item *text* could appear the following:

- *text* = FDILE SYSPROC
- *text* = DATA SET *dsname*

The data set containing the CLIST or REXX exec to be executed was not partitioned or sequential. If the data set was allocated to SYSPROC, it was not partitioned.

Module: IKJCT43E

Audience: EXEC user

IKJ56503I DATA SET *dsname* NOT USABLE + CANNOT OPEN DATA SET FIND ERROR *xxxx*

Explanation: The SYSPROC data set could not be opened, a member of the SYSPROC data set could not be found, or there were errors while reading from the SYSPROC data set.

I/O SYNAD ERROR *synad info*

Explanation: An I/O error occurred using the SYSPROC data set. The SYNAD exit information was printed.

Module: CLIST or exec processing

Audience: EXEC user

IKJ56504I INVALID VALUE *x* FOR *y*

Explanation: Either your CLIST entered an incorrect value *x* for SYSOUTTRAP, or an invalid value *y* was generated by CLIST EXEC processing for SYSOUTLINE. Valid values for these variables are positive integers with 15 or less digits. Anything else will cause this message to be issued. Check your CLIST to ensure that your SYSOUTTRAP value is valid. If it is not valid, correct the CLIST statement and reexecute the CLIST. If your SYSOUTTRAP value is valid, contact your system programmer to resolve the problem.

Module: CLIST processing

Audience: EXEC user

IKJ56505I RECORD FORMAT U NOT ACCEPTABLE

Explanation: The RECFM for the data set containing the command procedure to be executed was other than VB or FB.

Module: CLIST processing

Audience: EXEC user

IKJ56506I INVALID POSITIONAL SPECIFICATION ON PROC STATEMENT *value* + SPECIFICATION MUST BE AN UNSIGNED INTEGER 1-8 DIGITS IN LENGTH

Explanation: The PROC statement in the command procedure did not have an integer indicating the number of positional parameters being used in the command procedure.

Module: IKJCT431

Audience: EXEC user

IKJ56507I INVALID [text] PARAMETER DEFINITION *value* ON PROC STATEMENT SYMBOLIC PARAM NAMES MUST BE ALPHANUMERIC WITH THE FIRST CHARACTER ALPHABETIC. THE MAX CHARACTER LENGTH IS 31 FOR KEYWORD PARMS AND 252 FOR POSITIONAL PARMS.

Explanation: For the item *text* could appear the following:

- *text* = POSITIONAL
- *text* = KEYWORD

There was invalid parameter syntax on the PROC statement of the command procedure to be executed.

Module: IKJCT431

Audience: EXEC user

IKJ56508I **INVALID DEFAULT VALUE FOR KEYWORD PARAMETER - *value* + DEFAULT VALUE MAY ONLY BE A NULL ENTRY, OR A CHARACTER STRING (QUOTED OR UNQUOTED)**

Explanation: Syntax for keywords on the PROC statement of the command procedure to be executed was incorrect.

Module: IKJCT431

Audience: EXEC user

IKJ56509I **MISSING POSITIONAL PARAMETERS + THE NUMBER OF POSITIONALS DEFINED IN THE PROC STATEMENT IS LESS THAN THE NUMBER SPECIFIED**

Explanation: The number of positional parameters specified on the PROC statement was greater than the positional specification on the PROC statement indicated.

Module: IKJCT431

Audience: EXEC user

IKJ56510I **INVALID SYMBOLIC PARAMETER REFERENCES + SYMBOLIC PARAMETER VALUES WERE ENTERED ON THE INVOCATION STATEMENT BUT SYMBOLIC PARAMETERS WERE NOT DEFINED IN THE COMMAND PROCEDURE**

Explanation: The user entered an EXEC statement with symbolic parameters but there were no symbolic parameters defined on the PROC card for the procedure to be executed.

Module: IKJEFE02

Audience: EXEC user

IKJ56511I **INSUFFICIENT VIRTUAL STORAGE TO EXECUTE COMMAND**

Explanation: A GETMAIN failure occurred.

Module: IKJCT431

Audience: EXEC user

IKJ56512I **LAST LINE OF PROCEDURE CONTAINS CONTINUATION INDICATOR**

Explanation: A continuation indicator was present in the last line of the command procedure.

Module: IKJEFE03

Audience: EXEC user

IKJ56513I *value* **NOT DEFINED IN PROC STATEMENT**

Explanation: There was a symbolic parameter (*value*), in a command procedure, not defined in the PROC statement.

Module: IKJEFE03

Audience: EXEC user

IKJ56514I **END OF FILE ENCOUNTERED DURING CONTINUATION PROCESSING**

Explanation: A CLIST or REXX exec was processing a continued record (a record ending with either + or -) when it reached the end of the data set.

Module: IKJCT43A

IKJ56515I LINE *nnnn* IN PROCEDURE EXCEEDS LIMITATION OF 32,764 CHARACTERS

Explanation: An output line, resulting from symbolic parameter substitution, exceeded the limit of 32,764 characters.

Module: IKJEFE03

Audience: EXEC user

IKJ56516I A SYMBOLIC PARAMETER EXCEEDS THE MAXIMUM ALLOWABLE LENGTH + THE
MAXIMUM ALLOWABLE LENGTH IS 31 CHARACTERS FOR KEYWORD PARAMETER AND 252
CHARACTERS FOR POSITIONAL PARAMETERS

Explanation: A symbolic parameter in a command procedure had an invalid syntax.

Module: IKJEFE05

Audience: EXEC user

IKJ56517I CONTINUED RECORD EXCEEDS THE MAX ALLOWED (32756)

Explanation: The maximum continuation record length is 32756 bytes. CLIST processing terminates.

Module: IKJCT43A

Audience: EXEC user

IKJ56518I INPUT RECORD IS TOO LONG--MAX IS 255 CHARACTERS

Explanation: The maximum record length for a fixed block CLIST or REXX exec data set is 255. Processing will not be performed on fixed block CLIST or REXX exec data sets with record lengths greater than 255.

Module: IKJCT43A

Audience: EXEC user

IKJ56519I NO USABLE CLIST RECORDS

Explanation: A CLIST contained either blank records or comments, but no executable statements.

Module: IKJCT43A

Audience: EXEC user

IKJ56520I MEMBER *member* NOT IN DATA SET *dsname*

Explanation: The member of the partitioned data set specified on the EXEC command could not be found.

Module: IKJCT43D

Audience: EXEC user

IKJ56521I MEMBER *member* SPECIFIED BUT DATA SET *dsname* NOT A PARTITIONED DATA SET

Explanation: A dsname and a member name were specified on the EXEC command but the data set was not partitioned.

Module: IKJCT43E

Audience: EXEC user

IKJ56522I ORGANIZATION OF FILE SYSPROC NOT ACCEPTABLE + ORGANIZATION MUST BE
PARTITIONED

Explanation: The organization of the SYSPROC data set must be partitioned when using the implicit form of EXEC.

Module: IKJEFE05

Audience: EXEC user

IKJ56523I [text] NOT USABLE CANNOT OPEN DATA SET

Explanation: For the item *text* could appear the following:

- *text* = FILE SYSPROC
- *text* = DATA SET *dsname*

The LOGON proc did not contain a SYSPROC DD card for use with the implicit EXEC, or the data set name specified could not be opened.

Module: IKJCT430 IKJEFE05

Audience: EXEC user

IKJ56524I COMMAND SYSTEM ERROR + GETLINE RETURN CODE *error_code* STACK RETURN CODE *error_code* IKJCT43A RETURN CODE *error_code*

Explanation: The return code from one of the service routines used was greater than 0 and not 4.

[text] ENVIRONMENT COULD NOT BE ESTABLISHED, [text] RETURN CODE WAS *return_code*

- *text* = STAE
- *text* = ESTAE

Explanation: TSO/E could not establish a STAE or an ESTAE environment.

Module: IKJCT430, IKJCT43A

Audience: EXEC user

IKJ56525I INVALID DATA SET NAME, *dsname*. CLIST EXCEEDS 44 CHARACTERS

Explanation: The data set name specified with the explicit EXEC command syntax (and the TSO prefix, if it exists) exceeded the limit of 44 characters after the addition of the CLIST data set name qualifier.

Module: IKJCT43E

Audience: EXEC user

IKJ56526I STMT *num* - INVALID KEYWORD *name*.

Explanation: At the statement numbered "num" in a command procedure, the user specified an invalid keyword identified by "name" on a CONTROL statement.

For TSO/E Release 3 and subsequent releases, "num" refers to the physical line number of your listing. Blank lines and comment lines are counted as physical lines. To find the keyword in error, count down "num" physical lines from the top of your CLIST.

For releases of TSO/E before Release 3, "num" refers to the logical line number. A statement that is continued on the next physical line of your listing is still considered part of the same logical line. Blank lines and comment lines are not counted as logical lines. Thus, to find the keyword in error, count down "num" logical lines from the top of your CLIST.

Module: IKJCT432

Audience: EXEC user

IKJ56527I DEFAULT KEYWORD VALUE ENDING QUOTE ASSUMED - *parm('value')*

Explanation: The value of the keyword defined on the PROC statement was a quoted character string without an ending quote.

Module: IKJCT431

Audience: EXEC user

IKJ56528I STMT *num* - *name* AMBIGUOUS

Explanation: At the statement numbered “num” in the command procedure, the user entered an ambiguous keyword in the form represented by “name” on a CONTROL statement.

Module: IKJCT432

Audience: EXEC user

IKJ56529I SYMBOLIC PARAMS IN VALUE LIST IGNORED-*parms* + COMMAND PROCEDURE HAS NO PROC STATEMENT

Explanation: The user specified symbolic parameter values in the value list on the EXEC command with which he invoked a command procedure, but the procedure has no PROC statement to denote the symbolic parameters for which the user specified values.

NO SYMBOLIC PARAMS WERE DEFINED ON THE PROC STATEMENT

Explanation: The user specified symbolic parameter values in the EXEC command value list, but the command procedure's PROC statement specifies no positional parameters.

Module: IKJCT431

Audience: EXEC user

IKJ56530I *name* IS A MULTIPLY DEFINED SYMBOLIC PARM + EACH PARM NAME ON A PROC STATEMENT MUST BE UNIQUE

Explanation: The user entered two parameters with the same name on the PROC statement.

PARMS ON THE GLOBAL STATEMENT CANNOT BE PREVIOUSLY DEFINED

Explanation: A parameter that the writer of the command procedure coded on a GLOBAL statement had already been defined in the same procedure on either a PROC, READ, GLOBAL, SET, or READDVAL statement.

Module: IKJCT431 IKJCT432

Audience: EXEC user

IKJ56531I STMT *num* - *name* IS A MULTIPLY DEFINED LABEL

Explanation: The label specified as “name” on the statement numbered “num” was previously defined for another purpose within this procedure.

Module: IKJCT43C

Audience: EXEC user

IKJ56532I STMT *num* - LABEL *name* SPECIFIED BUT COMMAND NOT FOUND

Explanation: The statement numbered “num” contained a label specified as “name” but no command name.

Module: IKJCT432

Audience: EXEC user

IKJ56533I STMT *num* - IF STATEMENT CONTAINS NO EXPRESSION OR THEN KEYWORD

Explanation: The IF statement numbered “num” contained no valid expression or THEN clause, both of which are syntactically necessary.

Module: IKJCT432

Audience: EXEC user

IKJ56534I STMT *num* - A(N) [*stmt1*] STMT WAS FOUND FOR WHICH THERE IS NO CORRESPONDING
[*stmt2*] STMT

Explanation:

- *num* = statement number
- *stmt1* = The statement in the command procedure:
 - END
 - alternate END
 - ELSE
 - ENDDATA
 - SELECT
- *stmt2* = The statement that should have been previously specified to match the statement in the command procedure:
 - DO
 - IF
 - DATA
 - END
 - alternate END
- An END (or alternate string defined on the CONTROL statement to replace END), ELSE, or ENDDATA statement appeared in the command procedure without a matching previously specified DO, IF, or DATA statement, respectively.
- The CLIST syntax processor expected a WHEN or a series of WHENs with an optional OTHERWISE within a SELECT statement. This error is often caused by forgetting the DO and END statements around the list of statements following a WHEN or an OTHERWISE. The CLIST syntax processor ends processing of the SELECT statement to avoid misinterpreting the statements that follow. The CLIST syntax processor continues processing the next statement in the CLIST.

Module: IKJCT432 IKJCT43B**Audience:** EXEC user

IKJ56535I GLOBAL PARAMETERS SPECIFIED INCORRECTLY

Explanation: The number of GLOBAL symbolic parameters specified in a nested CLIST exceeds the number defined on the GLOBAL statement of the top level procedure. If the top-level procedure is a REXX exec, nested CLISTS cannot use any GLOBAL symbolic parameters.

Module: IKJCT430 IKJCT43C**Audience:** EXEC user

IKJ56536I STMT *num* - EXPRESSION FOLLOWING WHILE KEYWORD NOT FOUND, WHILE OPERAND IS IGNORED

Explanation: The procedure contained a DO statement at line number “*num*” with a WHILE operand that had no expression following it. The procedure will try to execute the DO statement as though the WHILE operand did not appear on it.

Module: IKJCT43B**Audience:** EXEC user

IKJ56537I END OF FILE ON CLIST OCCURRED BEFORE ALL [*text*] STATEMENTS WERE CLOSED

Explanation: For the item *text* could appear the following:

- *text* = DO
- *text* = DATA
- *text* = PROC

The end of file condition occurred before the command procedure could clear all its DO, DATA or PROC statements.

Module: IKJCT43B IKJCT43C**Audience:** EXEC user

IKJ56538I STMT *num* - EXPRESSION MISSING FROM SET STMT

Explanation: The SET statement numbered "num" contains no symbolic variable name.

Module: IKJCT43C

Audience: EXEC user

IKJ56539I STMT *num* - NUMBER OF PARMS SPECIFIED ON THE READ STMT EXCEEDS MAX OF 256

Explanation: The number of symbolic variables specified on the READ statement numbered "num" constituted a character string longer than the maximum length of 256.

Module: IKJCT43C

Audience: EXEC user

IKJ56540I STMT *num* - INVALID PARM SPECIFIED - *parm* + THE MAX LENGTH FOR EACH PARM ON THE GLOBAL STMT IS 31 AND ON THE READ(DVAL) STMT IS 252

Explanation: A parameter on the GLOBAL or READ statement numbered "num" exceeded the maximum permissible length.

SYMBOLIC PARM NAMES MUST BE ALPHANUMERIC WITH THE FIRST CHARACTER ALPHABETIC

Explanation: A GLOBAL, READ, READDVAL, or SET statement numbered "num" contained invalid characters.

NEW PARMS DEFINED ON THE READ(DVAL) STMT CANNOT EXCEED 31 CHARACTERS

Explanation: An implicit definition of a symbolic variable on a READ or SET statement numbered "num" exceeds 31 characters.

Module: IKJCT432

Audience: EXEC user

IKJ56541I NORMAL END OF FILE OCCURRED ON GETFILE (E400)

Explanation: The system detected an end of file condition on the last GETFILE execution.

Module: IKJCT437

Audience: EXEC user

IKJ56542I EXEC FILE I/O ERROR -
jobname,stepname,devicenumber,devicetype,ddname,operation,errordesc,trackaddr,QSAM

Explanation: There is a file I/O error of the type denoted by *errordesc*. These are the fields:

jobname - Name of the current job. This is your TSO identifier.

stepname - Name of the current job step.

devicenumber - Four-hex-digit device number. It uniquely defines the device on the system. It is in the primary subchannel set.

deviceclass - Class of the device. "D" represents DASD, "T" represents tape, "U" represents unit record, and "*" represents "other".

ddname - Name of the DD in the logon procedure, background JCL or dynamic allocation.

operation - Name of the macro that failed, such as GET or PUT.

errordesc - Fifteen-character summary of the hardware failure.

trackaddr - If the device is DASD, this is the location of the failing block and the format is *bbcchhr*, where *bb* is "0000" and *cchhr* is the cylinder, track and record numbers in hex. If it is a compressed format data set, this is the relative block number of the compressed failing block in the data set. If it is a z/OS UNIX file, then this is the hexadecimal offset into the file to the failure point.

If any of the above information is not available, that field will contain asterisks. For more information about the above variables, see the description of the SYNADAF macro in *z/OS DFSMS Macro Instructions for Data Sets*.

Module: IKJCT436

Audience: EXEC user

IKJ56543I STMT *num* - MISSING END STRING

Explanation: The CONTROL statement numbered “num” specified the END option for replacing the END statement with an equivalent character string, but failed to include the string to be used for the replacement.

Module: IKJCT43C

Audience: EXEC user

IKJ56544I STMT *num* - INVALID OR EXTRANEIOUS END STRING

Explanation: The string specified for the END(string) option of the CONTROL statement numbered “num” contains an invalid value.

Module: IKJCT43C

Audience: EXEC user

IKJ56545I THIS STATEMENT HAS AN EXPRESSION WITH MISSING OPERATORS

Explanation: The expression-handling routine could not find any operators for the expression.

AN EXPRESSION WITH OPERATORS OUT OF SEQUENCE

Explanation: The expression-handling routine found an invalid combination of operators and data elements.

AN EXPRESSION WITH A CHARACTER DATA ITEM USED NUMERICALLY

Explanation: The expression-handling routine found a character item used in an arithmetic operation.

A NUMBER EXCEEDING THE MAXIMUM ALLOWABLE VALUE

Explanation: The expression-evaluation routine found a number whose absolute value exceeded the maximum of 2,147,483,647. The expression evaluation has terminated.

EXCEEDED THE MAXIMUM NUMBER DURING EVALUATION

Explanation: The result of an arithmetic operation has exceeded the maximum permissible value of 2,147,483,647.

AN UNDEFINED SYMBOLIC VARIABLE

Explanation: Symbolic substitution found a variable that could not be located for its value.

ATTEMPTED TO UPDATE A SYSTEM VARIABLE

Explanation: The system detected an update to a system-provided variable (for example, &SYSTIME).

AN UNDEFINED KEYWORD

Explanation: The system was scanning for keywords on the statement and found one that was undefined.

A MISSING KEYWORD VALUE

Explanation: The system found a keyword that required a value, but could locate no value for it.

A TERMIN STRING GREATER THAN 256 CHARACTERS

Explanation: TERMIN processing found a delimiter that is too long.

MORE THAN 64 TERMIN STRINGS

Explanation: TERMIN processing found that the limit for specifying TERMIN delimiter strings had been exceeded.

AN INVALID FILENAME

Explanation: The file name was missing or invalid. The procedure may have attempted to perform I/O against a file that was not opened by the same procedure. You should either:

IKJ56546I

- Perform file I/O within the procedure that did the OPENFILE
- If the file name is to be shared between subprocedures in a CLIST, use the NGLOBAL statement to define the file name as a named global variable.

TRIED TO OPEN A FILE THAT IS CURRENTLY OPEN

Explanation: The system found that an OPENFILE statement had already been issued for that file.

AN INVALID OPEN OPTION

Explanation: The system was scanning for INPUT, OUTPUT, or UPDATE and found something else.

FAILED TO OPEN THE REQUESTED FILE

Explanation: The system detected that the data control block did not open. The file name was already missing.

TRIED TO USE A FILE THAT IS NOT CURRENTLY OPEN

Explanation: The system could find neither the requested file nor evidence that a task switch caused the automatic close of the file.

CAUSED A RECURSIVE CLIST ERROR

Explanation: The statement was in an error range and gave a non-zero return code. This message also appears if the statement had its own diagnostic printed.

AN INVALID &SUBSTR RANGE OR EXIT CODE EXPRESSION

Explanation: The &SUBSTR built-in function found invalid data or numbers in the substring range field (for example, the expression "&SUBSTR (1:10,AE)" is invalid because 10 is outside the range). The expression supplied in an 'EXIT CODE' statement did not resolve to a numeric value (for example, "EXIT CODE (X2)").

A MISSING BUILT-IN FUNCTION OPERAND

Explanation: The system encountered a built-in function without an open parenthesis after the name.

AN INVALID SYMBOLIC VARIABLE

Explanation: Except for positional parameters on PROC statements, symbolic variable names must include 1-31 alphanumeric characters, the first of which is alphabetic following an ampersand (&). PROC statement positional parameter names may have as many as 252 alphanumeric characters.

USED A LABEL AS A SYMBOLIC VARIABLE

Explanation: The system was locating the name for a value and found it was a label.

REFERENCED AN INVALID OR UNDEFINED LABEL

Explanation: The target of the GOTO statement could not be found or was missing entirely.

SUPPLIED AN UNREQUESTED PROMPT REPLY

Explanation: The system has found a prompt reply (a line within a DATA PROMPT – ENDDATA group) that was not needed to complete the immediately preceding command.

EXCEEDED THE MAXIMUM LENGTH DURING SYMBOLIC SUBSTITUTION

Explanation: THE CLIST statement length exceeds the maximum of 32,756. CLIST processing terminates.

Module: IKJCT433 IKJCT434 IKJCT436

Audience: EXEC user

IKJ56546I NO FLUSH NO PROMPT NO LIST NO CONLIST NO SYSMLIST NO MSG MAIN

Explanation: CONTROL statement without operands prints the current control options of the command procedure.

Module: IKJCT436

Audience: EXEC user

IKJ56547I INTERNAL COMMAND PROCEDURE EXEC ERROR CODE [text]

Explanation: For the item *text* could appear the following:

- *text* = Uyyyy
- *text* = Sxxx
- *text* = Ennn

The system has detected:

- U -- a user ABEND code *yyyy*
- S -- a system ABEND code *xxx*
- E -- a severe command procedure error *nnn*

EXEC ERROR CODE [text] HAS BEEN ISSUED RECURSIVELY

- *text* = Uyyyy
- *text* = Sxxx
- *text* = Ennn

Explanation: The system has detected a recursive I/O error while executing a CLIST. The following

- U -- a user ABEND code *yyyy*
- S -- a system ABEND code *xxx*
- E -- a severe command procedure error *nnn*

will indicate the most recent I/O failure which occurred.

Refer this message to the installation's system programmer.

Module: IKJCT433 IKJCT436

Audience: EXEC user

IKJ56548I INSUFFICIENT STORAGE FOR CLIST TO CONTINUE

Explanation: The system detected a GETMAIN failure.

Module: IKJCT433 IKJCT436

Audience: EXEC user

IKJ56549I PUTFILE ISSUED BEFORE ANY GETFILES (UPDATE MODE)

Explanation: Because PUTFILE needs a record to update while in update mode, a procedure must issue a GETFILE first.

Module: IKJCT437

Audience: EXEC user

IKJ56550I THE TERMIN/TERMING/READ STATEMENT IS NOT SUPPORTED FOR BACKGROUND PROCESSING

Explanation: The TERMIN, TERMING, and READ statements relate specifically to obtaining data from a foreground terminal and have no meaning in background mode.

Module: IKJCT436

Audience: EXEC user

IKJ56551I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: GETMAIN failed. The user must logon with a larger region.

Module: IKJEFA00

Program: ACCOUNT

IKJ56552I • IKJ56558I

IKJ56552I **COMMAND SYSTEM ERROR + IKJSCAN ERROR CODE** *error_code* **PUTGET ERROR CODE**
error_code **PUTLINE ERROR CODE** *error_code* **STAE ERROR CODE** *error_code* **STAI ERROR CODE**
error_code **STAX ERROR CODE** *error_code*

Explanation: An error return code was received from a service routine.

Module: IKJEFA00

Program: ACCOUNT

IKJ56553I **COMMAND NOT AUTHORIZED FOR USERID + YOUR INSTALLATION MUST AUTHORIZE
USE OF THIS COMMAND**

Explanation: The user is described in the UADS without account ability. The user must logon with a new user ID that has been authorized to use the ACCOUNT command.

Module: IKJEFA00

Program: ACCOUNT

IKJ56554I *subcommand_name* **ENDED DUE TO ERROR + SYSTEM COMPLETION CODE** *xxxx*

Explanation: The ACCOUNT STAE routine received control due to an abend in one of the ACCOUNT subcommands.

Module: IKJEFA00

Program: ACCOUNT

IKJ56555I **INVALID SUBCOMMAND** *name*

Explanation: The user has attempted to use a subcommand that does not compare with the list of valid ACCOUNT subcommands or their abbreviations.

Module: IKJEFA00

Program: ACCOUNT

IKJ56556I **INVALID COMMANDNAME SYNTAX**

Explanation: ACCOUNT was unable to syntax-check the command name.

Module: IKJEFA00

Program: ACCOUNT

IKJ56557I *data* **IGNORED**

Explanation: The user entered data with the ACCOUNT command.

Module: IKJEFA00

Program: ACCOUNT

IKJ56558I **UNABLE TO ADD FOR USERID** *user_id* **+ SPECIFY COMMAND IN SIMPLER FORM FOR
USERID** *user_id*

Explanation: The structure described in the datalist for user ID is too large to be added to the existing structure and one additional member block. Some of the items in the datalist must be eliminated and added later.

EXTENSION BLOCKS EXHAUSTED FOR USERID *user_id*

Explanation: The structure described in the datalist for user ID is too large to be added to the existing structure without exceeding ten member blocks. Items must be deleted from the user or existing items may be changed instead of added.

[*text*] **CANNOT BE USED MORE THAN 255 TIMES UNDER USERID** *user_id*

- *text* = ACCOUNT NUMBER_{yy}
- *text* = PROCEDURE NAME

Explanation: The ACCOUNT number/procedure name is being referenced by more than 255 PASSWORDS/ACCOUNT numbers.

Module: IKJEFA13

Program: ACCOUNT/ADD

IKJ56559I UNABLE TO ADD FOR USERID *user_id*, [*text*] NOT SUPPORTED

Explanation: For the item *text* could appear the following:

- *text* = PASSWORDS
- *text* = ACCOUNT NUMBERS

The *user_id* does not contain PASSWORD/ACCOUNT numbers so the structure described in the datalist cannot be built.

Module: IKJEFA13

Program: ACCOUNT/ADD

IKJ56560I ADDED

Explanation: Normal completion occurred.

Module: IKJEFA10

Program: ACCOUNT/ADD

IKJ56561I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: GETMAIN failed. The user must logon with a larger region.

NOT ENOUGH MAIN STORAGE TO ADD FOR USER *user_id*

Explanation: GETMAIN failed attempting to read in the user ID. The user must logon with a larger region.

Module: IKJEFA10

Program: ACCOUNT/ADD

IKJ56562I COMMAND SYSTEM ERROR + DUPLICATE USERID *user_id*

Explanation: The STOW return code was 8. ACCOUNT attempted to stow a new member block.

BLDL ERROR CODE *error_code*

STOW ERROR CODE *error_code*

ENQUEUE ERROR CODE *error_code*

PARSE ERROR CODE *error_code*

Explanation: An invalid service routine return code was returned.

Module: IKJEFA10, IKJEFA12

Program: ACCOUNT/ADD

IKJ56563I USER ATTRIBUTE DATA SET NOT USABLE + CANNOT OPEN DATA SET

Explanation: OPEN failed for SYSUADS. The file was not allocated.

BLDL I/O ERROR

Explanation: Bldl return code was 8.

STOW I/O ERROR

IKJ56564I • IKJ56567I

Explanation: The STOW return code was 16.

READ I/O ERROR

WRITE I/O ERROR

UADS BLOCK SIZE TOO SMALL

Explanation: The blocksize of the SYSUADS data set is not large enough to contain the user ID structure. The data set must be re-created with a larger blocksize.

NOT ENOUGH DIRECTORY SPACE

Explanation: The STOW return code was 12. The UADS data set must be re-created with a greater number of directory blocks.

BACKSPACE ERROR CODE

Explanation: ADD received a return code of 4 in attempting to backspace and reread the directory.

Module: IKJEFA10, IKJEFA12

Program: ACCOUNT/ADD

IKJ56564I DUPLICATE ITEM IGNORED, duplicate data

Explanation: A duplicate item was found in the datalist.

Module: IKJEFA12

Program: ACCOUNT/ADD

IKJ56565I [text]xx... NOT FOUND AS SPECIFIED BY NODELIST

Explanation: For the item *text* could appear the following:

- *text* = USERID
- *text* = PASSWORD
- *text* = ACCT NUMBER

The UADS structure described in the nodelist could not be located. *xx...* is the highest-level item not found.

Module: IKJEFA12

Program: ACCOUNT/ADD

IKJ56566I UNABLE TO ADD FOR USERID *user_id*, USERID IN USE

Explanation: The ENQUEUE return code was 4. The user is logged on and cannot be updated.

Module: IKJEFA12

Program: ACCOUNT/ADD

IKJ56567I USERID *user_id* ALREADY EXISTS

Explanation: ADD received a return code of 0 from BLDL while attempting to create a new user.

text **ALREADY EXISTS UNDER**

- *text* = PASSWORD
- *text* = ACCT NUMBER
- *text* = PROC NAME
- *text* = USERID *id*

Explanation: The data list item *xx...* already exists for the user and cannot be added.

Module: IKJEFA10, IKJEFA13

Program: ACCOUNT/ADD

IKJ56568I INVALID (NODELIST) + CANNOT CREATE ENTRY WITH USERID OF *

Explanation: The nodelist contains four items indicating a create for a new user but the user ID is an asterisk.

Module: IKJEFA10

Program: ACCOUNT/ADD

IKJ56569I UNABLE TO ADD FOR USERID *user_id*, [*text*] ARE REQUIRED

Explanation: For the item *text* could appear the following:

- *text* = PASSWORDS
- *text* = ACCT NUMBERS

The user ID contains PASSWORD/ACCOUNT numbers so the structure described in the datalist cannot be built.

REGION SIZE *size* EXCEEDS MAXIMUM SIZE FOR USERID *user_id*, MAXSIZE USED

Explanation: The size value of the procedure name being added is greater than the maxsize value of the user. The user's MAXSIZE value is now the size value for this procedure.

Module: IKJEFA13, IKJEFA12

Program: ACCOUNT/ADD

IKJ56570I CHANGED

Explanation: Normal completion occurred.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56571I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: GETMAIN failed. The user must logon with a larger region.

NOT ENOUGH MAIN STORAGE TO CHANGE FOR USERID *user_id*

Explanation: GETMAIN failed attempting to read in the *user_id*. The user must logon with a larger region.

NOT ENOUGH SPACE TO CHANGE FOR USERID *user_id*

Explanation: There is not enough space within the blocks allotted for this *user_id*. Issue the ADD subcommand of ACCOUNT to provide more space, then reissue the CHANGE subcommand.

Module: IKJEFA20, IKJEFA22, IKJEFA23

Program: ACCOUNT/CHANGE

**IKJ56572I COMMAND SYSTEM ERROR + PARSE ERROR CODE *error_code* PUTLINE ERROR CODE
error_code ACCOUNT GETSPACE ERROR CODE *error_code* ACCOUNT FREESPACE ERROR CODE
*error_code***

Explanation: An invalid service routine return code was returned.

Module: IKJEFA20, IKJEFA22, IKJEFA23

Program: ACCOUNT/CHANGE

IKJ56573I USER ATTRIBUTE DATA SET NOT USABLE + CANNOT OPEN DATA SET

Explanation: OPEN failed for SYSUADS. The file was not allocated.

BLDL ERROR CODE *error_code*

Explanation: BLDL return code was 8.

STOW ERROR CODE *error_code*

IKJ56574I • IKJ56578I

Explanation: STOW return code was 16.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56574I UNABLE TO CHANGE FOR USERID *user_id*, SPECIFIED MAXSIZE *nnnnn*, SMALLER THAN EXISTING PROCSIZE(S)

Explanation: The MAXSIZE specified in the command is less than the procsize of one or more procedures.

SPECIFIED PROCSIZE LARGER THAN MAXSIZE FOR USERID *user_id*, MAXSIZE USED

Explanation: The size value of the procedure name being changed is greater than the MAXSIZE value of the user. The user's MAXSIZE value is now the size value for this procedure.

Module: IKJEFA20, IKJEFA23

Program: ACCOUNT/CHANGE

IKJ56575I [*text*] NOT FOUND AS SPECIFIED BY NODELIST

Explanation: For the item *text* could appear the following:

- *text* = USERID
- *text* = PASSWORD
- *text* = ACCT NUMBER
- *text* = PROC NAME

The UADS structure described in the nodelist could not be located. The indicated name is the highest-level item not found.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56576I UNABLE TO CHANGE FOR USERID *user_id*, USERID IN USE

Explanation: ENQUEUE return code was 4. The user is logged on and cannot be updated.

***text* NOT SUPPORTED**

- *text* = DESTINATION
- *text* = PERFORMANCE GROUPS

Explanation: The user does not have destination or performance group support.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56577I USERID *user_id* ALREADY EXISTS

Explanation: CHANGE received a return code of 4 from STOW while attempting to create a new *user_id*.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56578I UNABLE TO CHANGE FOR USERID *user_id*, CONFLICTING PROCNAME DATA

Explanation: One or more of the procedure names being changed contain different size, unit information, or both.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56579I UNABLE TO CHANGE FOR USERID *user_id*, [*text*] NOT SUPPORTED

Explanation: For the item *text* could appear the following:

- *text* = PASSWORDS
- *text* = ACCT NUMBERS

The *user_id* does not contain PASSWORD/ACCOUNT numbers so the user cannot be changed.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56580I DELETED

Explanation: Normal completion occurred.

USERID *user_id* DELETED

Explanation: Normal completion occurred. The user has been deleted.

Module: IKJEFA30, IKJEFA32

Program: ACCOUNT/DELETE

IKJ56581I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: GETMAIN failed. The user must logon with a larger region.

Module: IKJEFA30

Program: ACCOUNT

IKJ56582I COMMAND SYSTEM ERROR + PUTLINE ERROR CODE *error_code* STOW ERROR CODE *error_code* PARSE ERROR CODE *error_code* READ ERROR CODE *error_code* FREESPACE ERROR CODE *error_code* WRITE ERROR CODE *error_code* BACKSPACE ERROR CODE *error_code*

Explanation: An invalid service routine return code was returned.

Module: IKJEFA30, IKJEFA32

Program: ACCOUNT/DELETE

IKJ56583I USER ATTRIBUTE DATA SET NOT USABLE + CANNOT OPEN DATA SET

Explanation: OPEN failed for SYSUADS. The file was not allocated.

BLDL I/O ERROR

Explanation: DELETE received a return code of 8 from BLDL.

STOW I/O ERROR

Explanation: DELETE received a return code of 16 from STOW.

Module: IKJEFA30, IKJEFA32

Program: ACCOUNT/DELETE

IKJ56584I COMMAND NOT FOUND. REQUIRED DDNAME *ddname* IS NOT ALLOCATED.

Explanation: A CLIST or REXX exec to be implicitly executed could not be found because the *ddname* was not allocated, although the ALTLIB level that corresponds to this *ddname* is still active.

User response: If you want this ALTLIB level to be active, allocate the *ddname* again. You can use the data set that contains the CLIST or REXX exec to be executed.

If you do not want this ALTLIB level to be active, issue the ALTLIB command with the DEACTIVATE operand for the appropriate level.

IKJ56585I • IKJ56590I

Then you can implicitly execute the CLIST or REXX exec again.

Module: IKJCT43D

Audience: Exec user

IKJ56585I [text]xx... NOT FOUND AS SPECIFIED

Explanation: For the item *text* could appear the following:

- *text* = USERID
- *text* = PASSWORD
- *text* = ACCT NUMBER
- *text* = PROC NAME

The UADS structure described in the nodelist could not be located. The value *xx...* is the highest-level item not found.

Module: IKJEFA32

Program: ACCOUNT/DELETE

IKJ56586I UNABLE TO DELETE, USERID IN USE

Explanation: ENQUEUE return code was 4. The user is logged on and cannot be updated.

Module: IKJEFA30

Program: ACCOUNT/DELETE

IKJ56587I INVALID (NODELIST) + NODELIST IS USERID/PASSWORD/ACCTNUMBER

Explanation: The nodelist was not specified correctly.

USER ATTRIBUTE STRUCTURE IS USERID, PASSWORD, ACCTNMBR, PROCNAME

Explanation: The nodelist was not specified correctly.

Module: IKJEFA30

Program: ACCOUNT/DELETE

IKJ56588I UNABLE TO DELETE FOR USERID *user_id*, [text] NOT SUPPORTED

Explanation: For the item *text* could appear the following:

- *text* = PASSWORDS
- *text* = ACCT NUMBERS

The user does not have password/account number support. This user was not modified.

UNABLE TO DELETE, PASSWORDS/ACCOUNT NUMBERS NOT SUPPORTED FOR ANY USER

Explanation: No PASSWORD/ACCOUNT number support was found for any user. No users were modified.

Module: IKJEFA32

Program: ACCOUNT/DELETE

IKJ56590I LISTED

Explanation: Normal completion occurred.

Module: IKJEFA40, IKJEFA42

Program: ACCOUNT/LIST

IKJ56591I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: GETMAIN failed. The user must logon with a larger region.

NOT ENOUGH MAIN STORAGE TO LIST FOR USERID *id*

Explanation: GETMAIN failed attempting to read in the user ID. The user must logon with a larger region.

Module: IKJEFA40, IKJEFA42

Program: ACCOUNT/LIST

IKJ56592I COMMAND SYSTEM ERROR + PARSE ERROR CODE *error_code* PUTLINE ERROR CODE *error_code* READ ERROR CODE *error_code*

Explanation: An invalid service routine return code was returned.

Module: IKJEFA40, IKJEFA42

Program: ACCOUNT/LIST

IKJ56593I USER ATTRIBUTE DATA SET NOT USABLE + CANNOT OPEN DATA SET

Explanation: OPEN failed for SYSUADS. The file was not allocated.

BLDL ERROR CODE *error_code*

Explanation: LIST received a return code of 8 from BLDL.

Module: IKJEFA40, IKJEFA42, IKJRBBBCR

Program: ACCOUNT/LIST, ACCOUNT/SYNC

IKJ56594I THE SYNC COMMAND PROCESSOR ENDED DUE TO ABEND CODE *abend_code*, REASON CODE *reason_code*

Explanation: The ACCOUNT executor routine invoked the SYNC command processor, which ended with the abend and reason code listed in the message.

Module: IKJEFA00

Program: ACCOUNT

IKJ56595I [*text*]*xx...* NOT FOUND AS SPECIFIED BY NODLIST

Explanation: For the item *text* could appear the following:

- *text* = USERID
- *text* = PASSWORD
- *text* = ACCT NUMBER
- *text* = PROC NAME

The UADS structure described in the nodelist could not be located. The value *xx...* is the highest-level item not found.

Module: IKJEFA40, IKJEFA42

Program: ACCOUNT/LIST

IKJ56596I UNABLE TO CHANGE FOR USERID *user_id*, NEW NAME WILL OCCUR MORE THAN 255 TIMES

Explanation: The ACCOUNT NUMBER/PROCEDURE name is being referred to by more than 255 passwords/account numbers.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56597I • IKJ56603I

IKJ56597I UNABLE TO CHANGE, INCOMPLETE COMMAND ENTERED

Explanation: Some of the information needed to execute a change command is missing.

UNABLE TO CHANGE, ASTERISK INVALID FOR NEW ACCOUNT NUMBER

Explanation: The datalist account number cannot be specified as an asterisk.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56598I UNABLE TO CHANGE, [text] NOT SUPPORTED FOR ANY USER. UNABLE TO DELETE FOR USERID user_id, [text] NOT SUPPORTED

Explanation: For the item *text* could appear the following:

- *text* = PASSWORDS
- *text* = ACCT NUMBERS

The level specified in the nodelist is not supported for any user.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56599I UNABLE TO CHANGE, NEW NAME EQUALS OLD NAME

Explanation: The last name in the nodelist is the same as the name in the datalist.

Module: IKJEFA20

Program: ACCOUNT/CHANGE

IKJ56600I UNRECOVERABLE COMMAND SYSTEM ERROR

Explanation: An attempt to reestablish TMP processing has failed and the TMP task is being terminated.

Module: IKJEFT05

Program: TMP

IKJ56601I COMMAND SYSTEM RESTARTING DUE TO CRITICAL ERROR

Explanation: An attempt to reinitialize command processing failed and the TMP is being reinitialized to request a new command.

Module: IKJEFT05

Program: TMP

IKJ56602I COMMAND SYSTEM RESTARTING DUE TO ERROR

Explanation: TMP task processing failed and command processing is being reinitialized to request a new command.

If this message is accompanied by return code 24, reason code -1, after the ATTN key was pressed during the execution of an authorized command, then this error can be ignored.

Module: IKJEFT05

Program: TMP

IKJ56603I ABEND *abend_code*

Explanation: A failure occurred in a TMP task and insufficient space is available for standard messages (IKJ56600I, IKJ56601I, or IKJ56602I). The TMP task is being terminated. Sxxx is for system error codes and Uxxx for user generated error codes.

Module: IKJEFT05

Program: TMP

IKJ56604I ABEND *abend_code*

Explanation: A failure occurred in a command task and insufficient space is available for standard message (IKJ56641I). The TMP task is being terminated. Sxxx is for system error codes and Uxxx for user generated error codes.

Module: IKJEFT04

Program: TMP

IKJ56605I ATTENTION INTERRUPTS WILL NOT BE PROCESSED UNTIL THE FIRST COMMAND FROM THE LOGON PROCEDURE HAS COMPLETED

Explanation: An attention interrupt occurred while the first command from the logon procedure was processing. The attention is ignored and all subsequent attentions will be ignored until the first command has completed.

Note: There is a difference between CLIST and REXX EXEC processing. If the first command is a REXX EXEC, the EXEC command remains active when the REXX EXEC runs. Once it ends, REXX returns to the EXEC command and the EXEC command ends. If the first command is a CLIST, the EXEC command will place the CLIST on the TSO/E command stack and then end.

Module: IKJEFT03

Program: TMP

IKJ56606I TSO/E attn processing ended due to error. RC= *return_code*

Explanation: The system recognized the user's attention interrupt, but incurred a system error during interrupt processing.

System action: TSO/E considers this error to be serious and terminates.

User response: Contact your system programmer to diagnose problems with TSO/E attention processing.

Module: IKJSATTN

Audience: If the error continues, contact your local support personnel or IBM support personnel for further assistance.

IKJ56607I TSO/E attn processing ended due to error. RC= *return_code* ERROR= *error_code*

Explanation: The system recognized the user's attention interrupt, but incurred a system error during interrupt processing.

System action: TSO/E considers this error to be serious and terminates.

User response: Contact your system programmer to diagnose problems with TSO/E attention processing.

Module: IKJSATTN

Audience: If the error continues, contact your local support personnel or IBM support personnel for further assistance.

IKJ56608I TSO/E attn processing ended due to error. RC= *return_code* ABEND = *abend_code* REASON= *reason_code*

Explanation: The system recognized the user's attention interrupt, but incurred a system error during interrupt processing.

System action: TSO/E considers this error to be serious and terminates.

User response: Contact your system programmer to diagnose problems with TSO/E attention processing.

Module: IKJSATTN

IKJ56609I • IKJ56612I

Audience: If the error continues, contact your local support personnel or IBM support personnel for further assistance.

IKJ56609I TSO/E attn processing ended due to error. RC= *return_code* ERROR= *error_code* ABEND= *abend_code*
REASON= *reason_code*

Explanation: The system recognized the user's attention interrupt, but incurred a system error during interrupt processing.

System action: TSO/E considers this error to be serious and terminates.

User response: Contact your system programmer to diagnose problems with TSO/E attention processing.

Module: IKJSATTN

Audience: If the error continues, contact your local support personnel or IBM support personnel for further assistance.

IKJ56610I The requested command or program could not be invoked. + The environment in which the command was to run was not valid.

Explanation: An attempt was made to invoke an authorized command, program, or service that is not permitted to run in the current environment. TSO/E does not permit authorized commands, programs, or services to run when outstanding asynchronous APPC/MVS requests exist. The TSO/E terminal monitor program checked for any existing asynchronous APPC/MVS requests and found that at least one such request did exist.

System action: The requested command, program, or service was not permitted to run. This message is issued, and a return code is set to a value that indicates that the function failed.

User response: It is possible that a service that you invoked before invoking the requested command, program, or service requested the outstanding asynchronous APPC/MVS request. If you log off and log on again, the system will clean up the request automatically. You should also report this problem to your system programmer.

Module: IKJEFT01

Audience: TSO/E user

Program: TMP

IKJ56611I The requested command or program could not be invoked. + The ATBAMR1 routine gave return code *return_code*.

Explanation: An attempt was made to invoke an authorized command, program, or service that is not permitted to run in the current environment. Authorized commands, programs, and services are not permitted to run when outstanding asynchronous APPC/MVS requests exist. The TSO/E terminal monitor program attempted to check for any existing asynchronous APPC/MVS requests, but the service that it invoked gave an unexpected return code.

System action: The requested command, program, or service was not permitted to run. This message is issued, and the return code is set to a value that indicates that the function failed.

User response: Check the return code that appears in the message. Take the action prescribed for the error as documented in *z/OS MVS Programming: Writing Transaction Programs for APPC/MVS* for the ATBAMR1 routine.

Module: IKJEFT01

Audience: TSO/E user

Program: TMP

IKJ56612I IKJURPS processing ended due to error. RC=*xx* or IKJURPS processing ended due to error. RC=*xx*
ERROR=*yy* or IKJURPS processing ended due to error. RC=*xx* ABEND=*abend_code*
REASON=*reason_code*

Explanation: IKJURPS was unable to process the request.

System action: IKJURPS does not process the request.

User response: Diagnose the error based on the code or codes you received on the message.

Module: IKJURPS

Audience: Application Programmer

IKJ56613I **The command has terminated. MVS/ESA version or higher level is required for keyword.**

Explanation: TSO/E is not able to process the request because the version or release of MVS is not at the indicated level or higher.

System action: TSO/E does not process the request.

User response: None.

Module: IKJCNPRF, IKJCNSOL, IKJEFT82, IKJPRMLB

IKJ56614I **The requested command or program could not be invoked.+ The Miscellaneous Event Exit Manager found unauthorized asynchronous activity.**

Explanation: An attempt was made to invoke a command, program, or service that is not permitted to run in the current environment. TSO/E does not permit commands, programs, or services to run in an isolated environment (for example, running an authorized command or program) when outstanding unauthorized activity exist.

The TSO/E terminal monitor program checked for any existing asynchronous unauthorized activity and found, that at least one such request did exist.

System action: The requested command, program, or service was not permitted to run. This message is issued, and a return code is set to a value that indicates that the function failed.

User response: It is possible that a service that you invoked before invoking the requested command, program, or service requested the outstanding asynchronous unauthorized activity. If you log off and log on again, the system will clean up the request automatically. If the error continues, contact your local support personnel for further assistance.

Module: IKJEFT01

Audience: TSO/E user

Program: TMP

IKJ56615I **The requested command or program could not be invoked.+ The Miscellaneous Event Exit Manager gave return_code**

Explanation: An attempt was made to invoke a command, program, or service that is not permitted to run in the current environment. TSO/E does not permit commands, programs, or services to run in an isolated environment (for example, running an authorized command or program) when outstanding unauthorized activity exist.

The TSO/E terminal monitor program attempted to check for any existing asynchronous activity, but the service that it invoked indicated that it encountered an unexpected error.

System action: The requested command, program, or service was not permitted to run. This message is issued, and the return code is set to a value that indicates that the function failed.

User response: Contact your local support personnel or IBM service personnel to diagnose the problem with the outstanding asynchronous unauthorized activity.

Module: IKJEFT01

Audience: TSO/E user

Program: TMP

IKJ56620I *[text]* **command encountered. TSO/E session is terminated.**

Explanation: For *[text]* could appear the following:

- MVS STOP

The TSO/E IKJEFT01 TMP found that an MVS STOP command was issued for this address space. Note that this message is only issued when the IKJEFT01 TMP detects the STOP command.

IKJ56621I • IKJ56626I

- MVS MODIFY

The TSO/E IKJEFT01 TMP found that an MVS MODIFY command was issued for this address space, that was neither STOP nor MODIFY. Note that this message is only issued when the IKJEFT01 TMP detects the command

- unknown MVS operator

The TSO/E IKJEFT01 TMP found that an MVS command was issued for this address space, that was neither STOP nor MODIFY.

If another program is processing commands under the IKJEFT01 TMP (that is, the IKJEFT01 TMP is not processing the commands directly), then the command may not be detected until the IKJEFT01 TMP re-gains control.

System action: The TMP stops processing of this session and returns to its caller.

User response: This message is for your information to indicate how the TSO/E session was terminated.

Module: IKJEFT02

Audience: TSO/E user

Program: TMP

IKJ56621I INVALID COMMAND NAME SYNTAX

Explanation: Command scan found a syntactical error in the command name.

User response: Make sure that the command name meets the following syntax requirements:

See the chapter about verifying command and subcommand names with command scan service routine in *z/OS TSO/E Programming Services* for more information.

Module: IKJEFT02

Program: TMP

IKJ56622I COMMAND NOT FOUND

Explanation: A syntactically correct command name cannot be located by the system.

Module: IKJEFT02

Program: TMP

IKJ56623I *command_name* IS UNSUPPORTED COMMAND NAME IN BACKGROUND

Explanation: The command entered is not supported for use in background mode.

Module: IKJEFT02

Program: TMP

IKJ56625I TSOLOGON TERMINATED. IKJEF3LD3 RETURNED TOO FEW JCL STATEMENTS.

Explanation: Your installation supplied incorrect data to TSO/E.

System action: Logon processing is terminated.

User response: Contact your system programmer and supply the message that you received.

Module: IKJEF3LE3

Audience: TSO/E user

IKJ56626I TSOLOGON TERMINATED. IKJEF3LD3 RETURNED A JCL BUFFER LENGTH THAT IS NOT VALID.

Explanation: Your installation supplied incorrect data to TSO/E.

System action: Logon processing is terminated.

User response: Contact your system programmer and supply the message that you received.

Module: IKJEFLE3

Audience: TSO/E user

IKJ56629A ENTER NEW PASSWORD

Explanation: The new password option was selected. New password should be entered in the PASSWORD field.

System action: The system prompts for a new password.

User response: Enter a valid new password.

Module: IKJEFLE

Audience: TSO/E user

IKJ56637I You attempted to run a command, program, CLIST, or REXX exec from an authorized environment. This is not supported under the dynamic TSO/E environment.

Explanation: You are running in an address space with a TSO/E environment created by the TSO/E environment service. You asked to use the TSO/E service facility to invoke a command, program, CLIST, or REXX exec from an authorized TSO/E environment. This function is not available in this environment.

System action: This message is issued with an accompanying return code from the TSO/E service facility. The return code is 20 and the reason code is 68 from the TSO/E service facility.

User response: Remove the invocation.

Module: IKJEFTS2

Audience: Application programmer

IKJ56639I *abend_type* **ABEND CODE** *abend_code* **REASON CODE** *reason_code*

Explanation: An unexpected error occurred in the TSO/E table lookup service causing it to abnormally terminate.

System action: The table lookup service terminates.

User response: Contact your system programmer for assistance in diagnosing problems with the table lookup service.

Module: IKJTBL5

Audience: TSO/E user

Program: TMP

IKJ56640I *abend_type* **ABEND CODE** *abend_code* **REASON CODE** *reason_code* **or** *abend_type* **ABEND CODE** *abend_code* **REASON CODE** *reason_code* **PSW** *zzzzzzzzzzzzzzzzzz* **ASIDS: HOME=hhhh PRIMARY=pppp SECONDARY=ssss +**

Explanation: The shorter form of this message appears when a program abnormally terminates in its home address space while running under TSO/E TEST, or when TEST is issued for an abnormally terminating program which is in its home address space.

The longer form of this message is issued for a program executing in cross-memory mode that abnormally terminates while running under TSO/E TEST or for an abnormally terminating program for which TSO/E TEST has been issued. The TEST command cannot be used to restart the program in cross-memory mode.

TSO/E TEST DOES NOT RE-ESTABLISH THE CROSS MEMORY ENVIRONMENT THAT EXISTED AT THE TIME OF THE ABEND

Explanation: You cannot use TSO/E TEST to restart a program that terminated abnormally in the cross-memory environment. However, it can be used to display the contents of general purpose registers at the time of the abend.

Module: IKJEFT04

Program: TEST

IKJ56641I *program* ENDED DUE TO ERROR +**Explanation:** The program or command processor and its associated task is terminated.

If the program failed while you were using the TSO/E TEST facility, no plus sign appears after the message. Use TSO/E TEST subcommands to find the error.

If a plus sign appears after the message, enter a ? to obtain more information about the error. To use the TSO/E TEST facility for debugging, issue the TEST command.

abend_type ABEND CODE *abend_code* REASON CODE *reason_code*

or

abend_type ABEND CODE *abend_code* REASON CODE *reason_code* PSW *zzzzzzzzzzzzzzzzzzzz* ASIDS: HOME=*hhhh*
PRIMARY=*pppp* SECONDARY=*ssss*

Explanation: The shorter version of this message is issued when a program executing under TSO/E terminates abnormally in its home address space. Issue TEST after such an abend to display, update, or execute data or code.

The longer version of this message is issued for an abend within a cross memory environment. TSO/E considers a program to be in cross memory mode when either the address space selection bit in the PSW is on or when the home, primary, and secondary ASIDs are not all equal. If you issue TEST after abending in the cross memory environment, you can use TEST to update, display, or execute data or code only if that data or code is in the home address space.

Note: If the program that failed does not issue reason codes with the identified abend code, the reason code displayed in the secondary message is not valid.**Module:** IKJEFT04**Program:** TMP/TEST

IKJ56642I USER NOT AUTHORIZED TO DATASET + SYSTEM ABEND CODE *abend_code* REASON CODE *reason_code***Explanation:** The command task attempted to reference a data set to which the user is not authorized by the security system. See *z/OS MVS System Codes* for a description of abend codes.**Module:** IKJEFT04**Program:** TMP

IKJ56643I APF PROGRAM IN FORCE, TEST REQUEST REJECTED**Explanation:** The user entered a TEST command (without operands) following an abend in an APF-authorized command task.**Module:** IKJEFT02**Program:** TMP

IKJ56644I NO VALID TSO USERID, DEFAULT USER ATTRIBUTES USED**Explanation:** If RACF is installed, a background job will be run using the minimum default user attributes. Either the user ID was unidentifiable, or no user ID was specified as a JOB card parameter, or allocation of the user attributes data set (SYS1.UADS) failed.**Note:** An unidentifiable user ID can be a user ID that is greater than seven characters. If RACF or its equivalent is not active, then the system always issues this message.**Module:** IKJEFT01**Program:** TMP

IKJ56646I IKJEFRAF FAILED - RETURN CODE *return_code*.

Explanation: IKJEFRAF passed an unexpected return code to IKJEFT01. The UPT, and other information associated with the user id could not be obtained. This message will be followed by IKJ56644, which indicates that the default user attributes will be used.

Module: IKJEFT01

Program: TMP

IKJ56647I RACF IS INACTIVE.

Explanation: RACF was not active, so the UPT and other information associated with the user ID could not be obtained. This message will be followed by IKJ56644, which indicates that the default user attributes will be used.

Module: IKJEFT01

Program: TMP

IKJ56648I UNEXPECTED RACF *function* ERROR *error_code* REASON CODE *reason_code*

Explanation: The TSO/E RACF routine IKJEFRAF was trying to obtain or verify user ID information via the indicated RACF function. The RACF function could not obtain or verify the information and passed back an error and reason code. This message will be followed by IKJ56644 which indicates that the default user attributes will be used.

Module: IKJEFT01

Program: TMP

IKJ56649I ATTENTION PROCESSING ENDED DUE TO ERROR +

Explanation: CLIST attention facility processing ended unsuccessfully. Following the primary message, you will receive a message telling you whether the error was a system ABEND or a user ABEND.

SYSTEM ABEND CODE *abend_code* **REASON CODE** *reason_code*

Explanation: If the message text indicates a system ABEND, see *z/OS MVS System Codes*. for an explanation of the ABEND and reason codes.

USER ABEND CODE *abend_code* **REASON CODE** *reason_code*

Explanation: The following user ABENDs are issued by the CLIST attention facility. The reason code will contain the unexpected return codes of the TSO/E service routine as described below:

- ABEND 600 indicates that an unexpected return code was passed back from issuing STAX.
- ABEND 601 indicates that an unexpected return code was passed back from issuing STACK.
- ABEND 602 indicates that an unexpected return code was passed back from issuing PUTGET.

User ABEND 304 is issued by the terminal monitor program, and indicates that the CLIST attention facility terminated abnormally.

IKJ56650I TIME - *hh:mm:ss* CPU - *hh:mm:ss* SERVICE - *number* SESSION - *hh:mm:ss* MONTH DAY, YEAR

Explanation: The TIME command was entered.

Module: IKJEFT25

Program: TIME

IKJ56651I TIME FUNCTION CANNOT BE PERFORMED BECAUSE OF INOPERATIVE CLOCK

Explanation: The hardware clock is inoperative.

Module: IKJEFT25

Program: TIME

IKJ56652I • IKJ56660I

IKJ56652I You attempted to run an authorized command or program. This is not supported under the dynamic TSO/E environment.

Explanation: You are running in an address space with a TSO/E environment created by the TSO/E environment service. You tried to invoke an authorized command or program using the TSO/E service facility. This function is not available in this environment.

System action: This message is issued with an accompanying return code from the TSO/E service facility. The return code is 20 and the reason code is 68 from the TSO/E service facility.

User response: Remove the invocation.

Module: IKJEFTS2

Audience: Application programmer

IKJ56655I NO OPERANDS, COMMAND IGNORED

Explanation: No operands were specified with the TERMINAL command.

Module: IKJEFT80

Program: TERMINAL

IKJ56656I INVALID LINESIZE OPERAND, USE SCRSIZE

Explanation: The user specified the LINESIZE operand for the 2260-65 type terminal.

Module: IKJEFT80

Program: TERMINAL

IKJ56657I INVALID SCRSIZE OPERAND, USE LINESIZE

Explanation: The user specified the SCRSIZE operand for the 2741 type terminal.

Module: IKJEFT80

Program: TERMINAL

IKJ56658I SCREEN SIZE NOT STANDARD, SCREEN CONTROL ERROR MAY OCCUR

Explanation: The user specified a non-standard screen size for the 2260-65 type terminal.

Module: IKJEFT80

Program: TERMINAL

IKJ56659I BREAK INVALID FOR THIS TERMINAL

Explanation: The user specified the BREAK operand for a terminal that does not have the BREAK feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56660I NOBREAK INVALID FOR THIS TERMINAL

Explanation: The user specified NOBREAK for a terminal that does not have the break feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56661I TIMEOUT INVALID FOR THIS TERMINAL

Explanation: The TIMEOUT operand was specified for a terminal that does not have the timeout feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56662I NOTIMEOUT INVALID FOR THIS TERMINAL

Explanation: The user specified NOTIMEOUT for a terminal that does not have the feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56663I INVALID NUMBER OF ROWS

Explanation: The user specified the incorrect number of rows for the 2260-65 type terminal.

Module: IKJEFT80

Program: TERMINAL

IKJ56664I INVALID LENGTH OF ROW

Explanation: The user specified an invalid length for the 2260-65 type terminal.

Module: IKJEFT80

Program: TERMINAL

IKJ56665I [*text*] INVALID FOR THIS TERMINAL

Explanation: For the item *text* could appear the following:

- *text* = CLEAR
- *text* = NOCLEAR

The CLEAR or NOCLEAR parameter was specified for a terminal that does not support this feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56666I [*text*] INVALID FOR THIS TERMINAL

Explanation: For the item *text* could appear the following:

- *text* = INPUT
- *text* = NOINPUT

The INPUT or NOINPUT parameter was specified for a terminal that does not support this feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56668I TRANSLATE TABLE SIZE LESS THAN 516 BYTES

Explanation: The user specified a translate table on the TRAN parameter that was less than 516 bytes in length.

Module: IKJEFT80

Program: TERMINAL

IKJ56669I [*text*] INVALID FOR THIS TERMINAL

Explanation: For the item *text* could appear the following:

- *text* = SECOND
- *text* = NOSECOND

The SECOND or NOSECOND parameter was specified for a terminal that does not support this feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56670I TRANSLATE TABLE MUST HAVE NUMBERS AND UPPERCASE LETTERS DEFINED

Explanation: The user specified a translate table on the TRAN parameter that did not have numbers and upper case letters defined. Even though translation is not allowed for numbers and uppercase letters, they must be included in the table, translated to themselves.

Module: IKJEFT80

Program: TERMINAL

IKJ56671I NOCHAR INVALID, DEFAULT TRANSLATE TABLE IN USE

Explanation: The NOCHAR parameter is valid only when installation-written translation tables are being used.

Module: IKJEFT80

Program: TERMINAL

IKJ56672I [*text*] INVALID FOR THIS TERMINAL

Explanation: For the item *text* could appear the following:

- *text* = LINE
- *text* = NOLINE

The LINE or NOLINE parameter was specified for a terminal that does not support this feature.

Module: IKJEFT80

Program: TERMINAL

IKJ56673I 'CHAR(*x*)/NOCHAR LINE(*x*)/NOLINE PROMPT/NOPROMPT INTERCOM/NOINTERCOM PAUSE/NOPAUSE MSGID/NOMSGID MODE/NOMODE WTPMSG/NOWTPMSG PREFIX *dsname prefix*)/NOPREFIX'

Explanation: This message is issued when the LIST operand is specified on the PROFILE command or no keywords were specified on the command.

Module: IKJEFT82

Program: PROFILE

IKJ56674I THE USER PROFILE DOES NOT SUPPORT LANGUAGES. ANY LANGUAGES ENTERED ARE IGNORED.

Explanation: You specified the PLANGUAGE, SLANGUAGE keywords, or both on the PROFILE command, but your version of the user profile table does not support languages.

System action: The language(s) entered are not processed. All other processing is done. No error condition occurs.

User response: If you want to specify languages, notify your system administrator that you received this message.

Module: IKJEFT82

Program: PROFILE

IKJ56675I YOUR INSTALLATION MUST AUTHORIZE USE OF THE EDIT RECOVER/NORECOVER FACILITY

Explanation: Your TSO/E administrator must authorize the use of this facility for your user id.

Module: IKJEFT82

Program: PROFILE

IKJ56676I PLANGUAGE/SLANGUAGE KEYWORD(S) CAN NOT BE USED BECAUSE THE MVS MESSAGE SERVICE IS NOT ACTIVE.

Explanation: You specified the PLANGUAGE, SLANGUAGE keywords, or both on the PROFILE command, but the MVS message service is not active. The MVS message service must be active to use languages.

System action: The user profile table is not updated and the PROFILE command ends with return code 12.

User response: Contact your system programmer to have the MVS message service activated.

Module: IKJEFT82

Program: PROFILE

IKJ56677I *language* IS NOT AN ACTIVE LANGUAGE.

Explanation: The language specified on the PLANGUAGE or SLANGUAGE keyword is currently not active or is unavailable on the system.

System action: The user profile table is not updated and the PROFILE command ends with return code 12.

User response: Check the language specified to make sure you entered it correctly. Either retry the command or ask your system programmer to activate the language on your system.

Module: IKJEFT82

Program: PROFILE

IKJ56678I THE LANGUAGE *language* COULD NOT BE PROCESSED. + THE MVS MESSAGE SERVICE RETURN CODE WAS *return_code* AND THE REASON CODE WAS *reason_code*.

Explanation: The PROFILE command attempted to process the indicated language but the MVS message service returned an unexpected return code.

System action: The user profile table is not updated and the PROFILE command ends with return code 12.

System programmer response: See *z/OS MVS Programming: Authorized Assembler Services Reference LLA-SDU* for an explanation of the return and reason codes. Take the action suggested for the particular return code.

User response: Note the message ID and the displayed return and reason codes. Contact your system programmer with this information.

Module: PROFILE

Program: PROFILE

IKJ56686I COMMAND SYSTEM ERROR +

Explanation: Parse return code was greater than 4.

[*text*] DELETE CHARACTERS CHANGED ONLY TEMPORARILY

- *text* = LINE
- *text* = CHARACTER

Explanation: SVC 100 failure occurred.

PARSE ERROR CODE *error_code*

Explanation: You entered a question mark after receiving the above message.

Module: IKJEFT82

IKJ56687I •

Program: PROFILE

IKJ56687I BS OR ATTN OR CTLX INVALID FOR THIS TERMINAL

Explanation: A non-zero return code was returned after an STCC macro was issued. The STCC macro establishes the non-character type of delete control characters for the TSO/E system.

Module: IKJEFT82

Program: PROFILE

IKJ56688I CHAR(x)/NOCHAR LINE(x)/NOLINE PROMPT/NOPROMPT INTERCOM/NOINTERCOM PAUSE/NOPAUSE MSGID/NOMSGID MODE/NOMODE WTPMSG/NOWTPMSG RECOVER/NORECOVER PREFIX (*dsname_prefix*)/NOPREFIX PLANGUAGE(*language*) SLANGUAGE (*language*) VARSTORAGE(HIGH/LOW)

Explanation: This message is issued when the LIST operand is specified on the PROFILE command or when no keywords are specified on the command. If your version of the user profile table does not support languages, this message displays ENU (US English) in the language fields by default. If your installation uses language support, the three-character language code is displayed.

Module: IKJEFT82

Program: PROFILE

IKJ56689I DEFAULT [*text*] DELETE CHARACTERS IN EFFECT FOR THIS TERMINAL

Explanation: For the item *text* could appear the following:

- *text* = LINE
- *text* = CHARACTER

The user entered an invalid character for the LINE or CHAR parameter.

Module: IKJEFT82

Program: PROFILE

IKJ56690I YOU ARE NOT AUTHORIZED TO USE THE [*text*] FACILITY YOUR INSTALLATION MUST AUTHORIZE USE OF THE EDIT RECOVER/NORECOVER FACILITY

Explanation: For the item *text* could appear the following:

- *text* = RECOVER
- *text* = NORECOVER

The user entered the RECOVER or NORECOVER parameter but was not authorized by the installation to use that facility.

Module: IKJEFT82

Program: PROFILE

IKJ56700A ENTER missing data

Explanation: The user did not enter needed information.

Module: IKJEFP00

Program: PARSE

ENTER JOB NAME OR JOBNAME(*JOBID*) +
ENTER ALPHANUMERIC NAME(S), WITH FIRST CHARACTER ALPHABETIC AND MAXIMUM
OF 8 CHARACTERS. JOBNAME IS THE NAME ON THE JOB CARD AND *JOBID* IS THE ID
ASSIGNED BY THE JOB ENTRY SUBSYSTEM AT THE TIME THE JOB WAS SUBMITTED.

Explanation: The parse service routine is prompting the user because the CANCEL or STATUS command is

incorrect as entered. The *jobname* or *jobname(jobid)* is invalid or (for CANCEL only) no *jobname* or *jobname(jobid)* was specified.

CANCEL supplies the text of the second-level message as a parse PCL in CSECT IKJEFF4A of assembly module IKJEFF49. STATUS has second-level text in CSECT IKJEFF5A of assembly module IKJEFF50.

Module: IKJPARS

Program: CANCEL/STATUS

ENTER DATA SET NAME

Explanation: A data set name was not given or an incorrect one was entered. (Parse prompts for the data set name.)

Module: IKJEFG00

Program: CALL

ENTER MEMBER NAME

Explanation: An incorrect member name was specified (it could not be found in the data set). (Parse prompts for the member name.)

Module: IKJEFG00

Program: CALL

ENTER DATA SET NAME

Explanation: The EXEC command was entered without a data set name or with an invalid data set name. (Parse prompts for the data set name.)

Module: IKJPARS

Program: EXEC

ENTER FILE NAME

Explanation: The FILE keyword was specified without a ddname.

Module: IKJEFD20

Program: FREE

ENTER DATA SET NAME

Explanation: A dsname was missing or invalid. (Parse prompts for the data set name.)

Module: IKJEFD20

Program: FREE

ENTER JOBNAME OR JOBNAME(JOBID) + ENTER JOBNAME OF PREVIOUSLY SUBMITTED JOB

Explanation: Parse detected the absence of the required 'jobname' parameter.

Module: IKJPARS

Program: OUTPUT

ENTER CLASS NAME

Explanation: The required subfield was missing for the CLASS keyword.

Module: IKJPARS

Program: OUTPUT

ENTER NEW CLASSNAME

Explanation: The required subfield was missing for the NEWCLASS keyword.

Module: IKJPARS

Program: OUTPUT

ENTER REMOTE STATION ID FOR THE DEST KEYWORD

Explanation: The required subfield for the DEST keyword was missing.

Module: IKJPARS

Program: OUTPUT

**ENTER DATA SET NAME +
ENTER NAME OF DATA SET TO RECEIVE SAVE AREA**

Explanation: Parse detected the absence of the required 'data set name' parameter on the SAVE subcommand.

Module: IKJPARS

Program: OUTPUT

ENTER OLD DATA SET NAME

Explanation: The old data set name was not entered.

Module: IKJEHRN2

Program: RENAME

ENTER NEW DATA SET NAME

Explanation: The new data set name was not entered.

Module: IKJEHRN2

Program: RENAME

ENTER NAME OF DATA SET TO BE RENAMED

Explanation: The data set to be renamed was not entered.

Module: IKJEHRN2

Program: RENAME

ENTER NEW NAME TO BE GIVEN THE DATA SET

Explanation: The data set name was not entered.

Module: IKJEHRN2

Program: RENAME

**ENTER LIBRARY DATA SET NAME +
ENTER NAME OF LIBRARY CONTAINING ROUTINES USED BY YOUR PROGRAM**

Explanation: The LIB operand was entered without any data set names.

Module: IKJEFR00

Program: RUN

**ENTER DATA SET NAME +
ENTER NAME OF DATA SET CONTAINING JCL**

Explanation: The SUBMIT command was entered without a data set name field.

Module: IKJPARS

Program: SUBMIT

ENTER INPUT STRING, MAXIMUM IS 4

Explanation: The user entered the INPUT keyword on the TERMINAL command without entering a value.

Module: IKJEFP00

Program: TERMINAL

ENTER STRING TO BE USED FOR ATTENTION

Explanation: The user entered a question mark in response to the first message.

Module: IKJEFP00

Program: TERMINAL

ENTER CLEAR STRING, MAXIMUM IS 4

Explanation: The user entered the CLEAR keyword with the TERMINAL command without entering a value.

Module: IKJEFP00

Program: TERMINAL

ENTER STRING TO BE USED TO CLEAR SCREEN

Explanation: The user entered a question mark in response to the first message.

Module: IKJEFP00

Program: TERMINAL

ENTER LINESIZE, MAXIMUM IS 255

Explanation: The user entered the LINESIZE keyword on the TERMINAL command and did not enter a value.

Module: IKJEFP00

Program: TERMINAL

ENTER LENGTH OF LINE

Explanation: The user responded to the first message with a question mark.

Module: IKJEFP00

Program: TERMINAL

ENTER NUMBER OF SECONDS, MAXIMUM IS 2550

Explanation: The user entered the SECONDS keyword on the TERMINAL command with no value.

Module: IKJEFP00

Program: TERMINAL

ENTER NUMBER OF SECONDS TO ELAPSE BEFORE ATTENTION

Explanation: The user entered a question mark as a response to the first message.

Module: IKJEFP00

Program: TERMINAL

ENTER NUMBER OF LINES, MAXIMUM IS 255

Explanation: The user entered the LINES keyword with no value.

Module: IKJEFP00

Program: TERMINAL

ENTER NUMBER OF LINES TO PRINT BEFORE ATTENTION

Explanation: The user entered a question mark to the first message.

Module: IKJEFP00

Program: TERMINAL

ENTER LENGTH OF ROW, MAXIMUM IS 255

Explanation: The user entered a question mark in response to IKJ56664I.

Module: IKJEFP00

Program: TERMINAL

ENTER NUMBER OF ROWS, MAXIMUM IS 255

Explanation: The user entered a question mark in response to message IKJ56663I.

Module: IKJEFP00

Program: TERMINAL

**ENTER 1 TO 4 DIGIT INTEGER +
ENTER 1 TO 4 CHARACTER NUMERIC VALUE TO WHICH PREVIOUS COMMAND RETURN
CODE WILL BE COMPARED**

Explanation: The WHEN command was entered without a return code or with an invalid return code. (Parse prompts for the value.)

**ENTER 1 OR 2 CHARACTER OPERATOR +
ENTER VALID OPERATOR: EQ NE LT GT NL NG LE GE**

Explanation: WHEN command was entered without an operator or with an invalid operator. (Parse prompts for the operator.)

Module: IKJPARS

Program: WHEN/END

**ENTER INTEGER FROM 0 TO 99 OR CONSOLE NAME SPECIFYING CONSOLE IDENTIFIER OF
CONSOLE TO RECEIVE MESSAGE**

Explanation: There was a missing or incorrect parameter for the console identifier (CN) operand.

IKJ56701I MISSING missing data

Explanation: The user did not enter needed information and is in no-prompt mode.

Explanation: There was a missing or incorrect parameter for the console identifier (CN) operand.

MISSING INTEGER FROM 0 TO 99 SPECIFYING CONSOLE IDENTIFIER OF CONSOLE TO RECEIVE MESSAGE

Explanation: There was a missing or incorrect parameter for the console identifier (CN) operand. This message is displayed only when TSO/E is running in an MVS/ESA SP 3 environment.

Module: IKJEFP00

Program: PARSE

MISSING INTEGER FROM 0 TO 99 OR CONSOLE NAME SPECIFYING CONSOLE IDENTIFIER OF CONSOLE TO RECEIVE MESSAGE

IKJ56702A (The following messages are some of the second-level messages for message IKJ56702I. IKJ56702A is the message identifier for all these second-level messages.) ENTER A CORRECT NONDUPLICATE ATTR-LIST-NAME

Explanation: There was a missing or invalid parameter.

ENTER A DECIMAL NUMBER FROM 0 TO 99

Explanation: There was a missing or incorrect parameter for the number-of-channel-programs operand. TSO/E is running in an environment below MVS/ESA SP 4.3.0.

ENTER A DECIMAL NUMBER FROM 0 TO 255

Explanation: There was a missing or invalid parameter for the number-of-channel-programs operand.

ENTER A DECIMAL NUMBER FROM 0 TO 255 (254 FOR JES3 SYSTEMS)

Explanation: There was a missing or invalid parameter for the numbers of COPIES operand. JES2 Systems allow a maximum value of 255; JES3 Systems allow a maximum value of 254.

ENTER A DECIMAL NUMBER FROM 0-32760 OR CHARACTER X

Explanation: There was a missing or invalid parameter for the logical record length operand.

ENTER A JULIAN DATE IN YYDD FORMAT

Explanation: There was a missing or invalid parameter for the expiration date operand.

ENTER INTEGER FROM 0 TO 99 OR CONSOLE NAME SPECIFYING CONSOLE IDENTIFIER OF CONSOLE TO RECEIVE MESSAGE

Explanation: There was a missing or incorrect parameter for the console identifier (CN) operand.

ENTER INTEGER FROM 0 TO 99 SPECIFYING CONSOLE IDENTIFIER OF CONSOLE TO RECEIVE MESSAGE

Explanation: There was a missing or incorrect parameter for the console identifier (CN) operand. This message is displayed only when TSO/E is running in an MVS/ESA SP 3 environment.

ENTER A DECIMAL NUMBER FROM 0-93000

Explanation: There was a missing or invalid parameter for the retention period operand.

ENTER A DECIMAL NUMBER FROM 0-99 OR A CHARACTER L

Explanation: There was a missing or invalid parameter for the buffer offset operand.

ENTER A NUMBER FROM 0-4

Explanation: There was a missing or invalid parameter for the tape density operand.

ENTER A NUMBER LESS THAN [text]

Explanation:

- *text* = 65535
- *text* = 2096129

IKJ56702I • IKJ56708I

The number you specified on the MAXSIZE () or SIZE () parameter of the ACCOUNT command is incorrect. The parameter indicates the region size in 1 K (1024) byte units. Retype a number less than 2096129.

Module: IKJEFP00

Program: PARSE

IKJ56702I INVALID invalid data

Explanation: The user entered invalid data.

Module: IKJEFP00

Program: PARSE

IKJ56703A REENTER THIS OPERAND

Explanation: If the user is in prompt mode, he is prompted with this message until he enters the correct information or the processing of the command is stopped.

Module: IKJEFP00

Program: PARSE

IKJ56704I *data* IS AMBIGUOUS

Explanation: The user entered unnecessary information according to the way the information was specified on the parse macro instructions.

Module: IKJEFP00

Program: PARSE

IKJ56705I MISSING PASSWORD FOR *user_id*

Explanation: The user did not enter the required password with the LOGON command and is in no-prompt mode.

Module: IKJEFP00

Program: PARSE

IKJ56706I ENDING QUOTE ASSUMED, *data*

Explanation: The user did not enter an ending quote and the end of the buffer is reached. The quote is assumed at the end of the buffer.

Module: IKJEFP00

Program: PARSE

IKJ56707I RIGHT PARENTHESIS ASSUMED, *data*

Explanation: The user omitted the right parenthesis. It is assumed to be at the end of the buffer.

Module: IKJEFP00

Program: PARSE

IKJ56708I INVALID CURRENT PASSWORD, *password*

Explanation: The user has entered a non-alphanumeric character in a password or the password is more than eight characters in length.

Module: IKJEFP00

Program: PARSE

IKJ56709I **INVALID DATA SET NAME**, *dsname*

Explanation: The user entered an invalid data set name.

Module: IKJEFP00

Program: PARSE

IKJ56710I **INVALID USERID**, *user_id*

Explanation: The user entered an invalid *user_id*, an eight character or longer *user_id*, or one that is not defined to the system.

Module: IKJEFP00

Program: PARSE

IKJ56711I **INVALID ADDRESS**, *adr*

Explanation: The user entered an invalid address or expressed the address in the wrong way.

Module: IKJEFP00

Program: PARSE

IKJ56712I **INVALID KEYWORD**, *keyword*

Explanation: The user entered an invalid keyword, or a keyword that is not supported by the current TSO/E release, or a keyword that is not supported by the current MVS/ESA SP level.

Module: IKJEFP00

Program: PARSE

IKJ56713I **INVALID VALUE**, *value*

Explanation: The user entered an invalid value (operand on IKJPOSIT macro).

Module: IKJEFP00

Program: PARSE

IKJ56714A **Enter current password for** *user_id*

Explanation: The user did not enter a password after *user_id* and slash.

Enter current password for *user_id* — **New password will be ignored.**

Explanation: The user entered and verified a new password before entering the existing password. This new password will be ignored when the current password is entered.

Module: IKJEFP00

Program: PARSE

IKJ56715I **INVALID STRING**, *string*

Explanation: The user entered invalid string information. A string is an operand on the IKJPOSIT macro.

Module: IKJEFP00

Program: PARSE

IKJ56716I • IKJ56723I

IKJ56716I **EXTRANEOUS INFORMATION WAS IGNORED:** *data*

Explanation: The user entered more information than is necessary to process a command and parse cannot give it a disposition.

Module: IKJEFP00

Program: PARSE

IKJ56717I **INVALID** *invalid information*

Explanation: The user entered invalid information.

Module: IKJEFP00

Program: PARSE

IKJ56718A **REENTER THIS OPERAND +**

Explanation: The parse user has specified HELP= on the parse macros indicating that there are additional messages for this prompting sequence. The user can enter a '?' and get the other messages. A '?' must be entered for each available message.

Module: IKJEFP00

Program: PARSE

IKJ56719I **INVALID JOBNAME,** *jobname*

Explanation: The user entered a syntactically invalid jobname or jobid or both.

Module: IKJEFP00, IKJEFP02

Program: PARSE

IKJ56720I **INVALID DDNAME,** *ddname*

Explanation: The parse user specified a data set name with the DDNAM option on the IKJPOSIT macro and the user entered a syntactically invalid ddname.

Module: IKJEFP00, IKJEFP02

Program: PARSE

IKJ56721I **INVALID NEW PASSWORD,** *password*

Explanation: The user has entered a non-alphanumeric character in a new password or the new password is more than eight characters in length.

Module: IKJEFP00

Program: PARSE

IKJ56722I **ENTER NEW PASSWORD FOR** *user_id*

Explanation: The user did not enter a new password after the user_id/current password and ending slash.

Module: IKJEFP00

Program: PARSE

IKJ56723I **FALSE SHIFT-OUT CHARACTER IN INPUT WAS IGNORED.**

Explanation: The command buffer contained a shift-out character but no shift-in character. The shift-out character was ignored.

For more information on shift-in and shift-out characters and the double-byte character set string, see *z/OS TSO/E Programming Services*.

Module: IKJEFP06

Program: PARSE and COMMAND SCAN

IKJ56724I ODD (LAST) BYTE DROPPED FROM DOUBLE-BYTE CHARACTER STRING.

Explanation: The double-byte character set string (DBCS) contained an odd number of bytes. The last byte in the DBCS string is replaced with the shift-in character, and the original shift-in character is replaced with a blank.

For more information on the double-byte character set string, see *z/OS TSO/E Programming Services*.

Module: IKJEFP06

Program: PARSE and COMMAND SCAN

IKJ56725I OUT-OF-RANGE DBCS CHARACTER IN INPUT WAS REPLACED.

Explanation: A character in the double-byte character string (DBCS) was outside the character set range. The offending character is replaced with a X'4195'. Each byte of a DBCS character must be in the range X'41' to X'FE' with the exception of the double-byte form of a blank which has the value X'4040'.

For more information on the double-byte character set string, see *z/OS TSO/E Programming Services*.

Module: IKJEFP06

Program: PARSE and COMMAND SCAN

IKJ56726I SHIFT-OUT FOUND WITH NO CORRESPONDING SHIFT-IN

Explanation: The command buffer contained a shift-out character but no shift-in character. The shift-out character was ignored.

For more information on shift-in and shift-out characters and the double-byte character set (DBCS) string, see *z/OS TSO/E Programming Services*.

Module: IKJEFP06

Program: PARSE and COMMAND SCAN

IKJ56727I ODD NUMBER OF BYTES IN A DBCS STRING. PARSE TERMINATED.

Explanation: The double-byte character set (DBCS) string contained an odd number of bytes. PARSE will not attempt to interpret this string.

Module: IKJEFP06

Program: PARSE and COMMAND SCAN

IKJ56728I OUT-OF-RANGE DBCS CHARACTER IN INPUT. PARSE TERMINATED.

Explanation: A character in the double-byte character set (DBCS) string was outside the character set range. Each byte of a DBCS character must be in the range X'41' to X'FE' with the exception of the double-byte form of a blank, which has the value X'4040'.

Module: IKJEFP06

Program: PARSE and COMMAND SCAN

IKJ56729I NESTED SHIFT-OUT FOUND IN DBCS STRING. PARSE TERMINATED.

Explanation: The double-byte character set (DBCS) string contained a nested shift-out character. Each shift-out must be followed by a shift-in before another shift-out is allowed.

Module: IKJEFP06

IKJ56730I • IKJ56770E

Program: PARSE and COMMAND SCAN

IKJ56730I INVALID VOLSER, *volser*

Explanation: You specified a data set name with the VOLSER operand on the IKJPOSIT macro. The volume serial is not valid.

User response: Specify a valid volume serial name. The VOLSER operand is valid only with the DSNAME or DSTHING operand. If the first character is numeric, a maximum of six characters is allowed.

Module: IKJEFP00

Program: PARSE

IKJ56731I INVALID "*" IN DATA SET NAME

Explanation: The user entered a data set name that contained an "*". Either an data set not containing an "*", or an "*" alone can be entered.

Module: IKJEFT08

Program: TMP/CALL

IKJ56760I NO INFORMATION AVAILABLE

Explanation: This message is issued when the terminal user enters '?' to receive a second-level message, but there are no second-level messages available.

Module: IKJEFT45, IKJEFT52

Program: I/O SEV ROUT

IKJ56761A INVALID RESPONSE. ENTER ? OR HIT CARRIER RETURN

Explanation: The I/O service routine was in pause state and waiting for a '?' or a carriage return when the user entered more data.

Module: IKJEFT45

Program: I/O SEV ROUT

IKJ56762A PAUSE

Explanation: The I/O service routine has detected a second-level message when a PUTGET was issued in a command procedure with a pause in effect. The user has the option of seeing the second-level message (?) or flushing the message and continuing the command procedure (carriage return).

Module: IKJEFT45

Program: I/O SEV ROUT

IKJ56770E RACONVRT terminated. Recovery environment could not be established.

Explanation: RACONVRT received a non-zero return code from the ESTAE macro indicating that a recovery environment could not be established. RACONVRT terminated.

User response: Contact your system programmer.

Module: IKJRUR00

Audience: RACONVRT user

IKJ56771E RACONVRT terminated. The command was not invoked authorized.

Explanation: RACONVRT received a non-zero return code from the TESTAUTH macro indicating that the command is not APF-authorized, in supervisor state, or in an authorized key. RACONVRT terminated.

User response: Contact your system programmer. In order for the command to be invoked authorized, the name "RACONVRT" must be placed in the authorized command table, IKJEFTE2, or a RACONVRT entry must be made in the IKJTSO00 member of "logical" SYS1.PARMLIB.

Module: IKJRUR00

Audience: RACONVRT user

IKJ56772E RACONVRT terminated. The user has insufficient authority. + authority authority is needed.

Explanation: The invoker of the command does not have the proper authority indicated by *authority*. If RACF is installed, then RACF SPECIAL authority is needed. Otherwise, ACCOUNT authority is needed. RACONVRT terminated.

User response: Contact your TSO/E administrator. You must have the specified authority to use the RACONVRT command.

Module: IKJRUR00

Audience: RACONVRT user

IKJ56773E RACONVRT terminated. The command could not be parsed. + IKJPARS return code of *return_code*.

Explanation: RACONVRT received a non-zero return code from the parse routine, IKJPARS, indicating that the command buffer could not be parsed for the operand that was supplied. The second-level message indicates the return code from IKJPARS. RACONVRT terminated.

User response: Check the return code from the parse service routine. If possible, correct the error. Otherwise, contact your system programmer.

Module: IKJRUR00

Audience: RACONVRT user

IKJ56774E RACONVRT terminated. The I/O routines could not be loaded.

Explanation: RACONVRT could not load one or both of the I/O routines, IKJRUR04 and IKJEFA51. RACONVRT terminated.

User response: Contact your system programmer.

Module: IKJRUR00

Audience: RACONVRT user

IKJ56775E RACONVRT terminated. Unable to obtain the necessary storage. + GETMAIN returned a return code of *return_code*. *user_id* was the last successful user ID.

Explanation: RACONVRT received a non-zero return code from the GETMAIN macro, indicating that the storage needed to process all users could not be obtained.

System action: The user ID indicated was the last user ID that was successfully processed.

User response: You have the following alternatives to process the remaining user IDs:

- Try to logon with a larger region size. This will allow you to process more user IDs with a single RACONVRT command.
- Issue several RACONVRT commands, each specifying a range of user IDs in the INCLUDE/ EXCLUDE operand.
- If you are already using INCLUDE/ EXCLUDE, specify smaller ranges of user IDs.

Module: IKJRUR01

Audience: RACONVRT user

IKJ56776E • IKJ56780E

IKJ56776E RACONVRT terminated. The SYS1.UADS data set could not be opened.

Explanation: RACONVRT received a non-zero return code from the I/O routine, IKJEFA51, indicating that the data set could not be opened. RACONVRT terminated.

User response: Contact your system programmer.

Module: IKJRUR01

Audience: RACONVRT user

IKJ56777E RACONVRT terminated. Error reading the SYS1.UADS data set.

Explanation: RACONVRT received a non-zero return code from the SYS1.UADS read routine, IKJEFA51, indicating an error occurred while attempting a READ operation. RACONVRT terminated. The return code from RACONVRT is 32 (decimal) and the possible reason codes are decimal:

RSN	Cause
4	User ID not found in UADS directory
8	BLDL I/O error
12	not enough dynamic storage
20	I/O error
24	Encountered last entry in the directory detected by module IKJRUR01
28	I/O error plus subsequent PUTLINE or SYNADRLS failure

User response: Contact your system programmer.

Module: IKJRUR01

Audience: RACONVRT user

IKJ56778E RACONVRT terminated. RACF is not active.

Explanation: RACF is installed on the system, but the return code from the RACROUTE macro indicates that RACF is inactive. RACONVRT terminated. Contact your system programmer.

Module: IKJRUR01

Audience: RACONVRT user

IKJ56779E RACONVRT terminated. Error occurred during RACF processing. + RACXTRT return code of *return_code*.

Explanation: RACONVRT received a non-zero return code from the RACROUTE macro indicating that an error occurred during RACF processing. RACONVRT terminated.

User response: Contact your system programmer.

Module: IKJRUR01

Audience: RACONVRT user

IKJ56780E RACONVRT terminated. The *userprefix*.IKJ.RACONVRT.CLIST data set is not partitioned with LRECL=80, BLKSIZE=8000, and RECFM=FB.

Explanation: The specified data set already exists, but has been allocated with improper attributes. RACONVRT is terminated.

User response: You can either reallocate the data set with the proper attributes, or delete it. If you delete the data set, RACONVRT will reallocate the data set with the proper attributes.

Module: IKJRUR02

Audience: RACONVRT user

IKJ56781D The *userprefix.IKJ.RACONVRT.CLIST* data set already exists. To overwrite it, respond “YES”. Any other response will terminate RACONVRT.

Explanation: The specified data set already exists. You can end RACONVRT processing before the data set is overwritten.

User response: If you want to overwrite the data set, respond with “YES” and the data set will be overwritten. Otherwise, RACONVRT will terminate.

Module: IKJRUR02

Audience: RACONVRT user

IKJ56782E RACONVRT terminated. PUTGET failed when prompting the user with message IKJ56781D. + PUTGET return code of *return_code*

Explanation: RACONVRT received a non-zero return code from PUTGET indicating that the PUTGET failed. The second-level message indicates the return code from PUTGET. RACONVRT terminated.

User response: Check the return code from PUTGET. If possible, correct the error. Otherwise, contact your system programmer.

Module: IKJRUR02

Audience: RACONVRT user

IKJ56783E RACONVRT terminated. The *userprefix.IKJ.RACONVRT.CLIST* data set could not be allocated.

Explanation: RACONVRT received unexpected return codes while locating, obtaining or allocating the CLIST data set. RACONVRT terminated.

User response: Contact your system programmer.

Module: IKJRUR02

Audience: RACONVRT user

IKJ56784E RACONVRT terminated. The *user_prefix.IKJ.RACONVRT.CLIST* data set could not be opened.

Explanation: RACONVRT received a non-zero return code from the I/O routine, IKJRUR04, indicating that the data set could not be opened. RACONVRT terminated.

User response: Contact your system programmer.

Module: IKJRUR02

Audience: RACONVRT user

IKJ56785E RACONVRT terminated. Error writing to the *userprefix.IKJ.RACONVRT.CLIST* data set. + Return code of *return_code* and reason code of *reason_code*.

Explanation: RACONVRT received a non-zero return code from the I/O routine, IKJRUR04, or the SYNAD or DCB ABEND exits were entered, indicating that an I/O error occurred. RACONVRT terminated.

User response: Check the return and reason codes and if possible, correct the error. Otherwise, contact your system programmer.

Module: IKJRUR06

Audience: RACONVRT user

IKJ56786I RACONVRT successful. To customize the conversion, edit the members of the *user_prefix*.IKJ.RACONVRT.CLIST data set. To complete the conversion, execute the run member.

Explanation: RACONVRT has completed successfully.

User response: To complete the conversion, execute the RUN member of the *user_id*.IKJ.RACONVRT.CLIST data set.

Module: IKJRUR06

Audience: RACONVRT user

IKJ56787I USERID *user_id* was partially processed due to an invalid internal format. + Please verify the CLIST conversion entries for this *user_id*.

Explanation: RACONVRT has detected that the user ID entry in the UADS data set was invalid. One of the offset fields for the user ID given contained an invalid value. RACONVRT begins processing the next user ID.

User response: Verify that the CLIST conversion entries for this *user_id* are valid.

Module: IKJRUR01

Audience: RACONVRT user

IKJ56788I RACF is inactive. Proceeding as if RACF is not installed.

Explanation: RACONVRT has detected that RACF is inactive. RACONVRT can not determine if a user is defined to RACF. Therefore, RACONVRT will generate only ADDUSER commands for defining users to RACF.

User response: Contact your system programmer if you want RACF reactivated.

Module: IKJRUR01

Audience: RACONVRT user

IKJ56801I HELP DATA SET NOT USABLE + CANNOT OPEN DATA SET FIND I/O ERROR LOGICAL RECORD LENGTH NOT 80 HELP REQUIRES A PARTITIONED DATA SET

Explanation: One of the error conditions listed above occurred while using the HELP data set.

I/O SYNAD ERROR *synad info*

Explanation: An I/O error occurred using the HELP data set. The SYNAD exit information was printed.

Module: IKJEFH01

Program: HELP

IKJ56802I HELP NOT AVAILABLE + COMMAND *character_string* NOT FOUND, FOR MORE HELP ENTER HELP COMMAND *character_string* NOT FOUND LIST OF COMMANDS NOT FOUND SUBCOMMAND HELP NOT FOUND SUBCOMMAND *character_string* NOT FOUND, FOR MORE HELP ENTER HELP *command_name* SUBCOMMAND LIST NOT FOUND

Explanation: A HELP command was entered for an invalid command or subcommand or one with no HELP member.

Module: IKJEFH01

Program: HELP

IKJ56803I FOR MORE INFORMATION ENTER HELP COMMANDNAME OR HELP HELP

Explanation: The HELP command requirements, a list of available commands, have been satisfied.

Module: IKJEFH01

Program: HELP

IKJ56804I FOR MORE INFORMATION ENTER HELP SUBCOMMANDNAME OR HELP HELP

Explanation: The HELP command requirements, a list of available subcommands under the current command, have been satisfied.

Module: IKJEFH01

Program: HELP

IKJ56805I *command_name / subcommand_name / operand_identifier* NOT FOUND

Explanation: The object of the HELP command could not be found. The object is COMMANDNAME, SUBCOMMANDNAME or OPERATOR IDENT.

Module: IKJEFH01

Program: HELP

IKJ56806I *command_name / subcommand_name_keyword* KEYWORD NOT FOUND

Explanation: The keyword object of the HELP command could not be found.

Module: IKJEFH01

Program: HELP

IKJ56807I COMMAND SYSTEM ERROR + *service_routine* ERROR CODE *error_code*

Explanation: Parse passed a return code greater than 8 while checking the syntax of the HELP command.

Module: IKJEFFOR

Program: HELP

IKJ56808I THE MSGID KEYWORD MAY NOT BE SPECIFIED WITH OTHER KEYWORDS.

Explanation: The user invoked the HELP command with the MSGID keyword as well as another HELP keyword. The MSGID keyword is mutually exclusive with the other keywords.

System action: The HELP command terminates.

User response: Invoke the HELP command again. If you need the information requested by both keywords, you must invoke the HELP command again specifying the other keyword.

Module: IKJEFH01

Audience: Any TSO/E user

Program: HELP

IKJ56809I *language* IS NOT SUPPORTED ON YOUR TERMINAL

Explanation: The HELP command attempted to use the language(s) specified in the TSO/E User Profile Table (UPT) and the help data sets associated with the language(s). The language specified in the UPT contains characters that are not supported on the device that you are using (for example, DBCS characters).

System action: The HELP command attempts to use the secondary language for HELP.

User response: Check the languages that you specified on the PROFILE command and ensure that they are supported on the terminal you are using. If necessary, use another terminal that supports the language you want to use, or change the language to a language supported on the terminal you are using. You can contact your system programmer to find out what languages are active on your system, and what languages are supported on your devices.

Module: IKJEFH01

Audience: Any TSO/E user

Program: HELP

IKJ56810I NO HELP TEXT COULD BE FOUND FOR LANGUAGE *language*.

Explanation: The HELP command attempted to use the language(s) specified in the TSO/E User Profile Table (UPT) and the help data sets associated with the language(s). The language that is specified in the UPT did not have a corresponding entry set up by the PARMLIB HELP statement.

System action: The HELP command attempts to use the secondary language for HELP. If the secondary language is the language identified in this message, the default help text in the U.S. English data sets is used.

User response: Check the languages that you specified on the PROFILE command to ensure that they are supported at your installation. If the languages are supported, ask your system programmer to check the HELP PARMLIB statement to ensure that the help data sets are defined for the language that you intend to use.

Module: IKJEFH01

Audience: Any TSO/E user

Program: HELP

IKJ56850I *type operation*, **OVERRIDING DISPOSITION IGNORED**

Explanation: The dynamic allocation information reason code is 0008. For a description of dynamic allocation information reason codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56851I *type operation* **REQUESTED CATALOG/UNCATALOG/DELETE DISPOSITION UNSUCCESSFUL**

Explanation: The dynamic allocation information reason codes are 0021-0029, 0031-0039, and 0050. For a description of dynamic allocation information reason codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56852I *type NOT operation*, **FILENAME NOT SPECIFIED**

Explanation: The dynamic allocation error code is 0304. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56853I *type NOT operation*, **DECONCATENATION WOULD RESULT IN DUPLICATE FILENAMES**

Explanation: The dynamic allocation error code is 0314 or 0424. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56854I **INVALID FILENAME**

Explanation: The dynamic allocation error code is 0318. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56855I INVALID MEMBERNAME

Explanation: The dynamic allocation error code is 031C. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56856I INVALID DATA SET NAME

Explanation: The dynamic allocation error code is 0320. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56857I INVALID SYSOUT PROGRAM NAME

Explanation: The dynamic allocation error code is 0324. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56858I INVALID SYSOUT FORM NUMBER

Explanation: The dynamic allocation error code is 0328. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56859I INVALID DISPOSITION

Explanation: The dynamic allocation error code is 0338. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56860I *type* NOT DEALLOCATED, DELETE DISPOSITION INVALID FOR DATA SET ALLOCATED AS SHARED

Explanation: The dynamic allocation error code is 0358. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56861I *type* NOT operation, DATA SET IS OPEN

Explanation: The dynamic allocation error code is 0420. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

HELP is the data set name displayed in place of *type* when the actual data set name is not available.

Module: CALLER

Program: DAIRFAIL

IKJ56862I *type NOT operation, REQUEST DENIED BY INSTALLATION EXIT*

Explanation: The DAIR return code is 52 (dec).

Module: CALLER

Program: DAIRFAIL

IKJ56863I *type NOT operation, NOT ENOUGH STORAGE TO EXECUTE COMMAND*

Explanation: The dynamic allocation error code is 0204 or 172C. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56864I *type NOT operation, USER NOT AUTHORIZED FOR FUNCTION SPECIFIED*

Explanation: The dynamic allocation error code is 0368 or 0470. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

This message might have been caused by the attempt to allocate a JES internal reader while the TSO/E environment service is active. See *z/OS TSO/E Programming Services* for details on limitations and restrictions.

Module: CALLER

Program: DAIRFAIL

IKJ56865I **FILE name NOT operation, FILE NAME CURRENTLY ASSOCIATED WITH A NON-EXPLICIT ALLOCATION + FILE filename MUST BE FREED BEFORE USING EXPLICITLY**

Explanation: The dynamic allocation error code is 0434. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56866I *type NOT operation, CONCURRENT ALLOCATIONS EXCEEDED*

Explanation: The dynamic allocation error code is 0450. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56867I *type NOT operation, RELATIVE ENTRY NUMBER SPECIFIED NOT FOUND*

Explanation: The dynamic allocation error code is 0444. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56868I *type NOT CONCATENATED, A FILENAME SPECIFIED WAS NOT FOUND*

Explanation: The dynamic allocation error code is 0308 or 0438. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56869I *type NOT operation, A FILE NAME HAS BEEN SPECIFIED MORE THAN ONCE + EACH FILENAME SPECIFIED FOR CONCATENATION MUST BE UNIQUE*

Explanation: The dynamic allocation error code is 038C. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56870I *type NOT operation, RELATIVE GENERATION NUMBER EXCEEDS 35 CHARACTERS*

Explanation: The dynamic allocation error code is 0390. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56871I *type NOT operation, RELATIVE GENERATION NUMBER INCOMPATIBLE FOR SPECIFIED STATUS*

Explanation: The dynamic allocation error code is 0394. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56872I *type NOT operation, DATA SET OR MEMBER IS NOT ALLOCATED TO THE FILENAME SPECIFIED*

Explanation: The dynamic allocation error code is 0460. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56873I *type NOT operation, DATA SET NAME SPECIFIED IS A PRIVATE CATALOG*

Explanation: The dynamic allocation error code is 0464. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56874I *type NOT operation, AN ERROR OCCURRED ALLOCATING OR OPENING A PRIVATE CATALOG*

Explanation: The dynamic allocation error code is 0468. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56875I *type NOT operation, DESTINATION UNDEFINED TO SUBSYSTEM*

Explanation: The dynamic allocation error code is 046C. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56876I *type NOT operation, MUTUALLY EXCLUSIVE PARAMETERS SPECIFIED*

Explanation: The dynamic allocation error code is 0380. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56877I *type NOT operation, MUTUALLY INCLUSIVE PARAMETER MISSING*

Explanation: The dynamic allocation error code is 0384. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56878I *type NOT operation, REQUIRED PARAMETER MISSING*

Explanation: The dynamic allocation error code is 0388. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56879I *type NOT operation, REFERENCED DATA SET NAME IS A GDG GROUP NAME*

Explanation: The dynamic allocation error code is 0458. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56880I *type NOT operation + NUMBER OF DEVICES REQUIRED CURRENTLY UNAVAILABLE*

Explanation: The dynamic allocation error code is 0224. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

VOLUME OR DEVICE IS CURRENTLY UNAVAILABLE FOR SYSTEM USE

Explanation: The dynamic allocation error code is 0228. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

SPECIFIED DEVICE IN USE WITH A VOLUME THAT CANNOT BE DISMOUNTED

Explanation: The dynamic allocation error code is 0230. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

A VOLUME SPECIFIED IS ALREADY MOUNTED ON ANOTHER DEVICE

Explanation: The dynamic allocation error code is 0234 or 023C. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

INSUFFICIENT NUMBER OF VOLUME SERIALS HAVE BEEN SPECIFIED

Explanation: The dynamic allocation error code is 0398. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

UNIT AND VOLUME SPECIFIED ARE NOT SAME DEVICE TYPE

Explanation: The dynamic allocation error code is 039C. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

GDG PATTERN DSCB COULD NOT BE FOUND

Explanation: The dynamic allocation error code is 048C. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

GDG PATTERN DSCB NOT MOUNTED

Explanation: The dynamic allocation error code is 0488. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

REQUIRED CATALOG VOLUME CURRENTLY NOT MOUNTED

Explanation: The dynamic allocation error code is 5704 (CATALOG return code 4 from DAIR). For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56881I type NOT operation, DEVICE IS A CONSOLE + DYNAMIC ALLOCATION OF A DEVICE NOT SUPPORTED

Explanation: The dynamic allocation error code is 0240. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56882I type NOT operation, TOO MANY VOLUMES + NUMBER OF VOLUMES SPECIFIED EXCEEDS LIMIT

Explanation: The dynamic allocation error code is 0480. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56883I type NOT operation, REQUEST CANCELED

Explanation: The dynamic allocation error code is 0484. If IEF336I does not accompany this message, request was canceled by the operator. Otherwise, see IEF336I to determine the reason for the cancellation (default policy or installation exit). For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56884I type NOT operation, SUBSYSTEM UNABLE TO SERVICE YOUR REQUEST

Explanation: The dynamic allocation error code is 0478. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56885I type name NOT operation, + IF YOU DID NOT SPECIFY UNIT NAME CALL YOUR SYSTEM PROGRAMMER

Explanation: The dynamic allocation error code is 0498. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56886I *type name* NOT operation, + IF YOU DID NOT SPECIFY VOLUME NAME *volume* CALL YOUR SYSTEM PROGRAMMER

Explanation: The dynamic allocation error code is 049C. See the *Message Library: Mass Storage System Messages* publication for a detailed description of Mass Storage System (MSS) reason code 7.

Module: CALLER

Program: DAIRFAIL

IKJ56887I *type_name* NOT operation, MSVGP DOES NOT EXIST + IF YOU DID NOT SPECIFY MSVGP CALL YOUR SYSTEM PROGRAMMER

Explanation: The dynamic allocation error code is 04A0.

Module: CALLER

Program: DAIRFAIL

IKJ56888I *type_name* NOT operation, YOU ARE NOT AUTHORIZED TO DEFINE THIS DATA SET TO RACF + NOTIFY YOUR INSTALLATION MANAGER

Explanation: The dynamic allocation error code is 47AC. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56889I *type_name* NOT operation, YOUR RACF DATA SET DEFINITION ALREADY EXISTS + YOU CAN DELETE OR RENAME YOUR EXISTING DATA SET OR CONTACT THE RACF-COORDINATOR TO VERIFY RACF DEFINITION

Explanation: The dynamic allocation error code is 47A8. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56890I *type_name* NOT operation, PROTECT KEYWORD CAN NOT BE USED FOR THIS DATA SET + USE PROTECT FOR PERMANENT DIRECT ACCESS DATA SETS WITH STATUS OF NEW, OR MOD TREATED AS NEW, AND FOR THE FIRST NEW PERMANENT DATA SET ON A TAPE

Explanation: The dynamic allocation error code is 03A4. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56891I RACF IS NOT ACTIVE IN YOUR SYSTEM + NOTIFY YOUR INSTALLATION MANAGER

Explanation: The dynamic allocation error code is 04B4. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56893I *type_name* NOT operation (Allocation, LACS, and/or Storage Management Subsystem messages are displayed.)

Explanation: A system or installation error occurred. Messages produced by allocation, LACS, and/or Storage Management Subsystem (SMS) describing the error follow message IKJ56893I. The dynamic allocation error codes are 0274, 0284 through 02C4, 9700 through 9714, and direct access device space management (DADSM) allocate error

codes if SMS is installed. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

User response: Change the request and resubmit it.

Module: CALLER

Program: DAIRFAIL

IKJ56894I *type_name* NOT operation, SYSTEM OR INSTALLATION ERROR STORAGE MANAGEMENT SUBSYSTEM DETECTED AN ERROR, EITHER MESSAGES WERE NOT REQUESTED OR A SYSTEM ERROR OCCURRED

Explanation: A system or installation error occurred, but your installation did not request that messages be displayed. The dynamic allocation interface must be rewritten to request that these messages be displayed. The dynamic allocation error codes are 9700 through 9714. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

User response: Contact your system programmer for assistance.

Module: CALLER

Program: DAIRFAIL

IKJ56895I *type_name* NOT operation INVALID REFERENCE, ALLOCATE TERMINATED

Explanation: One of the following references was not valid:

- At least one of the specified output descriptors
- A referenced ddname.

The dynamic allocation error code is 04CC.

User response: Check and correct the list of output descriptors and ddname references and reissue the command. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: CALLER

Program: DAIRFAIL

IKJ56896I *type_name* NOT operation UNABLE TO ACCESS LOCKED CATALOG

Explanation: An unsuccessful attempt was made to access a catalog that was locked for recovery. You do not have the proper authorization to access a catalog locked for recovery. The dynamic allocation error code is 17BA. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

User response: Either obtain the proper authorization and reissue the request, or wait until the catalog is unlocked and reissue the request.

Module: CALLER

Program: DAIRFAIL

IKJ56897I *type_name* NOT operation NON-SMS-MANAGED DATA SET CANNOT BE CREATED ON A SMS MANAGED VOLUME

Explanation: An attempt was made to obtain space for a non-Storage Management Subsystem data set on a Storage Management Subsystem-managed volume. The dynamic allocation error code is 47C0. For a description of dynamic allocation return, informational, and error codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

User response: Change the unit requirements and reissue the request.

Module: CALLER

Program: DAIRFAIL

IKJ56898I *Type name operation, JOB NAME WAS USED TO OVERRIDE A RESERVED TEMPORARY NAME*

Explanation: A reserved temporary data set name was used on a SYSOUT allocation. The dynamic allocation error code is X'0044' and is described in *z/OS MVS Programming: Authorized Assembler Services Guide*.

System action: The job is allowed to continue, but the job name is used instead of the reserved name.

User response: If you do not want to receive this warning message, change the temporary data set name associated with the SYSOUT data set allocation. Otherwise, ignore the message.

Module: IEFAB4SF

Program: DAIRFAIL

IKJ56899I *Type name NOT operation + USER IS NOT AUTHORIZED TO ALLOCATE THE REQUESTED DEVICE*

Explanation: You attempted to allocate a device that you are not authorized to access. The dynamic allocation error code is X'04D4' and is described in *z/OS MVS Programming: Authorized Assembler Services Guide*.

System action: Processing terminates.

System programmer response: Determine if the user should have access to the given device. If so, define a RACF profile authorizing the user access to that device.

User response: Request a device that you are authorized to access or notify your security administrator.

Module: IEFAB434

Program: DAIRFAIL

IKJ56950I **BROADCAST DATA SET NOT USABLE + I/O SYNAD ERROR INSTALLATION MUST REFORMAT**

Explanation: An I/O error occurred.

CANNOT OPEN DATA SET

Explanation: DCBOFLAGS indicated that the broadcast data set was not opened.

Module: IKJEE575 IKJEE270

Audience: LISTBC user

IKJ56951I **NO BROADCAST MESSAGES**

Explanation: No messages of the type requested were found.

Module: IKJEE570

Audience: LISTBC user

IKJ56957I **NOT ENOUGH STORAGE TO EXECUTE COMMAND**

Explanation: The return code from parse was 16 or the return code from a conditional GETMAIN was 4.

Module: IKJEE575 IKJEE570

Audience: LISTBC user

IKJ56959I **COMMAND SYSTEM ERROR + SERVICE ROUTINE ERROR CODE** *error_code*

Explanation: The return code from any of the service routines was not 0 or was not a code indicating a specific problem.

Module: IKJEE575

Audience: LISTBC user

IKJ56960E LISTBC TERMINATED. THE COMMAND WAS NOT INVOKED AUTHORIZED.

Explanation: LISTBC determined that it was not running in an authorized state and terminated. For further assistance, contact your system programmer.

Module: IKJEES70

Audience: LISTBC user

IKJ56961E LISTBC TERMINATED. THE MESSAGE LOG COULD NOT BE ALLOCATED. + DYNAMIC ALLOCATION ERROR CODE OF *cc* AND INFORMATION REASON CODE OF *reason_code*.

Explanation: LISTBC was unable to allocate the message log. For a description of dynamic allocation return codes and reason codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: IKJEES69

Audience: LISTBC user

IKJ56962I YOUR USER LOG CONTAINS MESSAGES THAT CANNOT BE VIEWED AT YOUR CURRENT SECURITY LABEL.

Explanation: RACF indicates that the security label you are logged on with is not equal to or greater than the security label associated with one or more messages in your user log.

System action: The system does not display the message(s).

User response: Log on with an appropriate security label to view the message(s) or contact your security administrator.

Module: IKJEES69

Audience: LISTBC user

IKJ56963E RACINIT RETURN CODE OF *return_code* AND REASON CODE OF *reason_code*

Explanation: This message is a second-level message to IKJ56961E. LISTBC was unable to allocate the user log.

System action: Processing terminates.

User response: Contact your system programmer or see *z/OS MVS Programming: Authorized Assembler Services Reference LLA-SDU* for a description of the RACINIT return and reason codes.

Module: IKJEES69

Audience: LISTBC user

IKJ56964E LISTBC TERMINATED. THE LRECL IS GREATER THAN THE MAXIMUM LRECL ALLOWED FOR USER LOGS.

Explanation: LISTBC determined that the LRECL for the user log was greater than 232 bytes. See *z/OS TSO/E Customization* for more information about user logs.

System action: Processing terminates.

User response: Delete the user log and issue the LISTBC command to create a new user log.

Module: IKJEES69

Audience: LISTBC user

IKJ57xxxI Second-Level Messages

The following set of messages, See "IKJ57xxxI" through "IKJ57xxxI" for the descriptions of second-level messages all with the same identifier IKJ57xxxI, is an alphabetical listing of second-level messages. These second-level messages are issued in conjunction with first-level messages also in the IKJ57nnnI series. If you receive two IKJ57nnnI messages with the same identifier, but can only find one of the messages within the numerical listings in this document, scan the message texts of the following second-level messages for the other message and its meaning. (The alphabetical order of these second-level messages is determined by the constant terms of the message text and not the variable terms; for alphabetization purposes, all variable terms are ignored. Match the constant terms of the message you receive with the constant terms of the listed messages.)

IKJ57xxxI A BREAKPOINT WAS DETECTED IN A PRIVILEGED PROGRAM

Explanation: A breakpoint was detected in either a program running in a supervisor key or in an SVRB; because such breakpoints are impermissible, the test session is ended.

Module:

TEST

Audience: TEST user

IKJ57xxxI A RELATIVE ADDRESS IS NOT VALID WITH AN ALET OR AR VALUE

Explanation: The ALET or AR keyword cannot be specified with a relative address unless the ALET value is zero.

System action: TEST prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A QUALIFIED ADDRESS IS NOT VALID WITH AN ALET VALUE

Explanation: A qualified address is not allowed if you specified an ALET value.

System action: TEST prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR A BREAKPOINT

Explanation: TEST could not establish a breakpoint because the location specified is in an alternate address/data space. You cannot specify a symbol that has an ALET value to establish a breakpoint.

System action: The AT subcommand prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR A DCB ADDRESS

Explanation: You specified a DCB location that is in an alternate address/data space. You cannot specify a symbol that has an ALET value to locate a DCB.

System action: The LISTDCB subcommand prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR A PROGRAM ADDRESS

Explanation: You specified a location that is in an alternate address/data space. You cannot specify a symbol that has an ALET value to locate a program address.

System action: The WHERE subcommand prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR A PSW ADDRESS

Explanation: You specified a PSW location that is in an alternate address/data space. You cannot specify a symbol that has an ALET value to locate a PSW.

System action: The LISTPSW subcommand prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR A TCB ADDRESS

Explanation: You specified a TCB location that is in an alternate address/data space. You cannot specify a symbol that has an ALET value to locate a TCB.

System action: The LISTTCB subcommand prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR A VSR ADDRESS

Explanation: You specified a VSR™ location that is in an alternate address/data space. You cannot specify a symbol that has an ALET value to locate a VSR.

System action: The LISTVSR subcommand prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR AN EXECUTABLE ADDRESS

Explanation: You specified a location that is in an alternate address/data space. You cannot specify a symbol that has an ALET value to locate an executable address.

System action: The GO, CALL, or RUN subcommand prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI

IKJ57xxxI A SYMBOL WITH ALET IS NOT ALLOWED FOR THE DELETE, FREEMAIN, GETMAIN OR LOAD SUBCOMMAND

Explanation: You specified a location that is in an alternate address/data space. You cannot specify a symbol that has an ALET value to specify an address for the indicated subcommands.

System action: The subcommand terminates.

User response: Reenter the subcommand.

Module: TEST

Audience: TEST user

IKJ57xxxI ABSOLUTE VALUE TOO GREAT

Explanation: The absolute value of the entered value is larger than that allowed for the indicated data format.

Module: TEST

Audience: TEST user

IKJ57xxxI ADDRESS *address* EXCEEDS MAXIMUM VIRTUAL STORAGE SIZE

Explanation: The address given in a TSO/E subcommand resolves to a number larger than X'7FFFFFFF'.

Module: TEST

Audience: TEST user

IKJ57xxxI ADDRESS IN WRITE PROTECTED STORAGE

Explanation: The resolved address accesses storage which is protected and cannot be altered.

Module: TEST

Audience: TEST user

IKJ57xxxI ADDRESS TYPE IS STORAGE AND SECOND ADDRESS IS LESS THAN FIRST

Explanation: The second address is smaller than the first.

Module: TEST

Audience: TEST user

IKJ57xxxI ALETS SPECIFIED FOR EACH RANGE VALUE MUST BE EQUAL

Explanation: You must specify the same ALET value for both addresses in a range because the addresses must be in the same address/data space. The symbols have different ALET values equated with them.

System action: TEST prompts you to reenter the range of addresses.

User response: Reenter the range of addresses.

Module: TEST

Audience: TEST user

IKJ57xxxI ALL LOADNAMES FOR A DEFER REQUEST MUST BE THE SAME

Explanation: All of the load module names in the requested AT DEFER command were not the same.

Module: TEST

Audience: TEST user

IKJ57xxxI AMODE MUST BE 24, 31 or SWITCH

Explanation: You must enter a valid AMODE operand on the CALL, GO or RUN subcommand. Reenter the AMODE operand with 24, 31 or SWITCH.

Module: TEST

Audience: TEST user

IKJ57xxxI AN INVALID PDE WAS OBTAINED FROM PARSE

Explanation: The address does not correspond to any valid type.

Module: TEST

Audience: TEST user

IKJ57xxxI *module_name* ASSEMBLED WITHOUT TEST PARAMETER, INTERNAL SYMBOLS UNAVAILABLE

Explanation: The TEST option was not specified on the PARM keyword in the compile step for this module name.

Module: TEST

Audience: TEST user

IKJ57xxxI ATTEMPT QUALIFICATION AT NEXT BREAKPOINT

Explanation: The user has attempted to qualify at the current breakpoint.

Module: TEST

Audience: TEST user

IKJ57xxxI BLDL ERROR CODE 4

Explanation: The BLDL macro instruction returned a return code of 4.

Module: TEST

Audience: TEST user

IKJ57xxxI BLDL ERROR CODE 8

Explanation: The BLDL macro instruction returned a return code of 8.

Module: TEST

Audience: TEST user

IKJ57xxxI BOTH THE ACTIVE AND DEFERRED QUEUES ARE EMPTY

Explanation: Removal of a breakpoint was requested; however, there are no breakpoints known to the TEST system.

Module: TEST

Audience: TEST user

IKJ57xxxI *nnnn* BOUNDARY REQUIRED

Explanation: The required word alignment was not used; for example, fullword indicated, halfword given as address.

Module: TEST

Audience: TEST user

IKJ57xxxI

IKJ57xxxI BREAKPOINT SVC ERROR CODE 4

Explanation: An error has occurred in SVC 97 (TEST SVC).

Module: TEST

Audience: TEST user

IKJ57xxxI BREAKPOINTS ARE NO LONGER VALID

Explanation: The breakpoints previously established in program(s) being tested are no longer in effect.

Module: TEST

Audience: TEST user

IKJ57xxxI BREAKPOINTS ARE NOT SUPPORTED FOR THE *mnemonic* INSTRUCTION

Explanation: TSO/E cannot establish a breakpoint at the instruction named in the message. See the AT subcommand of TSO/E TEST in the *z/OS TSO/E Command Reference* for a list of instructions for which breakpoints cannot be established.

Module: TEST

Audience: TEST user

IKJ57xxxI BREAKPOINTS EXIST IN FROM DATA, NOT ALLOWED FOR AND/OR SUBCOMMANDS.

Explanation: Remove breakpoints from the "from" data (the first operand of an AND or OR subcommand) before you issue an AND or OR subcommand.

Module: TEST

Audience: TEST user

IKJ57xxxI BREAKPOINTS SET ARE STILL VALID

Explanation: Breakpoints previously established in program(s) being tested are still in effect.

Module: TEST

Audience: TEST user

IKJ57xxxI BREAKPOINTS WERE DEACTIVATED, TO ACTIVATE, USE THE AT COMMAND

Explanation: The breakpoints in an area of storage were removed because the indicated area was altered by an assignment.

Module: TEST

Audience: TEST user

IKJ57xxxI CALL SUBCOMMAND IS EXECUTED AS SPECIFIED

Explanation: This message is a warning that an address requested through the PARM, RESUME or RETURN keyword of the CALL subcommand is above the 16 MB line. Because the tested program is either in 24-bit addressing mode or the user specified AMODE(24), the called program may not work properly. If the CALL does not work correctly, reissue the subcommand specifying AMODE(31).

Module: TEST

Audience: TEST user

IKJ57xxxI COMMAND CHAIN LENGTH MAY NOT EXCEED 255 BYTES

Explanation: The length of the subcommand list entered is greater than 255 bytes.

Module: TEST

Audience: TEST user

IKJ57xxxI COUNT MUST BE FROM 0 TO 65535

Explanation: The COUNT value entered is not within the acceptable range of values.

Module: TEST

Audience: TEST user

IKJ57xxxI DATA FORMAT IS INCORRECT

Explanation: The indicated data format is not one of those allowed by the ASSIGNMENT command. That is, halfword is indicated but the number will not fit into a halfword.

Module: TEST

Audience: TEST user

IKJ57xxxI DATA LENGTH EXCEEDS REGISTER CAPACITY

Explanation: The data string length on the assignment was longer than that which can be placed in the indicated register.

Module: TEST

Audience: TEST user

IKJ57xxxI DATA SET WITH DDNAME *ddname* COULD NOT BE OPENED

Explanation: An attempt to OPEN the data set associated with specified ddname failed. Replace the symbolic address with an absolute or relative address.

Module: TEST

Audience: TEST user

IKJ57xxxI DATA STRING CONTAINS AN INVALID CHARACTER

Explanation: The value (DATA STRING) contains characters which are not correct with respect to the indicated data format.

Module: TEST

Audience: TEST user

IKJ57xxxI DATA STRING TOO LONG

Explanation: The length of the data string as entered is greater than that allowed for the indicated data format.

Module: TEST

Audience: TEST user

IKJ57xxxI DATASET ASSOCIATED WITH DEB NOT ON A DIRECT ACCESS STORAGE DEVICE

Explanation: The data set is assigned to a non-DASD device.

Module: TEST

Audience: TEST user

IKJ57xxxI

IKJ57xxxI DEBNMEXT FIELD IN DEB IS ZERO

Explanation: The DEB does not contain a DASD section.

Module: TEST

Audience: TEST user

IKJ57xxxI ENTRY NAME IS NOT ALLOWED WITH AN ALET VALUE

Explanation: The ALET keyword cannot be specified with an entry name address.

System action: TEST prompts you to reenter the address.

User response: Reenter the address.

Module: TEST

Audience: TEST user

IKJ57xxxI *address* EXTENDS INTO PROTECTED STORAGE

Explanation: A DCB extends into read-protected storage.

Module: TEST

Audience: TEST user

IKJ57xxxI FIRST ADDRESS OF RANGE MUST NOT BE HIGHER THAN LAST ADDRESS

Explanation: An address range was specified in which the first address was greater than the last address.

Module: TEST

Audience: TEST user

IKJ57xxxI *label* FOUND IN *name* DSECT FOR WHICH NO BASE ADDRESS EXISTS

Explanation: The label was found in a DSECT that has not been placed in the in-storage symbol table via the EQUATE command.

Module: TEST

Audience: TEST user

IKJ57xxxI FULLY-QUALIFIED ADDRESS MUST BE GIVEN

Explanation: A fully-qualified address was not specified but was required.

Module: TEST

Audience: TEST user

IKJ57xxxI IN *module* ABEND CODE = *abend_code*, IC = *nnnnnnnn* INSTR IMAGE = [*nnnnnnnnnnnnnnnn*]
[abend_table_insert]

Explanation: A TSO/E TEST module terminated abnormally. The module name, the module's storage location, and the system completion code are indicated in the message.

Module: TEST

Audience: TEST user

IKJ57xxxI INPUT NOT RESOLVED AS LOADNAME. CSECTNAME

Explanation: TEST is unable to convert the input to a machine address.

Module: TEST

Audience: TEST user

IKJ57xxxI INPUT NOT RESOLVED AS LOADNAME OR SYMBOL

Explanation: TEST is unable to convert the input to a machine address.

Module: TEST

Audience: TEST user

IKJ57xxxI INSTALLATION EXIT REASON CODE = *reason_code*

Explanation: The TEST installation exit referred to in the associated first-level message terminated with the indicated reason code.

System action: Processing terminates.

User response: Contact your system programmer with message ID and message content.

Module: TEST

Audience: TEST user

IKJ57xxxI INSUFFICIENT STORAGE

Explanation: Not enough dynamic storage could be obtained to complete the requested function.

Module: TEST

Audience: TEST user

IKJ57xxxI INVALID OP CODE

Explanation: This data does not contain a valid machine operation code.

Module: TEST

Audience: TEST user

IKJ57xxxI INVALID QUALIFIED ADDRESS

Explanation: The address validity check routine for the FREEMAIN subcommand has detected an invalid qualified address.

Module: TEST

Audience: TEST user

IKJ57xxxI INVALID RANGE BEGINNING *nnnnnnnn*

Explanation: OFF received a return code of 8 from IKJEGSRH.

Module: TEST

Audience: TEST user

IKJ57xxxI LENGTH MAY NOT EXCEED 64 WHEN REGISTERS ARE SPECIFIED

Explanation: The user has specified registers as addresses for the COPY subcommand and has specified a length greater than 64 bytes.

Module: TEST

IKJ57xxxI

Audience: TEST user

IKJ57xxxI **LENGTH MUST BE FROM 0 TO 65535**

Explanation: The length of the data copied must be from 0 to 65535 bytes when general register notation is not used as the from and to addresses.

Module: TEST

Audience: TEST user

IKJ57xxxI *module_name* **LINK-EDITED IN OVERLAY, NOT IN MAIN STORAGE**

Explanation: The SVC information block does not contain a ddname for the PDS for this member, and this is not a member in the SYS1.LINKLIB.

Module: TEST

Audience: TEST user

IKJ57xxxI *module_name* **LINK-EDITED WITHOUT TEST PARAMETER, INTERNAL SYMBOLS UNAVAILABLE**

Explanation: The TEST option was not specified on the PARM keyword in the LINKEDIT step or the LOAD MODULE.

Module: TEST

Audience: TEST user

IKJ57xxxI *module_name* **LOADED BY OS LOADER, INTERNAL SYMBOLS UNAVAILABLE**

Explanation: The module being tested is not a member in a PDS, so there are no CESD records available from which to read any symbols.

Module: TEST

Audience: TEST user

IKJ57xxxI *module_name* **LOADED BY OS LOADER, NOT ENOUGH MAIN STORAGE FOR EXTERNAL SYMBOLS**

Explanation: This is an OBJECT module as opposed to a LOAD module; however, this OS loader has not provided CESD (symbol) information.

Module: TEST

Audience: TEST user

IKJ57xxxI **MAXIMUM LENGTH FOR TYPE *type* IS *nnnnn***

Explanation: The length was adjusted.

Module: TEST

Audience: TEST user

IKJ57xxxI **MAXIMUM LENGTH IS 100**

Explanation: The value specified in the associated first-level message has exceeded the limit of 100.

Module: TEST

Audience: TEST user

IKJ57xxxI MINIMUM LENGTH FOR TYPE *type* IS *nnnnn*

Explanation: The length was adjusted.

Module: TEST

Audience: TEST user

IKJ57xxxI NEITHER SYMBOLS NOR BREAKPOINTS ARE AVAILABLE FOR THE PRIVILEGED MODULE BEING ACCESSED

Explanation: A module is being accessed which is either in a supervisor key or is running under a SVRB. This operation is not permissible; therefore, deferred breakpoints are not activated and symbols are not available.

Module: TEST

Audience: TEST user

IKJ57xxxI NO TCB EXISTS AT SPECIFIED ADDRESS

Explanation: The TCB address is invalid.

Module: TEST

Audience: TEST user

IKJ57xxxI *module_name* NOT BROUGHT INTO MAIN STORAGE UNDER TEST, SYMBOLS UNAVAILABLE

Explanation: SVC 61 has not operated to construct the SVC information.

Module: TEST

Audience: TEST user

IKJ57xxxI *label* NOT FOUND IN EXTERNAL SYMBOL TABLE FOR *module_name*

Explanation: There are no internal symbols, and label is not in the external symbol table.

Module: TEST

Audience: TEST user

IKJ57xxxI *symbol* NOT FOUND RELATED TO SPECIFIED TCB

Explanation: The message is issued if unable to locate symbol after search.

Module: TEST

Audience: TEST user

IKJ57xxxI *load_module* NOT FOUND UNDER THE TEST TASK STRUCTURE, SYMBOLS UNAVAILABLE
LOAD MODULE

Explanation: The specified load module is not represented on a CDE chain under the test task structure.

Module: TEST

Audience: TEST user

IKJ57xxxI *module* NOT FROM DATA SET IN LINKLIST LIBRARY AND DDNAME UNKNOWN. SYMBOLS UNAVAILABLE

Explanation: You have specified a symbolic address and, because the ddname or the data set name is unknown, the address cannot be resolved. Respecify the address as an absolute or relative address. Contact a system programmer to report this problem.

Module: TEST

IKJ57xxxI

Audience: TEST user

IKJ57xxxI *load_module* NOT FROM SYS1.LINKLIB DATA SET, SYMBOLS UNAVAILABLE

Explanation: You have specified a symbolic address and, because the ddname or the data set name is unknown, the address cannot be resolved. Respecify the address as an absolute or relative address. Contact a system programmer to report this problem.

Module: TEST

Audience: TEST user

IKJ57xxxI *symbol* NOT IN INTERNAL SYMBOL TABLE FOR csectname

Explanation: The specified symbol does not appear in the CESD records for this CSECT.

Module: TEST

Audience: TEST user

IKJ57xxxI null message with capacity for six inserts

Explanation: The entire message is created dynamically. It contains such information as SYNAD information.

Module: TEST

Audience: TEST user

IKJ57xxxI OPEN ERROR

Explanation: The OPEN macro has failed for the data set from which the requested module is to be loaded.

Module: TEST

Audience: TEST user

IKJ57xxxI OVERLAY PROGRAMS NOT SUPPORTED BY RUN SUBCOMMAND, USE GO SUBCOMMAND

Explanation: RUN was specified for a program that is link-edited as an overlay structure. GO may be used to execute the program instead of RUN.

Module: TEST

Audience: TEST user

IKJ57xxxI PARSE ERROR CODE 12

Explanation: Parse return code was 12. The user's request was not honored.

Module: TEST

Audience: TEST user

IKJ57xxxI PART OF RANGE IS WRITE PROTECTED

Explanation: Part of range entered is in write-protected storage.

Module: TEST

Audience: TEST user

IKJ57xxxI PRINT DATA SET MUST BE PHYSICAL SEQUENTIAL

Explanation: The data set organization is not physical sequential.

Module: TEST

Audience: TEST user

IKJ57xxxI PROGRAM NOT ON LOAD LIST

Explanation: The DELETE subcommand was unable to delete the requested program from main storage because it was not on the load list.

Module: TEST

Audience: TEST user

IKJ57xxxI RANGE CONTAINS BOTH A STORAGE AND A REGISTER ADDRESS

Explanation: The addresses specified for TO and FROM are not compatible.

Module: TEST

Audience: TEST user

IKJ57xxxI REGISTER NOTATION MUST BE GENERAL REGISTER

Explanation: The user has specified register usage as addresses and has not used general register notation.

Module: TEST

Audience: TEST user

IKJ57xxxI REGISTER NOTATION MUST BE INDIRECT GENERAL REGISTER

Explanation: The form of the subcommand the user has specified requires that register notation be indirect general register.

Module: TEST

Audience: TEST user

IKJ57xxxI REGISTER NOTATION MUST BE INDIRECT GENERAL REGISTER WHEN POINTER IS SPECIFIED

Explanation: The user has specified the POINTER keyword with the COPY subcommand and used register notation other than indirect general register.

Module: TEST

Audience: TEST user

IKJ57xxxI REGISTER TYPE OF SECOND ADDRESS DIFFERS FROM FIRST

Explanation: The addresses specified for TO and FROM are not compatible.

Module: TEST

Audience: TEST user

IKJ57xxxI RENAME THE *member* OF THE PARTITIONED DATA SET AND REISSUE TEST USING THE NEW MEMBER NAME

Explanation: TSO/E has rejected the TEST command because the module name to be tested is identical to one already in the user's address space. Rename the module or add an alias to the member name specified for the partitioned data set. Reissue the TEST command using the new member name or alias.

Module: TEST

Audience: TEST user

IKJ57xxxI

IKJ57xxxI REQUEST EXCEEDED GREATEST VALID ADDRESS

Explanation: The list request extends beyond the highest machine address.

Module: TEST

Audience: TEST user

IKJ57xxxI SPECIFIED ADDRESS IS IN PROTECTED STORAGE

Explanation: TSO/E TEST address validity check routine determined that you cannot access the specified address.

Module: TEST

Audience: TEST user

IKJ57xxxI SPECIFIED EXPONENT IS GREATER THAN 2 DIGITS

Explanation: A floating point value (D or E data type) cannot have an exponent greater than two digits. Replace the exponent with a number no greater than two digits.

Module: TEST

Audience: TEST user

IKJ57xxxI SPECIFIED SYMBOLIC ADDRESS CANNOT BE RESOLVED. ABSOLUTE OR RELATIVE ADDRESSES MAY BE USED.

Explanation: The symbolic address cannot be resolved under TEST. Enter HELP GO as a TEST subcommand to obtain a description of the absolute and relative addresses. Respecify the address as an absolute or relative address.

Module: TEST

Audience: TEST user

IKJ57xxxI SVC FAILED WHEN ATTEMPTING TO OBTAIN A MODULE *module_name* THE ABEND CODE WAS *abend_code*

Explanation: LOAD or LINK SVC returned a test module with error code. This message is issued as a first-level message only.

Module: TEST

Audience: TEST user

IKJ57xxxI SVC FAILED WITH A RETURN CODE OF *return_code*

Explanation: ESTAE SVC returned with a non-zero return code.

Module: TEST

Audience: TEST user

IKJ57xxxI SVC 97 PASSED A RETURN CODE OF 8 AFTER VALIDITY CHECK

Explanation: SVC 97 was called to validity check an address and passed back a return code of 8.

Module: TEST

Audience: TEST user

IKJ57xxxI SVC 97 RETURN CODE NON-ZERO

Explanation: A subcommand process called SVC 97 and it returned a non-zero code.

Module: TEST

Audience: TEST user

IKJ57xxxI SYMBOL LENGTH EXCEEDS EIGHT CHARACTERS

Explanation: The length of the symbol entered is greater than 8 characters.

Module: TEST

Audience: TEST user

IKJ57xxxI SYSTEM ABEND CODE *abend_code*

Explanation: The system has abended with the specified abend code after a task switch has occurred for the LOAD, DELETE, GETMAIN, or FREEMAIN subcommands.

Module: TEST

Audience: TEST user

IKJ57xxxI SYSTEM COMPLETION CODE IS *xxxx*

Explanation: The module specified in associated first-level message has terminated abnormally with a system completion code of *xxxx*. See *z/OS MVS System Codes* for a description of abend codes.

Module: TEST

Audience: TEST user

IKJ57xxxI SYSTEM CONTROL BLOCK ERROR, TEST SESSION ENDED

Explanation: An error was found in a system control block.

The requested function cannot be completed.

Module: TEST

Audience: TEST user

IKJ57xxxI TCB KEYWORD IS IGNORED WHEN QUALIFYING AN ADDRESS

Explanation: The user has not fully qualified the address.

Module: TEST

Audience: TEST user

IKJ57xxxI TEST SESSION CANCELLED DUE TO UNRECOVERABLE SVC ERROR

Explanation: An unrecoverable error has occurred in an SVC used by TEST. TEST terminates.

Module: TEST

Audience: TEST user

IKJ57xxxI THE COMMAND ENTERED IS NOT SUPPORTED IN TEST MODE IN THIS SYSTEM

Explanation: An invalid subcommand or subcommand abbreviation has been entered.

Module: TEST

Audience: TEST user

IKJ57xxxI THE GIVEN ELEMENT NUMBER EQUALS OR EXCEEDS THE SECTION SIZE.

Explanation: You have specified a vector register with an element number that is greater than or equal to the section size of a vector register.

Module: TEST

Audience: TEST user

IKJ57xxxI

IKJ57xxxI THE *data area* IS IN PROTECTED STORAGE

Explanation: You have supplied an address on the LISTTCB subcommand that is not an address of an actual TCB. You do not have access to the data area named in the message.

Module: TEST

Audience: TEST user

IKJ57xxxI THE VALID DATA TYPES FOR REGISTER TYPE W ARE D OR X.

Explanation: The valid data types for a vector register in double precision are:

- D - double precision floating point
- X - hexadecimal.

Module: TEST

Audience: TEST user

IKJ57xxxI THE VALID DATA TYPES FOR REGISTER TYPE V ARE E, F, OR X.

Explanation: The valid data types for a vector register in single precision are:

- E - single precision floating point
- F - fixed point binary
- X - hexadecimal.

Module: TEST

Audience: TEST user

IKJ57xxxI THE VALID RANGE IS FROM 1 TO 256

Explanation: The specified length or multiplicity is outside value range.

Module: TEST

Audience: TEST user

IKJ57xxxI THE VALID TYPES FOR THE VECTOR MASK REGISTER ARE B OR X.

Explanation: The valid data types for the vector mask register are:

- B - binary
- X - hexadecimal

System action: TEST prompts you to reenter the value.

User response: Reenter the value.

Module: TEST

Audience: TEST user

IKJ57xxxI THIS SYSTEM DOES NOT SUPPORT THE VECTOR FACILITY.

Explanation: You cannot display or modify a vector register because the program is executing on a system that does not support the Vector Facility.

Module: TEST

Audience: TEST user

IKJ57xxxI UNABLE TO CONTINUE TEST SESSION

Explanation: Due to an error condition, control is returned to TMP.

Module: TEST

Audience: TEST user

IKJ57xxxI UNABLE TO LOCATE ADDRESS ON ACTIVE OR DEFERRED QUEUE

Explanation: The specified address does not exist in the list of active or deferred breakpoints.

Module: TEST

Audience: TEST user

IKJ57xxxI USE THE AMODE OPERAND ON CALL, GO, OR RUN TO CHANGE THE ADDRESSING MODE

Explanation: A program that is executing in 24-bit addressing mode cannot access data or code that is above 16 MB. If the address is correct, reenter the subcommand with the AMODE(31) operand. Otherwise, reenter the subcommand specifying the correct address with the appropriate AMODE operand.

Module: TEST

Audience: TEST user

IKJ57xxxI USER COMPLETION CODE IS *xxxx*

Explanation: The module specified in associated first-level messages has terminated abnormally with a user completion code of *xxxx*.

Module: TEST

Audience: TEST user

IKJ57xxxI VALID DATA TYPES ARE X OR D FOR REGISTER TYPE D

Explanation: Register type D was specified on the assignment with a data type other than X or D.

Module: TEST

Audience: TEST user

IKJ57xxxI VALID DATA TYPES ARE X OR E FOR REGISTER TYPE E

Explanation: Register type E was specified on the assignment with a data type other than X or E.

Module:

TEST

Audience: TEST user

IKJ57xxxI REQUIRED SYSTEM ROUTINE *routine-name* COULD NOT BE LOADED.

Explanation: During initialization of TSO/E TEST, routine ASMADOP could not be loaded. As a result, the AT subcommand and LIST subcommand with *data_type* operand *I* specified will not be able to process the instructions at the specified address.

System action: The subcommand will terminate.

User response: Notify your system programmer.

Module: TSO/E TEST command.

IKJ57xxxI SYSTEM ROUTINE *routine-name* FAILED WITH RETURN CODE *return-code*.

Explanation: TSO/E TEST processing invoked routine *routine-name*. The routine ended with return code *return-code*. If *routine-name* is ASMADOP, the AT subcommand and the LIST subcommand with *data_type* operand *I* specified will not be able to process the instructions at the specified address.

System action: The subcommand will terminate.

User response: Notify your system programmer.

Module: TSO/E TEST command.

IKJ57002I NO ACTIVE PROGRAM LEFT

Explanation: TEST has been brought out of a wait state but it cannot be determined which module posted it. TEST is being terminated.

Module: IKJEGINT

Audience: TEST user

IKJ57005I MEMBER *member* NOT IN DATA SET *dsname*

Explanation: The specific member name was not found in the directory of the specified data set.

MEMBER *member* NOT FOUND WITHIN THE STANDARD SEARCH ORDER

Explanation: The specified member name was not found in the standard search order (TSOLIB (TASKLIB), STEPLIB or JOBLIB, or current LNKST concatenation). Modules residing in the LPA or in both the LPA and a library in the standard search order are not eligible for the TEST command with the '*' operand.

Module: IKJEGINT

Audience: TEST user

IKJ57008I PARAMETER STRING LENGTH EXCEEDED

Explanation: The length of the PARM field entered on the TEST command has exceeded the limit of 100 characters.

Module: IKJEGLDR

Audience: TEST user

IKJ57021I INVALID COMMAND

Explanation: The command could not be found in the test subcommand tables.

Module: IKJEGMNL

Audience: TEST user

IKJ57022I BREAKPOINT SVC97 FAILED WITH A PROTECTION VIOLATION

Explanation: A module is being accessed which is either a supervisor key or is running under an SVRB. This is invalid; the session is ended.

Module: IGC0009G

Audience: TEST user

IKJ57023I PROGRAM UNDER TEST HAS TERMINATED NORMALLY

Explanation: The program being tested has reached successful termination. The user may enter further TEST subcommands.

Module: IKJEGMNL

Audience: TEST user

IKJ57024I AT *address*

Explanation: Program being tested is stopped at the indicated breakpoint.

Module: IKJEGMNL

Audience: TEST user

IKJ57025I PROGRAM UNDER TEST HAS TERMINATED

Explanation: The program being tested has terminated and TEST is terminating.

Module: IKJEGMNL

Audience: TEST user

IKJ57026I VECTOR SYSTEM PARAMETERS

Explanation: The system displays the vector system parameters.

System action: Processing continues.

User response: None.

Module: IKJEGLPV

Audience: TEST LISTVP user

IKJ57027I THE VCT|VIX VALUE IS NOT VALID. THE SETVSR REQUEST IS NOT PERFORMED.

Explanation: The value specified for the VCT or VIX operand of the TEST SETVSR subcommand is greater than the system section size. This condition is not allowed.

System action: The system does not execute the subcommand.

User response: Reissue the subcommand with the correct VCT or VIX operand value. You may first issue the TEST LISTVP subcommand to find out the section size value.

Module: TSO/E TEST command.

IKJ57028I BREAKPOINT PROCESSING NOT AVAILABLE AND LIST SUBCOMMAND RESTRICTED DUE TO A SYSTEM ERROR

Explanation: An error occurred during initialization of TSO/E TEST (e.g. routine AS MADOP could not be loaded). See second-level message for an explanation of the error. See "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438 for the descriptions of second-level messages.

System action: TSO/E TEST will continue to initialize.

User response: Notify your system programmer.

Module: TSO/E TEST command.

IKJ57031I INVALID BREAKPOINT ADDRESS *address*

Explanation: The specified address is not the address of a breakpoint.

Module: IKJEGOFF

Audience: TEST user

IKJ57036I NO BREAKPOINT FOUND

Explanation: Removal of a breakpoint was requested. However, there were no breakpoints found on the active or deferred queue.

Module: IKJEGOFF

Audience: TEST user

IKJ57060I VALUE BEGINNING *nnnnn* INVALID

Explanation: The value entered on the assignment command is invalid. The second-level message indicates why.

Module: IKJEGCVT

Audience: TEST user

IKJ57061I • IKJ57241I

IKJ57061I UNABLE TO MODIFY CONTENTS OF REGISTER(S)

Explanation: Due to an error in SVC 97, TEST was unable to modify the indicated registers.

Module: IKJEGASN

Audience: TEST user

IKJ57063I LENGTH ERROR FOR VALUE BEGINNING *nnnnn*

Explanation: The length of the data string (value) was too long for the indicated register.

Module: IKJEGASN

Audience: TEST user

IKJ57064I DATA TYPE ERROR FOR VALUE BEGINNING *nnnnn*

Explanation: A register was indicated but with an invalid data type for the register. See the second-level message for valid data types for the register. See "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438 for the descriptions of second-level messages.

Module: IKJEGASN

Audience: TEST user

IKJ57066I DATA AREA CONTAINED BREAKPOINT(S)

Explanation: The area of storage that was modified contained breakpoints, which were removed.

Module: IKJEGASN

Audience: TEST user

IKJ57090A ENTER COMMAND FOR CP

Explanation: This message is the prompting message that is issued when CP has been specified on the TEST command, which indicates a test of a command processor. The user should enter his command for his command processor test.

Module: IKJEGMNL

Audience: TEST user

IKJ57209I DCB FIELD NAME REQUIRED AFTER FIELD KEYWORD

Explanation: The name of the DCB field has been omitted.

Module: IKJEGDCB

Audience: TEST user

IKJ57219I TCB FIELD NAME REQUIRED AFTER FIELD KEYWORD

Explanation: A field in the TCB was not specified with the FIELD keyword.

Module: IKJEGTCB

Audience: TEST user

IKJ57241I INVALID *nnnnn*

Explanation: The user has supplied a length or multiplicity value less than 1 or greater than 256.

Module: IKJEGLST

Audience: TEST user

IKJ57242I RANGE EXTENDS INTO PROTECTED STORAGE

Explanation: The specified address range extends into read-protected storage.

Module: IKJEGLSA

Audience: TEST user

IKJ57243I INVALID LENGTH FOR TYPE *type*

Explanation: The specified length value is not compatible with data type.

Module: IKJEGLSA

Audience: TEST user

IKJ57244I INVALID DATA FOR TYPE *type*

Explanation: The data in storage is not consistent with type requested.

Module: IKJEGLSA

Audience: TEST user

IKJ57245I INVALID INSTRUCTION CODE AT *address*

Explanation: The op code is not a System z[®] machine instruction.

Module: IKJEGLSA

Audience: TEST user

IKJ57246I LIST REQUEST INCOMPLETE

Explanation: The LIST request extends beyond highest machine address.

Module: IKJEGLST

Audience: TEST user

IKJ57247I INVALID DATA FOR TYPE P

Explanation: An invalid packed decimal character was encountered.

Module: IKJEGLSA

Audience: TEST user

IKJ57272I UNABLE TO QUALIFY *symbol*

Explanation: TEST is not able to complete the QUALIFY request.

Module: IKJEGQFY

Audience: TEST user

IKJ57273I LOADNAME REQUIRED WITH TCB PARAMETER

Explanation: The user failed to supply load name.

Module: IKJEGQFY

Audience: TEST user

IKJ57274I • IKJ57296I

IKJ57274I SPECIFIED TCB IGNORED

Explanation: The address supplied was not fully qualified.

Module: IKJEGQFY

Audience: LISTDSI user

IKJ57277I QUALIFICATION IS UNDER TCB AT *address*

Explanation: The message is issued after the QUALIFY request has been performed.

Module: IKJEGQFY

Audience: TEST user

IKJ57280I ADDRESS *symbol* NOT FOUND

Explanation: The indicated symbol cannot be located by the symbol processor of TSO/E TEST. There should be an accompanying second-level message with a specific message.

Module: IKJEGSYM

Audience: TEST user

IKJ57281I SYMBOL *symbol* NOT AVAILABLE, SYSTEM ERROR

Explanation: Some system function failed. There should be an accompanying second-level message.

Module: IKJEGSYM

Audience: TEST user

IKJ57282I NOT ENOUGH MAIN STORAGE TO USE SYMBOLS

Explanation: The symbol processor issued an unsuccessful GETMAIN.

Module: IKJEGSYM

Audience: TEST user

IKJ57293I INVALID LENGTH FOR *symbol*, DEFAULTED TO *value*

Explanation: This message is issued if user's supplied length is not compatible with data type.

Module: IKJEGEQU

Audience: TEST user

IKJ57295I INVALID MULTIPLICITY OR LENGTH SPECIFIED

Explanation: The specified value is outside 1 to 256 value range.

Module: IKJEGEQU

Audience: TEST user

IKJ57296I SYMBOL TABLE IS EMPTY

Explanation: The symbol table in storage is empty.

Module: IKJEGEQU

Audience: TEST user

IKJ57297I *symbol* NOT FOUND IN SYMBOL TABLE

Explanation: The symbol to be dropped is not found.

Module: IKJEJEGU

Audience: TEST user

IKJ57302I COMMAND CHAIN TOO LONG

Explanation: The list of commands to be executed at the specified breakpoint(s) is greater than 255 characters in length.

Module: IKJEGAT

Audience: TEST user

IKJ57303I INVALID COUNT *nnnnn*

Explanation: The COUNT value specified is not within the acceptable range of values.

Module: IKJEGAT

Audience: TEST user

IKJ57305I NO BREAKPOINTS ESTABLISHED FROM *relative offset* OF RANGE BEGINNING *address*

Explanation: The breakpoint requested from relative offset through end of range is not established. Breakpoints before the relative offset have been established. See the second-level message for an explanation of the error. See "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438 for the descriptions of second-level messages.

Module: IKJEGAT

Audience: TEST user

IKJ57306I NO BREAKPOINT ESTABLISHED AT *address*

Explanation: The breakpoint specified cannot be established. See the second-level message for an explanation of the error. See "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438 for the descriptions of second-level messages.

Module: IKJEGAT

Audience: TEST user

IKJ57309I UNABLE TO ESTABLISH DEFER BREAKPOINT

Explanation: Breakpoints specified with the DEFER option cannot be established. See the second-level message for an explanation of the error. See "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438 for the descriptions of second-level messages.

Module: IKJEGATD

Audience: TEST user

IKJ57310I BREAKPOINT AT *addr* HAS BEEN DEACTIVATED

Explanation: The GO subcommand was issued to resume execution at a breakpoint. The breakpoint was established on an instruction for which TSO/E TEST only supports a single pass breakpoint. The breakpoint has been removed and will no longer be in effect until the user reestablishes it by using the AT subcommand of TSO/E TEST. See the GO subcommand of TSO/E TEST in *z/OS TSO/E Command Reference* for a list of instructions which support only single pass breakpoints.

Module: IKJEGGO

Audience: TEST user

IKJ57334I DEB DOES NOT HAVE A DIRECT ACCESS SECTION

Explanation: The DEB does not contain a DASD section.

Module: IKJEGDEB

Audience: TEST user

IKJ57335I DEB FIELD NAME REQUIRED AFTER FIELD KEYWORD

Explanation: This message is issued when the user omits the DEB field name.

Module: IKJEGDEB

Audience: TEST user

IKJ57336I DATA HAS BEEN LOST DURING I/O PROCESSING

Explanation: An error was detected when the CESD/SYM records were being read from auxiliary storage. Module IKJEGSYM was attempting to resolve CSECT/SYMBOL addresses.

Module: IKJEGSYM

Audience: TEST user

IKJ57370I UNABLE TO LOAD PROGRAM

Explanation: Due to an OPEN error or BLDL error, the LOAD subcommand was unable to satisfy the user's request.

Module: IKJEGLDF

Audience: TEST user

IKJ57371I The Binder service has returned return code *return_code* reason code *reason_code*

Explanation: The TEST command or subcommand invoked the Binder service to perform a task, but the task could not be performed.

System action: The TEST command or subcommand ends without performing the user's request.

System programmer response: Discover why the given return and reason codes were issued and correct the problem. See *DFSMS/MVS Version 1 Release 2: Program Management* for information related to the return and reason codes.

Module: IKJEGSYM

Audience: TEST user

IKJ57375I STORAGE AT *address*

Explanation: Storage was acquired successfully at this address by the GETMAIN command.

Module: IKJEGLDF

Audience: TEST user

IKJ57378I ZERO BYTES IS INVALID COUNT FOR GETMAIN

Explanation: A specified number of bytes (other than 0) must be specified with the GETMAIN command.

Module: IKJEGLDF

Audience: TEST user

IKJ57379I MEMBER NAME MISSING, RESPECIFY

Explanation: The user did not specify a member name to be loaded from the PDS specified with a LOAD subcommand.

Module: IKJEGLDF

Audience: TEST user

IKJ57382I ENTRY POINT AT *address* AMODE=*xx*

Explanation: The LOAD service routine successfully loaded the requested module at the address indicated in the message.

Module: IKJEGLDF

Audience: TEST user

IKJ57395I MAP COMPLETE

Explanation: LISTMAP is complete.

Module: IKJEGMAP

Audience: TEST user

IKJ57400I PERMANENT I/O ERROR

Explanation: I/O synad error exit is taken.

Module: IKJEGIO

Audience: TEST user

IKJ57401I UNABLE TO OPEN DATA SET

Explanation: OPEN failed to open data set successfully.

Module: IKJEGIO

Audience: TEST user

IKJ57404I TEST SVC 61 FAILED WITH A PROTECTION VIOLATION

Explanation: A module is being accessed which is either in a supervisor key or is running under SVRB. This operation is impermissible; therefore, deferred breakpoints are not activated and symbols are not available.

Module: IGC0006A

Audience: TEST user

IKJ57405I UNABLE TO PRINT INTO DATA SET *dsname*

Explanation: The specified data set is not compatible with access method.

Module: IKJEGIO

Audience: TEST user

IKJ57430I *subcommand_name* FAILED

Explanation: The subcommand specified could not complete due to an error. See second-level messages for an explanation of the error.

Module: IKJEGGO IKJEGLDR IKJEGSTA

Audience: TEST user

IKJ57454I • IKJ57501I

IKJ57454I INVALID FROM ADDRESS

Explanation: An invalid copy-from address has been specified for the COPY subcommand.

Module: IKJEGCPY

Audience: TEST user

IKJ57455I INVALID TO ADDRESS *address*

Explanation: The specified address is not usable.

Module: IKJEGAT IKJEGCPY IKJEGEQU

Audience: TEST user

IKJ57456I INVALID LENGTH *len*

Explanation: An invalid length was specified for the COPY subcommand.

Module: IKJEGCPY

Audience: TEST user

IKJ57457I INVALID ADDRESS RANGE BEGINNING *address*

Explanation: FROM and TO addresses are not compatible.

Module: IKJEGAT

Audience: TEST user

IKJ57461I COMMAND NOT FOUND

Explanation: The function requested in HELP command does not exist in SYS1.HELP data set.

Module: IKJEGCIV

Audience: TEST user

IKJ57462I *command_name* ENDED DUE TO ERROR

Explanation: The specified command is terminated due to an error. See second-level message for an explanation of the error.

Module: IKJEGCIV

Audience: TEST user

IKJ57501I TEST ENDED DUE TO ERROR +

Explanation: An unrecoverable error has occurred that will not allow TEST to continue. The reason for termination is described in the second-level message.

Module: IKJEGINT IKJEGMNL

Audience: TEST user

IKJ57xxxI Second-Level Messages

The following set of messages (see "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438) all with the same identifier IKJ57xxxI, is an alphabetical listing of second-level messages. These second-level messages are issued in conjunction with the first-level message IKJ57501I. If you receive two IKJ57501I messages, one of which contains message text TEST ENDED DUE TO ERROR + and a second with different text, scan the following list for the second-level message and its meaning.

IKJ57xxxI A PREVIOUS TEST REQUEST IS STILL ACTIVE

Explanation: You have made a test request for an APPC/MVS transaction program and a previous request is still active. APPC/MVS supports only one test request from an address space at a time.

System action: TEST is terminated.

User response: Cancel the previous test request by logging off or wait for the previous test to complete then submit this test request.

Module: TEST

Audience: Application programmer

IKJ57xxxI APPC IS NOT AVAILABLE

Explanation: APPC/MVS is not active or the APPC/MVS test enablement service is not active. It is possible that APPC/MVS is being restarted.

System action: TEST is terminated.

User response: Contact your system programmer.

Problem determination: System programmers should check the status of APPC/MVS. If APPC/MVS is active, check the SYSLOG to see if message ATB400I is issued. ATB400I indicates that the APPC/MVS test enablement service is not active.

Module: TEST

Audience: Application programmer

IKJ57xxxI APPC SYSTEM ERROR

Explanation: The test request to APPC/MVS failed due to an APPC/MVS system error.

System action: TEST is terminated.

User response: Report this problem to your system programmer.

Problem determination: A return code of 16 has been received from REGISTER_TEST or ACCEPT_TEST services of APPC/MVS. Refer to *MVS Component Diagnosis* for more information about these services and the return code.

Module: TEST

Audience: Application programmer

IKJ57xxxI BASE LU HAS NOT BEEN DEFINED FOR YOU

Explanation: The user started TEST with the BASELU keyword (or by the default), but there is no base LU defined for the user.

System action: TEST is terminated.

User response: Start TEST again with an LU name that represents a defined LU or ask your system programmer to define a base LU for you.

Module: TEST

Audience: Application programmer

IKJ57xxxI ERROR OCCURRED DURING TP PROFILE PROCESSING

Explanation: APPC/MVS failed to update the user-level transaction program profile to register the test request.

System action: TEST is terminated.

User response: Report this message to your system programmer.

Problem determination: When TEST registered the test request through the REGISTER_TEST callable service, it received return code 48. Refer to *MVS Component Diagnosis: APPC Component* for a description of the return code.

IKJ57xxxI

Module: TEST

Audience: Application programmer

IKJ57xxxI REQUESTED LU DOES NOT SUPPORT USER LEVEL TP PROFILES

Explanation: The installation does not allow user-level transaction program profiles for the LU specified on the TEST command. TEST needs the user-level transaction program profile to register the test request to APPC/MVS.

System action: TEST is terminated.

User response: Contact your system programmer to obtain the name of an LU that allows user-level profiles and use it to test your transaction program.

Module: TEST

Audience: Application programmer

IKJ57xxxI SECLABEL CHECK FAILED

Explanation: When SECLABEL checking is active, TEST cannot be used to test transaction programs in a LU=LOCAL environment.

System action: TEST is terminated.

User response: Test the transaction program in an environment other than LU=LOCAL.

Module: TEST

Audience: Application programmer

IKJ57xxxI TEST REQUEST FAILED. START TEST AGAIN

Explanation: When TSO/E TEST issued ACCEPT_TEST to accept the test request, the test request no longer existed. This may be caused by an APPC/MVS restart or an UNREGISTER_TEST request issued by another program on behalf of the user.

System action: TEST is terminated.

User response: Invoke TEST again. This will reregister the test request.

Audience: Application programmer

IKJ57xxxI THE LU NAME IS NOT SYNTACTICALLY VALID

Explanation: The LU name specified in the TEST command is not syntactically correct.

System action: TEST is terminated.

User response: Start TEST with a valid LU name.

Module: TEST

Audience: Application programmer

IKJ57xxxI THE LU NAME SPECIFIED IS UNDEFINED

Explanation: The LU name specified for the LU keyword is undefined.

System action: TEST is terminated.

User response: Start TEST again with an LU name that represents a defined LU.

Module: TEST

Audience: Application programmer

IKJ57xxxI THE TEST REQUEST FOR THIS TP HAS BEEN CANCELLED

Explanation: While the user is waiting for the inbound attach request, the test request is canceled for a reason other than that the user hit the attention key, such as a program issuing an UNREGISTER_TEST request on behalf of the user.

System action: TEST is terminated.

User response: If the user wants to continue to test the transaction program, start TEST again.

Module: TEST

Audience: Application programmer

IKJ57xxxI THE TP NAME IS NOT SYNTACTICALLY VALID

Explanation: APPC/MVS rejected this test request because the transaction program name is not syntactically correct. The transaction program name can have a length of 1 to 64 characters and can include any character from the character set 00640, which is composed of the uppercase and lowercase letters A through Z, numerals 0–9, and 19 special characters: .<(+&*);-/,%_>?:'="

System action: TEST is terminated.

User response: Invoke TEST using a valid transaction program name.

Module: TEST

Audience: Application programmer

IKJ57xxxI TP ALREADY EXISTS

Explanation: A transaction program already exists in the user's address space. Because APPC/MVS only supports one transaction program per address space, TEST is not able to invoke the transaction program that you requested.

System action: TEST is terminated.

User response: Log off and then log on with a logon procedure that does not initiate any APPC/MVS conversations (for example, allocation of DFM data sets).

Module: TEST

Audience: Application programmer

IKJ57xxxI TP MUST BE SPECIFIED WHEN KEEPTP IS SPECIFIED

Explanation: The keyword TP must be specified when KEEPTP is specified.

System action: TEST is terminated.

User response: Start TEST again with the TP keyword if you want to test an inbound transaction program, or without the KEEPTP keyword if you want to test an ordinary program.

Module: TEST

Audience: Application programmer

IKJ57xxxI TP MUST BE SPECIFIED WHEN LU OR BASELU IS SPECIFIED

Explanation: The keyword TP must be specified when one of the keywords, LU, or BASELU is specified.

System action: TEST is terminated.

User response: Start TEST again with the TP keyword if you want to test an inbound transaction program, or without the LU or BASELU keyword if you want to test an ordinary program.

Module: TEST

Audience: Application programmer

IKJ57xxxI YOU ARE NOT AUTHORIZED TO ACCESS THE USER LEVEL PROFILE FOR THIS TP

Explanation: You are not authorized to access the user-level transaction program profile for this transaction program name for the LU that you are using. You need to be authorized to access your user-level transaction program profile for the transaction program name that you specified to test the transaction program.

System action: TEST is terminated.

User response: Check if the transaction program name has been correctly specified. If it is correctly specified, contact your system security administrator to receive appropriate authorization.

Module:

TEST

Audience: Application programmer

IKJ57502I INVALID ADDRESS *address*

Explanation: An invalid address has been entered. See the second-level message for an explanation of the error. See "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438 for the descriptions of second-level messages.

Module: IKJEGASN IKJEGAT IKJEGCOM IKJEGCVT IKJEGDCB IKJEGDEB IKJEGEQU IKJEGGO IKJ EGLST IKJEGOFF IKJEGPSW IKJEGPCH IKJEGQFY IKJEGVSR

Audience: TEST user

IKJ57503I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: Not enough dynamic main storage could be obtained to allow the requested function to be completed.

Module: IKJEGDCB IKJEGDEB IKJEGEQU IKJEGGO IKJ EGLST IKJEGMAP IKJEGOFF IKJEGPCH IKJEGPSW

Audience: TEST user

IKJ57504I *command_name* FAILED, COMMAND SYSTEM ERROR

Explanation: An error has occurred and the module cannot continue. See the second-level message for an explanation of the error. See "IKJ57xxxI" on page 438 through "IKJ57xxxI" on page 438 for the descriptions of second-level messages for the descriptions of second-level messages.

Module: IKJEGAT IKJEGDCB IKJEGDEB IKJEGGO IKJEGINT IKJ EGLST IKJEGOFF IKJEGQFY

Audience: TEST user

IKJ57507I *module* FAILED

Explanation: The message is issued if the module is currently stopped at the address to be qualified.

Module: IKJEGQFY

Audience: TEST user

IKJ57522I YOU CAN ATTACH THE TP NOW

Explanation: APPC/MVS and TEST are now ready to receive the inbound attach request for the transaction program to be tested. The user may now attach the transaction program to be tested.

User response: Start the program that will attach the transaction program to be tested.

Module: IKJEGINT

Audience: Application programmer

IKJ57600I **FETCH ERROR IN** *module*

Explanation: LOAD or LINK SVC returned an abend code of 106.

Module: IGC0006A

Audience: TEST user

IKJ57601I **BAD PARAMETER LIST PASSED TO SVC** *svc_name_in_module* +

Explanation: LOAD or LINK SVC returned an abend code of 206.

Module: IGC0006A

Audience: TEST user

IKJ57602I **SVC** *svc_name* **REQUESTED TO LOAD ONLY MODULE** *in_module* +

Explanation: LOAD or LINK SVC returned an abend code of 406.

Module: IGC0006A

Audience: TEST user

IKJ57603I **A NON-AUTHORIZED COPY OF A SYSTEM ROUTINE WAS FOUND BY SVC**
svc_name_in_module +

Explanation: LOAD or LINK SVC returned an abend code of 306.

SVC *svc_name_in_module* **ATTEMPTED TO USE A MODULE FLAGGED NOT EXECUTABLE BY LKED**

Explanation: LOAD or LINK SVC returned an abend code of 706.

Module: IGC0006A

Audience: TEST user

IKJ57604I **MODULE NOT FOUND BY SVC** *svc_name_in_module* +

Explanation: LOAD or LINK SVC returned an abend code of 806.

Module: IGC0006A

Audience: TEST user

IKJ57605I **SVC** *svc_name_in_module* **CAUSED THE COUNT OF A REUSABLE LOAD MODULE TO EXCEED**
255 +

Explanation: LOAD, LINK, XCTL, or ATTACH returned an abend code of 906, or a return code of 4 or 8.

Module: IGC0006A

Audience: TEST user

IKJ57606I **SVC** *svc_name_in_module* **DETECTED AN INTERLOCK IN USING A SERIALLY REUSABLE**
MODULE

Explanation: LOAD, LINK, XCTL, or ATTACH returned an abend code of A06.

Module: CALLER

Audience: TEST user

IKJ57607I ESTAE IN A TEST MODULE WAS NOT AN INITIAL BRANCH ENTRY WITH THE CREATE OPTION +

Explanation: A TEST program issued an ESTAE and received a return code of 8.

Module: IKJEGIO

Audience: TEST user

IKJ57608I ESTAE IN A TEST MODULE EXIT ROUTINE OR PARM LIST WAS NOT VALID +

Explanation: A TEST program issued an ESTAE and received a return code of 12.

Module: IKJEGIO

Audience: TEST user

IKJ57609I ESTAE IN A TEST MODULE WAS ISSUED. THE SVC ENCOUNTERED AN UNEXPECTED ERROR WHILE PROCESSING +

Explanation: A TEST program issued an ESTAE and received a return code of 16.

Module: IKJEGIO

Audience: TEST user

IKJ57610I ESTAE IN A TEST MODULE WAS UNABLE TO OBTAIN STORAGE FOR AN SCB +

Explanation: A TEST program issued an ESTAE and received a return code of 20.

Module: IKJEGIO

Audience: TEST user

IKJ57611I ESTAE IN A TEST MODULE SETLOCK ENCOUNTERED AN ERROR CONDITION +

Explanation: A TEST program issued an ESTAE and received a return code of 24.

Module: IKJEGIO

Audience: TEST user

IKJ57612I ESTAE IN A TEST MODULE WAS NOT AN INITIAL BRANCH ENTRY WITH THE CREATE OPTION +

Explanation: A TEST program issued an ESTAE and received a return code of 28.

Module: IKJEGIO

Audience: TEST user

IKJ57613I FREEMAIN IN A TEST MODULE WAS UNABLE TO FREE STORAGE +

Explanation: A TEST program issued a FREEMAIN and received a return code of 4.

Module: IKJEGIO

Audience: TEST user

IKJ57614I FREEMAIN IN A TEST MODULE ATTEMPTED TO FREE STORAGE THAT WAS FIXED +

Explanation: A TEST program issued a FREEMAIN and received a return code of 8.

Module: IKJEGIO

Audience: TEST user

IKJ57615I GETMAIN IN A TEST MODULE WAS UNABLE TO OBTAIN ADDITIONAL STORAGE +

Explanation: A TEST program issued a GETMAIN and received a return code of 4.

Module: IKJEGIO

Audience: TEST user

IKJ57616I GETMAIN IN A TEST MODULE ATTEMPTED TO OBTAIN REAL PAGE STORAGE FOR SQA ON LSQA +

Explanation: A TEST program issued a GETMAIN and received a return code of 8.

Module: IKJEGIO

Audience: TEST user

IKJ57617I ESTAE FAILED TO PASS THE EXIT ADDRESS WHEN CANCELING NON-EXISTENT ESTAE REQUEST +

Explanation: A TEST program issued an ESTAE and received a return code of 4.

Module: IKJEGIO

Audience: TEST user

IKJ57650I ADDRESS *address* IS ABOVE 16 MEGABYTES. CURRENT ADDRESSING MODE IS 24-BIT. POSSIBLE USER ERROR. +

Explanation: This message is a warning that an address requested on the PARM, RESUME or RETURN keywords of the CALL subcommand is above the 16 MB line. Because the tested program is either in 24-bit addressing mode or the user specified AMODE(24), the called program may not work properly. If the CALL does not work as expected, reissue the CALL subcommand specifying AMODE(31).

Module: IKJEGGO

Audience: TEST user

IKJ57651I INVALID AMODE OPERAND *operand*

Explanation: You have entered an invalid AMODE operand on the CALL GO, or RUN subcommands. Reenter the subcommand with a valid addressing mode: 24, 31 or SWITCH.

Module: IKJEGGO

Audience: TEST user

IKJ57652I *control block* LOCATED AT *address*

Explanation: Before formatting the control block on the LISTDCB, LISTPSW, LISTDEB, or LISTTCB subcommands, the TSO/E TEST command processor displays the address of the control block.

Module: IKJEGDCB IKJEGDEB IKJEGPSW IKJEGTCB

Audience: TEST user

IKJ57653I TEST FAILED. LOGOFF AND THEN LOGON TO USE TEST

Explanation: The TSO/E TEST command processor has terminated because it was unable to initialize the data areas necessary to perform its processing. To use TEST, LOGOFF and then LOGON.

Module: IKJEGINT

Audience: TEST user

IKJ57654I **MODULE *name* ALREADY LOADED IN USER'S ADDRESS SPACE. MODULE NAME IDENTICAL TO SPECIFIED MEMBER NAME.**

Explanation: Rename the module so that it is not identical to the name of the module already loaded in your address space.

Module: IKJEGHDR

Audience: TEST user

IKJ57655I **TESTED PROGRAM WAS EXECUTING IN CROSS MEMORY MODE AND CANNOT BE RESTARTED IN THAT ENVIRONMENT**

Explanation: An attention request interrupted the program being tested and destroyed the cross-memory environment. Do not attempt to use TEST to restart the program in cross-memory mode. Do not specify subcommands such as GO, RUN or WHERE without operands.

Module: IKJEGATN

Audience: TEST user

IKJ57656I **BREAKPOINTS FOUND IN TO DATA AREA**

Explanation: The TSO/E TEST command processor has removed breakpoints pointed to by the second operand of an AND, OR or COPY subcommand. The processor removed the breakpoints while executing the subcommand.

Module: IKJEGCPY

Audience: TEST user

IKJ57657I **SPECIFIED ADDRESS *address* IS ABOVE 16 MEGABYTES BUT CURRENT ADDRESSING MODE IS 24-BIT +**

Explanation: The address specified on the subcommand is above 16 MB and cannot be executed in 24-bit mode. Either the tested program is in 24-bit addressing mode or AMODE(24) has been specified on CALL, GO or RUN subcommands. If the address is correct, reenter the subcommand adding the AMODE(31) operand. If the address is incorrect, reenter the subcommand while specifying the correct address and an appropriate value for the AMODE operand.

Module: IKJEGGO

Audience: TEST user

IKJ57658I **INFORMATION FOR SUBPOOLS IS INCOMPLETE**

Explanation: The LISTMAP subcommand processor has terminated after displaying the information available from the Virtual Storage Manager (VSM). Due to a problem with VSM, all of the information is not available.

Module: IKJEGMAP

Audience: TEST user

IKJ57659I **ERROR OBTAINING SUBPOOL INFORMATION**

Explanation: The LISTMAP subcommand processor of TSO/E TEST was unable to display subpool information because of an error with the Virtual Storage Manager (VSM).

Module: IKJEGMAP

Audience: TEST user

IKJ57660I DSNAME WHEN FULLY QUALIFIED WILL EXCEED 44 CHARACTERS

Explanation: You have entered a data set name as an operand of the PRINT keyword. That name will exceed 44 characters when fully qualified with the user ID. A data set name cannot be longer than 44 characters.

Module: IKJEGIO

Audience: TEST user

IKJ57661I NO BREAKPOINT ESTABLISHED AT *relative offset* IN THE RANGE BEGINNING AT *address* +

Explanation: No breakpoint is set for the specified instruction. TSO/E TEST does not support breakpoints for the PC (program call), PT (Program Transfer), SAC (Set Address Space Control), and SSAR (Set Secondary ASID) instructions.

Module: IKJEGAT

Audience: TEST user

IKJ57662I COMMAND ENTERED IS NOT PROCESSED BECAUSE TEST ENVIRONMENT ENDED DUE TO UNRECOVERABLE ERROR

Explanation: You are no longer in the TEST environment.

Module: IKJEFT04

Audience: TEST user

IKJ57663I DATA IS NOT PROCESSED BECAUSE THIS SYSTEM DOES NOT SUPPORT THE VECTOR FACILITY.

Explanation: You cannot use the LISTVSR subcommand because the program is executing on a system that does not support the Vector Facility.

Module: IKJEBVSR

Audience: TEST user

IKJ57664I DATA IS NOT PROCESSED BECAUSE THIS TASK HAS NOT USED THE VECTOR FACILITY.

Explanation: The program being executed does not use the Vector Facility. Therefore, you cannot modify or display vector registers, or use the LISTVSR subcommand.

Module: IKJEGASN IKJEGLST IKJEGVSR

Audience: TEST user

IKJ57665I TESTAUTH SUBCOMMAND EXIT REQUESTED SUBCOMMAND TERMINATION

Explanation: The TESTAUTH installation exit set a return code indicating that the subcommand should terminate.

System action: The subcommand terminates.

User response: Contact your system programmer with message ID and message content.

Module: IKJGRTR

Audience: TESTAUTH user

IKJ57666I TEST *name* EXIT RETURNED WITH AN INVALID RETURN CODE = *return_code*

Explanation: The indicated installation exit issued an invalid return code.

System action: The TEST command terminates.

User response: Contact your system programmer with message ID and message content.

Module: IKJGRTR

IKJ57667I • IKJ57703I

Audience: TEST user

IKJ57667I TEST SUBCOMMAND EXIT REQUESTED SUBCOMMAND TERMINATION.

Explanation: The TEST subcommand exit set a return code indicating that the subcommand should terminate.

System action: The subcommand terminates.

User response: Contact your system programmer with message ID and message content.

Module: IKJEGRTR

Audience: TEST user

IKJ57668I TESTAUTH *name* EXIT RETURNED WITH AN INVALID RETURN CODE = *return_code*

Explanation: The indicated installation exit issued an invalid return code.

System action: The TESTAUTH command terminates.

User response: Contact your system programmer with message ID and message content.

Module: IKJEGCOM

Audience: TESTAUTH user

IKJ57700I NO BREAKPOINT ESTABLISHED AT *address*

Explanation: TEST could not establish a breakpoint at the specified address.

System action: The AT subcommand prompts you to reenter the address.

User response: Refer to the second-level message that is issued for more information. Then reenter the address.

Module: IKJEGCVT

Audience: TEST user

IKJ57701I INVALID ALET OR AR VALUE

Explanation: You have specified an invalid value for the ALET or AR keyword.

System action: The system prompts you to reenter the value.

User response: Reenter the value.

Module: IKJEGCVT

Audience: TEST user

IKJ57702I INVALID DCB ADDRESS *address*

Explanation: You have specified an invalid address for a DCB.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCVT

Audience: TEST user

IKJ57703I INVALID DEB ADDRESS *address*

Explanation: You have specified an invalid address for a DEB.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCVT

Audience: TEST user

IKJ57704I INVALID TCB ADDRESS *address*

Explanation: You have specified an invalid address for a TCB.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCVT

Audience: TEST user

IKJ57705I INVALID ADDRESS TO QUALIFY *address*

Explanation: You have specified an invalid address.

System action: The system prompts you to reenter the address.

User response: Reenter the value.

Module: IKJEGCVT

Audience: TEST user

IKJ57706I INVALID ADDRESS *address*

Explanation: You have specified an invalid address.

System action: The system prompts you to reenter the address.

User response: Reenter the value.

Module: IKJEGCVT

Audience: TEST user

IKJ57707I INVALID WHERE LOCATION *address*

Explanation: You have specified an invalid location on the WHERE subcommand.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCVT

Audience: TEST user

IKJ57708I INVALID PSW ADDRESS *address*

Explanation: You have specified an invalid location for the PSW.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCVT

Audience: TEST user

IKJ57709I INVALID VSR ADDRESS *address*

Explanation: You have specified an invalid location for the VSR.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCVT

IKJ57710I • IKJ57715I

Audience: TEST user

IKJ57710I **INVALID ADDRESS** *address*

Explanation: You have specified an invalid address.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCVT

Audience: TEST user

IKJ57711I **INVALID EQUATED ADDRESS** *address*

Explanation: You have specified an invalid address on the EQUATE subcommand.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEQU

Audience: TEST user

IKJ57712I **INVALID ADDRESS** *address*

Explanation: You have specified an invalid address.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCOM

Audience: TEST user

IKJ57713I **INVALID ADDRESS** *address*

Explanation: You have specified an invalid address.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCOM

Audience: TEST user

IKJ57714I **INVALID ADDRESS** *address*

Explanation: You have specified an invalid address.

System action: The system prompts you to reenter the address.

User response: Reenter the address.

Module: IKJEGCOM

Audience: TEST user

IKJ57715I **The address qualified by the specified ALET or AR is not accessible.**

Explanation: The user attempted to display storage with the list command, but the storage was not accessible to the program being tested. The storage that was to be displayed was an address qualified by either an ALET or an access register (AR). The combination of the address and the ALET or AR pointed to storage that was not accessible to the program that was being tested.

System action: The LIST subcommand ends.

User response: Determine whether the address specified was not valid, whether the ALET or AR was not valid, or whether the combination of both was not valid. Try the LIST subcommand again if you determine that you specified a value incorrectly.

Module: LIST subcommand of TEST

Audience: All TSO/E users

IKJ57800I THE TESTAUTH COMMAND HAS BEEN TERMINATED BECAUSE SECURITY VERIFICATION COULD NOT BE PERFORMED. SECURITY PRODUCT RETURN CODE *return_code* REASON CODE *reason_code*.

Explanation: The security product used at your installation could not process the security verification request for the TESTAUTH resource.

System action: The TESTAUTH command terminates.

User response: Contact your system programmer with the security product return code and reason code.

Module: IKJEFT09

Audience: TESTAUTH user

IKJ57801I THE TESTAUTH COMMAND HAS BEEN TERMINATED BECAUSE A RECOVERY ENVIRONMENT COULD NOT BE ESTABLISHED.

Explanation: The ESTAE SVC indicated an error occurred while attempting to establish the recovery environment.

System action: The TESTAUTH command terminates.

User response: Contact your system programmer with message ID and message content.

Module: IKJEFT09

Audience: TESTAUTH user

IKJ57802I THE TESTAUTH COMMAND HAS BEEN TERMINATED BECAUSE IT HAS NOT BEEN INVOKED IN AN APF-AUTHORIZED ENVIRONMENT.

Explanation: The TESTAUTH command can be run only in an APF-authorized environment.

System action: The TESTAUTH command terminates.

User response: Contact your system programmer with the message ID and message content.

Module: IKJEFT09

Audience: TESTAUTH user

IKJ57803I THE TESTAUTH COMMAND HAS BEEN TERMINATED BECAUSE YOU ARE NOT AUTHORIZED TO USE THIS FUNCTION.

Explanation: You are not authorized to use the TESTAUTH command.

System action: The TESTAUTH command terminates.

User response: Contact your system management. With their approval, you can be authorized to use the TESTAUTH command.

Module: IKJEFT09

Audience: TESTAUTH user

IKJ58101I UNABLE TO PROTECT DATA SET *dsname* + PASSWORD DATA SET NOT FOUND PASSWORD DATA SET FULL I/O ERROR IN PASSWORD DATA SET

Explanation: Password protection was not applied to the specified data set.

Module: IKJEHPRO

IKJ58102I • IKJ58106I

Program: PROTECT

IKJ58102I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: A GETMAIN was issued and no space was available.

Module: IKJEHPRO

Program: PROTECT

IKJ58103I DATA SET *dsname* NOT IN CATALOG

Explanation: The partially-qualified data set names not cataloged cannot be protected using the TSO/E PROTECT command.

Module: IKJEHPRO

Program: PROTECT

IKJ58104I UNABLE TO MODIFY PROTECTION FLAGS OF DATA SET *dsname* +

Explanation: DSCB of the data set could not be modified; however, entry was made in the PASSWORD data set. See message IEH222I in *z/OS MVS System Messages, Vol 8 (IEF-IGD)* for recovery procedures.

DATA SET NOT IN CATALOG

Explanation: The data set could not be located because it was not cataloged.

DATA SET NOT ON VOLUME

Explanation: The data set was not on the volume indicated in the catalog entry.

DATA SPACE OWNED BY VSAM

Explanation: VSAM data set cannot be protected with the PROTECT command.

REQUIRED VOLUME NOT MOUNTED

Explanation: The volume containing the data set was not on the system. The device holding the data set may have been dynamically reconfigured. Note that the PROTECT command does not support dynamic UCBs.

TAPE DATA SET CANNOT BE PROTECTED BY PROTECT

Explanation: The PROTECT command cannot be used to protect tape data sets.

I/O ERROR WHILE UPDATING SECURITY FLAGS

Explanation: An error occurred while attempting to change the protection flags of a data set.

DATA SET IN USE

Explanation: The data set is currently in use.

Module: IKJEHPRO

Program: PROTECT

IKJ58105I INCORRECT PASSWORD ENTERED TWICE

Explanation: This message is issued while entering passwords as the result of a prompt.

Module: IKJEHPRO

Program: PROTECT

IKJ58106I PASSWORD ALREADY EXISTS

Explanation: The user attempted to add or replace a duplicate name that already existed.

Module: IKJEHPRO

Program: PROTECT

IKJ58107I PASSWORD DOES NOT EXIST

Explanation: The user attempted to delete or replace a nonexistent password.

Module: IKJEHPRO

Program: PROTECT

IKJ58108I PROTECT IS FOR DATA SETS, NOT MEMBERS

Explanation: A member name was entered.

Module: IKJEHPRO

Program: PROTECT

IKJ58109I USER DATA FIELD BLANK

Explanation: The user attempted to list a blank data field.

Module: IKJEHPRO

Program: PROTECT

IKJ58110I INCORRECT CONTROL PASSWORD

Explanation: The control password supplied was incorrect.

Module: IKJEHPRO

Program: PROTECT

IKJ58111I INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS

Explanation: The *dsname* entered was longer than 44 characters.

Module: IKJEHPRO

Program: PROTECT

IKJ58112I COMMAND SYSTEM ERROR +

Explanation: An error occurred as a result of other than an invalid command entry.

PARSE ERROR CODE *error_code*

DEFAULT ERROR CODE *error_code*

SVC 98 RETURN CODE *error_code*

Module: IKJEHPRO

Program: PROTECT

IKJ58201I DATA SET *dsname* NOT IN CATALOG

Explanation: The fully-qualified name could not be determined.

Module: IKJEHRN2

Program: RENAME

IKJ58202I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: A GETMAIN was issued and no space was available.

Module: IKJEHRN2

Program: RENAME

IKJ58203I • IKJ58207I

IKJ58203I DATA SET *dsname* NOT RENAMED, EXPIRATION DATE HAS NOT PASSED + SYSTEM OPERATOR DID NOT AUTHORIZE ACCESS TO DATA SET

Module: IKJEHRN2

Program: RENAME

IKJ58204I DATA SET *dsname* NOT USABLE + OPEN ERROR CODE *error_code*

Explanation: RENAME is unable to open data set.

Module: IKJEHRN2

Program: RENAME

IKJ58205I INVALID USE OF ALIAS KEYWORD + ALIAS VALID ONLY FOR MEMBERS OF PARTITIONED DATA SETS

Explanation: RENAME can be used to assign aliases only to members of partitioned data sets.

Module: IKJEHRN2

Program: RENAME

IKJ58206I INVALID USE OF * IN DSNAME + MORE THAN ONE * IN DATA SET NAME

Explanation: An asterisk '*' cannot be specified for more than one qualifier in the data set name.

*** NOT VALID AS FIRST INDEX LEVEL**

Explanation: An asterisk '*' cannot be specified as the first-level qualifier in the data set name.

DATA SET NAMES USED * AT DIFFERENT LEVELS

Explanation: An asterisk '*' was specified as a qualifier in the current data set name. An asterisk was also specified as a qualifier in the new data set name but at a different level.

*** CANNOT BE USED WITH MEMBER**

Explanation: An asterisk '*' cannot be specified as a qualifier in the data set name when a member name is specified.

Module: IKJEHRN2

Program: RENAME

IKJ58207I UNABLE TO RENAME DATA SET *dsname* +

Explanation: The data set could not be renamed.

RENAME ERROR CODE *error_code*

Explanation: There was a non-zero return code from the system RENAME macro instruction (probable I/O error).

BLDL ERROR CODE *error_code*

Explanation: A non-zero return code from the system BLDL macro instruction occurred when assigning aliases to members.

STOW ERROR CODE *error_code*

Explanation: A non-zero return code from the system STOW macro instruction occurred when renaming members.

DATA SET RESIDES ON MULTIPLE VOLUMES

Explanation: RENAME does not support multiple volumes on non-SMS-managed volumes.

DUPLICATE DATA SET ON VOLUME

Explanation: The name for the new data set is the same as an existing data set name.

PERMANENT I/O ERROR ON VOLUME

Explanation: A permanent I/O error has occurred on the volume where your data set resides.

RACF AUTHORIZATION CHECK FAILED

Explanation: Alter access for the old data set failed.

DNO DSCB FOUND FOR OLD NAME ON VOLUME

Explanation: No data set control block was found for the existing data set.

Module: IKJEHRN2

Program: RENAME

IKJ58208I INVALID USE OF COMMAND + BOTH MEMBERS MUST BE FROM THE SAME PARTITIONED DATA SET

Explanation: On a RENAME command, the new member name was in a partitioned data set different from the current member name.

A DATA SET CANNOT BE RENAMED TO A MEMBER NAME

Explanation: On a RENAME command, the new name specified a member of a partitioned data set, but the current name was not.

A MEMBER NAME CANNOT BE RENAMED TO A DATA SET

Explanation: On a RENAME command, the new name was not a member of a partitioned data set, but the current name was.

Module: IKJEHRN2

Program: RENAME

IKJ58209I DATA SET NAME REQUIRED WHEN MEMBER *member* SPECIFIED

Explanation: The PDS in which member is located was not specified.

Module: IKJEHRN2

Program: RENAME

IKJ58210I UNABLE TO UNCATALOG DATA SET *dsname* +

Explanation: The system tried and was unable to uncatalog the old data set.

CATALOG ERROR CODE *error_code*

Explanation: There was a non-zero return code from system's CATALOG macro instruction.

Module: IKJEHRN2

Program: RENAME

IKJ58211I DATA SET *dsname* NOT ALLOCATED, TOO MANY DATA SETS + USE FREE COMMAND TO FREE UNUSED DATA SETS

Explanation: The user has allocated the maximum number of data sets.

Module: IKJEHRN2

Program: RENAME

IKJ58212I DATA SET *dsname* NOT ALLOCATED, DATA SET NOT ON VOLUME + CATALOG INFORMATION INCORRECT

Explanation: Either the catalog information was not correct or the data set did not exist.

Module: IKJEHRN2

Program: RENAME

IKJ58213I DATA SET *dsname* NOT ALLOCATED, REQUIRED VOLUME NOT MOUNTED + VOLUME OR CVOL NOT ON SYSTEM AND CANNOT BE ACCESSED

Explanation: An attempt to allocate a data set has failed; a required volume, a CVOL, or a volume containing SYSCTLG was not mounted.

Module: IKJEHRN2

Program: RENAME

IKJ58214I DATA SET *dsname* NOT ALLOCATED, SYSTEM OR INSTALLATION ERROR +

Explanation: The allocation failure was not caused by a user error.

DYNAMIC ALLOCATION ERROR CODE *error_code*

Explanation: There was a non-zero return code from DAIR.

CATALOG I/O ERROR

Explanation: There was a permanent I/O error in catalog.

CATALOG ERROR CODE *error_code*

Explanation: There was a non-zero return code from the system CATALOG macro instruction.

Module: IKJEHRN2

Program: RENAME

IKJ58215I DATA SET *dsname* ALREADY IN USE, TRY LATER + DATA SET IS ALLOCATED TO ANOTHER JOB OR USER

Explanation: The specified data set could not be permanently allocated to this user.

Module: IKJEHRN2

Program: RENAME

IKJ58216I PROPER PASSWORD NOT SUPPLIED OR INVALID RACF AUTHORITY FOR *dsname*

Explanation: Your request to rename the data set indicated in the message failed. Either the data set is password-protected and you omitted the password on the RENAME command, the data set is RACF-protected and you do not have the ALTER authority required to rename it, or the data set is an SMS-managed generation data set (GDS).

Module: IKJEHRN2

Program: RENAME

IKJ58217I SPECIFIED MEMBER NOT IN DATA SET *dsname member*

Explanation: The specified member name could not be found in the specified partitioned data set.

Module: IKJEHRN2

Program: RENAME

IKJ58218I INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS

Explanation: Data set names cannot exceed 44 characters.

Module: IKJEHRN2

Program: RENAME

IKJ58219I NO DATA SETS FOUND TO MATCH * IN DSNAME

Explanation: The catalog did not contain any data sets with specified qualifiers.

Module: IKJEHRN2

Program: RENAME

IKJ58220I DATA SET *dsname* NOT ON A DIRECT ACCESS DEVICE, NOT SUPPORTED

Explanation: Data sets are renamed on direct access devices only.

Module: IKJEHRN2

Program: RENAME

IKJ58221I DATA SET NAME DSNAME RESIDES ON MULTIPLE VOLUMES, NOT SUPPORTED

Explanation: RENAME does not support multiple volume renaming.

Module: IKJEHRN2

Program: RENAME

IKJ58222I DATA SET *dsname* ALREADY EXISTS

Explanation: A data set is already cataloged or exists on the volume.

Module: IKJEHRN2

Program: RENAME

IKJ58223I MEMBER *member* ALREADY EXISTS

Explanation: PDS cannot contain duplicate member names.

Module: IKJEHRN2

Program: RENAME

IKJ58224I MEMBER SPECIFIED BUT *dsname* NOT A PARTITIONED DATA SET

Explanation: Member applies to a partitioned data set only.

Module: IKJEHRN2

Program: RENAME

IKJ58225I COMMAND SYSTEM ERROR +

Explanation: The error was not the result of an invalid command.

PARSE ERROR CODE *error_code*

DAIR ERROR CODE *error_code*

DEFAULT ERROR CODE *error_code*

Module: IKJEHRN2

Program: RENAME

IKJ58226I NO SPACE IN DIRECTORY FOR ALIAS

Explanation: The PDS directory was full.

Module: IKJEHRN2

Program: RENAME

IKJ58227I • IKJ58300I

IKJ58227I DATA SET NAME *dsname* WILL CREATE INVALID CATALOG STRUCTURE +

Explanation: The *dsname* cannot be used for a new entry.

A QUALIFIER CANNOT BE BOTH AN INDEX AND THE LAST QUALIFIER OF A DATA SET NAME

Explanation: This data set name is inconsistent with the existing catalogue structure. This may result from entering an incorrect password for a password-protected catalogue. Check for messages IEC113I or IEC331I. (See *z/OS MVS System Messages, Vol 7 (IEB-IEE)*.)

Module: IKJEHRN2

Program: RENAME

IKJ58228I UNABLE TO CATALOG DSNAME + CATALOG ERROR CODE *error_code*

Explanation: The data set was not renamed.

Module: IKJEHRN2

Program: RENAME

IKJ58229I DATA SET *dsname* NOT ALLOCATED + INVALID UNIT IN USER ATTRIBUTE DATA SET

Explanation: The user was not authorized to use specified unit type.

NO UNIT AVAILABLE

Explanation: The on-line unit needed was not available.

Module: IKJEHRN2

Program: RENAME

IKJ58230I UNABLE TO CATALOG OLD DATA SET *dsname*

Explanation: After a RENAME or CATALOG error, an attempt was made to restore the old data set. An error occurred trying to catalog the old data set.

Module: IKJEHRN2

Program: RENAME

IKJ58231I UNABLE TO RENAME SMS-MANAGED DATA SET

Explanation: The SMS-managed data set you requested could not be renamed.

Module: IKJEHRN2

Program: RENAME

IKJ58232I VSAM DATA SETS ARE NOT SUPPORTED.

Explanation: The specified data set is a VSAM data set. RENAME does not support VSAM data sets..

Module: IKJEHRN2

Program: RENAME

IKJ58300I HISTORY NOT AVAILABLE +

Explanation: The history information requested could not be listed.

REQUIRED VOLUME NOT MOUNTED

Explanation: The volume containing the data set was not mounted.

DATA SET NOT ON VOLUME

Explanation: The volume specified in catalog did not contain data set.

LOCATE ERROR CODE *error_code* I/O ERROR DURING OBTAIN, CODE *code*

Module: IKJEHAL1

Program: LISTALC

IKJ58301I MEMBERS NOT AVAILABLE +

Explanation: The PDS members information requested could not be listed.

NOT ENOUGH MAIN STORAGE

Explanation: Main storage was not available for a work area.

DIRECTORY STRUCTURE ERROR

Explanation: The PDS directory structure was in error.

I/O SYNAD ERROR DURING DIRECTORY SEARCH *synad info*

Explanation: The directory could not be read; synad info provides additional information.

Module: IKJEHAL1

Program: LISTALC

IKJ58302I NO DATA SETS ALLOCATED

Explanation: No data sets are allocated to the user.

Module: IKJEHAL1

Program: LISTALC

IKJ58303I NOT ENOUGH MAIN STORAGE TO LIST

Explanation:

- HISTORY
- MEMBERS
- SYSNAMES

Main storage was not available for a work area.

Module: IKJEHAL1

Program: LISTALC

IKJ58304I COMMAND SYSTEM ERROR +

Explanation: The error was not due to the user.

PARSE ERROR CODE *error_code*

Module: IKJEHAL1

Program: LISTALC

IKJ58305I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: Working storage was not available to the parse service routine.

Module: IKJEHAL1

Program: LISTALC

IKJ58400I • IKJ58405I

IKJ58400I LISTDSI FAILED. SEE REASON CODE IN VARIABLE SYSREASON.

Explanation: An error occurred during LISTDSI processing which prevented data set information from being obtained. See the message contained in SYSMSGLVL2 for additional details. To view the message, either type WRITE &SYSMSGLVL2 in your CLIST program or type SAY SYSMSGLVL2 in your exec.

System action: LISTDSI terminates.

User response: The user's response depends on the type of error indicated in &SYSMSGLVL2.

Module: IKJLDI00 IKJLDI04

IKJ58401I ERROR PARSING THE STATEMENT. PARSE SERVICE RETURN CODE IS *return_code*

Explanation: An error occurred while parsing the LISTDSI buffer. The return code from the parse service routine is provided in the message text. See *z/OS TSO/E Programming Services* for an explanation of the PARSE service return codes.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI00

IKJ58402I DYNAMIC ALLOCATION PROCESSING ERROR. SVC99 RETURN CODE IS *return_code*

Explanation: An error occurred during Dynamic Allocation SVC 99 processing. The return code from SVC99 is provided in the message text.

If you cannot solve the problem, contact your system programmer.

System action: LISTDSI terminates.

User response: The user's response depends on the return code from the dynamic allocation routine.

Module: IKJLDI01

IKJ58403I THE DATA SET IS A TYPE THAT CAN NOT BE PROCESSED.

Explanation: The data set type indicated that this data set is of a type which is not supported. Examples of unsupported data set types include null file, terminal file, UNIX file, SYSOUT file, and SYSIN file.

System action: LISTDSI terminates.

User response: The user should make sure the data set is not a null file, terminal file, SYSOUT file, or SYSIN file.

Module: IKJLDI00 IKJLDI04

IKJ58404I ERROR DETERMINING UNIT NAME. IEFEB4UV RETURN CODE IS *return_code*.

Explanation: An error occurred while invoking the IEFEB4UV service routine. The return code from IEFEB4UV is provided in the message text.

If you cannot solve the problem, contact your system programmer.

System action: LISTDSI terminates.

User response: The user's response depends on the return code from the IEFEB4UV routine.

Module: IKJLDI04

IKJ58405I DATA SET NOT CATALOGUED. THE LOCATE MACRO RETURN CODE IS *return_code*.

Explanation: An error occurred while invoking the LOCATE macro. The data set is not cataloged.

System action: LISTDSI terminates.

User response: Verify the data set name, volume serial number, or both. After verifying the data set name and/or volume serial number, either supply LISTDSI with the volume serial number by typing VOLUME(nnnnnn) where

“nnnnnn” represents the volume serial number, or catalog the data set.

Module: IKJLDI00

IKJ58406I ERROR OBTAINING DATA SET NAME. OBTAIN RETURN CODE IS *return_code*.

Explanation: An error occurred while invoking the OBTAIN macro. The OBTAIN return code is provided in the message text. For an explanation of the return code, see *z/OS DFSMSdfp Advanced Services*.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI04

IKJ58407I ERROR FINDING DEVICE TYPE. DEVTYPE MACRO RETURN CODE IS *return_code*.

Explanation: An error occurred while invoking the DEVTYPE macro. The DEVTYPE return code is provided in the message text. For an explanation of the return code, see *z/OS DFSMSdfp Advanced Services*.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI04

IKJ58408I THE DATA SET DOES NOT RESIDE ON A DIRECT ACCESS DEVICE.

Explanation: The input DATA SET to LISTDSI was not on a DASD volume. LISTDSI supports only DASD data sets.

System action: LISTDSI terminates.

User response: Do not use LISTDSI with data sets that do not reside on DASD devices.

Module: IKJLDI00

IKJ58409I HSM MIGRATED THE DATA SET. NORECALL PREVENTS RETRIEVAL.

Explanation: The data set cannot be retrieved to obtain any information.

If you want to recall the data set, reissue LISTDSI specifying the RECALL keyword, but be aware that this action might cause a processing delay.

System action: LISTDSI terminates.

User response: Make sure the data set is not migrated or specify the RECALL keyword.

Module: IKJLDI00

IKJ58410I DIRECTORY INFORMATION NOT OBTAINED.

Explanation: An attempt to obtain directory information has failed. See the message contained in SYMSGLVL2 for additional details. To view the message, either type WRITE &SYMSGLVL2 in your CLIST program or type SAY SYMSGLVL2 in your exec.

System action: LISTDSI provides whatever data set information it can.

User response: The user's response depends on the type of error indicated in SYMSGLVL2.

Module: IKJLDI02

IKJ58411I YOU HAVE INSUFFICIENT AUTHORITY TO ACCESS THE DATA SET.

Explanation: Access to the input data set is restricted. Either RACF has determined that you are not authorized for access, or the NORACF keyword was specified to indicate that RACF cannot be queried about your access authorization.

System action: LISTDSI provides whatever data set information it can without accessing the data set.

IKJ58412I • IKJ58418I

User response: Contact the owner of the data set for authorization or do not specify NORACF.

Module: IKJLDI02

IKJ58412I VSAM DATA SETS ARE NOT SUPPORTED.

Explanation: The specified data set is a VSAM data set. LISTDSI does not support VSAM data sets. The only valid results are the DSORG, UNIT, and VOLUME.

System action: LISTDSI provides only the data set organization, unit, and volume.

User response: Do not use LISTDSI with VSAM data sets.

Module: IKJLDI00

IKJ58413I THE DATA SET COULD NOT BE OPENED.

Explanation: LISTDSI was unable to obtain the data set's directory information because the data set could not be opened to read the directory blocks.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI02

IKJ58414I DEVICE TYPE NOT FOUND IN UNIT CONTROL BLOCK (UCB) TABLES.

Explanation: LISTDSI was unable to find the device type in the Unit Control Block tables.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI04

IKJ58417I *User or system* ABEND CODE *abend_code* REASON CODE *reason_code*

Explanation: An ABEND occurred during LISTDSI processing. The abend code is provided in the message text. If there is a REASON code, it follows the ABEND code. Information as to whether it was a USER or SYSTEM abend is also provided.

If a SYSABEND, SYSUDUMP, or SYSMDUMP file is allocated, a dump will be taken.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI00

IKJ58418I PARTIAL DATA SET INFORMATION NOT OBTAINED.

Explanation: Some data set information is not being displayed because either the data set is a VSAM data set or the data set resides on multiple volumes. LISTDSI does not support VSAM data sets. See the message contained in SYSMSGLVL2 for additional details. To view the message, either type WRITE &SYSMSGLVL2 in your CLIST program or SAY SYSMSGLVL2 in your exec.

System action: LISTDSI returns only partial data set information.

User response: Make sure the data set is not a VSAM data set. If the data set resides on multiple volumes, specify the MULTIVOL keyword to include all volumes in any size calculations.

Module: IKJLDI00

IKJ58419I DATA SET RESIDES ON MULTIPLE VOLUMES.

Explanation: The data set resides on multiple volumes. The data set size information is returned only for the first volume.

System action: LISTDSI returns only partial data set information.

User response: Specify the MULTIVOL keyword to include all volumes in any size calculations. Or specify the VOLUME (volnmX) keyword with the name of one of the volumes on which the data set resides to obtain data set size information for just the specified volume, volnmX.

If both the VOLUME and MULTIVOL keywords are specified, MULTIVOL is ignored.

Module: IKJLDI00

IKJ58420I DEVICE TYPE NOT FOUND IN ELIGIBLE DEVICE TABLE.

Explanation: LISTDSI was unable to find the device type in the eligible device table.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI04

IKJ58421I CATALOG ERROR OCCURRED WHILE TRYING TO LOCATE THE DATA SET.

Explanation: LISTDSI received a return code of 4 from the LOCATE macro, which means that there was a catalog error on that volume. For an explanation of the return code, see *z/OS DFSMSdfp Advanced Services*.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI00

IKJ58422I VOLUME NOT MOUNTED. OBTAIN MACRO RETURN CODE IS 0004.

Explanation: LISTDSI received a return code of 4 from the OBTAIN macro, which means that the volume on which the data set resides was not mounted.

System action: LISTDSI terminates.

User response: Contact the operator and have the volume mounted or contact your system programmer.

Module: IKJLDI04

IKJ58423I PERMANENT I/O ERROR ON VOLUME. OBTAIN MACRO RETURN CODE IS 0012.

Explanation: LISTDSI received a return code of 12 from the OBTAIN macro, which means that the volume on which the data set resides has a permanent I/O error.

System action: LISTDSI terminates.

User response: Contact your system programmer.

Module: IKJLDI04

IKJ58424I DATA SET NOT FOUND BY OBTAIN MACRO. RETURN CODE IS 0008.

Explanation: LISTDSI received a return code of 8 from the OBTAIN macro, which means that the data set was not found.

If you specified a volume serial (volser) ID, verify that it is correct. Also verify that the data set name is correct.

System action: LISTDSI terminates.

User response: If you are unable to solve the problem, contact your system programmer.

Module: IKJLDI04

IKJ58425I DATA SET MIGRATED TO A NON-DASD DEVICE.

Explanation: The data set has been migrated to a non-DASD device. The RECALL keyword has not been specified. LISTDSI will recall only data sets on DASD devices unless RECALL is specified. Specifying RECALL for a data set that is on a non-DASD device causes the terminal session to wait until the data set has been recalled.

System action: LISTDSI terminates.

User response: Reissue LISTDSI with the RECALL keyword. Be aware that when this is done, the performance of LISTDSI will decrease due to the delay caused by having the data set staged up to a point where data set information can be obtained.

Module: IKJLDI00

IKJ58427I NO VOLUME SERIAL IS ALLOCATED TO THE DATA SET.

Explanation: The DATA SET is a virtual I/O (VIO) data set or a job entry subsystem data set, which LISTDSI cannot process. LISTDSI supports only DASD data sets.

System action: LISTDSI terminates.

User response: Use a data set that resides on a DASD device.

Module: IKJLDI01

IKJ58428I DDNAME MUST BE ONE TO EIGHT CHARACTERS.

Explanation: The ddname you provided does not have from one to eight characters.

System action: LISTDSI terminates.

User response: You must make sure the ddname specified is from one to eight characters. You may have specified a ddname that is too long.

Module: IKJLDI00

IKJ58429I DATA SET NAME OR DDNAME MUST BE SPECIFIED.

Explanation: You issued LISTDSI without a data set name or ddname.

System action: LISTDSI terminates.

User response: Specify a valid data set name or ddname with LISTDSI.

Module: IKJLDI00

IKJ58430I Parameter SMSINFO is specified, however the data set is not SMS-managed.

Explanation: This message is preceded by message IKJ58418I. SMS information has been requested by either:

- The CLIST LISTDSI statement with the SMSINFO keyword operand, or
- The REXX LISTDSI function with the SMSINFO argument.

However, the specified data set is not SMS-managed.

Note: Message IKJ58430I is issued when SMSINFO is specified for a non-SMS-managed PDSE data set. The SMSINFO keyword is not necessary for this type of data set.

System action: LISTDSI continues. However, no SMS information is provided.

User response: If SMSINFO has been specified erroneously, ignore the message or remove the keyword.

Module: IKJLDI00

IKJ58431I ISITMGD Return Code: *return_code* Reason Code: *reason_code*

Explanation: This message is preceded by message IKJ58418I. SMS information has been requested by either:

- The CLIST LISTDSI statement with the SMSINFO keyword operand, or
- The CLIST LISTDSI statement with the DIRECTORY keyword operand, or
- The REXX LISTDSI function with the SMSINFO argument, or
- The REXX LISTDSI function with the DIRECTORY argument.

An internal service that is used by LISTDSI (the ISITMGD macro) returned an unexpected return and reason code. For an explanation of the return codes and reason codes, see *z/OS DFSMS Macro Instructions for Data Sets*.

System action: LISTDSI continues. However, no SMS information is provided.

User response: Contact your system programmer to determine the reason why the ISITMGD macro has failed.

Module: IKJLDI00

IKJ58432I Unable to retrieve SMS info, DFSMS has incorrect level.

Explanation: This message is preceded by message IKJ58418I. SMS information has been requested by either:

- The CLIST LISTDSI statement with the SMSINFO keyword operand, or
- The CLIST LISTDSI statement with the DIRECTORY keyword operand, or
- The REXX LISTDSI function with the SMSINFO argument, or
- The REXX LISTDSI function with the DIRECTORY argument.

However, this requires DFSMS/MVS 1.4 (or later) to be active on your system.

System action: LISTDSI continues. However, no SMS information is provided.

User response: Contact your system programmer to determine the level of the DFSMS/MVS or MVS/DFP.

Module: IKJLDI00

IKJ58433I THE SPECIFIED DATA SET IS A NON-SMS-MANAGED PDSE WHICH IS NOT SUPPORTED AT THE CURRENT LEVEL OF DFSMSDFP.

Explanation: This message is preceded by message IKJ58418I. DIRECTORY information has been requested for a non-SMS-managed PDSE data set by one of the following:

- The CLIST LISTDSI statement with the DIRECTORY keyword operand
- The REXX LISTDSI function with the DIRECTORY argument

However, the level of DFSMSdfp does not support non-SMS-managed PDSE data sets.

System action: LISTDSI continues. However, not all DIRECTORY information is provided.

User response: Contact your system programmer to install the appropriate level of DFSMSdfp to support non-SMS-managed PDSE data sets.

Module: IKJLDI00

IKJ58434I Unable to retrieve SMS information, OPEN error.

Explanation: This message is preceded by message IKJ58418I. SMS information has been requested by either:

- The CLIST LISTDSI statement with the SMSINFO keyword operand, or
- The CLIST LISTDSI statement with the DIRECTORY keyword operand, or
- The REXX LISTDSI function with the SMSINFO argument, or
- The REXX LISTDSI function with the DIRECTORY argument.

An error is encountered when attempting to open the data set to retrieve SMS information.

System action: LISTDSI continues. However, no SMS information is provided.

User response: Contact your system programmer.

IKJ58435I • IKJ58500I

Module: IKJLDI00

IKJ58435I Unexpected error returned by IGWFAMS.

Explanation: This message is preceded by message IKJ58418I. SMS information has been requested by either:

- The CLIST LISTDSI statement with the SMSINFO keyword operand, or
- The CLIST LISTDSI statement with the DIRECTORY keyword operand, or
- The REXX LISTDSI function with the SMSINFO argument, or
- The REXX LISTDSI function with the DIRECTORY argument.

The DFSMS/MVS service IGWFAMS, used internally by LISTDSI, has returned an unexpected return code. The problem may be caused by an incorrect setup of DFSMS/MVS.

System action: LISTDSI continues. However, no SMS information is provided.

User response: Contact your system programmer to diagnose the problem with DFSMS/MVS.

Module: IKJLDI00

IKJ58436I Unexpected error returned by the SMS service module.

Explanation: This message is preceded by message IKJ58418I.

- The CLIST LISTDSI statement with the SMSINFO keyword operand, or
- The CLIST LISTDSI statement with the DIRECTORY keyword operand, or
- The REXX LISTDSI function with the SMSINFO argument, or
- The REXX LISTDSI function with the DIRECTORY argument.

However, an internal error has been encountered within the LISTDSI command processor.

System action: LISTDSI continues. However, no SMS information is provided.

User response: If the IKJLDIxx modules of the LISTDSI command processor have not been changed, contact your IBM support personnel.

Module: IKJLDI00

IKJ58437I Unexpected error returned by IGGCSI00.

Explanation: This message is preceded by message IKJ58418I. SMS information has been requested by either

- The CLIST LISTDSI statement with the SMSINFO keyword operand, or
- The REXX LISTDSI function with the SMSINFO argument.

The DFSMS Catalog Search Interface either could not be loaded, or returned an unexpected return code. The problem may be caused by an incorrect setup of DFSMS.

System action: LISTDSI continues. However, no SMS information is provided.

User response: Contact your system programmer to either diagnose the problem with DFSMS or to grant you READ access to the data sets in question. The latter might allow LISTDSI to obtain SMS information by using a different DFSMS service.

Module: IKJLDI00

IKJ58500I DATA SET ATTRIBUTES NOT AVAILABLE +

Explanation: The DSCB was not usable for the specified data set. The message may also be caused by an attempt to do a LISTDS of a subsystem data set (such as a JES2 or JES3 SYSYOUT or SYSIN data set).

OBTAIN ERROR CODE *error_code* **VOLUME NOT ON SYSTEM AND CANNOT BE ACCESSED**

Module: IKJEHDS1

Program: LISTDS

IKJ58501I MEMBERS NOT AVAILABLE +

Explanation: The members information for PDS could not be listed.

NOT ENOUGH MAIN STORAGE

Explanation: Main storage was not available for work area.

DIRECTORY STRUCTURE ERROR

Explanation: The PDS directory structure was in error.

I/O SYNAD ERROR DURING DIRECTORY SEARCH *synad info*

Explanation: The directory cannot be read; synad info provides additional information.

Module: IKJEHMEM

Program: LISTDS

IKJ58502I DIRECTORY INFORMATION NOT AVAILABLE +

Explanation: PDS directory information could not be listed.

MEMBER NOT FOUND

Explanation: The specified member was not in the data set.

I/O ERROR DURING BLDL

Explanation: BLDL macro detected an error in the PDS directory.

DATA SET IS NOT A PARTITIONED**DATA SET**

Module: IKJEHDS1

Program: LISTDS

IKJ58503I DATA SET *dsname* NOT IN CATALOG

Explanation: The specified data set name was not cataloged.

Module: IKJEHDS1

Program: LISTDS

IKJ58504I COMPLETE VOLUME LIST NOT AVAILABLE + LOCATE ERROR CODE *error_code*

Explanation: There was a non-zero return code from the LOCATE macro instruction.

ALLOCATION INFORMATION NOT AVAILABLE

Explanation: The data set resided on more than five volumes, but only five volumes could be retrieved.

Module: IKJEHDS1

Program: LISTDS

IKJ58505I LABEL INFORMATION NOT AVAILABLE +

Explanation: The data set label could not be read.

OBTAIN ERROR CODE *error_code*

Module: IKJEHLBL

Program: LISTDS

IKJ58506I DATA SET *dsname* NOT ALLOCATED, TOO MANY DATA SETS + USE FREE COMMAND TO FREE UNUSED DATA SETS

Explanation: The user has allocated the maximum number of data sets.

Module: IKJEHDS1

Program: LISTDS

IKJ58507I DATA SET *dsname* NOT ALLOCATED, REQUIRED VOLUME NOT MOUNTED + VOLUME NOT ON SYSTEM AND CANNOT BE ACCESSED

Explanation: An attempt to allocate a data set has failed; a required volume, a CVOL, or a volume containing SYSCTLG was not mounted.

Module: IKJEHDS1

Program: LISTDS

IKJ58508I DATA SET *dsname* NOT ALLOCATED, SYSTEM OR INSTALLATION ERROR +

Explanation: Failure to allocate data set was not due to user.

DYNAMIC ALLOCATION ERROR CODE *error_code*

Explanation: There was a non-zero return code from the DAIR service routine.

CATALOG I/O ERROR

Explanation: The CATALOG macro instruction detected an I/O error.

Module: IKJEHDS1

Program: LISTDS

IKJ58509I DATA SET NAME REQUIRED WHEN MEMBER *member* IS SPECIFIED

Explanation: The user did not specify name of the PDS.

Module: IKJEHDS1

Program: LISTDS

IKJ58510I DATA SET *dsname* ALREADY IN USE TRY LATER + DATA SET IS ALLOCATED TO ANOTHER USER OR JOB

Explanation: The data set was allocated to another user or was permanently allocated to the requestor.

Module: IKJEHDS1

Program: LISTDS

IKJ58511I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: Working storage was not available to the parse service routine.

Module: IKJEHDS1

Program: LISTDS

IKJ58512I COMMAND SYSTEM ERROR +

Explanation: The error was not caused by the user.

PARSE ERROR CODE *error_code*

DYNAMIC ALLOCATION ERROR CODE *error_code*

Explanation: There was a non-zero return code from the DAIR service routine.

Module: IKJEHDS1

Program: LISTDS

IKJ58513I INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS

Explanation: Data set names cannot exceed 44 characters.

Module: IKJEHDS1

Program: LISTDS

IKJ58514I DATA SET *dsname* NOT USABLE + OPEN ERROR CODE *error_code* OPEN CODE *error_code*

Explanation: OPEN macro instruction abended with the specified return code.

Module: IKJEHDS1

Program: LISTDS

IKJ58516I INVALID USE OF * IN *dsname* + * NOT ALLOWED AT FIRST LEVEL

Explanation: An asterisk '*' cannot be specified as the first-level qualifier in the data set name.

MORE THAN ONE * NOT ALLOWED

Explanation: An asterisk '*' cannot be specified for more than one qualifier in the data set name.

Module: IKJEHDS1

Program: LISTDS

IKJ58517I UNABLE TO LIST * NAME OR LEVEL + * NOT ALLOWED AT FIRST LEVEL

Explanation: An asterisk '*' cannot be specified as the first-level qualifier in the data set name.

MORE THAN ONE * NOT ALLOWED

Explanation: An asterisk '*' cannot be specified for more than one qualifier in the data set name.

Module: IKJEHDS1

Program: LISTDS

IKJ58518I UNABLE TO COMPLETE PROCESSING FOR ENTRY *dsname*

Explanation: Your request failed because the system was unable to retrieve the information associated with the data set. LOCATE macro processing set a non-zero return code.

LOCATE ERROR CODE *error_code*

Explanation: Error code *error_code* is the return code from the LOCATE macro.

User response: For an explanation of the return code, see *z/OS DFSMSdfp Advanced Services*, or *z/OS MVS System Messages, Vol 6 (GOS-IEA)* under message IDC3009I.

Module: IKJEHDS1

Program: LISTDS

IKJ58600I QUALIFIERS FOR DATA SET *dsname* ARE valid qualifiers

Explanation: Valid qualifiers for the given data set are listed.

Module: IKJEHDEF

Program: DEFAULT

IKJ58601A • IKJ58606A

IKJ58601A ENTER QUALIFIER +

Explanation: The user is being prompted to enter a valid qualifier for the given data set.

DATA SET NAME WAS NOT FULLY QUALIFIED ENTER DESIRED QUALIFIER FROM ABOVE LIST

Explanation: Select a valid qualifier for the given data set.

Module: IKJEHDEF

Program: DEFAULT

IKJ58602I INVALID QUALIFIER *nnnnnnnnnnnn*

Explanation: The qualifier selected is invalid for the given data set.

Module: IKJEHDEF

Program: DEFAULT

IKJ58603A REENTER +

Explanation: Enter a valid qualifier for the given data set.

ONLY QUALIFIERS LISTED ARE VALID QUALIFIERS FOR THIS DATA SET NAME REENTER DESIRED QUALIFIER FROM ABOVE LIST

Explanation: Select a valid qualifier for the given data set.

QUALIFIERS CONTAIN FROM 1 TO 8 ALPHANUMERIC CHARACTERS REENTER

Explanation: Enter a valid qualifier for the given data set.

Module: IKJEHDEF

Program: DEFAULT

IKJ58604A ENTER OLD OR NEW QUALIFIER +

Explanation: Enter a valid old or new qualifier for given data set.

DATA SET NAME WAS NOT FULLY QUALIFIED ENTER NEW QUALIFIER OR ONE FROM ABOVE LIST

Explanation: Enter a valid qualifier for the given data set.

Module: IKJEHDEF

Program: DEFAULT

IKJ58605I DATA SET NAME *dsname* NOT COMPLETE

Explanation: Enter a valid data set name containing 1 to 44 alphanumeric characters.

Module: IKJEHDEF

Program: DEFAULT

IKJ58606A ENTER QUALIFIER FOR *dsname* +

Explanation: Select a valid qualifier for the given data set.

DATA SET NAME WAS NOT FULLY QUALIFIED ENTER NEW QUALIFIER

Explanation: Enter a valid qualifier for the given data set name.

Module: IKJEHDEF

Program: DEFAULT

IKJ58607I DATA SET *dsname* IS ABOUT TO BE REUSED

Explanation: The data set name given is a duplicate but may be used.

Module: IKJEHDEF

Program: DEFAULT

IKJ58608A ENTER CARRIER RETURN TO CONTINUE OR ATTENTION TO RESPECIFY COMMAND

Explanation: Choose either continued processing of the current command or entering of a new command.

Module: IKJEHDEF

Program: DEFAULT

IKJ58609I DATA SET NAME *dsname* CANNOT BE RESOLVED; SYSTEM ERROR

Explanation: The data set name is not valid in the catalog, causing a system error.

PUTLINE ERROR CODE *error_code*

PUTGET ERROR CODE *error_code*

LOCATE ERROR CODE *error_code*

GETMAIN ERROR CODE *error_code*

Module: IKJEHDEF

Program: DEFAULT

IKJ58610I DATA SET NAME *dsname* NOT FULLY QUALIFIED

Explanation: Enter a valid qualifier for the given data set name.

Module: IKJEHDEF

Program: DEFAULT

IKJ58611E BROADCAST DATA SET NOT USABLE + I/O SYNAD ERROR CANNOT OPEN DATA SET

Explanation: There was either an OPEN error or an I/O error on the broadcast data set.

User response: Contact your system programmer.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58613E USER ATTRIBUTE DATA SET NOT USABLE + CANNOT OPEN DATA SET

Explanation: OPEN failed for the UADS data set. The file was not allocated.

User response: Contact your system programmer.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58614E NO SPACE IN BROADCAST DATA SET FOR USERIDS

Explanation: The SYNC command attempted to add the user IDs from the UADS, the TSO/E segment, or both of the RACF data base. The mail section of the broadcast data set is full and cannot accommodate more user IDs.

User response: Have your system programmer allocate a larger broadcast data set, and reissue the SYNC command.

Module: SYNC

Audience: SYNC command user

IKJ58616I BROADCAST DATA SET INITIALIZED AND SYNCHRONIZED

Explanation: The SYNC command ended with a return code of zero. The broadcast data set was synchronized as requested.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58617I BROADCAST DATA SET WAS NOT SYNCHRONIZED WITH THE RACF DATA BASE. + RACF MUST BE INSTALLED TO SYNCHRONIZE WITH THE RACF DATA BASE

Explanation: The SYNC command was unable to synchronize the broadcast data set with the TSO/E segment of the RACF data base. RACF must be installed to perform the synchronization.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58618I SYNC TERMINATED. USER UNAUTHORIZED TO ISSUE SYNC COMMAND. + USER MUST HAVE ACCOUNT AUTHORITY TO ISSUE THE SYNC COMMAND.

Explanation: You do not have ACCOUNT authority, which is required to issue the SYNC command. Your installation's TSO/E administrator must give you ACCOUNT authority. After ACCOUNT authority has been given to you, reissue the SYNC command.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58619E BROADCAST DATA SET NOT SYNCHRONIZED WITH THE UADS DATA SET. + THE USER ATTRIBUTE DATA SET (UADS) IS NOT ALLOCATED TO DDNAME 'SYSUADS'

Explanation: You used either the UADS or BOTH parameter on the SYNC command. The synchronization did not occur because the user attribute data set is not allocated to the ddname SYSUADS. If your installation uses the UADS to maintain user information, allocate the UADS to the ddname SYSUADS, and reissue the SYNC command. Otherwise, issue the SYNC command with the RACF operand to synchronize the broadcast data set with the TSO/E segment of the RACF data base.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58620E SYNC TERMINATED. THE COMMAND WAS NOT INVOKED AUTHORIZED.

Explanation: The SYNC command was issued with either the BOTH or the RACF operand, and was not invoked in an authorized environment. In order for the broadcast data set to be synchronized with the TSO/E segment of the RACF data base, the command must be defined to the system as an authorized command. Have your system programmer define SYNC as an authorized command.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58621E SYNC TERMINATED. RECOVERY ENVIRONMENT WAS NOT ESTABLISHED. + A RETURN CODE OF *return_code* WAS RECEIVED WHEN ATTEMPTING TO ESTABLISH RECOVERY.

Explanation: An unexpected return code was received after the SYNC command issued the ESTAE macro to establish a recovery environment. Contact your system programmer.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58622E SYNC TERMINATED. COULD NOT PARSE THE COMMAND BUFFER. + THE PARSE SERVICE ROUTINE ISSUED A RETURN CODE OF *return_code*

Explanation: The parse service routine was invoked to parse the command buffer for the operand. A return code other than zero was returned from the parse service routine. Contact your system programmer.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58624E SYNC TERMINATED. INPUT DATA SETS ARE NOT USABLE. + UADS IS NOT ALLOCATED TO DDNAME 'SYSUADS' AND RACF VERSION 1.8 OR HIGHER IS NOT INSTALLED

Explanation: You specified the BOTH operand on the SYNC command. The UADS is not allocated to the ddname SYSUADS, and RACF is not installed on the system. Allocate the UADS to ddname SYSUADS and reissue the SYNC command with the UADS operand.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58625I BROADCAST DATA SET SYNCHRONIZED WITH RACF DATA BASE ONLY. + THE USER ATTRIBUTE DATA SET (UADS) IS NOT ALLOCATED TO DDNAME 'SYSUADS'

Explanation: You specified the BOTH operand on the SYNC command, and the UADS is not allocated to the ddname SYSUADS. SYNC synchronized the broadcast data set with the TSO/E segment of the RACF data base.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ58626E BROADCAST DATA SET NOT SYNCHRONIZED. RACF IS NOT ACTIVE.

Explanation: An attempt was made by SYNC to synchronize the broadcast data set with the TSO/E segment of the RACF data base. The SYNC command received a return code from RACF indicating that RACF was inactive.

User response: Contact your system programmer.

Module: IKJRBBBCR

Audience: SYNC command user

IKJ59001I PRINTDS TERMINATED. MUTUALLY EXCLUSIVE OPERANDS WERE SPECIFIED. *Operand* CANNOT BE SPECIFIED WITH *operand*.

Explanation: Two or more mutually exclusive operands were specified on the PRINTDS command. Respecify the operands in error.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59002I PRINTDS TERMINATED. DATA SET *dsname* NOT PARTITIONED OR SEQUENTIAL.

Explanation: An input data set was specified that is neither partitioned nor sequential. You can only print partitioned or sequential data sets.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59003I PRINTDS TERMINATED. DATA SET *dsname* HAS A RECORD FORMAT WHICH IS NOT SUPPORTED. SPANNED, TRACK OVERFLOW, AND UNDEFINED RECORD FORMATS ARE NOT SUPPORTED.

Explanation: The specified data set has a non-valid record format. Only data sets with non-spanned fixed or

IKJ59004I • IKJ59010I

variable record format can be printed using the PRINTDS command. Check the record format of the specified data set.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59004I PRINTDS TERMINATED. *File/todataset* SPECIFIED REFERS TO A SYSOUT DATA SET.

Explanation: The specified FILE name or TODATASET name is allocated to a SYSOUT data set. You cannot print SYSOUT data sets with the PRINTDS command. Change the FILE name or TODATASET name to one that does not refer to a SYSOUT data set and then reissue the PRINTDS command.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59005I PRINTDS TERMINATED. INPUT DATA SET *dsname* IS EMPTY.

Explanation: The specified data set is empty. It was allocated as a new data set and nothing has been written to it.

System action: The PRINTDS command processor terminates.

User response: Change the data set name to a data set that has been written to or put some data in the empty data set and reissue the PRINTDS command.

Module: PRINTDS

Audience: PRINTDS user

IKJ59007I PRINTDS TERMINATED. MEMBER *member* NOT FOUND IN DATA SET *dsname*.

Explanation: The specified member name does not exist in the data set. Correct the data set name and the member name.

Module: IKJEFY52 IKJEFY57

Audience: PRINTDS user

IKJ59008I PRINTDS TERMINATED. UNABLE TO OPEN DATA SET *dsname*.

Explanation: The specified data set could not be opened. Contact your TSO/E administrator for assistance.

Module: IKJEFY57

Audience: PRINTDS user

IKJ59009I UNABLE TO CLOSE DATA SET *dsname*. IT REMAINS OPEN. THIS ERROR OCCURRED AFTER PRINTING SUCCESSFULLY.

Explanation: The specified data set could not be closed. You may have received correct output because the error occurred after printing. If you do not receive correct output, contact your TSO/E administrator for assistance.

Module: IKJEFY57

Audience: PRINTDS user

IKJ59010I PRINTDS TERMINATED. TODATASET *dsname* NOT SEQUENTIAL OR A MEMBER OF A PARTITIONED DATA SET.

Explanation: The specified data set is neither a sequential data set nor a member of a partitioned data set. Specify a sequential data set or a member of a partitioned data set and reissue the PRINTDS command.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59011I PRINTDS TERMINATED. UNABLE TO OPEN A SYSOUT DATA SET.

Explanation: A SYSOUT data set could not be opened. Reissue the PRINTDS command. If the problem recurs, contact your TSO/E administrator for assistance.

Module: IKJEFY57

Audience: PRINTDS user

IKJ59012I UNABLE TO CLOSE A SYSOUT DATA SET. IT REMAINS OPEN.

Explanation: A SYSOUT data set could be closed. This error occurred after printing successfully to all of the SYSOUT data sets. Check your output to see if you can determine the cause of the error. If you do not receive the correct output, contact your TSO/E administrator for assistance.

Module: IKJEFY57

Audience: PRINTDS user

IKJ59013I PRINTDS TERMINATED. A SPECIFIED OUTPUT DESCRIPTOR WAS NOT VALID.

Explanation: One or more of the specified output descriptors does not exist, or one of the output descriptors was specified incorrectly. Check to see if all of the specified output descriptors exist and are defined correctly.

Module: IKJEFY62

Audience: PRINTDS user

IKJ59014I PRINTDS TERMINATED. MORE THAN 4 CHARACTER SETS WERE SPECIFIED.

Explanation: The CHARS operand contains more than four character set names. The maximum is four. Reissue the PRINTDS command with four or less character set names.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59015I PRINTDS TERMINATED. MORE THAN 32 COLUMN PAIRS WERE SPECIFIED.

Explanation: The COLUMNS operand contains more than 32 column pairs. The maximum is 32. Reissue the PRINTDS command with 32 or less column pairs.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59016I PRINTDS TERMINATED. MORE THAN 8 COPY GROUP VALUES WERE SPECIFIED.

Explanation: The COPIES operand contains more than eight copy groups. The maximum is eight. Reissue the PRINTDS command with 8 or less copy groups.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59017I PRINTDS TERMINATED. THE SUM OF THE SPECIFIED COPY GROUP VALUES IS MORE THAN 255.

Explanation: The COPIES operand contains copy group values that add up to more than 255. The maximum is 255. Reissue the PRINTDS command with 255 or less copy group values.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59018I PRINTDS TERMINATED. MORE THAN 128 OUTPUT DESCRIPTORS WERE SPECIFIED.

Explanation: The OUTDES operand contains more than 128 output descriptor names. The maximum is 128. Reissue the PRINTDS command with 128 or less output descriptors names.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59019I PRINTDS TERMINATED. MORE THAN 255 *dsnames* OR SYSOUT *dsnames* WERE SPECIFIED

Explanation: The DATASET or DSNAMES operand was specified with more than 255 data set names, or more than the maximum of 255 SYSOUT data sets were generated by printing the specified input data sets. Try one of the following actions:

- Reissue the PRINTDS command with fewer data set names.
- If printing a partitioned data set with many members causes more than 255 SYSOUT data sets to be generated, split the input data set into several smaller partitioned data sets. Then reissue the PRINTDS command to print each data set separately.
- Use the PRINTDS command to print individual input data set members.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59020I PRINTDS TERMINATED. BOTTOM OR TOP MARGIN CANNOT BE LARGER THAN THE PAGE LENGTH MINUS 6.

Explanation: Either the BMARGIN or the TMARGIN operand contains a value that exceeds the maximum of the page length value minus 6. Reissue the PRINTDS command with a smaller BMARGIN or TMARGIN value, or specify a larger PAGELEN value.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59021I PRINTDS TERMINATED. PAGE LENGTH LESS BOTTOM AND TOP MARGINS MUST BE NO LESS THAN 6.

Explanation: The page length value minus the top and bottom margins is less than the minimum of 6. Reissue the PRINTDS command with valid PAGELEN, BMARGIN, and TMARGIN values.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59023I PRINTDS TERMINATED. NOT ENOUGH SPACE IN TODATASET *name*. ALLOCATE THE DATA SET WITH MORE SPACE AND REISSUE THE PRINTDS COMMAND.

Explanation: The specified TODATASET has not been allocated with enough space to hold all of the requested output. Allocate the TODATASET operand with more space and reissue the PRINTDS command.

Module: IKJEFY59

Audience: PRINTDS user

IKJ59024I THE PRINTDS COMMAND FAILED. ENTER ? FOR MORE INFORMATION.

Explanation: The data set could not be allocated for the reason specified in the message. Check the specified data set to see if you can determine the cause of the error. The message may also be caused by an attempt to do a PRINTDS of a subsystem data set (such as a JES2 or JES3 SYSYOUT or SYSIN data set).

This message is accompanied by any of the following second-level messages: IKJ59049I, IKJ59053I, IKJ59050I, IKJ59054I, IKJ59051I, IKJ59055I, IKJ59052I, IKJ59056I, which describes the error.

Module: IKJEFY52 IKJEFY62

Audience: PRINTDS user

IKJ59025I YOU HAVE EXCEEDED THE INSTALLATION DEFINED LIMIT ON THE MAXIMUM NUMBER OF PRINTED LINES ALLOWED DURING A TSO/E SESSION.

Explanation: A 722 ABEND occurred during processing of the PRINTDS command. The installation-defined maximum number of output lines for the session has been exceeded. Start another TSO/E session and reissue the PRINTDS command. If your input data set is very large, you may want to split the data set into several smaller data sets or use the LINES operand.

Module: IKJEFY59

Audience: PRINTDS user

IKJ59027I DATA SET NAME REQUIRED WITH MEMBER NAME.

Explanation: The DATASET operand was specified with a member name, but with no data set name. You may have accidentally enclosed the data set name within an extra set of parenthesis. For example, if you specify PRINTDS DA((MYDATA)), then PRINTDS assumes (MYDATA) is a member name. Specify the correct data set name. If you want to specify a data set member, enter the data set name followed by the member name in parenthesis. Otherwise, specify the data set name.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59028I PRINTDS TERMINATED. THE SPECIFIED LINE NUMBER LOCATION EXTENDS BEYOND THE END OF RECORD FOR DATA SET *dsname*.

Explanation: The specified line number location using the NUM or SNUM operand extends beyond the end of the record of the indicated data set. The line number location must lie within the logical record. Check the start and length of the line number. Reissue the PRINTDS command with a new line number location and a new line number length.

If the input data set record contains a carriage control or a trc character, then column position 1 refers to the first character position after the carriage control character or trc character.

Module: IKJEFY63

Audience: PRINTDS user

IKJ59029I PRINTDS TERMINATED. THE PRINTDS INSTALLATION EXIT HAS RETURNED A NON-VALID VALUE FOR THE *parm_value* PARAMETER.

Explanation: The value of the indicated parameter, as specified by the installation exit, is not valid. Contact your TSO/E administrator for assistance.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59030I LINE NUMBER WITHIN DATA SET *dsname* IS NOT NUMERIC. RELATIVE RECORD NUMBER *nnn* CONTAINS THE NON-VALID LINE NUMBER. PRINTING IS TERMINATED FOR THIS DATA SET.

Explanation: This message is a warning message. PRINTDS set a return code of 4. The relative record number specified in the message is the number (starting from the top of the data set or member) of the record in error. Printing of the data set or member is terminated. If you are printing a list of input data sets, printing continues with the next data set. If you are printing members of a partitioned data set, printing continues with the next member.

Check if the specified line number location and line number length matches that of the indicated input data set. If the input data set record contains a carriage control or a trc character, then column position 1 refers to the first character position after the carriage control character or trc character.

Module: IKJEFY63

Audience: PRINTDS user

IKJ59031I PRINTDS TERMINATED. A DCF CHARACTER SET NAME WITHIN THE FIRST RECORD OF DATA SET *dsname* CONTAINS MORE THAN FOUR CHARACTERS.

Explanation: The first record of the specified data set contains character set information. One of these character sets contains more than four characters. Check the character set information in the first record. It might be necessary to re-create the input data set using DCF. You may also print the data set using the NODCF operand. PRINTDS will then ignore all of the character set names, but the formatting might also be incorrect.

Module: IKJEFY63

Audience: PRINTDS user

IKJ59032I PRINTDS TERMINATED. A DCF CHARACTER SET NAME WITHIN THE FIRST RECORD OF DATA SET *dsname* CONTAINS A NON-VALID CHARACTER.

Explanation: The first record of the specified data set contains character set information. One of these character sets contains a non-valid character. Check the character set information in the first record. It might be necessary to re-create the input data set using DCF. You may also print the data set using the NODCF operand. PRINTDS will then ignore all of the character set names, but the formatting might also be incorrect.

Module: IKJEFY63

Audience: PRINTDS user

IKJ59033I PRINTDS TERMINATED. INPUT DATA SET *dsname* RESIDES ON MORE THAN ONE VOLUME. ALLOCATE THE TODATASET BEFORE ISSUING THE PRINTDS COMMAND.

Explanation: The specified input data set resides on more than one volume. PRINTDS is unable to calculate the correct amount of DASD space for the TODATASET. Allocate a TODATASET with sufficient space before issuing the PRINTDS command, or print the input data set directly to SYSOUT.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59034I DATA FROM INPUT DATA SET *dsname* MAY BE TRUNCATED WHEN BEING WRITTEN TO TODATASET *name*.

Explanation: The LRECL of your pre-allocated TODATASET is not large enough to hold a maximum length output record. PRINTDS processing continues, but it set a return code of 4. Check to see if your TODATASET contains all of the data from the input or do one of the following:

- Pre-allocate the TODATASET with a larger LRECL and reissue the PRINTDS command.
- Reissue the PRINTDS command specifying a new (not pre-allocated) TODATASET.
- Reissue the PRINTDS command with the COLUMNS operand to print selected columns from the input data set.

Module: IKJEFY53

Audience: PRINTDS user

IKJ59035I PRINTDS TERMINATED. FILE *name* NOT ALLOCATED.

Explanation: The indicated file name was not pre-allocated. Allocate the file before issuing the PRINTDS command.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59036I PRINTDS TERMINATED. UNABLE TO ALLOCATE *todataset/sysout data set* WITH LRECL OR BLKSIZE THAT EXCEEDS 32760 BYTES.

Explanation: PRINTDS has determined that it must allocate a data set with an LRECL or BLKSIZE that exceeds the maximum allowed value of 32760 bytes. This error typically occurs when trying to print an input data set with a fixed record format and an LRECL from 32753 to 32760 bytes to a SYSOUT data set. The maximum size of the data

portion of an input record that can be printed to SYSOUT is 32752 bytes.

If you are trying to print to a SYSOUT data set, use the COLUMNS operand to print just the specific columns that you want to be printed. The sum of all specified columns plus the BIND value must not exceed 32752 when printing to a SYSOUT data set.

If you were trying to print to a new TODATASET, you can pre-allocate the data set with a fixed record format and an LRECL of 32760 before issuing the PRINTDS command.

Module: IKJEFY52 IKJEFY62

Audience: PRINTDS user

IKJ59037I PRINTDS TERMINATED. UNABLE TO PRINT DATA SET *dsname*. INPUT RECORD LENGTH PLUS SPECIFIED BIND VALUE IS MORE THAN 32760 BYTES.

Explanation: The input data set LRECL plus the specified BIND value exceeds 32760 bytes, which requires a SYSOUT data set or TODATASET with LRECL greater than the maximum allowed value of 32760 bytes. Specify a smaller BIND value or use the COLUMNS operand to print selected columns from the input data set. Then reissue the PRINTDS command. The sum of all specified columns plus the BIND value should not exceed 32752 when printing to a SYSOUT data set.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59038I PRINTDS TERMINATED. UNABLE TO PRINT DATA SET *dsname*. SUM OF ALL SPECIFIED COLUMNS IS MORE THAN 32760 BYTES.

Explanation: The sum of all specified columns exceeds 32760, which requires a SYSOUT data set or TODATASET with LRECL greater than the maximum allowed value of 32760 bytes.

Specify fewer column pairs, or specify smaller column ranges. The sum of all column pairs must be less than or equal to 32760 bytes. The sum of all specified columns plus the BIND value should not exceed 32752 when printing to a SYSOUT data set.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59039I PRINTDS TERMINATED. UNABLE TO PRINT DATA SET *dsname*. SUM OF ALL SPECIFIED COLUMNS PLUS SPECIFIED BIND VALUE IS MORE THAN 32760 BYTES.

Explanation: The sum of all specified columns plus the specified BIND value exceeds 32760, which requires a SYSOUT data set or TODATASET with LRECL greater than the maximum allowed value of 32760 bytes.

Specify fewer column pairs, specify smaller column ranges, or specify a smaller BIND value. The sum of all column pairs plus the BIND value must be less than or equal to 32760 bytes.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59040I PRINTDS TERMINATED. SINGLE, DOUBLE, OR TRIPLE OPERAND IS NOT ALLOWED BECAUSE INPUT DATA SET *dsname* REMAINS ANSI OR MACHINE CARRIAGE CONTROL CHARACTERS.

Explanation: The SINGLE, DOUBLE, or TRIPLE operand is not allowed when an input data set contains carriage control characters. SINGLE, DOUBLE, or TRIPLE spacing is not consistent with the line spacing already provided by the carriage control characters within the data set. Reissue the PRINTDS command without specifying SINGLE, DOUBLE, or TRIPLE.

Another alternative is to first use PRINTDS to print the input data set to a pre-allocated TODATASET, where the TODATASET has been pre-allocated without ANSI or MACHINE carriage control. For how to print the input data set this way, see *z/OS TSO/E Command Reference*.

Module: IKJEFY52

IKJ59042I • IKJ59052I

Audience: PRINTDS user

IKJ59042I PRINTDS TERMINATED. SIZE OF THE OUTPUT DATA SET NEEDED EXCEEDS THE MAXIMUM SIZE THAT PRINTDS CAN ALLOCATE FOR A TODATASET.

Explanation: When determining the number of tracks needed for the output dataset, PRINTDS found that it exceeds the maximum number of tracks that PRINTDS can allocate for a LARGE format data set (X'FFFFFF') or for an extended format data set (X'EFFFFF1') per volume. PRINTDS cannot allocate a TODATASET of sufficient size on one volume. The print request fails.

System action: The PRINTDS command processor terminates.

User response: If you specified more than one input data set to PRINTDS, you can try printing them one at a time.

If you specified DOUBLE or TRIPLE spacing, you can try printing with SINGLE spacing.

If you specified printing to a member of a partitioned data set, try specifying a sequential TODATASET.

Alternatively, you can try to pre-allocate an output TODATASET with sufficient size to hold your PRINTDS output. You can pre-allocate the output data set as a multi-volume data set or as an extended format data set, if necessary, to obtain sufficient space. Then reissue the PRINTDS command directing its output to the pre-allocated TODATASET.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59049I (Message text provided by dynamic allocation regarding the SVC99 error.)

Explanation: The data set could not be allocated for the reason specified in the message.

System action: The PRINTDS command processor terminates.

User response: Check the specified data set to see if the cause of the error can be determined.

Module: PRINTDS

Audience: PRINTDS user

IKJ59050I System/user ABEND CODE *abend_code* REASON CODE *reason_code*.

Explanation: The PRINTDS command abnormally terminated with the indicated ABEND and REASON codes. Reissue the PRINTDS command. If the problem recurs, contact your TSO/E administrator for assistance.

Module: IKJEFY59

Audience: PRINTDS user

IKJ59051I RECOVERY ENVIRONMENT COULD NOT BE ESTABLISHED. ESTAE MACRO RETURN CODE WAS *return_code*.

Explanation: The PRINTDS command could not establish recovery. The ESTAE macro returned with the indicated error code. Reissue the PRINTDS command. If the problem recurs, contact your TSO/E administrator for assistance.

Module: IKJEFY50

Audience: PRINTDS user

IKJ59052I DYNAMIC ALLOCATION RETURN CODE *return_code* REASON CODE *reason_code*

Explanation: Dynamic allocation encountered an error when attempting to allocate or deallocate a data set, but it did not pass back a message for this error condition. Reissue the PRINTDS command. If the problem recurs, contact your TSO/E administrator for assistance or to interpret the return and reason codes, see *z/OS MVS Programming: Authorized Assembler Services Guide*.

Module: IKJEFY52 IKJEFY62

Audience: PRINTDS user

IKJ59053I *jobname, stepname, uad, dt, dd_name, opernm, error_description, trkaddr_blknbr, accmth.*

Explanation: (Message text provided by GET/READ or PUT regarding the error.)

An error was found reading (GET/READ) an input record or writing (PUT) an output record. This is an error message returned by the SYNADAF macro (SYNAD exit routine). It contains information formatted as follows:

- *jobname* is the job name
- *stepname* is the stepname
- *uad* is the unit address
- *dt* is the device type
- *dd_name* is the ddname
- *opernm* is the operation attempted
- *error_description* is the error description
- *trkaddr_blknbr* is the track address and the block number
- *accmth* is the access method.

For more information about the SYNADAF macro, see *z/OS DFSMS Macro Instructions for Data Sets*.

System action: The PRINTDS command processor terminates.

User response: Correct the error described by the GET/READ or PUT message text.

Module: IKJEFY57

Audience: PRINTDS user

IKJ59054I **PARSE TERMINATED WITH RETURN CODE** *return_code*.

Explanation: The PARSE service encountered an error. Reissue the PRINTDS command. If the problem recurs, contact your TSO/E administrator for assistance or see *z/OS TSO/E Programming Services* to interpret the return code.

Module: IKJEFY51

Audience: PRINTDS user

IKJ59055I **DATA SET** *dsname* **NOT FOUND. LOCATE MACRO RETURN CODE WAS** *return_code*.

Explanation: The LOCATE macro returned a non-zero return code indicating that the specified data set could not be found. Check the specified data set. Contact your TSO/E administrator for assistance or see *z/OS DFSMSdfp Advanced Services* to interpret the return code. The message may also be caused by an attempt to do a PRINTDS of a subsystem data set (such as a JES2 or JES3 SYSYOUT or SYSIN data set).

Module: IKJEFY52

Audience: PRINTDS user

IKJ59056I **ERROR OBTAINING INFORMATION ON DATA SET** *dsname*. **OBTAIN MACRO RETURN CODE WAS** *return_code*.

Explanation: The OBTAIN macro returned a non-zero return code indicating that information about the specified data set could not be found. Check the specified data set. Contact your TSO/E administrator for assistance or see *z/OS DFSMSdfp Advanced Services* to interpret the return code.

Module: IKJEFY52

Audience: PRINTDS user

IKJ59100E **THE OUTPUT DESCRIPTOR** *outdes* **ALREADY EXISTS +**

IKJ59101E **THE OUTPUT DESCRIPTOR MUST BE FREED BEFORE IT CAN BE SPECIFIED AS NEW**

Explanation: The output descriptor you specified as NEW already exists.

System action: The OUTDES command terminates.

IKJ59102E • IKJ59109E

User response: Either free the output descriptor, and reissue the OUTDES command with the NEW operand, or issue the OUTDES command with the REUSE operand.

Module: IKJEFY01

Audience: OUTDES user

IKJ59102E BATCH OUTPUT DESCRIPTOR *outdes* CANNOT BE REUSED

Explanation: You specified the REUSE operand on the OUTDES command, but the specified output descriptor was created using the OUTPUT JCL statement, and cannot be freed dynamically.

System action: The OUTDES command terminates.

User response: The output descriptor will be freed either after the job runs, or after you log off.

Module: IKJEFY01

Audience: OUTDES user

IKJ59103E DYNAMIC OUTPUT SVC RETURN CODE *return_code* REASON CODE *reason_code*

Explanation: The dynamic output SVC returned *return_code* and *reason_code*. This is a second-level message for IKJ59162E and IKJ59106E.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: IKJEFY04

Audience: OUTDES user

IKJ59106E THE INSTALLATION REJECTED THE DYNAMIC OUTPUT REQUEST

Explanation: The installation exit for the dynamic output SVC returned a return code and a reason code and canceled your request. The second-level message IKJ59103E contains the return and reason codes returned by the dynamic output SVC.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: IKJEFY04

Audience: OUTDES user

IKJ59107E OUTDES TERMINATED DUE TO INSTALLATION EXIT IKJEFY11 +

IKJ59108E TERMINATED WITH REASON CODE *reason_code*

Explanation: The OUTDES command was terminated by exit IKJEFY11. The reason code *reason_code* is issued by the exit.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: IKJEFY01

Audience: OUTDES user

IKJ59109E OUTDES TERMINATED DUE TO INSTALLATION EXIT IKJEFY12 +

IKJ59110E TERMINATED WITH REASON CODE *reason_code*

Explanation: The OUTDES command was terminated by exit IKJEFY12. The reason code *reason_code* is issued by the exit.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: IKJEFY01

Audience: OUTDES user

IKJ59111E OUTDES TERMINATED. INVALID RETURN CODE FROM INSTALLATION EXIT +

IKJ59112E INSTALLATION EXIT RETURN CODE *return_code*

Explanation: The installation exit returned a return code that could not be processed.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: OUTDES

Audience: OUTDES user

IKJ59113E OUTDES TERMINATED. BAD ROUTER RETURN CODE FOR IKJEFY11 +

IKJ59114E ROUTER RETURN CODE *return_code*

Explanation: The TSO/E exit router returned a return code that could not be processed.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: OUTDES

Audience: OUTDES user

IKJ59115E OUTDES TERMINATED. INVALID RETURN CODE FROM INSTALLATION EXIT IKJEFY12 +

IKJ59116E INSTALLATION EXIT RETURN CODE *return_code*

Explanation: The installation exit returned a return code that could not be processed.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: OUTDES

Audience: OUTDES user

IKJ59117E OUTDES TERMINATED. BAD ROUTER RETURN CODE FOR IKJEFY12 +

IKJ59118E ROUTER RETURN CODE *return_code*

Explanation: The TSO/E exit router returned a return code that could not be processed.

System action: The OUTDES command terminates.

User response: Contact your system programmer.

Module: OUTDES

Audience: OUTDES user

IKJ59119E THE OUTPUT DESCRIPTOR IS NOT CREATED +

IKJ59120E THE OUTPUT DESCRIPTOR IS SPECIFIED WITH NO PARAMETERS

Explanation: You did not specify any operands on the OUTDES command. The output descriptor was not created.

System action: The OUTDES command terminates.

User response: Specify valid operands on the OUTDES command and reissue it. For a description of the OUTDES command, see *z/OS TSO/E Command Reference*.

Module: OUTDES

Audience: OUTDES user

IKJ59157I ACCESS OF THE CNCCB WAS UNSUCCESSFUL, THE CNCCB WILL NOT BE DISPLAYED.

Explanation: You specified the CNCCB parameter on the TSODATA verb exit, but the CNCCB cannot be accessed. The access macro IKJVEACM returned an unsuccessful return code.

System action: The TSODATA verb exit ends normally but the CNCCB is not displayed.

User response: Contact your system programmer for assistance.

Module: TSODATA

IKJ59158I STORAGE ACCESSED FOR THE CNCCB MAYBE INVALID. THE CNCCB WILL NOT BE DISPLAYED.

Explanation: Storage accessed for the CNCCB contained an invalid control block identifier.

System action: The TSODATA verb exit ends normally but the CNCCB is not displayed.

User response: Contact your system programmer for assistance.

Module: TSODATA

IKJ59162E UNEXPECTED ERROR OCCURRED IN PROCESSING THE *command_name* COMMAND

Explanation: An error occurred while processing the *command_name* command. The second-level message, IKJ59163I, gives more information about the error.

User response: See the second-level message IKJ59163E, IKJ59164E, or IKJ59103E.

Module: ALLOCATE

Audience: ALLOCATE user

IKJ59163E SCHEDULER JCL FACILITY RETURN CODE *return_code* REASON CODE *reason_code*

Explanation: This second-level message is displayed because the scheduler JCL facility verify routine ended unexpectedly. The return code and reason code are indicated in the message.

User response: Contact your TSO/E administrator for assistance.

Module: ALLOCATE

Audience: ALLOCATE user

IKJ59164E NOT ENOUGH STORAGE FOR TEXT UNIT BUFFER

Explanation: This second-level message is displayed because the system does not have enough virtual storage to allocate the data set.

User response: Contact your TSO/E administrator for assistance.

Module: ALLOCATE

Audience: ALLOCATE user

IKJ59165E OUTDES TERMINATED: OUTDES IS VALID ONLY UNDER A JES2 SUBSYSTEM.

Explanation: You entered the OUTDES command, but you are not running under a JES2 subsystem. The OUTDES command is valid only under a JES2 subsystem.

System action: The OUTDES command terminates.

Module: OUTDES

Audience: OUTDES user

IKJ59200I WHEN SYSTEM ERROR + PARSE ERROR CODE STACK ERROR CODE

Explanation: The WHEN command processor received a parse or stack error code.

Module: IKJEFE11

Program: WHEN

IKJ59202I WHEN COMMAND NOT EXECUTED, NO RETURN CODE + PREVIOUS COMMAND ABENDED WITH A USER ABEND CODE *abend_code* PREVIOUS COMMAND ABENDED WITH A SYSTEM ABEND CODE *abend_code*

Explanation: WHEN detected that the previous command abended.

Module: IKJEFE11

Program: WHEN

IKJ60739I PARSE RETURN CODE IS *return_code* GENTRANS RETURN CODE IS *return_code*

Explanation: Parse returned a code other than 0, 4, or 16 or GENTRANS returned a code other than 0 or 12. This message is the second level to IKJ60743I.

Module: IKJEFATT

Program: ATTRIB

IKJ60741I NOT ENOUGH MAIN STORAGE TO EXECUTE COMMAND

Explanation: Parse or GENTRANS issued a GETMAIN, and no space was available.

Module: IKJEFATT

Program: ATTRIB

IKJ60743I COMMAND SYSTEM ERROR

Explanation: Parse or GENTRANS failure. The second-level message from parse is IKJ60739I.

Module: IKJEFATT

Program: ATTRIB

IKJ76011I DATA SET *dsname* NOT IN CATALOG

Explanation: (1) Either an attempt to allocate a (presumably) existing data set has failed; the data set name was not found in the catalog; or (2) an attempt to allocate a data set other than the load module output or listing output data sets has failed; the data set name is inconsistent with the existing catalog structure.

Prompting for a new data set name will follow.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76013I DATA SET *dsname* NOT IN CATALOG

Explanation: (1) Either an attempt to allocate a (presumably) existing data set has failed; the data set name was not found in the catalog; or (2) an attempt to allocate a data set other than the load module output or listing output data sets has failed; the data set name is inconsistent with the existing catalog structure. Prompting for a new data set name is not possible.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76023I [*text*] NOT ALLOCATED, TOO MANY DATA SETS USE FREE COMMAND TO FREE UNUSED DATA SETS

Explanation: For the item *text* could appear the following:

- *text* = DATA SET *dsname*
- *text* = UTILITY DATA
- *text* = SET

The return code was 16. An attempt to allocate a data set has failed; previous allocations have exhausted the available entries in the task I/O table (TIOT).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76033I DATA SET *dsname* NOT ALLOCATED, DATA SET NOT ON VOLUME + CATALOG INFORMATION INCORRECT

Explanation: The return code is 12, the DAIR return code was X'6708'.

An attempt to allocate a data set has failed; the required DSCB was not found in the VTOC on the required volume.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76043I DATA SET *dsname* NOT ALLOCATED, REQUIRED VOLUME NOT MOUNTED +

Explanation: The DAIR return code was X'08' or X'0C.' An attempt to allocate a data set has failed; a required volume, a CVOL, or a volume containing SYSCTLG was not mounted.

VOLUME OR CVOL NOT ON SYSTEM AND CANNOT BE ACCESSED

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76053I [*text*] NOT ALLOCATED, SYSTEM OR INSTALLATION ERROR

Explanation: For the item *text* could appear the following:

- *text* = DATA SET *dsname*
- *text* = UTILITY DATA
- *text* = SET

An attempt to allocate a data set has failed for one of the reasons below:

DYNAMIC ALLOCATION ERROR CODE *error_code*

Explanation: An error was detected by DAIR in allocating a data set.

CATALOG ERROR CODE *error_code*

Explanation: An error was detected by catalog.

CATALOG I/O ERROR

Explanation: A permanent I/O error occurred while processing the catalog.

DADSM ERROR CODE *error_code*

Explanation: An error was detected by DADSM in allocating a data set.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76063I DATA SET *dsname* ALREADY IN USE, TRY LATER +

Explanation: The DAIR return code was X'0210'.

DATA SET IS ALLOCATED TO ANOTHER JOB OR USER

Explanation: An attempt to allocate a data set has failed; the data set is currently allocated to another user and its disposition is incompatible with the allocation requested (for example, the previous allocation was OLD and the allocation requested was SHR).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76073I CONTROL STATEMENT DATA SET NOT USABLE +

Explanation: The attempt to allocate a data set for the passage of control statements accepted from the terminal to the linkage editor has failed for one of the reasons below.

I/O SYNAD ERROR

Explanation: An I/O error occurred while using the data set specified by the control card.

OPEN ERROR

Explanation: The specified data set could not be opened.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76080A ENTER CONTROL STATEMENTS

Explanation: The user is being prompted for control statements to be accepted from the terminal and passed to the linkage editor (see also message IKJ76083I).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76083I CONTROL STATEMENTS MISSING

Explanation: Control statements were specified to be input from the terminal, but noprompt mode was in effect.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76091I INVALID CONTROL STATEMENT *image* +

Explanation: The control statement entered was not acceptable to the linkage editor.

STATEMENT EXCEEDS 70 CHARACTERS

Explanation: The control statement went past column 70.

INVALID OPERATION

Explanation: The operation specified in the control statement was invalid for the linkage editor.

Module: AKJLKL01

IKJ76100A • IKJ76151I

Program: LINK/LOADGO

IKJ76100A REENTER

Explanation: The user is being prompted for reentry of a linkage editor control statement accepted from the terminal in which an error was detected (see message IKJ76091I).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76111I END OF CONTROL STATEMENTS

Explanation: A null line was encountered indicating the end of terminal input.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76121I INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS

Explanation: A qualified data set name cannot exceed 44 characters. Prompting will be done.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76123I INVALID DATA SET NAME, *dsname* EXCEEDS 44 CHARACTERS

Explanation: A qualified data set name cannot exceed 44 characters. Prompting is not possible.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76133I *dsname* NOT A PARTITIONED DATA SET A [*text*] DATA SET MUST BE PARTITIONED

Explanation: For the item *text* could appear the following:

- *text* = LOAD MODULE
- *text* = LIBRARY

The dynamic allocation return code (converted by DAIR) was X'0330'. The attempt to allocate the library or load module output data set has failed; the data set exists but is not a partitioned data set.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76143I MEMBER *member* NOT IN DATA SET *dsname* +

Explanation: The specified member could not be found in the data set. BLDL returned a non-zero return code.

TEMPNAME ASSUMED AS MEMBER NAME

Explanation: The attempt to allocate an input data set has failed; the specified member name or, by default, the member name tempname, was not found in the partitioned data set.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76151I VALID TYPES FOR DATA SET *dsname* ARE OBJ AND DATA

Explanation: The allocation of an input data set cannot be made because (1) the rightmost qualifier was not specified in the data set name and (2) both of the valid input data sets exist (that is, those data set names which have as their rightmost qualifiers OBJ and DATA). Link command only (see also messages IKJ76170A and IKJ76173I).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76161I VALID TYPES FOR DATA SET *dsname* ARE LOAD AND OBJ

Explanation: The allocation of an input data set cannot be made because (1) the rightmost qualifier was not specified in the data set name and (2) both of the valid input data sets exist (that is, those data set names which have as their rightmost qualifiers OBJ and LOAD). Load command only (see also messages IKJ76170A and IKJ76173I).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76170A ENTER TYPE

Explanation: The user is being prompted for the rightmost qualifier of an input data set name (see messages IKJ76151I and IKJ76161I; see also message IKJ76173I).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76173I TYPE MISSING

Explanation: The allocation of an input data set has failed; because of no-prompt mode, the user could not be prompted for the rightmost qualifier of the input data set name (see message IKJ76151I and IKJ76161I; see also message IKJ76170A).

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76181I MEMBER *member* SPECIFIED BUT *dsname* NOT A PARTITIONED DATA SET

Explanation: A member name was specified for a sequential data set, the dynamic allocation return code (converted by DAIR) was X'0330'.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76193I ERROR IN CONCATENATING [*text*] DATA SETS

Explanation: For the item *text* could appear the following:

- *text* = INPUT
- *text* = LIBRARY

The DAIR return code was 12. Either (1) the attempt to concatenate the input or library data sets has failed, or (2) more than 25 data set names were specified in the input or library data set name list.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76203I COMMAND SYSTEM ERROR +

Explanation: A service routine terminated abnormally.

service_routine **ERROR CODE** *error_code*

Explanation: An attempt to allocate a data set has failed; an error has been detected by a service routine or an abend has occurred in a service routine.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76213I DATA SET *dsname* WILL CREATE INVALID CATALOG STRUCTURE + A QUALIFIER CANNOT BE BOTH AN INDEX AND THE LAST QUALIFIER OF A DATA SET NAME

Explanation: The attempt to allocate a new load module output or listing output data set has failed; the data set name is inconsistent with the existing catalog structure.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76223I DATA SET *dsname* NOT ALLOCATED, NOT ENOUGH SPACE ON VOLUMES +

Explanation: The DAIR return code was X'4714'.

USE DELETE COMMAND TO DELETE UNUSED DATA SETS

Explanation: An attempt to allocate a data set has failed; the quantity of space required is not available.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76231I PARAMETER FIELD TRUNCATED TO 100 CHARACTERS

Explanation: The parameter field passed to the LOADER was longer than 100 characters.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ76241I DYNAMIC ALLOCATION FAILURE - RETURN CODE *return_code*

Explanation: The DAIR and dynamic allocation sequence of processing detected an error during an attempt either (1) to allocate a data set to the terminal, or (2) to allocate a dummy data set.

Module: AKJLKL01

Program: LINK/LOADGO

IKJ79000I UNABLE TO OPEN THE DIRECTORY OF A PDS USING A VARIABLE RECORD FORMAT

Explanation: You used the OPENFILE statement (without specifying a member name) for a partitioned data set allocated with a variable record format. You must use a fixed or undefined record format to access the directory of the PDS.

To access a member of the PDS, specify a member name when allocating the data set.

Module: IKJCT437

IKJ79002I THIS STATEMENT HAS AN INVALID &SYSINDEX START PARAMETER. THE START PARAMETER MUST BE A NON-NEGATIVE WHOLE NUMBER

Explanation: This message is issued when the &SYSINDEX built-in function is specified with an invalid start parameter.

Module: IKJCT439

IKJ79003I THIS STATEMENT HAS AN INVALID &SYSINDEX EXPRESSION

Explanation: This message is issued when the &SYSINDEX built-in function is specified with an invalid target string (the character string for which you are searching) or string (the larger character to be searched). For more information about the &SYSINDEX built-in function, see *z/OS TSO/E CLISTs*.

Module: IKJCT439

IKJ79004I THIS STATEMENT HAS AN INVALID &SYSNSUB LEVEL PARAMETER; THE LEVEL PARAMETER IS A NUMBER 0-99

Explanation: This message is issued when the &SYSNSUB built-in function is specified with an invalid LEVEL parameter.

Module: IKJCT439

IKJ79005I THIS STATEMENT HAS A MISSING &SYSNSUB LEVEL PARAMETER AND/OR EXPRESSION PARAMETER

Explanation: This message is issued when the &SYSNSUB built-in function is specified with one of the required parameters missing.

Module: IKJCT439

IKJ79006I THIS STATEMENT HAS A &SYSNSUB LEVEL PARAMETER THAT HAS USED A BUILT-IN FUNCTION AS A SYMBOLIC VARIABLE

Explanation: This message is issued when the &SYSNSUB LEVEL parameter contains another CLIST built-in function. CLIST built-in functions are not allowed within the &SYSNSUB LEVEL parameter.

Module: IKJCT439

IKJ79007I THIS STATEMENT TRIED TO WRITE TO A FILE OPEN FOR INPUT

Explanation: You attempted to write to a file that was open for input only. To write to a file, it must be open for output. Specify the OUTPUT keyword on the OPENFILE statement to open the file for output.

Module: IKJCT437

IKJ79008I THIS STATEMENT TRIED TO READ FROM A FILE OPEN FOR OUTPUT

Explanation: You attempted to read from a file that was open for output only. To read from a file, it must be open for input. Remove the OUTPUT keyword from the OPENFILE statement, and specify the INPUT keyword.

Module: IKJCT437

IKJ79009I PHASE 1 PROCESSING OF CLIST OR REXX EXEC ENDED ABNORMALLY.

Explanation: An error caused during the setup to interpret the REXX exec or in the first phase of CLIST processing ended abnormally. See message IKJ79010I for ABEND and REASON codes that identify the error.

This error may have also been caused by the attempt to load a REXX exec or CLIST from the SYSPROC or SYSEXEC system file, if the data sets concatenated in SYSPROC or SYSEXEC are of different organization and record specifications. Specifically, the record format (RECFM) and the logical record length (LRECL) need to be identical. See *z/OS TSO/E User's Guide* for more details on concatenating data sets, and *z/OS TSO/E Command Reference* for details on the ALLOCATE command and its operands.

Module: IKJCT430

IKJ79010I ABEND Code: *Cxxx* REASON CODE: *reason_code*

Explanation: The first phase of CLIST processing, the setup for interpreting a REXX exec, or the clean up after interpreting a REXX exec ended abnormally with the given ABEND and REASON codes. See *z/OS MVS System Codes* for explanations of the ABEND and REASON codes.

Module: IKJCT430

IKJ79011I PHASE 2 PROCESSING OF CLIST ENDED ABNORMALLY.

Explanation: An error caused the second phase of CLIST processing to end abnormally. See message IKJ79012I for ABEND and REASON codes that identify the error.

Module: IKJCT433

IKJ79012I ABEND Code: Cxxx REASON CODE: reason_code

Explanation: The second phase of CLIST processing ended abnormally with the given ABEND and REASON codes. See *z/OS MVS System Codes*. for explanations of the ABEND and REASON codes.

Module: IKJCT433

IKJ79013I CLIST TERMINATED. UNABLE TO ESTABLISH ESTAE.

Explanation: The second phase of CLIST processing ended abnormally because its recovery code was unable to establish an ESTAE. For more information, report the problem to your IBM service representative.

Module: IKJCT433

IKJ79014I STMT *nn* SELECT STATEMENT NOT FOLLOWED BY A WHEN STATEMENT.

Explanation: The SELECT statement syntax requires one or more WHEN clauses to follow the SELECT statement. A WHEN clause did not immediately follow the SELECT, and the CLIST cannot be executed.

To correct the SELECT statement, insert a WHEN clause immediately following the SELECT. For more information about the SELECT statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79015I STMT *nn* LABELS ARE NOT ALLOWED ON THE WHEN STATEMENT.

Explanation: The syntax for the SELECT statement does not allow labels on a WHEN clause. A label was found on the WHEN clause, and the CLIST cannot be executed.

To correct the CLIST, remove the label from the WHEN clause. For more information about the SELECT statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79016I STMT *nn* THE WHEN EXPRESSION MUST BE PARENTHESIZED.

Explanation: Expressions on the WHEN clause of a SELECT statement must be enclosed in parentheses. An expression on a WHEN clause was found without parentheses around it, and the CLIST cannot be executed.

To correct the WHEN clause, enclose the expression in parentheses. For more information about the SELECT statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79017I STMT *nn* UNBALANCED PARENTHESES AROUND THE WHEN EXPRESSION.

Explanation: Expressions on the WHEN clause of a SELECT statement must be enclosed between an equal (balanced) number of left and right parentheses. A WHEN expression was found with an unequal (unbalanced) number of left and right parentheses around it, and the CLIST cannot be executed.

To correct the WHEN clause, make sure that the expression has the same number of left and right parentheses around it. For more information about the SELECT statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79018I STMT *nn* LABELS ARE NOT ALLOWED ON THE OTHERWISE STATEMENT.

Explanation: The syntax for the SELECT statement does not allow labels on an OTHERWISE clause. In this case, a label was found on the OTHERWISE clause, and the CLIST cannot be executed.

To correct the CLIST, remove the label from the OTHERWISE clause. For more information about the SELECT statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79019I STMT *nn* "=" IS MISSING FROM THE ITERATIVE DO.

Explanation: An equal sign (=) does not follow the control variable on an iterative DO statement. The CLIST cannot be executed.

To correct the CLIST, add an equal sign after the variable on the DO statement. For more information about the DO statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79020I STMT *nn* AN EXPRESSION MUST FOLLOW THE "=" ON THE ITERATIVE DO.

Explanation: The equal sign (=) on an iterative DO statement is not followed by an expression. The CLIST cannot be executed.

To correct the CLIST, include an expression after the equal sign on the iterative DO statement. For more information about the DO statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79021I STMT *nn* "TO" IS MISSING FROM THE ITERATIVE DO.

Explanation: An iterative DO statement does not have a TO keyword indicating the value to which the control variable should increase or decrease. The CLIST cannot be executed.

To correct the CLIST, include a TO keyword on the iterative DO statement. For more information about the DO statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79022I STMT *nn* AN EXPRESSION MUST FOLLOW THE "TO" ON THE ITERATIVE DO.

Explanation: An iterative DO statement does not have an expression following the TO keyword. The CLIST cannot be executed.

To correct the CLIST, include an expression after the TO keyword on the iterative DO statement. The expression should produce a value to which the control variable increases or decreases. For more information about the DO statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79023I STMT *nn* AN EXPRESSION MUST FOLLOW THE "BY" ON THE ITERATIVE DO.

Explanation: An iterative DO statement does not have an expression following the BY keyword. The CLIST cannot be executed.

To correct the CLIST, include an expression after the BY keyword on the iterative DO statement. The expression should produce a value by which the control variable increases or decreases each time the DO loop executes. For more information about the DO statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79024I A TO/FROM/BY EXPRESSION MUST SPECIFY A NUMERIC VALUE.

Explanation: Evaluation of the TO, BY, or FROM expression on the iterative DO statement resulted in character data. The expression must evaluate to a decimal integer. The CLIST cannot be executed.

To correct the CLIST, modify the given expression so that it evaluates to a decimal integer. For more information about the DO statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT446

IKJ79025I STMT *nn* AN EXPRESSION MUST FOLLOW "UNTIL".

Explanation: A DO-UNTIL statement does not have an expression following the UNTIL keyword. The CLIST cannot be executed.

To correct the CLIST, include an expression after the UNTIL keyword on the DO-UNTIL statement. The expression should specify a condition, for example, &I; = 1. The DO-UNTIL statement executes until that condition is true. For more information about the DO statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79026I STMT *nn* A SUBPROCEDURE STATEMENT MUST HAVE A LABEL.

Explanation: A PROC statement, other than a PROC statement on the first executable line of the CLIST, does not have a label. The CLIST cannot be executed.

PROC statements that are not on the first executable line of a CLIST are considered to be the first line of a subprocedure. As such, the PROC statement must have a label that can be used to call the subprocedure. To correct the CLIST, add a label to the PROC statement. For more information about subprocedures and PROC statements, see *z/OS TSO/E CLISTS*.

Module: IKJCT432

IKJ79027I STMT *nn* CLIST CONTAINS MORE THAN ONE PROCEDURE NAMED *label*.

Explanation: All procedure names in a CLIST must be unique, but two PROC statements were found to have the same name (label). The CLIST cannot be executed.

To correct the CLIST, change the label on one of the matching PROC statements. For more information about subprocedures and PROC statements, see *z/OS TSO/E CLISTS*.

Module: IKJCT43C

IKJ79028I SYSCALL TARGET MUST BE A SUBPROCEDURE IN THE CLIST.

Explanation: A name specified on a SYSCALL statement does not match the name of a subprocedure in the CLIST. The SYSCALL statement cannot be executed.

To correct the CLIST, make sure that the name on the SYSCALL statement matches the name of the intended PROC statement. For more information about the SYSCALL and PROC statements, see *z/OS TSO/E CLISTS*.

Module: IKJCT446

IKJ79029I A PROCEDURE NAME HAS BEEN USED AS A SYMBOLIC VARIABLE.

Explanation: A symbolic variable matches the name (label) of a PROC statement. PROC statement names can appear only on the PROC statement and on a corresponding SYSCALL statement. Symbolic variables cannot have the same name as a PROC statement. The CLIST cannot be executed.

To correct the CLIST, modify the symbolic variable or the PROC statement label so that they no longer match. For more information about the PROC statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT440

IKJ79030I THE KEYWORD ON THE RETURN STATEMENT IS NOT VALID.

Explanation: The RETURN statement is followed by something other than the CODE keyword; only the CODE keyword can appear on the RETURN statement. The CLIST cannot be executed.

To correct the CLIST, modify the RETURN statement so that it contains no keyword other than CODE. For more information about the RETURN statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT436

IKJ79031I VARIABLES MARKED AS CALL-BY-REFERENCE MUST BE PARAMETERS.

Explanation: The SYSREF statement contains variables that do not match parameters on the PROC statement. Variables on the SYSREF statement must match parameters named on the subprocedure's PROC statement. The CLIST cannot be executed.

To correct the CLIST, modify the SYSREF statement so that it contains only variables that match parameters on the subprocedure's PROC statement. For more information about the SYSREF statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT440

IKJ79032I UNDEFINED CALL-BY-REFERENCE VARIABLES SPECIFIED.

Explanation: One or more of the variables specified on the SYSREF statement did not have a corresponding variable passed on the caller's SYSCALL statement. The CLIST cannot be executed.

To correct the CLIST, modify the SYSREF or SYSCALL statement so that any variable named on the SYSREF statement has a corresponding variable passed as a parameter on the SYSCALL statement. For more information about the SYSREF and SYSCALL statements, see *z/OS TSO/E CLISTS*.

Module: IKJCT440

IKJ79039I OTHER THAN DBCS CHARACTERS FOUND IN A DBCS STRING.

Explanation: Characters of the double-byte character set (DBCS) each consist of two individual bytes containing code points in the range '41' to 'FE', or '4040', the DBCS blank. The DBCS string in error contained code points that were outside of the range of the valid DBCS characters.

To correct the error, verify that DBCS strings contain only valid DBCS characters. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT433

IKJ79040I ODD NUMBER OF BYTES FOUND IN A DBCS STRING.

Explanation: All characters of the double-byte character set (DBCS) are two bytes in length. The DBCS string in error contained an odd number of bytes, indicating that one of the DBCS characters was incomplete (was a single byte).

To correct the error, verify that each of the characters in the DBCS string consists of two bytes. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT433

IKJ79041I UNABLE TO FIND THE END OF A DBCS STRING.

Explanation: To distinguish between characters of the EBCDIC character set and the double-byte character set (DBCS), DBCS characters must be enclosed between a shift-out delimiter ('0E') and a shift-in delimiter ('0F'). In this error, the shift-in delimiter ('0F') was not found after a shift-out delimiter ('0E').

To correct the error, insert the character '0F' at the end of the DBCS string beginning with '0E'. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT433

IKJ79042I SECOND SHIFT-OUT FOUND BEFORE FINDING A SHIFT-IN.

Explanation: Strings of characters of the double-byte character set (DBCS) must be enclosed between a shift-out delimiter ('0E') and a shift-in delimiter ('0F'). In this error, two shift-out characters were found without an intervening shift-in character, indicating that one DBCS string is nested within another DBCS string. The shift-out and shift-in characters themselves are not allowed within another DBCS string and should be removed from the inner DBCS string.

To correct the error, remove the characters '0E' and '0F' from around the inner (nested) DBCS string. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT433

IKJ79043I STMT *nn* OTHER THAN DBCS CHARACTERS FOUND IN A DBCS STRING

Explanation: Characters of the double-byte character set (DBCS) each consist of two individual bytes containing code points in the range '41' to 'FE', or '4040', the DBCS blank. The DBCS string in error contained code points that were outside of the range of the valid DBCS characters.

To correct the error, verify that DBCS strings contain only valid DBCS characters. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79044I STMT *nn* ODD NUMBER OF BYTES FOUND IN A DBCS STRING.

Explanation: All characters of the double-byte character set (DBCS) are two bytes in length. The DBCS string in error contained an odd number of bytes, indicating that one of the DBCS characters was incomplete (was a single byte).

To correct the error, verify that each of the characters in the DBCS string consists of two bytes. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79045I STMT *nn* UNABLE TO FIND THE END OF A DBCS STRING.

Explanation: To distinguish between characters of the EBCDIC character set and the double-byte character set (DBCS), DBCS characters must be enclosed between a shift-out delimiter ('0E') and a shift-in delimiter ('0F'). In this error, the shift-in delimiter ('0F') was not found after a shift-out delimiter ('0E').

To correct the error, insert the character '0F' at the end of the DBCS string beginning with '0E'. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79046I STMT *nn* SECOND SHIFT-OUT FOUND BEFORE FINDING A SHIFT-IN.

Explanation: Strings of characters of the double-byte character set (DBCS) must be enclosed between a shift-out delimiter ('0E') and a shift-in delimiter ('0F'). In this error, two shift-out characters were found without an intervening shift-in character, indicating that one DBCS string is nested within another DBCS string. The shift-out and shift-in characters themselves are not allowed within another DBCS string and should be removed from the inner DBCS string.

To correct the error, remove the characters '0E' and '0F' from around the inner (nested) DBCS string. For more information about DBCS strings and characters, see *z/OS TSO/E CLISTS*.

Module: IKJCT43B

IKJ79048I THIS STATEMENT TRIED TO UPDATE A FILE AFTER END OF FILE WAS REACHED

Explanation: You cannot update a file after end of file has occurred. To add to the end of a file, allocate the file with a disposition of mod and open it for output.

Module: IKJCT437

IKJ79049I THIS STATEMENT TRIED TO UPDATE AN EMPTY FILE

Explanation: You cannot update an empty file. To add to the file, open it for output and use PUTFILE to write to it.

Module: IKJCT437

IKJ79054I CLIST EXCEEDS MAXIMUM ALLOWABLE LENGTH.

Explanation: The system cannot execute the requested CLIST because its internal representation (the command procedure block or COMPROC) exceeds 16 megabytes.

Module: IKJCT432

IKJ79055I Module FAILED WITH RETURN CODE *return_code*.

Explanation: One of the following modules failed:

- IKJCT44B
- IKJCT44S

Note the name of the failing module and the return code and contact your TSO/E administrator for further information about the exact nature of the failure.

Module: IKJCT433 IKJCT436

IKJ79057I DATA SETS WITH A LOGICAL RECORD LENGTH GREATER THAN 32767 ARE NOT SUPPORTED FOR CLIST I/O

Explanation: CLIST does not support records that span more than one block. For more information on the OPENFILE statement, see *z/OS TSO/E CLISTS*.

Module: IKJCT437

IKJ79060I ERROR/ATTN STATEMENT NOT ALLOWED WITHIN ERROR OR ATTENTION EXIT.

Explanation: An ERROR or ATTN statement was found in an error or attention routine in a subprocedure. The CLIST cannot be executed.

To correct the CLIST, remove the ERROR or ATTN statement from within the error or attention routine. For more information about error or attention routines, see *z/OS TSO/E CLISTS*.

Module: IKJCT436

IKJ79061I EBCDIC DATA FOR &SYSTWOBYTE IS OUTSIDE VALID DBCS RANGE.

Explanation: The built-in function &SYSTWOBYTE translates an EBCDIC string into the double-byte character set (DBCS). The valid DBCS code points that correspond to EBCDIC data and can be translated are '4040' and '42db' where *db* is a code point in the range of '41' to 'FE'. In this error, the &SYSTWOBYTE built-in function was issued for EBCDIC data outside of the range '40' to 'FE' and translation to DBCS was not possible.

To correct the error, remove any EBCDIC data outside of the range '40' to 'FE' from the &SYSTWOBYTE string. For more information about &SYSTWOBYTE and DBCS, see *z/OS TSO/E CLISTS*.

Module: IKJCT439

IKJ79062I STMT nn PROCEDURE NAME MUST NOT EXCEED 31 CHARACTERS.

Explanation: The label on a PROC statement contains more than 31 characters. The CLIST cannot be executed.

To correct the CLIST, modify the label so that it does not exceed 31 characters. For more information about labels and PROC statements, see *z/OS TSO/E CLISTS*.

Module: IKJCT432

IKJ79063I INVALID DATA SET NAME, *dsname*. EXEC EXCEEDS 44 CHARACTERS

Explanation: The data set name specified with the explicit EXEC command syntax (and the TSO/E prefix, if it exists) exceeded the limit of 44 characters after the addition of the EXEC data set name qualifier.

User response: Specify the data set name with 44 or less characters and reissue the EXEC command.

Module: IKJCT43D

Audience: EXEC user

IKJ79064I *command_name* NOT FOUND. A VALID ALTLIB ENVIRONMENT DOES NOT EXIST.

Explanation: The system previously created an ALTLIB environment that it expected to use for the current request. The EXEC command determined that this environment is in error.

System action: The EXEC command processor terminates.

User response: Contact your system programmer for assistance in diagnosing problems with the ALTLIB environment.

Module: EXEC command

Audience: EXEC command user

IKJ79065I (Sub)Command *command_name* cannot be executed. A REXX environment does not exist.

Explanation: You issued a command or subcommand that is either a REXX exec or calls a REXX exec during its processing. A REXX exec requires a REXX language processor environment in which to run. That environment does not exist.

System action: The EXEC command stops processing the command or subcommand you issued.

System programmer response: A REXX language processor environment is required for running a REXX exec. A language processor environment may not exist for the following reasons:

- Your installation is using a user-written terminal monitor program (TMP) and the TMP does not initialize a language processor environment. If you do not use the TMP that TSO/E provides, TSO/E does not automatically initialize a language processor environment. The user-written TMP must call the REXX initialization routine, IRXINIT, to initialize an environment for processing REXX execs.
- A REXX language processor environment previously existed on a specific task level and handled REXX processing. The task was terminated, which means the language processor environment was also terminated. A REXX language processor environment is available only as long as the task at which the environment was created exists. For example, you can use the TSO/E environment service, IKJTSEV, to create a TSO/E environment in a non-TSO/E address space. IKJTSEV also creates a language processor environment at the same task level at which you invoke IKJTSEV. When the task at which you created the TSO/E environment is terminated, the language processor environment is terminated. The language processor environment that IKJTSEV creates is available only as long as the task at which you invoke IKJTSEV exists. See *z/OS TSO/E Programming Services* for more information about the TSO/E environment service, IKJTSEV.

For more information about language processor environments, see *z/OS TSO/E REXX Reference*.

User response: Contact your system programmer to diagnose problems with the availability of a language processor environment for REXX.

Module: IKJCT430

Audience: EXEC user

IKJ79066I *data_set_name* cannot be executed. A REXX environment does not exist.

Explanation: You issued the EXEC command and specified the name of a data set that contains a REXX exec. A REXX exec requires a REXX language processor environment in which to run. This environment does not exist.

In some circumstances, REXX is specified for *data_set_name*. When that happens, regardless of the particular data set or the PDS member you tried to execute as a REXX exec, no exec can be executed because there is no REXX environment in which to process it.

System action: The EXEC command stops processing.

System programmer response: A REXX language processor environment is required for running a REXX exec. A language processor environment may not exist for the following reasons:

- Your installation is using a user-written terminal monitor program (TMP) and the TMP does not initialize a language processor environment. If you do not use the TMP that TSO/E provides, TSO/E does not automatically initialize a language processor environment. The user-written TMP must call the REXX initialization routine, IRXINIT, to initialize an environment for processing REXX execs.
- A REXX language processor environment previously existed on a specific task level and handled REXX processing. The task was terminated, which means the language processor environment was also terminated. A REXX language processor environment is available only as long as the task at which the environment was created exists. For example, you can use the TSO/E environment service, IKJTSOEV, to create a TSO/E environment in a non-TSO/E address space. IKJTSOEV also creates a language processor environment at the same task level at which you invoke IKJTSOEV. When the task at which you created the TSO/E environment is terminated, the language processor environment is terminated. The language processor environment that IKJTSOEV creates is available only as long as the task at which you invoke IKJTSOEV exists. See *z/OS TSO/E Programming Services* for more information about the TSO/E environment service, IKJTSOEV.

For more information about language processor environments, see *z/OS TSO/E REXX Reference*.

User response: Contact your system programmer to diagnose problems with the availability of a language processor environment for REXX.

Module: IKJCT43D IKJCT430

Audience: EXEC user

IKJ79067I *data_set_name(member_name)* **cannot be executed. A REXX environment does not exist.**

Explanation: You issued the EXEC command and specified the name of a data set that contains a REXX exec. A REXX exec requires a REXX language processor environment in which to run. This environment does not exist.

System action: The EXEC command stops processing.

System programmer response: A REXX language processor environment is required for running a REXX exec. A language processor environment may not exist for the following reasons:

- Your installation is using a user-written terminal monitor program (TMP) and the TMP does not initialize a language processor environment. If you do not use the TMP that TSO/E provides, TSO/E does not automatically initialize a language processor environment. The user-written TMP must call the REXX initialization routine, IRXINIT, to initialize an environment for processing REXX execs.
- A REXX language processor environment previously existed on a specific task level and handled REXX processing. The task was terminated, which means the language processor environment was also terminated. A REXX language processor environment is available only as long as the task at which the environment was created exists. For example, you can use the TSO/E environment service, IKJTSOEV, to create a TSO/E environment in a non-TSO/E address space. IKJTSOEV also creates a language processor environment at the same task level at which you invoke IKJTSOEV. When the task at which you created the TSO/E environment is terminated, the language processor environment is terminated. The language processor environment that IKJTSOEV creates is available only as long as the task at which you invoke IKJTSOEV exists. See *z/OS TSO/E Programming Services* for more information about the TSO/E environment service, IKJTSOEV.

For more information about language processor environments, see *z/OS TSO/E REXX Reference*.

User response: Contact your system programmer to diagnose problems with the availability of a language processor environment for REXX.

Module: IKJCT43D IKJCT430

Audience: EXEC user

IKJ79068I Keyword or Positional parameter list on PROC statement exceeds maximum length allowed.

Explanation: You specified either too many keywords, positional parameters, or both on the PROCEDURE statement of the CLIST being invoked.

System action: CLIST processing is terminated.

User response: Reduce the number of keywords or positional parameters on the PROC statement.

The PCL which represents the keywords and positional parameters built for the PROC statement has exceeded the maximum which can be passed to PARSE of 32767 bytes.

Module: IKJCT431

Audience: NONE

IKJ79069I Error encountered while processing a system variable

Explanation: A diagnostic message, issued before this message, should give the detailed reason for this malfunction.

User response: Get the diagnostic message and follow the advise given.

Module: IKJCT443

Program: CLIST

IKJ79070I System variable SYSJES or SYSNODE failed. IEFSSREQ return code: *return_code* SSOBRETN: *code*

Explanation: The subsystem service IEFSSREQ, which was invoked to obtain JES information, failed. For more information see *z/OS MVS Using the Subsystem Interface*.

User response: Do not use this function as long as your installation does not support this subsystem service.

Module: IKJCT443

Program: CLIST

IKJ79071I System variable *variable_name* failed. It requires product level *product_level*

Explanation: The required product level is not installed for the requested system variable.

User response: Do not use this function as long as your installation does not support this subsystem service.

Module: IKJCT443

Program: CLIST

IKJ79072I SYSSMS failed, because service IGWASYS returned with RC: *return_code* and REA: *reason_code*

Explanation: The service IGWASYS, which was invoked for the function, failed. For more information, see *z/OS DFSMSdfp Advanced Services*.

User response: Do not use this function as long as your installation does not support this subsystem service.

Module: IKJCT443

Program: CLIST

IKJ79073I System variable SYSAPPCLU failed, because service ATBEXAI returned with RC: *return_code*

Explanation: The subsystem service ATBEXAI, which was invoked to obtain the LU name, failed. For more information, see *z/OS MVS Programming: Writing Transaction Programs for APPC/MVS*.

Module: IKJCT443

Program: CLIST

IKJ79074I System variable SYSAPPCLU or SYSSMS failed – service *service_name* could not be loaded.

Explanation: The service *service_name* is required for this function, but could not be loaded.

User response: Ask your system administrator to make this service available in a system library.

Module: IKJCT443

Program: CLIST

IKJ79075I System variable *variable_name* failed, because service ASASYMBM returned with RC: *return_code*

Explanation: An error occurred in a call to the multiple virtual storage (MVS) symbol substitution service (ASASYMBM). An error occurred when ASASYMBM tried to substitute text for a symbol specified in the function.

Return code 8 typically means that the variable name is not specified properly, such that the resulting substitution would be greater than eight characters.

See *z/OS MVS Initialization and Tuning Reference* for the syntax of the SYSDEF ... SYMDEF statement. For detailed information about ASASYMBM return codes, see *z/OS MVS Programming: Assembler Services Reference ABE-HSP*.

User response: If the error persists, call your IBM support personnel.

Module: IKJCT443

Program: CLIST

IKJ79101I COMMAND *command_name* TERMINATED DUE TO ATTENTION

Explanation: The command processor listed in the message, which was invoked by the TSOEXEC command processor, ended due to an attention interrupt. Either you pressed the attention key or TSO/E generated an attention interrupt. An attention interrupt to a command processor invoked by the TSOEXEC command processor causes the invoked command processor to end abnormally.

Module: IKJEFTEX

Program: TSOEXEC

IKJ79102I *command_name* ENDED DUE TO ERROR +

Explanation: The command processor listed in the message, which was invoked by the TSOEXEC command processor, ended unsuccessfully.

IKJ79102I SYSTEM ABEND CODE *abend_code* REASON CODE *reason_code*

Explanation: The command processor listed in the primary message, which was invoked by the TSOEXEC command processor, ended with the abend code and return code listed in the secondary message text.

If the message text indicates a user abend, see the documentation for that command for an explanation of the abend and reason codes. If the message text indicates a system abend, see *z/OS MVS System Codes* for an explanation of the abend and reason codes.

Module: IKJEFTEX

Program: TSOEXEC

IKJ79102I USER ABEND CODE *abend_code* REASON CODE *reason_code*

Explanation: The command processor listed in the primary message, which was invoked by the TSOEXEC command processor, ended with the abend code and return code listed in the secondary message text. See the documentation for that command for an explanation of the abend code and reason code.

Module: IKJEFTEX

Program: TSOEXEC

IKJ79103I TSOEXEC FAILED WHILE EXECUTING THE *command_name* COMMAND +

Explanation: The command processor listed in the message was invoked by the TSOEXEC command processor and was terminated due to an error in the TSO/E Service Routine (IKJEFTSR).

IKJ79103I TSO/E SERVICE ROUTINE RETURN CODE *return_code*

Explanation: A command processor, which was invoked by the TSOEXEC command processor, terminated because the TSO/E Service Routine ended with the above return code. See *z/OS TSO/E Programming Services* for an explanation of the TSO/E Service Routine return codes.

Module: IKJEFTEX

Program: TSOEXEC

IKJ79104I COMMAND *command_name* NOT FOUND

Explanation: You attempted to invoke the command processor listed in the message text, with the TSOEXEC command. However the command processor does not exist.

Module: IKJEFTEX

Program: TSOEXEC

IKJ79105I INVALID COMMAND NAME SYNTAX *command_name*

Explanation: The command listed in the message text, which was invoked by the TSOEXEC command processor, had incorrect syntax. See *z/OS TSO/E Command Reference* for an explanation of the TSO/E commands and their syntax.

Module: IKJEFTEX

Program: TSOEXEC

IKJ79106I *command_name* IS UNSUPPORTED COMMAND NAME IN BACKGROUND

Explanation: The command listed in the message text, which was invoked by the TSOEXEC command processor, is not allowed in a background environment. See *z/OS TSO/E User's Guide* for an explanation of which TSO/E commands are not allowed in the background.

Module: IKJEFTEX

Program: TSOEXEC

IKJ79150I EXIT NAME *exit_name* WAS NOT FOUND.

Explanation: You attempted to invoke the exit named in the message text, however the exit is not properly defined to TSO/E. Contact your system programmer to resolve the problem.

Module: IKJRTR01

Audience: Exit user

IKJ79151I ERROR OCCURRED WHILE INVOKING EXIT *exit_name* + ABEND CODE *abend_code* REASON CODE *reason_code*.

Explanation: A TSO/E internal function ABENDED while invoking the exit named in the message text. The secondary message displays the ABEND and the reason code. For an explanation of the ABEND and reason codes, see *z/OS MVS System Codes*. For additional assistance, contact your system programmer.

Module: IKJRTR01

Audience: Exit user

IKJ79152I ERROR OCCURRED IN EXIT *exit_name*. + ABEND CODE *abend_code* REASON CODE *reason_code*.

Explanation: An error occurred in the exit named in the message text. The secondary message displays the ABEND and the reason code. For an explanation of the ABEND and reason codes, see *z/OS MVS System Codes*. For additional assistance, contact your system programmer.

Module: IKJRTR01

Audience: Exit user

IKJ79153I ERROR DETECTED WHILE INVOKING EXIT *exit_name* + UNABLE TO ESTABLISH RECOVERY ENVIRONMENT.

Explanation: An error occurred while establishing addressability to the exit named in the message text. The secondary message indicates the problem. Contact your system programmer to resolve the problem.

Module: IKJRTR01

Audience: Exit user

IKJ79154I INSTALLATION EXIT *exit_name* REQUESTED TERMINATION. + REASON CODE *reason_code*

Explanation: The exit named in the message text requested termination. The secondary message displays the reason code. Contact your system programmer to resolve the problem.

Module: IKJRTR01

Audience: Exit user

IKJ79200I COMMAND TERMINATED DUE TO ATTENTION

Explanation: An attention interrupt occurred while the system was processing a FIB command (CANCEL, OUTPUT, STATUS, or SUBMIT). The interrupt stopped command processing. You cannot resume processing by entering a null line after the READY message appears, as you can after most attention interrupts.

Module: IKJEFF00

IKJ79201I COMMAND ENDED DUE TO ERROR +

Explanation: While processing a FIB command (CANCEL, OUTPUT, STATUS, or SUBMIT), the FIB command interface routine (IKJEFF76) terminated abnormally. The secondary message displays the system ABEND code.

Module: IKJEFF00

IKJ79202I COMMAND ENDED DUE TO ERROR +

Explanation: While processing a FIB command (CANCEL, OUTPUT, STATUS, or SUBMIT), the FIB command interface routine (IKJEFF76) issued a failing or an unexpected return code. A secondary message displays the system return code.

Module: IKJEFF00

IKJ79203I COMMAND ENDED DUE TO ERROR +

Explanation: While processing a FIB command (CANCEL, OUTPUT, STATUS, or SUBMIT), the FIB SVC100 (IKJEFF00) terminated abnormally. The secondary message displays the system ABEND code.

Module: IKJEFF00

IKJ79204I You attempted to run an unsupported function in a dynamic TSO environment.

Explanation: You are running in an address space with a TSO/E environment created by the TSO/E environment service. You tried to invoke an unsupported function in this environment.

User response: Remove the invocation.

IKJ79301I • IKJ79310I

Module: IKJEFF00

Audience: Application programmer

IKJ79301I ALTLIB terminated. Insufficient virtual storage to satisfy request. +

Explanation: The ALTLIB command processor needs to obtain more virtual storage than is currently available.

System action: The ALTLIB command processor abnormally terminates.

User response: If ISPF is currently active, try exiting at least one active application. If this does not help or if ISPF is not currently active, logon with a larger region size. For help, contact the person who defines your region size.

Module: IKJADLIB IKJADUDD

Audience: ALTLIB user

IKJ79307I ALTLIB terminated. Extraneous information specified. +

Explanation: You specified two or more operands on the ALTLIB command that conflict with one another. This message is accompanied by one of the following messages describing what operands are in error.

Specify a data set list or DDNAME only when activating an application-level alternative library.

Specify the COND or UNCOND keywords only when activating an application-level alternative library.

Specify USER, APPLICATION, SYSTEM, or ALL only when activating or deactivating.

System action: The ALTLIB command processor abnormally terminates.

User response: Check the operands entered to see which of the operands was in error.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79308I ALTLIB terminated. Exceeded maximum number of stacked application levels. +

Explanation: You currently have eight application-level ddnames stacked for the type of application you are activating. No more than eight can be stacked.

System action: The ALTLIB command processor abnormally terminates.

User response: Issue the ALTLIB command with the DEACTIVATE operand for the specified type of application before trying to activate another of the same type.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79309I ALTLIB terminated. Member names are not allowed. +

Explanation: You specified a member name in the list of data sets for the DATASET or DSNAME operand. A member name is not allowed.

System action: The ALTLIB command processor abnormally terminates.

User response: Issue the ALTLIB command specifying only the names of partitioned data sets in the list of data set names.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79310I ALTLIB terminated. Exceeded maximum number of data sets. +

Explanation: You specified more than 15 data sets in the list of data sets for the DATASET or DSNAME operand.

System action: The ALTLIB command processor abnormally terminates.

User response: Issue the ALTLIB command specifying no more than 15 data set names.

IKJ79316I • IKJ79320I

System action: The ALTLIB command processor abnormally terminates.

User response: Issue the ALTLIB command with the DISPLAY operand and, from the messages that ALTLIB displays, decide if you need to activate another application-level library of the same type.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79316I ALTLIB terminated. DDNAME *ddname* is allocated to the terminal. +

Explanation: The specified *ddname* that is to act as the application level library is allocated to the terminal. ALTLIB does not allow you to use the terminal as the device from which to read an EXEC or CLIST.

System action: The ALTLIB command processor abnormally terminates.

User response: Issue the ALLOCATE command specifying a list of data sets.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79317I ALTLIB terminated. Severe error occurred in IKJDAIR. +

Explanation: The TSO/E program IKJDAIR encountered an error when attempting to check the allocation of a *ddname*. This message is accompanied by the following message:

IKJDAIR return code is *return_code*.

System action: The ALTLIB command processor abnormally terminates.

User response: Reissue the ALTLIB command. If the problem recurs, contact your system programmer for assistance, or consult *z/OS TSO/E Programming Services* to interpret the return code.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79319I ALTLIB terminated. Severe error allocating data sets for the DATASET keyword. +

Explanation: Dynamic allocation encountered an error when attempting to allocate a data set.

System action: The ALTLIB command processor abnormally terminates. This message is accompanied by one of the following messages which further describes the reason the ALTLIB command failed.

Message text is provided by dynamic allocation regarding the SVC99 error.

User response: Check the specified data set to see if the cause of the error can be determined.

Dynamic allocation return code *return_code* reason code *reason_code*

User response: Contact your system programmer or consult *z/OS MVS Programming: Authorized Assembler Services Guide* to interpret the return and reason codes.

Data set *dsname* is not a partitioned data set.

User response: A data set that is not partitioned is specified in the list of data sets. Only partitioned data sets can be specified using the ALTLIB command. Issue the ALTLIB command specifying only the names of partitioned data sets.

Module: IKJADALC

Audience: ALTLIB user

IKJ79320I Unable to free previously allocated data sets. Enter ? for more information. +

Explanation: Dynamic allocation encountered an error when attempting to deallocate a data set.

System action: This is a warning. The ALTLIB command continues after issuing the message. If you issued the ALTLIB command to DEACTIVATE or RESET alternative libraries, these libraries will no longer be searched. The allocation of the *ddname* specified in the message will not change. This message is accompanied by further messages describing the reason the ALTLIB command failed:

Message text is provided by dynamic allocation regarding the SVC99 error.

User response: Check the specified ddname to see if the cause of the error can be determined.

Dynamic allocation return code *return_code* **reason code** *reason_code*

User response: Contact your TSO/E administrator for assistance, or consult *z/OS MVS Programming: Authorized Assembler Services Guide* to interpret the return and reason codes.

Module: IKJADALC

Audience: ALTLIB user

IKJ79321I Stacked DDNAME=ddname

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show any ddnames that are stacked for the given application-level.

System action: This is information only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79322I Current search order (by DDNAME) is:

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show any ddnames that are currently being searched.

System action: This is information only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79323I User-level EXEC DDNAME=SYSUEXEC

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show that the user-level EXEC ddname is being searched.

System action: This is information only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79324I User-level CLIST DDNAME=SYSUPROC

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show that the user-level CLIST ddname is being searched.

System action: This is information only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79325I Application-level EXEC DDNAME=*ddname*

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show that the application-level EXEC *ddname* is being searched.

System action: This is information only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79326I Application-level CLIST DDNAME=*ddname*

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show that the application-level CLIST *ddname* is being searched.

System action: This is information only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79327I System-level EXEC DDNAME=*ddname*

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show that the system-level EXEC *ddname* is being searched.

System action: This message is informational only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79328I System-level CLIST DDNAME=*ddname*

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command processor issues this message to show that the system-level CLIST *ddname* is being searched.

System action: This is information only.

User response: None.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79329I No levels are currently being searched.

Explanation: You specified the ALTLIB command with the DISPLAY operand or deactivated all levels of searching with the DEACTIVATE and ALL operands. The ALTLIB command processor issues this message to show that no levels are currently being searched.

System action: This is information only.

User response: Use the ACTIVATE operand to activate one or more levels for searching.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79330I ALTLIB terminated. Unable to establish an alternative library environment.

Explanation: The TSO/E program IKJADTAB encountered an error when attempting to establish an alternative library environment. This message is accompanied by the following message:

IKJADTAB return code *return_code*

System action: The ALTLIB command processor abnormally terminates.

User response: Reissue the ALTLIB command. If the problem recurs, contact your TSO/E administrator for assistance, or consult *z/OS TSO/E Programming Services* to interpret the return code.

Module: IKJADTAB

Audience: ALTLIB user

IKJ79332I ALTLIB terminated. Unable to establish recovery environment. +

Explanation: The ALTLIB command processor could not establish recovery. This message is accompanied by the following message:

ESTAE macro return code *return_code*

System action: The ALTLIB command processor abnormally terminates.

User response: Reissue the ALTLIB command. If the problem recurs, contact your system programmer for assistance.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79333I IKJADTAB terminated. Unable to establish recovery environment. +

Explanation: The TSO/E program IKJADTAB could not establish recovery. This message is accompanied by the following message:

ESTAE macro return code *return_code*.

System action: IKJADTAB abnormally terminates.

User response: Contact your system programmer for assistance.

Module: IKJADTAB

Audience: ALTLIB user

IKJ79334I IKJADTAB terminated. Insufficient virtual storage to satisfy request. +

Explanation: The TSO/E program IKJADTAB needs to obtain more virtual storage than is currently available.

System action: IKJADTAB abnormally terminates.

User response: If ISPF is currently active, try exiting at least one active application. If this does not help or if ISPF is not currently active, logon with a larger region size. For help, contact the person who defines your region size.

Module: IKJADTAB

Audience: ALTLIB user

IKJ79335I IKJADTAB terminated. Inconsistent or invalid parameters passed to IKJADTAB. +

Explanation: A program that invoked the TSO/E program IKJADTAB is passing inconsistent or invalid parameters. This message is accompanied by the following message:

IKJADTAB return code *return_code*

System action: IKJADTAB abnormally terminates.

User response: Reinvoke the program that invoked IKJADTAB. If the problem recurs, contact your system programmer for assistance, or consult *z/OS TSO/E Programming Services* to interpret the return code.

IKJ79336I • IKJ79338I

Module: IKJADTAB

Audience: ALTLIB user

IKJ79336I IKJADTAB terminated. Invalid ADTAB_LIKE parameter passed to IKJADTAB. +

Explanation: A program that invoked the TSO/E program IKJADTAB is passing an invalid ADTAB_LIKE parameter. This message is accompanied by the following message:

IKJADTAB return code *return_code*

System action: IKJADTAB abnormally terminates.

User response: Reinvoke the program that invoked IKJADTAB. If the problem recurs, contact your system programmer for assistance, or consult *z/OS TSO/E Programming Services* to interpret the return code.

Module: IKJADTAB

Audience: ALTLIB user

IKJ79337I IKJADTAB terminated. Invalid token passed to IKJADTAB. +

Explanation: A program that invoked the TSO/E program IKJADTAB is passing an invalid token. This message is accompanied by the following message:

Invalid token is *token* **IKJADTAB return code** *return_code*

System action: IKJADTAB abnormally terminates.

User response: Reinvoke the program that invoked IKJADTAB. If the problem recurs, contact your system programmer for assistance, or consult *z/OS TSO/E Programming Services* to interpret the return code.

Module: IKJADTAB

Audience: ALTLIB user

IKJ79338I ALTLIB terminated. An EXEC environment does not exist.

Explanation: The ALTLIB action you are requesting requires that a REXX environment be available, but it is not available.

System action: ALTLIB abnormally terminates.

System programmer response: A REXX language processor environment is required for running the ALTLIB action. A language processor environment may not exist for the following reasons:

- Your installation is using a user-written terminal monitor program (TMP) and the TMP does not initialize a language processor environment. If you do not use the TMP that TSO/E provides, TSO/E does not automatically initialize a language processor environment. The user-written TMP must call the REXX initialization routine, IRXINIT, to initialize an environment for processing REXX execs.
- A REXX language processor environment previously existed on a specific task level and handled REXX processing. The task was terminated, which means the language processor environment was also terminated. A REXX language processor environment is available only as long as the task at which the environment was created exists.

For example, you can use the TSO/E environment service, IKJTSOEV, to create a TSO/E environment in a non-TSO/E address space. IKJTSOEV also creates a language processor environment at the same task level at which you invoke IKJTSOEV. When the task at which you created the TSO/E environment is terminated, the language processor environment is terminated. The language processor environment that IKJTSOEV creates is available only as long as the task at which you invoke IKJTSOEV exists. See *z/OS TSO/E Programming Services* for more information about the TSO/E environment service, IKJTSOEV.

For more information about language processor environments, see *z/OS TSO/E REXX Reference*.

User response: Contact your system programmer to diagnose problems with the availability of a language processor environment for REXX.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79339I [USER|SYSTEM]-LEVEL CLIST activated; [USER|SYSTEM]-LEVEL EXEC cannot be activated. +

Explanation: You requested that both the CLIST ddname and the EXEC ddname at either the user level or system level be activated, but because a REXX environment does not exist, only the user or system CLIST level is activated. This message is accompanied by the following message:

An EXEC environment does not exist.

System action: This is a warning. Because the user-level CLIST ddname is defined as 'SYSUPROC' and the system-level ddname is defined as 'SYSPROC,' the CLIST ddname for the level you specified can be activated. Because the EXEC environment contains information needed to execute an EXEC and it is not available, it is not activated. The ALTLIB command continues after issuing the message.

System programmer response: A REXX language processor environment is required for activating the user/system exec DD. A language processor environment may not exist for the following reasons:

- Your installation is using a user-written terminal monitor program (TMP) and the TMP does not initialize a language processor environment. If you do not use the TMP that TSO/E provides, TSO/E does not automatically initialize a language processor environment. The user-written TMP must call the REXX initialization routine, IRXINIT, to initialize an environment for processing REXX execs.
- A REXX language processor environment previously existed on a specific task level and handled REXX processing. The task was terminated, which means the language processor environment was also terminated. A REXX language processor environment is available only as long as the task at which the environment was created exists.

For example, you can use the TSO/E environment service, IKJTSOEV, to create a TSO/E environment in a non-TSO/E address space. IKJTSOEV also creates a language processor environment at the same task level at which you invoke IKJTSOEV. When the task at which you created the TSO/E environment is terminated, the language processor environment is terminated. The language processor environment that IKJTSOEV creates is available only as long as the task at which you invoke IKJTSOEV exists. See *z/OS TSO/E Programming Services* for more information about the TSO/E environment service, IKJTSOEV.

For more information about language processor environments, see *z/OS TSO/E REXX Reference*.

User response: Contact your system programmer to diagnose problems with the availability of a language processor environment for REXX.

Module: IKJADLIB

Audience: ALTLIB user

IKJ79340I ALTLIB EXEC levels are not available for searching. +

Explanation: You specified the ALTLIB command with the DISPLAY operand. The ALTLIB command issues this message to show that a REXX environment does not exist. The message is accompanied by the following message:

An EXEC environment does not exist.

System action: This is a warning. Because the EXEC environment contains information needed to execute an EXEC and it is not available, if you try to activate an ALTLIB level for EXEC it will result in an error. The ALTLIB command continues after issuing the message.

User response: Contact your system programmer to diagnose problems with the availability of a language processor environment for REXX.

Module: IKJADTAB

Audience: ALTLIB user

IKJ79341I The ALTLIB command abnormally terminated. +

Explanation: An unexpected error occurred in the ALTLIB command, causing it to abnormally terminate. The message is accompanied by the following message:

(SYSTEM|USER) ABEND CODE 'ac' REASON CODE 'reason_code'.

System action: The ALTLIB command processor terminates.

IKJ79342I • IKJH0202E

User response: Contact your system programmer for assistance in diagnosing problems with the ATLLIB command processor.

Module: ATLLIB

Audience: ATLLIB command user

IKJ79342I ATLLIB terminated. A valid ATLLIB environment does not exist. +

Explanation: The system previously created an environment that it expected to use for the current request. The ATLLIB command determined that this environment is in error. The message is accompanied by the following message:

Contact your system programmer to diagnose problems with the ATLLIB environment.

System action: The ATLLIB command processor terminates.

User response: Contact your system programmer for assistance in diagnosing problems with the ATLLIB environment.

Module: ATLLIB

Audience: ATLLIB command user

IKJ79343I IKJADTAB terminated. A valid IKJADTAB environment does not exist. +

Explanation: The system previously created an environment that it expected to use for the current request. The TSO/E program IKJADTAB determined that this environment is in error. The message is accompanied by the following message:

IKJADTAB return code *return_code*. Contact your system programmer to diagnose problems with the IKJADTAB environment.

System action: IKJADTAB terminates the request.

User response: Contact your system programmer to diagnose problems with the IKJADTAB environment.

Module: IKJADTB2

Audience: IKJADTAB user

IKJH101I Report-title Report

Explanation: Header line for TSO/E health checks.

System action: Processing continues.

Module: IKJHCR00

IKJH0201I User Logs are in use.

Explanation: CHECK (IBMTSOE, TSOE_SEND_CHECK) has detected that the IBM suggested implementation of user logs is in use.

System action: Processing continues. There is no affect on the system.

Module: IKJHCR00

IKJH0202E User logs are not in use.

Explanation: CHECK (IBMTSOE, TSOE_USERLOGS) has detected that messages are being stored in the system broadcast data set instead of individual user logs.

TSO/E user logs reduce contention on the system broadcast data set. Problems with the broadcast data set can slow or prevent TSO/E logons.

System action: Processing continues. There is no affect on the system.

Operator response: Report this problem to the system programmer.

System programmer response: If the system broadcast data set is intended to be used for user mail, no action is required. Consider using a check policy in HZSPRMxx to DELETE or DEACTIVATE this check:

```
ADDREP,POLICY,NAME(DELETEDCHECKS)
DELETE,CHECK(IBMTSOE,TSOE_USERLOGS)
```

Otherwise, implement the setting for user logs.

To implement user logs, check which IKJTSOxx parmlib member is active by using the MVS DISPLAY IKJTSO command or TSO/E PARMLIB LIST command. Then make a copy of the active parmlib member or the sample IKJTSO00 member in SYS1.SAMPLIB and modify the SEND parameters as shown:

```
LOGNAME(user log data set name)
```

```
CHKBROD(ON)
```

Use the MVS SET IKJTSO or TSO/E PARMLIB UPDATE command to activate the updated member. See z/OS TSO/E Customization for more information about implementing user logs.

Problem determination: Issue the MVS DISPLAY IKJTSO,SEND or TSO/E PARMLIB LIST(SEND) command to determine if the current setting for LOGNAME is correct.

Module: IKJHCR00

IKJH0301I All TSO/E PARMLIB settings were initialized successfully.

Explanation: CHECK (IBMTSOE, TSOE_PARMLIB_CHECK) determined that no errors were encountered when loading PARMLIB settings during TSO/E initialization.

System action: Processing continues. There is no affect on the system.

Module: IKJHCR00

IKJH0302E TSO/E PARMLIB defaults were used for parmlib_cmd_name due to an error.

Explanation: CHECK (IBMTSOE, TSOE_PARMLIB_CHECK) determined that errors were encountered processing PARMLIB settings during TSO/E initialization for the PARMLIB operand noted in the message.

System action: Processing continues. There is no affect on the system.

Operator response: Report this problem to the system programmer.

System programmer response: Correct errors and issue TSO/E PARMLIB UPDATE command to activate updates.

Problem determination: The probable cause of the error is the incorrect syntax in the IKJTSOxx PARMLIB member that was used for the last IPL. Check that the member has no syntax errors. Message IKJ712I and messages associated with TSO/E parsing routines may have been written to the system log. Use the TSO/E PARMLIB CHECK command to locate any syntax errors. If no syntax errors are present there may have been an I/O error while processing the PARMLIB member during initialization.

Module: IKJHCR00

IKJH0303E Unrecognized TSO/E PARMLIB setting found during initialization.

Explanation: CHECK (IBMTSOE, TSOE_PARMLIB_ERROR) determined that errors were encountered processing the TSO/E PARMLIB member during initialization. Default settings may have been used which could differ from intended settings.

System action: Processing continues. There is no effect on the system.

Operator response: Report this problem to the system programmer.

System programmer response: Correct errors and issue TSO/E PARMLIB UPDATE command to activate updates.

Problem determination: The probable cause of the error is incorrect syntax in the IKJTSOxx PARMLIB member that was used for the last IPL. Check that the member has no syntax errors. Message IKJ705I may have been written to

IKJH0304E

the system log. Use the TSO/E PARMLIB CHECK command to locate any syntax errors.

Module: IKJHCR00

IKJH0304E TSO/E PARMLIB Initialization did not complete for parmlib_cmd_name.

Explanation: CHECK(IBMTSOE,TSOE_PARMLIB_ERROR) determined that initialization for the PARMLIB operand noted in the message did not complete. TSO/E settings were not defined for the set of options associated with the operand noted in the message. TSO/E processing may not behave as desired due to these uninitialized settings.

System action: Processing continues. There is no effect on the system.

Operator response: Report this problem to the system programmer.

System programmer response: Correct errors and issue TSO/E PARMLIB UPDATE command to activate updates.

Problem determination: The probable cause of the error was a failure processing the IKJTSOxx PARMLIB member during the last IPL. Check that the member has no errors. Messages associated with the error may have been written to the system log.

Module: IKJHCR00

Chapter 7. TSO/E terminal messages (INM...)

Component name	INM
Program producing message	TRANSMIT and RECEIVE commands
Audience and where produced	For terminal user: at the terminal. For system programmer: SYSTSPRT listing.
Message format	INMzyyyyn z Issuer of Message: R RECEIVE command. X TRANSMIT command. C Common messages issued by both the TRANSMIT and the RECEIVE commands. yyy Message serial number. n Type code: A Action. The terminal user must perform the action specified in the message text. I Information; no action is required.
Comments	The words enclosed in single quotation marks in the message text indicate that the system supplies specific information which varies depending on the circumstances. That information is available only when the system displays the message at the terminal. A plus sign (+) after the message text indicates that more information is available. To receive more information, type a question mark (?) and press the Enter key.

This chapter describes TSO/E Interactive Data Transmission Facility (IDTF) messages directed to a terminal user.

INMC001I The NAMES data set *dsname* is not usable. +

Explanation: The command processor cannot use the indicated NAMES data set. This message is accompanied by further messages describing the problem that makes this data set unusable.

System action: The TRANSMIT or RECEIVE command processor abnormally terminates.

User response: Your response depends on the type of error indicated by subsequent messages.

Module: INMCA, INMC SYN

Audience: TRANSMIT or RECEIVE user

INMC002I An error occurred during allocation.

Explanation: This message is preceded by message INMC001I which identified the NAMES data set that was being processed. The TRANSMIT or RECEIVE command processor had attempted to allocate the data set but the allocation failed. This message is followed by one of the standard TSO/E allocation error messages identifying the specific error.

System action: The TRANSMIT or RECEIVE command processor abnormally terminates.

INMC003I • INMC006I

User response: Your response depends on the type of error indicated by subsequent messages.

Module: INMCA

Audience: TRANSMIT or RECEIVE user

INMC003I OPEN failed for the data set.

Explanation: This message is preceded by message INMC001I which identified the NAMES data set that was being processed. The TRANSMIT or RECEIVE command had issued an OPEN for the indicated data set, but the OPEN was unsuccessful.

System action: The TRANSMIT command abnormally terminates. The RECEIVE command treats this as a warning message and continues without the use of the indicated data set.

User response: Notify your system programmer.

Module: INMCA, INMRQ, INMXQ

Audience: TRANSMIT or RECEIVE user

INMC004I Logical record length may not be greater than 255.

Explanation: This message is preceded by message INMC001I which identified the NAMES data set that was being processed. The TRANSMIT or RECEIVE command processor attempted to use the indicated data set but found a record length greater than 255.

System action: The TRANSMIT command processor abnormally terminates. The RECEIVE command processor treats this as a warning message and continues without the use of the indicated data set.

User response: Rebuild the NAMES data set using a record length of 255 or less.

Module: INMCA

Audience: TRANSMIT or RECEIVE user

INMC005A Press the PA1 key to exit from *command*. Any other response will cause the command to continue.

Explanation: The TRANSMIT or RECEIVE command processor detected an attention interrupt.

System action: Unlock the terminal keyboard and wait for some action by the user. If the user responds with another attention interrupt, the command processor passes control to the terminal monitor program, which then issues the READY message. After any other response, the processing of the interrupted TRANSMIT or RECEIVE command continues.

User response: Either press the PA1 key to terminate TRANSMIT or RECEIVE processing, or press the Enter key to resume TRANSMIT or RECEIVE processing.

Module: INMCX

Audience: TRANSMIT or RECEIVE user

INMC006I Dsname=*dsname*, record number=*nn*. Record text:

Explanation: The TRANSMIT or RECEIVE command processor encountered a syntax error in one of the NAMES data sets. The dsname and record number given in the message indicate the data set and record within the data set in which the error was detected. A previous message indicated the nature of the error, and message INMC007I, which follows, displays the text of the record in error.

System action: Both the TRANSMIT and RECEIVE command processors treat this as a warning message and continue processing of the indicated NAMES data set.

User response: Correct the syntax error.

Module: INCMMSGI

Audience: TRANSMIT or RECEIVE user

INMC007I *record_text.*

Explanation: This message gives the text of a record in a NAMES data set in which a syntax error was detected. The message is preceded by message INMC006I identifying the data set and by other messages identifying the syntax error.

System action: Continue processing the remainder of the NAMES data set.

User response: You must correct the syntax error.

Module: INMCMSGI

Audience: TRANSMIT or RECEIVE user

INMC008I **A permanent I/O error occurred after record number *nn*. +**

Explanation: A permanent I/O error has occurred during the processing of a NAMES data set. This message is preceded by message INMC001I identifying the data set in which the error occurred. It is followed by message INMC009I which describes the specific nature of the I/O error.

System action: Stop processing of this NAMES data set. The TRANSMIT command processor treats this as a severe error and terminates. The RECEIVE command processor treats it as a warning and continues without the use of the data set.

User response: Take action based on the following message, INMC009I.

Module: INMC SYN

Audience: TRANSMIT or RECEIVE user

INMC009I *I/O_error_message_text.*

Explanation: An I/O error has occurred during the processing of a NAMES data set. Preceding messages have indicated the data set which was being processed. For an explanation of the message text, see Message IOS000I in *z/OS MVS System Messages, Vol 9 (IGF-IWM)*.

System action: Stop processing of this NAMES data set. The TRANSMIT command processor treats this as a severe error and terminates. The RECEIVE command processor treats it as a warning and continues without the use of the data set.

User response: See message IEA000I or message IOS001I.

Module: INMC SYN

Audience: TRANSMIT or RECEIVE user

INMC010I **Only ten: ALTCTL tags are allowed. Subsequent ones are being ignored.**

Explanation: The TRANSMIT and RECEIVE commands support only ten NAMES data sets, but the NAMES data set specified more than ten via the ALTCTL tag. This message is followed by message INMC006I identifying the data set and record in which the ALTCTL tag was found.

System action: Only the first ten NAMES data sets are used. Others are ignored.

User response: Remove the necessary number of ALTCTL specifications from the indicated NAMES data set.

Module: INMRQ, INMXQ

Audience: TRANSMIT or RECEIVE user

INMC011I **The value *dsname* is too long for an ALTCTL tag. It will be ignored.**

Explanation: An ALTCTL tag was found in a NAMES data set with more than 44 characters. A data set name must be 44 characters or less. This message is followed by message INMC006I identifying the data set and record in which the erroneous ALTCTL tag was found.

System action: The ALTCTL tag and its associated value are ignored.

User response: Correct the data set name value.

INMC012I • INMC154I

Module: INMRQ, INMXQ

Audience: TRANSMIT or RECEIVE user

INMC012I The data set organization of names data sets must be physical sequential.

Explanation: The TRANSMIT or RECEIVE command processor found a NAMES data set that was not organized as a physical sequential data set. All NAMES data sets must be physical sequential data sets.

System action: The TRANSMIT or RECEIVE command processor terminates.

User response: Assign only physical sequential data sets as NAMES data sets.

Module: INMCA

Audience: TRANSMIT or RECEIVE user

INMC150I *command_name* command terminated by installation exit *exit_name*

Explanation: The TRANSMIT or RECEIVE command invoked the named installation exit routine, which terminated the command.

System action: The TRANSMIT or RECEIVE command terminates.

User response: Contact your system programmer for assistance.

Module: INMCA

Audience: TRANSMIT or RECEIVE user

INMC151I *installation_supplied_message_text*

Explanation: The TRANSMIT or RECEIVE command invoked an installation exit that returned this text to be sent as a message to the user.

System action: None.

User response: Contact your system programmer for assistance.

Module: INMCA, INMCA

Audience: TRANSMIT or RECEIVE user

INMC153I Unexpected error from ISITMGD, **Retcode:** *return_code*, **Reason:** *reason_code*.

Explanation: This message is preceded by message INMX216I or INMR200I. An internal service that is used by TRANSMIT or RECEIVE (the ISITMGD macro) returned an unexpected error. For an explanation of the return codes and reason codes, see *z/OS DFSMS Macro Instructions for Data Sets*.

System action: The TRANSMIT or RECEIVE command processor terminates.

User response: Contact your system programmer.

Module: INMXI, INMRALLO

Audience: TRANSMIT or RECEIVE user

INMC154I Unexpected error returned by IGWFAMS.

Explanation: This message is preceded by message INMX216I or INMR200I. The SMS service IGWFAMS, used internally by TRANSMIT and RECEIVE, has returned an unexpected error.

System action: The TRANSMIT or RECEIVE command processor terminates.

User response: Contact your system programmer.

Module: INMXI, INMRALLO

Audience: TRANSMIT or RECEIVE user

INMC155I Retrieving JES node name failed, return code from IEFSSREQ: *return_code*, node name set to ????????

Explanation: Because an asterisk was found in the TRANSREC NODESMF (*,*) statement in IKJTSOxx member of "logical" SYS1.PARMLIB, an attempt was made to retrieve the node name from JES by means of the IEFSSREQ interface. However, IEFSSREQ has returned an unexpected error.

Note: the use of TRANSREC NODESMF (*,*) is only supported at JES2 4.3.0 or higher or JES3 5.1.1 or higher.

System action: Processing of TRANSMIT or RECEIVE continues, however, the node name is set to ????????

A return_code of 4 from IEFSSREQ indicates that the subsystem (JES) does not support this function.

User response: If a return_code of 4 is received from IEFSSREQ, the system programmer should update IKJTSOxx TRANSREC NODESMF to hardcode valid nodenames and smfids. Otherwise, contact your system programmer to determine why IEFSSREQ failed.

Module: INMXM, INMRTFY

Audience: TRANSMIT or RECEIVE user

INMC156I Unexpected error returned by the SMS service module.

Explanation: An internal problem was encountered in connection with service module IKJSMS1, which retrieves data set information from SMS.

System action: The function is terminated. Abend 0AF is forced.

User response: Contact your system programmer to diagnose the problem.

Module: The caller of IKJSMS1, INMXI, INMRALLO

Audience: TRANSMIT or RECEIVE user

INMC214I Invalid message length provided by installation exit for message INMC151I

Explanation: A message length value of less than 0 or greater than 243 was provided by an installation exit for the message text to be issued with message INMC151I.

System action: Message INMC151 is not issued by the TRANSMIT or RECEIVE command. Processing continues normally.

User response: Contact your system programmer for assistance.

Module: INMCA

Audience: TRANSMIT or RECEIVE user

INMR000I No more files remain for the RECEIVE command to process.

Explanation: You have received all messages and data sets available for your prefix ID.

System action: The RECEIVE command processor terminates.

User response: None.

Module: INMRM

Audience: RECEIVE user

INMR001I Restore successful to data set *dsname*.

Explanation: The RECEIVE command processor successfully completed restoring (or copying) the current file, which is now stored in the indicated data set.

System action: The RECEIVE command processor terminates.

User response: None.

Module: INMRM

INMR002I • INMR006I

Audience: RECEIVE user

INMR002I File deleted.

Explanation: The RECEIVE command has deleted the current input file, even though it was not successfully restored. Files which have not been successfully restored are deleted only with the consent of the user. Therefore, this file was deleted as a result of either the DELETE keyword being specified in response to message INMR907A or by K not being specified in response to message IMNR910A.

System action: The RECEIVE command continues with the next file.

User response: None.

Module: INMRM

Audience: RECEIVE user

INMR003I You have no messages or data sets to receive.

Explanation: The RECEIVE command has ended successfully. No messages or data sets are available for you to receive.

System action: The RECEIVE command processor terminates normally.

User response: None.

Module: INMRM

Audience: RECEIVE user

INMR004I DELETE ignored; file contains previously received data.

Explanation: The file you attempted to delete contains information copied during a previous RECEIVE operation. The information was received using the INDATASET, INDSNAME, INFILE, or INDDNAME parameter on the RECEIVE command. You cannot delete such files using the RECEIVE command.

System action: The RECEIVE command processor terminates normally.

User response: To delete the file, type the TSO/E DELETE command followed by the data set name.

Module: INMRM

Audience: RECEIVE user

INMR005I Invalid message length provided by installation exit for message INMR151I.

Explanation: An invalid message length value of less than 0 or greater than 243 was provided by an installation exit for the message text to be issued with message ID INMR151I.

System action: Message INMR151I is not issued, but the RECEIVE command processor continues normally.

User response: Notify your system programmer.

Module: INMRZ

Audience: RECEIVE user

INMR006I RECEIVE command terminated. The data set you specified cannot be used to receive the incoming data set. The block sizes are incompatible.

Explanation: The data set that was specified as a RESTORE parameter cannot be used to receive the incoming data set. The block size of the specified data set is larger than the track size of the device on which it resides. In addition, the incoming data set has an unknown block size. This combination is incompatible.

System action: The RECEIVE command processor terminates.

User response: Specify a different data set to receive the incoming data set, or change the block size of the data set specified as a RESTORE parameter. The specified data set must have a block size smaller than the track size of the device on which it resides.

Module: INMRBVS

Audience: RECEIVE user

INMR007I Time stamp in the incoming data is not valid. Zero will be substituted.

Explanation: The incoming data has an invalid time stamp in the control records. The time stamp consists of the date and time. Zero will be substituted, and processing will continue normally. See *z/OS TSO/E Customization* for more information about specifying dates and times in control records.

System action: The RECEIVE command processor continues normally.

User response: None.

Module: INMCTIME

Audience: RECEIVE user

INMR008I The input file has been kept. No more files will be processed by the receive command.

Explanation: The RECEIVE data set post-processing exit (INMRZ12) requested that the input file for this RECEIVE operation be kept. No other files will be processed during this invocation of the RECEIVE command.

System action: The RECEIVE command processor terminates.

User response: None.

Module: INMRM

Audience: RECEIVE user

INMR009I Warning: Generated data set name is too long; has been truncated to a valid data set name.

Explanation: When RECEIVE is issued to read an incoming data set the generated default name is derived from the name of the incoming data set by replacing the high-level qualifier of the incoming data set by the receiving user's TSO prefix.

System action: The data set is successfully restored. The data set name is truncated to 44 characters. If the resulting name ends with a period, the period is also truncated. The new name is shown in message INMR001I, which follows message INMR009I.

User response: None.

Module: INMRM

Audience: RECEIVE user

INMR030I RECEIVE command terminated. ABEND *abend_code*.

Explanation: The RECEIVE command processor has abnormally terminated. The ABEND termination code is specified by the *abend_code* in the message. Message INMR031I which follows gives the reason code (register 15 value) for the ABEND.

System action: The RECEIVE command processor terminates.

User response: User response depends on the nature of the ABEND. Some ABEND codes, such as B37 and D37, are indications of lack of space and generally indicate that the ABEND was the result of user errors. Other ABEND codes, such as the 0Cx series, are program checks and should be corrected through the IBM programming service system.

Module: INMRR

Audience: RECEIVE user

INMR031I • INMR035I

INMR031I Register 15 value at ABEND was *nnnn*.

Explanation: The RECEIVE command processor has abnormally terminated. The ABEND termination code is specified by message INMR030I. This message gives the value for register 15 at the time of the ABEND; for certain ABENDs, this value is a reason code.

System action: The RECEIVE command processor terminates abnormally.

User response: User response depends on the nature of the ABEND.

Module: INMRR

Audience: RECEIVE user

INMR032I RECEIVE command terminated. Incorrect use of the RESTORE keyword. +

Explanation: The RECEIVE command processor prompted the user for parameters to be used in copying a file and the user replied with the RESTORE keyword. Only COPY, DELETE, or END are valid if the file contains errors.

System action: The RECEIVE command processor terminates.

User response: Do not specify the RESTORE keyword in response to message INMR907A.

Module: INMRUINP

Audience: RECEIVE user

INMR033I File type cannot be restored.

Explanation: The file you attempted to receive does not have a format that is valid for the RECEIVE command to process.

System action: The RECEIVE command processor terminates.

User response: Do not specify the RESTORE keyword in response to message INMR907A.

Module: INMRUINP

Audience: RECEIVE user

INMR034I RECEIVE command terminated. Failure in command syntax checking. +

Explanation: The RECEIVE command processor invoked the IKJPARS TSO/E service routine to perform syntax checking on the command parameters, but the service routine completed unsuccessfully. Subsequent messages identify the error more precisely.

System action: The RECEIVE command processor terminates abnormally.

User response: Your response is determined by the messages that follow.

Module: INMRSCMD, INMRUINP

Audience: RECEIVE user

INMR035I The command was incomplete or in error, but prompting was inhibited

Explanation: The RECEIVE command processor invoked the IKJPARS TSO/E service routine to perform syntax checking on the command parameters. However, the service routine completed unsuccessfully because the RECEIVE command or RESTORE specification was incomplete or in error and prompting was inhibited. Prompting is inhibited when you enter the PROFILE command with the NOPROMPT keyword, or when you execute a CLIST in NOPROMPT mode (the default), or when you execute a REXX exec with the PROMPT option off.

System action: The RECEIVE command processor terminates.

User response: Issue the PROFILE command with the PROMPT keyword, add a "CONTROL PROMPT" command to the CLIST, or add PROMPT(ON) for an exec. These actions allow the RECEIVE command processor to issue the normal prompting messages, which then enables you to correct the invalid or incomplete command.

Module: INMRSCMD, INMRUINP

Audience: RECEIVE user

INMR036I Return code *return_code* from IKJPARS

Explanation: The RECEIVE command processor invoked the IKJPARS TSO/E service routine to perform syntax checking on the command parameters, but the service routine completed unsuccessfully. Return codes from IKJPARS are explained in *z/OS TSO/E Programming Services*.

System action: The RECEIVE command processor terminates abnormally.

User response: Your action depends on the return code from IKJPARS.

Module: INMRSCMD, INMRUINP

Audience: RECEIVE user

INMR037I RECEIVE command terminated. Return code *nm* from JES.

Explanation: The RECEIVE command processor invoked the JES subsystem interface to determine if any Interactive Data Transmission Facility files were available for you to receive. The JES subsystem request was not successful and returned the code displayed in the error message.

System action: The RECEIVE command processor terminates abnormally.

User response: Notify your system programmer.

Module: INMRM

Audience: RECEIVE user

INMR040I Error attempting to prompt for data set deletion information. +

Explanation: The RECEIVE command processor encountered a file that had invalid or missing header records. The command processor determined that the file could not be restored and should therefore be deleted. However, when the command processor attempted to prompt the user for permission to delete the file, the prompt failed. A subsequent message indicates the exact nature of the prompting failure.

System action: The RECEIVE command processor terminates abnormally. The file cannot be deleted.

User response: Note the specific type of prompt error indicated by a subsequent message and use this information to correct the problem.

Module: INMRM

Audience: RECEIVE user

INMR041I Prompting was inhibited.

Explanation: The RECEIVE command was attempting to prompt you for permission to delete a file which was in error, but prompting was inhibited. Prompting is inhibited when you enter the PROFILE command with the NOPROMPT keyword, when you execute a CLIST in NOPROMPT mode (the default), or when you execute a REXX exec with the PROMPT option off.

System action: The RECEIVE command terminates abnormally.

User response: Issue the PROFILE command with the PROMPT keyword, add a "CONTROL PROMPT" command to the CLIST, or add PROMPT(ON) for an exec. These actions allow the RECEIVE command processor to issue the normal prompting messages when the RECEIVE command is next invoked.

Module: INMRM

Audience: RECEIVE user

INMR042I RECEIVE failed; system cannot prompt you for information. +

Explanation: The RECEIVE command failed. The system needs additional information to complete RECEIVE processing. However, it cannot prompt you for that information, because your current TSO/E PROFILE setting is NOPROMPT, you are running a CLIST in CONTROL NOPROMPT mode, or you are running a REXX exec with the PROMPT option off.

System action: The RECEIVE command terminates abnormally.

User response: Note the specific type of prompt error indicated by subsequent messages, and use this information to correct the problem.

Module: INMRALLO, INMRCODE, INMRF, INMRUINP

Audience: RECEIVE user

INMR043I Prompting was inhibited.

Explanation: The RECEIVE command processor was attempting to prompt the user for data set RESTORE parameters but prompting was inhibited. Prompting is inhibited when you enter the PROFILE command with the NOPROMPT keyword, when you execute a CLIST in NOPROMPT mode (the default), or when you execute a REXX exec with the PROMPT option off.

System action: The RECEIVE command terminates abnormally.

User response: Issue the PROFILE command with the PROMPT keyword, add a "CONTROL PROMPT" command to the CLIST. or add PROMPT(ON) for an exec. These actions allow the RECEIVE command processor to issue the normal prompting messages when the RECEIVE command is next invoked.

Module: INMRALLO, INMRCODE, INMRF, INMRUINP

Audience: RECEIVE user

INMR044I Return code *return_code* from IKJEFF02.

Explanation: The RECEIVE command processor invoked the IKJEFF02 TSO/E service routine to prompt the user for data set RESTORE parameters. However, the prompt failed and the service routine issued the *return_code* provided in the message text. Return codes for IKJEFF02 are explained in *z/OS TSO/E Programming Services*.

System action: The RECEIVE command terminates abnormally.

User response: Use the IKJEFF02 return code to determine the specific reason for the prompting failure. Then use this information to correct the error.

Module: INMRALLO, INMRCODE, INMRF, INMRM, INMRUINP

Audience: RECEIVE user

INMR045I Data set *dsname* already exists. Reply 'R' to replace it. +

Explanation: The RECEIVE command processor generated the indicated default name for the output data set and found that a data set with that name already existed. A reply of 'R' to this message will allow the RECEIVE command processor to overwrite the data set or identically named members within the data set. Any other reply will cause the RECEIVE command processor to terminate abnormally.

System action: The RECEIVE command processor waits for a response.

User response: Reply 'R' for RECEIVE to overwrite the data set or identically named members within the data set. Reply anything else to terminate RECEIVE processing without receiving the data.

Module: INMRALLO

Audience: RECEIVE user

INMR046I Any other reply will cause RECEIVE to terminate without overwriting the file.

Explanation: The RECEIVE command generated the default name for the output data set and found that the data set already exists and that it is a sequential data set. A reply of 'R' to this message will allow RECEIVE to over write the data set. Any other reply will cause RECEIVE to terminate.

System action: The RECEIVE command waits for a response from you.

User response: Reply 'R' or something else, as appropriate.

Module: INMRALLO

Audience: RECEIVE user

INMR047I Data set *dsname* already exists. RECEIVE exit specified NOPROMPT.

Explanation: The RECEIVE command processor generated the indicated default name for the output data set and found that a data set with that name already existed. The RECEIVE exit, INMRZ11R, specified NOPROMPT.

System action: The RECEIVE command processor continued and wrote over the data set.

User response: None.

Module: RECEIVE

Audience: RECEIVE user

INMR056I RECEIVE command terminated. You are not authorized to receive data for *user_id*.

Explanation: You are not authorized to specify the USERID keyword on the RECEIVE command.

System action: The RECEIVE command processor terminates.

User response: Check with your installation management. With their approval, you may be authorized to use the USERID keyword.

Module: INMRM

Audience: RECEIVE user

INMR057I RECEIVE command terminated because it was not invoked authorized.

Explanation: The RECEIVE command was invoked in a non-authorized environment but required some authorized function (either the external writer interface or the use of IEBCOPY to reload a partitioned data set). RECEIVE can only be run non-authorized for receiving sequential files and only when the INDATASET, INDSNAME, INFILE, or INDDNAME keyword is specified.

System action: The RECEIVE command processor terminates.

User response: If you feel the RECEIVE command should have been authorized, check with your installation support personnel about environments which may not be authorized (such as option 6 of SPF).

Module: INMRM, INMRPDS

Audience: RECEIVE user

INMR060I RECEIVE command terminated. Output data set unusable. +

Explanation: The RECEIVE command processor was attempting to restore or copy an output data set and encountered an error. Subsequent messages indicate the specific nature of the error.

System action: The RECEIVE command processor terminates.

User response: Use the information provided in subsequent messages to correct the error. You may then reissue the RECEIVE command.

Module: INMRALLO, INMRVBS, INMRM80

Audience: RECEIVE user

INMR061I *Dsname is a sequential data set, but the data set being received is partitioned.*

Explanation: The RECEIVE command processor was attempting to restore a data set to the indicated data set name. The specified data set is sequential while the data set being received is partitioned.

System action: The RECEIVE command processor terminates.

User response: Reissue the RECEIVE command, specifying a partitioned data set to which the RECEIVE command processor should restore the data.

Module: INMRALLO

Audience: RECEIVE user

INMR062I *Dsname is a partitioned data set, but no member name was specified.*

Explanation: The RECEIVE command processor was attempting to restore a data set to the indicated data set name. The specified data set is partitioned, but the data set being received is a sequential data set and no member name was specified.

System action: The RECEIVE command processor terminates.

User response: Reissue the RECEIVE command, specifying a sequential data set or a member of a partitioned data set.

Module: INMRALLO

Audience: RECEIVE user

INMR063I **Allocation failure for data set** *dsname*

Explanation: The RECEIVE command processor was attempting to restore a data set to the indicated data set name. However, when SVC 99 was issued to allocate the data set, it failed. Subsequent messages indicate the exact nature of the failure.

System action: The RECEIVE command processor terminates.

User response: Verify that the data set name is correct and that the data set can either be used or be created. Subsequent messages may also help to isolate the cause of failure.

Module: INMRALLO

Audience: RECEIVE user

INMR064I **A single member was specified, but more than one member was being received.**

Explanation: The RECEIVE command processor was attempting to restore a partitioned data set containing more than one member. However, the user specified the target data set as a single member of a partitioned data set.

System action: The RECEIVE command processor terminates.

User response: Reissue the RECEIVE command, specifying the name of a partitioned data set (without a member name) as the output data set. This will enable the RECEIVE command processor to create a member in the output data set for each received member.

Module: INMRUINP

Audience: RECEIVE user

INMR065I **Record format of output data set incompatible with record format of incoming file. +**

Explanation: The RECEIVE command processor was attempting to restore a data set. However, the target data set specified by the user was incompatible with the received data and restoration was not possible. Message INMR066I, which follows, gives the format of the received data.

System action: The RECEIVE command processor terminates.

User response: Enter a question mark to get more information about the incoming file. Then, using this information, reissue the RECEIVE command specifying a compatible data set or a data set name that is not already in use. The

RECEIVE command processor can now create a data set with the appropriate attributes.

Module: INMRVBS, INMR80

Audience: RECEIVE user

INMR066I Input: RECFM=*rrr*, LRECL=*lll*, BLKSIZE=*bbb*.

Explanation: The RECEIVE command processor was attempting to restore a data set. However, the target data set specified by the user was incompatible with the received data and restoration was not possible. This message gives the attributes of the received data.

System action: The RECEIVE command processor terminates.

User response: Reissue the RECEIVE command, specifying a compatible data set or a data set name that is not already in use. The RECEIVE command processor can now create a data set with the appropriate attributes.

Module: INMRVBS, INMR80

Audience: RECEIVE user

INMR067I Data set *dsname* is invalid. Enter RECEIVE. When prompted, specify valid data set name.

Explanation: You must specify a valid data set name. The default data set name is not valid.

System action: The RECEIVE command processor terminates abnormally.

User response: Reissue the RECEIVE command, specifying a valid data set name via the DSNAME or DATASET keywords in response to the IMNR906A prompt message.

Module: INMRALLO

Audience: RECEIVE user

INMR068I RECEIVE ended. Input record length '999' is too long.

Explanation: You have specified RESTORE(log). The incoming data had a record length of greater than 255 (record length for the log) and could not be written to the log.

System action: The RECEIVE command processor terminates.

User response: Reissue the RECEIVE command. In response to message INMR907A, specify DATASET or DSNAME instead of RESTORE(log).

Module: INMRF

Audience: RECEIVE user

INMR069I Data set organization of data set *dsname* is not supported.

Explanation: The RECEIVE command was issued and the indicated data set had a data set organization not supported by RECEIVE. Supported organizations are physical sequential and partitioned.

System action: The RECEIVE command terminates.

User response: You cannot receive into data sets of this type. Reissue the RECEIVE command and specify an output data set with a supported data set organization.

Module: INMRALLO

Audience: RECEIVE user

INMR070I RECEIVE command terminated. Failure in partitioned data set reloading process. +

Explanation: The RECEIVE command processor was attempting to restore a partitioned data set and was setting up for or using the IEBCOPY utility to reload the data set. An error was encountered in this process. Subsequent messages describe the exact nature of this error.

System action: The RECEIVE command terminates.

INMR071I • INMR080I

User response: Use the information provided in following messages to correct the error. Then, reissue the RECEIVE command.

Module: INMRALLO, INMRPDS

Audience: RECEIVE user

INMR071I Allocation failed for IEBCOPY *nmn* file.

Explanation: The RECEIVE command was attempting to restore a partitioned data set and was allocating temporary files to be used by the IEBCOPY utility during the reload. The allocation of one of these files failed. (The file for which allocation failed is either 'INPUT', 'CONTROL CARD', 'MESSAGE', or 'SYSUT3 WORK'.) The failure was probably caused by specification errors in the installation control CSECT INMXPARM. If the VIO keyword was incorrectly specified, the 'INPUT', 'CONTROL CARD', or 'SYSUT3 WORK' allocations may fail. If the SYSOUT keyword was incorrect, then the 'MESSAGE' file allocation may fail. An incorrect specification of the SYSOUT keyword on the RECEIVE command data set prompt could cause the 'MESSAGE' file allocation to fail.

System action: The RECEIVE command processor terminates.

User response: Contact your system programmer.

Module: INMRALLO, INMRPDS

Audience: RECEIVE user

INMR072I Return code *return_code* from IEBCOPY utility.

Explanation: The RECEIVE command processor was attempting to restore a partitioned data set and had invoked the IEBCOPY utility to reload the data set. The utility terminated with errors which may have appeared at the terminal.

System action: The RECEIVE command processor terminates.

User response: Correct the problem as indicated by the IEBCOPY messages. If no IEBCOPY messages were received, reissue the RECEIVE command and add the SYSOUT(*) keyword to the reply to message INMR907I.

Module: INMRPDS

Audience: RECEIVE user

INMR073I Return code *return_code* from IEBCOPY utility.

Explanation: The RECEIVE command processor was attempting to restore a partitioned data set and had invoked the IEBCOPY utility to reload the data set. The utility terminated with errors which may have appeared at the terminal.

System action: The RECEIVE command processor terminates.

User response: Correct the problem as indicated by the IEBCOPY messages. If no IEBCOPY messages were received, reissue the RECEIVE command and add the SYSOUT(*) keyword to the reply to message INMR907I.

Module: INMRPDS

Audience: RECEIVE user

INMR080I RECEIVE command terminated. Failure in decryption processing. +

Explanation: The RECEIVE command processor was attempting to decipher an encrypted file, but failed during the decipher process. Subsequent messages indicate the specific error encountered.

System action: The RECEIVE command processor terminates.

User response: Use the subsequent messages to correct the problem and then reissue the RECEIVE command.

Module: INMRALLO, INMRCODE

Audience: RECEIVE user

INMR081I Allocation failed for REPRO command *nmn* file.

Explanation: The RECEIVE command processor was attempting to decipher an encrypted file and was allocating temporary files to be used by the AMS REPRO command. The allocation for one of these files failed. (The file for which allocation failed is either 'CONTROL CARD' or 'MESSAGE'.) The failure was probably caused by specification errors in the installation control CSECT INMXPARM. If the VIO keyword was incorrectly specified, the 'CONTROL CARD' file allocation may fail. If the SYSOUT keyword was incorrect, then the 'MESSAGE' file allocation may fail. An incorrect specification of the SYSOUT keyword on the RECEIVE command data set prompt could also cause the 'MESSAGE' file allocation to fail.

System action: The RECEIVE command processor terminates.

User response: Contact your system programmer.

Module: INMRALLO, INMRCODE

Audience: RECEIVE user

INMR082I Return code *return_code* from IDCAMS REPRO command.

Explanation: The RECEIVE command processor was attempting to decipher an encrypted data set and had invoked the AMS REPRO command processor to decipher the file. The REPRO command processor terminated with errors and may have sent messages to the terminal.

System action: The RECEIVE command processor terminates.

User response: Use the IDCAMS messages to correct the problem. If no IDCAMS messages were received, reissue the RECEIVE command and add the SYSOUT(*) keyword to the reply to message INMR907I.

Module: INMRCODE

Audience: RECEIVE user

INMR083I Open failed for DDname *ddname*.

Explanation: The RECEIVE command processor was unable to open the specified DD name.

System action: The RECEIVE command processor terminates.

User response: Retry the command.

Module: INMRCODE

Audience: RECEIVE user

INMR090I RECEIVE command logging function terminated. +

Explanation: The RECEIVE command processor was attempting to log a received file and encountered an error in the logging process. Subsequent messages indicate the exact nature of the error.

System action: The RECEIVE command processor continues, but this file cannot be logged.

User response: Use subsequent messages to correct the problem.

Module: INMRLOGO

Audience: RECEIVE user

INMR091I Error allocating log data set *dsname* +

Explanation: The RECEIVE command processor was attempting to log a received file but was unable to allocate the indicated log data set. A subsequent message indicates the exact nature of the allocation failure.

System action: The RECEIVE command processor continues, but this file cannot be logged.

User response: Use the allocation message to correct the problem.

Module: INMRLOGO

Audience: RECEIVE user

INMR092I • INMR108I

INMR092I OPEN error for log data set *dsname*.

Explanation: The RECEIVE command processor was attempting to log a received file but was unable to OPEN the indicated log data set.

System action: The RECEIVE command processor continues, but this file cannot be logged.

User response: Ensure that the indicated log data set is usable.

Module: INMRLOGO

Audience: RECEIVE user

INMR093I Log entry will be written to data set *dsname*.

Explanation: The RECEIVE command processor was logging a received file to a data set that is not the user's default log. This happened because the originating user's entry in the NAMES file specified the LOGNAME tag.

System action: The RECEIVE command processor continues normally.

User response: None.

Module: INMRLOGO

Audience: RECEIVE user

INMR101I Restore not possible. Unsupported utility *xxx* requested by input file.

Explanation: The RECEIVE command processor was reading the control records of an incoming file and encountered a request for an unsupported utility in the INMR02 control record. The unsupported utility is part of a new facility for network transmission which is not supported by your RECEIVE command. The received data cannot be restored, but can be copied in transmission format.

System action: The RECEIVE command processor issues message INMR907I to allow the user to specify the COPY or DELETE option.

User response: None.

Module: INMRO

Audience: RECEIVE user

INMR102I RESTORE not possible. Input data is not complete.

Explanation: The RECEIVE command processor was reading the control records of an incoming file and found them either incorrect or incomplete. The incoming file cannot be correctly restored.

System action: The RECEIVE command processor issues message INMR907I to allow the user to specify the COPY or DELETE option.

User response: None.

Module: INMRO

Audience: RECEIVE user

INMR108I RECEIVE command terminated. Trailer record missing.

Explanation: The RECEIVE command processor encountered an input file with a missing trailer control record. The error was probably the result of an incomplete transmission from the originator.

System action: The RECEIVE command processor terminates, leaving the incoming file on the JES spool.

User response: Reissue the RECEIVE command, specifying the COPY or DELETE option.

Module: INMRVBS

Audience: RECEIVE user

INMR109I An error was encountered while processing a control record.

Explanation: The RECEIVE command processor encountered an end-of-file condition while processing a control record following the data file.

System action: The RECEIVE command processor terminates, leaving the incoming file on the JES spool.

User response: Reissue the RECEIVE command, and specify the COPY or DELETE option.

Module: INMRVBS

Audience: RECEIVE user

INMR127I Error in allocation for JES input data set.

Explanation: The RECEIVE command attempted to allocate a spool file and the allocation failed. The RECEIVE command obtained the name of a spool file from JES using the process SYSOUT subsystem interface. When the RECEIVE command attempted to allocate the spool file using the spool file name, the allocation failed.

System action: The RECEIVE command processor terminates and a system dump is taken.

User response: Reissue the RECEIVE command. If the problem recurs, notify your system programmer.

Module: INMRM

Audience: RECEIVE user

INMR128I Data set organization for data set *dsname* is not supported for RECEIVE input.

Explanation: The RECEIVE command was issued with the INDATASET, INDSNAME, INDDNAME, or INFILE keyword. However, the specified input file had a data set organization that RECEIVE cannot use.

System action: The RECEIVE command terminates.

User response: You must specify either a sequential data set or a member of a partitioned data set then, reissue the RECEIVE command.

Module: INMRM

Audience: RECEIVE user

INMR129I Error in allocation for data set *dsname*.

Explanation: The RECEIVE command was issued with the INDATASET or INDSNAME keyword. The RECEIVE command processor was attempting to allocate the specified input data set but the allocation failed. Subsequent messages identify the exact nature of the allocation failure.

System action: The RECEIVE command processor terminates.

User response: Reissue the RECEIVE command, specifying a valid input data set.

Module: INMRM

Audience: RECEIVE user

INMR130I RECEIVE command terminated. Input data set unusable. +

Explanation: The RECEIVE command processor encountered an unrecoverable error in its input file. Subsequent messages identify the exact nature of the error.

System action: The RECEIVE command processor terminates.

User response: None.

Module: INMRF, INMRM, INMRO, INMRVBS, INMR80

Audience: RECEIVE user

INMR131I • INMR135I

INMR131I Error in OPEN for DDNAME *ddname*.

Explanation: The RECEIVE command was issued with the INDDNAME or INFILE keyword. An OPEN was issued for the specified file, but the OPEN was unsuccessful.

System action: The RECEIVE command processor terminates.

User response: Check the validity of the specified file and reissue the RECEIVE command.

Module: INMRM

Audience: RECEIVE user

INMR132I Error in OPEN for data set *dsname*.

Explanation: The RECEIVE command was issued with the INDATASET or INDSNAME keyword. The data set was allocated successfully, but the OPEN for the data set failed.

System action: The RECEIVE command processor terminates and a system dump is taken.

User response: Notify your system programmer.

Module: INMRM

Audience: RECEIVE user

INMR133I Error in OPEN for JES input file.

Explanation: The RECEIVE command processor input selected an input file from the JES spool and the file was successfully allocated. However, an OPEN for the file failed.

System action: The RECEIVE command processor terminates and a system dump is taken.

User response: Notify your system programmer.

Module: INMRM

Audience: RECEIVE user

INMR134I Deallocation failed for input file.

Explanation: The RECEIVE command processor was performing cleanup after processing an input file and an attempt to deallocate the input file failed.

System action: The RECEIVE command processor terminates and a system dump is taken.

User response: Notify your system programmer.

Module: INMRM

Audience: RECEIVE user

INMR135I Permanent I/O error reading input file. +

Explanation: The RECEIVE command processor encountered a permanent I/O error. A subsequent message identifies the I/O error.

System action: The RECEIVE command processor terminates.

User response: Notify your system programmer.

Module: INMRF, INMRO, INMRVBS, INMR80

Audience: RECEIVE user

INMR136I *I/O_error_message_text*

Explanation: The RECEIVE command processor encountered a permanent I/O error. For an explanation of the message text, see Message IOS000I in *z/OS MVS System Messages, Vol 9 (IGF-IWM)*.

System action: The RECEIVE command processor terminates.

User response: Notify your system programmer.

Module: INMRF, INMRO, INMRVBS, INMR80

Audience: RECEIVE user

INMR137I **Unable to terminate external writer.**

Explanation: The RECEIVE command processor was performing cleanup before termination but failed to terminate the external writer interface. A subsequent message indicates the exact nature of the error encountered.

System action: The RECEIVE command processor terminates and a system dump is taken.

User response: Notify your system programmer.

Module: INMRM

Audience: RECEIVE user

INMR138I **Received record longer than output block size.**

Explanation: The RECEIVE command processor encountered a record too large to be written to the output file. The current input file cannot be correctly restored.

System action: The RECEIVE command processor terminates.

User response: Reissue the RECEIVE command, specifying either the COPY or DELETE option.

Module: INMRF, INMRVBS

Audience: RECEIVE user

INMR139I **Input file is empty.**

Explanation: The RECEIVE command processor encountered an empty input file.

System action: If the input file was a JES spool file, the RECEIVE command processor asks permission to delete the file. If the input was specified via INDATASET, INDSNAME, or INFILE, the RECEIVE command processor terminates.

User response: If the input file was a JES spool file, you will probably want to delete the file and continue with the next one. To do this, press the Enter key in response to prompt message INMR910A.

Module: INMRUINP

Audience: RECEIVE user

INMR140I **Receipt notification unsuccessful. +**

Explanation: The RECEIVE command processor was attempting to send notification of receipt back to the sender of the file, but the notification was unsuccessful. A subsequent message describes the exact nature of the error.

System action: The RECEIVE command processor terminates the notification process and continues with the next input file.

User response: None.

Module: INMRNTFY

Audience: RECEIVE user

INMR141I • INMR145I

INMR141I OPEN failed for JES output file.

Explanation: The RECEIVE command processor was attempting to send a notification of receipt back to the sender of the file, but the attempt to OPEN the SYSOUT file used for the message to the sender was unsuccessful.

System action: The RECEIVE command processor terminates the notification process and continues with the next input file.

User response: None.

Module: INMRNTFY

Audience: RECEIVE user

INMR142I Node name *node_name* not known to JES.

Explanation: The RECEIVE command processor was attempting to send notification of receipt back to the sender of the file, but failed because the sender's node name was not known to JES at your node.

System action: The RECEIVE command processor terminates the notification process and continues with the next input file.

User response: Ask your system programmer to define the sender's node to JES at your node.

Module: INMRNTFY

Audience: RECEIVE user

INMR143I Error allocating JES output file.

Explanation: The RECEIVE command processor was attempting to send a notification of receipt back to the sender of the file, but failed because of an error in allocating a SYSOUT file for the message to the sender. A subsequent message describes the error more precisely.

System action: The RECEIVE command processor terminates the notification process and continues with the next input file.

User response: None.

Module: INMRNTFY

Audience: RECEIVE user

INMR144I Sender notified of receipt.

Explanation: The RECEIVE command has sent a receipt acknowledgment back to the sender of the file.

System action: Continues with the normal processing.

User response: None.

Module: INMRNTFY

Audience: RECEIVE user

INMR145I RECEIVE terminated, JES is not active.

Explanation: The system could not execute the RECEIVE command because JES was not active when you issued RECEIVE.

System action: Terminates RECEIVE processing.

User response: Reissue the RECEIVE command after JES has been started.

Module: INMRM

Audience: RECEIVE user

INMR146I System not at required level to support userid.

Explanation: The RECEIVE command processor was unable to send notification of receipt to the user identified in the message.

System action: The RECEIVE command processor makes no further attempt to notify the sender. It continues with the next input file.

User response: None

Module: INMRNTFY

Audience: RECEIVE user

INMR149I Exit INMRZ21R returned a non-zero return code.

Explanation: The RECEIVE command invoked installation exit INMXZ21R, which returned a non-zero return code.

System action: The RECEIVE command processor does not perform the logging function.

User response: Contact your system programmer for assistance.

Module: INMRZ

Audience: RECEIVE user

INMR150I RECEIVE command terminated by installation exit *exit_name*.

Explanation: The RECEIVE command processor invoked the named installation exit and the exit instructed the RECEIVE command processor to terminate.

System action: The RECEIVE command processor terminates.

User response: Contact you system programmer.

Module: INMRZ

Audience: RECEIVE user

INMR151I *Installation_message_text*

Explanation: The RECEIVE command processor invoked an installation exit and the exit returned this message text.

System action: None.

User response: Contact your system programmer.

Module: INMRZ, INMRZ

Audience: RECEIVE user

INMR152I RECEIVE failed. Your node ID not recognized.

Explanation: The RECEIVE command failed because the CSECT INMXPARM does not contain the node ID of the receiving system.

Your installation might not have replaced the IBM-supplied default CSECT, the node ID might be misspelled or omitted, or INMXPARM might not be installed correctly.

System action: The RECEIVE command processor terminates.

User response: Check the node ID. If it is correct and the problem persists, notify your system programmer.

Module: INMRM

Audience: RECEIVE user

INMR153I RECEIVE failed. Userid not available.

Explanation: The RECEIVE command requires that a valid TSO/E user ID be present in the ASXBUSER control block field before terminal monitor program initiation. A valid TSO/E user ID is, non-blank, one to seven characters in length, first character must be an alphabetic or national character (A-Z, #, @, \$). The other characters may be alphanumeric or national characters (A-Z, 0-9, #, @, \$).

System action: The RECEIVE command processor terminates.

User response: Run RECEIVE in the foreground and notify your system programmer. RECEIVE will not run in the background unless RACF is installed or the ASXBUSER field is filled in with a valid TSO/E user ID before module IKJEFT01 receives control. Note that the user ID specified as IKJEFT01 receives control must not be longer than seven characters in length.

Module: INMRM

Audience: RECEIVE user

INMR154I The incoming data set is a 'DATA / PROGRAM LIBRARY'

Explanation: This message informs you that your are receiving a PDSE that is either a program library or a data library. A data library can be received into a data library, an empty PDSE (library), or a PDS. A program library can be received into a program library or an empty PDSE (library).

System action: The RECEIVE command processor terminates.

User response: None.

Module: INMRALLO

Audience: RECEIVE user

INMR155I A sequential data set cannot be received into a program library.

Explanation: This message is preceded by message INMR060I. An attempt was made to receive a sequential data set into a program library.

System action: The RECEIVE command processor terminates.

User response: Resubmit the command, but with a different output data set type. A sequential data set can be received as a member of a data library, a member of a PDS, or into a sequential data set.

Module: INMRALLO

Audience: RECEIVE user

INMR156I A PDS or PDS member cannot be received into a Program Library.

Explanation: This message is preceded by message INMR060I. An attempt was made to receive a PDS or PDS member into a program library. The RECEIVE command does not support this.

A PDS or PDS member can be received into a PDS.

System action: The RECEIVE command processor terminates.

User response: Resubmit the command, but with a different output data set type.

If you are sure that the PDS members to be received contain executable load modules, you may receive them into a program library by performing the following steps:

1. Receive the PDS or PDS member into a PDS.
2. Copy the PDS into the program library, for example, with IEBCOPY.

Module: INMRALLO

Audience: RECEIVE user

INMR157I A Data Library or member cannot be received into a Program Library or vice versa.

Explanation: This message is preceded by message INMR060I. Data libraries can contain only data, program libraries can contain only program objects. Receiving data into program libraries, or program objects into data libraries, is not permitted.

System action: The RECEIVE command processor terminates.

User response: Resubmit the command, but with a different output data set type.

A data library or member of a data library can be received into a data library or PDS. A program library or member of a program library can be received only into a program library or an empty PDSE (LIBRARY).

Module: INMRALLO

Audience: RECEIVE user

INMR158I A Program Library or member can only be received into a Program Library or a library.

Explanation: This message is preceded by message INMR060I. An attempt was made to receive program objects into a data set other than a program library or an empty PDSE. This is not permitted. Program objects can be received only into program libraries or empty PDSEs.

The output data set may be specified explicitly by the terminal user, or it may have been allocated implicitly. If allocated implicitly, and SMS was not active, the data set is allocated as a PDS.

Note: An empty PDSE becomes a program library (or data library) after the first member of either type is stored in it, that is, the first member stored in an empty PDSE determines the library type. The library type remains determined to the library also when all members are deleted from it.

System action: The RECEIVE command processor terminates.

User response: None

Module: INMRALLO

Audience: RECEIVE user

INMR159I The incoming data set is a PDSE Program Library or member. This type of data set is not supported.

Explanation: An attempt was made to receive a program library or member of a program library. However, this requires DFSMS/MVS 1.1 (or later) or MVS/DFP 3.3 (or later) to be active on your system.

System action: The RECEIVE command processor terminates.

User response: Contact your system programmer to determine the level of your DFSMS/MVS or MVS/DFP system.

Module: INMRALLO

Audience: RECEIVE user

INMR200I RECEIVE command terminated, error encountered when retrieving SMS information +

Explanation: A problem has been encountered when attempting to retrieve data set information from SMS.

System action: The RECEIVE command processor terminates.

User response: Inspect the corresponding second-level message for more information.

Module: INMRALLO

Audience: RECEIVE user

INMR800I The RECEIVE command failed. The PUTGET service routine issued return code *return_code*.

Explanation: While processing a RECEIVE command in the background, the system invoked the PUTGET service routine to obtain user input. The PUTGET service routine issued the failing return code shown in the message. For an explanation of the return code, see *z/OS TSO/E Programming Services*.

INMR900I • INMR906A

System action: The RECEIVE command processor terminates.

User response: Use the PUTGET return code to determine the reason for failure and correct the error.

Module: INMRALLO, INMRCODE, INMRF, INMRM, INMRUINP

Audience: RECEIVE user

INMR900I

Explanation: The command processor has completed processing an input file and is preparing for the next. This message provides a visual separator between the two messages. Receive continues with the normal processing.

System action: None.

User response: None.

Module: INMRM

Audience: RECEIVE user

INMR901I Data set *dsname* from *user_id* on *node_name*.

Explanation: The RECEIVE command processor has selected an input file and has read the control records. This message identifies the user ID and the node name of the sender. The string *dsname* will be either the name of the data set transmitted or a string identifying a non data set transmission. Such strings are: **'** MESSAGE **'** identifying terminal text.

System action: Continue with the normal processing.

User response: None.

Module: INMRUINP

Audience: RECEIVE user

INMR902I Members:

Explanation: The RECEIVE command processor is processing an input file which is a partitioned data set. This message lists the members of the data set that are being received.

Note: This message is not issued if the entire data set was transmitted.

System action: Continues with the normal processing.

User response: None.

Module: INMRUINP

Audience: RECEIVE user

INMR906A Enter RESTORE parameters or 'DELETE' or 'END'. +

Explanation: The RECEIVE command processor has issued messages to the user indicating the name and origin of the current input file. It is now prompting the user for the next action to take.

System action: Wait for instructions from the user.

User response: You may specify 'END', in which case the RECEIVE command processor will terminate, leaving the file to be processed by a later invocation of the RECEIVE command. You may specify 'DELETE', in which case the RECEIVE command processor will delete the current file and continue with the next one. If the current file is to be processed immediately, you may enter any (or none) of the RESTORE parameter values.

Module: INMRUINP

Audience: RECEIVE user

INMR907A Enter COPY parameters or 'DELETE' OR 'END'. +

Explanation: The RECEIVE command was processing an input file that contained errors and could not be correctly restored. It is now prompting the user for the next action to take.

System action: Wait for instructions from the user.

User response: You may specify 'END', in which case the RECEIVE command processor will terminate, leaving the file to be processed by a later invocation of the RECEIVE command. You may specify 'DELETE', in which case the RECEIVE command processor will delete the current file and continue with the next one. If the current file is to be processed immediately, you may enter any (or none) of the COPY parameter values. If you enter the BLKSIZE parameter, it will be ignored.

Module: INMRUINP

Audience: RECEIVE user

INMR908A The input file attributes are: DSORG=*dd*, RECFM=*rrr*, LRECL=*ll*, BLKSIZE=*bb*. File Size = *mmm* Zbytes. +

Explanation: Zbytes = K | M to indicate whether the file size is in kbytes (such as kilobytes) or mbytes (such as megabytes).

System action: Wait for restore instructions from the user (see message INMR906I or INMR907I).

User response: Use this information to select the proper data set into which to restore the data.

Module: INMRUINP

Audience: RECEIVE user

INMR909A You may enter DSNAME, SPACE, UNIT, VOL, OLD/NEW, or RESTORE/COPY/DELETE/END.

Explanation: This is a partial list of the options that may be entered in response to prompt messages INMR906I and INMR907I. A more complete list is available in the command language reference manual.

System action: Wait for restore instructions from the user.

User response: Reply with appropriate options.

Module: INMRUINP

Audience: RECEIVE user

INMR910A Reply 'K' to keep this file on the spool. +

Explanation: The RECEIVE command processor has encountered an input file in which there are such severe errors that it has assumed the file should be deleted. For example, it encountered a null file or an I/O error on the first record of a file. The RECEIVE command processor is now requesting permission to delete the input file.

System action: Wait for a response from the user.

User response: Reply 'K' if you want to have the file kept on the JES spool for a retry of the RECEIVE operation. Any other reply (for example a null reply) will allow the RECEIVE command processor to delete the file, except in a background environment when RECEIVE will allow the input file to be retained.

Module: INMRM

Audience: RECEIVE user

INMR911A Any reply other than 'K' causes file to be deleted.

Explanation: The RECEIVE command was processing a file in which there were such severe errors that it has assumed the file should be deleted. Examples are a null file or an I/O error on the first record of a file. The RECEIVE command is requesting permission to delete the input file.

System action: Wait for deletion permission from the user.

User response: Reply 'K' if you want to have the file kept on the JES spool for a retry of the RECEIVE operation.

INMR912I • INMR917I

Any other reply (for example a null reply) will allow the file to be deleted.

Module: INMRM

Audience: RECEIVE user

INMR912I A severe error was detected and the current input file is unusable.

Explanation: The RECEIVE command was processing a file in which there were such severe errors that it has assumed the file should be deleted. Examples are a null file or an I/O error on the first record of a file. The RECEIVE command is requesting permission to delete the input file.

System action: Wait for deletion permission from the user.

User response: Reply 'K' if you want to have the file kept on the JES spool for a retry of the RECEIVE operation. Any other reply (for example a null reply) will allow the file to be deleted.

Module: INMRM

Audience: RECEIVE user

INMR913I The PREVIEW option is invalid with partitioned data sets or enciphered files. It has been ignored.

Explanation: The RECEIVE command processor encountered a partitioned data set or an enciphered data set. The PREVIEW option was specified, but the RECEIVE command processor does not support PREVIEW for these files.

System action: The PREVIEW specification is ignored and normal processing continues.

User response: None.

Module: INMRM

Audience: RECEIVE user

INMR916I Data set was enciphered. Enter Access Method Services REPRO DECIPHER options to restore the file. +

Explanation: The RECEIVE command processor encountered an input file that was enciphered by the sender.

System action: The RECEIVE command processor waits for the user to enter DECIPHER options to be passed to the Access Method Services REPRO command.

User response: You should enter DECIPHER options for the Access Method Services REPRO command. If you are not sure what options are valid, consult your system programmer or the manual *OS/VS1 and OS/VS2 MVS Access Method Services Cryptographic Option*. You may enter any valid sub-option of the DECIPHER keyword of the REPRO command.

Module: INMRCODE

Audience: RECEIVE user

INMR917I You may enter any subfield of the DECIPHER operand of the Access Method Services REPRO command. +

Explanation: The RECEIVE command encountered an input file which was enciphered by the sender. You should enter DECIPHER options for the Access Method Services REPRO command.

System action: RECEIVE waits for the user to enter DECIPHER options to be passed to the Access Method Services REPRO command.

User response: If you are not sure what options are valid, consult your local encryption expert or the manual *OS/VS1 and OS/VS2 MVS Access Method Services Cryptographic Option*. You may enter anything in response to this message which is a valid sub-option of the DECIPHER keyword of the REPRO command.

Module: INMRCODE

Audience: RECEIVE user

INMR918I Valid options include: DATAKEYFILE, DATAKEYVALUE, SYSTEMKEY, SYSTEMDATAKEY, and SYSTEMKEYNAME.

Explanation: The RECEIVE command encountered an input file which was enciphered by the sender. You should enter DECIPHER options for the Access Method Services REPRO command.

System action: RECEIVE waits for the user to enter DECIPHER options to be passed to the Access Method Services REPRO command.

User response: If you are not sure what options are valid, consult your local encryption expert or the manual *OS/VS1 and OS/VS2 MVS Access Method Services Cryptographic Option*. You may enter anything in response to this message which is a valid sub-option of the DECIPHER keyword of the REPRO command.

Module: INMRCODE

Audience: RECEIVE user

INMR921I Received file appears not to be an Interactive Data Transmission Facility file. The first record is:

Explanation: The RECEIVE command processor encountered an input file in which the header records were missing or in error. The file cannot be restored in the normal fashion. By default, the RECEIVE command processor copies the input file directly to the output file without any attempt at reformatting. The next message line sent to the terminal will be the first record of the file.

System action: Default to COPY mode instead of RESTORE mode.

User response: None.

Module: INMRUINP

Audience: RECEIVE user

INMR922I *Text_of_first_received_record.*

Explanation: The RECEIVE command processor encountered an input file in which the control header records were missing or in error. The file cannot be restored in the normal fashion. By default, the RECEIVE command processor copies the input file directly to the output file without any attempt at reformatting.

System action: Default to COPY mode instead of RESTORE mode.

User response: None.

Module: INMRUINP

Audience: RECEIVE user

INMR931I Acknowledgment from *user_id* on *node_name*.

Explanation: The RECEIVE command processor is processing an input file which is a receipt acknowledgment from another node. This message identifies the receiver of the file and the receiver's node name. The next message issued identifies the file that was received. This message line is the first record of the file.

System action: None.

User response: None.

Module: INMRO

Audience: RECEIVE user

INMR932I Data set *dsname* sent *date*.

Explanation: The RECEIVE command is processing an input file which is a receipt acknowledgment from another node. This message identifies the file received, the time of its original transmission, and the status of the RECEIVE operation. The RECEIVE status value will be either 'STORED', 'DELETED' or the message identifier of an error condition causing a RECEIVE failure.

System action: None.

INMR933A • INMX019I

User response: None.

Module: INMRO

Audience: RECEIVE user

INMR933A Trailer record missing. Enter "DELETE" or "END".

Explanation: The input file the RECEIVE command is processing contains only header records. The trailer record is missing.

System action: The RECEIVE command processor waits for you to enter either DELETE or END.

User response: To delete the current file and continue processing the next one, enter DELETE. To terminate RECEIVE command processing without deleting the file, enter END.

Module: INMRF

Audience: RECEIVE user

INMR934I A single member was specified, but an entire partitioned data set was being received.

Explanation: The RECEIVE command processor was attempting to restore an entire partitioned data set containing one or more members. However, the user specified the target data set as a single member of a partitioned data set.

System action: The RECEIVE command processor terminates abnormally.

User response: Reissue the RECEIVE command, specifying the name of a partitioned data set (without a member name) as the output data set. This action enables the RECEIVE command processor to restore the entire partitioned data set to the output data set.

Module: INMRUINP

Audience: RECEIVE user

INMX000I *nnnn* records sent to *node_name.user_id*

Explanation: A successful transmission has been made to the node and user ID given in the message. The value *nnnn* is the number of 80-character records that the data occupied. Control records are not included in this value.

System action: The TRANSMIT command processor continues with other transmissions or terminates if the transmission to all addressees is complete.

User response: None.

Module: INMXXMIT

Audience: TRANSMIT user

INMX001I Transmission occurred on *dd/mm/yy* at *hh:mm:ss*.

Explanation: A successful transmission has been made to the node and user ID given in message INMX000I. The time and date of the transmission are given in the message.

System action: The TRANSMIT command processor continues with other transmissions or terminates if the transmission to all addressees is complete.

User response: None.

Module: INMXXMIT

Audience: TRANSMIT user

INMX019I No addressees found in the distribution list chain. Nicknames for all entries in the distribution list chain point to distribution lists.

Explanation: All the entries in the distribution list chain were resolved; that is, valid nicknames were defined for them. All those nicknames, however, referred to other distribution lists that contained no :userid tags.

System action: The TRANSMIT command processor terminates.

User response: Check your NAMES data sets to ensure that the distribution list chain contains at least one user ID and node.

For example, if a user tries to transmit to X, defined in the NAMES data set as follows, no addressees will be found in the distribution list chain.

```
:nick.X :list.Y Z
:nick.Y :list.X
:nick.Z :list.Z
```

At least one nickname in the distribution list chain must be resolvable to a user ID and node. In the above example, to make Z resolve to a user ID and node, use the :user_id and :node tags:

```
:nick.Z :userid.PB219 :node.NODENAME
```

When the user transmits to X, in the above example, the message or data will be sent to user ID PB219 at node NODENAME.

Module: INMXQ

Audience: TRANSMIT user

INMX020I Nickname *name* was not found in any names data set. *name* is ignored.

Explanation: The name given in the message was not found in any NAMES data set and therefore is not used to generate the node and user for an addressee. The name is either from a TRANSMIT command or from a distribution list.

System action: The TRANSMIT command processor continues, ignoring the unresolvable name. If all addressee names are unresolvable, the TRANSMIT command terminates.

User response: Check your NAMES data sets to ensure that the required name is present.

Module: INMXQ

Audience: TRANSMIT user

INMX021I More than 10 prolog lines have been found, subsequent prolog lines are ignored

Explanation: The TRANSMIT command processor was scanning the control section of the NAMES data set and found more than 10 prolog tags.

System action: Prolog lines after the tenth are indicated as errors and then ignored. The TRANSMIT command processor continues using the first 10 lines.

User response: Remove the extra prolog lines from the NAMES data set.

Module: INMXQ

Audience: TRANSMIT user

INMX022I More than 10 epilog lines have been found, subsequent epilog lines are ignored

Explanation: The TRANSMIT command processor was scanning the control section of the NAMES data set and found more than 10 epilog tags.

System action: Epilog lines after the tenth are indicated as errors and then ignored. The TRANSMIT command processor continues using the first 10 lines.

User response: Remove the extra epilog lines from the NAMES data set.

Module: INMXQ

Audience: TRANSMIT user

INMX023I Nicknames not found in any NAMES data set searched. and

INMX024I Nickname *nickname* from distribution list *list_name* in NAMES data set *dsname* was not resolvable.

Explanation: Your message, data set, or both were not sent to one or more of the nicknames in your distribution list, because the nicknames are not defined in an appropriate NAMES data set. Nicknames must be defined either in the same prefix.NAMES.TEXT data set as the distribution list or in a NAMES data set identified on an :altctl. tag.

NAMES data sets which were searched before the current NAMES data set are not searched again to resolve the nickname or distribution list entry.

System action: The TRANSMIT command processor transmits to all the defined nicknames specified with the command and then terminates.

User response: Define the nicknames in an appropriate NAMES data set. For example, to define nicknames for the Group distribution list (:nick.Group :list.John Mary), type the following:

```
:nick.John :userid.JOHN :node.NODENAME  
:nick.MARY :userid.MST :node.NODENAME
```

Module: INMXQ

Audience: TRANSMIT user

INMX025I TRANSMIT command terminated because more than 200 nicknames were found

Explanation: The TRANSMIT command processor was resolving the addressee list and found more than 200 nicknames. Either the distribution lists are large or they form a loop where one of the lists includes itself.

System action: The TRANSMIT command processor terminates.

User response: Check for a distribution list that references itself (or references another list that references the first) or for large lists that generate more than 200 nicknames. In the first case, eliminate the circular reference. In the second case, split the list or lists into several executions of the TRANSMIT command.

Module: INMXQ

Audience: TRANSMIT user

INMX026I The last name processed was *name*

Explanation: The TRANSMIT command processor was resolving the addressee list and found more than 200 nicknames. The message shows the last nickname processed.

System action: The TRANSMIT command processor terminates.

User response: Check for a distribution list that references itself (or references another list that references the first) or for large lists that generate more than 200 nicknames. In the first case, eliminate the circular reference. In the second case, split the list or lists into several executions of the TRANSMIT command.

Module: INMXQ

Audience: TRANSMIT user

INMX027I TRANSMIT command terminated because more than 200 addressees were found

Explanation: The TRANSMIT command processor was resolving the addressee list and found more than 200 addressees. Large numbers of addressees might result either from large distribution lists or from lists that form a loop where one list includes itself.

System action: The TRANSMIT command processor terminates.

User response: Check for a distribution list that references itself (or references another list that references the first) or for large lists that generate more than 200 addressees. In the first case, eliminate the circular reference. In the second case, split the list or lists into several executions of the TRANSMIT command.

Module: INMXQ

Audience: TRANSMIT user

INMX028I The last nickname processed was *name*

Explanation: The TRANSMIT command processor was resolving the addressee list and found more than 200 addressees. The message shows the last nickname processed.

System action: The TRANSMIT command processor terminates.

User response: Check for a distribution list that references itself (or references another list that references the first) or for large lists that generate more than 200 addressees. In the first case, eliminate the circular reference. In the second case, split the list or lists into several executions of the TRANSMIT command.

Module: INMXQ

Audience: TRANSMIT user

INMX029I A :NICK tag was found for nickname *name*, but it did not contain a :USERID tag

Explanation: The TRANSMIT command processor was resolving a nickname from the addressee list and encountered what appeared to be a matching entry in the NAMES data set, but the entry did not have a USERID specification and could not be used.

System action: The TRANSMIT command processor continues, but the indicated nickname is not used for transmission. If the nickname in error was the only addressee, the TRANSMIT command processor terminates.

User response: Correct the NAMES data set entry for this nickname and reissue the TRANSMIT command.

Module: INMXQ

Audience: TRANSMIT user

INMX030I The nickname *name* is too long. It is ignored.

Explanation: The TRANSMIT command processor was processing a distribution list from the NAMES data set and encountered the name shown in the message within the list. The name is too long to be a valid nickname.

System action: The TRANSMIT command processor continues, ignoring the invalid nickname.

User response: Correct the distribution list and reissue the TRANSMIT command.

Module: INMXQ

Audience: TRANSMIT user

INMX031I Too many log requests were encountered. Logging to logname *name* will not be done.

Explanation: The TRANSMIT command processor was stacking requests for logging and an internal table overflowed. The precise number of log requests that the table can contain depends on the number of different log files, and whether the logging requests are from nickname or distribution list entries.

System action: Continue processing, bypassing the log requests for the indicated log file.

User response: None.

Module: INMXQ

Audience: TRANSMIT user

INMX032I TRANSMIT command terminated. Transmission limit of *nnn* records exceeded. +

Explanation: The TRANSMIT command processor was performing the transmission, but the number of records transmitted exceeded the installation-specified limit.

System action: The TRANSMIT command processor terminates and the transmission is purged.

User response: Divide the data to be transmitted into smaller pieces that can be transmitted separately.

Module: INMXO, INMXXMIT

Audience: TRANSMIT user

INMX033I • INMX037I

INMX033I You have exceeded the maximum transmission size set by your installation.

Explanation: The TRANSMIT command processor was performing the transmission, but the number of records transmitted exceeded the installation-specified limit.

System action: The TRANSMIT command processor terminates and the transmission is purged.

User response: Divide the data to be transmitted into smaller pieces that can be transmitted separately.

Module: INMXO, INMXXMIT

Audience: TRANSMIT user

INMX034I WARNING: *mmm* records transmitted. Your installation limit is *mmmm* records.

Explanation: The TRANSMIT command processor was performing the transmission, and reached a warning level specified by the installation. The TRANSMIT command processor continues.

System action: Continue the transmission.

User response: None.

Module: INMXO, INMXXMIT

Audience: TRANSMIT user

INMX035I ENCIPHER was specified, but has been disabled by your installation. It is ignored.

Explanation: The TRANSMIT command processor was requested to encipher the data before transmission. However your installation has disabled this capability.

System action: Continue the transmission without enciphering the data.

User response: Notify your system programmer that the TRANSMIT command INMXPARM installation CSECT does not allow the ENCIPHER option.

Module: INMXUINP

Audience: TRANSMIT user

INMX036I Keywords 'SEQUENTIAL' and 'MEMBERS' conflict. 'SEQUENTIAL' is ignored.

Explanation: The TRANSMIT command processor was checking its command parameters and found both the SEQUENTIAL keyword and the MEMBERS keyword. These keywords can not be used together for more than one member, or for transmission by ddname if the data set was not pre-allocated with a member name.

System action: Ignore the SEQUENTIAL keyword and continue normally.

User response: Do not specify both the SEQUENTIAL and MEMBERS keywords on a single invocation of the TRANSMIT command for more than one member. If transmission is by ddname, pre-allocate the data set with the member name to be used for the transmission.

Module: INMXI, INMXUINP

Audience: TRANSMIT user

INMX037I TRANSMIT command terminated. Abend *abend_code*

Explanation: The TRANSMIT command processor has terminated abnormally. *abend_code* is the abend termination code. Message INMX031I follows and gives the register 15 value (reason code) for the ABEND.

System action: The TRANSMIT command processor terminates.

User response: User response depends on the nature of the abend. Some abend codes like B37 and D37 are indications of lack of space and generally are user errors. Abend codes 0Cx are program checks and should be corrected through the IBM programming service system.

Module: INMXR

Audience: TRANSMIT user

INMX038I Register 15 value at ABEND was *nnnn*

Explanation: The TRANSMIT command processor has terminated abnormally. Message INMX037I specifies the abend termination. Message INMX038I gives the value from register 15, which for some abend codes is a reason code.

System action: The TRANSMIT command processor terminates.

User response: User response depends on the nature of the abend. Some abend codes like B37 and D37 are indications of lack of space and generally are user errors. Abend codes 0Cx are program checks and should be corrected through the IBM programming service system.

Module: INMXR

Audience: TRANSMIT user

INMX040I TRANSMIT command terminated. Failure in partitioned data set unload. USING IEBCOPY. +

Explanation: The TRANSMIT command processor was attempting to unload a partitioned data set before its transmission. Some part of the unloading process failed. Other messages follow this one to indicate more precisely what happened.

System action: The TRANSMIT command processor terminates.

User response: Correct the error as indicated by the following messages and reissue the TRANSMIT command.

Module: INMXPDS

Audience: TRANSMIT user

INMX041I IEBCOPY return code=*return_code*

Explanation: The TRANSMIT command processor was attempting to unload a partitioned data set before its transmission. The IEBCOPY utility, used to unload the data set had a non-zero return code. IEBCOPY messages might have been written to the terminal explaining the error.

System action: The TRANSMIT command processor terminates.

User response: Correct the error as indicated by accompanying IEBCOPY messages and reissue the TRANSMIT command. Failure to get IEBCOPY messages might result from the specification of the SYSOUT parameter (defaulted by the installation in the INMXPARM). If so, you can get the IEBCOPY error messages by reissuing the TRANSMIT command, specifying the SYSOUT(*) keyword.

Module: INMXPDS

Audience: TRANSMIT user

INMX042I Allocation error building *nnnn* file

Explanation: The TRANSMIT command processor was attempting to unload a partitioned data set before its transmission. Several temporary files are used in the unload process and the allocation for one of these failed. Possible files are CONTROL CARD, MESSAGE, SYSUT3 WORK, and OUTPUT. Additional messages follow detailing the type of allocation error. The most probable cause of this error is the incorrect specification of the SYSOUT or VIO parameters of the installation control CSECT, INMXPARM.

System action: The TRANSMIT command processor terminates.

User response: Notify your installation management.

Module: INMXPDS

Audience: TRANSMIT user

INMX043I Null partitioned data sets cannot be transmitted

Explanation: The TRANSMIT command processor detected that the partitioned data set indicated in the TRANSMIT command did not contain any members. The TRANSMIT command does not allow transmission of empty partitioned data sets.

System action: The TRANSMIT command processor terminates.

User response: Ensure that the partitioned data set contains at least one member.

Module: INMXPDS

Audience: TRANSMIT user

INMX050I TRANSMIT command terminated. Failure during encipher processing. +

Explanation: The TRANSMIT command processor was attempting to encipher a data set before its transmission. Some part of the encipher process failed. Additional messages identify the specific failure.

System action: The TRANSMIT command processor terminates.

User response: Correct the error as identified by subsequent messages and reissue the TRANSMIT command.

Module: INMXCODE, INMXM

Audience: TRANSMIT user

INMX051I IDCAMS return code = *return_code*

Explanation: The TRANSMIT command processor was attempting to encipher a data set before its transmission. The IDCAMS utility, invoked to encipher the data set had a non-zero return code. IDCAMS messages might have been written to the terminal explaining the error.

System action: The TRANSMIT command processor terminates.

User response: Correct the error as indicated by accompanying IDCAMS messages and reissue the TRANSMIT command. Failure to get IDCAMS messages might result from the specification of the SYSOUT parameter (defaulted by the installation in the INMXPARM module). If so, you can get the IDCAMS error messages by reissuing the TRANSMIT command, specifying the SYSOUT(*) keyword.

Module: INMXCODE

Audience: TRANSMIT user

INMX052I Allocation error building *nnnn* file

Explanation: The TRANSMIT command processor was attempting to encipher a data set before its transmission. Several temporary files are used in the encipher process and the allocation for one of these files failed. Possible files are CONTROL CARD, MESSAGE, and OUTPUT. Additional messages follow detailing the type of allocation error. The most probable cause of this error is the incorrect specification of the SYSOUT or VIO parameters of the installation control CSECT, INMXPARM.

System action: The TRANSMIT command processor terminates.

User response: Notify your installation management.

Module: INMXCODE, INMXI, INMXM

Audience: TRANSMIT user

INMX057I RDJFCB failed for DDname *ddname*

Explanation: The TRANSMIT command was issued with the DDNAME or FILE keyword and *ddname*. A RDJFCB macro issued for that *ddname* failed. For more information about this macro, see *z/OS DFSMSdfp Advanced Services*. The TRANSMIT command terminates.

User response: Notify your system programmer.

Module: INMXI

Audience: TRANSMIT user

INMX058I DEVTYPE failed for DDname *ddname*

Explanation: The TRANSMIT command was issued with the DDNAME or FILE keyword and *ddname*. A DEVTYPE macro issued for that *ddname* failed. For more information about this macro, see *z/OS DFSMSdfp Advanced Services*.

System action: The TRANSMIT command processor terminates.

User response: Notify your system programmer.

Module: INMXI

Audience: TRANSMIT user

INMX059I DDname *ddname* was not allocated.

Explanation: The TRANSMIT command was issued with the DDNAME or FILE keyword and the *ddname* specified in the message. A file by the *ddname* specified was not allocated.

System action: The TRANSMIT command processor terminates.

User response: Check that the *ddname* is properly allocated and reissue the TRANSMIT command.

Module: INMXI

Audience: TRANSMIT user

INMX060I TRANSMIT command terminated. Input data set unusable. +

Explanation: The TRANSMIT command processor was processing the file it was going to transmit and encountered some type of error in the file. Subsequent messages further identify the error.

System action: The TRANSMIT command processor terminates.

User response: Correct the error as identified by subsequent messages and reissue the TRANSMIT command.

Module: INMXI, INMXXMIT

Audience: TRANSMIT user

INMX061I Allocation failed for data set *dsname* +

Explanation: The TRANSMIT command processor was attempting to allocate the specified data set, but the allocation failed. A subsequent message identifies the cause of the allocation failure.

System action: The TRANSMIT command processor terminates.

User response: Correct the error as identified by subsequent messages and reissue the TRANSMIT command.

Module: INMXI

Audience: TRANSMIT user

INMX062I OPEN failed for data set *dsname*

Explanation: The TRANSMIT command was issued with the DATASET or DSNAME keyword. The TRANSMIT command issued an OPEN for the specified data set, but the OPEN failed.

System action: The TRANSMIT command processor terminates.

User response: Notify your system programmer.

Module: INMXXMIT

Audience: TRANSMIT user

INMX063I • INMX067I

INMX063I OPEN failed for DDname *ddname*

Explanation: The TRANSMIT command was issued with the DDNAME or FILE keyword and the ddname specified in the message. An OPEN for that ddname failed. The most probable cause of this error is that the specified ddname was not allocated.

System action: The TRANSMIT command processor terminates.

User response: Check that the ddname is properly allocated and reissue the TRANSMIT command.

Module: INMXI

Audience: TRANSMIT user

INMX064I Data set *dsname* not on volume indicated by the catalog

Explanation: The TRANSMIT command was issued with the DATASET or DSNAME keyword. The indicated data set was cataloged, but not found on the volume indicated by the catalog.

System action: The TRANSMIT command terminates.

User response: Check that the requested data set exists and that it is cataloged correctly, then reissue the TRANSMIT command.

Module: INMXI

Audience: TRANSMIT user

INMX065I Required volume *volser* not mounted

Explanation: The TRANSMIT command was issued with the DATASET or DSNAME keyword. The indicated data set was cataloged, but the volume on which it resides was not mounted.

System action: The TRANSMIT command terminates.

User response: Check that the requested data set exists and that it is cataloged correctly, then reissue the TRANSMIT command.

Module: INMXI

Audience: TRANSMIT user

INMX066I I/O error in VTOC of volume *volser*

Explanation: The TRANSMIT command was issued with the DATASET or DSNAME keyword. The indicated data set was found and an OBTAIN was issued to get information about the data set. The OBTAIN SVC set a return code indicating an I/O error in the VTOC of the volume.

System action: The TRANSMIT command terminates.

User response: Notify your local data management support person that the indicated volume has problems.

Module: INMXI

Audience: TRANSMIT user

INMX067I OBTAIN return code *return_code* for data set *dsname*

Explanation: The TRANSMIT command was issued with the DATASET or DSNAME keyword. The indicated data set was found and an OBTAIN was issued to get information about the data set. The OBTAIN SVC set an error return code.

System action: The TRANSMIT command terminates and a system dump is taken.

User response: Check the specific OBTAIN return code in *z/OS MVS Programming: Authorized Assembler Services Guide* to determine the cause of the problem.

Module: INMXI

Audience: TRANSMIT user

INMX068I Data sets with keys are not supported

Explanation: The TRANSMIT command was issued with the DATASET or DSNAME keyword. The indicated data set was found to have keys, but keys are not supported by the TRANSMIT command.

System action: The TRANSMIT command terminates.

User response: You can not TRANSMIT data sets with keys. If you have an unload utility that will create a non-keyed data set from the keyed file, you can transmit the non-keyed version and rebuild the original data set manually at the destination.

Module: INMXI

Audience: TRANSMIT user

INMX069I Data set organization of data set *dsname* is not supported

Explanation: The TRANSMIT command was issued with the DATASET or DSNAME keyword. The indicated data set had a data set organization not supported by TRANSMIT. Supported organizations are physical sequential and partitioned.

System action: The TRANSMIT command terminates.

User response: You can not TRANSMIT data sets of this type. If you have an unload utility that will create a physical sequential data set from the original file, you can transmit the sequential version and rebuild the original manually at the destination.

Module: INMXI

Audience: TRANSMIT user

INMX070I Permanent I/O error on input data set +

Explanation: The TRANSMIT command processor was reading the input file specified on the TRANSMIT command when an I/O error was encountered.

System action: The TRANSMIT command processor terminates.

User response: None.

Module: INMXI, INMXLOG, INMXO, INMXXMIT

Audience: TRANSMIT user

INMX071I *Text_of_I/O_error_in_message_INMX070I*

Explanation: The TRANSMIT command processor was reading the input file specified on the TRANSMIT command when an I/O error was encountered.

System action: The TRANSMIT command processor terminates.

User response: None.

Module: INMXI, INMXLOG, INMXO, INMXXMIT

Audience: TRANSMIT user

INMX072I NULL SEQUENTIAL DATA SETS CANNOT BE TRANSMITTED

Explanation: The TRANSMIT command does not allow transmission of empty sequential data sets. For concatenations, the first data set can not be empty.

System action: The TRANSMIT command processor terminates.

User response: Ensure that the sequential data set contains data.

Module: INMXI

Audience: TRANSMIT user

INMX073I • INMX077I

INMX073I Log process failed for log data set *dsname*

Explanation: The TRANSMIT command processor was attempting to make a log entry in the indicated log data set. The attempt failed for reasons identified in subsequent messages.

System action: The TRANSMIT command processor continues with any log entries for other log data sets.

User response: Correct the problems as indicated in subsequent messages.

Module: INMXLOG

Audience: TRANSMIT user

INMX074I OPEN for the data set failed

Explanation: The TRANSMIT command processor was attempting to make a log entry in the log data set indicated by message INMX073I. The data set was allocated correctly, but when an OPEN was issued, the OPEN failed.

System action: The TRANSMIT command processor continues with log requests for other data sets.

User response: Verify the usability of the indicated log data set.

Module: INMXLOG

Audience: TRANSMIT user

INMX075I Message file *ddname* contains attributes that are not valid. +

Explanation: The TRANSMIT command processor checked the attributes of the file specified on the MSGDDNAME or MSGFILE parameter and found that they were not valid. A file specified on the MSGDDNAME or MSGFILE parameter must have a data set allocated that has a record format of fixed-blocked, a logical record length 80, and must be sequential (either a sequential data set or a member of a partitioned data set).

System action: The TRANSMIT command processor terminates.

User response: Check the attributes of the data set allocated to the file. If they are not valid, reallocate the data set with the correct attributes and reissue the TRANSMIT command.

Module: TRANSMIT

Audience: TRANSMIT user

INMX076I Message file must have attributes LRECL=80 with RECFM=FB or RECFM=F, and must be sequential or a member of a partitioned data set.

Explanation: The TRANSMIT command processor checked the attributes of the file specified on the MSGDDNAME or MSGFILE parameter and found that they were not valid. A file specified on the MSGDDNAME or MSGFILE parameter must have a data set allocated that has a record format of fixed-blocked, logical record length 80, and must be sequential (either a sequential data set or a member of a partitioned data set).

System action: The TRANSMIT command processor terminates.

User response: Check the attributes of the data set allocated to the file. If they are not valid, reallocate the data set with the correct attributes and reissue the TRANSMIT command.

Module: INMXI

Audience: TRANSMIT user

INMX077I I/O error occurred while reading the message data set.

Explanation: The TRANSMIT command processor was reading the input file specified on the MSGDDNAME or MSGFILE parameter of the TRANSMIT command when an I/O error was encountered.

System action: The TRANSMIT command processor terminates.

User response: None.

Module: INMXI, INMXLOG, INMXO, INMXXMIT

INMX078I Open failed for the message data set.

Explanation: The TRANSMIT command processor could not open the file associated with the MSGDDNAME, MSGFILE, MSGDATASET or MSGDSNAME parameter.

System action: The TRANSMIT command processor terminates.

User response: None.

Module: INMXI, INMXLOG, INMXO, INMXXMIT

Audience: TRANSMIT user

INMX079I Message data set *dsname* contains attributes that are not valid. +

Explanation: The TRANSMIT command processor checked the attributes of the data set specified on the MSGDATASET or MSGDSNAME parameter and found that they were not valid. The data set specified on the MSGDATASET or MSGDSNAME parameter must have a record format of fixed-blocked, a logical record length 80, and must be sequential (either a sequential data set or a member of a partitioned data set).

System action: The TRANSMIT command processor terminates.

User response: Check the attributes of the data set. If they are not valid, reallocate the data set with the correct attributes and reissue the TRANSMIT command.

Module: TRANSMIT

Audience: TRANSMIT user

INMX080I Message data set must have attributes LRECL=80 with RECFM=FB or RECFM=F, and must be sequential or a member of a partitioned data set.

Explanation: The TRANSMIT command processor checked the attributes of the data set specified on the MSGDATASET or MSGDSNAME parameter and found that they were not valid. The data set specified on the MSGDATASET or MSGDSNAME parameter must have a record format of fixed-blocked, logical record length 80, and must be sequential (either a sequential data set or a member of a partitioned data set).

System action: The TRANSMIT command processor terminates.

User response: Check the attributes of the data set. If they are not valid, reallocate the data set with the correct attributes and reissue the TRANSMIT command.

Module: INMXI

Audience: TRANSMIT user

INMX081I TRANSMIT command terminated because it was not invoked authorized

Explanation: The TRANSMIT command was invoked in a non-authorized environment (for example, under SPF option 6).

System action: The TRANSMIT command terminates.

User response: Do not issue the TRANSMIT command in a non-authorized environment.

Module: INMXPDS

Audience: TRANSMIT user

INMX083I TRANSMIT command terminated. The OPEN failed on file passed from IEBCOPY or Access Method Service REPRO.

Explanation: The TRANSMIT command was invoked to transmit a partitioned data set or the TRANSMIT command had enciphered the transmitted data set. The data sets written by the partitioned data set unload utility (IEBCOPY) or the encipher utility (Access Method Services REPRO) could not be reopened as input to the transmission process.

System action: The TRANSMIT command terminates and a system dump is taken.

INMX084I • INMX092I

User response: Notify your system programmer.

Module: INMXXMIT

Audience: TRANSMIT user

INMX084I The data set specified in the LOGDATASET or the LOGDSNAME parameter must be sequential.

Explanation: The TRANSMIT command attempted to log the data or message to the log data set specified in the LOGDATASET or LOGDSNAME parameter. The log data set was not sequential.

System action: The TRANSMIT command terminates.

User response: Reissue the TRANSMIT command and specify a sequential data set in the LOGDATASET or LOGDSNAME parameter.

Module: TRANSMIT

Audience: TRANSMIT user

INMX085I Logging to data set *dsname* did not occur because the data set is a partitioned data set.

Explanation: The specified log data set name in *dsname* is not a sequential data set.

System action: Logging to the specified data set did not occur.

User response: Allocate the specified log data set as a sequential data set and reissue the TRANSMIT command.

Module: TRANSMIT

Audience: TRANSMIT user

INMX090A Enter *message* for receiver. Enter *string* to stop.

Explanation: The TRANSMIT command was invoked with the LINE keyword and is prompting the you for data or message text to be sent.

System action: The TRANSMIT command waits for you to enter one or more lines of input.

User response: Enter one or more lines of text, depressing the Enter key after each line. After all text lines have been entered, enter the indicated string to allow the TRANSMIT command to continue.

Module: INMXTIN

Audience: TRANSMIT user

INMX091I End of input buffer has been reached. A partial transmission has been sent.

Explanation: There is no more room in the input buffer for messages or data while in line mode. Up to 220 lines may be entered, this includes the prologue if one exists. The last line you entered was not transmitted, however all previous lines were transmitted successfully.

System action: The TRANSMIT command continues processing with as much data as will fit into the buffer.

User response: To transmit more messages or data, re-issue the TRANSMIT command.

Module: INMXTIN

Audience: TRANSMIT user

INMX092I TRANSMIT command terminated. Failure in command syntax checking. +

Explanation: The TRANSMIT command invoked the IKJPARS TSO/E service routine to perform syntax checking on the command parameters. The IKJPARS routine detected errors in command syntax. Subsequent messages identify the specific errors.

System action: The TRANSMIT command terminates.

User response: Correct the errors as indicated by subsequent messages.

Module: INMXUINP

Audience: TRANSMIT user

INMX094I The command was incomplete, but prompting is not allowed

Explanation: The TRANSMIT command invoked the IKJPARS TSO/E service routine to perform syntax checking on the command parameters. The parameters were incomplete or in error, but IKJPARS was prevented from prompting either by a PROFILE NOPROMPT specification, by the CONTROL NOPROMPT (perhaps defaulted) specification within a CLIST, or by PROMPT(ON) within a REXX exec.

System action: The TRANSMIT command terminates.

User response: If the TRANSMIT was within a CLIST or REXX exec, specify CONTROL PROMPT in the CLIST or PROMPT(ON) in the exec to allow prompting. Or, issue the PROFILE PROMPT command to allow prompting outside the CLIST.

Module: INMXUINP

Audience: TRANSMIT user

INMX099I RDJFCB FAILED FOR DATASET *dsname*

Explanation: The TRANSMIT command was issued with the DATASET or DA operand and the DSNAME operand. A RDJFCB macro issued for the specified data set failed. For more information about this macro, see *z/OS DFSMSdfp Advanced Services*.

System action: The TRANSMIT command terminates.

User response: Contact your system programmer.

Module: INMXI

Audience: TRANSMIT user

INMX100A Enter ENCIPHER options for Access Method Service REPRO command +

Explanation: The TRANSMIT command was invoked with the ENCIPHER option. You are being prompted to specify the encryption options you want passed to the Access Method Services REPRO command as subfields of the ENCIPHER keyword.

System action: The TRANSMIT command waits for a response from the user.

User response: Consult the manual *OS/VS1 and OS/VS2 MVS Access Method Services Cryptographic Option* for the options that control enciphering data.

Module: INMXCODE

Audience: TRANSMIT user

INMX101I Valid options include: EXTERNALKEYNAME, INTERNALKEYNAME, PRIVATEKEY, CIPHERUNIT, DATAKEYFILE, DATAKEYVALUE, SHIPKEYNAMES, STOREDATAKEY, STOREKEYNAME, USERDATA

Explanation: The TRANSMIT command was invoked with the ENCIPHER option. You are being prompted to specify the encryption options you want passed to the Access Method Services REPRO command as subfields of the ENCIPHER keyword.

System action: The TRANSMIT command waits for your response.

User response: Consult the manual *OS/VS1 and OS/VS2 MVS Access Method Services Cryptographic Option* for the options that control enciphering data.

Module: INMXCODE

Audience: TRANSMIT user

INMX105I • INMX150I

INMX105I TRANSMIT command terminated. Unable to prompt for control parameters. +

Explanation: The TRANSMIT command processor was attempting to prompt for ENCIPHER parameters but prompting failed. The cause of the prompt failure is identified in a subsequent message.

System action: The TRANSMIT command processor terminates.

User response: The correct response to this message is determined by the message that follows.

Module: INMXCODE

Audience: TRANSMIT user

INMX106I Prompting was inhibited

Explanation: The TRANSMIT command processor tried to prompt for ENCIPHER parameters but prompting was not allowed. Either PROFILE NOPROMPT is specified, the TRANSMIT occurred in a CLIST or REXX exec in which CONTROL NOPROMPT in the CLIST was either specified or defaulted or the PROMPT option was off in the exec.

System action: The TRANSMIT command processor terminates.

User response: Specify CONTROL PROMPT in a CLIST, PROMPT(ON) in a REXX exec, or PROFILE PROMPT in TSO/E mode.

Module: INMXCODE

Audience: TRANSMIT user

INMX107I Return code *return_code* from IKJEFF02

Explanation: The TRANSMIT command processor tried to prompt for ENCIPHER parameters but prompting failed. The return code from IKJEFF02 is indicated in this message. A TSO/E message follows message INMX107I and describes the IKJEFF02 return code.

System action: The TRANSMIT command processor terminates.

User response: See the description of the following TSO/E message.

Module: INMXCODE

Audience: TRANSMIT user

INMX149I Exit INMXZ21R returned a non-zero return code.

Explanation: The TRANSMIT command invoked installation exit INMXZ21R, which returned a non-zero return code.

System action: The TRANSMIT command processor does not perform the logging function.

User response: Contact your system programmer for assistance

Module: INMXZ

Audience: TRANSMIT user

INMX150I TRANSMIT command terminated by installation exit *exit_name*.

Explanation: The TRANSMIT command invoked the named installation exit routine, which terminated the TRANSMIT command

System action: The TRANSMIT command terminates.

User response: Contact your system programmer.

Module: INMXZ

INMX151I *installation_message_text*

Explanation: The TRANSMIT command invoked an installation exit that returned this text to be send as a message to the user.

System action: None.

User response: Contact your system programmer.

Module: INMXZ, INMXZ

Audience: TRANSMIT user

INMX152I **TRANSMIT failed. Your node ID not recognized.**

Explanation: The TRANSMIT command failed, because the CSECT INMXPARM does not contain your node ID.

Your installation might not have replaced the IBM-supplied default CSECT, the node ID might be misspelled or omitted, or INMXPARM might not be installed correctly.

System action: The TRANSMIT command processor terminates.

User response: Check the node ID. If the node is correct and the problem persists, notify your system programmer.

Module: INMXM

Audience: TRANSMIT user

INMX153I **Addressee list has been invalidated by installation exit *exit_name*.**

Explanation: The TRANSMIT command invoked an installation exit that invalidated all of the intended addressees.

System action: The TRANSMIT command terminates.

User response: Contact your system programmer.

Module: INMXZ

Audience: TRANSMIT user

INMX201I **Transmission for *node.userid* unsuccessful**

Explanation: The TRANSMIT command processor was performing the transmission to the indicated user ID when an error occurred. Subsequent messages identify the error.

System action: Depending on the type of error, the TRANSMIT command might attempt transmissions to other addressees or it might terminate at this point.

User response: Correct the error as indicated in subsequent messages and reissue the TRANSMIT command.

Module: INMXASYS

Audience: TRANSMIT user

INMX202I **Node name *node_name* not defined to JES**

Explanation: The TRANSMIT command processor was performing the transmission to the addressee indicated in message INMX201I. The transmission was unsuccessful because the requested node name was not known to JES.

System action: No transmission is made to this addressee. Transmissions to other addressees will continue.

User response: Verify that the node name is correct. If it is correct, have your system programmer define it in the JES initialization statements.

Module: INMXASYS

Audience: TRANSMIT user

INMX203I JES output file allocation error

Explanation: The TRANSMIT command processor was performing the transmission to the addressee indicated in message INMX201I. The TRANSMIT command processor attempted to allocate a SYSOUT file specifying that node and user ID, but the allocation failed. A subsequent message identifies the allocation failure.

System action: The TRANSMIT command terminates.

User response: Notify your installation management.

Module: INMXASYS

Audience: TRANSMIT user

INMX204I JES output file OPEN failure

Explanation: The TRANSMIT command processor was performing the transmission to the addressee indicated in message INMX201I. The TRANSMIT command processor attempted to OPEN a SYSOUT file specifying that node and user ID, but the OPEN failed.

System action: The TRANSMIT command terminates and a system dump is taken.

User response: Notify your installation management.

Module: INMXASYS

Audience: TRANSMIT user

INMX206I TRANSMIT command terminated. Output DDname OPEN failed.

Explanation: The TRANSMIT command was issued with the OUTDDNAME or OUTFILE keyword. An OPEN for the specified ddname failed.

System action: The TRANSMIT command terminates.

User response: Verify that the ddname was correct and that it was allocated correctly, then reissue the TRANSMIT command.

Module: INMXASYS

Audience: TRANSMIT user

INMX208I TRANSMIT command terminated. Output data set allocation failed. DSN=*dsname*.

Explanation: The TRANSMIT command was issued with the OUTDSNAME or OUTDDNAME keyword. An allocation for the specified data set failed. Subsequent messages identify the type of allocation failure.

System action: The TRANSMIT command terminates.

User response: Verify that the data set name was correct and that it is usable, then reissue the TRANSMIT command.

Module: INMXASYS

Audience: TRANSMIT user

INMX209I TRANSMIT command terminated. Output data set *dsname* is not a sequential data set.

Explanation: The TRANSMIT command was issued with the OUTDSNAME or OUTDDNAME keyword. The specified data set was not a physical sequential data set and could not be used.

System action: The TRANSMIT command terminates.

User response: Verify that the data set name was correct and that it is a physical sequential data set, then reissue the TRANSMIT command.

Module: INMXASYS

Audience: TRANSMIT user

INMX210I TRANSMIT command terminated. OPEN failed for output data set *dsname*

Explanation: The TRANSMIT command was issued with the OUTDSNAME or OUTDDNAME keyword. An OPEN failed for the specified data set.

System action: The TRANSMIT command terminates.

User response: Verify that the data set name was correct and that it is usable, then reissue the TRANSMIT command.

Module: INMXASYS

Audience: TRANSMIT user

INMX211I System not at required level to support *user_id*.

Explanation: The TRANSMIT command processor was unable to transmit to the user identified in the message.

System action: The TRANSMIT command processor makes no further attempt to process the transmission. It continues with the next transmission.

User response: None.

Module: INMXASYS

Audience: TRANSMIT user

INMX213I More than 100 names found in a distribution list. Nicknames after "nickname" ignored.

Explanation: The TRANSMIT command processor was resolving a distribution list and found over 100 names in the list. The message shows the last name processed. One execution of the TRANSMIT command can process up to 200 addressees. You can nest a distribution list within another distribution list, but the total of addressees in the two lists cannot exceed 200.

System action: The TRANSMIT command continues for the first 100 names in the distribution list.

User response: Split the large distribution list into several executions of the TRANSMIT command if over 200 nicknames total. Split the large list into smaller distribution lists if less than 200 nicknames total.

Module: INMXQ

Audience: TRANSMIT user

INMX214I Invalid message length provided by installation exit for message INMX151I.

Explanation: An invalid message length value of less than 0 or greater than 243 was provided by an installation exit for the message text to be issued with message ID INMX151I.

System action: Message INMX151I is not issued, but the TRANSMIT command processor continues normally.

User response: Notify your system programmer.

Module: INMXZ

Audience: TRANSMIT user

INMX215I Program objects cannot be transmitted as a sequential file.

Explanation: Program objects are executable load modules, which can be transmitted only as program libraries or members of program libraries.

System action: The transmission is terminated.

User response: Resubmit the TRANSMIT command without the SEQUENTIAL keyword operand.

Module: INMXI

Audience: TRANSMIT user

INMX216I • INMX800I

INMX216I TRANSMIT command terminated. Error encountered when retrieving SMS information +

Explanation: A problem was encountered when attempting to retrieve data set information from SMS.

System action: The function is terminated.

User response: Inspect the corresponding second-level message for more information.

Module: INMXI

Audience: TRANSMIT user

INMX217I The specified data set is a PDSE. This type of data set is not supported.

Explanation: An attempt was made to transmit a PDSE. However, this requires DFSMS 1.1 (or later) or MVS/DFP 3.2 (or later) to be active on your system.

System action: The transmission is terminated.

User response: Contact your system programmer to determine the level of DFSMS/MVS or MVS/DFP installed and active on your system.

Module: INMXI

Audience: TRANSMIT user

INMX218I The specified data set is a non-SMS-managed PDSE which is not supported at the current level of DFSMSdfp.

Explanation: This message is preceded by message INMX216I. The PDSE being processed by the TRANSMIT command is not SMS-managed. The appropriate DFSMSdfp PTFs to support non-SMS-managed PDSE data sets are not installed.

System action: The TRANSMIT command processor terminates.

User response: Contact your system programmer and request that the appropriate PTFs be installed.

Module: INMXI

Audience: TRANSMIT user

INMX220I TRANSMIT command terminated. Data set or file being transmitted exceeds maximum size allowed.

Explanation: The size of the data set or file being transmitted exceeds the maximum size that TRANSMIT/RECEIVE can handle. The architected maximum size is X'FFFFFFFF' MB (megabytes), or approximately 4,096 TB (terabytes).

System action: The TRANSMIT command processor terminates.

User response: If possible breakup the data into smaller sized data sets. Then TRANSMIT each separately.

Module: INMXO

Audience: TRANSMIT User

INMX800I The TRANSMIT command failed. The PUTGET service routine issued return code *return_code*

Explanation: While processing the TRANSMIT command, the system invoked the PUTGET service routine to obtain user input. The PUTGET service routine issued the failing return code shown in the message. For an explanation of the return code, see *z/OS TSO/E Programming Services*.

System action: The TRANSMIT command processor terminates.

User response: Use the PUTGET return code to determine the reason for failure and correct the error, or contact your system programmer.

Module: INMXTIN

Audience: TRANSMIT user

Chapter 8. TSO/E terminal messages (IRX...)

Component name	IRX
Program producing message	REXX processing
Audience and where produced	For REXX user: at the terminal. For REXX system programmer: SYSPRINT listing.
Message format	<i>IRXxxyyyn</i> <i>xx</i> System module prefix (in decimal). <i>yy</i> Message serial number identifying the program that issued the message. <i>n</i> Type code: E Error; processing may terminate. I Information; some action is required.
Comments	The words printed in italics in the message text indicates that the system supplies specific information which varies depending on the circumstances. That information is available only when the system displays the message at the terminal. Reason codes displayed in REXX messages are represented in decimal.

IRX0003I Error running *exec_name*, line *nn*: Program is unreadable

Explanation: The exec could not be read. The most likely reason for this error is if you called IRXEXEC and passed a pre-loaded exec that was in error. The language processor could not read the format of the exec.

System action: Exec processing terminates.

User response: Check the format of the exec you are passing or contact your system programmer for assistance.

Module: IRXEEXEC

Audience: REXX user

IRX0004I Error running *exec_name*, line *nn*: Program interrupted

Explanation: The system interrupted the exec. Often this is due to issuing the HI (halt interpretation) or HE (halt execution) immediate command or EXECUTIL HI. In any of these cases, the interruption is not due to an error.

The message can also be issued if another error occurred and exec processing was terminated. In this case, the message explaining the error is issued, followed by this message stating that the program was interrupted.

System action: Exec processing terminates.

User response: If you issued an HI or HE immediate command, or EXECUTIL HI, continue as planned. Otherwise, if an error caused exec processing to terminate, check the other error message and correct the problem.

Module: IRXEEXEC

Audience: REXX user

IRX0005I Machine storage exhausted

Explanation: While attempting to process an exec, the language processor was unable to get the storage needed for its work areas and variables. This may have occurred because a program that called IRXEXEC or an exec has already used up most of the available storage itself, or because a program or exec did not terminate properly, but instead, went into a loop.

System action: Exec processing terminates.

User response: If a program invoked IRXEXEC, check how the program obtains and frees storage. Also, check whether the program or exec is looping. Contact your system programmer for assistance.

Module: IRXEEXEC

Audience: REXX user

IRX0006I Error running *exec_name*, line *nn*: Unmatched *"/ or quote**

Explanation: The language processor reached the end of the file (or the end of data in an INTERPRET statement) without finding the ending **/* for a comment or the ending quote for a literal string.

System action: Exec processing terminates.

User response: Edit the exec and add the closing **/* or quote. You can also insert a TRACE SCAN statement at the top of your program and rerun it. The resulting output should show where the error exists.

Module: IRXEEXEC

Audience: REXX user

IRX0007I Error running *exec_name*, line *nn*: WHEN or OTHERWISE expected

Explanation: The language processor expects a series of WHENs and an OTHERWISE within a SELECT statement. This message is issued when any other instruction is found or if all WHEN expressions are found to be false and an OTHERWISE is not present. The error is often caused by forgetting the DO and END instructions around the list of instructions following a WHEN. For example:

WRONG	RIGHT
Select	Select
When a=b then	When a=b then DO
Say 'A equals B'	Say 'A equals B'
exit	exit
Otherwise nop	end
end	Otherwise nop
	end

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0008I Error running *exec_name*, line *nn*: Unexpected THEN or ELSE

Explanation: The language processor found a THEN or an ELSE that does not match a corresponding IF clause. This situation is often caused by forgetting to put an END or DO-END in the THEN part of a complex IF-THEN-ELSE construction. For example:

WRONG	RIGHT
If a=b then do;	If a=b then do;
Say EQUALS	Say EQUALS
exit	exit
else	end
Say NOT EQUALS	else
	Say NOT EQUALS

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0009I Error running *exec_name*, line *nn*: Unexpected WHEN or OTHERWISE

Explanation: The language processor found a WHEN or OTHERWISE instruction outside of a SELECT construction. You may have accidentally enclosed the instruction in a DO-END construction by leaving off an END instruction, or you may have tried to branch to it with a SIGNAL statement, which cannot work because the SELECT is then terminated.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0010I Error running *exec_name*, line *nn*: Unexpected or unmatched END

Explanation: The language processor found more END statements in your exec than DO or SELECT statements, or the ENDS were placed so that they did not match the DOs or SELECTs. This message can occur if you try to signal into the middle of a loop. In this case, the END will be unexpected because the previous DO will not have been executed. Remember also, that SIGNAL terminates any current loops, so it cannot be used to jump from one place inside a loop to another.

This message can also occur if you place an END immediately after a THEN or ELSE construction.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec. It may be helpful to use TRACE SCAN to show the structure of the exec and make it more obvious where the error is. Putting the name of the control variable on END statements that close repetitive loops can also help you locate this kind of error.

Module: IRXEEXEC

Audience: REXX user

IRX0011I Error running *exec_name*, line *nn*: Control stack full

Explanation: This message is issued if you exceed the limit of 250 levels of nesting of control structures (DO-END, IF-THEN-ELSE, and so on).

This message could be caused by a looping INTERPRET instruction, such as:

```
line='INTERPRET line'
INTERPRET line
```

These lines would loop until they exceeded the nesting level limit and this message would be issued. Similarly, a recursive subroutine that does not terminate correctly could loop until it causes this message.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0012I Error running *exec_name*, line *nn*: Clause too long

Explanation: Your program has exceeded the implementation restriction that limits the length of the internal or external representation of a clause.

If the cause of this message is not obvious to you, it may be due to a missing quote that has caused a number of lines to be included in one long string. In this case, the error probably occurred at the start of the data included in the clause traceback (flagged by +++ on the terminal).

The internal representation of a clause does not include comments or multiple blanks that are outside of strings. Note also that any symbol (name) gains two characters in length in the internal representation.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0013I Error running *exec_name*, line *nn*: Invalid character in program

Explanation: The language processor found an invalid character outside of a literal (quoted) string. Valid characters are:

Alphanumerics

A-Z a-z 0-9

Name Characters

@ # \$ % ? . ! _

Special characters

& * () - + = \ | ~ ' " ; : < , > / %

If delimited by X'0E' (shift-out) and X'0F' (shift-in), and if ETMODE is on, X'41' through X'FE' (the DBCS characters) are also valid characters.

Some causes of this error are:

- Using accented and other language-specific characters in symbols.
- Using DBCS characters without setting OPTIONS ETMODE on.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0014I Error running *exec_name*, line *nn*: Incomplete DO/SELECT/IF

Explanation: The language processor reached the end of the file (or end of data for an INTERPRET instruction) and found that there is a DO or SELECT without a matching END, or an IF that is not followed by a THEN clause.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec. You can use TRACE SCAN to show the structure of the program, thereby making it easier to find where the missing END or THEN should be. Putting the name of the control variable on ENDS that close repetitive loops can also help you locate this kind of error.

Module: IRXEEXEC

Audience: REXX user

IRX0015I Error running *exec_name*, line *nn*: Invalid hexadecimal or binary string

Explanation: For the language processor, hexadecimal strings cannot have leading or trailing blanks and can have imbedded blanks at byte boundaries only. Similarly, binary strings can have blanks added at the boundaries of groups of four binary digits, and only the digits 0 and 1 are allowed. The following are all valid hexadecimal strings:

```
'13'X
'A3C2 1c34'X
'1de8'X
```

The following are all valid binary strings:

```
'00110001'B
'101 1101'B
'1'B
```

You may have incorrectly typed one of the digits, for example, typing a letter o instead of the number 0 or the letter l for number 1. This message can also occur if you follow a string by the 1-character symbol X or B (the name of the variable *X* or *B* respectively), when the string is not intended to be taken as a hexadecimal or binary representation. In this case, use the explicit concatenation operator (||) to concatenate the string to the value of the symbol.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0016I Error running *exec_name*, line *nn*: Label not found

Explanation: The language processor could not find the label specified by a SIGNAL instruction or a label matching an enabled condition when the corresponding (trapped) event occurred. You may have incorrectly typed the label or forgotten to include it.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0017I Error running *exec_name*, line *nn*: Unexpected PROCEDURE

Explanation: The language processor encountered a PROCEDURE instruction in an invalid position. This could occur because:

- No internal routines are active
- A PROCEDURE instruction has already been encountered in the internal routine, or
- The PROCEDURE instruction was not the first instruction executed after the CALL or function invocation.

This error can be caused by “dropping through” to an internal routine, rather than invoking it with a CALL or a function call.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0018I Error running *exec_name*, line *nn*: THEN expected

Explanation: All IF and WHEN clauses must be followed by a THEN clause. Another clause was found before a THEN statement was found.

System action: Exec processing terminates.

User response: Insert a THEN clause between the IF or WHEN clause and the following clause.

Module: IRXEEXEC

Audience: REXX user

IRX0019I Error running *exec_name*, line *nn*: String or symbol expected

Explanation: The language processor expected a symbol following the keywords CALL, SIGNAL, SIGNAL ON, or SIGNAL OFF but none was found. You may have omitted the string or symbol, or you may have inserted a special character (such as a parenthesis) in it.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0020I Error running *exec_name*, line *nn*: Symbol expected

Explanation: The language processor either expected a symbol following the END, ITERATE, LEAVE, NUMERIC, PARSE, or PROCEDURE keywords or expected a list of symbols following the DROP, UPPER, or PROCEDURE (with EXPOSE option) keywords. A symbol or list of symbols was not found.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0021I Error running *exec_name*, line *nn*: Invalid data on end of clause

Explanation: You have followed a clause, such as SELECT or NOP, by some data other than a comment.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0022I Error running *exec_name*, line *nn*: Invalid character string

Explanation: A character string that has unmatched SO-SI pairs (that is, an SO without an SI) or an odd number of bytes between the SO-SI characters was scanned with OPTIONS ETMODE in effect.

System action: Exec processing terminates.

User response: Correct the invalid character string in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0023I Error running *exec_name*, line *nn*: Invalid SBCS/DBCS mixed string

Explanation: A character string that has unmatched SO-SI pairs (that is, an SO without an SI) or an odd number of bytes between the SO-SI characters was processed with OPTIONS EXMODE in effect.

System action: Exec processing terminates.

User response: Correct the invalid character string in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0024I Error running *exec_name*, line *nn*: Invalid TRACE request

Explanation: The language processor issues this message when:

- The action specified on a TRACE instruction or the argument to the built-in function starts with a letter that is not a valid alphabetic character option. The valid options are A, C, E, F, I, L, N, O, R, or S.
- An attempt is made to request TRACE SCAN when inside any control construction or while in interactive debug.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0025I Error running *exec_name*, line *nn*: Invalid sub-keyword found

Explanation: The language processor expected a particular sub-keyword at this position in an instruction and something else was found. For example, the NUMERIC instruction must be followed by the sub-keyword DIGITS, FUZZ, or FORM. If NUMERIC is followed by anything else, this message is issued.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0026I Error running *exec_name*, line *nn*: Invalid whole number

Explanation: The language processor found an expression that did not evaluate to a whole number or that was greater than the limit, for these uses, of 999,999,999. The expression appeared in the NUMERIC instruction, a parsing positional pattern, or the right hand term of the exponentiation (** operator).

This message can also be issued if the return code passed back from an EXIT or RETURN instruction (when an exec is called as a command, rather than as a function or subroutine) is not a whole number or will not fit in a System/370 register. You may have incorrectly typed the name of a symbol so that it is not the name of a variable in the expression on any of these statements. This might be true, for example, if you entered "EXIT CR" instead of "EXIT RC".

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0027I Error running *exec_name*, line *nn*: Invalid DO syntax

Explanation: The language processor found a syntax error in the DO instruction. You might have used BY or TO twice or used BY, TO, or FOR when you did not specify a control variable.

System action: Exec processing terminates.

IRX0028I • IRX0030I

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0028I Error running *exec_name*, line *nn*: Invalid LEAVE or ITERATE

Explanation: The language processor encountered an invalid LEAVE or ITERATE instruction. The instruction was invalid because:

- No loop is active, or
- The name specified on the instruction does not match the control variable of any active loop.

Note that internal routine calls and the INTERPRET instruction protect DO loops by making them inactive. Therefore, for example, a LEAVE instruction in a subroutine cannot affect a DO loop in the calling routine.

This message can occur if you use the SIGNAL instruction to transfer control within or into a loop. A SIGNAL instruction terminates all active loops and any ITERATE or LEAVE instruction issued then would cause this message to be issued.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0029I Error running *exec_name*, line *nn*: Environment name too long

Explanation: The language processor encountered an address environment name specified on an ADDRESS instruction that is longer than the limit of 8 characters.

System action: Exec processing terminates.

User response: Specify the address environment name on the ADDRESS instruction correctly.

Module: IRXEEXEC

Audience: REXX user

IRX0030I Error running *exec_name*, line *nn*: Name or string > 250 characters

Explanation: The language processor found a variable or a literal (quoted) string that is longer than the limit.

The limit for names is 250 characters, following any substitutions. A possible cause of this error is the use of a period (.) in a name, causing an unexpected substitution.

The limit for a literal string is 250 characters. This error can be caused by leaving off an ending quote (or putting a single quotation mark in a string) because several clauses can be included in the string. For example, the string 'don't' should be written as 'don't' or "don't".

If this is not the case, you can create a larger string using concatenation. For example:

```
a = "...long_string_1..."
b = "...long_string_2..."
c = a || b
```

where *long_string_1* and *long_string_2* are character strings less than 250 characters long.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0031I Error running *exec_name*, line *nn*: Name starts with number or “.”

Explanation: The language processor found a symbol whose name begins with a numeric digit or a period (.). The REXX language rules do not allow you to assign a value to a symbol whose name begins with a numeric digit or a period because you could then redefine numeric constants, which would be catastrophic.

System action: Exec processing terminates.

User response: Rename the variable correctly. It is suggested to start a variable name with an alphabetic character, but some other characters are allowed.

Module: IRXEEXEC

Audience: REXX user

IRX0032I Error running *exec_name*, line *nn*: Invalid use of stem

Explanation: The exec attempted to change the value of a symbol that is a stem. (A stem is that part of a symbol up to the first period. You use a stem when you want to affect all variables beginning with that stem.) This may be in the UPPER instruction where the action in this case is unknown, and therefore in error.

System action: Exec processing terminates.

User response: Change the exec so that it does not attempt to change the value of a stem.

Module: IRXEEXEC

Audience: REXX user

IRX0033I Error running *exec_name*, line *nn*: Invalid expression result

Explanation: The language processor encountered an expression result that is invalid in its particular context. The result may be invalid because an illegal FUZZ or DIGITS value was used in a NUMERIC instruction (FUZZ cannot become larger than DIGITS).

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0034I Error running *exec_name*, line *nn*: Logical value not 0 or 1

Explanation: The language processor found an expression in an IF, WHEN, DO WHILE, or DO UNTIL phrase that did not result in a 0 or 1. Any value operated on by a logical operator (\neg , \backslash , $|$, $\&$, or $\&\&$) must result in a 0 or 1. For example, the phrase `If result then exit rc` will fail if result has a value other than 0 or 1. Thus, the phrase would be better written as `If result \neq 0 then exit rc`.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0035I Error running *exec_name*, line *nn*: Invalid expression

Explanation: The language processor found a grammatical error in an expression. You might have ended an expression with an operator, had two adjacent operators with no data in between, or included special characters (such as operators) in an intended character expression without enclosing them in quotes. For example, the message is issued if you have the following clause in an exec:

```
answer = x ++ 5
```

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

IRX0036I • IRX0040I

Module: IRXEEXEC

Audience: REXX user

IRX0036I Error running *exec_name*, line *nn*: Unmatched "(" in expression

Explanation: The language processor found an unmatched parenthesis within an expression. You will get this message if you include a single parenthesis in a command without enclosing it in quotes.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0037I Error running *exec_name*, line *nn*: Unexpected ",", or ")"

Explanation: The language processor found a comma (,) outside a routine invocation or too many right parentheses in an expression. You will get this message if you include a comma in a character expression without enclosing it in quotes. For example, the instruction:

Say Enter A, B, or C

should be written as:

Say 'Enter A, B, or C'

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0038I Error running *exec_name*, line *nn*: Invalid template or pattern

Explanation: The language processor found an invalid special character, for example %, within a parsing template, or the syntax of a variable trigger was incorrect (no symbol was found after a left parenthesis). This message is also issued if the WITH sub-keyword is omitted in a PARSE VALUE instruction.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0039I Error running *exec_name*, line *nn*: Evaluation stack overflow

Explanation: The language processor was not able to evaluate the expression because it is too complex (many nested parentheses, functions, and so on).

System action: Exec processing terminates.

User response: Break up the expressions by assigning sub-expressions to temporary variables.

Module: IRXEEXEC

Audience: REXX user

IRX0040I Error running *exec_name*, line *nn*: Incorrect call to routine

Explanation: The language processor encountered an incorrectly used call to a built-in or external routine. You may have passed invalid data (arguments) to the routine. This is the most common possible cause and is dependent on the actual routine. If a routine returns a non-zero return code, the language processor issues this message and passes back its return code of 20040.

If you were not trying to invoke a routine, you may have a symbol or a string adjacent to a "(" when you meant it to be separated by a space or an operator. This causes it to be seen as a function call. For example, TIME(4+5) should be written as TIME*(4+5).

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0041I Error running *exec_name*, line *nn*: Bad arithmetic conversion

Explanation: The language processor found a term in an arithmetic expression that was not a valid number or that had an exponent outside the allowed range of -999,999,999 to +999,999,999.

You may have incorrectly typed a variable name, or included an arithmetic operator in a character expression without putting it in quotes. For example, you should write the command EXECIO * DISKW OUTDD (FINIS as: 'EXECIO * DISKW OUTDD (FINIS'

Otherwise, the language processor tries to multiply "EXECIO" by "DISKW".

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0042I Error running *exec_name*, line *nn*: Arithmetic overflow/underflow

Explanation: The language processor encountered a result of an arithmetic operation that required an exponent greater than the limit of 9 digits (more than 999,999,999 or less than -999,999,999).

This error can occur during evaluation of an expression (often as a result of trying to divide a number by 0), or during the stepping of a DO loop control variable.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0043I Error running *exec_name*, line *nn*: Routine not found

Explanation: The language processor was unable to find a routine called in your exec. You invoked a function within an expression or in a subroutine invoked by CALL, but the specified label is not in the program or is not the name of a built-in function. TSO/E is also unable to locate it externally.

The simplest, and probably most common, cause of this error is typing the name incorrectly. Another possibility may be that one of the function packages is not available.

If you were not trying to invoke a routine, you may have put a symbol or string adjacent to a "(" when you meant it to be separated by a space or operator. The language processor would process that as a function invocation. For example, the string 3(4+5) should be written as 3*(4+5).

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0044I Error running *exec_name*, line *nn*: Function did not return data

Explanation: The language processor invoked an external routine within an expression. The routine seemed to end without error, but it did not return data for use in the expression.

This may be due to using the STORAGE function to read storage you are not allowed to read. In this case, the STORAGE function does not return any data.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0045I Error running *exec_name*, line *nn*: No data specified on function RETURN

Explanation: An exec has been called as a function, but an attempt is being made to return (by a RETURN; instruction) without passing back any data. Similarly, an internal routine, called as a function, must end with a RETURN statement specifying an expression.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0046I Error running *exec_name*, line *nn*: Invalid variable reference

Explanation: Within an ARG, DROP, PARSE, PULL or PROCEDURE instruction, the syntax of a variable reference (a variable whose value is to be used, indicated by its name being enclosed in parentheses) is incorrect. The right parenthesis that should immediately follow the variable name may be missing.

System action: Exec processing terminates.

User response: Make the necessary corrections in the exec.

Module: IRXEEXEC

Audience: REXX user

IRX0047I Error running *exec_name*, line *nn*: Unexpected label

Explanation: A label, being used incorrectly, was encountered in the expression being evaluated for an INTERPRET instruction or in an expression entered during interactive debug.

System action: Exec processing terminates.

User response: Do not use a label in these expressions.

Module: IRXEEXEC

Audience: REXX user

IRX0048I Error running *exec_name*, line *nn*: Failure in system service

Explanation: The language processor terminates exec processing because some system service, such as user input or output or manipulation of the data stack has failed to work correctly.

System action: Exec processing terminates.

User response: Ensure that your input is correct and that your exec is working correctly. Contact your system programmer for assistance.

Module: IRXEEXEC

Audience: REXX user

IRX0049I Error running *exec_name*, line *nn*: **Interpreter failure**

Explanation: The language processor carries out numerous internal self-consistency checks. It issues this message if it encounters a severe error.

System action: Exec processing terminates.

User response: Contact your system programmer for assistance. Report any occurrence of this message to your IBM representative.

Module: IRXEEXEC

IRX0100I +++ Interactive trace. TRACE OFF to end debug, ENTER to continue. +++

Explanation: This is an informational message, which indicates that the interactive debug facility is active. Interactive debug lets you interactively control the execution of a REXX exec.

System action: The language processor pauses after most instructions that are traced at the terminal. Exec processing continues from pause point to pause point depending on the user's response.

User response: Press the Enter key to continue exec processing and tracing of the exec. The language processor executes the next instruction in the exec and pauses at the next pause point.

To re-execute the last instruction in the exec that was traced, enter an equal sign (=). You can also enter additional instructions, such as REXX keyword instructions and commands. The language processor processes your input immediately before it processes the next instruction in the exec.

To end interactive trace, enter TRACE OFF. In this case, exec processing continues but interactive tracing is no longer active.

See *z/OS TSO/E REXX Reference*, for more information about the TRACE instruction and the interactive debug facility.

Module: IRXSYSET

Audience: REXX user

IRX0105I Exec <execname> is: *full-name-of-exec*

Explanation: This message is issued in conjunction with a previous message, IRX00nnI (nn= 01-99), to specify the full name of the exec referred to in that message as <execname>.

When an exec name exceeds 60 characters, the generic placeholder string <execname> is inserted in place of the actual exec name in any syntax error messages (IRX00nnI, nn= 01-99) that accepts an exec name insert. Following that message, message IRX0105I is issued to specify the full name of the exec that is represented by the generic insert, <execname>.

System action: See System Action specified in the associated IRX00nnI message.

User response: See User Response specified in the associated IRX00nnI message.

Module: IRXEEXEC

Audience: REXX user

IRX0106I Function, subroutine, or host command <execname> is: *full-name-of-exec*

Explanation: This message is issued in conjunction with a previous message (IRX0250E-IRX0256E, or IRX0246I-IRX0248I) to specify the full name of the exec referred to in that message as <execname>.

When an exec name exceeding 60 characters is inserted in one of the above messages by REXX Recovery, a generic placeholder string <execname> is inserted in the message in place of the actual name of the exec. Following that message, message IRX0106I is issued to specify the full name of the exec that is represented by the generic insert, <execname>.

System action: See System Action specified in the associated IRX00nnI message.

User response: See User Response specified in the associated IRX00nnI message.

Module: IRXRECOV

IRX0110I • IRX0113I

Audience: REXX user

IRX0110I The REXX exec cannot be interpreted.

Explanation: An error occurred before the language processor received control to process the exec. There are many possible reasons for the error, such as the exec could not be loaded, recovery could not be established, or storage could not be obtained.

If alternate messages are displayed, the alternate message provides the specific reason for why the exec could not be processed. If alternate messages are not displayed for the language processor environment in which the exec is running, the environment block still contains the message ID of the alternate message.

System action: Exec processing terminates.

User response: Try running the exec again. If the error continues, contact your system programmer for assistance.

Module: IRXEEXEC

Audience: REXX user

IRX0111I The IRXEEXEC pre-processing routine returned a non-zero return code.

Explanation: The interpretation exit routine returned a non-zero return code.

The interpretation exit routine is invoked whenever the IRXEEXEC routine is called to process an exec. The name of the exit that is invoked is specified on the call to the initialization routine IRXINIT (in the module name table) and is stored in the system control block. The exit is used to check the parameters that are passed to IRXEEXEC, change the parameters, or terminate exec processing. This message was issued because the exit routine returned a non-zero return code to terminate exec processing.

System action: Exec processing terminates.

User response: Contact your system programmer for assistance.

Module: IRXSYSET

Audience: REXX user

IRX0112I The REXX exec cannot be loaded.

Explanation: The exec could not be read from the data set and put into storage in a format that the language processor could use.

In non-TSO/E address spaces, you may provide your own load routine to load execs. The load routine may have returned a non-zero return code, which results in this message being issued.

System action: Exec processing terminates.

User response: Check to see if the exec exists. The exec might be empty. If it is *not* empty, try running the exec again. If the error continues, contact your system programmer for assistance.

Module: IRXSYSET

Audience: REXX user

IRX0113I The attention exit cannot be established.

Explanation: In the TSO/E address space, the system has to set up attention facilities before the language processor processes an exec. The attention facilities could not be established.

System action: Exec processing terminates.

User response: Contact your system programmer for assistance.

Module: IRXSYSET

Audience: REXX user

IRX0155E The module IRXCMPTM is not available.

Explanation: REXX attempted to load the compiler programming table module, IRXCMPTM, to execute either a compiled REXX program or a compiled REXX exec. The REXX language processor could not find module IRXCMPTM.

System action: Processing terminates.

System programmer response: Ensure that the compiler programming table module, IRXCMPTM, is in a data set that is in the search sequence for an MVS load.

User response: Contact your system programmer for assistance.

Module: IRXENTRY

Audience: REXX user

IRX0156E The run-time processor *processor_name* is not available.

Explanation: REXX attempted to initialize the compiler runtime processor and the initialization failed. See the appropriate REXX compiler documentation for the compiler runtime processor *processor_name* to determine the appropriate action.

System action: Exec processing terminates.

System programmer response: Determine why the initialization routine failed for the compiler runtime processor.

User response: Contact your system programmer for assistance.

Module: IRXENTRY

Audience: REXX user

IRX0157E Routine *routine_name* of the run-time processor *processor_name* was not found.

Explanation: During processing of a compiled REXX exec or compiled REXX program, the compiler programming table (IRXCMPTB) identified the routine *routine_name* as being required. However, the routine could not be located. See the appropriate REXX compiler documentation for the compiler runtime processor *processor_name* to determine the appropriate action.

System action: Exec processing terminates.

System programmer response: Determine why the compiler interface routine *routine_name* was not available.

User response: Contact your system programmer for assistance.

Module: IRXCLOAD

Audience: REXX user

IRX0158E The run-time processor *processor_name* could not be found.

Explanation: During processing of a compiled REXX exec or compiled REXX program, REXX identified the compiler runtime processor *processor_name* as being required. However, the run-time processor could not be loaded. See the appropriate REXX compiler documentation for the compiler runtime processor *processor_name* to determine the appropriate action.

System action: Exec processing terminates.

System programmer response: Determine why the compiler runtime processor *processor_name* could not be found.

User response: Contact your system programmer for assistance.

Module: IRXCLOAD

Audience: REXX user

IRX0159E • IRX0205I

IRX0159E **The run-time processor *processor_name* is not available.**

Explanation: REXX attempted to find an entry for the compiler runtime processor in the compiler programming table module, IRXCMPTM, but could not find it.

System action: Exec processing terminates.

System programmer response: Add the compiler runtime processor *processor_name* to the compiler programming table module IRXCMPTM.

User response: Contact your system programmer for assistance.

Module: IRXENTRY

Audience: REXX user

IRX0200I **Invalid parameter(s).**

Explanation: One or more invalid parameters were specified on the call to either the host command environment table routine (IRXSUBCM) or the trace and execution control service routine (IRXIC).

System action: The routine does not perform the requested function.

User response: Check the parameters passed to the routine and correct any that are not valid.

Module: IRXEIC IRXESUBC

Audience: REXX user

IRX0201I **A module cannot be loaded into storage.**

Explanation: Either the IRXEEXEC or IRXTERM routine was called, but a module that the routine needs could not be loaded into storage.

System action: The routine does not perform the requested function.

User response: Make sure modules are link-edited so they can be loaded into storage. Contact your system programmer for assistance.

Module: IRXEEXEC IRXITERM

Audience: REXX user

IRX0203I **Recovery cannot be established.**

Explanation: Either the IRXEEXEC or IRXTERM routine was called, but recovery could not be established.

System action: The routine does not perform the requested function.

User response: Contact your system programmer for assistance.

Module: IRXEEXEC IRXITERM

Audience: REXX user

IRX0205I **A lock cannot be obtained.**

Explanation: A lock that is needed by either the environment termination routine (IRXTERM) or the address environment service routine (IRXSUBCM) could not be obtained.

System action: The routine does not perform the requested function.

User response: Log off from the system, log on, and try again. If the problem persists, contact your system programmer for assistance.

Module: IRXITERM

Audience: REXX user

IRX0207I Storage cannot be obtained.

Explanation: The exec processing routine or the address environment service routine was called, but the routine could not obtain the storage it needed.

This error may occur because the program that called the routine has already used up most of the available storage itself or the program went into a loop.

System action: The routine does not perform the requested function.

User response: Check how the program obtains and frees storage and that it is working correctly. Contact your system programmer for assistance.

Module: IRXEEXEC

Audience: REXX user

IRX0210E The first character in the variable name passed to OUTTRAP is invalid.

Explanation: The OUTTRAP function was specified, but the first character of the variable name used in OUTTRAP is incorrect.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the variable name for OUTTRAP. The variable name for OUTTRAP follows the same rules for variable names in the REXX language. The variable name must begin with an alphabetic character or with the special characters @, #, \$, ?, !, or _. For more information about REXX variables, see *z/OS TSO/E REXX User's Guide*. For more information about the OUTTRAP function, see *z/OS TSO/E REXX Reference*.

Module: IRXFTRAP

Audience: REXX user

IRX0211E There is an invalid character in the variable name passed to OUTTRAP.

Explanation: The OUTTRAP function was specified, but the variable name used in OUTTRAP is incorrect.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the variable name for OUTTRAP. The variable name for OUTTRAP must follow the same rules for valid variable names in the REXX language. Refer to *z/OS TSO/E REXX Reference* and *z/OS TSO/E REXX User's Guide* for the specific rules for REXX variable names (including compound variable names and DBCS variable names). For more information about the OUTTRAP function, see *z/OS TSO/E REXX Reference*.

Module: IRXFTRAP

Audience: REXX user

IRX0212E The variable name for OUTTRAP is missing or the length of the variable name is too long.

Explanation: The OUTTRAP function was specified, but either you did not specify the variable name or the variable name was too long. The variable name is required for OUTTRAP.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the OUTTRAP function and specify a valid variable name.

Module: IRXFTRAP

Audience: REXX user

IRX0213E **The length of the maximum count passed to OUTTRAP is too long to allow for concatenation to the variable name passed to OUTTRAP.**

Explanation: The OUTTRAP function was specified, but the maximum count value contains too many digits to allow for concatenation with the specified variable name. The resulting variable would not be valid.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the OUTTRAP function and use a maximum count value that contains fewer digits or specify a variable name that contains fewer characters.

Module: IRXFTRAP

Audience: REXX user

IRX0214E **The maximum count number passed to OUTTRAP is invalid.**

Explanation: The maximum count number used in the OUTTRAP function contained characters that are not valid.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: For the maximum count, specify an integer or an asterisk (*).

Module: IRXFTRAP

Audience: REXX user

IRX0215E **The CONCAT operand is invalid.**

Explanation: The concatenation operand for the OUTTRAP function is incorrect. The operand must be either CONCAT or NOCONCAT. The default is CONCAT.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the operand on the OUTTRAP function.

Module: IRXFTRAP

Audience: REXX user

IRX0216E **The variable update for OUTTRAP failed.**

Explanation: The OUTTRAP function called the IKJCT441 variable access routine and the routine returned a non-zero return code to OUTTRAP.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Contact your system programmer for assistance.

Module: IRXFTRAP

Audience: REXX user

IRX0217E **Too many arguments were passed to OUTTRAP.**

Explanation: The OUTTRAP function contained too many operands. OUTTRAP has a maximum of four operands: the variable name, the maximum count, the concatenation operand (CONCAT or NOCONCAT), and the skip amount.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the operands on OUTTRAP.

Module: IRXFTRAP

Audience: REXX user

IRX0218E The skip amount argument passed to OUTTRAP is invalid.

Explanation: The skip amount argument used in the OUTTRAP function is incorrect for one or more of the following reasons:

- Some of characters are not valid.
- The skip amount is out of the allowed range.
- The skip amount is longer than 36 characters.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: For the skip amount, you may specify an integer in the range 0 to 999,999,999. Leading zeros are ignored, as long as the total length of the argument does not exceed 36 characters. This argument is optional. If not specified, the default skip amount is 0.

Module: IRXFTRAP

Audience: REXX user

IRX0220E No arguments were specified for the function.

Explanation: A variable name was not specified for the SYSVAR function. A variable name is required in the form SYSVAR(*variable_name*).

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the SYSVAR function and specify a variable name.

Module: IRXSYSVR

Audience: REXX user

IRX0221E This system variable is not supported for SYSVAR processing.

Explanation: Either the variable name specified for the SYSVAR function is not valid or the level of MVS on which TSO/E is running does not support the variable name specified.

System action: Exec processing terminates.

User response: Correct the SYSVAR function and specify a valid variable name in the form SYSVAR(*variable_name*) or remove the variable name from the SYSVAR statement.

Module: IRXSYSVR

Audience: REXX user

IRX0222E Multiple arguments are not allowed for the SYSVAR function.

Explanation: The SYSVAR function was specified with multiple arguments. Only one variable name is allowed for the SYSVAR function.

System action: Exec processing terminates.

User response: Correct the SYSVAR function and specify one variable name in the form SYSVAR(*variable_name*).

Module: IRXSYSVR

Audience: REXX user

IRX0227E SYSCPUS error. One or more of the arguments are not valid.

Explanation: The argument specified on the SYSCPUS function is not valid, or a wrong number of arguments are specified.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Verify the argument on the SYSCPUS function invocation and make the necessary corrections.

Module: IRXSYSYCP

Audience: REXX user

IRX0228E SYSCPUS error. The attempt to store a REXX variable failed.

Explanation: The REXX variable access routine encountered an error while trying to set a REXX variable.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Ask your system programmer to contact the IBM support personnel regarding this problem.

Module: IRXSYSYCP

Audience: REXX user

IRX0229E MVSVAR function failed, because service IGWASYS returned with RC: *return_code* and reason code:*reason_code*.

Explanation: The service IGWASYS, which was invoked for the function, failed. For more information, see *z/OS DFSMSdfp Advanced Services*.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Do not use this function as long as your installation does not support this subsystem service.

Module: IRXMVSVR

Audience: REXX user

IRX0230E No arguments were specified for the function.

Explanation: A variable name was not specified for the MVSVAR function. A variable name is required in the form MVSVAR(*'variable_name'*) or MVSVAR('SYMDEF',*'variable_name'*).

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the MVSVAR function and specify a variable name.

Module: IRXMVSVR

Audience: REXX user

IRX0231E This system variable is not supported for MVSVAR processing.

Explanation: Either the variable name specified for the MVSVAR function is not valid or the level of MVS on which TSO/E is running does not support the variable name specified.

System action: Exec processing terminates.

User response: Correct the MVSVAR function and specify a valid variable name in the form MVSVAR(*'variable_name'*) or MVSVAR('SYMDEF',*'variable_name'*).

Module: IRXMVSVR

Audience: REXX user

IRX0232E Invalid arguments specified for the MVSVAR function.

Explanation: The MVSVAR function was specified with wrong arguments.

System action: Exec processing terminates.

User response: Correct the MVSVAR function and specify a valid variable name in the form MVSVAR(*variable_name*) or MVSVAR('SYMDEF',*variable_name*).

Module: IRXMVSVR

Audience: REXX user

IRX0233E SYSVAR function failed because the service IEFSSREQ returned with return code *return_code* and SSOBRETN code.

Explanation: The subsystem service IEFSSREQ, which was invoked to obtain JES information, failed. For more information see *z/OS MVS Using the Subsystem Interface*.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Do not use this function as long as your installation does not support this subsystem service.

Module: IRXSYSVR

Audience: REXX user

IRX0234E The argument *argument* of the MVSVAR or SYSVAR function failed. It requires product level *product_level*.

Explanation: The required product is not installed for the MVSVAR or SYSVAR function with the displayed argument.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Do not use this function as long as your installation does not support this function.

Module: IRXMVSVR IRXSYSVR

Audience: REXX user

IRX0236E The SYSAPPCLU argument failed because the service ATBEXAI returned with return code *return_code*.

Explanation: The subsystem service ATBEXAI, which was invoked to obtain the LU name, failed. For more information see *z/OS MVS Programming: Writing Transaction Programs for APPC/MVS*.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Do not use this function as long as your installation does not support this subsystem service.

Module: IRXMVSVR

Audience: REXX user

IRX0237E MVSVAR function failed due to error in call to MVS ASASYMBM service. Return code from ASASYMBM: *return_code*.

Explanation: The MVSVAR function failed because an error occurred in a call to the multiple virtual storage (MVS) symbol substitution service (ASASYMBM). An error occurred when ASASYMBM tried to substitute text for a symbol specified in the function.

Return code 8 typically means that the variable name is not specified properly, such that the resulting substitution would be greater than eight characters.

See *z/OS MVS Initialization and Tuning Reference* for the syntax of the SYSDEF ... SYMDEF statement. For detailed

IRX0238E • IRX0240I

information about ASASYMBM return codes, see *z/OS MVS Programming: Assembler Services Reference ABE-HSP*.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

Module: IRXMVSVR

Audience: REXX user

IRX0238E MVSVAR function failed, because the service *service_name* could not be loaded.

Explanation: The service *service_name* is required for this function, but it could not be loaded.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Ask your system administrator to make this service available in a system library.

Module: IRXMVSVR

Audience: REXX user

IRX0239E Function error; an attempt to obtain storage failed.

Explanation: The function you invoked attempted to obtain storage, but the attempt failed.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Log on again with a larger region size. If the problem persists, ask your system programmer to contact the IBM support personnel regarding this error.

Module: IRXSYSVR IRXSYSCP

Audience: REXX user

IRX0240I Invalid parameters to STORAGE function.

Explanation: The STORAGE function was used with invalid values. You must specify an address. Optionally, you can also specify the length and data values. You may have omitted the address, used an address that was too large, or specified a length that was not valid (for example, a negative length value).

The address value specified can be a 31-bit address or a 64-bit address. A 31-bit address consists of 1 to 8 hexadecimal characters. The following are examples of 31-bit addresses.

Hexadecimal Addr Specified	Binary Address used by STORAGE	Comment
10	'00000010'x	- Valid 31-bit.
00000010	'00000010'x	- Valid 31-bit.
80000010	'00000010'x	- Valid 31-bit. The high-order sign bit ignored in a 31-bit addr.
8B88	'00008B88'x	- Valid 31-bit addr.

The following illustrates some valid and invalid 64-bit addresses:

Hexadecimal Addr Specified	Binary Address used by STORAGE	Comment
_00000010	'0000000000000010'x	- Valid 64-bit addr. (Padded to left with 0's to 64-bits.) Addresses same area as 31-bit addr '00000010'x.
0_00000010	'0000000000000010'x	- Valid 64-bit addr. Addresses same area as _00000010.
0_80000010	'0000000080000010'x	- Valid 64-bit addr. Addr is 2GB beyond the 0_00000010 addr.
000001EF10	'000000000001EF10'x	- Valid 64-bit addr.

1EF_80000010	'000001EF80000010'x	- Valid 64-bit addr.
1EF80000010	'000001EF80000010'x	- Valid 64-bit addr without "_" separator.
000001EF_80000010	'000001EF80000000'x	- Valid 64-bit addr.
000001EF_10	Invalid Addr	- Right half of 64-bit addr <8 chars.
00000001EF_000010	Invalid Addr	- Left half of addr >8 chars, right half <8 chars.
0000001EF_80000010	Invalid Addr	- More than 16 hex chars.
00001EF8000001000	Invalid Addr	- More than 16 hex chars.

FOR EXAMPLE:

```

z = STORAGE(10,4)                /* Read 4 chars of storage at 31-bit
                                addr '00000010'X          */

z = STORAGE(1ef_80000010,10)     /* Read first 10 chars of storage at
                                64-bit addr '1EF80000010'X  */

z = STORAGE(5db0_0f780000,4,'ANTZ') /* Read 4 chars at 64-bit addr
                                '5DB00F80000'X and replace those
                                with the characters 'ANTZ'.    */

```

System action: Exec processing continues.

User response: Correct the STORAGE function and specify a correct address and, optionally, the length and data values.

Module: IRXFSTOR

Audience: REXX user

IRX0241I STORAGE function in read-only mode, but new value argument was specified.

Explanation: The STORAGE function was executing in read-only mode, but you specified a new value in argument three to request that the STORAGE function overwrite data at the specified address with the new value. This usage is not allowed.

When executing in read-only mode, the STORAGE function can read but not alter storage. In this case, only two arguments are allowed.

System action: Exec processing continues.

User response: Correct the STORAGE function by removing the argument specifying a new value.

Module: IRXFSTOR

Audience: REXX user

IRX0242I STORAGE function not allowed in current REXX environment.

Explanation: You called the REXX STORAGE function, but this function is not allowed in the current REXX environment. No storage information is returned.

System action: Exec processing continues.

User response: You cannot use the REXX STORAGE function in the REXX environment under which you are currently running.

Module: IRXFSTOR

Audience: REXX user

IRX0245I REXX exec execution halted.

Explanation: REXX recovery detected abend code 66D reason code 50, or abend code x3E (where *x* is a value 0–F). Execution of the currently executing exec is halted. This is not an error condition, and no dump is taken. The exec is terminated because either:

- The user entered the HE command in response to the attention prompt message.
- The task that attached the REXX exec detached the REXX exec before the exec completed.

This message will accompany message IRX0929I if the exec was terminated because the HE immediate command was issued during REXX attention processing. For more information on the HE command, see *z/OS TSO/E REXX Reference*.

System action: The exec currently executing is terminated.

If the exec was executed from the TSO/E READY prompt, only the exec that is currently executing will be terminated. Any exec or CLIST that called the currently executing exec will continue executing.

If the exec was executed from an ISPF environment, all execs and CLISTs running under the same task as the exec currently executing will be terminated. For example, when an exec is executed from ISPF and it calls other execs, the last exec that it called, and all execs above it up to where it began, will be terminated.

User response: No action required. This is an informational message.

Module: IRXRECOV

Audience: REXX user

IRX0246I Execution halted while in external function *function_name*.

Explanation: The REXX exec was executing in the external function *function_name* at the time its execution was halted.

System action: The exec and the external function *function_name* are terminated.

User response: No action required. This is an informational message. Message IRX0245I will accompany this message.

Module: IRXRECOV

Audience: REXX user

IRX0247I Execution halted while in external subroutine *subroutine_name*.

Explanation: The REXX exec was executing in the external subroutine *subroutine_name* at the time its execution was halted.

System action: The exec and the external subroutine *subroutine_name* are terminated.

User response: No action required. This is an informational message. Message IRX0245I will accompany this message.

Module: IRXRECOV

Audience: REXX user

IRX0248I Execution halted in host command *command_name* or address environment routine for *routine_name*.

Explanation: The halted REXX exec was executing either the host command *command_name*, or in the host command environment routine for address environment *routine_name* at the time its execution was halted.

System action: The exec and the host command or host command environment routine are halted.

User response: No action required. This is an informational message. Message IRX0245I will accompany this message.

Module: IRXRECOV

Audience: REXX user

IRX0250E System abend code *abend_code*, reason code *reason_code*.

Explanation: A system abend occurred while an exec was processing or while a language processor environment was being initialized or terminated. The reason code is represented in decimal.

System action: If the abend occurred in system code or in installation replaceable routines or exits, which function as an extension of the system code, a dump is taken (if appropriate) and the failing routine returns with return code 100. If the abend occurred in an external function or subroutine, a host command, or one of the address environment routines during exec processing, a dump is taken (if appropriate) and the exec continues processing.

User response: Try to determine the cause of the failure and correct the problem or contact your system programmer for assistance.

Module: IRXRECOV

Audience: REXX user

IRX0251E User abend code *abend_code*, reason code *reason_code*.

Explanation: A user abend occurred while an exec was processing or while a language processor environment was being initialized or terminated. The reason code is represented in decimal.

System action: If the abend occurred in system code or in installation replaceable routines or exits, which function as an extension of the system code, a dump is taken (if appropriate) and the failing routine returns with return code 104. If the abend occurred in an external function or subroutine, a host command, or one of the address environment routines during exec processing, a dump is taken (if appropriate) and the exec continues processing.

User response: Try to determine the cause of the failure and correct the problem or contact your system programmer for assistance.

Module: IRXRECOV

Audience: REXX user

IRX0252E Recovery retry to module *module_name* failed.

Explanation: After an abend occurred in system code or in an installation replaceable routine or exit, which functions as an extension of system code, the recovery routine retried back to the specified module (*module_name*) to clean up resources. The retry also failed.

If the retry was made for either the initialization routine (IRXINIT) or the exec processing routine (IRXEXEC), a second retry is performed. During the second retry attempt, no additional environment cleanup is performed. The IRXINIT or IRXEXEC routine only attempts to return normally to its caller with return code 100 (system abend) or return code 104 (user abend). IRXINIT or IRXEXEC also attempts to return abend and reason code information in register 0.

If the retry was made for the termination routine (IRXTERM), the retry attempts to continue with environment termination. If more than three retry failures occur, one final retry is made, but no additional environment cleanup is performed. The termination routine IRXTERM only attempts to return normally to its caller with return code 100 (system abend) or return code 104 (user abend). IRXTERM also attempts to return abend and reason code information in register 0.

System action: Exec processing terminates.

User response: Try to determine the cause of the failure and correct the problem or contact your system programmer for assistance.

Module: IRXRECOV

Audience: REXX user

IRX0253E Abend in external function *function_name*.

Explanation: An abend occurred in an external function during exec processing. See message IRX0250E or IRX0251E for abend code and reason code information.

The recovery routine provides a dump (for appropriate abends), and retries back to the language processor to

IRX0254E • IRX0260E

continue exec processing. The exec can trap abend failures in external functions by using SIGNAL ON FAILURE or SIGNAL ON ERROR.

System action: Exec processing continues.

User response: Correct the external function that failed or contact your system programmer for assistance.

Module: IRXRECOV

Audience: REXX user

IRX0254E **Abend in external subroutine** *subroutine_name*.

Explanation: An abend occurred in an external subroutine during exec processing. See message IRX0250E or IRX0251E for abend code and reason code information.

The recovery routine provides a dump (for appropriate abends), and retries back to the language processor to continue exec processing. The exec can trap abend failures in external subroutines by using SIGNAL ON FAILURE or SIGNAL ON ERROR.

System action: Exec processing continues.

User response: Correct the external subroutine that failed or contact your system programmer for assistance.

Module: IRXRECOV

Audience: REXX user

IRX0255E **Abend in host command** *command_name* **or address environment routine** *routine_name*.

Explanation: During exec processing, an abend occurred in either a host command or one of the address environment routines. See message IRX0250E or IRX0251E for abend code and reason code information.

The recovery routine provides a dump (for appropriate abends), and retries back to the language processor to continue exec processing. The exec can trap abend failures by using SIGNAL ON FAILURE or SIGNAL ON ERROR.

System action: Exec processing continues.

User response: Correct the command or the address environment routine that failed or contact your system programmer for assistance.

Module: IRXRECOV

Audience: REXX user

IRX0256E **Unable to retry to language processor after abend.**

Explanation: An abend occurred during exec processing, but the recovery routine is not able to restart the language processor because internal control blocks are incorrect. The IRXEXEC routine completes with return code 100 (system abend) or return code 104 (user abend). IRXEXEC also attempts to return abend and reason code information in register 0.

This problem may be caused by a storage overlay of certain internal REXX control blocks.

System action: Exec processing terminates.

User response: Contact your system programmer for assistance.

Module: IRXRECOV

Audience: REXX user

IRX0260E **Invalid parameter list passed to** *routine_name*.

Explanation: The routine you called (as specified by *routine_name* in the message) passed a parameter list that was incorrect.

System action: The routine does not perform the requested function.

User response: Check the parameter list on the call to the routine. Specifically, check that all parameters are valid,

that you are specifying the correct number of parameters, and that the high-order bit is on (set to 1) in the last parameter to indicate the end of the parameter list.

Module: All external REXX (entry points) routines

Audience: REXX user

IRX0270E Invalid argument was passed to the PROMPT function.

Explanation: The PROMPT function was specified, but the argument specified on the function was incorrect.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the argument on the PROMPT function. The valid arguments are:

- Null -- returns the current state of prompting
- ON -- prompting is set on
- OFF -- prompting is set off

Module: IRXFPRMT

Audience: REXX user

IRX0271E Invalid TSO/E input stack address was found.

Explanation: An TSO/E invalid input stack was detected while processing the PROMPT function.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Contact your system programmer for assistance.

Module: IRXFPRMT

Audience: REXX user

IRX0272E Too many arguments were passed to PROMPT.

Explanation: You specified more than one argument on the PROMPT function.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Reissue the PROMPT function with one valid argument.

Module: IRXFPRMT

Audience: REXX user

IRX0273E Invalid argument was passed to the MSG function.

Explanation: The MSG function was specified, but the argument specified on the function was incorrect.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the argument on the MSG function. The valid arguments are:

- Null -- returns the current state of message issuing
- ON -- message issuing is set on
- OFF -- message issuing is set off

Module: IRXFMSG

Audience: REXX user

IRX0274E • IRX0278E

IRX0274E Too many arguments were passed to MSG.

Explanation: You specified more than one argument on the MSG function.

System action: The function ends, and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Reissue the MSG function with one valid argument.

Module: MSG function

Audience: REXX user

IRX0275E Too many arguments were passed to LISTDSI.

Explanation: You specified more than one argument on the LISTDSI function; only one argument is allowed.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Reissue the LISTDSI function with one valid argument.

Module: IRXLSTDS

Audience: REXX user

IRX0276E Invalid argument was passed to the TRAPMSG function.

Explanation: The TRAPMSG function was specified, but the argument specified on the function was incorrect.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Correct the argument on the TRAPMSG function. The valid arguments are:

- Null - returns the current state of TRAPMSG.
- ON - TRAPMSG state is turned ON and the previous state of TRAPMSG is returned.
- OFF - TRAPMSG state is turned OFF and the previous state of TRAPMSG is returned.

Module: IRXFTMSG

Audience: REXX user

IRX0277E Too many arguments were passed to TRAPMSG.

Explanation: You specified more than one argument on the TRAPMSG function.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Resissue the TRAPMSG function with one valid argument.

Module: IRXFTMSG

Audience: REXX user

IRX0278E Error attempting to change TRAPMSG setting.

Explanation: REXX TRAPMSG encountered an error while trying to set the TRAPMSG indicator. This may indicate an internal error.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends. The TRAPMSG state is not changed.

User response: Ensure that you are in a valid environment for the TRAPMSG function. If so, try issuing TRAPMSG again.

TRAPMSG is only valid when running in an environment integrated with TSO/E. It is only meaningful if the exec also has enabled output trapping with the REXX OUTTRAP function.

Module: IRXFTMSG

Audience: REXX user

IRX0280I GETMSG error; one or more of the arguments are not valid.

Explanation: One or more arguments specified on the GETMSG function are not valid or too many arguments were specified.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Check all the arguments on the GETMSG function invocation and make the necessary corrections.

Module: IRXFGETM

Audience: REXX user

IRX0281I GETMSG error; the attempt to store a REXX variable failed.

Explanation: The REXX variable access routine encountered an error while trying to set a REXX variable.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Ask your system programmer to contact the IBM support personnel regarding this problem.

Module: IRXFGETM

Audience: REXX user

IRX0283I GETMSG error; an attempt to obtain storage failed.

Explanation: The GETMSG function attempted to obtain storage, but the attempt failed.

System action: The function ends and a syntax error occurs. If you do not have a SYNTAX trap enabled, the exec ends.

User response: Log on again with a larger region size. If the problem persists, ask your system programmer to contact the IBM support personnel regarding this error.

Module: IRXFGETM

Audience: REXX user

IRX0289I SETLANG error; the argument is not valid.

Explanation: The SETLANG function received an argument that is not valid, or too many arguments were specified. The argument must be a valid 3-character language code. For a list of the valid language codes, see *z/OS TSO/E REXX Reference*.

System action: The function ends.

User response: Specify a valid language code.

Module: IRXFLANG

Audience: TSO/E user

IRX0300E The message module *module* could not be loaded.

Explanation: The REXX message issuing routine attempted to load a module containing messages and the load failed. The name of the load module is displayed in the message.

System action: This message is issued and REXX attempts to issue the message in US English.

User response: The language specified for REXX in the initialization parameters or through the SETLANG function must be a valid 3-character language code representing a language installed on your system. Contact your system programmer to learn what languages are on your system. For a list of valid language codes, see *z/OS TSO/E REXX Reference*.

IRX0301E • IRX0400E

Module: IRXEMSG

Audience: TSO/E User

IRX0301E The message *message_id* could not be found in the message table.

Explanation: Message number *message_id* could not be located in the message table.

This is typically a system error where a routine could not find a message in a message module. However, your installation may have installed the message modules incorrectly or renamed them incorrectly.

System action: The specified message *message_id* is not issued.

User response: Contact your system programmer for assistance.

Module: IRXSYSET

Audience: REXX user

IRX0303E Too many parameters were passed for message *message_id*.

Explanation: An error occurred during text substitution for message *message_id*.

This is typically a system error where a routine could not substitute message text information. However, your installation may have installed the message modules incorrectly or renamed them incorrectly.

System action: The specified message *message_id* is not issued.

User response: Contact your system programmer for assistance.

Module: IRXEMSG

Audience: REXX user

IRX0304E A parameter of invalid length was passed to message *message_id*.

Explanation: An error occurred during text substitution for message *message_id*.

This is typically a system error. However, your installation may have installed the message modules incorrectly or renamed them incorrectly.

System action: The specified message *message_id* is not issued.

User response: Contact your system programmer for assistance.

Module: IRXEMSG

Audience: REXX user

IRX0305E The parameter(s) passed to message *message_id* were too large.

Explanation: An error occurred during text substitution for message *message_id*.

This is typically a system error where a routine could not substitute message text information. However, your installation may have installed the message modules incorrectly or renamed them incorrectly.

System action: The specified message *message_id* is not issued.

User response: Contact your system programmer for assistance.

Module: IRXEMSG

Audience: REXX user

IRX0400E Unable to open file *ddname*. The REXX exec *exec_name* could not be loaded.

Explanation: The load routine could not open the specified file *ddname*. The exec could not be loaded.

This is typically a system error. However, if the specified file was already opened, but opened in the wrong mode (for example, open for I/O), the OPEN fails.

System action: The exec is not loaded.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0401E An unknown function request was passed to the REXX exec load routine.

Explanation: The exec load routine was called, but the function specified on the call is not supported.

System action: No function is performed.

User response: Correct the call to the exec load routine or contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0402E Invalid or missing parameters passed to exec load for a "LOAD", "STATUS", or "CLOSEDD" request.

Explanation: The exec load routine was invoked for the "LOAD", "STATUS", or "CLOSEDD" function, but some of the parameters on the call were either missing or were incorrect.

System action: The requested function is not performed.

User response: Correct the call to the exec load routine or contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0403E Invalid or missing parameters passed to exec load for a "LOADCOMP" request.

Explanation: The exec load routine was invoked for a "LOADCOMP" request, but some of the parameters on the call were either missing or were incorrect.

System action: The requested function is not performed.

User response: Correct the call to the exec load routine or contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0404E Invalid or missing EXECBLK parameter passed to the exec load routine.

Explanation: The exec load routine was invoked, but the exec block (EXECBLK) parameter specified on the call was either missing or was incorrect.

This message is issued because the address of the EXECBLK was not specified on the call, the format of the EXECBLK was incorrect, or the format was correct but some required fields were missing. On the call to the exec load routine, the address of the EXECBLK is required. The EXECBLK must contain the EXECBLK identifier and length.

System action: The requested function is not performed.

User response: Make the necessary corrections or contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0406E • IRX0410E

IRX0406E REXX exec load file *ddname* does not contain exec member *exec_name*.

Explanation: The specified exec load file does not contain the specified exec member.

System action: The exec is not loaded.

User response: Correct the member name of the exec or the exec load file *ddname*.

Module: IRXELOAD

Audience: REXX user

IRX0407E Exec member name must be specified when the exec load DD refers to a partitioned data set.

Explanation: The exec load DD refers to a partitioned data set, but an exec member name was not specified in the exec block (EXECBLK).

System action: The exec is not loaded.

User response: When calling the exec load routine, specify the member name of the exec in the EXECBLK to load from a partitioned data set.

Module: IRXELOAD

Audience: REXX user

IRX0408E Exec member name must not be specified when exec load DD refers to a sequential data set.

Explanation: On the call to the exec load routine, the exec load DD referred to a sequential data set, but an exec member name was also specified in the exec block (EXECBLK).

System action: The exec is not loaded.

User response: If you want to load the exec from a sequential data set, do not specify a member name in the EXECBLK on the call to the exec load routine.

Module: IRXELOAD

Audience: REXX user

IRX0409E Record format of exec load data set is not valid. RECFM must be fixed or variable, and spanned or track overflow records are not supported.

Explanation: An exec load file has a record format that is not valid. Execs can be loaded only from files that have a non-spanned fixed or variable record format. Spanned, track overflow, and undefined record formats are not supported.

System action: The exec is not loaded.

User response: Check the record format of the indicated exec load file. If necessary, copy your execs to a new exec file having the correct record format or contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0410E Unable to delete the specified REXX exec. It cannot be found.

Explanation: The exec load routine was invoked to delete (FREE) an exec, but the exec is currently not loaded under this task.

System action: The exec cannot be deleted.

User response: Before you try to delete (FREE) an exec, invoke the exec load routine with the "STATUS" function to determine if the exec is currently loaded or contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0420E Unable to serialize during the REXX exec load function *function*.

Explanation: The exec load routine was not able to serialize on a system resource when the routine was called for the specified function.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0421E Unable to release serialization during the REXX exec load function *function*.

Explanation: The exec load routine was not able to release serialization on a system resource when the routine was called for the specified function.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0422E Unable to obtain storage during the REXX exec load function *function*.

Explanation: The exec load routine was not able to obtain storage when it was called for the specified function.

System action: The function is not performed.

User response: Logon with a larger region size or contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0423E Invalid storage amount requested during the REXX exec load function *function*.

Explanation: The exec load routine was not able to obtain storage when it was called for the specified function. An invalid amount was requested. This is an internal system error.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0424E Caller of exec load routine must serialize when requesting the *function* function.

Explanation: The caller of the exec load routine must serialize on required system resources when invoking the exec load routine for the specified function.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0430E The specified exec load file *ddname* cannot be closed. It is not owned by the current task.

Explanation: The specified exec load file cannot be closed by this exec or by this task. The file is owned by a higher-level task and only the task that owns the file can close it.

System action: The file is not closed.

IRX0431E • IRX0440E

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0431E The specified exec load file *ddname* cannot be closed. It was not opened as an exec load file.

Explanation: The exec load routine cannot close the specified file. The file was not opened for the routine.

System action: The file is not closed.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0432E The specified exec load file *ddname* cannot be closed. It is not known to the current REXX environment.

Explanation: The exec load routine cannot close the specified exec load file. The file is not defined in the current language processor environment.

System action: The file is not closed.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0435E An invalid record was found during exec load. This is an internal error.

Explanation: An invalid record was found during the exec load process. This may be the result of a system overlay or a serious internal problem.

This problem can also indicate that the user or installation has concatenated both RECFM=VB and RECFM=FB data sets to your exec load library (typically SYSEXEC), or to your CLIST library (SYSPROC), or exec or CLIST libraries defined by the ALTLIB command.

Data sets with mixed record formats should not be concatenated to SYSEXEC or SYSPROC, nor to any of the exec or CLIST load data sets as defined by ALTLIB. Doing so may cause a variety of unpredictable results.

System action: The load function is terminated.

User response: Check your exec load DD, especially SYSEXEC, for invalid data set concatenations. If necessary, contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0440E No I/O buffer is available for exec load from file *file_name*. This is an internal error.

Explanation: No internal I/O buffer is available during exec load. This may be the result of a system overlay or serious internal problem. This is an internal system error.

System action: The load function is terminated.

User response: Contact your system programmer for assistance.

Module: IRXELOAD

Audience: REXX user

IRX0441E TSOLOAD is not a valid function request when the environment is not integrated into TSO/E.

Explanation: You attempted to use TSOLOAD, but the current language processor environment was not integrated into TSO/E.

System action: The TSOLOAD function is not performed.

User response: Use the LOAD function provided by the exec load routine.

Module: IRXLOAD

IRX0442E REXX exec member *exec_name* does not exist in the TSOLOAD search order.

Explanation: The exec load routine attempted to load the REXX exec member displayed in this message using the current TSO/E search order. This REXX exec member is not contained in any of the currently active load files.

System action: The exec is not loaded.

User response: Correct the member name of the exec or change the TSO/E search order that the exec load routine TSOLOAD function uses to load execs.

Module: IRXLOAD

Audience: REXX user

IRX0501E An unknown function request was passed to the REXX I/O routine. Function *function* is not supported.

Explanation: The REXX I/O routine was invoked for an unknown function.

System action: No function is performed.

User response: Correct the call to the REXX I/O routine, or contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0502E An attempt was made to 'READ' from file *ddname*, which is opened, but not for input. 'READ' is not allowed.

Explanation: The exec tried to read from the specified file, but the function is not allowed. The indicated file is not open for input.

System action: The READ function is not performed.

User response: If the indicated file is currently opened for 'WRITE', close it and reopen it for input, or update, or contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0503E An attempt was made to 'WRITE' to file *ddname* which is opened, but not for output. 'WRITE' is not allowed.

Explanation: The exec tried to write to the specified file, but the function is not allowed. The indicated file is not open for output.

System action: The WRITE function is not performed.

User response: If the indicated file is currently opened for 'READ', close it and reopen if for output, or update, or contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0509E Invalid record format for data set allocated to file *ddname*. RECFM must be fixed or variable. Spanned records or records with track overflow are not supported.

Explanation: A REXX data set has a non-valid record format. I/O is supported only to or from data sets with non-spanned fixed or variable record format. Spanned, track overflow, and undefined record formats are not supported.

System action: I/O is not performed.

User response: Check the record format of the indicated I/O file to ensure proper record format, or contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0510E Invalid record format for file *ddname*. RECFM may be F, FS, FB, FBS, V, VS, VB, VBS, or U with optional carriage control. Records with track overflow are not supported.

Explanation: A REXX data set has a non-valid record format. I/O is supported only to or from data sets with F, FS, FB, FBS, V, VS, VB, VBS, or U record formats. The record format may also include an optional carriage control. Records with track overflow are not supported.

System action: I/O is not performed.

User response: Check the record format of the indicated I/O file to ensure proper record format, or contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0511E File *ddname* having RECFM VS or VBS cannot be opened for update. It can only be opened for input or output.

Explanation: The REXX data set allocated to file *ddname* has a spanned record format, either VS, or VBS. It cannot be opened in update mode. However, it can be opened for input or output.

System action: I/O is not performed.

User response: Check the record format of the indicated I/O file to ensure proper record format. If it is correctly a VS or VBS file, you can separately read or write the file.

If you need to modify a valid VS or VBS file, you can read the entire data set into REXX variables, and close the input file, as:

```
"EXECIO * DISKR <ddname> (STEM rec. FINIS"
```

Then within your exec, update all rec.i record variables, as required. Finally rewrite the entire data set of N records (where N = rec.0) with the updated records, and close the file to complete the update as:

```
"EXECIO "N" DISKW <ddname> (STEM rec. FINIS"
```

Module: IRXIOGPT

Audience: REXX user

IRX0520E Unable to serialize during the REXX I/O function, *function*.

Explanation: The REXX I/O routine was unable to serialize when called for the specified function.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0521E Unable to release serialization during the REXX I/O function, *function*.

Explanation: The REXX I/O routine was unable to release serialization when called for the specified function.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0522E Unable to obtain storage during the REXX I/O function, *function*.

Explanation: The REXX I/O routine was unable to obtain storage when called for the specified function.

System action: The function is not performed.

User response: Log on with a larger region size, or contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0523E Invalid storage amount requested during the REXX I/O function, *function*.

Explanation: The REXX I/O routine was unable to obtain storage when called for the specified function. An amount that was not valid was requested. This is an internal error.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0524E Caller of REXX I/O routine must serialize when requesting the *function* function.

Explanation: The caller of the REXX I/O routine must serialize when invoking the REXX I/O routine for the specified function.

System action: The function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0530E Unable to close file *ddname*. It is owned by a higher task.

Explanation: The specified REXX I/O file cannot be closed by this exec or by this task. It is owned by a higher-level task and only the owning task may close the file.

System action: The file is not closed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0531E Unable to close file *ddname*. It was not opened by the REXX I/O routine.

Explanation: The specified file cannot be closed by the REXX I/O routine. It was not opened for I/O.

System action: The file is not closed.

User response: Contact your system programmer for assistance.

IRX0532E • IRX0540E

Module: IRXIOGPT

Audience: REXX user

IRX0532E Unable to close file *ddname*. It is not open.

Explanation: The specified REXX I/O file cannot be closed by the REXX I/O routine. It is not defined in the current REXX environment.

System action: The file is not closed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0533E Unable to READ and/or WRITE from exec. The *function* request is not allowed.

Explanation: This current exec has tried to either READ from a file or WRITE to a file. Either one or both of these functions is not permitted for execs in the current REXX environment. The function is not allowed.

System action: The function is not performed.

User response: Do not attempt to READ, WRITE, or both from execs in this environment, or contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0535E The REXX I/O service was called to WRITE a record but an invalid record was provided.

Explanation: A record that was not valid was found during a REXX I/O WRITE request. This may be the result of a system overlay, or other serious internal problem.

System action: The WRITE function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0536E Record cannot be updated. No record from file *ddname* has been read for update.

Explanation: The REXX I/O routine was called to update a record, from the specified file, but the update is not allowed because no record has been read for update. Update only allows the re-writing (in-place) of the last record read. The WRITE function is terminated.

System action: The WRITE function is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0540E No I/O buffer is available for input or output with file *ddname*.

Explanation: No internal I/O buffer is available during REXX I/O. This may be the result of a system overlay, or other serious internal problem. The REXX I/O function is terminated.

System action: I/O is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0541E Update failed. Number of record specified does not match number of last record read.

Explanation: The absolute number of the record to be updated does not match the number of the last record read. The update is not allowed.

This error may indicate multiple tasks are simultaneously processing the same file. The number of the last record read by the updating task may be out of sync with what it expects if another task is also reading the file with the same DCB.

System action: The update is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOGPT

Audience: REXX user

IRX0551E The exec load file *ddname* must be allocated to either a partitioned or sequential data set.

Explanation: The data set organization (DSORG) of the specified exec load file is not partitioned or sequential. No other data set organization is supported for the exec load file. An exec cannot be loaded from this file.

System action: The exec is not loaded.

User response: The exec load file must be allocated to one or more partitioned or sequential data sets. Allocate the exec load file to a data set or a concatenation of data sets with the appropriate data set organization, or contact your system programmer for assistance.

Module: IRXIOCDS

Audience: REXX user

IRX0552E The input or output file *ddname* is associated with a partitioned data set. A member name must be specified.

Explanation: The data set organization (DSORG) of the specified I/O file is partitioned. The name of the member to which I/O is to be performed must also be specified on the file allocation.

REXX I/O can be performed only to a file that is allocated to a sequential data set, or to a single member of a partitioned data set. When doing I/O to a partitioned data set member, you must allocate both the data set and the member. For example, using the TSO/E ALLOCATE command, allocate the input file REPORTDD to member JULY88 of the partitioned data set 'DEPTXYZ.REPORTS' as follows:

```
ALLOC FI(REPORTDD) DA('DEPTXYZ.REPORTS(JULY88)')+
SHR
```

System action: I/O is not performed.

User response: Allocate the input file correctly, or contact your system programmer for assistance.

Module: IRXIOCDS

Audience: REXX user

IRX0553E The input or output file *ddname* must be allocated to a sequential data set, or single member of a partitioned data set.

Explanation: The data set organization (DSORG) of the specified I/O file is not sequential or partitioned. I/O is supported only if the file is allocated to a sequential data set, or to a single member of a partitioned data set.

REXX I/O can be performed only to a file that is allocated to a sequential data set, or to a single member of a partitioned data set. When doing I/O to a partitioned data set member, you must allocate both the data set and the member. For example, using TSO/E's ALLOCATE command, allocate the input file REPORTDD to member JULY88 of the partitioned data set 'DEPTXYZ.REPORTS' as follows:

```
ALLOC FI(REPORTDD) DA('DEPTXYZ.REPORTS(JULY88)')+
SHR
```

System action: I/O is not performed.

IRX0554E • IRX0561E

User response: Allocate the input file correctly, or contact your system programmer for assistance.

Module: IRXIOCD5

Audience: REXX user

IRX0554E The exec load file *ddname* is not allocated. The REXX exec cannot be loaded.

Explanation: The specified exec load file has not been allocated. This file must be allocated before the exec load routine can find or load your exec.

System action: The exec cannot be loaded.

User response: Allocate the specified exec load file before trying to run your exec, or contact your system programmer for assistance.

Module: IRXIOCD5

Audience: REXX user

IRX0555E The input or output file *ddname* is not allocated. It cannot be opened for I/O.

Explanation: The specified REXX I/O file has not been allocated. It cannot be opened for REXX I/O.

System action: I/O is not performed.

User response: Allocate the specified REXX I/O file before trying to perform I/O, or contact your system programmer for assistance.

Module: IRXIOCD5

Audience: REXX user

IRX0556E Error on call to SVC99 to retrieve information about file *ddname*.

Explanation: An error occurred while using dynamic allocation (SVC99) to retrieve information about the specified file. This can occur when attempting to load an exec or when attempting to perform REXX I/O.

System action: I/O is not performed.

User response: Verify that the specified file has been properly allocated as an I/O file or as an exec load file, or contact your system programmer for assistance.

Module: IRXIOCD5

Audience: REXX user

IRX0560E Invalid service request was passed to REXX I/O linkage assist routine. Service *service_name* is not supported.

Explanation: The REXX I/O linkage assist routine has been invoked for an unsupported function. This is an internal error.

System action: No function is performed.

User response: Contact your system programmer for assistance.

Module: IRXIOLAR

Audience: REXX user

IRX0561E Error during READ or GET from file *ddname*. Record read exceeds the internal buffer size.

Explanation: The record read by the REXX I/O linkage assist routine during a READ or GET request is larger than what will fit in the buffer provided. Storage may have been overlaid. This is an internal error. This can occur when attempting to load an exec or when attempting to perform REXX I/O.

System action: I/O is not performed.

User response: Contact your system programmer for assistance.

Module: IRXIOLAR

Audience: REXX user

IRX0562E **Abnormal completion of the *service_name* Data Management macro.**

Explanation: An error occurred while trying to perform the specified data management service. The service terminated abnormally.

This message may be accompanied by a more specific system message from the REXX I/O linkage assist routine's SYNAD error routine.

This message is also issued when the system searches a ddname for an exec, and incompatible data sets were allocated to the ddname. For example, the system issues this message if you allocate both partitioned and sequential data sets to SYSEXEC. In this case, the system does not search SYSEXEC. The failing macro might be either OPEN or FIND.

System action: The data management service *service_name* did not complete.

User response: Try to correct the condition causing the error as described by the associated SYNAD error message, or contact your system programmer for assistance.

Correct the data set allocations to the ddname from which the execs are loaded.

Module: IRXIOLAR

Audience: REXX user

IRX0563E **Unable to open file *ddname*.**

Explanation: An error occurred while trying to open the specified file using the Data Management OPEN macro. This message may be accompanied by other messages that describe the cause of the open failure.

System action: The file is not opened.

User response: Correct the error condition, or contact your system programmer for assistance.

Module: IRXIOLAR

Audience: REXX user

IRX0564E **Unable to close file *ddname*.**

Explanation: An error occurred while trying to close the specified file using the Data Management CLOSE macro. This message may be accompanied by other messages that describe the cause of the close failure.

System action: The file is not closed.

User response: Correct the error condition, or contact your system programmer for assistance.

Module: IRXIOLAR

Audience: REXX user

IRX0565E *job_name, stepname, uad, dt, dd_name, opernm, error_description, trkaddr_blknbr, accmth*

Explanation: An error occurred while the REXX I/O linkage assist routine was trying to perform some data management service. This is an error message returned by the SYNADAF macro. It contains information formatted as follows:

- *jobname* is the job name
- *stepname* is the stepname
- *uad* is the unit address
- *dt* is the device type
- *dd_name* is the ddname
- *opernm* is the operation attempted
- *error_description* is the error description
- *trkaddr_blknbr* is the track address and the block number
- *accmth* is the access method.

IRX0566E • IRX0568E

For more information about the SYNADAF macro, see *z/OS DFSMS Macro Instructions for Data Sets*.

System action: I/O is not performed.

User response: Try to correct the error condition, or contact your system programmer for assistance.

Module: IRXIOLAR

Audience: REXX user

IRX0566E Unable to perform I/O operation on file *file*. Data set number *n* is empty or contains no end-of-file mark.

Explanation: An attempt was made to open a file for input. A data set that is allocated to the file has no end-of-file mark. It is possible that this data set was allocated with no data ever having been written to it. The *n*th data set concatenated to the file listed in the message was the data set with no end-of-file mark. The file was not successfully opened for the I/O operation.

A data set with no end-of-file is usually a newly allocated empty non-SMS managed data set which has never been written to. If you need to allow for a possible empty sequential data set in your file concatenation, insure that the data set is allocated as an SMS managed data set.

REXX I/O and REXX EXECIO allow an empty or null data set within a file concatenation if that empty data set is SMS managed. (SMS managed sequential data sets are those allocated with a Management Class specified.)

System action: Exec processing continues.

User response: Determine why your exec is trying to read from a file that never contained data. If data is supposed to be in the file, determine why no data exists.

If you need to allow a possibly empty data set to exist within the file concatenation to be read, insure that this data set is allocated as an SMS managed data set.

Module: IRXIOLAR

Audience: REXX user

IRX0567E Unable to perform I/O operation on file *file*. OBTAIN error code *error_code* was received for data set number *n*.

Explanation: An attempt was made to obtain information on a data set. An error occurred in the OBTAIN system service. The error occurred while attempting to obtain information on the *n*th data set in the file listed in the message. The file was not successfully opened for the I/O operation.

System action: Exec processing continues.

User response: Check the return code from the OBTAIN service and determine the reason for the failure.

Module: IRXIOLAR

Audience: REXX user

IRX0568E *file* was not found.

Explanation: An attempt was made to obtain information on a data set allocated to the file *file*. While searching the system for file *file*, it could not be located. The file was not successfully opened for the I/O operation.

System action: Exec processing continues.

User response: Contact your system programmer for assistance.

Module: IRXIOLAR

Audience: REXX user

IRX0570E Unable to obtain or free storage for terminal I/O.

Explanation: A request was made in an exec to read from the REXX input stream and virtual storage was not available.

System action: I/O is not performed.

User response: Try to correct the error condition, or contact your system programmer for assistance.

Module: IRXSYSCO

Audience: REXX user

IRX0571E Unable to read from or write to the terminal for the current exec.

Explanation: An error occurred when a request was made in an exec to read from or write to the terminal. This can be an internal error or an error in the PUTLINE or GETLINE service routine.

System action: I/O is not performed.

User response: Contact your system programmer for assistance.

Module: IRXSYSCO

Audience: REXX user

IRX0572E Invalid function request.

Explanation: A function that was not valid was passed to an I/O routine.

System action: I/O is not performed.

User response: Try to correct the error condition, or contact your system programmer for assistance.

Module: IRXSYSCO

Audience: REXX user

IRX0601E EXECIO "lines" positional parameter is not valid. Specify * or a number.

Explanation: The first EXECIO positional parameter must specify the number of lines to be processed by EXECIO.

An * means that end-of-file terminates the EXECIO DISKR or DISKRU operation, and a null line or an uninitialized STEM variable terminates an EXECIO DISKW operation. A number indicates an exact number of lines to process before EXECIO terminates.

System action: EXECIO terminates.

User response: Specify either * or a number.

Module: IRXEXPR

Audience: REXX user

IRX0602E EXECIO "lines" positional parameter is missing.

Explanation: The first EXECIO positional parameter is required, and must specify the number of lines to be processed by EXECIO. Specify either * or a number.

An * means that end-of-file terminates the EXECIO DISKR or DISKRU operation, and a null line or an uninitialized STEM variable terminates an EXECIO DISKW operation. A number indicates an exact number of lines to process before EXECIO terminates.

System action: EXECIO terminates.

User response: Specify either * or a number.

Module: IRXEXPR

Audience: REXX user

IRX0603E • IRX0607E

IRX0603E EXECIO “operation” positional parameter is not valid. Specify DISKR, DISKRU, or DISKW.

Explanation: The second positional parameter on the EXECIO command is not valid. It must specify one of the valid operations to be performed.

System action: EXECIO terminates.

User response: Specify DISKR (input) to read a file, DISKRU (update) to update a file, or DISKW (output) to write a file.

Module: IRXEXPR

Audience: REXX user

IRX0604E EXECIO “operation” positional parameter is missing. Specify DISKR, DISKRU, or DISKW.

Explanation: The second positional parameter on the EXECIO command is missing. It must be a valid “operation” identifier: DISKR, DISKRU, or DISKW. It is required and must specify one of the valid operations to be performed.

System action: EXECIO terminates.

User response: Specify DISKR (input) to read a file, DISKRU (update) to update a file, or DISKW (output) to write a file.

Module: IRXEXPR

Audience: REXX user

IRX0605E EXECIO “ddname” positional parameter is not valid.

Explanation: The third positional parameter on the EXECIO command is not a valid “ddname” (or file).

System action: EXECIO terminates.

User response: Specify a 1 to 8 character “ddname” (file name) to which or from which I/O is to be performed. The DD should be allocated to a sequential data set, or to a single member of a partitioned data set.

Module: IRXEXPR

Audience: REXX user

IRX0606E EXECIO “ddname” positional parameter is missing.

Explanation: The third positional parameter on the EXECIO command is missing. This parameter is required.

System action: EXECIO terminates.

User response: Specify a 1 to 8 character “ddname” (file name) to which or from which I/O is to be performed. The DD should be allocated to a sequential data set, or to a single member of a partitioned data set.

Module: IRXEXPR

Audience: REXX user

IRX0607E EXECIO “linenum” positional parameter is not valid. Specify a number or nothing.

Explanation: The fourth positional parameter on the EXECIO command, if specified, must be a valid number. This parameter represents the record number at which reading is to begin for a DISKR or DISKRU operation. This parameter is not valid when DISKW is specified.

System action: EXECIO terminates.

User response: Specify a “linenum” value, or specify nothing.

Module: IRXEXPR

Audience: REXX user

IRX0608E No EXECIO positional parameters were found. Three are required.

Explanation: No positional parameters were found for the EXECIO command. However, you must specify at least three positional parameters.

System action: EXECIO terminates.

User response: Specify a number or * as the first positional parameter to indicate the number of lines to process. Specify DISKR, DISKRU, or DISKW (the operation) as the second positional parameter. Specify the "ddname" to or from which I/O is to be done as the third positional parameter.

Module: IRXEXPRS

Audience: REXX user

IRX0609E Too many EXECIO positional parameters found. A maximum of four may be specified.

Explanation: An unknown positional parameter was specified.

System action: EXECIO terminates.

User response: You may specify a maximum of four positional parameters. Remove any extra parameters. If you want to specify EXECIO options, they must follow the positional parameters, and are delimited from the positional parameters by a left parenthesis "(".

Module: IRXEXPRS

Audience: REXX user

IRX0610E No STEM name was found after EXECIO STEM option.

Explanation: No STEM variable name was specified after the EXECIO "STEM" option.

System action: EXECIO terminates.

User response: Specify the name of the STEM variable after the "STEM" option of the EXECIO command. A STEM variable name may be from 1 to 240 characters in length.

Module: IRXEXPRS

Audience: REXX user

IRX0611E EXECIO STEM option is specified more than once.

Explanation: The EXECIO STEM option can only be specified once on the EXECIO command.

System action: EXECIO terminates.

User response: Correct the EXECIO command so that STEM is only specified once.

Module: IRXEXPRS

Audience: REXX user

IRX0612E EXECIO STEM name is not valid or is too long.

Explanation: The specified EXECIO STEM name is not valid or is too long.

System action: EXECIO terminates.

User response: Valid names are 1 to 240 characters in length, and must be valid REXX variable names.

Module: IRXEXPRS

Audience: REXX user

IRX0613E • IRX0617E

IRX0613E EXECIO FIFO or LIFO options are not allowed with STEM.

Explanation: The EXECIO FIFO or LIFO option was specified with the STEM option. However, FIFO and LIFO cannot be specified with the STEM option.

System action: EXECIO terminates.

User response: Remove either the STEM option or the FIFO/LIFO option.

Module: IRXEXPR

Audience: REXX user

IRX0614E EXECIO FIFO or LIFO options are not allowed with DISKW.

Explanation: The EXECIO FIFO or LIFO option was specified with the DISKW "operation". However, FIFO and LIFO cannot be specified with DISKW.

System action: EXECIO terminates.

User response: Correct the EXECIO command so FIFO and LIFO are not specified when DISKW is specified.

Module: IRXEXPR

Audience: REXX user

IRX0615E EXECIO "linenum" parameter is not allowed with DISKW.

Explanation: The EXECIO "linenum" parameter was specified with the DISKW "operation". However, "linenum" cannot be specified with DISKW.

System action: EXECIO terminates.

User response: Correct the EXECIO command so that the "linenum" parameter is not specified when DISKW is specified.

Module: IRXEXPR

Audience: REXX user

IRX0616E EXECIO SKIP option is not allowed with DISKW.

Explanation: The EXECIO SKIP option was specified with the DISKW "operation". However, SKIP cannot be specified with DISKW.

System action: EXECIO terminates.

User response: Correct the EXECIO command so that the SKIP option is not specified when DISKW is specified.

Module: IRXEXPR

Audience: REXX user

IRX0617E EXECIO error. Unrecognized or ambiguous keyword found.

Explanation: An unknown or ambiguous EXECIO keyword option was found on the EXECIO command. It cannot be processed. An unknown option is something other than the valid options FIFO, LIFO, STEM, SKIP, FINIS, and OPEN. An ambiguous option is something like FI (which may be either FIFO or FINIS).

System action: EXECIO terminates.

User response: Change the EXECIO keyword to a valid option.

Module: IRXEXPR

Audience: REXX user

IRX0650E EXECIO internal error. Report the problem to IBM.

Explanation: The EXECIO routine detected an internal error and immediately terminated processing.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0651E EXECIO error. STEM variable name is not valid.

Explanation: A REXX variable access routine (IKJCT441 or IRXEXCOM) has detected a non-valid REXX variable name used with the EXECIO "STEM" option.

System action: EXECIO terminates.

User response: Specify a valid REXX variable name after the EXECIO "STEM" option. The STEM variable name may be from 1 to 240 characters in length.

Module: IRXEXIO

Audience: REXX user

IRX0652E EXECIO error while trying to fetch a REXX variable.

Explanation: An error occurred in a REXX variable access routine (IKJCT441 or IRXEXCOM) during a variable "fetch" operation from the EXECIO routine. The variable value was not obtained successfully.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0653E EXECIO error while trying to store a REXX variable.

Explanation: An error occurred in a REXX variable access routine (IKJCT441 or IRXEXCOM) during a variable "store" (or "set") operation from the EXECIO routine. The variable value was not set successfully.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0654E EXECIO error. An attempt was made to read or write to an unusable record.

Explanation: An unusable record was encountered while trying to read or write a record during EXECIO processing. This is an internal error.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0660E • IRX0671E

IRX0660E EXECIO error. Unable to serialize.

Explanation: The EXECIO routine was unable to serialize. EXECIO processing is not performed.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0661E EXECIO error. Unable to release serialization.

Explanation: The EXECIO routine was unable to release serialization.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0662E EXECIO error. Unable to obtain storage.

Explanation: The EXECIO routine was unable to obtain storage.

System action: EXECIO terminates.

User response: Log on with a larger region size, or contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0663E EXECIO error. Invalid storage amount requested.

Explanation: The EXECIO routine was unable to obtain storage. An amount was requested that is not valid. This is an internal error.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0670E EXECIO error while trying to GET or PUT a record.

Explanation: The REXX I/O routine returned a bad return code to the EXECIO routine during an I/O operation.

This message may be accompanied by another message (from the REXX I/O routine) that more fully describes the error condition.

System action: EXECIO terminates.

User response: Try to correct the error condition, or contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0671E EXECIO error while trying to close a DD.

Explanation: The REXX I/O routine returned a bad return code to the EXECIO routine during a 'CLOSE' request. The specified file cannot be closed by this exec.

This message may be accompanied by another message from the REXX I/O routine which more fully describes the error condition.

A likely cause of this error is attempting to close a file that was opened by a higher-level task. You may have specified the EXECIO "FINIS" option or the "linenum" positional parameter for a file (ddname) that was opened under another task. However, you should specify only a file that has not yet been opened, or that was opened at the current task level when using the "FINIS" option or the "linenum" parameter.

Note: Both "FINIS" and "linenum" cause EXECIO to attempt to close the specified file. However, EXECIO can only close files that were opened at the same task level as that of the currently executing exec.

System action: EXECIO terminates.

User response: Contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0672E EXECIO error while trying to get an element from the data stack.

Explanation: The stack routine returned a bad return code to the EXECIO routine while trying to get an element from the data stack or default input file.

This message may be accompanied by another message that more fully describes the error condition.

System action: EXECIO terminates.

User response: Try to correct the error condition, or contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0673E EXECIO error while trying to put an element on the data stack.

Explanation: The stack routine has returned a bad return code to the EXECIO routine while trying to add an element to the data stack

This message may be accompanied by another message from the stack routine that more fully describes the error condition.

System action: EXECIO terminates.

User response: Try to correct the error condition, or contact your system programmer for assistance.

Module: IRXEXIO

Audience: REXX user

IRX0674E EXECIO is unable to open file *ddname* for DISKR or DISKRU. The file is already open, but not for input.

Explanation: The EXECIO routine tried to open the specified file for DISKR or DISKRU, but the file is already open in a mode that is not compatible with DISKR or DISKRU. Most likely, this file is open for DISKW.

System action: The open for DISKR or DISKRU is not performed. The file remains open in the mode in which it was opened before this open request.

User response: First close the file. Then reissue the EXECIO open request.

Module: IRXEXIO

Audience: REXX user

IRX0675E EXECIO is unable to open file *ddname* for DISKW. The file is already open, but not for output.

Explanation: The EXECIO routine tried to open the specified file for DISKW, but the file is already open in a mode that is not compatible with DISKW. Most likely, this file is open for DISKR.

System action: The open for DISKW is not performed. The file remains open in the mode in which it was opened before this open request.

IRX0700I • IRX0751I

User response: First close the file. Then reissue the EXECIO open request.

Module: IRXEXIO

Audience: REXX user

IRX0700I A REXX exec is executing under the REXX environment.

Explanation: The REXX language processor environment cannot be terminated because an exec is executing under the environment.

System action: The REXX language processor environment is not terminated.

User response: Terminate the language processor environment only after all execs have completed.

Module: IRXITERM

Audience: REXX user

IRX0701I The REXX environment has dependent environment(s).

Explanation: The REXX language processor environment was the first environment initialized under the task, but is not the last remaining REXX environment under the task. The first REXX environment initialized on a task must be the last REXX environment terminated on the task.

System action: The REXX language processor environment is not terminated.

User response: Terminate the first REXX environment established under a task only after all other REXX environments on the task have been terminated.

Module: IRXITERM

Audience: REXX user

IRX0702I IRXTERMX returned a non-zero return code.

Explanation: The REXX language processor environment termination exit routine (IRXTERMX) returned a non-zero return code.

System action: The REXX language processor environment is not terminated.

User response: Contact your system programmer for assistance.

Module: IRXITERM

Audience: REXX user

IRX0750I The address environment entry cannot be found, added or deleted.

Explanation: The IRXSUBCM routine was called to change, add, or delete an entry in the host command environment table SUBCOMTB. The entry was either not found in the table or could not be added to or deleted from the table. The request to update the SUBCOMTB table is not performed. The most likely reason for this error is that the parameters were specified incorrectly on the call to IRXSUBCM.

System action: The table is not updated.

User response: Check that the function (add, delete, update, or query), address, length, and address environment name parameters were specified correctly on the call or contact your system programmer for assistance.

Module: IRXESUBC

Audience: REXX user

IRX0751I The REXX immediate command cannot be performed.

Explanation: An immediate command (HI, HT, RT, TS, TE) cannot be performed because an immediate command that was not valid was passed to the IRXIC routine.

System action: The immediate command is not performed and IRXIC processing ends.

User response: Verify the parameters passed to IRXIC and contact your system programmer for assistance.

Module: IRXEIC

Audience: REXX user

IRX0760E An error occurred while retrieving the result of a REXX function.

Explanation: The get result routine (IRXRLT) encountered an error while attempting to retrieve the REXX evaluation block. One of the following alternate messages will accompany this primary message, and will describe the error in more detail.

- IRX0761E
- IRX0762E
- IRX0763E

System action: The system action will vary depending on the particular error found. See the alternate message for details.

User response: Contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0761E A data area to hold the result was not supplied by the caller.

Explanation: The parameter that should contain the address of the evaluation block supplied by the caller, into which the REXX evaluation block will be copied, is zero.

System action: No data is moved. The REXX evaluation block remains intact. An error code is passed to the caller.

User response: Call the get result routine (IRXRLT) again, supplying the address of an evaluation block large enough to contain the entire result. Or, contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0762E The REXX evaluation block is not valid.

Explanation: An error has been detected in the REXX evaluation block supplied by the system. The entire result is considered unreliable.

System action: No data is moved. The REXX evaluation block is deleted. An error code is passed to the caller.

User response: Contact the system programmer for the installation.

Module: IRXERSLT

Audience: REXX user

IRX0763E The GETRLT parameter is not valid while an exec is executing.

Explanation: The get result routine may not be called with the GETRLT parameter while an exec is executing. This operation is valid only after all execs running under the current environment have completed.

The application must be modified to call the get result routine with the GETRLT parameter only after all execs running under the current environment have completed.

System action: No data is moved. An error code is passed to the caller.

User response: Contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0765E An error occurred while obtaining a new REXX evaluation block.

Explanation: The get result routine (IRXRLT) encountered an error while attempting to replace the REXX evaluation block with a new one. One of the following alternate messages will accompany this primary message, and will describe the error in more detail.

- IRX0766E
- IRX0767E
- IRX0768E

System action: The system action will vary depending on the particular error found. See the alternate message for details.

User response: Contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0766E The GETBLOCK parameter is not valid under the current operation.

Explanation: The get result routine may only be called with the GETBLOCK parameter from an external function or subroutine. It may not be called when the REXX exec is a command, or when no exec is executing under the current environment.

The application must be modified to call the get result routine with the GETBLOCK parameter only from an external function or subroutine.

System action: A new evaluation block is not obtained. The original REXX evaluation block remains intact. An error code is passed to the caller.

User response: Contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0767E There was insufficient storage available for the new REXX evaluation block.

Explanation: The get result routine could not obtain the amount of storage requested for the new REXX evaluation block.

System action: A new evaluation block is not obtained. The original REXX evaluation block remains intact. An error code is passed to the caller.

User response: Verify the length of the data area requested for the new REXX evaluation block. Or, contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0768E The length specified for the new REXX evaluation block is not valid.

Explanation: The parameter that should contain the length, in bytes, of the requested data area for the new REXX evaluation block is negative or greater than the maximum allowed.

System action: A new evaluation block is not obtained. The original REXX evaluation block remains intact. An error code is passed to the caller.

User response: Verify the length of the data area requested for the new REXX evaluation block. Or, contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0770E An error occurred during a request for the REXX evaluation block.

Explanation: The get result routine encountered an error that prevents it from performing any type of service. Alternate message IRX0771E or IRX0772E will accompany this primary message, and will describe the error in more detail.

System action: The system action will vary depending on the particular error found. See the alternate message for details.

User response: Contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0771E *Function is not a valid function for the get result routine.*

Explanation: The parameter that should contain the function to be performed by the get result routine did not match the allowable values.

System action: An error code is passed to the caller.

User response: Verify the value passed in the function field of the parameter list to the get result routine (IRXRLT). Or, contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0772E The parameter list to IRXRLT is invalid.

Explanation: The parameter list to the get result routine (IRXRLT) is not valid.

System action: IRXRLT processing terminates.

User response: Verify the values passed in the parameter list to the get result routine (IRXRLT). Or, contact the author of the application that called the get result service routine.

Module: IRXERSLT

Audience: REXX user

IRX0798I The REXX environment cannot be terminated.

Explanation: The REXX language processor environment cannot be terminated. Possible reasons are:

- Recovery cannot be established
- Storage cannot be obtained
- The module cannot be loaded
- Serialization cannot be established
- A REXX exec is still executing.

System action: The REXX language processor environment is not terminated.

User response: Contact your system programmer for assistance.

Module: IRXITERM

Audience: REXX user

IRX0801E Unable to serialize or release serialization when accessing the TSO/E data stack.

Explanation: The data stack routine was unable to either serialize or release serialization when accessing the data stack.

System action: Data stack processing terminates.

User response: Contact the system programmer for the installation.

Module: IRXESTK

IRX0802E • IRX0806E

Audience: REXX user

IRX0802E **Storage not available.**

Explanation: Dynamic storage was not available for a stack control block or element.

System action: Data stack processing terminates.

User response: Increase the region size parameter on the LOGON panel or contact your system programmer for assistance.

Module: IRXESTK

Audience: REXX user

IRX0803E **Invalid stack function, *function* requested.**

Explanation: A non-supported function request was specified in the call to the data stack routine.

System action: Data stack processing terminates.

User response: Contact your system programmer for assistance.

Module: IRXESTK

Audience: REXX user

IRX0804E **Serialization control was not obtained prior to executing a data stack function.**

Explanation: The INIT or TERM function was requested in the call to the data stack routine. The caller did not have serialization control.

System action: Data stack processing terminates.

User response: Contact your system programmer for assistance.

Module: IRXESTK

Audience: REXX user

IRX0805E **The stack that was associated with the active environment block at initialization no longer exists.**

Explanation: The data stack that was originally in use when this exec or function was started no longer exists. This can be caused by establishing multiple REXX environments and not requesting their termination in the reverse order of their creation.

System action: Data stack processing terminates.

User response: Contact your system programmer for assistance.

Module: IRXESTK

Audience: REXX user

IRX0806E **Either the stack marker counter was not correct or a stack function was requested before the stack was initialized.**

Explanation: Either an internal control block error in the data stack was detected, or stack processing was called to process a REXX environment whose stack was not initialized.

System action: Data stack processing terminates.

User response: Contact your system programmer for assistance.

Module: IRXESTK

Audience: REXX user

IRX0810E Table synchronization error for the current ADDRESS environment.

Explanation: The host command in the current exec could not be processed because initialization for the active ADDRESS environment was not complete.

System action: The host command environment routine terminates.

User response: Contact your system programmer for assistance.

Module: IRXSYSHO

Audience: REXX user

IRX0811E Accessing of exec variables was not complete after ADDRESS environment *environment* completed.

Explanation: A problem occurred in synchronizing the access to exec variables when calling a host command for the specified ADDRESS environment.

System action: The host command environment routine terminates.

User response: Contact your system programmer for assistance.

Module: IRXSYSHO

Audience: REXX user

IRX0812E Exec variables were being accessed while the exec was executing.

Explanation: A problem occurred in synchronizing the access to exec variables when returning from an external function, subroutine, or host command.

System action: The host command environment routine or function search routine terminates.

User response: Contact your system programmer for assistance.

Module: IRXSYSFU IRXSYSHO

Audience: REXX user

IRX0813E System error while attempting to load ADDRESS environment *environment*.

Explanation: The ADDRESS environment could not be loaded. Either an I/O error occurred, or the environment name could not be found.

System action: The host command environment routine terminates.

User response: Contact your system programmer for assistance.

Module: IRXSYSHO

Audience: REXX user

IRX0814E Accessing of exec variables was not complete after external function/subroutine completed.

Explanation: A problem occurred in synchronizing the access to exec variables when calling or returning from an external function, subroutine, or host command.

System action: The host command environment routine or function search routine terminates.

User response: Contact your system programmer for assistance.

Module: IRXSYSFU

Audience: REXX user

IRX0820E The requested routine *routine_name* could not be found

Explanation: The routine name specified could not be found in the host command environment table.

System action: The host command environment routine terminates.

User response: Make the necessary corrections to the routine name.

Module: IRXAPPC

Audience: Application programmer

IRX0821E The number of parameters specified on the *routine_name* routine is incorrect

Explanation: Either too many or too few parameters were specified for the routine invocation.

System action: The host command environment routine terminates.

User response: Supply the correct number of parameters for the routine invocation.

Module: IRXAPPC

Audience: Application programmer

IRX0822E The variable or value specified for parameter *parameter* is not valid

Explanation: Either the variable name specified for the parameter is not valid or the value of the variable for this parameter is not valid and cannot be processed.

System action: The host command environment routine terminates.

User response: Make the necessary corrections to the exec.

Module: IRXAPPC

Audience: Application programmer

IRX0823I The requested host command environment, *environment_name*, is not supported on the level of MVS installed on this system.

Explanation: The user attempted to enter an ADDRESS CPICOMM, ADDRESS LU62, or APPCMVS host command in either a pre-MVS/ESA SP 4.2.0 or a pre-MVS/ESA SP 4.3.0 environment. These host command environments are not supported in pre-MVS/ESA SP 4.2.0 or pre-MVS/ESA SP 4.3.0 as follows: ADDRESS CPICOMM, and ADDRESS LU62 can be entered only in MVS/ESA SP 4.2.0 or later; ADDRESS APPCMVS can be entered only in MVS/ESA SP 4.3.0 or later.

System action: The host command environment routine terminates.

User response: Make the necessary corrections to the exec.

Module: IRXAPPC

Audience: Application programmer

IRX0824E The requested callable service *callable_service* is not supported on the level of MVS installed on this system.

Explanation: A callable service invocation was attempted on a level of MVS that does not support the requested callable service.

System action: The host command environment routine terminates.

System programmer response: The REXX exec invoking the callable service should be executed on the level of MVS which supports the specified callable service.

User response: Change or remove the invocation for the specified callable service.

Module: IRXAPPC

Audience: REXX user

IRX0900E REXX initialization failed with return code *retcode* and reason code *reascode*.

Explanation: The IRXINIT REXX initialization routine failed with the return code and reason code specified in the message. Refer to *z/OS TSO/E REXX Reference* under the description of IRXINIT for more information about the meaning of the specified return code and reason code.

System action: IRXINIT terminates unsuccessfully.

User response: After referring to the return code and reason code information, correct the call to IRXINIT. You may need to contact your system programmer for assistance.

Module: IRXINIT or IRXITPA.

Audience: REXX user or system programmer. This message usually goes to a TSO/E user, but it may also be issued to the system CONSOLE during an unsuccessful TSO/E user LOGON.

IRX0901E REXX initialization failed with return code *retcode* and reason code *reascode*. Module *modname* could not be loaded.

Explanation: The IRXINIT REXX initialization routine failed with the return code 20 and reason code 21 as specified in the message. Refer to *z/OS TSO/E REXX Reference* under the description of IRXINIT for more information about the meaning of the specified return code and reason code.

The error occurred because the specified module could not be loaded. If you recently changed this module make sure it is linked correctly and is available in a load library accessible to IRXINIT.

This error sometimes occurs when the name of a new function package routine (or other routine) is added to some REXX parameter module, but the specified load module is not made available in one of the accessible load libraries.

Note: A REXX parameter module is a non-executable module that is passed to IRXINIT during REXX environment initialization to describe and control the attributes of the REXX environment being initialized. (Examples of REXX parameter modules include IRXPARMS, IRXTSPRM, IRXISPRM.)

System action: IRXINIT terminates unsuccessfully.

User response: After referring to the return code and reason code information and missing module information, make the specified load module available. You may want to place the module in a STEPLIB or in a system load library. You may need to contact your system programmer for assistance.

Module: IRXINIT or IRXITPA.

Audience: REXX user or system programmer. This message usually goes to a TSO user, but it may also be issued to the system CONSOLE during an unsuccessful TSO/E user LOGON.

IRX0910I THE EXECUTIL COMMAND FAILED +

Explanation: The EXECUTIL command failed.

System action: The EXECUTIL command processor terminates.

User response: To find out more information about why it failed, type a ? to display an additional message. One of the following additional messages will describe the error in more detail:

- IRX0911I
- IRX0912I
- IRX0913I
- IRX0917I
- IRX0918I

Module: IRXTUTIL

Audience: REXX user

IRX0911I PARSE COMPLETED WITH A RETURN CODE OF *return_code*

Explanation: The parse service routine returned a non-zero return code.

System action: The EXECUTIL command processor terminates.

User response: Reissue the EXECUTIL command. If the error persists, contact your system programmer for assistance.

Module: IRXTUTIL

Audience: REXX user

IRX0912I THE *command* IMMEDIATE COMMAND FAILED

Explanation: An error was detected while attempting to process the specified immediate command for EXECUTIL.

System action: The EXECUTIL command processor terminates.

User response: Reissue the EXECUTIL command. If the error persists, contact your system programmer for assistance.

Module: IRXTUTIL

Audience: REXX user

IRX0913I THE RENAME SUBCOMMAND FAILED

Explanation: An error was detected while attempting to process the RENAME subcommand of EXECUTIL.

System action: The EXECUTIL command processor terminates.

User response: Reissue the EXECUTIL command. If the error persists, contact your system programmer for assistance.

Module: IRXTUTIL

Audience: REXX user

IRX0914I MODULE *module* CANNOT BE LOADED INTO STORAGE

Explanation: The specified module cannot be loaded into storage because the module was not found.

System action: The EXECUTIL command processor terminates.

User response: Contact your system programmer for assistance.

Module: IRXTREN

Audience: REXX user

IRX0915I FUNCTION *function* NOT FOUND

Explanation: The specified function name cannot be found in the function package table.

System action: The EXECUTIL command processor terminates.

User response: Reissue the EXECUTIL command with a valid function name.

Module: IRXTREN

Audience: REXX user

IRX0916I ERROR ENCOUNTERED WHILE SEARCHING FOR FUNCTION

Explanation: While searching for an entry in the function package table, an error was encountered.

System action: The EXECUTIL command processor terminates.

User response: Contact your system programmer for assistance.

Module: IRXTREN

Audience: REXX user

IRX0917I **UNABLE TO ESTABLISH A RECOVERY ENVIRONMENT. ESTAE MACRO RETURN CODE IS**
return_code.

Explanation: Because the return code from the ESTAE macro is greater than zero, a recovery environment cannot be established.

System action: The EXECUTIL command processor terminates.

User response: Contact your system programmer for assistance.

Module: IRXTUTIL

Audience: REXX user

IRX0918I **A REXX ENVIRONMENT DOES NOT EXIST.**

Explanation: A REXX environment is required for running the EXECUTIL command. The environment does not exist.

System action: The EXECUTIL command processor terminates.

System programmer response: A REXX language processor environment is required for running the EXECUTIL command processor. A language processor environment may not exist for the following reasons:

- Your installation is using a user-written terminal monitor program (TMP) and the TMP does not initialize a language processor environment. If you do not use the TMP that TSO/E provides, TSO/E does not automatically initialize a language processor environment. The user-written TMP must call the REXX initialization routine, IRXINIT, to initialize an environment for processing REXX execs.
- A REXX language processor environment previously existed on a specific task level and handled REXX processing. The task was terminated, which means the language processor environment was also terminated. A REXX language processor environment is available only as long as the task at which the environment was created exists. For example, you can use the TSO/E environment service, IKJTSOEV, to create a TSO/E environment in a non-TSO/E address space. IKJTSOEV also creates a language processor environment at the same task level at which you invoke IKJTSOEV. When the task at which you created the TSO/E environment is terminated, the language processor environment is terminated. The language processor environment that IKJTSOEV creates is available only as long as the task at which you invoke IKJTSOEV exists. See *z/OS TSO/E Programming Services* for more information about the TSO/E environment service, IKJTSOEV.

For more information about language processor environments, see *z/OS TSO/E REXX Reference*.

User response: Contact your system programmer to diagnose problems with the availability of a language processor environment for REXX.

Module: IRXTUTIL

Audience: REXX user

IRX0920I **ENTER HI TO END, A NULL LINE TO CONTINUE, OR AN IMMEDIATE COMMAND +**

Explanation: You pressed the attention key while running a REXX exec.

System action: The system waits for a user response.

User response: To end the attention interrupt, enter HI. To continue processing, enter a null line. To perform other actions, enter one of the following:

- HT - halt typing
- RT - resume typing
- TS - trace start
- TE - trace end

Module: IRXATTN

Audience: REXX user

IRX0921I ATTENTION PROCESSING FAILED

Explanation: You pressed the attention key, but attention processing failed.

System action: Processing continues.

User response: To find out more information about why it failed, type a ? to display an additional message. One of the following additional messages will describe the error in more detail:

- IRX0922I
- IRX0923I
- IRX0924I
- IRX0925I

Module: IRXATTN

Audience: REXX user

IRX0922I PUTGET COMPLETED WITH A RETURN CODE OF *return_code*

Explanation: Attention processing failed because the PUTGET service failed with the specified return code.

System action: Processing continues.

User response: See *z/OS TSO/E Programming Services* for an explanation of the return code or contact your system programmer for assistance.

Module: IRXATTN

Audience: REXX user

IRX0923I SCAN COMPLETED WITH A RETURN CODE OF *return_code*

Explanation: Attention processing failed because the command scan service routine failed with the specified return code.

System action: Processing continues.

User response: See *z/OS TSO/E Programming Services* for an explanation of the return code or contact your system programmer for assistance.

Module: IRXATTN

Audience: REXX user

IRX0924I PARSE COMPLETED WITH A RETURN CODE OF *return_code*

Explanation: Attention processing failed because the parse service routine failed with the specified return code.

System action: Processing continues.

User response: See *z/OS TSO/E Programming Services* for an explanation of the return code or contact your system programmer for assistance.

Module: IRXATTN

Audience: REXX user

IRX0925I STORAGE COULD NOT BE OBTAINED

Explanation: Attention processing failed because virtual storage is not available.

System action: Processing continues.

User response: Contact your system programmer for assistance.

Module: IRXATTN

Audience: REXX user

IRX0926I THE *command* IMMEDIATE COMMAND FAILED

Explanation: The specified immediate command could not be processed.

System action: Processing continues.

User response: Contact your system programmer for assistance.

Module: IRXATTN

Audience: REXX user

IRX0927I IMMEDIATE COMMANDS ARE: HI, HT, RT, TS, TE

Explanation: You did not specify a valid immediate command. The immediate commands for attention processing are:

- HI - halt interpretation
- HT - halt typing
- RT - resume typing
- TS - trace start
- TE - trace end

System action: Processing continues.

User response: Specify one of the valid immediate commands for attention processing.

Module: IRXATTN

Audience: REXX user

IRX0928I IMMEDIATE COMMANDS ARE: HI, HT, RT, TS, TE, HE

Explanation: You did not specify a valid immediate command. The immediate commands for attention processing are:

- HI - halt interpretation
- HT - halt typing
- RT - resume typing
- TS - trace start
- TE - trace end
- HE - halt execution

System action: Processing continues.

User response: Specify one of the valid immediate commands for attention processing, or enter a null line to resume processing at the point where the attention interrupt occurred.

Module: IRXATTN

Audience: REXX user

IRX0929I EXECUTION HALTED BY USER REQUEST...

Explanation: Your response to the REXX attention prompt was the HE (halt execution) immediate command. Execution of the current REXX exec is halted. This message may also be accompanied by message IRX0245I, and possibly by IRX0246I, IRX0247I, or IRX0248I.

The HE immediate command may be used to halt the execution of an exec that has invoked an external function, subroutine, or host command, which fails to return to the exec. HE may be used when you attempt to terminate a looping function, subroutine, or host command that is written in a language other than REXX.

HE does not alter the setting of the HI (halt interpretation) condition. Use the HI command to terminate an exec whenever possible.

System action: Processing continues.

User response: No action required. This is an informational message.

Module: IRXATTN

IRX0931I

Audience: REXX user

IRX0931I ATTNROUT COMPLETED WITH A RETURN CODE OF *return_code*.

Explanation: Your installation's attention handling exit has returned an undefined return code to REXX attention processing. The return code was *return_code*. REXX attention processing ignores the return code.

System action: REXX attention processing continues.

User response: Notify your system programmer of the message and the return code.

REXX attention processing continues normally.

Module: IRXATTN

Audience: REXX user and system programmer

Appendix. Accessibility

Accessible publications for this product are offered through the z/OS Information Center, which is available at www.ibm.com/systems/z/os/zos/bkserv/.

If you experience difficulty with the accessibility of any z/OS information, please send a detailed message to mhvrcfs@us.ibm.com or to the following mailing address:

IBM Corporation
Attention: MHVRCFS Reader Comments
Department H6MA, Building 707
2455 South Road
Poughkeepsie, NY 12601-5400
USA

Accessibility features

Accessibility features help a user who has a physical disability, such as restricted mobility or limited vision, to use software products successfully. The major accessibility features in z/OS enable users to:

- Use assistive technologies such as screen readers and screen magnifier software
- Operate specific or equivalent features using only the keyboard
- Customize display attributes such as color, contrast, and font size.

Using assistive technologies

Assistive technology products, such as screen readers, function with the user interfaces found in z/OS. Consult the assistive technology documentation for specific information when using such products to access z/OS interfaces.

Keyboard navigation of the user interface

Users can access z/OS user interfaces using TSO/E or ISPF. Refer to *z/OS TSO/E Primer*, *z/OS TSO/E User's Guide*, and *z/OS ISPF User's Guide Vol I* for information about accessing TSO/E and ISPF interfaces. These guides describe how to use TSO/E and ISPF, including the use of keyboard shortcuts or function keys (PF keys). Each guide includes the default settings for the PF keys and explains how to modify their functions.

Dotted decimal syntax diagrams

Syntax diagrams are provided in dotted decimal format for users accessing the z/OS Information Center using a screen reader. In dotted decimal format, each syntax element is written on a separate line. If two or more syntax elements are always present together (or always absent together), they can appear on the same line, because they can be considered as a single compound syntax element.

Each line starts with a dotted decimal number; for example, 3 or 3.1 or 3.1.1. To hear these numbers correctly, make sure that your screen reader is set to read out punctuation. All the syntax elements that have the same dotted decimal number (for example, all the syntax elements that have the number 3.1) are mutually

exclusive alternatives. If you hear the lines 3.1 USERID and 3.1 SYSTEMID, you know that your syntax can include either USERID or SYSTEMID, but not both.

The dotted decimal numbering level denotes the level of nesting. For example, if a syntax element with dotted decimal number 3 is followed by a series of syntax elements with dotted decimal number 3.1, all the syntax elements numbered 3.1 are subordinate to the syntax element numbered 3.

Certain words and symbols are used next to the dotted decimal numbers to add information about the syntax elements. Occasionally, these words and symbols might occur at the beginning of the element itself. For ease of identification, if the word or symbol is a part of the syntax element, it is preceded by the backslash (\) character. The * symbol can be used next to a dotted decimal number to indicate that the syntax element repeats. For example, syntax element *FILE with dotted decimal number 3 is given the format 3 * FILE. Format 3* FILE indicates that syntax element FILE repeats. Format 3* * FILE indicates that syntax element * FILE repeats.

Characters such as commas, which are used to separate a string of syntax elements, are shown in the syntax just before the items they separate. These characters can appear on the same line as each item, or on a separate line with the same dotted decimal number as the relevant items. The line can also show another symbol giving information about the syntax elements. For example, the lines 5.1*, 5.1 LASTRUN, and 5.1 DELETE mean that if you use more than one of the LASTRUN and DELETE syntax elements, the elements must be separated by a comma. If no separator is given, assume that you use a blank to separate each syntax element.

If a syntax element is preceded by the % symbol, this indicates a reference that is defined elsewhere. The string following the % symbol is the name of a syntax fragment rather than a literal. For example, the line 2.1 %OP1 means that you should refer to separate syntax fragment OP1.

The following words and symbols are used next to the dotted decimal numbers:

- ? means an optional syntax element. A dotted decimal number followed by the ? symbol indicates that all the syntax elements with a corresponding dotted decimal number, and any subordinate syntax elements, are optional. If there is only one syntax element with a dotted decimal number, the ? symbol is displayed on the same line as the syntax element, (for example 5? NOTIFY). If there is more than one syntax element with a dotted decimal number, the ? symbol is displayed on a line by itself, followed by the syntax elements that are optional. For example, if you hear the lines 5 ?, 5 NOTIFY, and 5 UPDATE, you know that syntax elements NOTIFY and UPDATE are optional; that is, you can choose one or none of them. The ? symbol is equivalent to a bypass line in a railroad diagram.
- ! means a default syntax element. A dotted decimal number followed by the ! symbol and a syntax element indicates that the syntax element is the default option for all syntax elements that share the same dotted decimal number. Only one of the syntax elements that share the same dotted decimal number can specify a ! symbol. For example, if you hear the lines 2? FILE, 2.1! (KEEP), and 2.1 (DELETE), you know that (KEEP) is the default option for the FILE keyword. In this example, if you include the FILE keyword but do not specify an option, default option KEEP will be applied. A default option also applies to the next higher dotted decimal number. In this example, if the FILE keyword is omitted, default FILE(KEEP) is used. However, if you hear the lines 2? FILE, 2.1, 2.1.1!

(KEEP), and 2.1.1 (DELETE), the default option KEEP only applies to the next higher dotted decimal number, 2.1 (which does not have an associated keyword), and does not apply to 2? FILE. Nothing is used if the keyword FILE is omitted.

- * means a syntax element that can be repeated 0 or more times. A dotted decimal number followed by the * symbol indicates that this syntax element can be used zero or more times; that is, it is optional and can be repeated. For example, if you hear the line 5.1* data area, you know that you can include one data area, more than one data area, or no data area. If you hear the lines 3*, 3 HOST, and 3 STATE, you know that you can include HOST, STATE, both together, or nothing.

Note:

1. If a dotted decimal number has an asterisk (*) next to it and there is only one item with that dotted decimal number, you can repeat that same item more than once.
 2. If a dotted decimal number has an asterisk next to it and several items have that dotted decimal number, you can use more than one item from the list, but you cannot use the items more than once each. In the previous example, you could write HOST STATE, but you could not write HOST HOST.
 3. The * symbol is equivalent to a loop-back line in a railroad syntax diagram.
- + means a syntax element that must be included one or more times. A dotted decimal number followed by the + symbol indicates that this syntax element must be included one or more times; that is, it must be included at least once and can be repeated. For example, if you hear the line 6.1+ data area, you must include at least one data area. If you hear the lines 2+, 2 HOST, and 2 STATE, you know that you must include HOST, STATE, or both. Similar to the * symbol, the + symbol can only repeat a particular item if it is the only item with that dotted decimal number. The + symbol, like the * symbol, is equivalent to a loop-back line in a railroad syntax diagram.

Notices

This information was developed for products and services offered in the U.S.A. or elsewhere.

IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk, NY 10504-1785
U.S.A

For license inquiries regarding double-byte character set (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

Intellectual Property Licensing
Legal and Intellectual Property Law
IBM Japan, Ltd.
19-21, Nihonbashi-Hakozakicho, Chuo-ku
Tokyo 103-8510, Japan

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law: INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Any references in this information to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this IBM product and use of those Web sites is at your own risk.

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

Site Counsel
IBM Corporation
2455 South Road
Poughkeepsie, NY 12601-5400
USA

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this information and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement, or any equivalent agreement between us.

Information concerning non-IBM products was obtained from the suppliers of those products, their published announcements or other publicly available sources. IBM has not tested those products and cannot confirm the accuracy of performance, compatibility or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

All statements regarding IBM's future direction or intent are subject to change or withdrawal without notice, and represent goals and objectives only.

If you are viewing this information softcopy, the photographs and color illustrations may not appear.

COPYRIGHT LICENSE:

This information might contain sample application programs in source language, which illustrate programming techniques on various operating platforms. You may copy, modify, and distribute these sample programs in any form without payment to IBM, for the purposes of developing, using, marketing or distributing application programs conforming to the application programming interface for the operating platform for which the sample programs are written. These examples have not been thoroughly tested under all conditions. IBM, therefore, cannot guarantee or imply reliability, serviceability, or function of these programs. The sample programs are provided "AS IS", without warranty of any kind. IBM shall not be liable for any damages arising out of your use of the sample programs.

Policy for unsupported hardware

Various z/OS elements, such as DFSMS, HCD, JES2, JES3, and MVS, contain code that supports specific hardware servers or devices. In some cases, this device-related element support remains in the product even after the hardware devices pass their announced End of Service date. z/OS may continue to service element code; however, it will not provide service related to unsupported hardware devices. Software problems related to these devices will not be accepted

for service, and current service activity will cease if a problem is determined to be associated with out-of-support devices. In such cases, fixes will not be issued.

Minimum supported hardware

The minimum supported hardware for z/OS releases identified in z/OS announcements can subsequently change when service for particular servers or devices is withdrawn. Likewise, the levels of other software products supported on a particular release of z/OS are subject to the service support lifecycle of those products. Therefore, z/OS and its product publications (for example, panels, samples, messages, and product documentation) can include references to hardware and software that is no longer supported.

- For information about software support lifecycle, see: IBM Lifecycle Support for z/OS (<http://www.ibm.com/software/support/systemsz/lifecycle/>)
- For information about currently-supported IBM hardware, contact your IBM representative.

Trademarks

IBM, the IBM logo, and [ibm.com](http://www.ibm.com) are trademarks or registered trademarks of International Business Machines Corp., registered in many jurisdictions worldwide. Other product and service names might be trademarks of IBM or other companies. A current list of IBM trademarks is available on the Web at "Copyright and trademark information" at www.ibm.com/legal/copytrade.shtml (<http://www.ibm.com/legal/copytrade.shtml>).

Index

A

accessibility 647
 contact IBM 647
 features 647
ADF002I 1
ADF003I 1
ADF004I 1
ADF005A 2
ADF005I 2
ADF006I 2
ADF010I 2
ADF011I 2
ADF012I 2
ADF013I 3
ADF014I 3
ADF015I 3
ADF016I 3
ADF017I 3
ADF018I 3
ADF019I 3
ADF021I 4
ADF022I 4
ADF023I 4
ADF025I 4
ADF027I 4
ADF028I 4
ADF029I 4
ADF030I 4
ADF031I 5
ADF032A 5
ADF033I 5
ADF041A 5
ADF101I 5
ADF102I 5
ADF103I 5
ADF104I 5
ADF105I 6
ADF106I 6
ADF107I 6
ADF108I 6
ADF109I 6
ADF110I 6
ADF111I 6
ADF112A 6
ADF112I 6
ADF113A 7
ADF113I 7
ADF114I 7
ADF115I 7
ADF116I 7
ADF117I 7
ADF118I 7
ADF119I 7
ADF120I 7
ADF121I 8
ADF122I 8
ADF201I 8
ADF202I 8
ADF203A 8
ADF203I 8
ADF204I 8

ADF205I 8
ADF301I 8
ADF302A 9
ADF302I 9
ADF303I 9
assistive technologies 647

C

CHSCMI01I 11
CHSCMI02I 11
CHSCMI03E 12
CHSCMI04I 12
CHSCMI05E 12
CHSCMI06I 12
CHSCMI07E 12
CHSCMI08E 13
CHSCMI09E 13
CHSCMI10I 13
CHSCMI11E 13
CHSCMI12E 13
CHSCMI13E 14
CHSCMI14I 14
CHSCMI15I 14
CHSCMI16E 14
CHSCMI17E 14
CHSCOM01I 16
CHSCOM02I 16
CHSCOM03E 16
CHSCOM04E 16
CHSCOM05E 16
CHSCOM06E 16
CHSCOM07I 17
CHSCOM08I 17
CHSCOM09I 17
CHSCOM10I 17
CHSCOM11I 17
CHSCPS01E 18
CHSCPS02E 18
CHSCPS03E 18
CHSCPS04E 18
CHSCPS05E 18
CHSCPS06E 19
CHSCPS07I 19
CHSCPS08I 19
CHSCPS09E 19
CHSCPS10I 19
CHSCSI01E 15
CHSCSI02I 15
CHSCSI03I 15
CHSCSI04I 15
CHSCUT01I 20
CHSCUT02E 20
CHSCUT03E 20
CHSCUT04I 20
CHSCUT05I 20
CHSCUT06I 20
CHSCUT07I 21
CHSCUT08I 21
CHSCUT09E 21
CHSCUT11E 21
CHSCUT12E 21
CHSCUT13E 22
CHSCUT14E 22
CHSCUT15E 22
CHSDCA01E 22
CHSDCA03E 22
CHSDCA04E 23
CHSDCA05E 23
CHSDCA06I 23
CHSDCA07E 23
CHSDCA08I 23
CHSDCA09E 24
CHSDCOM01I 24
CHSDCOM02E 24
CHSDCOM03E 24
CHSDCOM04E 24
CHSDCOM05E 25
CHSDCOM06E 25
CHSDCOM07I 25
CHSDCOM08I 25
CHSDCOM09I 25
CHSDCOM10E 25
CHSDCOM11E 26
CHSDCOM12I 26
CHSINF01E 26
CHSINF02I 26
CHSINF03E 26
CHSIPM01E 27
CHSIPM02I 27
CHSIPM03E 27
CHSIPM04I 27
CHSIPM05E 28
CHSIPM06I 28
CHSIPM07I 28
CHSIPM08I 28
CHSREC01I 28
CHSREC02I 29
CHSREC03I 29
CHSREC04I 29
CHSREC06I 29
CHSREC07I 29
CHSREC08I 30
CHSREC09E 30
CHSRUT01E 30
CHSRUT02E 30
CHSRUTR01I 30
CHSRUTR02I 31
CHSRUTR03I 31
CHSRUTR04I 31
CHSRUTR05I 31
CHSRUTR06I 31
CHSRUTR07I 32
CHSRUTR08E 32
CHSRUTR09E 32
CHSRUTR10E 32
CHSRUTR11E 32
CHSRUTR12I 33
CHSRUTR13I 33
CHSRUTR14I 33
CHSRUTR15I 33
CHSRUTR16E 33

CHSRUTR17I 34
 CHSSPR01I 34
 CHSSRI01I 34
 CHSSRI02I 34
 CHSSRI03I 34
 CHSSRI04E 35
 CHSSRI05E 35
 CHSSRI06E 35
 CHSSRV01E 35
 CHSSRV02I 35
 CHSSRV03I 36
 CHSTCA01E 36
 CHSTCA02E 36
 CHSTCA03I 36
 CHSTCA04I 36
 CHSTCA05E 37
 CHSTCA06I 37
 CHSTCA07E 37
 CHSTCA08E 37
 CHSTCA09I 37
 CHSTCA10I 38
 CHSTCA11E 38
 CHSTCA12E 38
 CHSTCA13I 38
 CHSTCA14E 38
 CHSTCA15E 39
 CHSTCA16E 39
 CHSTCA17E 39
 CHSTCA18E 39
 CHSTCA19I 39
 CHSTCA20E 40
 CHSTRH01I 40
 CHSTRH02I 40
 CHSTRH201I 41
 CHSTRH202I 41
 CHSTRL01I 42
 CHSTRR01I 42
 CHSTRS01I 42
 CHSTSF01I 42
 CHSTSF02I 42
 CHSTSF03I 43
 CHSTSF04I 43
 CHSTSF05I 43
 CHSTSF06I 43
 CHSTSF07I 43
 CHSTSF08I 44
 CHSTSF09I 44
 CHSTSF10I 44
 CHSTSF11I 44
 CHSTSF12I 44
 CHSTSF13I 45
 CHSTSF14I 45
 CHSTSF15I 45
 CHSTSF16I 45
 CHSTSF17I 45
 CHSTSF18I 46
 CHSTTP01I 46
 CHSTTP02I 46
 COF10301I 47
 COF10302I 47
 COF10303I 48
 COF10304I 48
 COF10305I 48
 COF10306I 48
 COF10307I 49
 COF10308I 50

I
 ICQAB000 52
 ICQAB001 52
 ICQAB002 52
 ICQAB003 52
 ICQAB004 52
 ICQAB005 52
 ICQAB006 52
 ICQAB007 53
 ICQAB008 53
 ICQAB009 53
 ICQAB010 53
 ICQAB011 53
 ICQAB012 53
 ICQAB013 53
 ICQAB014 54
 ICQAB015 54
 ICQAB016 54
 ICQAB017 54
 ICQAB018 54
 ICQAB019 54
 ICQAB020 54
 ICQAB021 55
 ICQAB022 55
 ICQAB023 55
 ICQAB024 55
 ICQAB025 55
 ICQAB026 55
 ICQAB027 55
 ICQAB028 55
 ICQAB029 56
 ICQAB030 56
 ICQAB031 56
 ICQAB032 56
 ICQAB033 56
 ICQAB034 56
 ICQAB035 56
 ICQAB036 57
 ICQAB037 57
 ICQAB038 57
 ICQAB039 57
 ICQAB040 57
 ICQAB041 58
 ICQAB042 58
 ICQAB043 58
 ICQAB044 58
 ICQAB045 58
 ICQAB046 58
 ICQAB047 59
 ICQAB048 59
 ICQAB049 59
 ICQAB100 59
 ICQAB101 59
 ICQAB102 59
 ICQAB103 59
 ICQAB104 59
 ICQAB105 60
 ICQAB106 60
 ICQAB107 60
 ICQAB108 60
 ICQAB109 60
 ICQAB110 60
 ICQAB111 60
 ICQAB112 60
 ICQAB113 61
 ICQAB114 61
 ICQAB115 61

ICQAB116 61
 ICQAB117 61
 ICQAB118 61
 ICQAB119 61
 ICQAB120 62
 ICQAB121 62
 ICQAB122 62
 ICQAB124 62
 ICQAB125 62
 ICQAB126 62
 ICQAB127 62
 ICQAB128 63
 ICQAB129 63
 ICQAB200 63
 ICQAB201 63
 ICQAB202 63
 ICQAB203 63
 ICQAB204 63
 ICQAB205 64
 ICQAB206 64
 ICQAB207 64
 ICQAB208 64
 ICQAB209 64
 ICQAB210 64
 ICQAB211 64
 ICQAB212 65
 ICQAB213 65
 ICQAB214 65
 ICQAB215 65
 ICQAB216 65
 ICQAB217 65
 ICQAB218 65
 ICQAB219 65
 ICQAB220 66
 ICQAB221 66
 ICQAB222 66
 ICQAB223 66
 ICQAB224 66
 ICQAB225 66
 ICQAB226 66
 ICQAB227 67
 ICQAB228 67
 ICQAB229 67
 ICQAB402 67
 ICQAB405 67
 ICQAB500 67
 ICQAB501 67
 ICQAB502 68
 ICQAB504 68
 ICQAB505 68
 ICQAB506 68
 ICQAB602 68
 ICQAB603 68
 ICQAB604 68
 ICQAB700 68
 ICQAD000 68
 ICQAD001 69
 ICQAD003 69
 ICQAD004 69
 ICQAD005 69
 ICQAD006 69
 ICQAD007 69
 ICQAD009 69
 ICQAD010 70
 ICQAD011 70
 ICQAD012 70
 ICQAD013 70

ICQAD014	70	ICQAI004	80	ICQAM102	91
ICQAD015	70	ICQAI005	80	ICQAM105	91
ICQAD016	70	ICQAI006	80	ICQAM106	91
ICQAD017	70	ICQAI007	80	ICQAM107	91
ICQAD018	71	ICQAI008	81	ICQAM108	91
ICQAD019	71	ICQAI009	81	ICQAM109	91
ICQAD020	71	ICQAI010	81	ICQAM110	92
ICQAD021	71	ICQAI011	81	ICQAM111	92
ICQAD022	71	ICQAI012	81	ICQAM112	92
ICQAD023	71	ICQAI013	81	ICQAM121	92
ICQAD024	71	ICQAI015	82	ICQAM122	92
ICQAD025	72	ICQAI020	82	ICQAM123	92
ICQAD026	72	ICQAI021	82	ICQAM124	93
ICQAD028	72	ICQAI022	82	ICQAM125	93
ICQAD030	72	ICQAI023	82	ICQAM126	93
ICQAD031	72	ICQAI024	82	ICQAM127	93
ICQAE000	72	ICQAI025	83	ICQAM128	93
ICQAE001	72	ICQAI026	83	ICQAM129	94
ICQAE002	72	ICQAI027	83	ICQAM130	94
ICQAE003	73	ICQAI028	83	ICQAM131	94
ICQAE004	73	ICQAI029	84	ICQAM132	94
ICQAE005	73	ICQAI030	84	ICQAM133	95
ICQAE007	73	ICQAI031	84	ICQAM134	95
ICQAE008	73	ICQAI032	84	ICQAM135	95
ICQAE009	73	ICQAM007	84	ICQAM136	95
ICQAE010	74	ICQAM008	84	ICQAM137	95
ICQAE011	74	ICQAM009	85	ICQAM138	96
ICQAE013	74	ICQAM010	85	ICQAM190	96
ICQAE014	74	ICQAM011	85	ICQAM191	96
ICQAE017	74	ICQAM012	85	ICQAM192	96
ICQAE018	74	ICQAM013	85	ICQAM193	96
ICQAE020	74	ICQAM014	85	ICQAM194	97
ICQAE021	75	ICQAM015	85	ICQAM195	97
ICQAE022	75	ICQAM016	85	ICQAM196	97
ICQAE023	75	ICQAM017	86	ICQAM197	97
ICQAE025	75	ICQAM018	86	ICQAM198	97
ICQAE026	75	ICQAM019	86	ICQAM199	98
ICQAE027	75	ICQAM020	86	ICQAM200	98
ICQAE028	75	ICQAM021	86	ICQAM204	98
ICQAE029	76	ICQAM030	86	ICQAM205	98
ICQAE040	76	ICQAM031	86	ICQAM206	98
ICQAE041	76	ICQAM032	86	ICQAM207	98
ICQAE042	76	ICQAM033	87	ICQAM208	98
ICQAE043	76	ICQAM034	87	ICQAM209	99
ICQAE044	76	ICQAM035	87	ICQAM221	99
ICQAE045	76	ICQAM036	87	ICQAM222	99
ICQAE046	77	ICQAM037	87	ICQAM223	99
ICQAE047	77	ICQAM038	87	ICQAM224	99
ICQAE048	77	ICQAM039	87	ICQAM225	99
ICQAE049	77	ICQAM040	88	ICQAM226	99
ICQAE050	77	ICQAM041	88	ICQAM227	99
ICQAE051	77	ICQAM042	88	ICQAM228	100
ICQAE052	77	ICQAM043	88	ICQAM229	100
ICQAE053	78	ICQAM044	88	ICQAM300	100
ICQAE055	78	ICQAM045	88	ICQAM301	100
ICQAE056	78	ICQAM046	88	ICQAM302	100
ICQAE057	78	ICQAM047	89	ICQAM303	100
ICQAE058	78	ICQAM048	89	ICQAM304	100
ICQAE059	78	ICQAM049	89	ICQAM305	100
ICQAE061	78	ICQAM072	89	ICQAM306	101
ICQAE062	79	ICQAM073	89	ICQAM307	101
ICQAE063	79	ICQAM075	90	ICQAM308	101
ICQAE064	79	ICQAM076	90	ICQAM309	101
ICQAI000	79	ICQAM077	90	ICQAM310	101
ICQAI001	79	ICQAM078	90	ICQAM311	101
ICQAI002	80	ICQAM100	90	ICQAM312	102
ICQAI003	80	ICQAM101	91	ICQAM313	102

ICQAM314	102	ICQAM706	113	ICQAM786	126
ICQAM315	102	ICQAM707	114	ICQAM787	126
ICQAM316	102	ICQAM708	114	ICQAM788	126
ICQAM317	102	ICQAM710	114	ICQAM789	126
ICQAM318	102	ICQAM711	114	ICQAM790	126
ICQAM319	103	ICQAM712	114	ICQAM791	127
ICQAM320	103	ICQAM713	114	ICQAM792	127
ICQAM321	103	ICQAM714	115	ICQAM793	127
ICQAM322	103	ICQAM715	115	ICQAM794	127
ICQAM323	103	ICQAM716	115	ICQAM800	127
ICQAM324	103	ICQAM717	115	ICQAM801	127
ICQAM325	103	ICQAM720	115	ICQAM802	128
ICQAM326	104	ICQAM721	115	ICQAM803	128
ICQAM327	104	ICQAM730	115	ICQAM804	128
ICQAM328	104	ICQAM731	115	ICQAM805	128
ICQAM329	104	ICQAM732	116	ICQAM806	128
ICQAM400	104	ICQAM733	116	ICQAM807	128
ICQAM403	104	ICQAM734	116	ICQAM808	128
ICQAM404	105	ICQAM735	116	ICQAM809	129
ICQAM405	105	ICQAM737	116	ICQAM810	129
ICQAM406	105	ICQAM738	116	ICQAM811	129
ICQAM410	105	ICQAM739	117	ICQAM812	129
ICQAM411	106	ICQAM740	117	ICQAM813	129
ICQAM412	106	ICQAM741	117	ICQAM814	129
ICQAM413	106	ICQAM742	117	ICQAM815	129
ICQAM421	106	ICQAM743	117	ICQAM816	130
ICQAM422	106	ICQAM744	118	ICQAM817	130
ICQAM423	107	ICQAM745	118	ICQAM818	130
ICQAM424	107	ICQAM746	118	ICQAM820	130
ICQAM425	107	ICQAM747	118	ICQAM821	130
ICQAM501	107	ICQAM748	118	ICQAM822	130
ICQAM502	107	ICQAM749	118	ICQAM823	131
ICQAM503	107	ICQAM750	119	ICQAM824	131
ICQAM504	108	ICQAM751	119	ICQAM825	131
ICQAM505	108	ICQAM752	119	ICQAM826	131
ICQAM507	108	ICQAM753	119	ICQAM827	131
ICQAM600	108	ICQAM754	119	ICQAM828	131
ICQAM601	108	ICQAM755	120	ICQAM831	132
ICQAM602	108	ICQAM756	120	ICQAM832	132
ICQAM603	108	ICQAM757	120	ICQAM833	132
ICQAM604	109	ICQAM759	120	ICQAM834	132
ICQAM605	109	ICQAM760	120	ICQAM835	132
ICQAM608	109	ICQAM761	121	ICQAM836	132
ICQAM609	109	ICQAM762	121	ICQAM837	133
ICQAM610	109	ICQAM763	121	ICQAM838	133
ICQAM611	109	ICQAM764	121	ICQAM839	133
ICQAM613	109	ICQAM765	121	ICQAM840	133
ICQAM614	110	ICQAM766	122	ICQAM841	133
ICQAM615	110	ICQAM767	122	ICQAM842	133
ICQAM620	110	ICQAM768	122	ICQAM843	133
ICQAM621	110	ICQAM769	122	ICQAM844	134
ICQAM623	110	ICQAM770	122	ICQAM845	134
ICQAM624	111	ICQAM771	123	ICQAM846	134
ICQAM625	111	ICQAM772	123	ICQAM847	134
ICQAM630	111	ICQAM773	123	ICQAM848	134
ICQAM631	111	ICQAM774	123	ICQAM849	134
ICQAM633	111	ICQAM775	123	ICQAM850	134
ICQAM636	112	ICQAM776	124	ICQAM851	135
ICQAM637	112	ICQAM777	124	ICQAM852	135
ICQAM638	112	ICQAM778	124	ICQAM853	135
ICQAM639	112	ICQAM779	124	ICQAM854	135
ICQAM700	112	ICQAM780	124	ICQAM855	135
ICQAM701	113	ICQAM781	125	ICQAM856	136
ICQAM702	113	ICQAM782	125	ICQAM857	136
ICQAM703	113	ICQAM783	125	ICQAM858	136
ICQAM704	113	ICQAM784	125	ICQAM860	136
ICQAM705	113	ICQAM785	125	ICQAM861	136

ICQAM862	136	ICQAM937	149	ICQAN504	159
ICQAM863	137	ICQAM938	149	ICQAN505	159
ICQAM864	137	ICQAM939	149	ICQAN506	159
ICQAM865	137	ICQAM940	150	ICQAN602	160
ICQAM866	137	ICQAM941	150	ICQAN603	160
ICQAM867	137	ICQAM942	150	ICQAN604	160
ICQAM868	137	ICQAM943	150	ICQAN605	160
ICQAM869	137	ICQAM944	150	ICQAN606	160
ICQAM870	138	ICQAM945	151	ICQAN607	160
ICQAM871	138	ICQAM946	151	ICQAN608	160
ICQAM872	138	ICQAM947	151	ICQAN700	160
ICQAM873	138	ICQAM948	151	ICQAN701	160
ICQAM880	138	ICQAM949	151	ICQAP000	161
ICQAM881	138	ICQAM951	152	ICQAP001	161
ICQAM882	139	ICQAM952	152	ICQAP002	161
ICQAM883	139	ICQAM953	152	ICQAP003	161
ICQAM884	139	ICQAM954	152	ICQAP004	161
ICQAM885	139	ICQAM955	152	ICQAP005	161
ICQAM886	139	ICQAM956	152	ICQAP007	161
ICQAM887	139	ICQAM957	152	ICQAP008	161
ICQAM888	140	ICQAM960	152	ICQAP009	162
ICQAM889	140	ICQAM961	153	ICQAP010	162
ICQAM890	140	ICQAM962	153	ICQAP011	162
ICQAM891	140	ICQAM963	153	ICQAP012	162
ICQAM892	140	ICQAM964	153	ICQAP013	162
ICQAM893	141	ICQAM965	153	ICQAP014	162
ICQAM894	141	ICQAM966	153	ICQAP015	162
ICQAM895	141	ICQAM967	153	ICQAP016	163
ICQAM896	141	ICQAM980	154	ICQAP017	163
ICQAM897	141	ICQAM981	154	ICQAP018	163
ICQAM898	142	ICQAM990	154	ICQAP019	163
ICQAM899	142	ICQAM991	154	ICQAP021	163
ICQAM901	142	ICQAM992	154	ICQAP022	164
ICQAM902	142	ICQAM993	155	ICQAP023	164
ICQAM903	142	ICQAM994	155	ICQAP024	164
ICQAM904	143	ICQAN000	155	ICQAP025	164
ICQAM905	143	ICQAN001	155	ICQAP026	164
ICQAM906	143	ICQAN002	155	ICQAP027	164
ICQAM907	143	ICQAN003	155	ICQAP028	164
ICQAM908	143	ICQAN004	156	ICQAP029	164
ICQAM909	144	ICQAN005	156	ICQAP030	165
ICQAM911	144	ICQAN007	156	ICQAP031	165
ICQAM912	144	ICQAN008	156	ICQAP033	165
ICQAM913	144	ICQAN009	156	ICQAP034	165
ICQAM914	144	ICQAN100	156	ICQAP035	165
ICQAM915	145	ICQAN101	156	ICQAP036	165
ICQAM916	145	ICQAN102	156	ICQAP037	165
ICQAM917	145	ICQAN104	157	ICQAP038	165
ICQAM918	145	ICQAN106	157	ICQAP039	166
ICQAM919	145	ICQAN107	157	ICQAP040	166
ICQAM920	146	ICQAN109	157	ICQAP041	166
ICQAM921	146	ICQAN110	157	ICQAP042	166
ICQAM922	146	ICQAN111	157	ICQAP043	166
ICQAM923	146	ICQAN112	157	ICQAP044	166
ICQAM924	146	ICQAN115	157	ICQAP045	166
ICQAM925	147	ICQAN400	158	ICQAP046	166
ICQAM926	147	ICQAN402	158	ICQAP047	166
ICQAM927	147	ICQAN403	158	ICQAP048	167
ICQAM928	147	ICQAN404	158	ICQAP049	167
ICQAM929	147	ICQAN405	158	ICQAP050	167
ICQAM930	148	ICQAN406	158	ICQAP051	167
ICQAM931	148	ICQAN407	158	ICQAP052	167
ICQAM932	148	ICQAN408	159	ICQAP053	167
ICQAM933	148	ICQAN409	159	ICQAP054	167
ICQAM934	148	ICQAN500	159	ICQAP055	167
ICQAM935	149	ICQAN501	159	ICQAP056	168
ICQAM936	149	ICQAN502	159	ICQAP057	168

ICQAP058	168	ICQAS513	177	ICQAS910	187
ICQAP059	168	ICQAS515	178	ICQAS912	188
ICQAP060	168	ICQAS516	178	ICQAS914	188
ICQAP061	168	ICQAS517	178	ICQAS915	188
ICQAP062	169	ICQAS518	178	ICQAS916	188
ICQAP063	169	ICQAS520	178	ICQAS918	188
ICQAP064	169	ICQAS521	178	ICQAS921	188
ICQAP065	169	ICQAS522	178	ICQAS922	188
ICQAP066	169	ICQAS523	179	ICQAS923	189
ICQAP067	169	ICQAS525	179	ICQAS924	189
ICQAP068	169	ICQAS526	179	ICQAS927	189
ICQAP069	170	ICQAS527	179	ICQAS928	189
ICQAP071	170	ICQAS528	179	ICQAS930	189
ICQAP073	170	ICQAS530	179	ICQAS931	189
ICQAP074	170	ICQAS531	179	ICQAS932	189
ICQAP075	170	ICQAS532	180	ICQAS933	190
ICQAP076	170	ICQAS533	180	ICQAS934	190
ICQAP077	170	ICQAS535	180	ICQAS935	190
ICQAP078	170	ICQAS536	180	ICQAS936	190
ICQAP080	171	ICQAS537	180	ICQAS937	190
ICQAP081	171	ICQAS538	180	ICQAS938	190
ICQAP082	171	ICQAS540	180	ICQAS939	190
ICQAP083	171	ICQAS541	181	ICQCA000	191
ICQAP084	171	ICQAS542	181	ICQCA001	191
ICQAP085	171	ICQAS543	181	ICQCA002	191
ICQAS100	171	ICQAS550	181	ICQCA003	191
ICQAS101	172	ICQAS551	181	ICQCA004	191
ICQAS102	172	ICQAS552	181	ICQCA005	191
ICQAS103	172	ICQAS553	181	ICQCA006	191
ICQAS400	172	ICQAS554	181	ICQCA007	192
ICQAS401	172	ICQAS556	182	ICQCA008	192
ICQAS402	172	ICQAS557	182	ICQCA009	192
ICQAS403	172	ICQAS558	182	ICQCA010	192
ICQAS405	173	ICQAS559	182	ICQCA011	192
ICQAS410	173	ICQAS560	182	ICQCA012	192
ICQAS411	173	ICQAS562	182	ICQCA013	192
ICQAS412	173	ICQAS564	182	ICQCA014	192
ICQAS413	173	ICQAS565	183	ICQCA015	193
ICQAS414	173	ICQAS566	183	ICQCA016	193
ICQAS420	173	ICQAS567	183	ICQCA017	193
ICQAS421	174	ICQAS568	183	ICQCA018	193
ICQAS422	174	ICQAS570	184	ICQCA019	193
ICQAS423	174	ICQAS571	184	ICQCA100	193
ICQAS424	174	ICQAS572	184	ICQCA101	194
ICQAS430	174	ICQAS573	184	ICQCA103	194
ICQAS431	174	ICQAS575	184	ICQCA104	194
ICQAS432	174	ICQAS576	184	ICQCA105	194
ICQAS433	175	ICQAS580	184	ICQCA106	194
ICQAS434	175	ICQAS581	184	ICQCA107	195
ICQAS440	175	ICQAS582	185	ICQCA108	195
ICQAS441	175	ICQAS583	185	ICQCA109	195
ICQAS442	175	ICQAS584	185	ICQCA110	195
ICQAS443	175	ICQAS585	185	ICQCA111	195
ICQAS450	175	ICQAS590	185	ICQCA112	195
ICQAS500	176	ICQAS591	185	ICQCA113	195
ICQAS501	176	ICQAS592	185	ICQCA116	196
ICQAS502	176	ICQAS593	186	ICQCA117	196
ICQAS503	176	ICQAS594	186	ICQCA118	196
ICQAS504	176	ICQAS596	186	ICQCA121	196
ICQAS505	176	ICQAS700	186	ICQCA122	196
ICQAS506	176	ICQAS701	186	ICQCA123	196
ICQAS507	177	ICQAS900	187	ICQCA124	196
ICQAS508	177	ICQAS901	187	ICQCA125	197
ICQAS509	177	ICQAS903	187	ICQCA126	197
ICQAS510	177	ICQAS904	187	ICQCA127	197
ICQAS511	177	ICQAS906	187	ICQCA128	197
ICQAS512	177	ICQAS907	187	ICQCA129	197

ICQCA130	197	ICQCA249	207	ICQCB003	218
ICQCA131	197	ICQCA250	207	ICQCB004	218
ICQCA132	197	ICQCA251	207	ICQCB005	218
ICQCA133	198	ICQCA252	207	ICQCB006	218
ICQCA134	198	ICQCA254	208	ICQCB007	219
ICQCA136	198	ICQCA255	208	ICQCB008	219
ICQCA137	198	ICQCA256	208	ICQCB009	219
ICQCA138	198	ICQCA257	208	ICQCB010	219
ICQCA139	198	ICQCA258	208	ICQCB011	219
ICQCA140	198	ICQCA259	208	ICQCB012	219
ICQCA141	199	ICQCA260	209	ICQCB014	219
ICQCA142	199	ICQCA261	209	ICQCB015	220
ICQCA143	199	ICQCA262	209	ICQCB019	220
ICQCA144	199	ICQCA263	209	ICQCB020	220
ICQCA145	199	ICQCA264	210	ICQCB021	220
ICQCA146	199	ICQCA265	210	ICQCB022	220
ICQCA147	199	ICQCA266	210	ICQCB023	220
ICQCA150	199	ICQCA267	210	ICQCB024	221
ICQCA151	200	ICQCA301	210	ICQCB025	221
ICQCA152	200	ICQCA302	211	ICQCB026	221
ICQCA153	200	ICQCA303	211	ICQCB027	221
ICQCA200	200	ICQCA304	211	ICQCB028	221
ICQCA201	200	ICQCA305	211	ICQCG000	221
ICQCA203	200	ICQCA306	211	ICQCG001	221
ICQCA204	201	ICQCA307	211	ICQCG002	222
ICQCA205	201	ICQCA308	211	ICQCG004	222
ICQCA206	201	ICQCA309	212	ICQCG005	222
ICQCA207	201	ICQCA310	212	ICQCG006	222
ICQCA208	201	ICQCA311	212	ICQCG007	222
ICQCA209	201	ICQCA312	212	ICQCG008	222
ICQCA210	201	ICQCA313	212	ICQCG009	222
ICQCA211	202	ICQCA314	212	ICQCG010	222
ICQCA212	202	ICQCA316	212	ICQCG011	223
ICQCA213	202	ICQCA320	213	ICQCG012	223
ICQCA215	202	ICQCA321	213	ICQCG015	223
ICQCA216	202	ICQCA322	213	ICQCG017	223
ICQCA217	202	ICQCA323	213	ICQCI000	223
ICQCA218	202	ICQCA324	213	ICQCI005	223
ICQCA219	203	ICQCA325	213	ICQCI006	223
ICQCA220	203	ICQCA700	213	ICQCI007	223
ICQCA221	203	ICQCA701	213	ICQCI008	224
ICQCA222	203	ICQCA710	214	ICQCI009	224
ICQCA223	203	ICQCA711	214	ICQCI010	224
ICQCA224	203	ICQCA712	214	ICQCI011	224
ICQCA225	203	ICQCA713	214	ICQCI012	224
ICQCA226	204	ICQCA714	214	ICQCI013	224
ICQCA227	204	ICQCA715	214	ICQCI014	225
ICQCA228	204	ICQCA716	215	ICQCI015	225
ICQCA229	204	ICQCA717	215	ICQCI016	225
ICQCA230	204	ICQCA718	215	ICQCI017	225
ICQCA231	204	ICQCA719	215	ICQCI018	225
ICQCA232	204	ICQCA720	215	ICQCI019	225
ICQCA233	204	ICQCA721	215	ICQCI020	225
ICQCA234	205	ICQCA722	216	ICQCI021	225
ICQCA235	205	ICQCA731	216	ICQCI022	226
ICQCA236	205	ICQCA732	216	ICQCI023	226
ICQCA238	205	ICQCA733	216	ICQCI024	226
ICQCA239	205	ICQCA734	216	ICQCI025	226
ICQCA240	206	ICQCA800	216	ICQCI026	226
ICQCA241	206	ICQCA801	217	ICQCI027	226
ICQCA242	206	ICQCA802	217	ICQCI028	226
ICQCA243	206	ICQCA803	217	ICQCI029	226
ICQCA244	206	ICQCA804	217	ICQCI030	227
ICQCA245	206	ICQCA805	217	ICQCI031	227
ICQCA246	207	ICQCB000	218	ICQCI032	227
ICQCA247	207	ICQCB001	218	ICQCI033	227
ICQCA248	207	ICQCB002	218	ICQCI034	227

ICQCI035	227	ICQCR001	238	ICQGC038	250
ICQCI036	227	ICQCR002	238	ICQGC039	250
ICQCI037	227	ICQCR003	239	ICQGC040	251
ICQCI038	228	ICQCR004	239	ICQGC041	251
ICQCI039	228	ICQCR005	239	ICQGC042	251
ICQCI040	228	ICQCR006	239	ICQGC043	251
ICQCI041	228	ICQCR007	239	ICQGC044	251
ICQCI042	228	ICQCR008	239	ICQGC045	251
ICQCI043	228	ICQGA000	239	ICQGC046	252
ICQCI044	228	ICQGA001	239	ICQGC047	252
ICQCI045	229	ICQGA002	240	ICQGC048	252
ICQCI046	229	ICQGA003	240	ICQGC049	252
ICQCI047	229	ICQGA004	240	ICQGC050	252
ICQCI048	229	ICQGA005	240	ICQGC051	252
ICQCI049	229	ICQGA006	240	ICQGC052	253
ICQCL011	229	ICQGA010	240	ICQGC053	253
ICQCL012	229	ICQGA011	241	ICQGC054	253
ICQCL013	229	ICQGA012	241	ICQGC055	253
ICQCL015	230	ICQGA020	241	ICQGC056	253
ICQCL019	230	ICQGA021	241	ICQGC057	253
ICQCL021	230	ICQGA022	241	ICQGC058	253
ICQCL022	230	ICQGA023	241	ICQGC060	254
ICQCN000	230	ICQGA024	242	ICQGC061	254
ICQCN001	231	ICQGA025	242	ICQGC063	254
ICQCN002	231	ICQGA026	242	ICQGC064	254
ICQCN003	231	ICQGA027	242	ICQGC065	254
ICQCN004	231	ICQGA028	242	ICQGC066	254
ICQCN005	231	ICQGA029	242	ICQGC070	254
ICQCN200	231	ICQGA030	243	ICQGC071	254
ICQCN201	232	ICQGA031	243	ICQGC072	255
ICQCN202	232	ICQGA032	243	ICQGC073	255
ICQCN203	232	ICQGA033	243	ICQGC074	255
ICQCN205	232	ICQGA036	243	ICQGC075	255
ICQCN206	232	ICQGA037	244	ICQGC076	255
ICQCN207	232	ICQGA038	244	ICQGC077	255
ICQCN208	233	ICQGA039	244	ICQGC078	255
ICQCN209	233	ICQGC000	244	ICQGC080	256
ICQCN210	233	ICQGC001	245	ICQGC081	256
ICQCN211	233	ICQGC003	245	ICQGC082	256
ICQCN212	233	ICQGC010	245	ICQGC083	256
ICQCN213	234	ICQGC011	245	ICQGC084	256
ICQCN215	234	ICQGC012	245	ICQGC085	256
ICQCN216	234	ICQGC013	245	ICQGC101	256
ICQCN217	234	ICQGC014	246	ICQGC102	257
ICQCP001	234	ICQGC015	246	ICQGC103	257
ICQCP002	234	ICQGC016	246	ICQGC104	257
ICQCP003	235	ICQGC017	246	ICQGC105	257
ICQCP004	235	ICQGC018	246	ICQGC106	257
ICQCP005	235	ICQGC019	248	ICQGC107	257
ICQCP006	235	ICQGC020	248	ICQGC108	257
ICQCP007	235	ICQGC021	248	ICQGC350	257
ICQCP008	235	ICQGC022	249	ICQGC351	258
ICQCP009	236	ICQGC023	249	ICQGC352	258
ICQCP010	236	ICQGC024	249	ICQGC353	258
ICQCP011	236	ICQGC025	249	ICQGC354	258
ICQCP012	236	ICQGC026	249	ICQGC355	258
ICQCP013	236	ICQGC027	249	ICQGC356	259
ICQCP014	236	ICQGC028	249	ICQGC357	259
ICQCP015	237	ICQGC029	249	ICQGC358	259
ICQCP016	237	ICQGC030	249	ICQGC359	259
ICQCP017	237	ICQGC031	250	ICQGC360	259
ICQCP018	237	ICQGC032	250	ICQGC361	260
ICQCP019	238	ICQGC033	250	ICQGC362	260
ICQCP030	238	ICQGC034	250	ICQGC363	260
ICQCP031	238	ICQGC035	250	ICQGC364	260
ICQCP032	238	ICQGC036	250	ICQGC365	260
ICQCP033	238	ICQGC037	250	ICQGC366	261

ICQGC367	261	ICQSP048	274	IKJ52320I	295
ICQGC368	261	ICQSP049	274	IKJ52321I	295
ICQGC369	261	ICQSP050	275	IKJ52330I	295
ICQGC370	261	ICQSP051	275	IKJ52331I	295
ICQGC371	262	ICQSP052	275	IKJ52332I	295
ICQGC373	262	ICQSP053	275	IKJ52333I	296
ICQGC374	262	ICQSP054	275	IKJ52334I	296
ICQGC375	262	ICQSP055	276	IKJ52335I	296
ICQGC376	262	ICQSP056	276	IKJ52336I	296
ICQGC377	263	ICQSP057	276	IKJ52337I	296
ICQGC378	263	ICQSP058	276	IKJ52338I	297
ICQGC379	263	ICQSP431	276	IKJ52339I	297
ICQGC401	263	ICQSP432	277	IKJ52340A	297
ICQGC402	263	ICQSP433	277	IKJ52341A	297
ICQGC403	264	ICQSP434	277	IKJ52342I	297
ICQGC404	264	ICQSP435	277	IKJ52343I	297
ICQGC989	264	IDY00001I	279	IKJ52344I	298
ICQGC990	264	IDY00007I	279	IKJ52360I	298
ICQGC991	264	IDY00009I	280	IKJ52361I	298
ICQGC992	265	IDY00010I	280	IKJ52362I	298
ICQGC993	265	IDY00012I	280	IKJ52363I	298
ICQGC994	265	IDY00013I	280	IKJ52364I	298
ICQGC995	265	IDY00014I	280	IKJ52365I	299
ICQGC996	265	IDY00015I	281	IKJ52366I	299
ICQGC997	266	IDY00016I	281	IKJ52367I	299
ICQGC998	266	IDY00017I	281	IKJ52368I	299
ICQGC999	266	IDY00019I	281	IKJ52400I	299
ICQSP000	266	IDY00020I	282	IKJ52402I	299
ICQSP001	266	IDY00022I	282	IKJ52422I	299
ICQSP002	267	IDY00023I	282	IKJ52423I	300
ICQSP003	267	IDY00024I	282	IKJ52424I	300
ICQSP004	267	IDY00028I	283	IKJ52425I	300
ICQSP005	267	IDY00029I	283	IKJ52426I	300
ICQSP006	267	IDY00030I	283	IKJ52427I	300
ICQSP010	267	IDY00032I	283	IKJ52428I	301
ICQSP011	268	IDY00041I	283	IKJ52429I	301
ICQSP012	268	IDY00042I	284	IKJ52430I	301
ICQSP013	268	IDY00043I	284	IKJ52431I	301
ICQSP014	268	IDY00044I	284	IKJ52432A	301
ICQSP015	268	IDY00045I	284	IKJ52433A	302
ICQSP016	269	IDY00046I	285	IKJ52500I	302
ICQSP017	269	IDY00047I	285	IKJ52501I	302
ICQSP018	269	IDY00048I	285	IKJ52502I	302
ICQSP019	269	IDY00049I	285	IKJ52503I	302
ICQSP021	269	IDY00050I	286	IKJ52504I	302
ICQSP022	270	IDY00051I	286	IKJ52505I	303
ICQSP023	270	IDY00052I	286	IKJ52506I	303
ICQSP024	270	IKJ52021I	291	IKJ52507I	303
ICQSP025	270	IKJ52301I	291	IKJ52550I	303
ICQSP026	271	IKJ52302I	291	IKJ52551I	303
ICQSP027	271	IKJ52303I	292	IKJ52552I	303
ICQSP028	271	IKJ52304I	292	IKJ52553I	304
ICQSP029	271	IKJ52305I	292	IKJ52554I	304
ICQSP030	271	IKJ52306I	292	IKJ52555I	304
ICQSP031	272	IKJ52307I	292	IKJ52556I	304
ICQSP032	272	IKJ52308I	293	IKJ52557I	304
ICQSP035	272	IKJ52309I	293	IKJ52558I	304
ICQSP036	272	IKJ52310I	293	IKJ52559I	304
ICQSP037	272	IKJ52311I	293	IKJ52560I	304
ICQSP040	273	IKJ52312I	293	IKJ52561I	305
ICQSP041	273	IKJ52313I	294	IKJ52562I	305
ICQSP042	273	IKJ52314I	294	IKJ52563A	305
ICQSP043	273	IKJ52315I	294	IKJ52564A	305
ICQSP044	273	IKJ52316I	294	IKJ52565I	305
ICQSP045	274	IKJ52317I	294	IKJ52567A	305
ICQSP046	274	IKJ52318I	294	IKJ52568I	305
ICQSP047	274	IKJ52319I	295	IKJ52569I	306

IKJ52570I	306	IKJ55104E	317	IKJ55356I	331
IKJ52571I	306	IKJ55105E	317	IKJ55357I	331
IKJ52572I	306	IKJ55106E	317	IKJ55361I	331
IKJ52573A	306	IKJ55107I	317	IKJ55362I	332
IKJ52574I	306	IKJ55108E	317	IKJ55363I	332
IKJ52575I	307	IKJ55110E	318	IKJ55364I	333
IKJ52576I	307	IKJ55111E	318	IKJ55365I	333
IKJ52577I	307	IKJ55112E	318	IKJ56000I	333
IKJ52578I	307	IKJ55113I	318	IKJ56001I	333
IKJ52579I	307	IKJ55114I	318	IKJ56002I	333
IKJ52580I	307	IKJ55115E	319	IKJ56003I	334
IKJ52581I	308	IKJ55116E	319	IKJ56004I	334
IKJ52582I	308	IKJ55117E	319	IKJ56005I	334
IKJ52583I	308	IKJ55118E	319	IKJ56006I	334
IKJ52584I	308	IKJ55120E	319	IKJ56007I	334
IKJ52585I	308	IKJ55121I	319	IKJ56052I	334
IKJ52586I	308	IKJ55123E	320	IKJ56053I	334
IKJ52587I	309	IKJ55124E	320	IKJ56054I	334
IKJ52588I	309	IKJ55125E	320	IKJ56055I	335
IKJ52590I	309	IKJ55126E	321	IKJ56056I	335
IKJ52591I	309	IKJ55127E	321	IKJ56057I	335
IKJ52592I	309	IKJ55128E	321	IKJ56101I	335
IKJ52593I	309	IKJ55130E	321	IKJ56104I	335
IKJ52594I	310	IKJ55131E	321	IKJ56107I	335
IKJ52595I	310	IKJ55132E	322	IKJ56109I	336
IKJ54001I	310	IKJ55133E	322	IKJ56110I	336
IKJ54003I	310	IKJ55134E	322	IKJ56111I	336
IKJ54012A	310	IKJ55135I	322	IKJ56112A	336
IKJ54013I	310	IKJ55136E	322	IKJ56113A	337
IKJ54014I	310	IKJ55137E	323	IKJ56113I	336
IKJ54016I	311	IKJ55138E	323	IKJ56114A	337
IKJ54018A	311	IKJ55139E	323	IKJ56120I	337
IKJ55000I	311	IKJ55140E	323	IKJ56121I	337
IKJ55001I	311	IKJ55141E	323	IKJ56122I	337
IKJ55002A	311	IKJ55142E	324	IKJ56123I	337
IKJ55003I	311	IKJ55143E	324	IKJ56124I	338
IKJ55004I	311	IKJ55144E	324	IKJ56130I	338
IKJ55005I	312	IKJ55301I	324	IKJ56131I	338
IKJ55006I	312	IKJ55302I	325	IKJ56132I	338
IKJ55007I	312	IKJ55303I	325	IKJ56133I	338
IKJ55008I	312	IKJ55304I	325	IKJ56134I	338
IKJ55009I	312	IKJ55305I	325	IKJ56135I	339
IKJ55050I	312	IKJ55306A	325	IKJ56136I	339
IKJ55051I	312	IKJ55307I	326	IKJ56137I	339
IKJ55052I	313	IKJ55308I	326	IKJ56138I	339
IKJ55053I	313	IKJ55309I	326	IKJ56139I	339
IKJ55054I	313	IKJ55310I	326	IKJ56140I	339
IKJ55055E	313	IKJ55311I	327	IKJ56141I	340
IKJ55056E	313	IKJ55312I	327	IKJ56142I	340
IKJ55057E	313	IKJ55313I	327	IKJ56143I	340
IKJ55058I	314	IKJ55314I	327	IKJ56144E	340
IKJ55072I	314	IKJ55315I	328	IKJ56145E	340
IKJ55074I	314	IKJ55316I	328	IKJ56146E	340
IKJ55075I	314	IKJ55317I	328	IKJ56147E	341
IKJ55077I	315	IKJ55318I	328	IKJ56150I	341
IKJ55080I	315	IKJ55319I	328	IKJ56152I	341
IKJ55081I	315	IKJ55321I	329	IKJ56154I	341
IKJ55082I	315	IKJ55322I	329	IKJ56155I	341
IKJ55083I	315	IKJ55323I	329	IKJ56156I	342
IKJ55084I	315	IKJ55324I	329	IKJ56157E	342
IKJ55085I	315	IKJ55325I	329	IKJ56158E	342
IKJ55088I	316	IKJ55327I	330	IKJ56159E	342
IKJ55089I	316	IKJ55351I	330	IKJ56190I	342
IKJ55100I	316	IKJ55352I	330	IKJ56191I	342
IKJ55101E	316	IKJ55353I	330	IKJ56192I	343
IKJ55102E	316	IKJ55354I	330	IKJ56193I	343
IKJ55103E	316	IKJ55355I	331	IKJ56194I	343

IKJ56195I 343
IKJ56196I 343
IKJ56197I 343
IKJ56198I 344
IKJ56199I 344
IKJ56200I 344
IKJ56202I 344
IKJ56205I 344
IKJ56208A 344
IKJ56208I 344
IKJ56211I 345
IKJ56216I 345
IKJ56217I 345
IKJ56218I 345
IKJ56219I 345
IKJ56220I 345
IKJ56221I 346
IKJ56222I 346
IKJ56223I 346
IKJ56224I 346
IKJ56225I 347
IKJ56226I 347
IKJ56227I 347
IKJ56228I 347
IKJ56229I 347
IKJ56230I 348
IKJ56231I 348
IKJ56232I 349
IKJ56233I 349
IKJ56234I 349
IKJ56235I 350
IKJ56236I 350
IKJ56238I 350
IKJ56239I 350
IKJ56240I 350
IKJ56241I 350
IKJ56242I 351
IKJ56243I 351
IKJ56244I 351
IKJ56245I 351
IKJ56246I 351
IKJ56247I 352
IKJ56248I 352
IKJ56249I 352
IKJ56250I 352
IKJ56251I 352
IKJ56252I 352
IKJ56254I 353
IKJ56256I 353
IKJ56257I 353
IKJ56258I 353
IKJ56259I 353
IKJ56260I 354
IKJ56261I 354
IKJ56262I 354
IKJ56263I 354
IKJ56264I 354
IKJ56265I 354
IKJ56266I 355
IKJ56268I 355
IKJ56269I 355
IKJ56270I 355
IKJ56271I 355
IKJ56272I 355
IKJ56273I 356
IKJ56274A 356
IKJ56275A 356

IKJ56276A 356
IKJ56277I 356
IKJ56280A 356
IKJ56281I 356
IKJ56282I 357
IKJ56283I 357
IKJ56284I 357
IKJ56285I 358
IKJ56286I 358
IKJ56287I 358
IKJ56288I 358
IKJ56289I 358
IKJ56291I 359
IKJ56292I 359
IKJ56293I 359
IKJ56294I 360
IKJ56295I 360
IKJ56309I 360
IKJ56310I 360
IKJ56311I 361
IKJ56312I 361
IKJ56313I 361
IKJ56318I 361
IKJ56319I 362
IKJ56320I 362
IKJ56321I 362
IKJ56323I 362
IKJ56325I 362
IKJ56328A 362
IKJ56328I 363
IKJ56330I 363
IKJ56332I 363
IKJ56333I 363
IKJ56339I 363
IKJ56340I 363
IKJ56341I 363
IKJ56342I 364
IKJ56343I 364
IKJ56344I 364
IKJ56345I 364
IKJ56346I 364
IKJ56347I 364
IKJ56348I 365
IKJ56349I 365
IKJ56350I 365
IKJ56351I 365
IKJ56353I 365
IKJ56357I 365
IKJ56358I 365
IKJ56400A 366
IKJ56401I 366
IKJ56402I 366
IKJ56403I 366
IKJ56404I 366
IKJ56405I 366
IKJ56406I 366
IKJ56407I 366
IKJ56408I 367
IKJ56409I 367
IKJ56410I 367
IKJ56411I 367
IKJ56412I 367
IKJ56413I 367
IKJ56414I 367
IKJ56415I 368
IKJ56416I 368
IKJ56417I 368

IKJ56418I 368
IKJ56419I 368
IKJ56420I 368
IKJ56421I 369
IKJ56422I 369
IKJ56423I 369
IKJ56424I 369
IKJ56425I 369
IKJ56426I 369
IKJ56427I 370
IKJ56428I 370
IKJ56429A 370
IKJ56430I 370
IKJ56431I 370
IKJ56432I 370
IKJ56433I 370
IKJ56434I 371
IKJ56435I 371
IKJ56436I 371
IKJ56437A 371
IKJ56438I 371
IKJ56439A 371
IKJ56440I 371
IKJ56441I 372
IKJ56442I 372
IKJ56443I 372
IKJ56444I 372
IKJ56445I 372
IKJ56446I 372
IKJ56447A 372
IKJ56448I 373
IKJ56449A 373
IKJ56450I 373
IKJ56451I 373
IKJ56452I 373
IKJ56453I 374
IKJ56454I 374
IKJ56455I 374
IKJ56456I 374
IKJ56457I 374
IKJ56458I 376
IKJ56459I 376
IKJ56461I 376
IKJ56464I 376
IKJ56465I 376
IKJ56466I 376
IKJ56467I 377
IKJ56468I 377
IKJ56470I 377
IKJ56471I 377
IKJ56472A 378
IKJ56473I 378
IKJ56479I 378
IKJ56480I 378
IKJ56481I 379
IKJ56482I 379
IKJ56483I 379
IKJ56484I 379
IKJ56485I 379
IKJ56486I 379
IKJ56487I 380
IKJ56488I 380
IKJ56489I 380
IKJ56490I 380
IKJ56491I 380
IKJ56492I 380
IKJ56493I 380

IKJ56494I	381	IKJ56562I	393	IKJ56646I	407
IKJ56495I	381	IKJ56563I	393	IKJ56647I	407
IKJ56496I	381	IKJ56564I	394	IKJ56648I	407
IKJ56497I	381	IKJ56565I	394	IKJ56649I	407
IKJ56498I	381	IKJ56566I	394	IKJ56650I	407
IKJ56500I	381	IKJ56567I	394	IKJ56651I	407
IKJ56501I	381	IKJ56568I	395	IKJ56652I	408
IKJ56502I	382	IKJ56569I	395	IKJ56655I	408
IKJ56503I	382	IKJ56570I	395	IKJ56656I	408
IKJ56504I	382	IKJ56571I	395	IKJ56657I	408
IKJ56505I	382	IKJ56572I	395	IKJ56658I	408
IKJ56506I	382	IKJ56573I	395	IKJ56659I	408
IKJ56507I	382	IKJ56574I	396	IKJ56660I	408
IKJ56508I	383	IKJ56575I	396	IKJ56661I	409
IKJ56509I	383	IKJ56576I	396	IKJ56662I	409
IKJ56510I	383	IKJ56577I	396	IKJ56663I	409
IKJ56511I	383	IKJ56578I	396	IKJ56664I	409
IKJ56512I	383	IKJ56579I	397	IKJ56665I	409
IKJ56513I	383	IKJ56580I	397	IKJ56666I	409
IKJ56514I	383	IKJ56581I	397	IKJ56668I	409
IKJ56515I	384	IKJ56582I	397	IKJ56669I	410
IKJ56516I	384	IKJ56583I	397	IKJ56670I	410
IKJ56517I	384	IKJ56584I	397	IKJ56671I	410
IKJ56518I	384	IKJ56585I	398	IKJ56672I	410
IKJ56519I	384	IKJ56586I	398	IKJ56673I	410
IKJ56520I	384	IKJ56587I	398	IKJ56674I	410
IKJ56521I	384	IKJ56588I	398	IKJ56675I	411
IKJ56522I	384	IKJ56590I	398	IKJ56676I	411
IKJ56523I	385	IKJ56591I	399	IKJ56677I	411
IKJ56524I	385	IKJ56592I	399	IKJ56678I	411
IKJ56525I	385	IKJ56593I	399	IKJ56686I	411
IKJ56526I	385	IKJ56594I	399	IKJ56687I	412
IKJ56527I	385	IKJ56595I	399	IKJ56688I	412
IKJ56528I	386	IKJ56596I	399	IKJ56689I	412
IKJ56529I	386	IKJ56597I	400	IKJ56690I	412
IKJ56530I	386	IKJ56598I	400	IKJ56700A	412
IKJ56531I	386	IKJ56599I	400	IKJ56701I	417
IKJ56532I	386	IKJ56600I	400	IKJ56702A	417
IKJ56533I	386	IKJ56601I	400	IKJ56702I	418
IKJ56534I	387	IKJ56602I	400	IKJ56703A	418
IKJ56535I	387	IKJ56603I	400	IKJ56704I	418
IKJ56536I	387	IKJ56604I	401	IKJ56705I	418
IKJ56537I	387	IKJ56605I	401	IKJ56706I	418
IKJ56538I	388	IKJ56606I	401	IKJ56707I	418
IKJ56539I	388	IKJ56607I	401	IKJ56708I	418
IKJ56540I	388	IKJ56608I	401	IKJ56709I	419
IKJ56541I	388	IKJ56609I	402	IKJ56710I	419
IKJ56542I	388	IKJ56610I	402	IKJ56711I	419
IKJ56543I	389	IKJ56611I	402	IKJ56712I	419
IKJ56544I	389	IKJ56612I	402	IKJ56713I	419
IKJ56545I	389	IKJ56613I	403	IKJ56714A	419
IKJ56546I	390	IKJ56614I	403	IKJ56715I	419
IKJ56547I	391	IKJ56615I	403	IKJ56716I	420
IKJ56548I	391	IKJ56620I	403	IKJ56717I	420
IKJ56549I	391	IKJ56621I	404	IKJ56718A	420
IKJ56550I	391	IKJ56622I	404	IKJ56719I	420
IKJ56551I	391	IKJ56623I	404	IKJ56720I	420
IKJ56552I	392	IKJ56625I	404	IKJ56721I	420
IKJ56553I	392	IKJ56626I	404	IKJ56722I	420
IKJ56554I	392	IKJ56629A	405	IKJ56723I	420
IKJ56555I	392	IKJ56637I	405	IKJ56724I	421
IKJ56556I	392	IKJ56639I	405	IKJ56725I	421
IKJ56557I	392	IKJ56640I	405	IKJ56726I	421
IKJ56558I	392	IKJ56641I	406	IKJ56727I	421
IKJ56559I	393	IKJ56642I	406	IKJ56728I	421
IKJ56560I	393	IKJ56643I	406	IKJ56729I	421
IKJ56561I	393	IKJ56644I	406	IKJ56730I	422

IKJ56731I	422	IKJ56884I	433	IKJ57309I	459
IKJ56760I	422	IKJ56885I	433	IKJ57310I	459
IKJ56761A	422	IKJ56886I	434	IKJ57334I	460
IKJ56762A	422	IKJ56887I	434	IKJ57335I	460
IKJ56770E	422	IKJ56888I	434	IKJ57336I	460
IKJ56771E	423	IKJ56889I	434	IKJ57370I	460
IKJ56772E	423	IKJ56890I	434	IKJ57371I	460
IKJ56773E	423	IKJ56891I	434	IKJ57375I	460
IKJ56774E	423	IKJ56893I	434	IKJ57378I	460
IKJ56775E	423	IKJ56894I	435	IKJ57379I	461
IKJ56776E	424	IKJ56895I	435	IKJ57382I	461
IKJ56777E	424	IKJ56896I	435	IKJ57395I	461
IKJ56778E	424	IKJ56897I	435	IKJ57400I	461
IKJ56779E	424	IKJ56898I	436	IKJ57401I	461
IKJ56780E	424	IKJ56899I	436	IKJ57404I	461
IKJ56781D	425	IKJ56950I	436	IKJ57405I	461
IKJ56782E	425	IKJ56951I	436	IKJ57430I	461
IKJ56783E	425	IKJ56957I	436	IKJ57454I	462
IKJ56784E	425	IKJ56959I	436	IKJ57455I	462
IKJ56785E	425	IKJ56960E	437	IKJ57456I	462
IKJ56786I	426	IKJ56961E	437	IKJ57457I	462
IKJ56787I	426	IKJ56962I	437	IKJ57461I	462
IKJ56788I	426	IKJ56963E	437	IKJ57462I	462
IKJ56801I	426	IKJ56964E	437	IKJ57501I	462
IKJ56802I	426	IKJ57002I	454	IKJ57502I	466
IKJ56803I	426	IKJ57005I	454	IKJ57503I	466
IKJ56804I	427	IKJ57008I	454	IKJ57504I	466
IKJ56805I	427	IKJ57021I	454	IKJ57507I	466
IKJ56806I	427	IKJ57022I	454	IKJ57522I	466
IKJ56807I	427	IKJ57023I	454	IKJ57600I	467
IKJ56808I	427	IKJ57024I	454	IKJ57601I	467
IKJ56809I	427	IKJ57025I	455	IKJ57602I	467
IKJ56810I	428	IKJ57026I	455	IKJ57603I	467
IKJ56850I	428	IKJ57027I	455	IKJ57604I	467
IKJ56851I	428	IKJ57028I	455	IKJ57605I	467
IKJ56852I	428	IKJ57031I	455	IKJ57606I	467
IKJ56853I	428	IKJ57036I	455	IKJ57607I	468
IKJ56854I	428	IKJ57060I	455	IKJ57608I	468
IKJ56855I	429	IKJ57061I	456	IKJ57609I	468
IKJ56856I	429	IKJ57063I	456	IKJ57610I	468
IKJ56857I	429	IKJ57064I	456	IKJ57611I	468
IKJ56858I	429	IKJ57066I	456	IKJ57612I	468
IKJ56859I	429	IKJ57090A	456	IKJ57613I	468
IKJ56860I	429	IKJ57209I	456	IKJ57614I	468
IKJ56861I	429	IKJ57219I	456	IKJ57615I	469
IKJ56862I	430	IKJ57241I	456	IKJ57616I	469
IKJ56863I	430	IKJ57242I	457	IKJ57617I	469
IKJ56864I	430	IKJ57243I	457	IKJ57650I	469
IKJ56865I	430	IKJ57244I	457	IKJ57651I	469
IKJ56866I	430	IKJ57245I	457	IKJ57652I	469
IKJ56867I	430	IKJ57246I	457	IKJ57653I	469
IKJ56868I	430	IKJ57247I	457	IKJ57654I	470
IKJ56869I	431	IKJ57272I	457	IKJ57655I	470
IKJ56870I	431	IKJ57273I	457	IKJ57656I	470
IKJ56871I	431	IKJ57274I	458	IKJ57657I	470
IKJ56872I	431	IKJ57277I	458	IKJ57658I	470
IKJ56873I	431	IKJ57280I	458	IKJ57659I	470
IKJ56874I	431	IKJ57281I	458	IKJ57660I	471
IKJ56875I	431	IKJ57282I	458	IKJ57661I	471
IKJ56876I	432	IKJ57293I	458	IKJ57662I	471
IKJ56877I	432	IKJ57295I	458	IKJ57663I	471
IKJ56878I	432	IKJ57296I	458	IKJ57664I	471
IKJ56879I	432	IKJ57297I	459	IKJ57665I	471
IKJ56880I	432	IKJ57302I	459	IKJ57666I	471
IKJ56881I	433	IKJ57303I	459	IKJ57667I	472
IKJ56882I	433	IKJ57305I	459	IKJ57668I	472
IKJ56883I	433	IKJ57306I	459	IKJ57700I	472

IKJ57701I	472	IKJ58301I	483	IKJ58609I	495
IKJ57702I	472	IKJ58302I	483	IKJ58610I	495
IKJ57703I	472	IKJ58303I	483	IKJ58611E	495
IKJ57704I	473	IKJ58304I	483	IKJ58613E	495
IKJ57705I	473	IKJ58305I	483	IKJ58614E	495
IKJ57706I	473	IKJ58400I	484	IKJ58616I	496
IKJ57707I	473	IKJ58401I	484	IKJ58617I	496
IKJ57708I	473	IKJ58402I	484	IKJ58618I	496
IKJ57709I	473	IKJ58403I	484	IKJ58619E	496
IKJ57710I	474	IKJ58404I	484	IKJ58620E	496
IKJ57711I	474	IKJ58405I	484	IKJ58621E	496
IKJ57712I	474	IKJ58406I	485	IKJ58622E	497
IKJ57713I	474	IKJ58407I	485	IKJ58624E	497
IKJ57714I	474	IKJ58408I	485	IKJ58625I	497
IKJ57715I	474	IKJ58409I	485	IKJ58626E	497
IKJ57800I	475	IKJ58410I	485	IKJ59001I	497
IKJ57801I	475	IKJ58411I	485	IKJ59002I	497
IKJ57802I	475	IKJ58412I	486	IKJ59003I	497
IKJ57803I	475	IKJ58413I	486	IKJ59004I	498
IKJ57xxxI	438, 439, 440, 441, 442, 443, 444, 445, 446, 447, 448, 449, 450, 451, 452, 453, 463, 464, 465, 466	IKJ58414I	486	IKJ59005I	498
IKJ58101I	475	IKJ58417I	486	IKJ59007I	498
IKJ58102I	476	IKJ58418I	486	IKJ59008I	498
IKJ58103I	476	IKJ58419I	487	IKJ59009I	498
IKJ58104I	476	IKJ58420I	487	IKJ59010I	498
IKJ58105I	476	IKJ58421I	487	IKJ59011I	499
IKJ58106I	476	IKJ58422I	487	IKJ59012I	499
IKJ58107I	477	IKJ58423I	487	IKJ59013I	499
IKJ58108I	477	IKJ58424I	487	IKJ59014I	499
IKJ58109I	477	IKJ58425I	488	IKJ59015I	499
IKJ58110I	477	IKJ58427I	488	IKJ59016I	499
IKJ58111I	477	IKJ58428I	488	IKJ59017I	499
IKJ58112I	477	IKJ58429I	488	IKJ59018I	500
IKJ58201I	477	IKJ58430I	488	IKJ59019I	500
IKJ58202I	477	IKJ58431I	489	IKJ59020I	500
IKJ58203I	478	IKJ58432I	489	IKJ59021I	500
IKJ58204I	478	IKJ58433I	489	IKJ59023I	500
IKJ58205I	478	IKJ58434I	489	IKJ59024I	500
IKJ58206I	478	IKJ58435I	490	IKJ59025I	501
IKJ58207I	478	IKJ58436I	490	IKJ59027I	501
IKJ58208I	479	IKJ58437I	490	IKJ59028I	501
IKJ58209I	479	IKJ58500I	490	IKJ59029I	501
IKJ58210I	479	IKJ58501I	491	IKJ59030I	501
IKJ58211I	479	IKJ58502I	491	IKJ59031I	502
IKJ58212I	479	IKJ58503I	491	IKJ59032I	502
IKJ58213I	480	IKJ58504I	491	IKJ59033I	502
IKJ58214I	480	IKJ58505I	491	IKJ59034I	502
IKJ58215I	480	IKJ58506I	492	IKJ59035I	502
IKJ58216I	480	IKJ58507I	492	IKJ59036I	502
IKJ58217I	480	IKJ58508I	492	IKJ59037I	503
IKJ58218I	480	IKJ58509I	492	IKJ59038I	503
IKJ58219I	481	IKJ58510I	492	IKJ59039I	503
IKJ58220I	481	IKJ58511I	492	IKJ59040I	503
IKJ58221I	481	IKJ58512I	492	IKJ59042I	504
IKJ58222I	481	IKJ58513I	493	IKJ59049I	504
IKJ58223I	481	IKJ58514I	493	IKJ59050I	504
IKJ58224I	481	IKJ58516I	493	IKJ59051I	504
IKJ58225I	481	IKJ58517I	493	IKJ59052I	504
IKJ58226I	481	IKJ58518I	493	IKJ59053I	505
IKJ58227I	482	IKJ58600I	493	IKJ59054I	505
IKJ58228I	482	IKJ58601A	494	IKJ59055I	505
IKJ58229I	482	IKJ58602I	494	IKJ59056I	505
IKJ58230I	482	IKJ58603A	494	IKJ59100E	505
IKJ58231I	482	IKJ58604A	494	IKJ59101E	505
IKJ58232I	482	IKJ58605I	494	IKJ59102E	506
IKJ58300I	482	IKJ58606A	494	IKJ59103E	506
		IKJ58607I	495	IKJ59106E	506
		IKJ58608A	495	IKJ59107E	506

IKJ59108E	506	IKJ79016I	516	IKJ79311I	529
IKJ59109E	506	IKJ79017I	516	IKJ79312I	529
IKJ59110E	507	IKJ79018I	517	IKJ79313I	529
IKJ59111E	507	IKJ79019I	517	IKJ79314I	529
IKJ59112E	507	IKJ79020I	517	IKJ79315I	529
IKJ59113E	507	IKJ79021I	517	IKJ79316I	530
IKJ59114E	507	IKJ79022I	517	IKJ79317I	530
IKJ59115E	507	IKJ79023I	517	IKJ79319I	530
IKJ59116E	507	IKJ79024I	518	IKJ79320I	530
IKJ59117E	507	IKJ79025I	518	IKJ79321I	531
IKJ59118E	507	IKJ79026I	518	IKJ79322I	531
IKJ59119E	508	IKJ79027I	518	IKJ79323I	531
IKJ59120E	508	IKJ79028I	518	IKJ79324I	531
IKJ59157I	508	IKJ79029I	518	IKJ79325I	532
IKJ59158I	508	IKJ79030I	519	IKJ79326I	532
IKJ59162E	508	IKJ79031I	519	IKJ79327I	532
IKJ59163E	508	IKJ79032I	519	IKJ79328I	532
IKJ59164E	508	IKJ79039I	519	IKJ79329I	532
IKJ59165E	509	IKJ79040I	519	IKJ79330I	533
IKJ59200I	509	IKJ79041I	519	IKJ79332I	533
IKJ59202I	509	IKJ79042I	520	IKJ79333I	533
IKJ60739I	509	IKJ79043I	520	IKJ79334I	533
IKJ60741I	509	IKJ79044I	520	IKJ79335I	533
IKJ60743I	509	IKJ79045I	520	IKJ79336I	534
IKJ76011I	509	IKJ79046I	520	IKJ79337I	534
IKJ76013I	510	IKJ79048I	520	IKJ79338I	534
IKJ76023I	510	IKJ79049I	521	IKJ79339I	535
IKJ76033I	510	IKJ79054I	521	IKJ79340I	535
IKJ76043I	510	IKJ79055I	521	IKJ79341I	535
IKJ76053I	510	IKJ79057I	521	IKJ79342I	536
IKJ76063I	511	IKJ79060I	521	IKJ79343I	536
IKJ76073I	511	IKJ79061I	521	IKJH0201I	536
IKJ76080A	511	IKJ79062I	521	IKJH0202E	536
IKJ76083I	511	IKJ79063I	522	IKJH0301I	537
IKJ76091I	511	IKJ79064I	522	IKJH0302E	537
IKJ76100A	512	IKJ79065I	522	IKJH0303E	537
IKJ76111I	512	IKJ79066I	522	IKJH0304E	538
IKJ76121I	512	IKJ79067I	523	IKJH101I	536
IKJ76123I	512	IKJ79068I	524	INMC001I	539
IKJ76133I	512	IKJ79069I	524	INMC002I	539
IKJ76143I	512	IKJ79070I	524	INMC003I	540
IKJ76151I	512	IKJ79071I	524	INMC004I	540
IKJ76161I	513	IKJ79072I	524	INMC005A	540
IKJ76170A	513	IKJ79073I	524	INMC006I	540
IKJ76173I	513	IKJ79074I	525	INMC007I	541
IKJ76181I	513	IKJ79075I	525	INMC008I	541
IKJ76193I	513	IKJ79101I	525	INMC009I	541
IKJ76203I	513	IKJ79102I	525	INMC010I	541
IKJ76213I	514	IKJ79103I	526	INMC011I	541
IKJ76223I	514	IKJ79104I	526	INMC012I	542
IKJ76231I	514	IKJ79105I	526	INMC150I	542
IKJ76241I	514	IKJ79106I	526	INMC151I	542
IKJ79000I	514	IKJ79150I	526	INMC153I	542
IKJ79002I	514	IKJ79151I	526	INMC154I	542
IKJ79003I	514	IKJ79152I	527	INMC155I	543
IKJ79004I	515	IKJ79153I	527	INMC156I	543
IKJ79005I	515	IKJ79154I	527	INMC214I	543
IKJ79006I	515	IKJ79200I	527	INMR000I	543
IKJ79007I	515	IKJ79201I	527	INMR001I	543
IKJ79008I	515	IKJ79202I	527	INMR002I	544
IKJ79009I	515	IKJ79203I	527	INMR003I	544
IKJ79010I	515	IKJ79204I	527	INMR004I	544
IKJ79011I	516	IKJ79301I	528	INMR005I	544
IKJ79012I	516	IKJ79307I	528	INMR006I	544
IKJ79013I	516	IKJ79308I	528	INMR007I	545
IKJ79014I	516	IKJ79309I	528	INMR008I	545
IKJ79015I	516	IKJ79310I	528	INMR009I	545

INMR030I	545	INMR152I	559	INMX065I	574
INMR031I	546	INMR153I	560	INMX066I	574
INMR032I	546	INMR154I	560	INMX067I	574
INMR033I	546	INMR155I	560	INMX068I	575
INMR034I	546	INMR156I	560	INMX069I	575
INMR035I	546	INMR157I	561	INMX070I	575
INMR036I	547	INMR158I	561	INMX071I	575
INMR037I	547	INMR159I	561	INMX072I	575
INMR040I	547	INMR200I	561	INMX073I	576
INMR041I	547	INMR800I	561	INMX074I	576
INMR042I	548	INMR900I	562	INMX075I	576
INMR043I	548	INMR901I	562	INMX076I	576
INMR044I	548	INMR902I	562	INMX077I	576
INMR045I	548	INMR906A	562	INMX078I	577
INMR046I	549	INMR907A	563	INMX079I	577
INMR047I	549	INMR908A	563	INMX080I	577
INMR056I	549	INMR909A	563	INMX081I	577
INMR057I	549	INMR910A	563	INMX083I	577
INMR060I	549	INMR911A	563	INMX084I	578
INMR061I	550	INMR912I	564	INMX085I	578
INMR062I	550	INMR913I	564	INMX090A	578
INMR063I	550	INMR916I	564	INMX091I	578
INMR064I	550	INMR917I	564	INMX092I	578
INMR065I	550	INMR918I	565	INMX094I	579
INMR066I	551	INMR921I	565	INMX099I	579
INMR067I	551	INMR922I	565	INMX100A	579
INMR068I	551	INMR931I	565	INMX101I	579
INMR069I	551	INMR932I	565	INMX105I	580
INMR070I	551	INMR933A	566	INMX106I	580
INMR071I	552	INMR934I	566	INMX107I	580
INMR072I	552	INMX000I	566	INMX149I	580
INMR073I	552	INMX001I	566	INMX150I	580
INMR080I	552	INMX019I	566	INMX151I	581
INMR081I	553	INMX020I	567	INMX152I	581
INMR082I	553	INMX021I	567	INMX153I	581
INMR083I	553	INMX022I	567	INMX201I	581
INMR090I	553	INMX023I	568	INMX202I	581
INMR091I	553	INMX024I	568	INMX203I	582
INMR092I	554	INMX025I	568	INMX204I	582
INMR093I	554	INMX026I	568	INMX206I	582
INMR101I	554	INMX027I	568	INMX208I	582
INMR102I	554	INMX028I	569	INMX209I	582
INMR108I	554	INMX029I	569	INMX210I	583
INMR109I	555	INMX030I	569	INMX211I	583
INMR127I	555	INMX031I	569	INMX213I	583
INMR128I	555	INMX032I	569	INMX214I	583
INMR129I	555	INMX033I	570	INMX215I	583
INMR130I	555	INMX034I	570	INMX216I	584
INMR131I	556	INMX035I	570	INMX217I	584
INMR132I	556	INMX036I	570	INMX218I	584
INMR133I	556	INMX037I	570	INMX220I	584
INMR134I	556	INMX038I	571	INMX800I	584
INMR135I	556	INMX040I	571	IRX0003I	585
INMR136I	557	INMX041I	571	IRX0004I	585
INMR137I	557	INMX042I	571	IRX0005I	586
INMR138I	557	INMX043I	572	IRX0006I	586
INMR139I	557	INMX050I	572	IRX0007I	586
INMR140I	557	INMX051I	572	IRX0008I	586
INMR141I	558	INMX052I	572	IRX0009I	587
INMR142I	558	INMX057I	572	IRX0010I	587
INMR143I	558	INMX058I	573	IRX0011I	587
INMR144I	558	INMX059I	573	IRX0012I	588
INMR145I	558	INMX060I	573	IRX0013I	588
INMR146I	559	INMX061I	573	IRX0014I	588
INMR149I	559	INMX062I	573	IRX0015I	589
INMR150I	559	INMX063I	574	IRX0016I	589
INMR151I	559	INMX064I	574	IRX0017I	589

IRX0018I	590	IRX0233E	605	IRX0520E	620
IRX0019I	590	IRX0234E	605	IRX0521E	621
IRX0020I	590	IRX0236E	605	IRX0522E	621
IRX0021I	590	IRX0237E	605	IRX0523E	621
IRX0022I	590	IRX0238E	606	IRX0524E	621
IRX0023I	591	IRX0239E	606	IRX0530E	621
IRX0024I	591	IRX0240I	606	IRX0531E	621
IRX0025I	591	IRX0241I	607	IRX0532E	622
IRX0026I	591	IRX0242I	607	IRX0533E	622
IRX0027I	591	IRX0245I	608	IRX0535E	622
IRX0028I	592	IRX0246I	608	IRX0536E	622
IRX0029I	592	IRX0247I	608	IRX0540E	622
IRX0030I	592	IRX0248I	608	IRX0541E	623
IRX0031I	593	IRX0250E	609	IRX0551E	623
IRX0032I	593	IRX0251E	609	IRX0552E	623
IRX0033I	593	IRX0252E	609	IRX0553E	623
IRX0034I	593	IRX0253E	609	IRX0554E	624
IRX0035I	593	IRX0254E	610	IRX0555E	624
IRX0036I	594	IRX0255E	610	IRX0556E	624
IRX0037I	594	IRX0256E	610	IRX0560E	624
IRX0038I	594	IRX0260E	610	IRX0561E	624
IRX0039I	594	IRX0270E	611	IRX0562E	625
IRX0040I	594	IRX0271E	611	IRX0563E	625
IRX0041I	595	IRX0272E	611	IRX0564E	625
IRX0042I	595	IRX0273E	611	IRX0565E	625
IRX0043I	595	IRX0274E	612	IRX0566E	626
IRX0044I	596	IRX0275E	612	IRX0567E	626
IRX0045I	596	IRX0276E	612	IRX0568E	626
IRX0046I	596	IRX0277E	612	IRX0570E	627
IRX0047I	596	IRX0278E	612	IRX0571E	627
IRX0048I	596	IRX0280I	613	IRX0572E	627
IRX0049I	597	IRX0281I	613	IRX0601E	627
IRX0100I	597	IRX0283I	613	IRX0602E	627
IRX0105I	597	IRX0289I	613	IRX0603E	628
IRX0106I	597	IRX0300E	613	IRX0604E	628
IRX0110I	598	IRX0301E	614	IRX0605E	628
IRX0111I	598	IRX0303E	614	IRX0606E	628
IRX0112I	598	IRX0304E	614	IRX0607E	628
IRX0113I	598	IRX0305E	614	IRX0608E	629
IRX0155E	599	IRX0400E	614	IRX0609E	629
IRX0156E	599	IRX0401E	615	IRX0610E	629
IRX0157E	599	IRX0402E	615	IRX0611E	629
IRX0158E	599	IRX0403E	615	IRX0612E	629
IRX0159E	600	IRX0404E	615	IRX0613E	630
IRX0200I	600	IRX0406E	616	IRX0614E	630
IRX0201I	600	IRX0407E	616	IRX0615E	630
IRX0203I	600	IRX0408E	616	IRX0616E	630
IRX0205I	600	IRX0409E	616	IRX0617E	630
IRX0207I	601	IRX0410E	616	IRX0650E	631
IRX0210E	601	IRX0420E	617	IRX0651E	631
IRX0211E	601	IRX0421E	617	IRX0652E	631
IRX0212E	601	IRX0422E	617	IRX0653E	631
IRX0213E	602	IRX0423E	617	IRX0654E	631
IRX0214E	602	IRX0424E	617	IRX0660E	632
IRX0215E	602	IRX0430E	617	IRX0661E	632
IRX0216E	602	IRX0431E	618	IRX0662E	632
IRX0217E	602	IRX0432E	618	IRX0663E	632
IRX0218E	603	IRX0435E	618	IRX0670E	632
IRX0220E	603	IRX0440E	618	IRX0671E	632
IRX0221E	603	IRX0441E	619	IRX0672E	633
IRX0222E	603	IRX0442E	619	IRX0673E	633
IRX0227E	604	IRX0501E	619	IRX0674E	633
IRX0228E	604	IRX0502E	619	IRX0675E	633
IRX0229E	604	IRX0503E	619	IRX0700I	634
IRX0230E	604	IRX0509E	620	IRX0701I	634
IRX0231E	604	IRX0510E	620	IRX0702I	634
IRX0232E	605	IRX0511E	620	IRX0750I	634

IRX0751I 634
IRX0760E 635
IRX0761E 635
IRX0762E 635
IRX0763E 635
IRX0765E 636
IRX0766E 636
IRX0767E 636
IRX0768E 636
IRX0770E 637
IRX0771E 637
IRX0772E 637
IRX0798I 637
IRX0801E 637
IRX0802E 638
IRX0803E 638
IRX0804E 638
IRX0805E 638
IRX0806E 638
IRX0810E 639
IRX0811E 639
IRX0812E 639
IRX0813E 639
IRX0814E 639
IRX0820E 640
IRX0821E 640
IRX0822E 640
IRX0823I 640
IRX0824E 640
IRX0900E 641
IRX0901E 641
IRX0910I 641
IRX0911I 642
IRX0912I 642
IRX0913I 642
IRX0914I 642
IRX0915I 642
IRX0916I 642
IRX0917I 643
IRX0918I 643
IRX0920I 643
IRX0921I 644
IRX0922I 644
IRX0923I 644
IRX0924I 644
IRX0925I 644
IRX0926I 645
IRX0927I 645
IRX0928I 645
IRX0929I 645
IRX0931I 646

K

keyboard
 navigation 647
 PF keys 647
 shortcut keys 647

N

navigation
 keyboard 647
None 290, 291
Notices 651

S

sending comments to IBM xi
shortcut keys 647
Summary of changes xiii

T

trademarks 653

U

user interface
 ISPF 647
 TSO/E 647



Product Number: 5650-ZOS

Printed in USA

SA32-0970-00

