

# CL/SUPERSESSION® CL/GATEWAY®

---

V e r s i o n 1 4 7

# Actions

## Action Code Menu

- S begin or resume a session
- T terminate the session
- B begin a background session
- P print the screen image
- X transmit the screen image
- H help for the application
- I display additional information
- D delete the session from the menu
- M modify the session definition
- L add from Global session list
- A add a session

Command ==>

Enter F=Help F12=Cancel

## Definition of Terms

- |                               |   |
|-------------------------------|---|
| <b>Action bar</b>             | Top line of the Main Menu.  |
| <b>Home position</b>          | Underscore at the beginning of the action bar, where you enter a fast path. |
| <b>Session ID input field</b> | Underscore next to a session ID, where you specify an action.               |
| <b>Command prompt</b>         | Field at the bottom of each menu, where you enter commands.                 |

## Using Action Codes

If you know the action code, enter it next to the desired session ID on the Main Menu.

To view a list of actions:

1. Type a slash (/) next to the desired session ID.
2. Press **F10** to move the cursor to the home position.
3. Enter **A**. The Action Code Menu (shown above) is displayed.
4. Enter an action code in the entry field on the first line.

## Fast Pathing

At the home position, enter a letter to specify a pulldown followed by a single-letter selection from the pulldown menu.

For example:

**OT** for **Options** pulldown, **Trigger keys** selection

**CD** for **Commands** pulldown, **Date** command

Note: There is no fast pathing to the Actions pulldown.

# Options

## Product Options

Type a selection number or position the cursor on a line and press ENTER.

- \_ 1. Trigger keys (T)...
- 2. Preferences (P)...
- 3. Personal information (I)...
- 4. Window options (W)...

Command ===>

Enter F1=Help F12=Cancel

## Triggers

A trigger is a key sequence consisting of a phrase and key, or simply a single key. Entering a trigger invokes a CL/SUPERSESSION function. You can use triggers only while you are in a multi-application session, not from a CL/SUPERSESSION display. When you use a trigger phrase, the field containing the cursor is the only field on the screen CL/SUPERSESSION reads.

### Listing Available Triggers

1. At the Main Menu, press **F10** to move the cursor to the home position.
2. Select **Trigger keys** from the Options pulldown. Tab or scroll through the list. See the Candle-supplied triggers on the other side of this card.

### Using a Trigger

1. If the trigger is a phrase, type the **trigger phrase** in the first position of any input field. Leave the cursor in the field so that the trigger phrase is recognized.
2. Press the **trigger key**.

### Modifying, Adding, or Deleting a Trigger

1. On the trigger list, enter an action code beside the trigger:  
**M** to modify, **A** to add, or **D** to delete.
2. To add or modify, enter phrase, trigger key, dialog name, or parameters.
3. Press **F12** to exit.

# Commands

## Command Selection Menu

Select a command with the cursor, using TAB, then press ENTER.

Add	Background	BEep	BOttom
BULletins	Date	DElete	eXit
Help	List	KLSLOCK	Msgid
News	Panid	REOrder	Reset
REtrieve	Start	Terminate	TIme
TOp	Whoami		

Command ==>

Enter F1=Help F12=Cancel

## Commands

Enter **C** at the home position to select the Commands pulldown.

<b>Add</b>	Add a new session to the Main Menu
<b>Background</b>	Start a session in the background
<b>BEep</b>	Toggle the audible alarm on and off
<b>BOttom</b>	Scroll to the bottom of the selection list
<b>BULletins</b>	Display information from system bulletins
<b>Date</b>	Display today's date
<b>DElete</b>	Delete a session from the Main Menu
<b>eXit</b>	Log off product
<b>Help</b>	View command descriptions
<b>List</b>	Display list of authorized applications
<b>KLSLOCK</b>	Lock your terminal
<b>Msgid</b>	Toggle the display of message number on and off.
<b>News</b>	Display current news.
<b>Panid</b>	Toggle the display of the panel identifier on and off.
<b>REOrder</b>	Change the order of menu items
<b>Reset</b>	Reinitialize your environment
<b>REtrieve</b>	Retrieve the most recent command
<b>Start</b>	Start a session
<b>Terminate</b>	Terminate a session
<b>TIme</b>	Display the current time
<b>TOp</b>	Scroll to the top of the selection list
<b>Whoami</b>	Display identifiers for your terminal and the system

# Features

## Product Features

Type a selection number or position the cursor on a line and press ENTER.

- \_ 1. Cut and Paste (C)...
- 2. Send Messages (M)...

Command ===>

Enter F1=Help F12=Cancel

## Cut and Paste

### Setting Cut and Paste Options

1. Enter **F** at the home position to select the Features pulldown.
2. Select **Cut and Paste** and press Enter.
3. Make sure status is **On**.
4. Remember your Cut and Paste key.
5. Press **Enter**.

### Cutting

1. In an active session, go to the screen you want to cut.
2. Move the cursor to the upper left corner of the area to cut.
3. Press the **Cut and Paste** key.
4. Place the cursor next to **Cut** and press Enter.
5. Move the cursor to the lower right corner of the area to cut.
6. Press the **Cut and Paste key**.
7. Press **F12** to exit.

### Pasting

1. On the screen where you want to paste, create enough blank lines to accommodate the data that was cut.
2. Move the cursor to the upper left corner of the area where you want to paste.
3. Press the **Cut and Paste** key.
4. Place the cursor next to **Paste** and press Enter.

# Help

## Help Menu

Type a selection number or position the cursor on a line and press Enter.

- 1. Tutorial help (T)...
- 2. How to get help (H)...
- 3. Help with function keys (K)...

Command ===>

Enter F1=Help F12=Cancel

## Help from the Action Bar

- Enter **H** at the home position to select the Help pulldown.

## Field Help

1. Move the cursor to an input field.
2. Press **F1** for field help.
3. Press **F2** for panel help.

## Panel Help

1. Move the cursor to a non-input area.
2. Press **F1** for panel help.
3. Press **F2** for help about help.

## Command Help

- If you know the command, enter **HELP commandname** next to Command ===>.

Information on that command is displayed.

- If you are not familiar with the available commands, move the cursor to Command ===> and press **F1**.

A list of commands is displayed.

## Session Management

### Starting a Session

- Enter **S** next to the session ID you want to start.

### Starting Multiple Sessions

1. Enter **S** next to the session you want to start in the foreground.
2. Enter **B** next to the session you want to start in the background.

### Getting a List of Authorized Sessions

- Enter **L** next to any session ID.

### Adding a Session to the Main Menu from Your Authorized List

1. Enter **L** next to any session ID.
2. Tab or scroll through the list, entering **A** next to each session you want to add to the Main Menu.
3. Press **F12** to exit the selection list.

### Deleting a Session from the Main Menu

1. Enter **D** next to the session ID you want to remove.
2. Press **Enter** to confirm the delete request.

## Using Window Control

The Window Control pop-up gives you access to several commands that open and close windows, zoom to full screen and return, and control your movement in a window.

To change the window control keys, select **Window options** from the Options pulldown. These are the default settings:

### Default Window Control Keys

PA1	Window control key
F3	Zoom/unzoom window
F7	Scroll up
F8	Scroll down
F10	Scroll left
F11	Scroll right
F9	Jump to next window
F2	Horizontal split
F4	Vertical split
F5	Delete window

### Opening a Session Window

1. Move the cursor to where you want the vertical or horizontal window to appear.
2. Press the window control key (**PA1**). The Window Control pop-up appears.
3. Press the horizontal (**F2**) or vertical (**F4**) split key. Where the cursor was positioned, a window opens containing a copy of the CL/SUPERSESSION Main Menu.
4. Start another application in the new window.

### Closing a Session Window

1. Move the cursor into the window you want to close and press **Enter**.
2. Press the window control key (**PA1**). The Window Control pop-up appears.
3. Press the delete window key (**F5**). The window closes, but the application remains active.



## Candle-Supplied Trigger Dialogs and Trigger Keys

The table below shows the trigger dialogs that Candle supplies. The first and second columns list the default trigger phrases and trigger keys. Your system administrator may have changed the trigger phrases and keys, and added other trigger dialogs. Use the spaces provided to record any dialogs that were created for your site. For information on how to use triggers, see Options on the other side of this card.

Phrase	Key	Dialog	Action
@p	Enter	KLSPRINT	Print the screen.
\b	Enter	KLSACTBS	Start a background session.
\ft	Enter	KLSFXFER	Toggle file transfer mode.
\g	Enter	KLSGOTO	Go to the named session.
\j	Enter	KLSNEXTW	Jump to the next open window.
\l	Enter	KLSLOCK	Lock the physical terminal.
\m	Enter	blank	Return to Main Menu.
\n	Enter	KLSNEXTS	Go to the next session.
\o	Enter	KLSVTOPT	List virtual session options.
\p	Enter	KLSPREVS	Go to the previous session.
\q	Enter	KLSQUIT	Log off CL/SUPERSESSION.
\t	Enter	KLSTERMS	Terminate a session.
\z	Enter	KLSZOOM	Toggle window zoom.
\pm	Enter	KLVPMOPT	List physical session options.

## In Case of Trouble

If you have problems using CL/SUPERSESSSION, report them to your network coordinator, supervisor, or help desk. They will need the following information.

- date and time the problem occurred
- application or service you were using
- user ID
- terminal name
- CL/SUPERSESSSION panel ID

When having a problem, your terminal name may not be readily available. You can move the cursor to any Command ==> prompt and enter **WHOAMI**. Record your terminal name in the space provided below, or on a label affixed to your terminal.

Use the additional spaces to record the telephone numbers of your support contacts.

### Terminal Information and Support Phone Numbers

Terminal Name \_\_\_\_\_

Network Coordinator Phone \_\_\_\_\_

Help Desk Phone \_\_\_\_\_

### For More Information

Refer to the CL/SUPERSESSSION and CL/GATEWAY for MVS  
User's Guide.

Candle Corporation  
201 North Douglas Street  
El Segundo, California 90245